

KiCad Git Cheat Sheet (One Page)

START PROJECT

```
git init
git add .
git commit -m "initial commit"
git branch -M main
```

ADD REMOTE (GitHub)

```
git remote add origin <repo-url>
git push -u origin main
```

CREATE PRODUCT BRANCH

```
git checkout -b product-A
```

SAVE WORK

```
git add .
git commit -m "change description"
```

CREATE VERSION

```
git tag productA-v1
git push origin productA-v1
```

PUSH BRANCH TO REMOTE

```
git push -u origin product-A
git push --all
git push --tags
```

SWITCH PRODUCT

```
git checkout product-B
```

LIST VERSIONS

```
git tag
```

KICAD .GITIGNORE (AUTO CLEAN JUNK FILES)

```
*.kicad_prl
*.kicad_pro-bak
*.kicad_sch-bak
*.kicad_pcb-bak
*.bak
*.tmp
*.lck
fp-info-cache/
__pycache__/
```

RECOMMENDED ELECTRONICS FOLDER STRUCTURE

Project/

hardware/
 pcb/
 schematics/
firmware/
docs/
manufacturing/
simulation/

FIRST TIME CLEAN (if needed)

git rm -r --cached .

git add .

git commit -m "Clean repo using gitignore"