BODY TONE GYM · MANAGEMENT SYSTEM

Scanner and gate setup checklist

From plugging in the fingerprint scanner and relay to the first member let in by fingerprint. Tick each box as you go. If a step fails, stop and send the hardware test report and the log to Apex Dev Studios.

Date _____ PC _____

Branch _____ Done by _____

1 The hardware

- [ ] **ZKTeco ZK9500 fingerprint scanner.** The gym's HID scanner does not work with Gymli.
- [ ] **USB relay board**: Seeit USBM-RELAY02 or an LCUS CH340 board. The gym's Itensity gate box does not work with Gymli.
- [ ] Both plugged into the PC that will run Gymli Check-in. The scanner's light is on.

2 Drivers

- [ ] **ZKTeco driver installed**: `setup.exe` from the ZKFinger SDK ("Fingerprint Reader Standard Driver"). Already done on Luthando's laptop.
- [ ] **Relay driver**: Device Manager → Ports shows `USB-SERIAL CH340 (COMx)`.
  - If it shows an unknown device instead: install the CH340 driver from wch-ic.com (search "CH341SER").

3 Hardware test (before anything else)

Unzip the latest GymliCheckin build, then double-click **Hardware test.bat**. Nothing is saved or sent.

- [ ] Step 2: `libzkfp.dll` **found**.
  - If it says only the 32-bit version is installed: copy the x64 `libzkfp.dll` from the SDK's `c` folder into the GymliCheckin folder.
- [ ] Step 3: 4 scans of one finger → template made.
- [ ] Same finger → **recognised**. A different finger → **not recognised**.
- [ ] Step 5: answer `y` and the relay **clicks**.

Any step fails?
Stop here. Send the report saved on the desktop (`gymli-hardware-test-….txt`) to Apex Dev Studios.

4 Settings (the step most often missed)

The website alone cannot scan. **Gymli.Checkin.exe** must run on the PC the scanner is plugged into. It starts in **simulation mode**, so the settings must be changed first.

- [ ] Web app, signed in as manager, correct branch chosen: **Settings** → **Check-in PCs** → **Add check-in login**. Write the email and password down: the password is shown **once**.

  Email _____

- [ ] Edit **appsettings.json** in the GymliCheckin folder:

```
"Mode": "hardware",
"Reader": "zkteco",
"DeviceEmail": "checkin-…@gymli.local",
"DevicePassword": "…",
"RelayType": "auto",
```

- [ ] If **install.ps1** was ever run on this PC: edit **C:\ProgramData\Gymli\appsettings.json** instead. That file overrides the one in the folder.
- [ ] Start **Gymli.Checkin.exe**. It runs hidden: its icon appears next to the clock.

5 Check it is connected

- [ ] Web app → **Settings** → **Check-in PCs**: **Online**, scanner ✓, gate ✓.

Shows offline?
The check-in email or password in step 4 is wrong, or Gymli.Checkin.exe is not running. Hover the icon next to the clock to see its status.

6 Enrol the new member

- [ ] **Members** → **Add member**, fill in the details and save.
- [ ] **Enrol fingerprint** → **Start**.
- [ ] Press **Capture scan** and place the finger. Do this **4 times**, lifting the finger in between.
- [ ] **Log payment**, for example a day pass. Without a payment the scan is denied: "No paid membership".
- [ ] Scan the finger at the scanner: the relay **clicks once**.
- [ ] **Door log** shows the member as **Let in**.
- [ ] A finger that is not enrolled: no click, Door log shows **Fingerprint not recognised**.

7 The real gate (only after step 6 passes)

- [ ] Relay 1's **COM** and **NO** terminals to the two thin wires that go to the turnstile. Leave NC empty.
- [ ] Scan an enrolled, paid finger: the arm unlocks for **one** entry.

For a desk test
The relay's click is enough. Wire the gate only once the click works.

8 Still on the list (once, before go-live)

- [ ] New database index: in **apps/web** run **npx firebase deploy --only firestore --project fundanii-ai**
- [ ] Clear the old demo data: **npm run reset:live -- <manager email> '<password>'**

! If something goes wrong

What to send

- The hardware test report from the desktop.
- The newest file in **C:\ProgramData\Gymli\logs**.
- A photo of any error on screen.

Good to know

- This is the first run of the scanner code on a real ZK9500. Every error code is logged, so problems can be fixed quickly.
- After a let-in, scans are ignored for 2.5 s while the arm turns.