

1.A user reports their laptop won't power on even when plugged in. List 5 troubleshooting steps you would take to diagnose the cause, and for each step, explain what you are checking for.

Troubleshooting Step	What I am Checking For
1. Check the power outlet and charger	Make sure the wall socket works and the charger is not damaged.
2. Check the charging light	See if the charging LED turns on. If not, the charger or battery may have a problem.
3. Remove the battery (if possible)	Connect only the charger and try to turn on the laptop. This checks if the battery is faulty.
4. Hold the power button for 15–20 seconds	This removes any leftover power and fixes a temporary power issue.
5. Check for hardware problems	Listen for fan noise or look for lights on the laptop. If there is no response, there may be a hardware problem such as the motherboard or RAM.

2.You receive a helpdesk ticket: 'My monitor is showing a blank screen, but the CPU seems to be running.' Write a step-by-step troubleshooting flow you would follow to identify and resolve the issue.Hint: Consider checking both hardware connections and basic display settings.

Troubleshooting Flow for a Blank Monitor

Step	What to Do
1. Check the monitor power	Make sure the monitor is turned on and the power cable is connected properly.
2. Check the display cable	Make sure the HDMI, VGA, or DisplayPort cable is connected tightly to both the monitor and the CPU.
3. Check the monitor input source	Make sure the monitor is set to the correct input (HDMI, VGA, or DP).
4. Restart the computer	Turn the computer off and on again to see if the display comes back.
5. Test with another monitor or cable	Use a different monitor or display cable. If it works, the old monitor or cable is faulty.
6. Check display settings	If the screen appears, check the display resolution and make sure the correct monitor is selected.
7. Check hardware	If the screen is still blank, check the RAM and graphics card to make sure they are properly connected.

3.A user complains that their wireless mouse is unresponsive, but the keyboard works fine. Describe how you would isolate whether the issue is with the mouse, the USB port, or the system settings.

Troubleshooting a Wireless Mouse

Check	What to Do	What It Tells You
1. Check the mouse	Make sure the mouse is turned on and the battery is not dead.	If it still does not work, the mouse may be faulty.
2. Check the USB receiver	Remove the USB receiver and plug it into another USB port.	If it works in another port, the first USB port has a problem.
3. Test the mouse on another computer	Connect the mouse to a different computer.	If it does not work there, the mouse is faulty. If it works, the problem is with the original computer.
4. Check system settings	Open Mouse Settings and Device Manager to see if the mouse is detected and enabled.	If the mouse is disabled or the driver has an error, update or enable it.
5. Restart the computer	Restart the computer and test the mouse again.	This can fix temporary software or driver issues.

4. Imagine you are working on a helpdesk team for a gaming cafe. One system is overheating and shutting down during use. List 3 possible hardware causes and describe how you would check each one. Hint: Think about fans, dust, and thermal paste.

Overheating Computer

Hardware Cause	How to Check
1. Cooling fan is not working	Check if the CPU fan is spinning properly. If it is not spinning or is making noise, replace the fan.
2. Too much dust inside the computer	Open the computer case and check for dust on the fan and heat sink. Clean the dust with compressed air or a soft brush.
3. Thermal paste is old or dry	Remove the CPU cooler and check the thermal paste. If it is dry, clean it and apply new thermal paste.