


Enraged Rabbit Project Carrot Feeder assembly and setup

Printing tips :

- Use the printing tips found on the EnragedRabbit Github (Carrot Feeder section)



1 Prepare the filament blocks





- Each channel of the Carrot Feeder is one filament block
- There two available versions for the block : with or without the M3 threaded insert. The threaded insert is though to insert properly, so if you're not comfortable doing it, use the version without it (you'll screw the M3x16 directly in the plastic)

1-a Insert the magnet and the M3 threaded insert



Every 6x3 magnet insert on the Carrot Feeder has a small flat slot on the side : use it to easily remove the magnet if needed



1-b Insert the latch, lock it with the M3x16 screw (don't screw too hard, be gentle) and insert the numbering plate (just click it in)




Numbering plates can be easily removed with a small flat-head screwdriver, using the bottom slot of the plate

1-c


Prepare the filament block top hat

- Install the free rolling bondtech gear, take care of its orientation!
- Insert the 6x3 magnet : **IT SHOULD REPEL THE ONE FROM THE FILAMENT BLOCK**




1-d

Slide in the top hat locker plate (use the « 0 » value to begin with). Make sure it's fully inserted



1-e

Press-fit the ECAS bowden fit and install the top hat block you just did




- Top hat should be inserted without forcing too much (play with the part orientation)
- Once inserted, rest position should be as seen on the left, thanks to the repelling magnets (with latch open)
- Push down the top hat and close the latch. You can now press on the top hat with a finger (it will go down) and release the finger (it will go up), like a spring mechanism

2

Gear box assembly


2-a

Prepare the M4 wheel



GT2 20T Pulley 6 mm,
5mm bore, endcap removed


M3x8 (or 6) BHCS



2-b

Prepare the Gear Box front


MR85 bearing



7xM3 threaded inserts

- Those M3 threaded inserts are difficult to insert (not much plastic behind), go slowly and do not put your soldering iron tip inside the insert if the tip sticks out of it
- Push those inserts using the soldering iron from the side, and take your time to make them well aligned with the holes


Mechanical switch

2x M2x10 SHCS
(not shown)

- Pre-wire the mechanical endstop (should be in a NO configuration). Prepare around 10 cm long of cables (24 awg is more than enough). Crimping will be done later in the build

2-c


Prepare the Gear Box back



4xM3 threaded inserts


2-d

Prepare the M4 Gear Arm




Don't forget to put some blue Loctite or similar on the grub screw of the GT2 20T Pulley

- You can already install the Gear motor (G label on the connector plate) cabling. Connect the 4 pins molex microfit connector in the dedicated slot (press fit). Use the zip-tie channel to secure the cable path



i The microfit connector to install in the ERCF is the Female housing (with Male crimps). Just push them from the ERCF inside towards the exterior




Molex Microfit connector to install in the ERCF part

2-e Prepare the 2x M5 threaded rods

2xM5 nuts (nut + counter-nut) OR 1xM5 nut + 1xM5 Nylock nut (the outside one)




2-f Install the threaded rods in the Gear Box Front



2-g Install the first Side Latch and the Gear Box Back

i Before installing the Side Latches, make sure you've released their print-in-place mechanism (use a allen wrench in the arm's hole to unlock it if needed)

- Do not screw too hard the 2x M3x20 SHCS, you should be able to lock//unlock the latch without trouble



2-g

Install the 5mm axis

188mm GT2,
6mm belt

5mm D-cut shaft

M4 Wheel

Don't forget to install the belt!

No need to tighten the grub screws for the M4 wheel yet, we'll adjust the wheel//shaft position later

2-hInstall the 2nd Side Latch and the M4 Gear Arm

2x M3x40 SHCS

2x M3x12 SHCS

2-i

Install the knob, tighten the M4 grub screw and tension the belt

- Press fit to the max the Knob on the 5mm shaft
- Put the Knob + Shaft assembly at around 1mm of the M4 Gear Arm part
- Tighten the M4 Wheel grub screws using the side access
- Tighten the belt by rotating the motor around it's M3x12 SHCS screw
- Test the motion using the Knob, it should be smooth

M4 Wheel grub
screw access

Knob

2-j

Take a break, eat some gummy bears (not provided) or whatever, if you want !

3

Prepare the Block End

MR85 bearing

2xM3 threaded inserts

4

Install the Filament Blocks

4-a

Slide a single Bondtech gears on the 5mm shaft


Yes, only one ! Also don't tighten its grub screw**Take care of the gear orientation !!**

Bondtech gear

4-b

Slide in the first filament block

Filament Block



4-c


Repeat steps 4-a and 4-b for all your Filament Blocks

4-d

Plot twist : Also slide in the Bearing Blocks (recommended is 1 Bearing Block every 3 Filament Blocks)

MR85 bearing


Bearing Block



4-e

When all blocks are inserted, install the Block End

- Use your fingers to push the threaded rods, in the gear box, into their proper position
- Tighten the M5 nuts on the M5 threaded rods
- While the whole assembly should be relatively stiff, it will flex//bend, this is expected
- Check that the 5mm D-cut shaft is well inserted into the bearing of the Block End
- Don't check the 5mm axis motion yet, as no Bondtech gears are tighten yet




M5 washer + Nut (not shown yet)

5

Align and tighten the Bondtech gears


1,75mm filament

Gear to align




- Use a small ptfе tube (a few cms long is enough) and insert it in the first channel
- Use a some 1,75mm filament and insert it in the channel
- Use the knob to align the D-Cut shaft (cut facing the top)
- Align the Bondtech gears properly on the filament and screw it down, use some blue Loctite on the grub screw
- To check the proper alignment : Once done, let the filament in the filament block and turns by hand the gear axis using the knob (both directions). The filament should not move (it should not touch the Bondtech gears you've just fixed)
- Repeat this process for all channels

6 Assemble the detector cart






6-a Prepare the detector cart parts






6-b Install the lever

- Make sure the lever spins freely around the 1,75mm filament axis
- Install the magnets so they repel each other !
- The rest position of the lever should be « down » (right picture) while the triggered position (using a 1,75 filament) should be « up » (left picture)



6-c Install the optical detector


- Slide the optical detector into its support
- Install the detector support in the detector cart and then slide//screw in the 2xM3x30 SHCS screws
- Use the screws to position the detector around the middle of his allow movement range
- Make sure the head of the 2 screws are well inserted in the bottom slots of the detector cart and then slide in the Sliding Locker



i You can now use the two screws to precisely adjust the optical detector position (we'll do that later in the assembly//setup)

7


Assemble the Selector Cart



7-a


Prepare the detector cart parts

- Make sure magnets (Selector Cart and the Selector Door) attract each other
- Use 2x M2x8mm screws (or similar) to fix the servo on the cart, directly screw in the plastic part
- The LM8UU (or the RJ4JP-01-08) are press-fitted in their slot



7-a


Assemble the detector cart parts



- Slide-in the Detector Cart, make sure the 2x M3X20 SHCS screws of the Detector Cart slides properly in their dedicated slots on the Selector Cart (they are not screwed-in, just guided)
- Just clip the door, as shown on the item #7. We'll deal with the wiring later on


8

Assemble the whole top linear axis



8-a

Prepare the idler block



M5 Nylock nut


M5x16 BHCS




GT2 20T idler, 6mm width, 5mm bore

8-b

Prepare the motor support



4x M3 threaded inserts




2x M3 threaded inserts

GT2 20T Pulley, 6mm width, 5mm bore

Motor lock

NEMA17 20mm Pancake



2x M3x8 SHCS


4x M3x8 SHCS

Don't tighten the grub screw yet

8-c


Prepare the selector cart cabling

- Connect the optical sensor using a JST connector and then insert the 3 wires into the dedicated groove, up to the drag chain anchor point
- Use the servo motor cable zip tie slot to firmly secure the servo wiring, make sure the servo cable is doing a nice « 90° » turn in between the servo and the zip tie slot, as shown below



Servo motor cable

Zip tie




Drag chain end zip tie slot

Filament detector cable groove

Servo motor cable zip tie slot

8-d


Assemble the axis



- Insert **FULLY** the 8mm smooth rods in the idler block, you can see them on the other side of the idler block hole
- Insert the selector cart on the 8mm rods
- Insert the rods other end in the motor support, and use 2x M3x12 SHCS screw to get in contact with the rods (adjustment will be done later on)

2x M3x12 SHCS


9 Assemble the top block to the bottom one



- Tighten the 2x M5x30 BHCS screws and make sure that the top block can rotate properly while having a stiff junction


10 Finish the cabling

10-a Install the 7x7 drag chain




- Pass the servo and optical sensors cables into the drag chain, then fix the drag chain to the system
- Use zip-ties to secure cables at both ends of the drag chain

10-b Pass the whole wire harness to the ERCF connector plate



- Add the NEMA17 pancake motor cable to the wire harness from the selector, anchor the whole harness to the Block_End part using the dedicated zip tie slot
- Use the groove under the filaments blocks to guide the wire harness to the micro-fit connector plate on the GearBox. Use the zip tie slots on the bearing blocks to secure the harness

10-c Install the 2 ERCF feet




Don't pinch the wire harness under the 2 feet!

11 Install the selector belt

11-a Install the Gear_Box_Top


Gear motor cable groove



3x M3x8 SHCS

11-b Adjust the 8mm rods


Screws for the adjustment



- Use the screws on the selector-motor side to finely adjust the 8mm rods position. The goal is to match the 3 domes pattern on the Idler_Block on the ones of the Gear_Box_Top. You should be able to lock the two latches without any issues when you close the top block.



11-c Install and tension the selector belt



M3x20 SHCS

- Use the belt_tensionner and a M3x20 SHCS screw to tension the 6mm GT2 belt. Ensure nothing is bending due to overtightening

Main assembly of the ERCF is done!

Good job!

- You may have noticed that we didn't install the servo arm yet! Don't worry, this will be done in step 13!

12 (Optionnal) Installation on a Voron V2

12-a Choosing a connector output



- There are two possibilities for you to wire the ERCF to your Voron V2, either using the MicroFit3 connectors leftovers you should have after building the V2 or using JST-SM connectors
- Build your ERCF cable accordingly, using the following guidelines :



S for Selector Motor
(the pancake), 4 pins




G for Gear Motor
(the big one), 4 pins



12-b Connections in the electronics compartment

- This is an exemple, you can adapt it to your setup of course. **Only mandatory part is to use the 5V/GND from the Rpi power supply** (the 5V 5A you should have), servo are power hungry and it won't behave that well if the current is drawn from the SKR

'XY//AB' SKR Board





Servo PWM (pin 1.26)

Endstop signal (pin 1.25)

Optical sensor signal (pin 1.0)

Toolhead filament detector
(5V, GND and signal)

- You can install the ERCF in any position//orientation you want. If you wish to use the typical Vertical-at-the-back-of-the-V2 or the typical Horizontal-on-the-top-of-the-V2 installations, you can use the following mounting system



Example of my own setup (V2.4 300mm³, 9 channels ERCF). Don't mind the 2020 draft assembly, I don't have the proper 2020 lengths for the ERCF support yet.

13 First steps with the ERCF

13-a Install the servo arm

13-c Calibrate the channels

13-b Home the ERCF

First steps guide coming soon!!!