GENERAL INFORMATION:

SIMPLWINDOWS NAME:	Qsys Nv Decoder
CATEGORY:	Qsys
VERSION:	5.0.0
SUMMARY:	Selects the source for one HDMI output of a Q-SYS NV Series decoder (e.g. NV-32-H) and reports the currently selected source.
GENERAL NOTES:	Source values are sent unchanged as the decoder output's select index; use the numbering shown on that output's source selector in Q-SYS. Use one instance of this module per HDMI output to be controlled.
CRESTRON HARDWARE REQUIRED:	3 Series Processor or 4 Series Processor
SETUP OF CRESTRON HARDWARE:	Requires a Qsys Core module in the same program with a matching CoreID.
VENDOR FIRMWARE:	N/A
VENDOR SETUP:	Works with a Q-SYS NV Series decoder (e.g. NV-32-H, NV-21-HU); Script Access must be External or All.
GENERATION:	Generated by Claude Code from SIMPL+ and SIMPL# source files

CONTROL:

Source	A	Source index to route to the selected HDMI output. Sent each time the value changes.

FEEDBACK:

[CurrentSource]	A	Source index currently selected on the HDMI output, as reported by Q-SYS.

PARAMETERS:

CoreID	S	Used to address this module to a Qsys Core module. Must match the CoreID of the Qsys Core module. Default: 1
ComponentName	S	Code Name of the NV decoder component in the Q-SYS design.
OutputNumber	Dec	HDMI output to control (0–2). Default: 1

TESTING:

SAMPLE PROGRAM:	3-Series: 3 Series Test.smw 4-Series: 4 Series Test.smw
REVISION HISTORY:	