GENERAL INFORMATION:

SIMPLWINDOWS NAME:	Qsys Matrix Mixer Output All Crosspoints
CATEGORY:	Qsys
VERSION:	5.0.0
SUMMARY:	Controls and reports the mute state of every crosspoint feeding one output of a Q-SYS Matrix Mixer, from input 1 up to InputCount. The mixer is addressed as a Named Component by its Code Name (ComponentName parameter). For each input X up to InputCount, the module uses the input_X_output_Y_mute control, where Y is the Output parameter.
GENERAL NOTES:	Only inputs 1 to InputCount are controlled. Signals above InputCount do nothing. MuteIsOn[n] follows the Q-SYS control, so it also updates when changes are made from Q-SYS or another control system. Current states are sent when the module connects to the Core. Use one instance of this module per mixer output.
CRESTRON HARDWARE REQUIRED:	3 Series Processor or 4 Series Processor
SETUP OF CRESTRON HARDWARE:	Requires a Qsys Core module in the same program with a matching CoreID.
VENDOR FIRMWARE:	N/A
VENDOR SETUP:	In Q-SYS Designer, set the Matrix Mixer component's Code Name to match the ComponentName parameter and set its Script Access to External (or All).
GENERATION:	Generated by Claude Code from SIMPL+ and SIMPL# source files

CONTROL:

[MuteOn[1]]–[MuteOn[128]]	D	Pulse to mute the crosspoint from input n to the selected output.
[MuteOff[1]]–[MuteOff[128]]	D	Pulse to unmute the crosspoint from input n to the selected output.

FEEDBACK:

[MuteIsOn[1]]–[MuteIsOn[128]]	D	High while the crosspoint from input n to the selected output is muted.

PARAMETERS:

CoreID	S	Used to address this module to a Qsys Core module. Must match the CoreID of the Qsys Core module. Default: 1
ComponentName	S	Code Name of the Matrix Mixer component in the Q-SYS design.
InputCount	Dec	Number of mixer inputs to control, starting at input 1 (1–128).
Output	Dec	Matrix Mixer output number whose crosspoints are controlled.

TESTING:

SAMPLE PROGRAM:	3-Series: 3 Series Test.smw 4-Series: 4 Series Test.smw
REVISION HISTORY:	