Pin Description:

The T_ beginning of interface are for touch control pins ; The SD_ beginning of interface are for SD card control pins ; The F_ beginning of interface are for flash control pins ; Others interface are for TFT control pins

51 Test Code Interface Description:

Working voltage: 3.3V

Default IO connections:

Control Line：RS-P3^5;　WR-P3^6;　RD-P3^7;　CS-P1^0;　REST-P1^2;

Data Line: DB0-DB7 connect with P0^0-P0^7; DB8-DB15 connect with P2^0-P2^7;

Touch function of the connection:

(if you don't use the touch function and then don't connect)

D_CLK-P1^7; D_CS-P1^4; D_DIN-P3^0; D_OUT-P3^1; D_PENIRQ-P3^4;

● TFT Power: the power of the screen is 2.8-3.3V; don't use 5V, all pin voltage of this module must not exceed 3.3V.

● Backlight: the module has inherited the backlight driver circuit, When the LED_A interface connect with high level, then the backlight will be light; When the LED_A interface connect with low level, then the backlight will be not light; When the LED_A interface connect with PWM signal, then can control the brightness of the backlight.

Special note: the 4.3-inch and larger TFT backlight current consumption is relatively large, (the brightest 4.3-inch is more than 200 ma, the brightest 5-inch is more than 300 ma, the brightest 7 inch is more than the 500ma) If you are using USB power, then may exist some computer motherboards current supply is not enough, and it may cause severe partial pressure, which may causes the module does not work due to poor quality USB connection. Please make sure your power supply is stable enough. Thank you!