Chassis: Load/Balancer lab

In this lab you will configure a **chassis** with a load balancer and a [client machine](#) as shown in the illustration below.

Before you begin, you must have a load balancer, client machine, client config object, and server pool that you created in the previous labs.

Refer to the illustration and to the Chassis: Add slots and ports checklist that follows.

Procedure

1. Create a chassis. In the navigation pane, click Chassis and click the plus sign (+) next to Chassis. Name the chassis Chassis1 and click Create. Chassis1 appears in the navigation pane.
2. Add a load balancer slot. Click Chassis1 and click the plus sign (+) next to Slots. Name the slot LoadBalancer1 and click Create.
3. Add a client machine slot. Click Chassis1 and click the plus sign (+) next to Slots. Name the slot Client1 and click Create.

Addresses: install Round 2

Objective Add a new address to a client machine.

Scenario You have been asked to add a new address to a client machine. You have the example shell file that you created in the last lab, and you can modify it for this task.

Add the following line to the example shell file: `ifconfig eth1:1 10.1.1.1 netmask 255.255.255.0 up`

Save the file.

Run the shell file from the client machine. Switch to root first. Enter the command: `sh /tmp/example`

Verify the address is added by entering the command: `ifconfig -a`

```
[root@client1 ~]# ifconfig -a
eth0      Link encap:Ethernet  HWaddr 00:0C:29:E3:E1:E3
          inet addr:192.168.1.10  Bcast:192.168.1.255  Mask:255.255.255.0
          inet6 addr: fe80::20c:29ff:fee3:e1e3/64 Scope:Link
          UP BROADCAST RUNNING MULTICAST  MTU:1500  Metric:1
          RX packets:1 errors:0 dropped:0 overruns:0 frame:0
          TX packets:1 errors:0 dropped:0 overruns:0 carrier:0
          collisions:0 txqueuelen:1000
          RX bytes:60 (60.0 b)  TX bytes:60 (60.0 b)

eth1      Link encap:Ethernet  HWaddr 00:0C:29:E3:E1:ED
          inet addr:10.1.1.1  Bcast:10.1.1.255  Mask:255.255.255.0
          UP BROADCAST RUNNING MULTICAST  MTU:1500  Metric:1
          RX packets:0 errors:0 dropped:0 overruns:0 frame:0
          TX packets:0 errors:0 dropped:0 overruns:0 carrier:0
          collisions:0 txqueuelen:1000
          RX bytes:0 (0.0 b)  TX bytes:0 (0.0 b)

lo        Link encap:Local Loopback
          inet addr:127.0.0.1  Mask:255.0.0.0
          inet6 addr: ::1/128 Scope:Host
          UP LOOPBACK RUNNING  MTU:16436  Metric:1
          RX packets:0 errors:0 dropped:0 overruns:0 frame:0
          TX packets:0 errors:0 dropped:0 overruns:0 carrier:0
          collisions:0 txqueuelen:0
          RX bytes:0 (0.0 b)  TX bytes:0 (0.0 b)

[root@client1 ~]#
```

Notice that eth1:1 is not yet active.

Add the route to make the subinterface active according to plan B.