



SILENT SENTINEL

a Motorola Solutions Company

Fuji SX Camera External Universal Protocol

v2.4.4

1 Overview

This document describes **External Universal Protocol** to control **Fuji Sx** daylight block cameras (combined lens and camera). This document lists supported commands by **FujiSxCamera** driver. In the **NexOS** systems the **Fuji Sx** daylight camera always has name **Camera2**.

2 Lens control messages

The **Lens** submodule is part of the **Camera2** module. This submodule is responsible for lens control.

Table 2.1 - Action Commands and Parameter Change Commands: Messages start from **.../Command/Camera2/Lens/...** If the command is successfully sent to the lens controller, the system responds with **Ack**. Expected response time: **ip ping time to the system + 5 msec**. If a particular command is not supported by **FujiSxCamera** driver the **NexOS** system will return **Ack** but the action command or parameter will not be accepted by lens driver.

Command	Description
ZoomIn	Move zoom tele (in).
ZoomOut	Move zoom wide (out).
ZoomToPos:n	Move zoom to position. Parameter n : integer position value from 0 (full wide) to 65535 (full tele).
ZoomPos:n	Set zoom position. Parameter n : integer position value from 0 (full wide) to 65535 (full tele). Equivalent to ZoomToPos:n .
ZoomHwPos:n	Set zoom hardware position. Parameter n : integer position value from 0 (full wide) to 65535 (full tele). Equivalent to ZoomToPos:n .
ZoomStop	Stop zoom movement including stop zoom to position command.
FocusFar	Move focus far.
FocusNear	Move focus near.

Command	Description
FocusToPos:n	Move focus to position. Parameter n : integer position value from 0 (full near) to 65535 (full far).
FocusPos:n	Set focus position. Parameter n : integer position value from 0 (full near) to 65535 (full far). Equivalent to FocusToPos:n .
FocusHwPos:n	Set focus hardware position. Parameter n : integer position value from 0 (full near) to 65535 (full far). Equivalent to FocusToPos:n .
FocusStop	Stop focus movement including stop focus to position command.
IrisOpen	Move iris open.
IrisClose	Move iris close.
IrisToPos:n	Not supported by FujiSxCamera driver.
IrisPos:n	Not supported by FujiSxCamera driver.
IrisHwPos:n	Not supported by FujiSxCamera driver.
IrisStop	Not supported by FujiSxCamera driver.
RunAf	Start autofocus. It uses built in auto focus algorithm.
StopAf	Not supported by FujiSxCamera driver.
Restart	Restart lens controller.
FocusMode:n	Focus mode. Parameter n (integer): 0 - Manual 1 - Auto 2 - Quick auto focus.
FilterMode:n	Filter mode. Parameter n (integer): 0 - Visible light 1 - 950 nm 2 - 940 nm 3 - 850 nm 4 - 808 nm.
AfRoiMode:n	Not supported by FujiSxCamera driver.
ZoomSpeed:n	Set zoom speed. Parameter n : integer speed value [0-100%] of max hardware zoom speed.
FocusSpeed:n	Set focus speed. Parameter n : integer speed value [0-100%] of max hardware focus speed.
IrisSpeed:n	Not supported by FujiSxCamera driver.
FocusFactorThreshold:n	Set autofocus sensitivity. Parameter n (integer): 0 to 100 . Higher value means more sensitive autofocus trigger.
RefocusTimeoutSec:n	Not supported by FujiSxCamera driver.

Command	Description
IrisMode:n	Set iris mode. Parameter n (integer): 0 - Auto iris (full open); 1 to 13 - Manual iris position step for Sx800 lens; 1 to 19 - Manual iris position step for Sx1600 lens.
ExtenderMode:n	Not supported by FujiSxCamera driver.
StabiliserMode:n	Set optical image stabilization (OIS) mode. Parameter n (integer): 0 to 3 .
AfRange:n	Not supported by FujiSxCamera driver.
XFovDeg	Set horizontal field of view angle, degree. Parameter n : float horizontal field of view angle [deg].
YFovDeg	Set vertical field of view angle, degree. Parameter n : float vertical field of view angle [deg].
Custom1:n	Set AF area. Parameter n (integer): 0 - Center (fixed) 1 - Upper left 2 - Upper center 3 - Upper right 4 - Middle left 5 - Middle of middle 6 - Middle right 7 - Lower left 8 - Lower center 9 - Lower right
Custom2:n	Set backlight compensation. Parameter n (integer): 0 - OFF 1 - soft 2 - hard.
Custom3:n	Not supported by FujiSxCamera driver.
ZoomMaxSpeed:n	Set maximum zoom speed limit in JafarService. Parameter n (integer): 0 to 100 %. The speed set by ZoomSpeed:n or the AtRate modifier is scaled by this limit. Default: 100 %.
FocusMaxSpeed:n	Set maximum focus speed limit in JafarService. Parameter n (integer): 0 to 100 %. The speed set by FocusSpeed:n or the AtRate modifier is scaled by this limit. Default: 100 %.

Table 2.2 - Lens submodule queries. Messages start from **.../Query/Camera2/Lens/...**. Response from the system starts with **.../Reply/Camera2/Lens/...**. Expected response time: **ip ping time to the system + 5 msec**. If a particular query is not supported by **FujiSxCamera** driver the **NexOS** system will return default value which is not related to real behavior of lens.

Command	Description
ZoomPos	Query zoom position. Response: .../ZoomPos:n . Parameter n : integer position value from 0 (full wide) to 65535 (full tele).

Command	Description
FocusPos	Query focus position. Response: .../FocusPos:n . Parameter n : position value from 0 (full near) to 65535 (full far).
ZoomHwPos	Query zoom hardware position. Response: .../ZoomHwPos:n . Parameter n : integer position value from 0 (full wide) to 65535 (full tele).
FocusHwPos	Query focus hardware position. Response: .../FocusHwPos:n . Parameter n : position value from 0 (full near) to 65535 (full far).
IrisPos	Not supported by FujiSxCamera driver.
IrisHwPos	Not supported by FujiSxCamera driver.
ZoomSpeed	Query zoom speed. Response: .../ZoomSpeed:n . Parameter n : speed value [0-100%] (relative for particular lens).
FocusSpeed	Query focus speed. Response: .../FocusSpeed:n . Parameter n : speed value [0-100%] (relative for particular lens).
IrisSpeed	Not supported by FujiSxCamera driver.
FocusMode	Query focus mode. Response: .../FocusMode:n . Parameter n (integer): 0 - Manual 1 - Auto 2 - Quick auto focus.
FilterMode	Query filter mode. Response: .../FilterMode:n . Parameter n (integer): 0 - Visible light 1 - 950 nm 2 - 940 nm 3 - 850 nm 4 - 808 nm.
AfRoiMode	Not supported by FujiSxCamera driver.
IsConnected	Query connection status. Connection status show if lens controller has communication with lens hardware. Response: .../IsConnected:n . Parameter n : 0 - no response from lens, 1 - connected.
IsOpen	Query lens controller initialization status. Response: .../IsOpen:n . Parameter n (integer): 0 - lens controller not init, 1 - init.
FocusFactor	Not supported by FujiSxCamera driver.
FocusFactorThreshold	Not supported by FujiSxCamera driver.
RefocusTimeoutSec	Not supported by FujiSxCamera driver.
IsAfActive	Not supported by FujiSxCamera driver.
IrisMode	Not supported by FujiSxCamera driver.
ExtenderMode	Not supported by FujiSxCamera driver.
AfRange	Not supported by FujiSxCamera driver.

Command	Description
XFovDeg	Get horizontal field of view angle, degree. Response: .../XFovDeg:n . Parameter n : float horizontal field of view angle [deg].
YFovDeg	Get vertical field of view angle, degree. Response: .../YFovDeg:n . Parameter n : float vertical field of view angle [deg].
Temperature	Not supported by FujiSxCamera driver.
Custom1	Query AF area. Response: .../Custom1:n . Parameter n : 0 - Center (fixed) 1 - Upper left 2 - Upper center 3 - Upper right 4 - Middle left 5 - Middle of middle 6 - Middle right 7 - Lower left 8 - Lower center 9 - Lower right
Custom2	Query backlight compensation. Response: .../Custom2:n . Parameter n : 0 - OFF 1 - soft 2 - hard.
Custom3	Not supported by FujiSxCamera driver.
Type	Query lens type. Response: .../Type:n . Parameter n (string): FujiSx800 or FujiSx1600 depending on configured lens model.

Some example messages:

[client -> system] **ID:14/Command/Camera2/Lens/ZoomToPos:12000** - Go to zoom position 12000.

[system -> client] **ID:14/Ack** - Command accepted.

[client -> system] **ID:16/Query/Camera2/Lens/FocusPos** - Query focus position from camera 2.

[system -> client] **ID:16/Reply/Camera2/Lens/FocusPos:100** - Focus position from camera 2.

3 Camera control messages

Camera is a submodule which is part of **Camera2** module. **Camera** submodule is responsible for camera core (image sensor) control.

Table 3.1 - Action commands and commands to change parameters. Messages start from **.../Command/Camera2/Camera/....** Response from the system: **Ack**. Expected response time: **ip ping time to the system + 5 msec**. If a particular command is not supported by **FujiSxCamera** driver the **NexOS** system will return **Ack** but the action command or parameter will not be accepted by camera driver.

Command	Description
Restart	Restart camera controller.

Command	Description
Nuc	Not supported by FujiSxCamera driver.
ApplyParams	Defined as MENU BACK command.
SaveParams	Not supported by FujiSxCamera driver.
MenuOn	Enter camera menu.
MenuOff	Exit camera menu.
MenuSet	Menu SET command.
MenuUp	Move menu cursor up.
MenuDown	Move menu cursor down.
MenuLeft	Move menu cursor left.
MenuRight	Move menu cursor right.
FreezeSec:n	Not supported by FujiSxCamera driver.
Defreeze	Not supported by FujiSxCamera driver.
DisplayMode:n	Set display mode (camera menu). Parameter n (integer): 0 - Off, 1 - On.
ExposureMode:n	Not supported by FujiSxCamera driver.
ExposureTime:n	Set exposure time of the camera sensor. Parameter n (integer): the exposure time is limited by the frame interval. Camera controller should interpret the values as 100 μ s units, where the value 1 stands for 1/10000th of a second, 10000 for 1 second and 100000 for 10 seconds.
WhiteBalanceMode:n	Set white balance mode. Parameter n (integer): 1 or 0 - Auto 2 - Custom1 (Read preset, which can be set only by SDI menu) 3 - Custom2 (Read preset, which can be set only by SDI menu) 4 - Day 5 - Cloud 6 - ColorTemperature(Set the color temperature) 7 - Auto (white priority) others - Auto.
WhiteBalanceArea:n	Not supported by FujiSxCamera driver.
WideDynamicRangeMode:n	Set wide dynamic range mode. Parameter n (integer): 0 or 1 - Off, 2 - level 1, 3 - level 2.
StabilisationMode:n	Not supported by FujiSxCamera driver.

Command	Description
IsoSensitivity:n	Set ISO sensitivity. ShutterMode should be set to 0 - Manual shutter. Parameter n (integer): 1 - ISO 400 2 - ISO 500 3 - ISO 640 4 - ISO 800 5 - ISO 1000 6 - ISO 1250 7 - ISO 1600 8 - ISO 2000 9 - ISO 2500 10 - ISO 3200 11 - ISO 4000 12 - ISO 5000 13 - ISO 6400 14 - ISO 8000 15 - ISO 10000 16 - ISO 12800 17 - ISO 25600 18 - ISO 51200 19 - ISO 102400 20 - ISO 204800 21 - ISO 409600 22 - ISO 819200 others - ISO 400.
SceneMode:n	Set Day/Night mode. Parameter n (integer): 0 - Auto 1 - Manual Day 2 - Manual Night.
BrightnessMode:n	Not supported by FujiSxCamera driver.
Brightness:n	Set brightness. Parameter n (integer): 0 - 100%.
Contrast:n	Set contrast. Parameter n (integer): 1 - 100%.
GainMode:n	Set gain mode. Parameter n (integer): 0 - Standard 1 - Off 2 - Hyper others - Standard.
Gain:n	Not supported by FujiSxCamera driver.
SharpeningMode:n	Not supported by FujiSxCamera driver.
Sharpening:n	Set sharpening. Parameter n (integer): 1 - 100%.
Palette:n	Not supported by FujiSxCamera driver.

Command	Description
AgcMode:n	Set analog gain control mode. Parameter n (integer): 0 - Standard 1 - Off 2 - Hyper others - Standard.
ShutterMode:n	Set shutter mode. Parameter n (integer): 0 - Manual shutter 1 - Auto shutter, Lowest limit 1/8 sec 2 - Auto shutter, Lowest limit 1/15 sec 3 - Auto shutter, Lowest limit 1/30 sec 4 - Auto shutter, Lowest limit 1/60 sec 5 - Auto shutter, Lowest limit 1/125 sec others - Auto shutter, Lowest limit 1/8 sec.
ShutterPos:n	Not supported by FujiSxCamera driver.

Command	Description
ShutterSpeed:n	Set shutter speed. SHUTTER_MODE should be set to 0 - Manual shutter. Parameter n (integer): 1 - 1 2 - 1/1.3 3 - 1/1.6 4 - 1/2 5 - 1/2.5 6 - 1/3 7 - 1/4 8 - 1/5 9 - 1/6 10 - 1/8 11 - 1/10 12 - 1/13 13 - 1/15 14 - 1/20 15 - 1/25 16 - 1/30 17 - 1/40 18 - 1/50 19 - 1/60 20 - 1/80 21 - 1/100 22 - 1/120 23 - 1/125 24 - 1/160 25 - 1/200 26 - 1/250 27 - 1/320 28 - 1/400 29 - 1/500 30 - 1/640 31 - 1/800 32 - 1/1000 33 - 1/1250 34 - 1/1600 35 - 1/2000 36 - 1/2500 37 - 1/3200 38 - 1/4000 39 - 1/5000 40 - 1/6400 41 - 1/8000 42 - 1/10000 43 - 1/12800 44 - 1/16000 45 - 1/20000

Command	Description
	46 - 1/32000 others - 1/30.
ExposureCompensationMode:n	Not supported by FujiSxCamera driver.
ExposureCompensationPos:n	Not supported by FujiSxCamera driver.
DefogMode:n	Set defog mode. Parameter n (integer): 0 - Off 1 - level 1 2 - level 2 3 - level 3 others - Off.
DehazeMode:n	Set dehaze mode (heat haze reduction). Parameter n (integer): 0 - Off 1 - level 1 2 - level 2 3 - level 3 others - Off.
NoiseReductionMode:n	Set noise reduction mode. Parameter n (integer): 1 - Weak 2 - Middle 3 - Strong 0 - Middle.
BlackAndWhiteFilterMode:n	Not supported by FujiSxCamera driver.
FilterMode:n	Set filter mode. Parameter n (integer): 0 - Visible light 1 - 950 nm 2 - 940 nm 3 - 850 nm 4 - 808 nm others - visible light.
NucMode:n	Not supported by FujiSxCamera driver.
AutoNucIntervalSec:n	Not supported by FujiSxCamera driver.
AutoNucIntervalMin:n	Not supported by FujiSxCamera driver.
DdeMode:n	Not supported by FujiSxCamera driver.
DdeLevel:n	Not supported by FujiSxCamera driver.
AlcGate:n	Not supported by FujiSxCamera driver.
Sensitivity:n	Not supported by FujiSxCamera driver.
ChangingMode:n	Not supported by FujiSxCamera driver.

Command	Description
ChangingLevel:n	Set day to night changes threshold. Parameter n (integer): 0-255 level.
ChromaLevel:n	Not supported by FujiSxCamera driver.
Detail:n	Not supported by FujiSxCamera driver.
Profile:n	Set camera preset profile. Parameter n (integer): 0 - Day preset: defog off, ISO 400, day mode. 1 - Night preset: defog off, ISO 400, night mode. 2 - Auto preset: defog off, ISO 400, auto day/night mode. 3 - Defog preset: defog level 2, ISO 400, day mode. 4 - Max sensitivity preset: defog off, ISO 819200, day mode.
Custom1:n	Set night to day changes threshold. Parameter n (integer): 0-255 level.
Custom2:n	Set color temperature on white balance. WhiteBalanceMode should be set to 6 - ColorTemperature(Set the color temperature). Parameter n (integer): 1 - 3000K 2 - 5000K 3 - 9000K.
Custom3:n	Set antialiasing. Parameter n (integer): 0 - off 1 - on.
AgcRoiX0:n	Not supported by FujiSxCamera driver.
AgcRoiY0:n	Not supported by FujiSxCamera driver.
AgcRoiX1:n	Not supported by FujiSxCamera driver.
AgcRoiY1:n	Not supported by FujiSxCamera driver.

Table 3.2 - Camera submodule queries. Messages start from **.../Query/Camera2/Camera/...** Response from the system starts with **.../Reply/Camera2/Camera/...** Expected response time: **ip ping time to the system + 5 msec**. If a particular query is not supported by **FujiSxCamera** driver the **NexOS** system will return default value which is not related to real behavior of camera.

Command	Description
DisplayMode	Query display mode (camera menu). Response: .../DisplayMode:n . Parameter n (integer): 0 - Off, 1 - On.
ExposureMode	Not supported by FujiSxCamera driver.

Command	Description
ExposureTime	Query exposure time of the camera sensor. Response: .../ExposureTime:n . Parameter n (integer): the exposure time is limited by the frame interval. Camera controller should interpret the values as 100 µs units, where the value 1 stands for 1/10000th of a second, 10000 for 1 second and 100000 for 10 seconds.
WhiteBalanceMode	Query white balance mode. Response: .../WhiteBalanceMode:n . Parameter n (integer): 1 or 0 - Auto 2 - Custom1 (Read preset, which can be set only by SDI menu) 3 - Custom2 (Read preset, which can be set only by SDI menu) 4 - Day 5 - Cloud 6 - ColorTemperature(Set the color temperature) 7 - Auto (white priority) others - Auto.
WhiteBalanceArea	Not supported by FujiSxCamera driver.
WideDynamicRangeMode	Query wide dynamic range mode. Response: .../WideDynamicRangeMode:n . Parameter n (integer): 0 or 1 - Off, 2 - level 1, 3 - level 2.
StabilisationMode	Not supported by FujiSxCamera driver.
IsoSensitivity	Query ISO sensitivity. ShutterMode should be set to 0 - Manual shutter. Response: .../IsoSensitivity:n . Parameter n (integer): 1 - ISO 400 2 - ISO 500 3 - ISO 640 4 - ISO 800 5 - ISO 1000 6 - ISO 1250 7 - ISO 1600 8 - ISO 2000 9 - ISO 2500 10 - ISO 3200 11 - ISO 4000 12 - ISO 5000 13 - ISO 6400 14 - ISO 8000 15 - ISO 10000 16 - ISO 12800 17 - ISO 25600 18 - ISO 51200 19 - ISO 102400 20 - ISO 204800 21 - ISO 409600 22 - ISO 819200 others - ISO 400.

Command	Description
SceneMode	Query Day/Night mode. Response: .../SceneMode:n . Parameter n (integer): 0 - Auto 1 - Manual Day 2 - Manual Night.
BrightnessMode	Not supported by FujiSxCamera driver.
Brightness	Query brightness. Response: .../Brightness:n . Parameter n (integer): 0 - 100%.
Contrast	Query contrast. Response: .../Contrast:n . Parameter n (integer): 1 - 100%.
GainMode	Query gain mode. Response: .../GainMode:n . Parameter n (integer): 0 - Standard 1 - Off 2 - Hyper others - Standard.
Gain	Not supported by FujiSxCamera driver.
SharpeningMode	Not supported by FujiSxCamera driver.
Sharpening	Query sharpening. Response: .../Sharpening:n . Parameter n (integer): 1 - 100%.
Palette	Not supported by FujiSxCamera driver.
AgcMode	Query analog gain control mode. Response: .../AgcMode:n . Parameter n (integer): 0 - Standard 1 - Off 2 - Hyper others - Standard.
ShutterMode	Query shutter mode. Response: .../ShutterMode:n . Parameter n (integer): 0 - Manual shutter 1 - Auto shutter, Lowest limit 1/8 sec 2 - Auto shutter, Lowest limit 1/15 sec 3 - Auto shutter, Lowest limit 1/30 sec 4 - Auto shutter, Lowest limit 1/60 sec 5 - Auto shutter, Lowest limit 1/125 sec others - Auto shutter, Lowest limit 1/8 sec.
ShutterPos	Not supported by FujiSxCamera driver.

Command	Description
ShutterSpeed	Query shutter speed. Response: .../ShutterSpeed:n. Parameter n (integer): 1 - 1 2 - 1/1.3 3 - 1/1.6 4 - 1/2 5 - 1/2.5 6 - 1/3 7 - 1/4 8 - 1/5 9 - 1/6 10 - 1/8 11 - 1/10 12 - 1/13 13 - 1/15 14 - 1/20 15 - 1/25 16 - 1/30 17 - 1/40 18 - 1/50 19 - 1/60 20 - 1/80 21 - 1/100 22 - 1/120 23 - 1/125 24 - 1/160 25 - 1/200 26 - 1/250 27 - 1/320 28 - 1/400 29 - 1/500 30 - 1/640 31 - 1/800 32 - 1/1000 33 - 1/1250 34 - 1/1600 35 - 1/2000 36 - 1/2500 37 - 1/3200 38 - 1/4000 39 - 1/5000 40 - 1/6400 41 - 1/8000 42 - 1/10000 43 - 1/12800 44 - 1/16000 45 - 1/20000

Command	Description
	46 - 1/32000 others - 1/30.
ExposureCompensationMode	Not supported by FujiSxCamera driver.
ExposureCompensationPos	Not supported by FujiSxCamera driver.
DefogMode	Query defog mode. Response: .../DefogMode:n . Parameter n (integer): 0 - Off 1 - level 1 2 - level 2 3 - level 3 others - Off.
DehazeMode	Query dehaze mode (heat haze reduction). Response: .../DehazeMode:n . Parameter n (integer): 0 - Off 1 - level 1 2 - level 2 3 - level 3 others - Off.
NoiseReductionMode	Query noise reduction mode. Response: .../NoiseReductionMode:n . Parameter n (integer): 1 - Weak 2 - Middle 3 - Strong 0 - Middle.
BlackAndWhiteFilterMode	Not supported by FujiSxCamera driver.
FilterMode	Query filter mode. Response: .../FilterMode:n . Parameter n (integer): 0 - Visible light 1 - 950 nm 2 - 940 nm 3 - 850 nm 4 - 808 nm others - visible light.
NucMode	Not supported by FujiSxCamera driver.
AutoNucIntervalSec	Not supported by FujiSxCamera driver.
AutoNucIntervalMin	Not supported by FujiSxCamera driver.
DdeMode	Not supported by FujiSxCamera driver.
DdeLevel	Not supported by FujiSxCamera driver.
Temperature	Not supported by FujiSxCamera driver.

Command	Description
AlcGate	Not supported by FujiSxCamera driver.
Sensitivity	Not supported by FujiSxCamera driver.
ChangingMode	Not supported by FujiSxCamera driver.
ChangingLevel	Query day to night changes threshold. Response: .../ChangingLevel:n . Parameter n (integer): 0-255 level.
ChromaLevel	Not supported by FujiSxCamera driver.
Detail	Not supported by FujiSxCamera driver.
Profile	Query camera preset profile. Response: .../Profile:n . Parameter n (integer): 0 to 4 (see Profile:n command for profile descriptions).
IsConnected	Query connection status. Response: .../IsConnected:n . Parameter n (integer): 0 - no responses from camera, 1 - connected. Shows if we have a response from the camera.
IsOpen	Query open status. Response: .../IsOpen:n . Parameter n (integer): 1 - open, 0 - not open. Open status shows if the camera controller is initialized or not but does not show if the camera controller has communication with camera hardware.
Custom1	Query night to day changes threshold. Response: .../Custom1:n . Parameter n (integer): 0-255 level.
Custom2	Query color temperature on white balance. WhiteBalanceMode should be set to 6 - ColorTemperature(Set the color temperature). Response: .../Custom2:n . Parameter n (integer): 1 - 3000K 2 - 5000K 3 - 9000K.
Custom3	Query antialiasing. Response: .../Custom3:n . Parameter n (integer): 0 - off 1 - on.
AgcRoiX0	Not supported by FujiSxCamera driver.
AgcRoiY0	Not supported by FujiSxCamera driver.
AgcRoiX1	Not supported by FujiSxCamera driver.
AgcRoiY1	Not supported by FujiSxCamera driver.
Type	Query camera type. Response: .../Type:n . Parameter n (string): FujiSx for Fuji Sx cameras.

Some example messages:

[client -> system] **ID:18/Command/Camera2/Camera/Sensitivity:1** - Set sensitivity.

[system -> client] **ID:18/Ack** - command accepted.

[client -> system] **ID:19/Command/Camera2/Camera/DehazeMode:1** - Set dehaze mode.

[system -> client] **ID:19/Ack** - command accepted.

[client -> system] **ID:21/Query/Camera2/Camera/IsConnected** - Query connection status.

[system -> client] **ID:21/Reply/Camera2/Camera/IsConnected:1** - Connected.