



MAX78000 Secure Bootloader In-Application Programming with Python® User Guide

UGxxxx, Rev 2; 5/21

Abstract

This user guide details how update the end-user software application in the MAX78000 through the in-application programming, plus how to program the host code into the MAX32630FTHR board. Details on the MAX78000 secure bootloader can be found in the **MAX78000 Secure Bootloader User Guide**.

Python is a registered trademark of the Python Software Foundation.

Table of Contents

Introduction	3
System Requirements	4
Maxim Toolchain Installation	4
Environment Setup	4
Programming the MAX32630FTHR	5
Hardware Setup	7
In-Application Programming	8
Installing Microsoft Visual C++ Runtime	8
Installing OpenSSL Library	9
Compiling the Hello World Example with the Make Command	13
Generating AES Keys.....	13
Converting the .bin File to the .msbl File Format.....	14
Programming Keys to the Bootloader	14
MSBL File Programming	14
Locking the SWD Interface	16
Unlocking the SWD Interface.....	16
Revision History	17

List of Figures

Figure 1. The MAX32630FTHR and MAX32625PICO board connection.....	5
Figure 2. Serial port list.	5
Figure 3. CDC device driver warning.....	5
Figure 4. MAX32630FTHR host reset button.	6
Figure 5. MAX32630FTHR host blinking LED.	6
Figure 6. Pin Connection between the MAX32630FTHR and MAX78000FTHR	7
Figure 7. Downloading firmware with the download_fw_over_host.exe	15
Figure 8. Bootloader Configuration File.....	16

List of Tables

Table 1. Pin Connection between the MAX32630FTHR and MAX78000FTHR	7
---	---

Introduction

This application note provides the instructions to program example host code into the MAX32630FTHR development platform.

The document also gives details related to hardware setup and application programming by using the MAX78000 bootloader and example host code.

Note that the screenshots may differ according to the software versions, but the steps will be same.

System Requirements

To program the MAX78000 bootloader code into the MAX78000FTHR, the minimum requirements are as follows:

- Windows® PC
 - Windows 10, Windows 7
 - OpenSSL
 - Maxim Toolchain Software (more information, including download and installation instructions, is in this document)
- MAX78000FTHR and micro-USB cable
- MAX32630FTHR and micro-USB cable
- MAX32625PICO evaluation kit (EV kit) and micro-USB cable
- Test wires to connect the MAX78000FTHR and MAX32630FTHR

Maxim Toolchain Installation

To install the Maxim Toolchain to your PC, use the following steps:

1. Download the Maxim SDK [here](#).
2. After downloading is complete, double-click **MaximMicrosSDK.exe** and use the default settings and select **Next** until finished.

Environment Setup

Copy the release package content to your PC under the C:\MAX78000_MSBL folder.

Programming the MAX32630FTHR

To program example host code into the MAX32630FTHR, use the following steps:

1. Connect the grey 10-pin connector to the MAX32630FTHR and the MAX32625PICO board.
2. Connect the micro-USB cable to the MAX32625PICO and the PC.
3. Connect the micro-USB cable to the MAX32630FTHR and the PC.



Figure 1. The MAX32630FTHR and MAX32625PICO board connection.

4. Wait a few minutes for the Windows driver to install, then verify that it is installed correctly.
 - a. In the Windows 10 search box, type **Control Panel** (or for Windows 7, click **Control Panel** on the right side of the **Start Menu**). Either click **Hardware and Sound**, then **Device Manager**, or type **Device Manager** in the search box in the upper right.
 - b. If the drivers have correctly installed, you should see one port listed as **mbed Serial Port** for the MAX32625PICO. Note the COM port number for the USB serial device.




Figure 2. Serial port list.

- c. If you see the following, then you will need to install the correct Windows driver:




Figure 3. CDC device driver warning.

- d. Download the Arm Mbed® Windows serial port driver [here](#).
 - e. For Windows 10, run `mbedWinSerial_16466.exe` by double-clicking it.
5. Drag and drop `max32630fthr-host-vx.x.x.bin` into the correct DAPLINK drive.

6. Press the reset button on the MAX32630FTHR, as shown in **Figure 4**.



Figure 4. MAX32630FTHR host reset button.

7. Verify that the LED on the MAX32630FTHR is blinking, as shown in **Figure 5**.



Figure 5. MAX32630FTHR host blinking LED.

Hardware Setup

Connect the MAX32630FTHR and MAX78000 with test wires according to **Table 1**. Pin connection between MAX32630FTHR and MAX78000FTHR is given in **Figure 6**.

Table 1. Pin Connection between the MAX32630FTHR and MAX78000FTHR

PIN FUNCTION	MAX78000FTHR	MAX32630FTHR
EBL GPIO	P0.5	P5.4
I2C1_SCL	P0.16	P3.5 + 4.7K pullup
I2C1_SDA	P0.17	P3.4 + 4.7K pullup
RST	RSTN	P5.6
GND	GND	GND





Figure 6. Pin Connection between the MAX32630FTHR and MAX78000FTHR

In-Application Programming

Installing Microsoft Visual C++ Runtime

To download and install Microsoft Visual C++ Runtime, use the following steps:

1. Visit the download link **here** and click Download button.



Visual C++ Redistributable Packages for Visual Studio 2013

Important! Selecting a language below will dynamically change the complete page content to that language.

Select Language:

English

Download

2. Select vcredist_x86.exe and continue by selecting Next.

Choose the download you want

<input type="checkbox"/> File Name	Size
<input type="checkbox"/> vcredist_arm.exe	1.4 MB
<input type="checkbox"/> vcredist_x64.exe	6.9 MB
<input checked="" type="checkbox"/> vcredist_x86.exe	6.2 MB


Download Summary:
KBMBGB

1. vcredist_x86.exe


Total Size: 6.2 MB

Next

3. Download and run the setup file.
4. Read and click if you agree the terms. Then select Install.



5. Close the installation application.



Installing OpenSSL Library


To download and install OpenSSL Library, use the following steps:

1. Visit OpenSSL downloads page [here](#).
2. Select **Win32 OpenSSL v1.1.10L Light** package.


Download Win32/Win64 OpenSSL today using the links below!

File	Type	Description
Win64 OpenSSL v1.1.1f Light EXE MSI (experimental)	3MB Installer	Installs the most commonly used build of OpenSSL and is subject to local and state laws. More information can be found in the legal agreement of the project.
Win64 OpenSSL v1.1.1f EXE MSI (experimental)	63MB Installer	Installs Win64 OpenSSL v1.1.1f (subject to local and state laws. More information can be found in the legal agreement of the project).
Win32 OpenSSL v1.1.1f Light EXE MSI (experimental)	3MB Installer	Installs the most commonly used build of OpenSSL and is subject to local and state laws. More information can be found in the legal agreement of the project.
Win32 OpenSSL v1.1.1f EXE MSI (experimental)	54MB Installer	Installs Win32 OpenSSL v1.1.1f (subject to local and state laws. More information can be found in the legal agreement of the project).
Win64 OpenSSL v1.1.0L Light EXE MSI (experimental)	3MB Installer	Installs the most commonly used build of OpenSSL and is subject to local and state laws. More information can be found in the legal agreement of the project.
Win64 OpenSSL v1.1.0L EXE MSI (experimental)	37MB Installer	Installs Win64 OpenSSL v1.1.0L (subject to local and state laws. More information can be found in the legal agreement of the project).
Win32 OpenSSL v1.1.0L Light EXE MSI (experimental)	3MB Installer	Installs the most commonly used build of OpenSSL and is subject to local and state laws. More information can be found in the legal agreement of the project.
Win32 OpenSSL v1.1.0L EXE MSI (experimental)	30MB Installer	Installs Win32 OpenSSL v1.1.0L (subject to local and state laws. More information can be found in the legal agreement of the project).
Win64 OpenSSL v1.0.2u Light EXE MSI (experimental)	3MB Installer	Installs the most commonly used build of OpenSSL and is subject to local and state laws. More information can be found in the legal agreement of the project.
Win64 OpenSSL v1.0.2u EXE MSI (experimental)	23MB Installer	Installs Win64 OpenSSL v1.0.2u (subject to local and state laws. More information can be found in the legal agreement of the project).
Win32 OpenSSL v1.0.2u Light EXE MSI (experimental)	2MB Installer	Installs the most commonly used build of OpenSSL and is subject to local and state laws. More information can be found in the legal agreement of the project.
Win32 OpenSSL v1.0.2u EXE MSI (experimental)	20MB Installer	Installs Win32 OpenSSL v1.0.2u (subject to local and state laws. More information can be found in the legal agreement of the project).


- Download and run the installer.
- Read and click if you agree the terms. Then select Next.




- Leave the destination location default and click Next.




6. Leave **"The Windows system directory"** selected and click Next.



7. Click install.



8. When the installation is completed, click finish.



Compiling the Hello World Example with the Make Command

To compile the Hello World with the make command, use the following steps:

1. Navigate to the correct directory consisting Hello World Example in the **MinGW** window with the following command:

```
cd " C:\MAX78000_MSBL \MAX78000_Hello_World"
```

2. Enter the following command in the **MinGW** window and wait several minutes for the command to complete:

```
make
```

3. After successful compiling, the Hello world binary image *max78000.bin* will be in the "C:\MAX78000_MSBL \MAX78000_Hello_World\build" directory.

Be sure that the correct linker file is used for generating the .bin file. A sample linker file, max78000_with_bl.ld, can be found under the Hello_World example folder.

4. If you want to rebuild, then enter these commands respectively:

```
make clean
```

```
make
```

Generating AES Keys

Generated AES keys can be used for encrypting bin files during msbl file generation and loading to bootloader. Customer can use their own method for generating keys, but file format should be similar to the sample max78000_sample_key.txt file.

1. Navigate to the correct directory consisting key generation script in the **MinGW** window with the following command:

```
cd "C:\MAX78000_MSBL"
```

2. Enter the following command in the **MinGW** window to generate a key:

```
./generate_key_vX.sh
```

3. Rename generated key.txt as *max78000_key.txt* file for using msbl file generation or bootloader key programming.

Converting the .bin File to the .msbl File Format

The .msbl file is generated automatically by using a .msbl generator.

1. Navigate to the correct directory consisting msbl generator in the **MinGW** window with the following command:

```
cd "C:\MAX78000_MSBL"
```

2. Enter the following command in the **MinGW** window to convert the .bin application to a .msbl file:

```
./msblGenWin32.exe MAX78000_Hello_World.bin MAX78000 8192  
max78000_key.txt
```

3. Rename generated "max78000.msbl" file as "Hello_World.msbl"

Programming Keys to the Bootloader

To program the keys to the MAX78000 by using the MAX78000 bootloader, use the following steps:

At the command prompt or in the PowerShell window, enter the following commands, replacing COMxx with the correct USB serial device COM port found in section Programming the MAX32630FTHR at step 4.b.

```
download_fw_over_host.exe -k max78000_key.txt -p COMXX
```

Note that the shared keys are sample one and they should be updated accordingly before programming keys.

MSBL File Programming

To flash the application to the MAX78000 by using the MAX78000 bootloader, use the following steps:

At the command prompt or in the PowerShell window, enter the following commands, replacing COMxx with the correct USB serial device COM port found in section Programming the MAX32630FTHR at step 4.b.

```
download_fw_over_host.exe -f MAX78000_Hello_World.msbl -p COMXX
```

[illegible]

Figure 7. Downloading firmware with the `download_fw_over_host.exe`

9. The application has now been flashed to the chip. For advanced usage of flasher script, refer to the *Firmware_downloader_usage.txt* file.

Locking the SWD Interface

To lock the SWD Interface, use the following steps:

1. At file max78000_bl_config.cfg: Change the swd_lock value to 1 and save the file.

```
[BootConfig]
# Enter Bootloader Pin Check 0: Disable, 1: Enable
enter_bl_check = 0
# Enter Bootloader Pin [0,13]
ebl_pin = 5
# Enter Bootloader Pin Polarity 0: active low, 1: active high
ebl_pol = 0
# Valid Mark Check 0: Disable, 1: Enable
valid_mark_check = 1
# UART Interface Enable 0: Disable, 1: Enable
uart_enable = 1
# I2C Interface Enable 0: Disable, 1: Enable
i2c_enable = 1
# SPI Interface Enable 0: Disable, 1: Enable
spi_enable = 1
# I2C Slave Addr Valid Between 8 - 119
i2c_addr = 85
# CRC Check 0: Disable, 1: Enable
crc_check = 0
# Timeout to exit bootloader
ebl_timeout = 0
# Timeout mode 0 : 'Jump immediately', 1 : 'Wait for programmable delay', 2 : 'remain in bootloader until receive exit command'
exit_bl_mode = 1
# Set SWD Lock
swd_lock = 1
```

Figure 8. Bootloader Configuration File.

2. Run following command:
`configure_bootloader.exe -f max78000_bl_config.cfg -p COMXX`
3. Disconnect the micro-USB cable.
4. Reconnect the micro-USB cable. SWD is locked now.

Unlocking the SWD Interface

To unlock the SWD Interface, use the following steps:

1. At file max78000_bl_config.cfg: Change the swd_lock value to 0 and save the file.
2. Run the following command:
`./configure_bootloader.exe -f max78000_bl_config.cfg -p COMXX`
3. Disconnect the micro-USB cable.
4. Reconnect the micro-USB cable Now key and application are erased, SWD is unlocked, so a new key can be loaded.

Note that SWD can be locked and unlocked up to 4 times.

Revision History

REVISION NUMBER	REVISION DATE	DESCRIPTION	PAGES CHANGED
0	3/21	Initial release	—
1	3/21	<ul style="list-style-type: none">• Programming the MAX78000 with the Bootloader Firmware section added• Pin Connection between the MAX32630FTHR and MAX78000FTHR Figure added• Programming Keys to the Bootloader Section added	5, 8, 16
2	5/21	<ul style="list-style-type: none">• SWD Lock and Unlock Sections are Added	16,17

©2020 by Maxim Integrated Products, Inc. All rights reserved. Information in this publication concerning the devices, applications, or technology described is intended to suggest possible uses and may be superseded. MAXIM INTEGRATED PRODUCTS, INC. DOES NOT ASSUME LIABILITY FOR OR PROVIDE A REPRESENTATION OF ACCURACY OF THE INFORMATION, DEVICES, OR TECHNOLOGY DESCRIBED IN THIS DOCUMENT. MAXIM ALSO DOES NOT ASSUME LIABILITY FOR INTELLECTUAL PROPERTY INFRINGEMENT RELATED IN ANY MANNER TO USE OF INFORMATION, DEVICES, OR TECHNOLOGY DESCRIBED HEREIN OR OTHERWISE. The information contained within this document has been verified according to the general principles of electrical and mechanical engineering or registered trademarks of Maxim Integrated Products, Inc. All other product or service names are the property of their respective owners.