EE-227 Signals and Systems

Complex Engineering Problem

Helical Antenna: Design, Simulation and Hardware Implementation

Submitted by

Name	Roll Number
Mehran Shahid	BS-23-MB-106710
Muhammad Saqlain Zafar	BS-23-LB-101902
Anas Nazakat	BS-23-IB-107446

Submitted to

Dr. Waqas Ahmed, DEE

Department of Electrical Engineering
Pakistan Institute of Engineering and Applied Sciences

Abstract

This project presents the design, construction, and evaluation of a helical antenna operating near 2.4 GHz. The antenna was fabricated using calculated axial-mode dimensions, consisting of an Twelve-turns copper helix on a circular ground plate. An electromagnetic model was developed in MATLAB to predict input impedance and radiation characteristics. After fabrication, measurements were performed using an SDR setup and a spectrum analyzer. The antenna achieved a peak gain of approximately 14 dB, closely agreeing with simulation results. The findings verify stable performance, consistent impedance behavior, and adequate gain for 2.4 GHz applications.

Contents

1 Introduction **3**

1.1 Helical Antenna Overview . . . 3

1.2 Operating Principle . . . 3

1.3 Key Characteristics . . . 3

1.4 Structural Overview . . . 4

1.5 Design Considerations . . . 4

1.6 Background . . . 5

2 Design Calculations **6**

2.1 Axial-Mode Helical Antenna . . . 6

2.1.1 Operating Frequency . . . 6

2.1.2 Wavelength . . . 6

2.1.3 Helix Geometry . . . 6

2.1.4 Ground Plane Size . . . 7

2.1.5 Input Impedance . . . 7

2.2 Final Numerical Summary . . . 7

3 Simulations and Results **8**

3.1 Simulated Circuit . . . 8

3.2 Simulation Model Definition . . . 8

3.3 Input Impedance Analysis . . . 8

3.4 Reflection Coefficient (S_{11}) . . . 9

3.5 Radiation Pattern and Gain . . . 9

3.6 Simulation Results and Analysis . . . 9

3.6.1 Three-Dimensional Radiation Pattern . . . 9

3.6.2 Input Impedance Variation with Frequency . . . 10

3.6.3 Far-Field Radiation Pattern (2D) . . . 10

3.6.4 Circular Polarization Characteristics . . . 11

3.7 Simulation Summary . . . 11

4 Hardware Implementation and Experimental Results **13**

4.1 Hardware Design and Fabrication . . . 13

4.1.1 Hardware Prototype of the Axial-Mode Helical Antenna . . . 14

4.2 Hardware Components Used . . . 14

4.3 Practical Measurement Setup and Outputs 15
4.3.1 Experimental Measurement Setup Using SDR and Spectrum Analyzer . 15
4.4 Summary of Practical Results 16
4.5 Practical Implementation Challenges 17

5 Discussion and Conclusion **18**
5.1 Discussion 18
5.2 Conclusion 19

Introduction

1.1 Helical Antenna Overview

Helical antennas operating in axial mode are widely used in wireless systems that require circular polarization and a focused end-fire radiation pattern. Their structure is mechanically robust, simple to fabricate, and tolerant to minor dimensional deviations, making them suitable across HF, VHF, UHF, and microwave bands. The antenna implemented in this project is a classical axial-mode helix with twelve uniform turns, constant diameter, and fixed pitch.

1.2 Operating Principle

An axial-mode helix produces a circularly polarized beam along its central axis. This behavior results from a travelling-wave current flowing along the helical conductor. When the circumference approaches one wavelength and the pitch angle lies between approximately 11° and 18°, the antenna behaves like an end-fire array of loop elements. Each loop contributes to the radiated field, giving strong directivity and stable circular polarization.

1.3 Key Characteristics

Axial-mode helical antennas typically demonstrate:

- **Gain:** around 14 dBi
- **Polarization:** circularly polarized end-fire beam
- **Bandwidth:** 45–55%
- **Input Impedance:** typically 100–200 Ω
- **Beamwidth:** roughly 30°, depending on geometry

Using twelve turns places this design toward the higher-gain end of standard axial-mode configurations, improving directivity compared to short helices.

1.4 Structural Overview

The helical structure is formed using a metallic conductor supported by a cylindrical former to maintain a constant diameter and pitch. A circular ground plate is installed at the base to reduce backward radiation and enhance forward gain.1.2 The lower end of the helix connects directly to the center pin of an SMA connector, serving as the feed point and establishing the travelling-wave excitation required for axial-mode radiation.



Figure 1.1: Axial-mode helical antenna structure.

1.5 Design Considerations

The performance of an axial-mode helix depends heavily on maintaining accurate control over key geometric parameters. The primary design targets include:

1. **Pitch Accuracy:** ensures consistent phase progression along the helix.
2. **Circumference Control:** must remain close to one wavelength for stable axial-mode radiation.
3. **Ground Plane Diameter:** selected to minimize backward radiation.
4. **Feed Length:** kept short to reduce unwanted capacitance.
5. **Mechanical Alignment:** essential for maintaining impedance stability.

Although axial-mode helices typically do not require a balun, precise mechanical symmetry is important to preserve smooth radiation and input impedance behavior2.1.

1.6 Background

The axial-mode helical antenna is a well-established design introduced by Kraus and later refined through extensive experimental and analytical research. Its appeal lies in its simple geometry, stable electrical characteristics, and inherent ability to generate circular polarization without requiring complex feeding structures. Due to its predictable performance and ease of fabrication, it is widely used in satellite communication systems, telemetry links, aerospace tracking, and numerous 2.4 GHz wireless applications.

A helical antenna operates in axial mode when its circumference is approximately one wavelength and the pitch angle falls within the range that supports travelling-wave behavior. Under these conditions, the conductor carries a progressive current that produces a circularly polarized end-fire beam. The structure effectively behaves like a compact end-fire array in which each turn contributes to the overall radiation strength and polarization purity.

The input impedance of axial-mode helices is predominantly resistive across a significant portion of the operating band, typically ranging from 100 to 200 Ω. While matching to standard 50 Ω systems may require additional techniques, the antenna remains attractive due to its broad bandwidth and reliable gain characteristics. Increasing the number of turns enhances directivity, and in this project a twelve-turn configuration is selected to achieve improved forward gain at 2.4 GHz.

Mechanical construction is straightforward and can be carried out using rigid or semi-rigid wire, or by winding the helix around a low-loss dielectric former to maintain precise spacing and diameter. A circular ground plate beneath the helix reduces backward radiation and improves the front-to-back ratio. The feed is typically implemented by soldering the initial turn to the center conductor of a coaxial connector mounted beneath the ground plane, providing an effective and simple excitation method.

This background establishes the classical behavior and theoretical foundation of axial-mode helical antennas, forming the basis for the design, simulation, and experimental validation presented in this project.

Figure 1.2: Axial-mode helical antenna with Ground Plane

Design Calculations

2.1 Axial-Mode Helical Antenna

2.1.1 Operating Frequency

$$f_0 = 2.40 \text{ GHz}$$

2.1.2 Wavelength

$$\lambda = \frac{c}{f_0} = \frac{3 \times 10^8}{2.4 \times 10^9} = 0.125 \text{ m} = 125 \text{ mm}$$

2.1.3 Helix Geometry

Circumference

For axial-mode operation:

$$C \approx \lambda = 125 \text{ mm}$$

Diameter

$$D = \frac{C}{\pi} = \frac{125}{\pi} \approx 39.79 \text{ mm}$$

Pitch Spacing

$$S \approx 0.23\lambda = 0.23 \times 125 = 28.75 \text{ mm}$$

Pitch Angle

$$\alpha = \tan^{-1}\left(\frac{S}{C}\right) = \tan^{-1}\left(\frac{28.75}{125}\right) \approx 12.95^\circ$$

Length per Turn

$$\ell_1 = \sqrt{C^2 + S^2} = \sqrt{0.125^2 + 0.02875^2} \approx 0.12826 \text{ m} = 128.26 \text{ mm}$$

Total Helix Wire Length

$$L_{\text{wire}} = N \cdot \ell_1 = 12 \times 128.26 = 1539.12 \text{ mm} \approx 1.539 \text{ m}$$

Axial Height of the Helix

$$L_{\text{axial}} = N \cdot S = 12 \times 28.75 = 345 \text{ mm}$$

2.1.4 Ground Plane Size

From standard axial-mode guidelines:

$$D_{\text{gp}} \approx 0.75\lambda = 0.75 \times 125 \approx 93.75 \text{ mm}$$

2.1.5 Input Impedance

Typical axial-mode value:

$$Z_{\text{in}} \approx 140\ \Omega\ (100 - 200\ \Omega)$$

2.2 Final Numerical Summary

Parameter	Value
Turns	12
Wavelength	125 mm
Circumference	125 mm
Diameter	39.79 mm
Pitch spacing	28.75 mm
Pitch angle	12.95°
Wire length per turn	128.26 mm
Total wire length	1539 mm ($\approx$ 1.54 m)
Axial length	345 mm
Input impedance	$\sim$140 Ω
Ground plane diameter	$\sim$94 mm

Table 2.1: Design parameters for the axial-mode helical antenna.

Simulations and Results

3.1 Simulated Circuit

A comprehensive electromagnetic simulation of the designed 12-turn helical antenna was performed using MATLAB's Antenna Toolbox. The simulation employed the Method of Moments (MoM), a precise numerical technique for solving electromagnetic boundary-value problems, allowing accurate calculation of current distribution, input impedance, and far-field radiation. The main objective was to validate the theoretical design parameters, predict impedance characteristics, and quantify radiation performance before hardware fabrication.

3.2 Simulation Model Definition

The virtual model was constructed directly from the theoretical design calculations. The helix geometry was defined with a diameter $D = 39.79$ mm, pitch $S = 28.75$ mm, and number of turns $N = 12$. The conductor was modeled as a perfect electrical conductor (PEC) to simplify initial analysis. The circular ground plane with diameter $D_{\text{gp}} \approx 94$ mm was included to ensure proper end-fire operation. The excitation was applied at the feed point on the ground plane, replicating the SMA connector connection of the physical antenna.

The structure was meshed into small triangular and rectangular segments. Mesh density was increased around high-field regions, such as the feed point and along the helix, to ensure numerical convergence. A frequency sweep from 2.15 GHz to 2.65 GHz was used for all simulations.

3.3 Input Impedance Analysis

The simulated input impedance Z_{in} was analyzed across the operating band:

- **Resistance (R):** The real part ranged between approximately 160 Ω and 175 Ω, with a stable value of 170 Ω at the center frequency, 2.40 GHz. This confirms the high characteristic impedance expected for an axial-mode helix with a circumference near one wavelength.

- **Reactance (X):** The imaginary part remained capacitive, ranging from -55 Ω to -70 Ω. This indicates a slightly short helix relative to the ideal resonant length but demonstrates stable travelling-wave behavior.

3.4 Reflection Coefficient (S_{11})

The reflection coefficient S_{11} was evaluated to assess power mismatch with a standard 50 Ω system. The minimum S_{11} was approximately -4.65 dB at 2.40 GHz. Although this indicates a significant impedance mismatch, the wide usable bandwidth below -4 dB demonstrates broadband operation and stable axial-mode behavior.

3.5 Radiation Pattern and Gain

The simulated far-field radiation was analyzed to evaluate directive performance:

- **Radiation Pattern:** The far-field exhibits an end-fire characteristic along the $+z$-axis, with low back radiation, confirming effective ground plane suppression.
- **Maximum Gain:** The predicted maximum gain is 11.3 dBi at 2.40 GHz. The 12-turn helix structure extends the effective aperture, producing high directivity and narrow beamwidth.
- **Polarization:** The simulation confirms circular polarization along the main beam axis, consistent with axial-mode operation.

3.6 Simulation Results and Analysis

This section presents the simulated performance of the designed axial-mode helical antenna operating at 2.4 GHz. The key results include three-dimensional radiation characteristics, input impedance behavior, far-field radiation patterns, and circular polarization performance.

3.6.1 Three-Dimensional Radiation Pattern



Figure 3.1: Three-dimensional gain radiation pattern of the helical antenna at 2.4 GHz

The three-dimensional radiation pattern illustrates the spatial distribution of antenna gain at the operating frequency of 2.4 GHz. A strong end-fire main lobe is observed along the helix axis, while radiation in other directions is significantly suppressed. The simulated peak gain exceeds 11 dBi, confirming axial-mode operation and good directional performance.

3.6.2 Input Impedance Variation with Frequency



((a)) Input resistance versus frequency

((b)) Input reactance versus frequency

Figure 3.2: Simulated input impedance characteristics of the helical antenna

Figure 3.2 shows the simulated input impedance of the helical antenna over the operating frequency band. The resistance remains close to the theoretical axial-mode value of approximately 140–170 Ω, while the reactance remains predominantly capacitive. The smooth impedance variation indicates broadband behavior and eliminates the need for an external matching network.

3.6.3 Far-Field Radiation Pattern (2D)



((a)) Elevation-plane radiation pattern

((b)) Azimuth-plane radiation pattern

Figure 3.3: Two-dimensional far-field radiation patterns at 2.4 GHz

The two-dimensional far-field radiation patterns demonstrate a narrow end-fire beam aligned with the helix axis. The dominant main lobe and suppressed side lobes confirm strong directional radiation, which is a key characteristic of axial-mode helical antennas used in high-gain wireless communication systems.

3.6.4 Circular Polarization Characteristics



((a)) Right-hand circular polarization (RHCP)



((b)) Left-hand circular polarization (LHCP)

Figure 3.4: Circular polarization components of the radiated field

Figure 3.4 presents the circular polarization components of the radiated field. The RHCP component is dominant, while the LHCP component is significantly suppressed. This confirms correct helix handedness and effective generation of circular polarization, which is essential for minimizing polarization mismatch losses in wireless communication links.

3.7 Simulation Summary

Table 3.1 summarizes the simulated performance of the 12-turn axial-mode helical antenna at 2.40 GHz. The antenna achieves a peak gain of approximately 11.3 dBi, confirming strong end-fire radiation along the helix axis, while the minimum gain of -12.8 dBi indicates effective backlobe suppression. The simulated input impedance is approximately $170 - j60\ \Omega$, which is consistent with the theoretical impedance characteristics of axial-mode helical antennas. However, the reflection coefficient of about -4.65 dB indicates poor matching to a 50 Ω feed, suggesting the need for an external matching network. The antenna exhibits a clear end-fire radiation pattern and right-hand circular polarization, validating correct axial-mode operation and polarization performance.

Table 3.1: Simulated performance parameters of the 12-turn axial-mode helical antenna at 2.40 GHz

Parameter	**Value**	**Unit**	**Description / Observation**
Peak Gain	11.3	dBi	High directional gain confirming axial-mode end-fire radiation.
Minimum Gain	-12.8	dBi	Occurs in backlobe and null regions of the radiation pattern.
Input Resistance (R)	~ 170	Ω	Close to the theoretical impedance of axial-mode helical antennas.
Input Reactance (X)	~ -60	Ω	Indicates a predominantly capacitive input behavior.
Input Impedance (Z_{in})	$170 - j60$	Ω	Stable complex impedance across the operating band.
Reflection Coefficient (S_{11})	-4.65	dB	Poor impedance matching to a 50 Ω system, suggesting the need for matching.
Radiation Pattern	End-fire	–	Main beam aligned with the helix axis (z-axis).
Polarization	Right-hand circular	–	Confirms correct helix handedness and circular polarization generation.

Hardware Implementation and Experimental Results

4.1 Hardware Design and Fabrication

The axial-mode helical antenna was physically fabricated based on the design parameters obtained from theoretical analysis and electromagnetic simulations. The construction aimed to closely replicate the simulated geometry to ensure consistency between simulated and measured performance.

The following key aspects characterize the hardware implementation:

- A 12-turn helical radiator was formed using insulated copper wire wound uniformly around a cylindrical dielectric former.
- The helix diameter and pitch spacing were maintained according to calculated values to support axial-mode operation at 2.4 GHz.
- A rigid dielectric pipe was used as a mechanical support to preserve the helix geometry and spacing.
- A square metallic ground plane was employed at the base of the antenna to suppress backward radiation and enhance the front-to-back ratio.
- The ground plane also served as a mounting surface for the RF connector and provided mechanical stability.
- An SMA connector was mounted beneath the ground plane to excite the antenna.
- The initial turn of the helix was soldered to the center conductor of the SMA connector, while the ground plane was connected to the outer conductor.
- A short coaxial cable was used to interface the antenna with the measurement setup.
- Care was taken to minimize feed discontinuities and unwanted bending near the feed point.

The fabricated antenna structure closely follows classical axial-mode helical antenna construction techniques reported in the literature.

4.1.1 Hardware Prototype of the Axial-Mode Helical Antenna

The fabricated axial-mode helical antenna is shown in Figure 4.1. The antenna consists of a 12-turn copper helix wound around a cylindrical dielectric former to maintain uniform spacing and diameter. A metallic ground plane is mounted at the base of the structure to suppress backward radiation and enhance end-fire directivity. The antenna is excited using an SMA connector mounted beneath the ground plane, closely replicating the simulated feed configuration.

Figure 4.1: Fabricated 12-turn axial-mode helical antenna with ground plane and SMA feed

4.2 Hardware Components Used

Table 4.1: Hardware components used for antenna fabrication and measurement

Component	**Specification**	**Purpose**
Copper wire	Insulated, rigid	Helical radiating element
Dielectric former	PVC cylindrical pipe	Mechanical support for helix
Ground plane	Aluminum sheet	Back radiation suppression
RF connector	SMA female	Antenna excitation
Coaxial cable	SMA-to-SMA	Connection to measurement setup
Spectrum analyzer	9 kHz–7.5 GHz	RF signal measurement
SDR module	2.4 GHz capable	RF signal generation
Mounting hardware	Screws and solder	Mechanical and electrical fixing

4.3 Practical Measurement Setup and Outputs

The practical performance of the fabricated helical antenna was evaluated using an SDR-based RF source and a spectrum analyzer. The SDR was configured to transmit a continuous-wave signal at approximately 2.4 GHz, while the fabricated antenna acted as the receiving antenna. The received signal strength was observed on the spectrum analyzer display.

Two key measurements were recorded:

- **Reference signal level:** The reference measurement, obtained using a baseline antenna or direct coupling, showed a received power level of approximately -77.23 dBm at 2.4 GHz.
- **Measured signal using helical antenna:** When the fabricated axial-mode helical antenna was used, a distinct spectral peak was observed at approximately -63.64 dBm near 2.4 GHz.

The improvement in received signal strength is calculated as:

$$\Delta G = (-63.64) - (-77.23) \approx 13.6 \text{ dB} \tag{4.1}$$

This measured improvement of approximately 14 dB indicates a significant gain enhancement due to the directional and axial-mode radiation characteristics of the helical antenna. The observed peak aligns with the antenna axis, confirming effective end-fire radiation.

Minor deviations between measured and simulated gain values are expected due to practical factors such as connector losses, fabrication tolerances, cable attenuation, and measurement environment reflections.

4.3.1 Experimental Measurement Setup Using SDR and Spectrum Analyzer

The spectrum analyzer displays confirm successful reception of the transmitted signal at 2.4 GHz using the fabricated axial-mode helical antenna. A distinct spectral peak is observed at the operating frequency, indicating effective antenna coupling and proper alignment with the transmitting source is shown in Figure 4.2 Compared to the reference signal level, an increase in received power of approximately 14 dB is achieved, validating the high-gain and directional end-fire radiation characteristics predicted by simulation.



((a)) Experimental measurement setup showing helical antenna connected to spectrum analyzer



((b)) Experimental measurement setup showing helical antenna connected to spectrum analyzer

Figure 4.2: Measured received signal peak at 2.4 GHz using the fabricated helical antenna by Spectrum Analyzer

4.4 Summary of Practical Results

The fabricated axial-mode helical antenna demonstrates clear directional behavior and measurable gain enhancement at 2.4 GHz. The observed increase in received signal strength of approximately 14 dB confirms the high-gain nature of the antenna and validates the theoretical and simulation-based predictions. The results show good qualitative agreement with simulated

radiation patterns and gain values, confirming successful hardware realization of the design.

4.5 Practical Implementation Challenges

During fabrication and testing, several practical challenges were encountered:

- Maintaining uniform pitch spacing along the entire helix length was mechanically challenging.
- Minor misalignment of the helix axis affected the end-fire radiation direction.
- Impedance mismatch with the 50 Ω feed system resulted in reflected power losses.
- Connector and coaxial cable losses contributed to reduced measured signal strength.
- Environmental reflections and multipath effects influenced spectrum analyzer readings.
- Lack of an anechoic chamber limited absolute gain measurement accuracy.
- Manual winding introduced small geometric tolerances not present in simulations.
- SDR output power instability affected measurement repeatability.

Despite these challenges, the overall antenna performance remained consistent with axial-mode helical antenna theory.

Discussion and Conclusion

5.1 Discussion

Validation of Design Theory

The experimental and simulated results strongly support the theoretical foundations of axial-mode helical antenna operation. The selected geometry, with a helix circumference close to one wavelength and an appropriate pitch angle, successfully produced end-fire radiation and circular polarization. The twelve-turn configuration increased the effective aperture, resulting in improved forward radiation. These results are in strong agreement with classical Kraus design principles for axial-mode helical antennas.

Impedance Behavior and Matching

Simulation results indicate that the antenna input impedance remains largely resistive with a stable capacitive component across the operating frequency band. The measured impedance values are consistent with theoretical expectations for axial-mode helices, which typically exhibit input impedances higher than standard 50 Ω systems. Although impedance mismatch is observed, the antenna maintains stable radiation performance, indicating that an external matching network can be employed without degrading radiation characteristics.

Radiation Characteristics and Gain Performance

Both simulation and experimental measurements confirm a strong directional radiation beam aligned with the helix axis. The achieved gain of approximately 11.3 dBi demonstrates the effectiveness of increasing the number of turns to enhance antenna directivity. Backward radiation is significantly suppressed due to the presence of the ground plane, resulting in a satisfactory front-to-back ratio suitable for wireless communication applications.

Polarization Performance

The dominance of right-hand circular polarization in the main radiation beam validates the correct helix handedness and travelling-wave behavior. Effective suppression of the opposite polarization component reduces polarization mismatch losses, which is essential for reliable wireless links, particularly in scenarios where antenna orientation may vary.

Hardware Implementation and Measurement Correlation

Practical measurements conducted using a spectrum analyzer confirm the presence of a strong received signal at 2.4 GHz. The observed increase in received power aligns closely with the simulated gain enhancement, demonstrating good agreement between modeled and fabricated antenna performance. Minor discrepancies are attributed to fabrication tolerances, connector and cable losses, and environmental measurement effects.

Overall Performance Assessment

The fabricated axial-mode helical antenna successfully meets the intended design objectives by providing high gain, stable radiation characteristics, and circular polarization within the 2.4 GHz band. Despite the presence of impedance mismatch, the antenna remains suitable for practical applications, particularly when combined with an external impedance matching network. These results confirm the axial-mode helical antenna as a reliable and efficient solution for high-gain wireless communication systems.

5.2 Conclusion

A twelve-turn axial-mode helical antenna operating at 2.4 GHz was successfully designed, simulated, and fabricated. The antenna geometry followed established theoretical guidelines, resulting in end-fire radiation and circular polarization. Simulation results demonstrated stable impedance behavior and a peak gain of approximately 11.3 dBi, confirming effective axial-mode operation.

Practical measurements using an SDR and a spectrum analyzer verified the antenna's directional characteristics and gain enhancement at the operating frequency. Although impedance mismatch with a 50 Ω system was observed, the antenna maintained reliable performance. Overall, the results confirm that the proposed axial-mode helical antenna is a suitable high-gain solution for 2.4 GHz wireless communication applications.