Processor Prototyping Lab

Midterm Report

Connor Lai

Michael Wu

Atthin Chandrashekar

October 18, 2026

1 Executive Overview

This report explores the implementation of a RISCV CPU and the performance benefits and technicalities of a pipelined design. The most basic version of a RISCV CPU completes all five stages – that being instruction fetch, intstruction decode, execute, memory, and write back – all in a single cycle to achieve a net CPI of 1, however, due to its long critcal path, its must use lower clock speeds. To improve the performance of the processor, the design is pipelined, splitting up the CPU into its respective stages, executing one stage per cycle. The pipelined design utilizes overlap between the instructions to still achieve one instruction per cycle execution in the average case while greatly reducing the clock period. While pipelining improves the overall performance of the CPU, it also introduces many hazards. For one, the CPU cannot both fetch an instruction and access data memory at the same time due to the unified memory architecture. Additionally, the processor needs to handle data hazards from having multiple unfinished instructions in flight simulaneously. Further, jumps and branches require the CPU to erase misevaulated instructions and redirect to the correct instructions.

To determine the tangible performance gain from the pipelined design, clock frequency, CPI, total execution time, and FPGA resource utilization were measured and compared between the two processors. By evaluating these metrics across different memory latencies, the effects of pipeline hazards, memory stalls, and increased clock frequency on overall performance could be analyzed. The results showed that the pipelined processor consistently outperformed the single-cycle design, reducing execution time by approximately 16–22% across all tested memory latencies. At zero memory latency, the pipelined processor achieved a maximum operating frequency of 87.63 MHz compared to 50.03 MHz for the single-cycle design, resulting in a 22.2% reduction in execution time. However, this improvement came at the cost of increased hardware complexity and FPGA resource utilization, with 61.2% more slice LUTs and 94.7% more slice registers. Overall, the results demonstrate that pipelining improves processor performance by increasing operating frequency, despite the additional cycles introduced by pipeline hazards and memory stalls.

2 Processor Design

2.1 Single Cycle

2.2 Pipelined




Figure 1: Single Cycle Block Diagram

In order to convert the single cycle CPU into a pipelined processor pipeline registers were added between stages to carry each instructions data and control information. The pipeline was split into 5 stages consisting of instruction fetch, decode, execute, memory, and writeback. The pipelined procesor introduces hazards that weren't in the single cycle so we added a hazard and forwarding unit to detect and prevent the errors. The request unit from the single cycle was removed in the pipeline as the memory register had the same functionality and keeping the request unit would add an extra pipeline stage.

2.3 Forwarding Unit

The forwarding unit manages read after write dependecies by supplying results from memory or writeback directly to execute. It checks both operands independantly and forwards the newest possible result.

2.4 Hazard Unit

The hazard unit manages control hazards, structural hazards, and specfically the load-use data hazard. On an incorrect jump or for a jump redirect the hazard unit flushes any younger instructions. When multiple stages of the pipeline have simultaneous memory requests the hazard unit stalls the instructions until the memory controller returns the access completion signals. For the load use hazard it holds the instruction fetch, and decode stages, and inserts a bubble into execute to allow the load to advance until the results are available.

2.5 Branch Prediction

In order to minimize the branch prediciton rate a direct mapped branch prediction table and branch target buffer was implemented. The branch prediction table consists of two bit saturating counter that are indexed

Text for discussing your designs

3 Results

The single-cycle and pipelined processors were evaluated using the mergesort.asm benchmark at memory latencies of 0, 2, 6, and 10 cycles. Both designs were synthesized and simulated using mapped gate timing. Maximum operating frequencies were obtained from exec_data_sweep.sh, while dynamic instruction counts and CPUCLK cycle counts were obtained from make system.sim. Only CPUCLK cycles were used for CPI and execution time calculations. FPGA resource utilization was obtained from buildutilization.rpt.

The maximum operating frequency was determined by the smaller of half the MAIN frequency and the CPUCLK frequency:

$$f_{\max} = \min\left(\frac{f_{\text{MAIN}}}{2}, f_{\text{CPUCLK}}\right)$$

Average cycles per instruction (CPI) and total execution time were calculated as:

$$\text{CPI} = \frac{N_{\text{cycles}}}{N_{\text{instructions}}} \qquad T_{\text{exec}}(\mu s) = \frac{N_{\text{cycles}}}{f_{\max}(\text{MHz})}$$

The ideal instruction latency was calculated using the clock period and the number of pipeline stages:

$$T_{\text{ideal,single}}(\text{ns}) = \frac{1000}{f_{\max}(\text{MHz})}$$

$$T_{\text{ideal,pipeline}}(\text{ns}) = \frac{5000}{f_{\max}(\text{MHz})}$$

These metrics were used to compare execution performance, memory latency sensitivity, and hardware resource requirements between the two architectures.

3.1 Single Cycle

The single-cycle processor was evaluated using the mergesort.asm benchmark at memory latencies of 0, 2, 6, and 10 cycles. Maximum operating frequency was determined from synthesis timing reports using $f_{\max} = \min(f_{\text{MAIN}}/2, f_{\text{CPUCLK}})$. CPU cycle counts and dynamic instruction counts were obtained from simulation, while FPGA resource utilization was obtained from the synthesis reports. Table 1 summarizes the results.

Specification	**LAT = 0**	**LAT = 2**	**LAT = 6**	**LAT = 10**
MAIN Fmax (MHz)	100.35	100.03	100.03	100.03
CPUCLK Fmax (MHz)	50.03	50.09	50.09	50.09
Effective Fmax (MHz)	50.03	50.015	50.015	50.015
CPU Cycles	6907	13814	27628	41442
Instructions	5409	5409	5409	5409
Average CPI	1.277	2.554	5.108	7.662
Ideal Latency (ns)	19.988	19.994	19.994	19.994
Execution Time (μs)	138.06	276.20	552.39	828.59
Slice LUTs	1866	1866	1866	1866
Slice Registers	1180	1180	1180	1180
F7 Muxes	410	410	410	410
F8 Muxes	110	110	110	110

Table 1: Single-Cycle Processor Performance and FPGA Utilization

The single-cycle processor maintained an operating frequency of approximately 50 MHz across all memory latency configurations. However, CPI increased from 1.277 at LAT = 0 to 7.662 at LAT = 10, resulting in a sixfold increase in execution time from 138.06 to 828.59 μs. The instruction count of 5,409 indicates that the additional execution cycles were caused by memory-related delays rather than changes in program execution. These results demonstrate that memory latency significantly affects processor performance despite relatively constant operating frequency.

3.2 Pipelined

The five-stage pipelined processor was evaluated using the same mergesort.asm benchmark at memory latencies of 0, 2, 6, and 10 cycles. Table 2 summarizes the processor's performance and FPGA resource utilization.

Specification	**LAT = 0**	**LAT = 2**	**LAT = 6**	**LAT = 10**
MAIN Fmax (MHz)	177.43	143.39	143.39	143.39
CPUCLK Fmax (MHz)	87.63	71.695	71.695	71.695
Effective Fmax (MHz)	87.63	71.695	71.695	71.695
CPU Cycles	9408	16451	33197	47011
Instructions	5409	5409	5409	5409
Average CPI	1.739	3.041	6.137	8.691
Ideal Latency (ns)	57.06	69.74	69.74	69.74
Execution Time (μs)	107.36	229.46	463.03	655.71
Slice LUTs	3008	3008	3008	3008
Slice Registers	2297	2297	2297	2297
F7 Muxes	453	453	453	453
F8 Muxes	64	64	64	64

Table 2: Pipelined Processor Performance and FPGA Utilization

The pipelined processor achieved a maximum operating frequency of 87.63 MHz at LAT = 0, compared to approximately 50 MHz for the single-cycle processor. Despite its higher CPI of 1.739, the shorter clock period reduced total execution time to approximately 107.36 μs. As memory latency increased, CPI rose to 8.691 at LAT = 10, increasing execution time to 655.71 μs. The higher operating frequency allowed the pipelined processor to maintain lower execution times than the single-cycle design across all tested memory latencies.

3.3 Performance Comparison

The pipelined processor outperformed the single-cycle processor across all memory latencies despite having a higher CPI. Its higher operating frequency reduced execution time by 22.2% at LAT = 0 and 20.9% at LAT = 10. Table 3 summarizes the performance improvements.

LAT	Single (μs)	Pipeline (μs)	Speedup	Reduction
0	138.06	107.36	1.286	22.2%
2	276.20	229.46	1.204	16.9%
6	552.39	463.03	1.193	16.2%
10	828.59	655.71	1.264	20.9%

Table 3: Single-Cycle and Pipelined Processor Performance Comparison

Although pipeline stalls and hazards increased CPI, the higher clock frequency compensated for this, resulting in execution time reductions of approximately 16–22% across the tested memory latencies.

Resource	Single-Cycle	Pipelined	Change
Slice LUTs	1866	3008	+61.2%
Slice Registers	1180	2297	+94.7%
F7 Muxes	410	453	+10.5%
F8 Muxes	110	64	-41.8%

Table 4: FPGA Resource Utilization Comparison

The performance improvement comes at the cost of additional FPGA resources, with the pipelined processor requiring 61.2% more slice LUTs and 94.7% more slice Registers. This increased resource utilization reflects the additional pipeline registers, forwarding logic, hazard control, and branch prediction logic required for pipelined execution.

4 Conclusion

The mergesort benchmark showed that the pipelined processor completed execution faster than the single-cycle at every tested memory latency. The CPI of the pipeline processor was higher due to hazards and stalls, the increased clock frequency compensated for the extra cycles. Overall the execution time was 16–22% faster, with the largest reduction being at LAT = 0.

The increase in performance came at the cost of resource utilization. The pipeline used 1.61 time as many

5 Contributions

Connor Lai: Contributed to the development and verification of the pipelined processor, including the forwarding unit, hazard unit testbench, overall datapath integration, debugging, and testing. Also assisted with performance measurements for CPI and execution time, synthesis, and analysis of results.

Michael Wu: Contributed to the development of the single cycle CPU design and pipelined processor. This includes the hazard unit, forwarding unit testbench, pipeline control, and overall datapath integration, debugging, and testing. Also assisted with performance analysis and synthesis.