

USB4 2.0 ENGINEERING CHANGE NOTICE FORM

Title: No Response bit – Align Table

Applied to: USB4 Specification Version 2.0

Brief description of the functional changes:
A Router updates the No Response bit at the end of a SB transaction, which is initiated by a Connection Manager. The Text is correct, and this ECN aligns the table to the text.

Benefits as a result of the changes:
Spec is more coherent.

An assessment of the impact to the existing revision and systems that currently conform to the USB specification:
None

An analysis of the hardware implications:
None

An analysis of the software implications:
None

An analysis of the compliance testing implications:
None

USB4 2.0 ENGINEERING CHANGE NOTICE FORM

Actual Change

(a). Section 4.1.1.3.2 Connection Manager Access – No Change

A Router shall process an AT Command as described in Table 4-17. When a response to a local access is ready or when a Response Transaction is received, the Router shall update the USB4 Port Capability as follows:

- The *LEN* field in the AT Response, the RT Response, or the local access is copied to the *Length* field in the USB4 Port Capability.
- The **No Response** bit is updated.
- The *Result Code* bit in the USB4 Port Capability is updated.
- For a read, the *Data* DWs in the USB4 Port Capability are updated.

(b). Table 8-13. USB4 Port Capability Fields

Table 8-13. USB4 Port Capability Fields

DW	Register Name	Bit(s)	Field Name and Description	Type	Default Value
1	PORT_CS_1	...	...	...	...
		25	No Response (NR) A Router uses this field when a Connection Manager initiates a read or write to SB Register Space. A Router shall set this bit to 1b if it did not receive a response for the read/write (including after any retransmissions), <u>otherwise it shall be set to 0.</u> This field is only valid when the <i>Pending</i> bit is set to 0b.	R/W	0b