

ASSIGNMENT

Anuparthi Mohana Sai
mohansai0507@gmail.com

IITH - Future Wireless Communications (FWC)

CONTENTS

- 1 Question
- 2 Components
- 3 formulae
- 4 Truth table
- 5 Implementation

1 QUESTION

(GATE CS-2021)

Q.7. Let p and q be two proportions. Consider the following two formulae in propositional logic.

$$S1: (\neg p \wedge (p \vee q)) \longrightarrow q$$

$$S2: q \longrightarrow (\neg p \wedge (p \vee q))$$

Which one of the following choices is correct?

- 1) Both S1 and S2 are tautologies.
- 2) S1 is a tautology but S2 is not a tautology.
- 3) S1 is not a tautology but S2 is a tautology.
- 4) Neither S1 nor S2 is a tautology.

2 COMPONENTS

Component	Values	Quantity
ArduinoUNO		1
JumperWires	M-M	10
Breadboard		1
LED		2
Resistor	220ohms	2

Figure.a

3 FORMULAE

A tautology is a compound statement in Maths which always results in Truth(True) value.

Tautology formula:

$$p \longrightarrow q = \neg p \vee q$$

1 where:

\neg = Not operation

1 \wedge = and operation

1 \vee = or operation

1 a) Therefore the two propositional logics S1 and S2 formulae are:

2

$$S1: (\neg p \wedge (p \vee q)) \longrightarrow q = \neg((\neg p \wedge (p \vee q))) \vee q$$

$$S2: q \longrightarrow (\neg p \wedge (p \vee q)) = \neg q \vee (\neg p \wedge (p \vee q))$$

4 TRUTH TABLE

TABLE I: Truth table for expression S1

p	q	$\neg((\neg p \wedge (p \vee q))) \vee q$
false	false	true
false	true	true
true	false	true
true	true	true

From the above truth table it is seen that all the outputs are true. Therefore the expression "S1 is a tautology".

TABLE II: Truth table for expression S2

p	q	$\neg q \vee (\neg p \wedge (p \vee q))$
false	false	true
false	true	true
true	false	true
true	true	false

From the above truth table it is seen that one of the output is false, to meet the tautology condition all the outputs must be true. Therefore the expression "S2 is not a tautology".

5 IMPLEMENTATION

S1: $(\neg p \wedge (p \vee q)) \longrightarrow q = \neg((\neg p \wedge (p \vee q))) \vee q$

S2: $q \longrightarrow (\neg p \wedge (p \vee q)) = \neg q \vee (\neg p \wedge (p \vee q))$

Consider the expression S1:

Assume the variables p and q as A and B (as there are two expressions with same variables we assume one of the expression with variables A and B).

Therefore the expression S1 becomes as

S1: $(\neg A \wedge (A \vee B)) \longrightarrow B = \neg((\neg A \wedge (A \vee B))) \vee B$

TABLE III: connections

Arduino pin	INPUT	OUTPUT
2	A	
3	B	
4	p	
5	q	
6		C
8		R

a) Procedure

1. Connect the circuit as per the above table.
2. Connect the Output pins C and R to the LED's.
3. Connect the other end of the LED's to the Ground terminal.
4. Connect inputs to Vcc for logic 1, ground for logic 0.
5. Execute the circuits using the below code.

<https://github.com/Mohan200305/ide/blob/main/code/cs.cpp>

6. Change the values of A,B,P,Q in the code and verify the Truth tables respectively.

Answer is : **Option2 : S1 is a tautology but S2 is not a tautology.**