Stellar Cyber 6.6.0s is now live! Discover all the updates in the release notes!

Configuring ERSPAN Ingestion

You can configure a Modular Sensor to ingest GRE traffic mirrored with ERSPAN.

During installation, the timezone for sensors are automatically set to UTC+0. Since the logs for some security products might only include the local time without a timezone, Stellar Cyber recommends that you set the sensor timezone to the same timezone as your security product.

To ingest ERSPAN:

1. Configure ERSPAN on your Cisco switch.
2. Configure your sensor to ingest from the Cisco switch.
3. Verify Ingestion.

Configure ERSPAN on Your Cisco Switch

To configure ERSPAN on your Cisco switch:

1. Configure GRE.
2. Configure ERSPAN to mirror traffic to a specific port.
3. Note the IP address of the switch and the port you're mirroring to.

Configure Your Sensor to Ingest Logs from the Cisco Switch

To configure your sensor to ingest ERSPAN traffic from the Cisco Switch:

1. Log in to the Modular Sensor CLI and enter the following command:
2. `set interface ethernet<interface#> ip <IP address of the Cisco switch>/<network mask>`

   The `interface#` in the command above corresponds to the monitor port label on the sensor itself (for example, Ports 1..7 on a Photon 300).

   For example:

   ```
   set interface ethernet1 10.1.10.27/24
   ```

3. Verify with the `show interface` command.

   You should see the lin for the interface (`ethernet1` in this example) and the IP address of the mirror port (`10.1.10.27`).

Verifying Ingestion

To verify ingestion:

1. Select **Threat Hunting**.

   The **Interflow Search** tab appears.

2. Set **Indices** as **Traffic**.

   The table immediately updates to show ingested Interflow records.

© 2026 Stellar Cyber . All rights reserved.