



0 stars 124 forks 0 watching Activity

Public repository · Forked from [Xinyuan-LilyGO/LilyGo-LoRa-Series](#)

master ▾

...

Branches

Tags

This branch is [188 commits behind](#) Xinyuan-LilyGO:master.

LilyGO Update README.MD ... on Aug 4, 2020 28

[View code](#)

README.MD

PinOut

Pins	T_BEAM(AXP192)	T_BEAM_V07
LORA_SCK	5	5
LORA_MISO	19	19
LORA_MOSI	27	27
LORA_SS	18	18
LORA_DIO0	26	26
LORA_DIO1	33	33
LORA_DIO2	32	32
LORA_RST	23	23

Pins	T_BEAM(AXP192)	T_BEAM_V07
GPS_RX_PIN	34	12
GPS_TX_PIN	12	15
I2C_SDA	21	21
I2C_SCL	22	22
PMU_IRQ	35	N/A
USER BUTTON	36	N/A

Power Control Channel

Modules	T_BEAM_V10/V1.1	T_BEAM_V07
GPS	LDO3	No supoort
LORA	LDO2	No supoort
OLED	DCDC1	No supoort

Button Map

USB	BTN1	BTN2	BTN3
N/A	axp192 powerkey	user button	reset

Button Function:

- Click button 2 will cycle the user function, the default start to enable GPS positioning, the second click will be set to lora send, the third click will be set to lora receive, long press for two seconds and then release, will enter deep sleep

About OLED:

- The boot will scan the I2C device. If the OLED is found, all log information will be displayed in the OLED. If not, it will be printed on the serial port.

How to use

- For dependencies on other files please see `platformio.ini`
- Regarding the board, you can modify the board version and lora frequency in `board_def.h`
- If you use the Arduino IDE for compilation, please store `board_def.h` and `LilyGO-T-Beam.ino` in the same directory, and the directory folder name must be the same as `ino`

Deepsleep

- Regarding deep sleep, except for DCDC3, power off all channels of AXP192, the current consumption is about 580μA

Releases

No releases published

Packages

No packages published

Languages

● C++ 89.4% ● C 10.6%