Physics 3200Y: Lab 4

Jeremy Favro (0805980), Bryan Roberts (0691165), Melodie Johnston (0794390)
Department of Physics & Astronomy
Trent University, Peterborough, ON, Canada

March 29, 2026

Abstract

1 Introduction

This lab seeks to develop and test theoretical models for the field between two current carrying loops of wire. The developed models predict a high uniformity of the magnetic field between the coils in both magnitude and direction. The theoretical uniformity of the field will be investigated through the construction of the structure for which models were derived and the use of a magnetic field probe. Additionally the more mathematically challenging off-axis field of the coil structure will be measured and investigated.

2 Theory



Figure 1: Helmholtz coil structure

The construction under study, known as Helmholtz coils is illustrated in fig. 1. We consider two coils, each of radius R, separated by a distance R. In the figure, and for the following derivation, the coils are placed at $\pm R/2$ respectively with the origin between them as indicated in the figure. We begin by deriving the field due to a single current carrying loop and then utilize linear superposition to determine the total magnetic field due to a true Helmholtz coil system. The magnetic field for a wire loop represented by a (directed) contour $\mathcal{C}$ is given by the Biot-Savart law,

$$\mathbf{B}(\mathbf{r}) = \frac{\mu_0 I}{4\pi} \int_{\mathcal{C}} \frac{d\boldsymbol{\ell}' \times \boldsymbol{\mathscr{r}}'}{\mathscr{r}^3} \tag{1}$$

where $\boldsymbol{\mathscr{r}} = \mathbf{r} - \mathbf{r}'$ and $\mathbf{r}$ and $\mathbf{r}'$ represent the test-point and an integration variable respectively. To exploit the symmetries present in the problem we consider only the field on the axis of symmetry, hereon referred to as the on-axis field. This means that our position vector $\mathbf{r} = (0, 0, z)$ in cylindrical coordinates. Since we are considering only the field due to a single coil we take $\mathbf{r}' = R\hat{\mathbf{s}}$ which sweeps out the entire coil. This gives $\boldsymbol{\mathscr{r}} = z\widehat{\mathbf{z}} - R\hat{\mathbf{s}}$. Finally if we direct the contour such that the area vector is in $\widehat{\mathbf{z}}$, $d\ell' = Rd\phi'\hat{\boldsymbol{\phi}}$. This means that eq. (1) becomes

$$\begin{aligned}\mathbf{B}(\mathbf{r}) &= \frac{\mu_0 I}{4\pi} \int_0^{2\pi} \frac{Rd\phi' z\hat{\mathbf{s}} + R^2 d\phi' \widehat{\mathbf{z}}}{(z^2 + R^2)^{3/2}} \\ &= \frac{\mu_0 I}{2} \frac{R' z\hat{\mathbf{s}} + R^2\widehat{\mathbf{z}}}{(z^2 + R^2)^{3/2}}\end{aligned}$$

and since the magnetic field obeys linear superposition, N such coils very close together create a field given by

$$\mathbf{B}(\mathbf{r}) = \frac{\mu_0 N I}{2} \frac{R' z\hat{\mathbf{s}} + R^2\widehat{\mathbf{z}}}{(z^2 + R^2)^{3/2}}. \tag{2}$$

Now we can construct the field due to two such coils at $\pm R/2$ easily again by linear superposition,

$$\begin{aligned}\mathbf{B}(\mathbf{r}) = \frac{\mu_0 N I R^2}{2} \Bigg[&\frac{1}{((z + R/2)^2 + R^2)^{3/2}} \\ &+ \frac{1}{((z - R/2)^2 + R^2)^{3/2}} \Bigg] \widehat{\mathbf{z}}\end{aligned} \tag{3}$$

where we've canceled out the $\hat{\mathbf{s}}$ components of the field by symmetry. We can plot this expression (in natural units), and we see that indeed the field inside and near the center is highly uniform. This is the desired effect of the Helmholtz configuration.



Figure 2: Helmholtz coil relative magnetic field strength. The coloured curves are fields due to the individual coils, placed at $\pm 1/2$, and the black curve is their sum.

3 Methods

3.1 Coils

Two 200 turn, 10 cm radius, Pasco Scientific Helmholtz coils were used [1]. These were mounted on a ruled base, also manufactured by Pasco Scientific.

3.2 Magnetic Probe

The magnetic field produced by the coils was measured using a Pasco Scientific 2-axis field sensor [2]. The probe was positioned to measure the fields both perpendicular and parallel to the coil plane to verify the uniformity and self-canceling behaviour in these directions. Data was collected on the field in several configurations in order to verify the validity of assumptions made in theoretical derivations. Further discussion is available in the results section.

3.3 Linear Motion Sensor

In order to measure the field as a function of position in the coil a Pasco Scientific rotary motion sensor [3] was used, with the magnetic field probe mounted to a rigid support whose extension into the coils could be tracked by the motion sensor.

3.4 Alignment

A challenge in configuring the experiment was the need to measure as closely as possible to the axis of symmetry of the coils, as this is the region in which the theory derived previously applies. To align the probe vertically two rulers were placed perpendicularly and the axial field indicator dot on the probe was aligned with the appropriate position on the rulers. To align horizontally a similar process was used except with the perpendicular field indicator dot. The motion sensor was zeroed at 10 cm from the first coil.

Make some pictures of the setup here and shunt results to next page

4 Results

4.1 On-Axis

The on-axis field was collected in several configurations. These are: the normal Helmholtz configuration, one coil on and the other off for each coil, both coils at a separation of $2R$, and both coils at a separation of $R/2$. For each run the current passing through the coils was held at a value not exceeding 1.5 A, though due to coil heating a drop to as low as 1.47 A was observed.



Figure 3: Perpendicular and axial fields in a standard Helmholtz configuration.

4.1.1 Superposition

Figure out a good way to do this

4.2 Off-Axis

Blah blah

5 Discussion

References

[1] Helmholtz coils • EM-6722 — pasco.com. `https://www.pasco.com/products/lab-apparatus/electricity-and-magnetism/coils-and-cores/helmholtz-coils`. [Accessed 30-03-2026].

[2] PASPORT 2-Axis Magnetic Field Sensor • PS-2162 — pasco.com. `https:`



Figure 4: Perpendicular and axial fields in a $2R$ Helmholtz configuration.



Figure 5: Perpendicular and axial fields in an $R/2$ Helmholtz configuration.

//www.pasco.com/products/sensors/pasport/pasport-2-axis-magnetic-field-sensor. [Accessed 30-03-2026].

[3] PASPORT Rotary Motion Sensor • PS-2120A — pasco.com. https://www.pasco.com/products/sensors/pasport/pasport-rotary-motion-sensor. [Accessed 30-03-2026].



Figure 6: Perpendicular and axial fields in an $R/2$ Helmholtz configuration.



Figure 7: Perpendicular and axial fields in an $R/2$ Helmholtz configuration.