

Field-Distribution Engineering in Fractal Nonlinear Capacitors

Integrated, submission-ready manuscript skeleton (Abstract → References), incorporating the final theory/validation framework, precision edits, and figure-caption mini-results.

Abstract

The relentless scaling of passive components demands strategies beyond conventional material optimization. While fractal geometries have been explored to increase capacitance density through area enhancement, their interaction with nonlinear dielectrics remains underexplored. Here, we introduce **field-distribution engineering** via self-similar electrodes as a method to tailor the nonlinear capacitive response of thin-film dielectrics. We present a model that decouples geometric and material contributions: the differential capacitance is expressed as a **weighted field-distribution integral** of the intrinsic differential permittivity $\varepsilon_{\text{diff}}(E)$ against a geometry-controlled density $p(E)$. Using BaTiO_3 as a model nonlinear dielectric, we fabricate and characterize fractal capacitors of varying iteration depths. We demonstrate **superlinear scaling** of capacitance with fractal depth—exceeding predictions from a linear geometric series—and correlate this with simulated field distributions. The approach yields predictable fractional-order dynamics, characterized by a constant-phase element exponent α that decreases with iteration depth. However, field enhancement at fractal tips reduces the breakdown voltage, creating a trade-off that leads to an **optimal iteration depth** for maximum usable energy density. This framework of field-distribution engineering provides a general principle for co-designing geometry and material nonlinearity in next-generation passive devices.

Introduction

The Need for Geometric Leverage in Capacitor Scaling

The demand for higher capacitance density in integrated passive components continues to outpace the incremental gains from dielectric material discovery. While high- κ and nonlinear dielectrics (e.g., ferroelectrics like BaTiO_3) offer enhanced permittivity, their response is often strongly field-dependent and ultimately limited by breakdown [1,2]. This has spurred interest in **geometric amplification**—using electrode morphology to increase effective area within a fixed footprint.

Fractal Electrodes: From Area Enhancement to Field Distribution Control

Fractal and interdigitated electrodes are established techniques for increasing capacitance density [3,4]. In linear dielectrics, their benefit is well-modeled as an increase in effective electrode area or perimeter. However, in a **nonlinear dielectric**, where permittivity varies with local electric field $\varepsilon(E)$, the device response is no longer a simple function of geometry alone. The local field, and thus the material's contribution, is spatially modulated by the electrode morphology. Prior work on fractal capacitors has

largely overlooked this coupled electromechanical response, treating the dielectric as linear or ignoring the field heterogeneity inherent to self-similar structures [5,6]. This interaction **remains underexplored**, particularly in a framework that is both predictive and experimentally validated.

The Concept of Field-Distribution Engineering

We propose that the true design variable for nonlinear capacitors is not merely area, but the **statistical distribution of electric fields** $p(E)$ within the dielectric volume. A fractal electrode, by creating a hierarchy of feature scales, engineers this distribution, concentrating weight in regions of high or low field depending on the geometry. The device's macroscopic differential capacitance $C_d(V)$ then becomes a weighted functional of the material's $\epsilon_{\text{diff}}(E)$ over this distribution. This **field-distribution engineering** paradigm shifts the focus from maximizing area to sculpting the internal field landscape to optimally sample a material's nonlinear response.

This Work: A Coupled Theory and Validation

We develop a theoretical framework that separates exact small-signal electrostatics from a practical geometry-material decoupling approximation, and validate it using planar fractal electrodes of varying iteration depths paired with a thin-film ferroelectric dielectric (BaTiO₃). We demonstrate:

1. **Superlinear capacitance scaling** with fractal depth, explained by the field-distribution integral of $\epsilon_{\text{diff}}(E)$ against a simulated $p(E)$.
2. The emergence of **fractional-order dynamics** (constant-phase element behavior) that scales with geometric complexity.
3. The critical **breakdown-energy trade-off**, where field enhancement at fractal tips reduces operating voltage, leading to a well-defined optimum in usable energy density.

Theory

1. Small-Signal Differential Capacitance as a Second Variation

We consider an isotropic, nonlinear dielectric described by a constitutive relation $D(E) = \epsilon_0 E + P(E)$. The field-dependent differential permittivity is

$$\epsilon_{\text{diff}}(E) = \frac{dD}{dE}.$$

For a fixed electrode geometry G and dielectric domain Ω , the application of a DC bias V establishes a steady-state potential $\phi_b(\mathbf{x}; V)$, with the corresponding electric field $\mathbf{E}_b(\mathbf{x}; V) = -\nabla \phi_b$.

To define the small-signal (differential) capacitance $C_d(V; G)$, we consider a harmonic perturbation $\delta V e^{j\omega t}$ about the bias point. Linearizing Poisson's equation around the biased state yields a linear problem for the complex perturbation potential $\phi_1(\mathbf{x}; V)$, defined as the solution to

$$\nabla \cdot \left[\epsilon_{\text{diff}}(\mathbf{E}_b(\mathbf{x}; V)) \nabla \phi_1(\mathbf{x}; V) \right] = 0, \tag{A1}$$

with boundary conditions $\phi_1 = 1$ on the working electrode and $\phi_1 = 0$ on the counter-electrode. The differential capacitance is then given by the second variation of the electrostatic energy:

$$C_d(V; G) = \int_{\Omega} \epsilon_{\text{diff}}(\mathbf{E}_b(\mathbf{x}; V)) |\nabla \phi_1(\mathbf{x})|^2 d\Omega. \quad (1)$$

2. Field-Distribution Functional Representation

Equation (1) can be reinterpreted as a weighted average of the material response over the spatial field distribution. We define a normalized weighting measure

$$d\mu_V(\mathbf{x}) = \frac{\epsilon_{\text{diff}}(\mathbf{E}_b(\mathbf{x}; V)) |\nabla \phi_1(\mathbf{x})|^2 d\Omega}{\int_{\Omega} \epsilon_{\text{diff}}(\mathbf{E}_b(\mathbf{x}; V)) |\nabla \phi_1(\mathbf{x})|^2 d\Omega}.$$

Pushing this measure forward through the mapping $\mathbf{x} \mapsto E_b(\mathbf{x}; V)$ yields a biased field-distribution density $\tilde{p}_V(E; G)$, satisfying

$$\int_0^\infty f(E) \tilde{p}_V(E; G) dE = \int_{\Omega} f(E_b(\mathbf{x}; V)) d\mu_V(\mathbf{x})$$

for any test function f . This representation is exact, but $\tilde{p}_V$ generally depends on both geometry and bias through the biased solution.

To obtain a tractable design rule that separates geometry from material, we introduce a **geometry-only reference**. Let $\psi_1(\mathbf{x}; G)$ be the solution to Eq. (A1) with a constant $\epsilon_{\text{diff}} \equiv \epsilon_0$ (Laplace solution for the same geometry). Define

$$C_{\text{geo}}(G) = \epsilon_0 \int_{\Omega} |\nabla \psi_1|^2 d\Omega,$$

and the corresponding geometry-only field distribution using the unit-bias Laplace field magnitude $E_b^0(\mathbf{x})$:

$$p(E; G) dE = \frac{\int_{\Omega} \delta(E - E_b^0(\mathbf{x})) |\nabla \psi_1|^2 d\Omega}{C_{\text{geo}}(G)} \epsilon_0 |\nabla \psi_1|^2 d\Omega.$$

Using $p(E; G)$ as a zeroth-order approximation for $\tilde{p}_V(E; G)$ yields the central design relation:

$$\frac{C_d(V; G)}{C_{\text{geo}}(G)} \approx \int_0^\infty \frac{\epsilon_{\text{diff}}(E)}{\epsilon_0} p(E; G) dE. \quad (2)$$

This approximation becomes exact for a linear dielectric and remains accurate when spatial variations in ϵ_{diff} do not strongly perturb the field pattern from the Laplace solution.

Normalized-field form. With $\tilde{E} = E/(V/d)$, the geometry-only distribution can be reported as $p(\tilde{E}; G)$, bias-invariant by construction.

3. Material Model: Landau-Ginzburg-Devonshire (LGD)

For a ferroelectric dielectric such as BaTiO₃, the nonlinear polarization response is captured by the LGD free-energy expansion (1D, monodomain):

$$\mathcal{F}(P, E) = \frac{a}{2} P^2 + \frac{b}{4} P^4 + \frac{c}{6} P^6 - E P,$$

with equilibrium polarization satisfying

$$E = a P + b P^3 + c P^5.$$

With $D = \varepsilon_0 E + P$, the differential permittivity is

$$\varepsilon_{\mathrm{diff}}(E) = \frac{dD}{dE} = \varepsilon_0 + \frac{dP}{dE} = \varepsilon_0 + \frac{1}{a + 3b P^2 + 5c P^4}.$$

4. Self-Similar Electrodes: Geometric Scaling and Field Enhancement

Consider a self-similar electrode iterated to depth n . Let iteration k introduce N^k features with characteristic length $\ell_k = s^k \ell_0$ ($0 < s < 1$). If the capacitive contribution of a feature scales as ℓ^β ($\beta \approx 2$ for area-dominated, $\beta \approx 1$ for fringe-field-dominated), define

$$\rho_{\mathrm{total}}(n) = \sum_{k=0}^n (N s^\beta)^k = \sum_{k=0}^n \rho^k, \quad \rho = N s^\beta.$$

Features at scale k produce local field enhancement $\kappa_k \geq 1$ relative to $E_{\mathrm{avg}} = V/d$, i.e., $E_k(V) \approx \kappa_k V/d$. In practice κ_k and hotspot metrics are extracted from FEM (preferably via high-percentile fields rather than point maxima).

5. Coupled Geometry–Nonlinearity Scaling Model

A discrete approximation consistent with Eq. (2) is

$$C_d^{(n)}(V) \approx C_0 \sum_{k=0}^n \rho^k \gamma_k(V), \quad \gamma_k(V) = \frac{\varepsilon_{\mathrm{diff}}(\kappa_k V/d)}{\varepsilon_{\mathrm{diff}}(V/d)}.$$

Here C_0 is the base capacitance of the $k = 0$ structure with a linear dielectric.

6. Breakdown-Limited Optimization and Usable Energy

Let E_{bd} be intrinsic breakdown field. The breakdown voltage is constrained by the maximum enhancement factor:

$$V_{\mathrm{bd}}^{(n)} \lesssim \frac{d \cdot E_{\mathrm{bd}}}{\kappa_{\mathrm{max}}(n)}, \quad \kappa_{\mathrm{max}}(n) = \max_{k \leq n} \kappa_k. \tag{6}$$

Usable energy at operating voltage $V_{\text{op}} \leq V_{\text{bd}}^{(n)}$ is

$$U_{\text{use}}^{(n)}(V_{\text{op}}) = \int_0^{V_{\text{op}}} Q^{(n)}(V) \, dV, \quad Q^{(n)}(V) = \int_0^V C_d^{(n)}(V') \, dV'. \quad \text{tag{7}}$$

Equivalently,

$$U_{\text{use}}^{(n)}(V_{\text{op}}) = \int_0^{V_{\text{op}}} (V_{\text{op}} - V') C_d^{(n)}(V') \, dV'. \quad \text{tag{8}}$$

The model predicts an optimal depth n^* maximizing $U_{\text{use}}^{(n)}$.

7. Fractional-Order Dynamics from Distributed RC Networks

Self-similar morphology yields a broad distribution of time constants. A constant-phase element (CPE) captures dispersive impedance:

$$Z_{\text{CPE}}(\omega) = \frac{1}{Q(j\omega)^\alpha}, \quad 0 < \alpha < 1. \quad \text{tag{8}}$$

For a fractal electrode, α is expected to decrease with iteration depth n , reflecting broader relaxation spectra. This dispersive behavior is primarily geometric and can be characterized independently from dielectric nonlinearity via bias-dependent impedance spectroscopy.

Experimental Methods and Validation

1. Device Set and Experimental Matrix

- Fabricate matched sets: plain, interdigitated, and fractal geometries G_n for $n = 0..n_{\text{max}}$.
- Hold constant: footprint A , dielectric thickness d , dielectric stack, electrode metals, process conditions.
- Include replicates: N_{dev} per geometry/depth across $N_{\text{waf}} / N_{\text{dies}}$.

2. Fabrication and Structural Metrology

- Report g_{min} (minimum gap), linewidths, etch bias, and r_{tip} (tip radius/rounding) via SEM/CD-SEM/AFM.
- Identify truncation scale ℓ_{min} and quantify variability across device sets.
- Use parallel-plate control capacitor fabricated with identical dielectric and electrodes.
- Measure small-signal $C_d(V)$ with AC perturbation δV chosen to remain in the linearized regime.
- Map field as $E \approx V/d$ (account for series drops if relevant).
- Obtain $\varepsilon_{\text{diff}}(E) \approx C_d(V) d/A$.
- Optional: fit $\varepsilon_{\text{diff}}(E)$ to LGD (Eq. 3) and state hysteresis handling (minor loop / branch selection).

4. Electrical Characterization

- **C-V and loss:** measure $C_d(V; G)$ and $\tan \delta(V; G)$ across a safe bias range.
- **EIS:** measure $Z(\omega; V)$; fit to CPE (Q, α) + parasitics (R_s , leakage as needed).
- **Time domain (optional):** controlled charge/discharge; fit to stretched exponential or multi-exponential.

5. Breakdown Testing and Reliability Statistics

- Measure breakdown voltage V_{bd} using controlled ramp rate and current compliance.
- Report Weibull statistics for each n and geometry class.
- **Laplace reference:** solve with $\varepsilon = \varepsilon_0$ and unit bias to compute ψ_1 , $C_{geo}(G)$, and geometry-only $p(\tilde{E}; G)$.
- **Hotspot metrics:** compute $\kappa_{max}(n)$ from high-percentile $|\mathbf{E}|$ (mesh-converged, tip-refined meshes).
- **Distribution construction:** bin $\tilde{E}$ and accumulate weights $\propto \varepsilon_0 |\nabla \psi_1|^2$; normalize so $\int p(\tilde{E}) d\tilde{E} = 1$.

7. Model Validation Workflow

1. FEM: compute $p(\tilde{E}; G_n)$ for each n .
2. Material: measure $\varepsilon_{diff}(E)$ from control; optionally LGD-fit.
3. Predict: $\hat{C}_d(V; G_n) = C_{geo}(G_n) \int (\varepsilon_{diff}(E)/\varepsilon_0) p(E; G_n) dE$.
4. Verify: compare predicted vs measured $C_d(V)$, report NRMSE and uncertainty bands.
5. Breakdown trade-off: correlate $V_{bd}^{(n)}$ with $\kappa_{max}(n)$ and compute $U_{use}^{(n)}$ up to a conservative V_{op} .
6. Dispersion: validate $\alpha(n)$ decreases with n , including low-bias evidence.

Results (Template)

Figure 1 presents the intrinsic nonlinear dielectric response, decoupled from geometric effects. The differential permittivity $\varepsilon_{diff}(E)$ measured on the control parallel-plate capacitor shows **[describe trend]**. The data are well-described by the LGD model (Eq. 3), with fitted coefficients $a = [\text{val}]$, $b = [\text{val}]$, $c = [\text{val}]$. Loss tangent $\tan \delta(E)$ exhibits **[trend]**.

2. Engineered Field Distributions from Fractal Iteration

Figure 2 quantifies geometric manipulation of the field. SEM confirms self-similar patterning and $\ell_{min} = [\text{val}]$. Laplace-derived, geometry-only field-distribution densities $p(\tilde{E}; G_n)$ ($\tilde{E} = E/(V/d)$) reveal the core mechanism: with increasing n , the distribution develops a heavier high- $\tilde{E}$ tail. This tail corresponds to enhanced-field regions ($\tilde{E} \sim \kappa_k$) that weight $\varepsilon_{diff}(E)$ in Eq. (2) and enter the discrete model via $\gamma_k(V)$ in Eq. (5).

3. Prediction and Measurement of Differential Capacitance

Figure 3 validates Eq. (2). Predicted $\hat{C}_d(V)$ (lines) computed from measured $\varepsilon_{\text{diff}}(E)$ and simulated $p(\tilde{E}; G_n)$ agrees with measured $C_d(V)$ (symbols) over $V \leq V_{\text{op}}$. Report NRMSE = [X]% with uncertainty bands from $\varepsilon_{\text{diff}}$ noise and FEM discretization. **Superlinear scaling** is defined as $C_d^{(n)}(V)$ increasing faster with n than the linear-dielectric baseline $C_{\text{lin}}^{(n)} \propto \sum_{k=0}^n \rho^k$.

4. Fractal-Induced Dispersion and Fractional-Order Dynamics

Figure 4 shows EIS and CPE fits. α decreases systematically with iteration depth n , and the trend persists at low bias where $C_d(V)$ is nearly constant, supporting a primarily geometric origin for dispersion. Time-domain discharge shows progression from exponential to stretched-exponential relaxation as n increases.

5. Breakdown Statistics and the Usable Energy Trade-off

Figure 5 establishes the trade-off. The characteristic breakdown voltage $V_{\text{bd}}^{(n)}$ decreases with n (Weibull). When normalized by simulated $\kappa_{\text{max}}(n)$, the inferred intrinsic breakdown field $E_{\text{bd}} \approx \kappa_{\text{max}}(n)V_{\text{bd}}^{(n)}/d$ remains constant within uncertainty, consistent with geometry-driven breakdown reduction. Usable energy $U_{\text{use}}^{(n)}$ peaks at optimal depth $n^*=[\text{val}]$.

6. Comprehensive Performance Comparison

Figure 6 compares all geometries. Fractal device at n^* achieves [X]× increase in C_d at [Y] V vs plain; interdigitated yields [Z]×. Ragone-style plot uses $P_{\text{max}} = V_{\text{op}}^2/(4R_s)$ per unit volume; define how R_s is extracted and how volume is defined.

Discussion and Limitations

Synthesis of Findings

- Geometry sculpts $p(\tilde{E}; G_n)$, enabling predictive control of nonlinear response via Eq. (2).
- Fractional-order dynamics track geometric complexity ($\alpha(n)$ decreases with n).
- A breakdown-limited optimum n^* emerges as predicted by Eq. (6)–(7).

Limitations and Future Directions

(i) **Geometry-only approximation:** Eq. (2) uses a Laplace-derived $p(E; G)$ as a proxy for the fully coupled biased distribution; exact for linear dielectrics and accurate when $\varepsilon_{\text{diff}}$ variations do not strongly reshape the field pattern. Deviations are expected at highest biases; fully self-consistent nonlinear FEM is a next step.

(ii) **Hysteresis and loss:** Small-signal reversible $C_d(V)$ and $\tan \delta(V)$ are emphasized. Large-signal cycling may introduce hysteresis and additional dissipation; characterize branch selection/minor loops explicitly.

(iii) **Leakage and pre-breakdown conduction:** Field enhancement may increase leakage; future work should map $J(E, T)$ and geometry dependence.

(iv) **Feature sensitivity:** Hotspot fields depend on r_{tip} and g_{min} ; mitigate via metrology and FEM mesh convergence, but scalability requires tighter process control.

(v) **Extension to 3D:** Planar fractals provide a controlled platform; volumetric architectures may offer additional leverage but introduce deposition/void/defect challenges.

Conclusion

Self-similar electrodes provide a geometry-first knob—**field-distribution engineering**—for co-optimizing nonlinear dielectric response and device performance. The field-distribution integral framework links electrode design to bias-dependent capacitance, dispersion, breakdown-limited optimization, and usable energy via a unified, falsifiable model.

Figure Captions (Mini-Results)

Figure 1. Intrinsic nonlinear dielectric response of BaTiO₃. (a) Measured differential permittivity $\varepsilon_{\text{diff}}(E)$ (symbols) from a parallel-plate control capacitor, with fit to the LGD model (solid line). Inset: corresponding loss tangent $\tan \delta(E)$. (b) Nonlinear polarization response $P(E)$ implied by the fitted LGD constitutive relation (or measured minor-loop branch, if available).

Figure 2. Engineered field distributions via fractal iteration. (a) SEM micrographs of fabricated electrodes: plain, interdigitated, and fractal iterations $n = 0-3$. Scale bars: 2 μm . Inset: measured tip radius r_{tip} versus design scale ℓ_k . (b) FEM simulation of $|\mathbf{E}|$ at unit bias (log scale). (c) Geometry-only field-distribution densities $p(\tilde{E}; G_n)$ extracted from Laplace simulations, showing evolution of the high- $\tilde{E}$ tail with increasing n . Normalized so $\int p(\tilde{E}) d\tilde{E} = 1$.

Figure 3. Prediction and measurement of differential capacitance. (a) Measured $C_d(V)$ (symbols) for fractal iterations $n = 0-3$, compared to predictions (lines) from Eq. (2). Shaded bands represent uncertainty from $\varepsilon_{\text{diff}}(E)$ measurement and FEM discretization. (b) C_d at $V = 5 \text{ V}$ versus iteration depth n . Superlinear trend exceeds linear-dielectric geometric baseline $\sum \rho^k$. Error bars: device-to-device variation.

Figure 4. Geometric origin of fractional-order dynamics. (a) EIS data and CPE fits for $n = 0$ and $n = 3$ at $V = 0 \text{ V}$. (b) CPE exponent α versus n at low bias and high bias; decrease with n persists across bias. (c) Normalized discharge curves for matched initial charge showing exponential-to-stretched-exponential progression with increasing n .

Figure 5. Breakdown-energy trade-off and optimization. (a) Weibull plots of failure probability versus breakdown voltage V_{bd} . (b) Characteristic $V_{\text{bd}}^{(n)}$ and simulated $\kappa_{\text{max}}(n)$ versus n . Inset: inferred intrinsic breakdown field $E_{\text{bd}} = \kappa_{\text{max}}(n) V_{\text{bd}}^{(n)} / d$ remains approximately constant within uncertainty. (c) Usable energy density $U_{\text{use}}^{(n)}$ at $V_{\text{op}} = 0.8 V_{\text{bd}}^{(n)}$ peaks at n^* .

Figure 6. Comprehensive performance comparison. (a) C_d versus bias for all geometries: plain, interdigitated, and fractal at n^* . (b) Ragone-style plot of usable energy density versus power density, with $P_{\max} = V_{\text{op}}^2/(4R_s)$ per unit volume.

Submission Checklist (No-Regrets)

Conceptual & Narrative

- Abstract frames “field-distribution engineering” as core contribution.
- Intro establishes underexplored coupling of self-similar geometry with nonlinear $\varepsilon(E)$.
- Theory: exact small-signal form (Eq. 1) + practical decoupled approximation (Eq. 2).
- Causal chain maintained: geometry $\rightarrow p(\tilde{E}) \rightarrow$ predicted $C_d(V) \rightarrow$ measured $C_d(V)$ and dispersion $\rightarrow$ breakdown-limited optimum.

Technical Precision

- “Superlinear” defined vs linear-dielectric $\sum \rho^k$ baseline.
- Breakdown voltage decreases with n ; intrinsic E_{bd} inferred $\sim$ constant when normalized by $\kappa_{\max}$.
- $p(\tilde{E}; G)$ explicitly Laplace-derived (geometry-only) and bias-invariant by construction.
- Ragone power metric defined explicitly.
- $\alpha(n)$ trend shown at low bias.

Experimental Rigor

- Methods specify $p(\tilde{E})$ computation (binning, weighting, normalization).
 - FEM mesh-convergence and tip-refinement stated.
 - Hysteresis/branch selection stated for BaTiO₃.
 - Weibull breakdown analysis included.
 - Uncertainty bands shown for key plots.
-

References

- [1] Dawber, M.; Rabe, K. M.; Scott, J. F. *Physics of thin-film ferroelectric oxides*. **Rev. Mod. Phys.** 77, 1083–1130 (2005). DOI: 10.1103/RevModPhys.77.1083.
- [2] Tagantsev, A. K.; Sherman, V. O.; Astafiev, K. F.; Venkatesh, J.; Setter, N. *Ferroelectric materials for microwave tunable applications*. **Journal of Electroceramics** 11(1–2), 5–66 (2003). DOI: 10.1023/B:JECR.0000015661.81386.e6.
- [3] Samavati, H.; Hajimiri, A.; Shahani, A. R.; Nasserbakht, G. N.; Lee, T. H. *Fractal capacitors*. **IEEE Journal of Solid-State Circuits** 33(12), 2035–2041 (1998). DOI: 10.1109/4.735706.

[4] Kim, E.-S.; Liang, J.-G.; Wang, C.; Cho, M.-Y.; Oh, J.-M.; Kim, N.-Y. *Inter-digital capacitors with aerosol-deposited high-K dielectric layer for highest capacitance value in capacitive super-sensing applications*. **Scientific Reports** 9, 680 (2019). DOI: 10.1038/s41598-018-37416-7.

[5] Torabi, S.; Cherry, M.; Duijnste, E. A.; *et al.* *Rough Electrode Creates Excess Capacitance in Thin-Film Capacitors*. **ACS Applied Materials & Interfaces** 9(32), 27290–27297 (2017). DOI: 10.1021/acsami.7b06451.

[6] Lallart, M.; Wang, L.; Petit, L. *Enhancement of electrostatic energy harvesting using self-similar capacitor patterns*. **Journal of Intelligent Material Systems and Structures** 27(17), 2385–2394 (2016). DOI: 10.1177/1045389X16629573.

[7] Burke, A. *Ultracapacitors: why, how, and where is the technology*. **Journal of Power Sources** 91(1), 37–50 (2000). DOI: 10.1016/S0378-7753(00)00485-7.

Additional recommended references (dispersion/CPE and universal dielectric response)

[8] Brug, G. J.; van den Eeden, A. L. G.; Sluyters-Rehbach, M.; Sluyters, J. H. *The analysis of electrode impedances complicated by the presence of a constant phase element*. **Journal of Electroanalytical Chemistry and Interfacial Electrochemistry** 176(1–2), 275–295 (1984). DOI: 10.1016/S0022-0728(84)80324-1.

[9] Jonscher, A. K. *The ‘universal’ dielectric response*. **Nature** 267, 673–679 (1977). DOI: 10.1038/267673a0.

[10] Barsoukov, E.; Macdonald, J. R. (eds.). *Impedance Spectroscopy: Theory, Experiment, and Applications*. 2nd ed., Wiley-Interscience (2005).

Notes / Placeholders to Fill

- Numeric fit parameters a , b , c and their temperature/processing dependence.
- Exact $n_{\max}$, s , N , β used for geometry; report how ρ is extracted.
- NRMSE and uncertainty propagation method.
- Definition of volume/mass normalization for energy and power densities.
- Branch/minor-loop protocol for ferroelectric C-V extraction.

Citizen Gardens © 2025 CC-NC-ND 4.0