

Media Scheduler

status active

Media Scheduler

Table of Contents

- [About](#)
- [Getting Started](#)
- [Installation](#)
- [Circuit](#)
- [Web App](#)
- [Usage](#)
- [List Of Components](#)
- [Built Using](#)
- [DemoVideo](#)
- [Authors](#)

About

This repo contains

- Firmware
- Circuit
- Detailed instructions

for Media Scheduler.

Getting Started

These instructions will get you a copy of the project up and running on your system. The flowchart of the system is given below:

Prerequisites

Things you need to install the FW.


- 1x Raspberry Pi 3B or 4

Installation

A step by step series that tell you how to get the Firmware and Backend running

Raspberry Pi Zero W Configuration

1. Download and install Raspberry Pi Imager from here <https://www.raspberrypi.com/software/>
2. Download "Raspberry Pi OS with desktop and recommended software" from here <https://www.raspberrypi.com/software/operating-systems/>
3. Then extract the downloaded image file using any extraction software like 7-zip <https://www.7-zip.org/>
4. Put a 16 GB SD Card in your Laptop/PC.
5. Open the Raspberry Pi imager, Click on "Choose OS" button and scroll down to select "Use Custom" as shown below



6. Then select the extracted image file.
7. In the next step select your SD Card and then click on "Write" button to start the writing process.
8. That's it. It should be flashed within a few minutes.
9. Download this repository and open the configFiles folder of the repository and open wpasupplicant.conf file and add your WiFi credentials in it.

Firmware Configuration

10. Once done, remove the SD Card and re-insert it into your PC/Laptop and then open the "boot" volume. Copy the files of "configFiles" folder here in the "boot" volume. Also create an empty file named "ssh" in the "boot" volume if not already present.

11. Do the same steps for 2nd SD Card as well.
12. Then put the SD Card in the first Raspberry Pi Zero and power it on.
13. Then SSH into the Raspberry Pi which you can use using the command `ssh pi@raspberrypi.local`
14. Once you are logged in, execute the following command

Auto Firmware Installer

To install and Run Media Scheduler Automatically just run the following command on your Raspberry Pi terminal

- `curl -sSL https://raw.githubusercontent.com/Nauman3S/Media-Scheduler/main/Firmware/starter.sh | bash`

After the installer completes the process restart your raspberry pi.

Disabling Raspberry Pi Boot Messages

1. Execute the following command

- `sudo nano /boot/cmdline.txt`

2. Change the console from tty1 to

`console=tty3`

3. Add this to the end of the line. `loglevel=0` removes most of the messages from the boot and put the following line at the end

`quiet splash loglevel=0 logo.nologo vt.global_cursor_default=0`

4. Press CTRL+O and CTRL+X to save and exit.

5. `sudo nano /etc/rc.local`

6. Add this before 'exit 0':

7. Press CTRL+O and CTRL+X to save and exit.

- `dmesg --console-off`

7. Execute the following command

- `sudo update-rc.d motd remove`

8. `sudo nano /boot/config.txt`

9. Add the following line at the end of the file

- `disable_splash=1`


10. Press CTRL+O and CTRL+X to save and exit.

11. `sudo nano /boot/cmdline.txt`

12. Add below line to end of file

- `logo.nologo`

13. Press CTRL+O and CTRL+X to save and exit.



Components Pin Connection Details


Components pin connection details

Console Button

Console Button to open or close console

Button Pins	Raspberry Pi
PIN 1	GND
PIN 2	23

WebApp



Dashboard can be accessed using the credentials given below

- <https://mediascheduler-frontend.production.rehanshakir.com/>
- Email Address: admin@mediascheduler.com
- Passowrd: admin

Dashboard Features

- Upload Pictures and set their display time and display duration.
- Upload videos and set their display time.
- Upload default picture which will be displayed when nothing else is running.(uploading a picture with name default.png will make it a default picture)

Backend Link: <https://mediascheduler-backend.production.rehanshakir.com/api/fields>

Usage

1. Upload the code to your Raspberry Pi as mentioned in the [Installation](#) section above.
2. Now connect the circuit components as mentioned in [Circuit](#) section above.
3. Power on your raspberry pi.
4. Use the webapp dashboard to upload new videos/pictures.
5. To set a default picture, upload a image file named **default.png** and it will be automatically used as a default image.
6. Press the push button to open the terminal.

List of Components

Following components are used to make this project

1. Raspberry Pi 4 Kit [Raspberry Pi 4 Kit](#)
2. Generic Push buttons

Built Using

- [Python](#) - Programming Language
- [NodeJS](#) - JavaScript Framework for WebApp Backend
- [ReactJS](#) - JavaScript Framework for WebApp FrontEnd
- [MongoDB](#) - NoSQL Database for WebApp

Demo Video

[Media Scheduler Demo](#) - Media Scheduler Demo Video

Authors

- [@Nauman3S](#) - Development and Deployment