

Image Enhancement in the Frequency Domain

Subtopic 1: Introduction to Fourier Transform and Frequency Domain

Lecture by
Kiran Bagale

SXC, Maitighar Campus

December, 2025

Outline - Unit 3: Subtopic 1

- 1 Introduction to Frequency Domain
- 2 1-D Continuous Fourier Transform
- 3 2-D Continuous Fourier Transform
- 4 1-D Discrete Fourier Transform
- 5 2-D Discrete Fourier Transform
- 6 Comparison of Transform Types
- 7 Key Properties of Fourier Transforms
- 8 Applications in Image Processing
- 9 References

Why Frequency Domain Analysis?

- **Spatial Domain:** Direct manipulation of pixel values
 - Limited in understanding image structure
 - Some operations are complex to implement
- **Frequency Domain:** Representation of image in terms of frequency components
 - Provides deeper insight into image properties
 - Efficient implementation of many operations
 - Better understanding of image content
- **Key Advantage:** Convolution in spatial domain = Multiplication in frequency domain

Fourier Transform: Basic Concept

- **Core Idea:** Any periodic function can be represented as a sum of sinusoids with different frequencies, amplitudes, and phases
- **Fourier Series:** For periodic functions

$$f(x) = \frac{a_0}{2} + \sum_{n=1}^{\infty} [a_n \cos(nx) + b_n \sin(nx)] \quad (1)$$

- **Fourier Transform:** Extension to non-periodic functions
- **Mathematical Basis:** Based on the principle that complex signals can be decomposed into simpler sinusoidal components

1-D Continuous Fourier Transform (CFT)

Definition and Formula

- **Forward Transform:**

$$F(u) = \int_{-\infty}^{\infty} f(x) e^{-j2\pi ux} dx \quad (2)$$

where u is the frequency variable

- **Inverse Transform:**

$$f(x) = \int_{-\infty}^{\infty} F(u) e^{j2\pi ux} du \quad (3)$$

- $j = \sqrt{-1}$ (imaginary unit)
- $F(u)$ is a complex function: $F(u) = |F(u)|e^{j\phi(u)}$

Components of 1-D CFT

- **Magnitude Spectrum:**

$$|F(u)| = \sqrt{\text{Re}^2(F(u)) + \text{Im}^2(F(u))} \quad (4)$$

Represents the amplitude of each frequency component

- **Phase Spectrum:**

$$\phi(u) = \arctan\left(\frac{\text{Im}(F(u))}{\text{Re}(F(u))}\right) \quad (5)$$

Represents the phase angle of each frequency component

- **Power Spectrum:**

$$P(u) = |F(u)|^2 \quad (6)$$

Represents the power distribution across frequencies

2-D Continuous Fourier Transform (2-D CFT)

Extension to Two Dimensions

- **Forward Transform:**

$$F(u, v) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(x, y) e^{-j2\pi(ux+vy)} dx dy \quad (7)$$

where (u, v) are frequency variables in 2-D space

- **Inverse Transform:**

$$f(x, y) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} F(u, v) e^{j2\pi(ux+vy)} du dv \quad (8)$$

- Essential for analyzing **images** (2-D signals)

Properties of 2-D CFT

- **Separability:**

$$F(u, v) = \left[\int_{-\infty}^{\infty} f(x, y) e^{-j2\pi ux} dx \right] e^{-j2\pi vy} dy \quad (9)$$

2-D transform can be computed as successive 1-D transforms

- **Magnitude and Phase:**

$$|F(u, v)| = \sqrt{\text{Re}^2(F(u, v)) + \text{Im}^2(F(u, v))} \quad (10)$$

$$\phi(u, v) = \arctan \left(\frac{\text{Im}(F(u, v))}{\text{Re}(F(u, v))} \right) \quad (11)$$

- **Symmetry:** For real-valued images, $F(u, v) = F^*(-u, -v)$ (Hermitian symmetry)

1-D Discrete Fourier Transform (DFT)

Digital Implementation

- **Motivation:** Continuous transforms cannot be directly computed on digital devices

- **Forward DFT:**

$$F(u) = \sum_{x=0}^{N-1} f(x) e^{-j2\pi ux/N}, \quad u = 0, 1, \dots, N-1 \quad (12)$$

- **Inverse DFT:**

$$f(x) = \frac{1}{N} \sum_{u=0}^{N-1} F(u) e^{j2\pi ux/N}, \quad x = 0, 1, \dots, N-1 \quad (13)$$

- N is the number of samples (must be finite)

DFT Properties and Characteristics

- **Periodicity:**

$$F(u + N) = F(u), \quad f(x + N) = f(x) \quad (14)$$

Both time and frequency domains are periodic

- **Computational Complexity:** $O(N^2)$ for direct computation

- **Fast Fourier Transform (FFT):** Efficient algorithm reducing complexity to $O(N \log N)$

- Requires $N = 2^k$ (power of 2)
- Practical for real applications

- **Output Characteristics:**

- $F(0)$ is the DC component (average value)
- Conjugate symmetry for real inputs

2-D Discrete Fourier Transform (2-D DFT)

Image Domain Transformation

- **Forward 2-D DFT:**

$$F(u, v) = \sum_{x=0}^{M-1} \sum_{y=0}^{N-1} f(x, y) e^{-j2\pi(ux/M + vy/N)} \quad (15)$$

where $u = 0, 1, \dots, M-1$ and $v = 0, 1, \dots, N-1$

- **Inverse 2-D DFT:**

$$f(x, y) = \frac{1}{MN} \sum_{u=0}^{M-1} \sum_{v=0}^{N-1} F(u, v) e^{j2\pi(ux/M + vy/N)} \quad (16)$$

- $M \times N$ is the image size

2-D DFT: Image Interpretation

- **Frequency Representation:**

- Low frequencies: Gradual variations (overall image structure)
- High frequencies: Rapid variations (edges and details)

- **Magnitude Spectrum Characteristics:**

- **Center:** DC component (average brightness)
- **Near-center:** Low frequency components
- **Edges:** High frequency components

- **Separability Property:**

$$F(u, v) = \left[\sum_{x=0}^{M-1} f(x, y) e^{-j2\pi ux/M} \right] e^{-j2\pi vy/N} \quad (17)$$

Can compute using successive 1-D DFTs

Practical Considerations for 2-D DFT

- **Computational Efficiency:**

- Direct 2-D DFT: $O(M^2 N^2)$ operations
- Using 2-D FFT: $O(MN \log(MN))$ operations
- Separability: Reduces to $O(MN(\log M + \log N))$

- **Image Size Requirements:**

- FFT most efficient when $M = 2^p$ and $N = 2^q$
- Padding with zeros if necessary

- **Visualization:**

- Display $\log(1 + |F(u, v)|)$ for better visualization
- Shift zero frequency to center: `fftshift`

Summary: Transform Comparison

Aspect	1-D CFT	2-D CFT	1-D DFT	2-D DFT
Domain	Continuous	Continuous	Discrete	Discrete
Input	1-D signal	2-D signal	1-D sequence	2-D matrix
Output	Continuous	Continuous	Periodic seq.	Periodic matrix
Computation	Analytical	Analytical	Algorithmic	Algorithmic
Complexity	N/A	N/A	$O(N^2)$	$O(M^2 N^2)$
FFT	N/A	N/A	$O(N \log N)$	$O(MN \log MN)$
Practical Use	Theory	Theory	Digital signal	Images

- CFT: Theoretical foundation
- DFT: Practical digital implementation
- 2-D DFT: Essential for image processing applications

Important Properties

- **Linearity:** $\mathcal{F}\{af(x) + bg(x)\} = aF(u) + bG(u)$
- **Convolution Theorem:** $\mathcal{F}\{f(x) * g(x)\} = F(u) \cdot G(u)$
 - Spatial convolution = Frequency multiplication
 - Fundamental for filtering
- **Parseval's Theorem:** Energy is conserved between domains

$$\sum_{x=0}^{N-1} |f(x)|^2 = \frac{1}{N} \sum_{u=0}^{N-1} |F(u)|^2 \quad (18)$$

- **Shift Property:** Spatial shift $\Leftrightarrow$ Phase change in frequency domain

Applications of Frequency Domain Analysis

- **Image Filtering:**

- Low-pass filtering (smoothing, blur removal)
- High-pass filtering (edge detection)
- Band-pass filtering (feature enhancement)

- **Image Enhancement:**

- Contrast stretching
- Noise reduction
- Deblurring

- **Image Analysis:**

- Pattern recognition
- Feature extraction
- Image compression

Textbook and Reference Materials

Recommended Reading

- **Textbook:**

- Rafael C. Gonzalez and Richard E. Woods, *Digital Image Processing*, Pearson Edition, Latest Edition.

- **Reference Books:**

- I. Pitas, *Digital Image Processing Algorithms*, Prentice Hall, Latest Edition.
- A. K. Jain, *Fundamentals of Digital Image Processing*, Prentice Hall of India Pvt. Ltd., Latest Edition.
- K. Castleman, *Digital Image Processing*, Prentice Hall of India Pvt. Ltd., Latest Edition.

Key Takeaways

- **Frequency Domain:** Complementary view to spatial domain
- **Fourier Transform:** Mathematical tool for frequency analysis
- **Continuous vs. Discrete:** Theory vs. practice
- **1-D vs. 2-D:** Generalization from signals to images
- **Practical Implementation:** FFT enables efficient computation
- **Next Steps:** Frequency domain filtering and image enhancement

Questions?