在具有FC/FCoE組態的AIX主機上轉換SAN開機LUN

ONTAP 7-Mode Transition

NetApp
May 03, 2022

This PDF was generated from https://docs.netapp.com/zh-tw/ontap-7mode-transition/san-host/task_preparing_to_transition_san_boot_luns_on_aix_hosts_with_fc_fcoe_configurations.html on May 03, 2022. Always check docs.netapp.com for the latest.

目錄

在具有FC/FCoE組態的AIX主機上轉換SAN開機LUN 1
準備在具有FC/FCoE組態的AIX主機上轉換SAN開機LUN 1
在轉換複本型轉換的轉換階段之前、測試AIX主機上轉換後的SAN開機LUN 1
準備轉換具有FC/FCoE組態的AIX主機時、進行轉換階段的準備工作。 2
在轉換後、從具有FC/FCoE組態的AIX主機上的SAN開機LUN開機 2

在具有FC/FCoE組態的AIX主機上轉換SAN開機LUN

如果您使用Data ONTAP 7-Mode Transition Tool（7MTT）、將具有FC或FCoE組態的AIX主機上的SAN開機LUN從以7-Mode運作的VMware移轉至叢集Data ONTAP 式VMware、則必須在轉換前後執行特定步驟、以修正主機上的轉換問題。

準備在具有FC/FCoE組態的AIX主機上轉換SAN開機LUN

在具有FC/FCoE組態的AIX主機上轉換SAN開機LUN之前、您必須記錄安裝AIX的7-Mode LUN名稱、以及該LUN的SCSI裝置名稱。

1. 從以7-Mode控制器運作的支援主控台Data ONTAP 、識別安裝AIX 7.1和AIX 6.1作業系統的7-Mode LUN名稱：

   ’* LUN show*’

2. 取得主機上LUN的SCSI裝置名稱：

   「* sanlun LUN show*」

   在以下範例中、轉換LUN為「LUN_sanboot_FAS3170_aix04」、此LUN的SCSI裝置為「hdisk0」。

```
[04:02 AM root@822-aix03p1/]: sanlun lun show
controller[7mode]/
vserver[Cmode] lun-pathname
-----------------------------------------------------------------------
fas3170-aix04  /vol/vol_fas3170_aix04_sanboot/lun_sanboot_fas3170_aix04
kit            /vol/kit/kit_0
kit            /vol/kit/kit_0
filename    adapter protocol    size        mode
-------------------------------------
hdisk0     fcs0       FCP      100g   7
hdisk1     fcs0       FCP      5g       C
hdisk2     fcs0       FCP      5g       C
```

在轉換複本型轉換的轉換階段之前、測試AIX主機上轉換後的SAN開機LUN

如果您使用7-Mode Transition Tool（7MTT）2.2或更新版本、Data ONTAP 以及更新版本的版本號、以轉換7-Mode Windows主機LUN、您可以在Data ONTAP 轉換階段之前測試轉換的叢集式LUN、以確認它們是否正常運作。

您的7-Mode LUN必須已準備好進行轉換。

您應該維持測試主機與來源主機之間的硬體同位元、而且應該在測試主機上執行下列步驟。

在Data ONTAP 測試期間、叢集式的LUN會處於讀取/寫入模式。當測試完成且您正在準備轉換階段時、它們會轉換成唯讀模式。

步驟

1. 完成基礎資料複本之後、請在7MTT使用者介面（UI）中選取*測試模式*。
2. 在7MTT UI中、按一下*套用組態*。
3. 在測試主機上、登入硬體管理主控台、然後在* SMS*功能表中開機主機。
4. 主機開機後、請變更IP位址和主機名稱。
5. 驗證叢集Data ONTAP 式的LUN是否存在：

   「* sanlun LUN show*」

6. 視需要執行測試。
7. 關閉測試主機：

   h*關機

8. 在7MTT UI中、按一下*完成測試*。

如果您的叢集Data ONTAP 式支援LUN要重新對應至來源主機、您必須準備好來源主機以進行轉換階段。如果您的叢集Data ONTAP 式支援LUN仍要對應至測試主機、則測試主機不需要執行其他步驟。

準備轉換具有**FC/FCoE**組態的**AIX**主機時、進行轉換階段的準備工作。

在進入具有FC或FCoE組態之AIX主機的轉換階段之前、您必須執行特定步驟。

必須Data ONTAP 建立與叢集式支援節點的網路連線和分區。

對於複製型轉換、請在完成7-Mode Transition Tool中的Storage Cutover作業之後、執行這些步驟。AIX主機不支援無複製轉換。

步驟

1. 關閉主機：

   h*關機

在轉換後、從具有**FC/FCoE**組態的**AIX**主機上的**SAN**開機**LUN**開機

在具有FC或FCoE組態的AIX主機上轉換SAN開機LUN之後、您必須執行特定步驟、從SAN開機LUN開機主機。

對於複製型轉換、您必須在完成7-Mode Transition Tool中的Storage Cutover作業之後、執行這些步驟。AIX主機

不支援無複製轉換。

1. 登入硬體管理主控台（HMC）、然後在SMS功能表中啟動主機。
2. 選取主機。
3. 選擇*作業*>*啟動*>*設定檔*。
4. 按一下「進階」索引標籤。
5. 選取「* SMS*」、然後按一下「確定」。
6. 在SMS主功能表中、輸入「* 5 」以選取「 5」。選取開機選項*。
7. 輸入「* 1*」以選取「* 1」。選取「安裝/開機裝置*」。
8. 輸入「* 5 」以選取「 5」。列出所有裝置*。
9. 輸入ONTAP 您要開機的SAN開機LUN裝置編號。

   在下列範例中、所需的LUN為選項5：

```
Select Device
Device  Current     Device
Number      Position    Name
1.   -   PCIe2 4-port 1GbE Adapter
     ( loc=U78CB.001.WZS062Y-P1-C12-T1 )
2.   -   PCIe2 4-port 1GbE Adapter
     ( loc=U78CB.001.WZS062Y-P1-C12-T2 )
3.   -   PCIe2 4-port 1GbE Adapter
     ( loc=U78CB.001.WZS062Y-P1-C12-T3 )
4.   -   PCIe2 4-port 1GbE Adapter
     ( loc=U78CB.001.WZS062Y-P1-C12-T4 )
5.   -   107 GB     FC Harddisk, part=2 (AIX 7.1.0)
     ( loc=U78CB.001.WZS062Y-P1-C7-T1-W232200a09830ca3a-
L0000000000000000 )
6.   -   107 GB     FC Harddisk, part=2 (AIX 7.1.0)
     ( loc=U78CB.001.WZS062Y-P1-C7-T2-W232200a09830ca3a-
L0000000000000000 )
---------------------------------------------------------------
Navigation keys:
M = return to Main Menu  N = Next page of list
ESC key = return to previous screen   X = eXit System Management
Services
---------------------------------------------------------------
Type menu item number and press Enter or select Navigation keys: 5
```

10. 輸入「* 2 」以選取「 2」。正常模式Boot*。
11. 輸入「* 1*」結束SMS功能表。
12. 等待作業系統開機。

13. 顯示LUN路徑名稱：

    「* sanlun LUN show*」

    模式欄中的輸出應從「7」改為「C」。

Copyright Information

Copyright © 2022 NetApp, Inc. All rights reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means-graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system- without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

RESTRICTED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.277-7103 (October 1988) and FAR 52-227-19 (June 1987).

Trademark Information

NETAPP, the NETAPP logo, and the marks listed at http://www.netapp.com/TM are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.