# Migration tests

ONTAP

NetApp
February 24, 2022

This PDF was generated from https://docs.netapp.com/us-en/ontap-fli/san-migration/concept_migration_tests.html on February 24, 2022. Always check docs.netapp.com for the latest.

# Table of Contents

Migration tests . . . . . 1
Migration tests . . . . . 1
Test migration example using Hitachi AMS2100 . . . . . 1

# Migration tests

## Migration tests

You should perform one or more test migrations in order to verify that your arrays, switches, and hosts are properly configured and also in order to get several samples that can be extrapolated from to determine migration durations and levels of effort.

## Test migration example using Hitachi AMS2100

The following is an example test migration using a Hitachi AMS2100 as the foreign array. Depending on the arrays involved, host operating systems, and other variables, your steps may be different.

You can use the following example as a general guide to the steps required to perform test migrations. NetApp recommends performing test migrations as early as possible in order to find and have as much time as possible to resolve any issues brought to light by the tests. A test migration should be performed on all combinations of source and destination arrays before proceeding with the production migrations.

To perform a test migration, complete the following steps:

**Steps**

1. Create a 2 GB test LUN on the source array.
2. Log in to Hitachi Storage Navigator Modular as system.
3. Select AMS 2100 array.
4. Click **Show and Configure Array**.
5. Log in using root.
6. Expand **Groups** and select **Logical Units**.
7. Select **Create LU** to create the test LUN.
8. Create a test LUN of 2 GB.
9. Click **OK**.
10. Skip the LUN assignment here and proceed by clicking **Close**.
11. Verify LUN 0026 is created.
12. Expand **Groups**and select **Logical Units**.
13. Select **Host Groups** to map the test LUN to the cDOT_FLI host group.
14. Select host group cDOT_FLI created in the previous step and click **Edit Host Group**.
15. Choose the ports for the host group. In this example we choose 0a, 0e, 1a, 1e. Select the Forced Set to All Selected Ports option.




16. Click **Logical Units** and add the test LUN LUN0026.
17. Click **OK** to map the LUN.
18. Select **Yes, I Have Read the Above Warning and Want to Edit Host Group** and click **Confirm**.
19. Verify host group creation and click **Close**.
20. Verify the test LUN and mapping from the source storage to destination storage and perform Foreign LUN Import (FLI) import.
21. Log in to the ONTAP storage through SSH using admin user.
22. Change the mode to Advanced. `DataMig-cmode::> set -privilege advanced`
23. Enter y when asked if you want to continue with advanced commands.
24. Discover the source array on ONTAP. Wait for a few minutes and retry to detect the source array.`storage array show`
    a. When the storage array is discovered for the first time, ONTAP might not show the array by discovering automatically. Use the following instructions to reset the switch port where ONTAP initiator ports are connected.

       For example, the DataMig-cmode cluster initiator ports 0a and 0b of ONTAP are connected to Cisco ports 4/9 and 4/11. To reset port 4/9 on the Cisco switch:

       ```
       conf t
       interface fc4/9
       shutdown
       no shutdown
       exit
       exit
       ```

       Resetting one port is usually enough. Check the array list and LUN paths after resetting one port.

25. Verify the source array is discovered through all the initiator ports: `storage array config show -array-name HITACHI_DF600F_1`

```
             LUN   LUN
Node         Group Count     Array Name       Array Target Port
Initiator
------------ ----- ----- ----------------------------
-----------------------
DataMig-cmode-01 0     1    HITACHI_DF600F_1     50060e801046b960
0a
                                                 50060e801046b964
0b
                                                 50060e801046b968
0a
                                                 50060e801046b96c
0b
DataMig-cmode-02 0     1    HITACHI_DF600F_1     50060e801046b960
0a
                                                 50060e801046b964
0b
                                                 50060e801046b968
0a
                                                 50060e801046b96c
0b
```

26. List the test LUN mapped from Hitachi storage and verify the disk properties and paths: `storage disk show -array-name HITACHI_DF600F_1 -instance`

```
                   Disk: HIT-1.1
        Container Type: unassigned
            Owner/Home: -  / -
               DR Home: -
    Stack ID/Shelf/Bay: -  / -  / -
                   LUN: 0
                 Array: HITACHI_DF600F_1
                Vendor: HITACHI
                 Model: DF600F
         Serial Number: 83017542001A
                   UID:
48495441:43484920:38333031:37353432:30303236:00000000:00000000:00000000:
00000000:00000000
                   BPS: 512
         Physical Size: -
              Position: present
Checksum Compatibility: block
```

```
             Aggregate: -
                  Plex: -
Paths:
                                LUN  Initiator Side        Target Side
Link
Controller         Initiator     ID  Switch Port           Switch Port
Acc Use  Target Port                TPGN    Speed      I/O KB/s
IOPS
------------------ ---------  -----  --------------------
--------------------  --- ---  -----------------------  ------  -------
------------  ------------
DataMig-cmode-01   0a             0  DM-Cisco9506-1:4-9    DM-Cisco9506-
1:2-24   AO  INU  50060e801046b968              2   2 Gb/S             0
0
DataMig-cmode-01   0b             0  DM-Cisco9506-2:4-9    DM-Cisco9506-
2:2-24   AO  INU  50060e801046b96c              2   2 Gb/S             0
0
DataMig-cmode-01   0b             0  DM-Cisco9506-2:4-9    DM-Cisco9506-
2:1-14   AO  INU  50060e801046b964              1   2 Gb/S             0
0
DataMig-cmode-01   0a             0  DM-Cisco9506-1:4-9    DM-Cisco9506-
1:1-14   AO  INU  50060e801046b960              1   2 Gb/S             0
0
DataMig-cmode-02   0a             0  DM-Cisco9506-1:4-11   DM-Cisco9506-
1:2-24   AO  INU  50060e801046b968              2   2 Gb/S             0
0
DataMig-cmode-02   0b             0  DM-Cisco9506-2:4-11   DM-Cisco9506-
2:2-24   AO  INU  50060e801046b96c              2   2 Gb/S             0
0
DataMig-cmode-02   0b             0  DM-Cisco9506-2:4-11   DM-Cisco9506-
2:1-14   AO  INU  50060e801046b964              1   2 Gb/S             0
0
DataMig-cmode-02   0a             0  DM-Cisco9506-1:4-11   DM-Cisco9506-
1:1-14   AO  INU  50060e801046b960              1   2 Gb/S             0
0

Errors:
-

DataMig-cmode::*>
```

27. Mark the source LUN as foreign using the serial number: `storage disk set-foreign-lun { -serial-number 83017542001A } -is-foreign true`
28. Verify the source LUN is marked as foreign: `storage disk show -array-name HITACHI_DF600F_1`
29. List all foreign arrays and their serial numbers: `storage disk show -container-type foreign`

`-fields serial-number`

> The LUN create command detects the size and alignment based on partition offset and creates the LUN accordingly with the foreign-disk argument.

30. Create a destination volume: `vol create -vserver datamig flivol aggr1 -size 10g`
31. Create a test LUN using a foreign LUN: `lun create -vserver datamig -path /vol/flivol/testlun1 -ostype linux -foreign-disk 83017542001A`
32. List the test LUN and verify the size of the LUN with the source LUN: `lun show`

> For FLI offline migration, the LUN must be online to map it to an igroup and then must be offline before creating the LUN import relationship.

33. Create test igroup of protocol FCP without adding any initiators: `lun igroup create -vserver datamig -igroup testig1 -protocol fcp -ostype linux`
34. Map the test LUN to the test igroup: `lun map -vserver datamig -path /vol/flivol/testlun1 -igroup testig1`
35. Offline the test LUN: `lun offline -vserver datamig -path /vol/flivol/testlun1`
36. Create import relationship with test LUN and foreign LUN: `lun import create -vserver datamig -path /vol/flivol/testlun1 -foreign-disk 83017542001A`
37. Start the migration (import): `lun import start -vserver datamig -path /vol/flivol/testlun1`
38. Monitor the import progress: `lun import show -vserver datamig -path /vol/flivol/testlun1`
39. Check the import job is completed successfully: `lun import show -vserver datamig -path /vol/flivol/testlun1`

```
vserver foreign-disk   path                 operation admin operational
percent
                                          in progress state state
complete
---------------------------------------------------------------------------
-------
datamig 83017542001A   /vol/flivol/testlun1
                                             import    started
                                                             completed
100
```

40. Start the verify job to compare source and destination LUNs. Monitor the verify progress: `lun import verify start -vserver datamig -path /vol/flivol/testlun1`

```
DataMig-cmode::*> lun import show -vserver datamig -path
/vol/flivol/testlun1
vserver foreign-disk   path                operation admin operational
percent
                                         in progress state state
complete
---------------------------------------------------------------------
-------
datamig 83017542001A   /vol/flivol/testlun1
                                          verify    started
                                                        in_progress
44
```

41. Check the verify job is complete without any errors: `lun import show -vserver datamig -path /vol/flivol/testlun1`

```
vserver foreign-disk   path                operation admin operational
percent
                                         in progress state state
complete
---------------------------------------------------------------------
-------
datamig 83017542001A   /vol/flivol/testlun1
                                          verify    started
                                                        completed
100
```

42. Delete the import relationship to remove the migration job: `lun import delete -vserver datamig -path /vol/flivol/testlun1``lun import show -vserver datamig -path /vol/flivol/testlun1`
43. Unmap the test LUN from the test igroup: `lun unmap -vserver datamig -path /vol/flivol/testlun1 -igroup testig1`
44. Online the test LUN: `lun online -vserver datamig -path /vol/flivol/testlun1`
45. Mark the foreign LUN attribute to false: `storage disk modify { -serial-number 83017542001A } -is-foreign false`

> Do not remove the host group created on source storage with ONTAP initiator ports. The same host group is reused during migrations from that source array.

46. Remove test LUN from source storage.
    a. Log in to Hitachi Storage Navigator Modular as a system.
    b. Select AMS 2100 array and click **Show and Configure Array**.
    c. Log in using root.

d. Select **Groups**, then select **Host Groups**.
e. Select *cDOT_FLI Igroup* and click **Edit Host Group**.
f. In the **Edit Host Group** window, select all target ports chosen to map the test LUN and select **Forced Set to All Selected Ports**.
g. Select the **Logical Units** tab.
h. Select the test LUN from the **Assigned Logical Units** window.
i. Select **Remove** to remove the LUN mapping.
j. Click OK.
k. Do not remove the host group and continue deleting the test LUN.
l. Select Logical Units.
m. Select the test LUN created in the previous step (LUN0026).
n. Click **Delete LUN**.
o. Click **Confirm** to delete the test LUN.

47. Delete the test LUN on the destination storage.
    a. Log in to the ONTAP storage through SSH using admin user.
    b. Offline the test LUN on the NetApp storage system: `lun offline -vserver datamig -path /vol/flivol/testlun1`

    > Make sure you do not select another host LUN.

    c. Destroy the test LUN on the NetApp storage system: `lun destroy -vserver datamig -path /vol/flivol/testlun1`
    d. Offline the test volume on the NetApp storage system: `vol offline -vserver datamig -volume flivol`
    e. Destroy the test volume on the NetApp storage system: `vol destroy -vserver datamig -volume flivol`

**Copyright Information**

Copyright © 2022 NetApp, Inc. All rights reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means-graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system- without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

RESTRICTED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.277-7103 (October 1988) and FAR 52-227-19 (June 1987).

**Trademark Information**

NETAPP, the NETAPP logo, and the marks listed at http://www.netapp.com/TM are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.