

FLEX-DBS: a flexible wireless platform for bilateral constant-current deep brain stimulation in freely moving rodents

Robert D. Graham^{1,*}, Meaghan C. Creed¹, Matt Gaidica²

¹Department of Anesthesiology, Washington University School of Medicine, St. Louis, MO, USA

²Department of Neuroscience, Washington University School of Medicine, St. Louis, MO, USA

*Corresponding author: Robert D. Graham, robertg@wustl.edu

Running title: Wireless bilateral DBS for freely moving rodents

Abstract

Background: Preclinical deep brain stimulation (DBS) in rodents is central to understanding how DBS works, but most rodent DBS is delivered through a tether, which constrains behavior, home-cage experiments and uninterrupted stimulation. Most long-runtime wireless mouse stimulators achieve their runtimes by setting stimulation parameters before or around implantation and operating from supplies of about 3 V.

New method: FLEX-DBS (Flexible Deep Brain Stimulation) is a head-mounted, battery-powered stimulator that delivers bilateral constant-current stimulation from improved Howland current pumps on ± 5 V rails. Amplitude, pulse width and frequency are programmable in continuous and burst modes from an iOS application over Bluetooth Low Energy, and stimulation continues autonomously after the phone disconnects. The device measures $19.5 \times 22.5 \times 8.72$ mm, weighs 3.71 g in operation and runs on two size-13 zinc-air cells, which are exchanged by briefly detaching the device, pausing stimulation only for the exchange.

Results: Into a 1 k Ω bench load, delivered current increased approximately linearly with the amplitude setting and was repeatable from pulse to pulse, with an asymmetric biphasic waveform whose recovery phase ran at about one fifth of the stimulating amplitude. Battery current was 1.47–1.89 mA in standby and 3.15–3.42 mA during stimulation at amplitude settings of 60–400 μ A, giving a projected three days of continuous stimulation per pair of cells. Firmware v0.5 left a net charge of 26–35 % of the stimulating-phase charge per pulse into 1 k Ω . Into 47 k Ω , within the in-vivo load range, stimulating current was compliance-limited at 93 μ A. Pulse-derived estimates of the effective load presented by five implanted platinum electrodes in three mice had weekly means of 43–54 k Ω over eight weeks (32–80 k Ω across individual sessions), placing the maximum regulated current near 90 μ A (81–101 μ A at the weekly means). Analysis of the current-pump network bounds load-dependent current error at 3–8 % for these loads.

Comparison with existing methods: Among the published wireless rodent stimulators compared here, several offer some of these capabilities, but none combines bilateral constant-current output, real-time wireless control that continues as autonomous stimulation after disconnect, and both continuous and burst modes; FLEX-DBS does so at the cost of runtime measured in days rather than weeks.

Conclusions: FLEX-DBS is designed for untethered DBS experiments in which parameters must be set, changed and verified at the cage. Its measured power consumption permits a projected three days of continuous operation per cell pair; firmware v0.5 requires improved charge balancing before prolonged in-vivo stimulation. The electrode load, rather than the programmable range, sets the usable stimulation amplitude in vivo.

Keywords: deep brain stimulation; wireless stimulator; constant current; mouse; Bluetooth Low Energy; electrode impedance

1. Introduction

Deep brain stimulation (DBS) is a surgical therapy in which electrical current is delivered to discrete brain nuclei through implanted electrodes (Lozano et al., 2019). Although it is established primarily as a treatment for movement disorders, DBS is increasingly applied to psychiatric indications, chronic pain, neurodegenerative disorders and developmental disorders (Lozano et al., 2019; Krauss et al., 2021; Knotkova et al., 2021). Despite this growing adoption, the neural mechanisms underlying the therapeutic effects of DBS remain poorly understood, which limits both the rational optimization of stimulation parameters and patient selection (Murphy et al., 2021). Preclinical research in rodents therefore has an important role in determining the behavioral, circuit and synaptic mechanisms through which DBS acts (Creed et al., 2015; Creed, 2018).

Preclinical DBS is commonly delivered with the rodent physically tethered to an external pulse generator (Ewing et al., 2013), which constrains experimental design in several ways. A tether restricts the animal's movement and the environments in which it can be tested (Jiang et al., 2017); its measurable effects on stress markers and sleep can be small (Aulehner et al., 2022), but the restriction itself remains. These consequences complicate or prevent behavioral assays that depend on unconstrained motor behavior, such as spontaneous pain behaviors, movement-disorder phenotypes and social interaction, and so limit the translational relevance of behavioral observations. Tethering is also difficult to implement in the home cage, so stimulation is usually delivered in dedicated apparatus such as open-field chambers, which can itself alter naturalistic behavior. Together with the cost of conventional stimulators, these constraints limit the throughput and statistical power of preclinical DBS studies (Ewing et al., 2013).

Tethering also limits the timescales over which DBS can be studied. Clinically, DBS is delivered continuously for months to years, and its efficacy can wane over time for reasons that remain unclear (Fasano and Helmich, 2019). Some effects of DBS also develop over longer periods than the acute motor effects that dominate preclinical work: pallidal DBS for dystonia produces a delayed, progressive improvement over months (Kupsch et al., 2006), and in rats the behavioral effect of repeated subthalamic stimulation took several sessions to emerge (Aleksandrova et al., 2013). A wireless, battery-powered system for delivering sustained DBS in rodents would support mechanistic studies of why efficacy is lost with long-term stimulation and of indications in which therapeutic effects emerge slowly.

The few wireless rodent stimulators that exist were largely designed for chronic implantation. Most set the stimulation waveform and parameters before implantation or allow changes only through a near-field or cable programmer, which makes it difficult to change parameters during an experiment or to adjust them as the impedance of the electrode–tissue interface changes over the life of the implant. This is a critical limitation because stimulation parameters that produce a behavioral effect in one paradigm can be inert or even opposite in another, and the most informative preclinical studies have depended on varying frequency, amplitude and target within an experiment (Murphy et al., 2021). Low-frequency stimulation of the nucleus accumbens combined with pharmacology, for example, reversed cocaine-evoked synaptic plasticity where conventional high-frequency stimulation did not (Creed et al., 2015), and the effects of subthalamic stimulation on reward-related behavior, relevant to its motivational side effects, depend on stimulation parameters and task design (Vachez and Creed, 2020). Most published long-runtime mouse-scale systems also run from supplies of about 3 V, and several are single-channel.

An ideal preclinical DBS device would let the experimenter set and change parameters in a freely moving mouse in its home cage, deliver true constant current into electrodes whose impedance is uncertain and

changes after implantation, stimulate bilaterally, and support multiday experiments in which a battery exchange interrupts stimulation only briefly. Here we describe FLEX-DBS (Flexible Deep Brain Stimulation), a flexible wireless platform for bilateral constant-current deep brain stimulation in freely moving rodents. FLEX-DBS is a battery-powered, head-mounted device with ± 5 V compliance rails; programmable amplitude, pulse width and frequency; continuous and burst stimulation modes; and a Bluetooth Low Energy (BLE) interface to an iOS application. We present the design as one point in a general DBS architecture, characterize the electrode load it must drive in vivo, describe its electrical validation, and compare it with published wireless systems. The design gives compliance, current precision and real-time wireless control priority over the quiescent current needed for maintenance-free implantation. By combining untethered operation over hours to days with parameter flexibility and regulated current delivery, FLEX-DBS is designed to enable home-cage, social and extended-duration DBS experiments that are impractical with tethered stimulators or fixed-parameter implants, and to support systematic preclinical testing of stimulation paradigms for new clinical indications.

2. System architecture and implementation

2.1 General DBS architecture

Figure 1 presents the stimulator as a set of functional blocks, and Table 1 lists the FLEX-DBS implementation of each: energy source, power conditioning, timing and waveform generation, current regulation, polarity and output routing, charge recovery, supervisory logic, and wireless control. Published rodent stimulators differ mainly in how they implement these blocks, and those choices define the principal trade-offs: battery-direct (typically ~ 3 V) versus boosted rails, constant-current versus constant-voltage output, single versus split supplies, active versus passive charge recovery, real-time wireless control versus autonomous operation, and experimental flexibility versus power optimization for long-term implantation.

2.2 FLEX-DBS implementation

FLEX-DBS implements the general architecture with the choices listed in Table 1. The circuit schematic is provided as Supplementary material S1, and the firmware, application and communication protocol are released as open source (S2–S4); the main text describes function.

Table 1. FLEX-DBS implementation of each architectural block.

Block	FLEX-DBS implementation
Energy source	Two size-13 (PR48) zinc-air cells in series: 2.8 V nominal, ~ 280 mAh
Power conditioning	MAX17220 boost converter to +5 V; MAX1853 charge-pump inverter to -5 V; TPS709 LDO from +5 V to 3.3 V for logic
Timing and waveform	BGM220S microcontroller; pulse edges from a 32.768 kHz low-frequency timer; amplitude from a 16-bit DAC (AD5683) referenced to a 1.25 V precision reference (LT6656)
Current regulation	Two improved Howland current pumps (LT6020-1 dual precision op amp) on ± 5 V, one per hemisphere, sharing one DAC command
Polarity and routing	ADG1236 dual SPDT analog switch: each pump output either to its electrode or to ground; polarity reversal by stepping the DAC across the 1.25 V reference

Block	FLEX-DBS implementation
Charge recovery	Active, asymmetric: reverse-polarity phase at one-fifth amplitude for five times the pulse width
Supervisory logic	Same BGM220S; parameters held in non-volatile memory; battery voltage measured by the on-chip ADC
Wireless	BLE 5 with a custom text protocol; iOS application (MouseCap) for configuration; Hall-effect sensor (DRV5032) for magnet wake

Power tree. The two zinc-air cells feed the boost converter, which generates the +5 V rail. The negative rail is derived from +5 V by a charge-pump inverter that is enabled whenever +5 V is present. Logic runs from a 3.3 V linear regulator fed by +5 V. The output stage therefore has a 10 V supply span, and every subsystem, including the microcontroller and radio, sits downstream of the boost converter.

Current source. The 1.25 V reference serves as the analog mid-rail and as the external reference of the 16-bit DAC (external-reference variant, gain 2), so the DAC output spans 0–2.5 V centered on 1.25 V. Each Howland pump uses matched 10 k Ω input and feedback resistors on its inverting side and a 12 k Ω reference resistor balanced against a 10 k Ω resistor plus a 2 k Ω sense resistor on its non-inverting side, which satisfies the balance condition of the improved Howland topology (Texas Instruments, 2008). All network resistors are 0.1 % tolerance. At the reference voltage the commanded current is zero; stepping the DAC below the reference produces one polarity and stepping above it produces the other. The ideal transconductance is set by the 2 k Ω sense resistor, 0.5 mA/V, or 6.25 μ A per percent of full scale (625 μ A at 100 %). The application labels amplitude as a percentage and as the nominal current into a 1 k Ω load, $\sim$ 6 μ A per percent (300 μ A at 50 % and 600 μ A at 100 %).

Channels. The device has two output channels, one per hemisphere, each with its own Howland pump, switch and two-stage output filter (two 330 Ω series resistors, each followed by 470 pF to ground; 660 Ω in total per channel). The two channels share the DAC command, so they deliver the same amplitude and, in the current firmware, the same timing: both switches close and open together and both pumps see the same DAC steps. Independent timing per channel is possible with the existing hardware because each switch has its own control line; independent amplitude is not, because the DAC is shared. The four-pin electrode connector carries the two channel outputs and the ground return.

Pulse generation. Each pulse is sequenced by the microcontroller as a fixed chain: the op amp is brought out of shutdown and allowed 150 μ s to settle with the DAC at the zero-current reference; the switches then connect both pumps to their electrodes and are allowed 30 μ s; the DAC steps to the commanded amplitude I for the programmed pulse width P ; the DAC steps to the opposite polarity at $I/5$ for $5 \cdot P$; the DAC returns to the reference; the switches disconnect the electrodes; and the op amp is shut down. Switches change state only at zero commanded current, so the load is never connected to a saturated open-circuit current source and never disconnected mid-pulse, and pulse edges are produced by DAC steps into an already-connected load. The recovery phase is designed to carry the same charge as the stimulating phase; with firmware v0.5 the measured phases leave a net residual in the stimulating direction (Section 4.1). Because the op amp is enabled only around each pulse, its on-time is roughly 210μ s + $6 \cdot P$, about 10 % of the period for a 90 μ s setting at 130 Hz and up to about 50 % at 600 μ s.

Pulse and inter-pulse timing derive from the 32.768 kHz low-frequency timer, so every duration is quantized to one 30.5 μ s tick. To compensate for interrupt latency, tick quantization and the DAC write, the firmware subtracts a fixed overhead estimate from each phase (117 μ s from the stimulating phase and 116 μ s from the recovery phase). The compensation is not exact: at the 180 μ s setting the stimulating phase measured $\sim$ 240

μ s and the recovery phase ~ 860 μ s rather than 900 μ s. The stimulation period is set by a periodic timer whose period is computed in whole milliseconds, rounded down, so the delivered frequency takes one of seven values between ~ 83 and ~ 167 Hz (Table 2). The 130 Hz setting used throughout this work delivers 142.5 Hz; the 100 and 125 Hz settings correspond to whole-millisecond periods and are not rounded. In burst mode a second periodic timer starts a train of pulses at the intra-burst frequency every burst period and stops scheduling new pulses at the end of the burst duration. The first pulse of each burst occurs one intra-burst period after burst onset, and a pulse already in progress when the burst ends completes its full stimulating and recovery chain rather than being truncated.

Parameters. Table 2 lists the parameters exposed by the application and what the hardware and firmware v0.5 deliver for each. Parameters are stored in the microcontroller’s non-volatile memory and survive power cycling, so a device configured in the laboratory delivers the same protocol after its cells are replaced in the behavior room or home cage.

Table 2. Programmable stimulation parameters: application settings and delivered values (firmware v0.5). Measured values are from Section 4.1.

Parameter	App setting	Delivered	Notes
Amplitude	0–100 % in 1 % steps; labeled 0–600 μ A into 1 k Ω	16-bit DAC; ideal transconductance 6.25 μ A per percent (0–625 μ A); into 1 k Ω , ~ 4.7 μ A per percent + 47 μ A measured; limited by compliance at high load	Shared by both channels
Pulse width P	90–600 μ s in 30 μ s steps	Quantized to 30.5 μ s; 238–254 μ s measured at the 180 μ s setting	Recovery phase set to $5 \cdot P$ at $I/5$
Frequency (continuous mode)	80–160 Hz in 5 Hz steps	Period in whole milliseconds, rounded down: ~ 83 , 91, 100, 111, 125, 143 or 167 Hz	130 Hz setting delivers 142.5 Hz (measured)
Burst period	1 ms – 60 min	As set	Burst mode only
Intra-burst frequency	80–160 Hz in 5 Hz steps	Same seven values as continuous mode	Burst mode only
Burst duration	1 ms – 120 s	Capped at the burst period; about duration $\div$ intra-burst period pulses per burst	Burst mode only; in-flight pulse completes
Device ID	00–99	—	Displayed in the app for multi-animal cohorts

Wireless control and user interface. The device advertises as a BLE peripheral at a 2 s interval and exposes one service with a write characteristic (app to device) and a notify characteristic (device to app). Commands and responses are short ASCII strings of comma-separated key–value pairs; for example, `_M0,A50,F130,P90,G0,N0` sets continuous mode, 50 % amplitude, a 130 Hz frequency setting, a 90 μ s pulse-width setting, activation off and device number 0. The device replies with its full configuration, battery voltage and firmware version. The negotiated ATT MTU (up to 247 bytes) allows a complete configuration in a single packet. The iOS application (Figure 3) presents amplitude, pulse width and frequency as sliders with the derived current shown alongside, a segmented control for continuous versus

burst mode, and a toggle that starts the stimulation protocol. A red outline on the Sync button indicates that on-screen values differ from those confirmed by the device.

The intended workflow is configure-then-run: the experimenter connects, sets parameters, arms activation and disconnects; the device begins stimulating and stops advertising. Stimulation continues autonomously with no radio link. Passing a magnet over the device’s Hall-effect sensor re-enables advertising while stimulation continues; the phone can then reconnect to inspect battery voltage, change parameters without interrupting stimulation, or stop it, all without handling the animal. A status LED indicates when the device is advertising or connected and turns off during stimulation.

Battery telemetry. The microcontroller samples the battery voltage on request and reports it in millivolts; the application maps 1.4–2.8 V to a 0–100 % indicator.

Physical design. The circuit is built on a 1 mm thick printed circuit board measuring 19.5 mm × 22.5 mm, excluding the programming tab, and the assembled device is 8.72 mm thick (Figure 2). Firmware is loaded through a Tag-Connect TC2050 footprint on a break-away programming tab (Figure 2A, P), which can be cut off once firmware is loaded. Silicon Labs over-the-air device firmware update (DFU) is not currently enabled but could be added to allow firmware updates without the tab. A custom snap-on shroud covers the device (Figure 2B). The shroud was designed in Fusion 360 (Autodesk; design available at <https://a360.co/3TqHAXf>) and printed in PLA on a Bambu Lab X1 Carbon printer. The device with its electrode connector weighs 1.61 g with the programming tab removed (2.17 g with the tab), the shroud 0.48 g and each zinc-air cell 0.81 g, for 3.71 g in operation with two cells and the shroud (3.23 g without the shroud).

2.3 Design considerations

The architecture follows from a set of coupled experimental requirements rather than from a single optimum.

Stimulation envelope. Parameter ranges were chosen to reproduce protocols with established behavioral effects in our prior rodent DBS work rather than from theoretical models of neural activation. Stimulation at 100 μ A, 90 μ s and 130 Hz (Creed et al., 2012, 2013) is the reference protocol around which the application’s defaults are written. The frequency range covers the 130 Hz clinical standard and the 80–160 Hz window in which most rodent high-frequency protocols fall; it does not extend to the 30 and 60 Hz conditions used in earlier comparative work (Creed et al., 2011). Amplitude is programmable in ~ 6 μ A steps to 600 μ A nominal. Our prior protocols used 100 μ A (Creed et al., 2012, 2013) and, in one behavioral study, 12.5 μ A (Aleksandrova et al., 2013); the range above 100 μ A provides headroom for titration and for lower-impedance electrodes. Firmware v0.5 does not reproduce the programmed timing exactly, and the amplitude setting is a reproducible command rather than a calibrated delivered current. In practice we titrate amplitude in each animal against its behavioral effect, because electrode impedance and implant location vary between animals; on-board current or impedance sensing would make that titration more direct.

Compliance and electrode impedance. A constant-current source needs an output voltage of $I \cdot |Z|$ plus headroom for the sense resistor, the output filter and the amplifier’s swing limit. With ± 5 V rails, a 2 k Ω sense resistor and 660 Ω of series filter resistance per channel, the voltage available at the electrode in the stimulating phase is approximately 4.3 V at 100 μ A and 3.5 V at 400 μ A, from the 4.6 V swing measured into 47 k Ω (Section 4.1). The implanted electrodes used here present 32–80 k Ω in vivo (Section 3), so compliance rather than the programmable range sets the largest current that can be delivered. A battery-direct design with ~ 3 V of compliance would support substantially less current into the same electrodes.

Waveform and charge balance. Reversing the current through the electrode after each stimulating phase prevents net charge accumulation at the electrode–tissue interface and limits the generation of harmful elec-

trochemical reaction products (Merrill et al., 2005). FLEX-DBS does this actively but asymmetrically: the recovery phase is one-fifth the amplitude for five times the duration. Compared with a symmetric biphasic pulse, the low-amplitude recovery phase is less likely to be excitatory itself and avoids a sharp reversal transient; compared with passive electrode shorting, it recovers charge in a defined time regardless of the electrode’s RC time constant. The ratio is fixed in firmware.

Bilateral operation. Bilateral stimulation is standard in our behavioral protocols (Aleksandrova et al., 2013) and is required to reproduce them. The shared-DAC design halves the analog cost of a second channel and guarantees identical amplitude in both hemispheres. It cannot deliver different amplitudes to the two sides; that would require a second DAC or time-multiplexing of the existing one.

Wireless interaction. In the configure-then-run model the radio is not part of the stimulation path, so a dropped connection does not interrupt stimulation; the advertising interval, connection behavior and text protocol were chosen for reliability and ease of debugging rather than power.

Operating duration versus long-term implant power budget. The boost converter chain, the negative rail, the precision reference and an awake microcontroller were expected to dominate the platform current, and the design accepts that overhead to provide compliance, precision and reconfigurability.

3. Electrode impedance and stimulation robustness

A constant-current stimulator regulates current only while the voltage the electrode requires stays within its compliance, so the electrode load determines how much of the programmable range is usable.

3.1 Electrode construction

Electrodes were implanted using a custom 3D-printed electrode holder designed in Fusion 360 (Autodesk; design available at <https://a360.co/4rEBmq2>) and printed in clear biocompatible resin.

[Remaining construction details pending.]

3.2 In-vivo impedance measurement

Platinum electrodes were implanted bilaterally in four mice across two surgical cohorts (eight electrodes), and impedance was measured weekly from 1 to 8 weeks after implantation. At each session a StimJim stimulator (Cermak et al., 2019) delivered 10 μ A, 450 μ s pulses at 130 Hz for 10 s through each electrode against the common return, and the pulse voltage and delivered current reported by the StimJim were recorded five times. Impedance was computed as voltage divided by delivered current and averaged over the five readings; this quantity is an effective, pulse-derived estimate of the load, referred to as impedance in this section. This two-electrode configuration is the one the stimulator itself drives. Two- and three-electrode impedance spectroscopy measurements are highly correlated (Koo and Weiland, 2018), which supports the two-electrode configuration but does not validate the time-domain pulse estimate used here specifically. This pulse-based estimate matches the quantity that matters for a constant-current stimulator, the voltage required per unit of delivered current, rather than a small-signal impedance at a single frequency.

Three electrodes were excluded. One read near 0 V at every session, consistent with a short to the return. Both electrodes of one mouse gave unstable readings, varying by up to 4.7-fold between sessions and drifting within a session; whether this reflected the electrodes, the implant strategy or the recording setup could not be determined. The analyzed data set therefore comprises five electrodes from three mice, measured at eight weekly sessions (40 electrode-sessions).

Two properties of the measurement bound its interpretation. First, in a bench check against resistive loads, the voltage reported by the StimJim fell 6–73 % below the oscilloscope-measured voltage for loads of 2–68 k Ω , with the largest errors above 10 k Ω , which would bias the in-vivo values low. Second, the 450 μ s measurement pulse is longer than typical DBS pulses, so the polarization it includes would bias the values high relative to the load seen by shorter pulses. Because these biases act in opposite directions, the direction of the net error is unknown, and the values below are best treated as an estimate of the load range rather than a calibrated impedance.

3.3 In-vivo impedance and the compliance envelope

Across the five electrodes, impedance ranged from 32 to 80 k Ω (49.1 ± 9.9 k Ω , mean $\pm$ SD over all electrode-sessions). The weekly mean was 43.0 ± 7.4 k Ω at 1 week, peaked at 54.2 ± 14.8 k Ω at 3 weeks and returned to 44.6 ± 7.5 k Ω by 8 weeks, remaining within 43–54 k Ω throughout (Figure 4A). Mean impedance of individual electrodes ranged from 42.7 to 64.2 k Ω , so differences between electrodes (about 1.5-fold) were larger than the change in the group mean over time.

These loads place FLEX-DBS in its compliance-limited regime. With an output swing of about 4.6 V, measured into 47 k Ω , and 2.66 k Ω of sense and filter resistance in series with the electrode, the largest regulated current is approximately $I_{\max} = 4.6 \text{ V} / (|Z| + 2.66 \text{ k}\Omega)$ (Figure 4B). The weekly mean impedances correspond to 81–101 μ A, and individual electrode-sessions to 56–131 μ A, compared with the 600 μ A nominal range of the application. The 100 μ A reference protocol was within compliance in 11 of 40 electrode-sessions, and in 0 to 4 of the 8 sessions for individual electrodes. A battery-direct design with ~ 3 V of compliance would reach only ~ 38 –93 μ A into the same loads. The usable amplitude is set by electrode impedance and compliance together, not by the programmable range, and it differs between electrodes more than it changes over time after implantation.

4. Electrical validation of the wireless stimulator

4.1 Current accuracy and pulse fidelity

Both outputs of a device running firmware v0.5 were loaded with 1 k Ω resistors, and one output was recorded with a Joulescope JS220 Precision Energy Analyzer at 500 kHz for ~ 11 s at amplitude settings of 10, 50 and 100 % (180 μ s, 130 Hz; Figure 5). The same three settings were then recorded with both outputs loaded with nominal 47 k Ω resistors, within the range of effective loads estimated in vivo. Delivered current was taken as the voltage across the load divided by the load resistance. The meter’s own current channel showed 4–18 μ s spikes after each edge from automatic range switching, so both channels were passed through a 38 μ s median filter, which removes impulses while preserving steps; charge computed from the voltage changed by less than 0.5 nanocoulombs (nC) with filtering.

Delivered amplitude increased with the setting and was highly repeatable from pulse to pulse. The stimulating phase measured 106, 264 and 530 μ A at 10, 50 and 100 %, with a pulse-to-pulse SD below 0.5 μ A at every setting (Figure 5B). A line through the three settings has a slope of 4.7 μ A per percent and an intercept of +47 μ A, against the 6 μ A per percent shown in the application. The application value is therefore a reproducible setting rather than a calibrated current: the device delivers more than the nominal value at low settings and less at high settings. The recovery phase scaled with the stimulating phase at 1:4.7–4.9 (22, 56 and 113 μ A).

Pulse timing differed from the set values by a similar amount at every amplitude. At the 180 μ s setting the stimulating phase lasted 238–254 μ s and the recovery phase 854–878 μ s, against 900 μ s set, so the two phases did not carry equal charge: the median pulse delivered 27, 63 and 125 nC in the stimulating phase

and 19, 48 and 96 nC in the recovery phase, leaving a net 9.5, 17.3 and 33.0 nC per period in the stimulating direction (26–35 % of the stimulating-phase charge; Figure 5C). The 130 Hz setting delivered 142.5 Hz at every amplitude, a 7.02 ms period, because firmware v0.5 sets the period in whole milliseconds (Table 2), and the period varied with an SD of 29–38 μ s, about one 30.5 μ s timer tick.

Into 47 k Ω , delivered current was limited by compliance (Figure 5B). At the 50 and 100 % settings the stimulating phase was flat-topped at 92.6 μ A, which implies an output swing of 4.6 V across the load and the 2.66 k Ω of sense and filter resistance in series with it. The recovery phase reached 47 μ A at 50 %, below the 56 μ A delivered into 1 k Ω , and was also limited at 100 %, at about 88 μ A (4.4 V). At 10 %, below the limit, the edges were slow at this load: the stimulating phase was still rising when it ended (peak 51 μ A, against 106 μ A into 1 k Ω), and the cause, possibly capacitance on the load side, was not identified. Because these effects reduce the stimulating phase more than the recovery phase, the net charge per period changed sign with amplitude, at +5.5, –13.3 and –48.4 nC for 10, 50 and 100 % (Figure 5C). At a 0 % setting into 47 k Ω the output carried a residual of about 1 nC per period during the active window, small relative to the imbalance above; in use, stimulation is turned off rather than set to 0 %. Other pulse widths and loads were not characterized.

4.2 Battery and operating duration

Battery current was measured at the cell terminals in each operating state with the same Joulescope JS220 (Table 3). The device draws 1.47 mA when idle and not advertising, 1.62 mA while advertising, 1.89 mA while connected to the application, and 3.15–3.42 mA while stimulating at amplitude settings labeled 60 and 400 μ A, respectively, into 1 k Ω with a 180 μ s pulse width at the 130 Hz frequency setting (142.5 Hz delivered).

Table 3. Measured battery current and projected runtime on two size-13 zinc-air cells in series ($\sim$ 280 mAh; 90 % of nameplate capacity assumed usable). Stimulation rows use a 1 k Ω load, a 180 μ s pulse width and the 130 Hz setting, which delivers 142.5 Hz, and give the amplitude as labeled in the application. The continuous-stimulation projection was confirmed in a manual bench test that was not logged.

Operating state	Battery current	Projected runtime
Idle, not advertising	1.47 mA	$\sim$ 7.1 d
Advertising	1.62 mA	$\sim$ 6.5 d
Connected to app	1.89 mA	$\sim$ 5.6 d
Stimulating, 60 μ A	3.15 mA	$\sim$ 3.3 d
Stimulating, 400 μ A	3.42 mA	$\sim$ 3.1 d

Two features of these numbers define the usable experimental window. First, raising the amplitude setting from 60 to 400 μ A increased battery current by only 0.27 mA, so delivered amplitude contributes relatively little to the power budget. Entering the stimulation state adds 1.68–1.95 mA over idle; this reflects circuitry and processing that are active while the stimulation protocol runs, and how it divides among subsystems was not measured. Second, even at the highest measured current a fresh pair of cells has a projected runtime of about three days of continuous stimulation, and more than five days of standby with the phone connected. The power budget therefore permits hours-long, overnight and multiday sessions without disturbing the animal, with longer studies possible through a brief battery exchange, which requires detaching the device and pauses stimulation; charge balance in the present firmware is a separate constraint. Zinc-air cells are inexpensive and widely available, which suits a device whose cells are replaced frequently.

The device is intended for chronic studies with scheduled battery exchange, not as a fully implanted, maintenance-free system.

5. Comparison with existing methods

Table 4 places FLEX-DBS alongside published wireless rodent stimulators that are small enough for mice or are architecturally instructive. The columns are the properties that most often determine whether a system can run a given experiment: species and mass, channels, output type, supply or compliance, waveform and stimulation modes, how parameters are set, and power and operating duration. Supplementary Table S7 adds programmable ranges, dimensions and release status.

Table 4. FLEX-DBS in the context of published wireless rodent stimulators. Values as reported by the authors; blank, not reported; parentheses, an alternate value from the same source. Ranges, dimensions and release status: Table S7. CC, constant current; CV, constant voltage.

System	Species tested	Mass with battery	Channels	Output	Supply / compliance	Waveform and modes	Parameter control	Current draw; operating duration
FLEX-DBS (this work)	Mouse	3.71 g with shroud (two zinc-air cells)	2; shared amplitude and timing[†]	CC	±5 V rails; ~4.6 V swing (measured)	Asymmetric biphasic, 1:5 recovery; continuous or burst[†]	Real-time BLE from an iOS app; autonomous after disconnect[†]	3.15–3.42 mA stimulating; ~3 d per cell pair (projected)
t-IPG, Paulat et al. (2026)	Mouse (s-IPG also in rats and mice)	0.9 g (s-IPG 1.6 g)	2, time-delayed	CC	3 V lithium cell, direct	Cathodic phase with long low-amplitude anodic phase; theta- and beta-burst modes	Predefined paradigms via near-field transponder	21.3 µA maximum; 49 d voltage-compliant
STELLA, Plocksties et al. (2021)	Rat (proposed for mice >20 g)	4.0 g encapsulated (CR1225); 2.6 g (CR1216)	2, synchronized	CC	Boost 3.1–3.7 V; 2.2–2.8 V at electrode	Monophasic, passive charge balance	Firmware set before implantation; Hall sensor steps through presets	7.6–8.3 µA; ≥12 wk in vitro, 42 d in vivo
Grotemeyer et al. (2024)	Mouse	2 g	1	CC	3 V (two 1.5 V cells)	Monophasic, passive discharge	Cable programmer, reprogrammable after implantation; reed switch on/off	~20 µA; 52 d in vitro
Fleischer et al. (2020)	Mouse	2.8 g	1	CC	3 V (two V364 cells)	Monophasic, passive discharge	Programmed before mounting; switch on/off	~20 µA; ~30 d in vitro
de Haas et al. (2012)	Mouse	2.1 g with batteries and lead	2, alternating pulses	CC (adaptive resistance)	4.65 V (three 337 silver-oxide cells); regulates into 15–45 kΩ	Symmetric biphasic	Amplitude set by reprogramming in a fixture; magnet on/off	15 d standby, 10 h stimulating
Alpaugh et al. (2019)	Mouse	4.7 g	1	CC	3 V (two 393 cells); 2.1 V output headroom	Balanced biphasic	Preprogrammed via external circuit; no radio	~2 wk per cell set, ≥30 d with weekly exchange
Kouzani et al. (2013)	Rat (designed for mice)	3.27 g (head-mount)	1	CC	3.1 V (two silver-oxide cells)	Monophasic, capacitor-coupled	Preprogrammed; changes require reflashing or a resistor change	~870 µA; 12.3 d on bench, 7 d in vivo
Pinnell et al. (2018)	Rat	2.8 g with battery and head cap (text: 2.7 g)	2	CC	12.29 V regulated	Monophasic or biphasic; dual-frequency burst	Wired programmer; amplitude by potentiometer; magnet on/off	35 µA in low-power state; ~30 h stimulating
Burton et al. (2021)	Rat	0.046 g, battery-free	1 bipolar electrode	CV	1.5–5.5 V (regulated)	Biphasic	Real time via modulation of RF power	9.35 mW while stimulating; >36 d in vivo with RF power
Shen et al. (2026)	Rat	12.5 g (7.5 g battery)	Not stated; used unilaterally	CV	3.7 V Li-ion	Biphasic	Real-time BLE (MATLAB interface)	≥300 h on 400 mAh

[†]New paradigm enabling.

Three patterns emerge. First, the mouse-scale systems with runtimes of weeks (Paulat et al., 2026; Plocksties et al., 2021; Grottemeyer et al., 2024; Fleischer et al., 2020) run from supplies of about 3 V, either directly from the cells or through a small boost that leaves 2.2–2.8 V at the electrode, and draw roughly 8–22 μA . Their parameters are set before implantation or through a near-field or cable programmer, and a magnet or reed switch turns stimulation on and off or steps through presets. Their average currents are two orders of magnitude below the 3.15–3.42 mA of FLEX-DBS, a gap that delivered amplitude does not explain and that reflects the circuitry FLEX-DBS keeps active to provide compliance rails, precision analog stages and a radio. The low supply also bounds the load these systems can drive: Alpaugh et al. (2019) note that their 2.1 V of output headroom delivers the full 149 μA only into loads below about 20 k Ω , well below the 32–80 k Ω measured in vivo here. Second, the systems that offer real-time wireless control are rat-scale or externally powered and regulate voltage rather than current: Burton et al. (2021) harvest power from a radio-frequency field in the arena, and Shen et al. (2026) use BLE with a 7.5 g battery. Pinnell et al. (2018) combine constant current, two channels and 12.29 V compliance in a 2.8 g package, but set parameters through a wired programmer and potentiometers and run for about 30 h. Third, no system compared here combines bilateral constant-current output, compliance rails of ± 5 V, continuously programmable amplitude, pulse width and frequency, burst mode, and real-time phone control. That combination is what FLEX-DBS contributes, and it is bought with runtime measured in days rather than weeks.

For a fully implanted study with fixed parameters and no routine access to the animal, an architecture such as that of Paulat et al. (2026) or Plocksties et al. (2021) is more suitable; FLEX-DBS targets experiments in which parameters must be changed at the cage.

6. In-vivo functional validation

6.1 Experimental paradigm

[Pending.]

6.2 Video-based behavioral analysis

[Pending.]

6.3 Functional equivalence

[Pending.]

7. Discussion

FLEX-DBS provides flexible, bilateral, constant-current DBS with real-time wireless control for experiments in freely moving rodents. Its measured power consumption permits a projected three days of continuous stimulation per pair of cells, with longer studies possible through a brief battery exchange. Removing the tether while retaining the ability to set, change and verify parameters at the cage allows paradigms our laboratory has used with tethered hardware (Creed et al., 2012, 2011; Aleksandrova et al., 2013; Creed et al., 2013) to move into home-cage, social and extended-duration assays in which a tether is a significant confound.

The in-vivo load measurements reinforce that DBS delivery is a systems problem. Electrode impedance and stimulator compliance jointly determine whether the commanded constant current is actually delivered, and impedance differs between electrodes and varies over the weeks after implantation. A stimulator specified only by its programmable current range has not been fully specified. For the implanted platinum electrodes

used here, with pulse-derived effective loads of 32–80 k Ω and weekly means of 43–54 k Ω , the ± 5 V rails of FLEX-DBS support roughly 56–131 μ A, well below the 600 μ A programmable range and centered on the 100 μ A protocols used in prior work. We therefore recommend reporting the compliance limit alongside the measured load distribution (Figure 4B) for any rodent stimulator.

Two practical consequences follow. First, electrode impedance is the most direct lever on usable amplitude, and future protocols will establish a method for fabricating lower-impedance electrodes. Second, amplitude should be titrated in each animal against its behavioral effect, as in our protocols, rather than taken from the application’s nominal value. A configurable stimulator lets the experimenter confirm that a chosen amplitude is both deliverable into the implanted load and behaviorally effective, and adjust it if either condition fails.

Flexible multiday systems and fully implanted long-duration systems occupy different optimization spaces, and the measured current budget shows why. Raising the amplitude setting from 60 to 400 μ A adds only 0.27 mA, whereas entering the stimulation state adds 1.68–1.95 mA over idle, so most of the current drawn during stimulation reflects circuitry and processing required while the protocol runs rather than delivered amplitude. The design carries that overhead deliberately, because each block enables a capability of FLEX-DBS: a boost converter and inverter provide ± 5 V compliance; a continuously powered precision DAC and reference set the current reproducibly; an awake microcontroller sequences each pulse; and the radio stack permits configuration and verification at the cage. Power was reduced within these constraints, most visibly by shutting the output amplifier down between pulses, but maintenance-free operation for weeks or months was not the primary objective.

A fully implanted derivative would invert these priorities: battery-direct operation at ~ 3 V if electrode impedance allows it, a shared current source with hardware-timed polarity switching, asymmetric or passive charge recovery, a radio used only to configure, and a microcontroller whose hardware peripherals can sequence a pulse without waking the core. Published mouse-scale systems show that this combination reaches average currents of roughly 8–22 μ A (Paulat et al., 2026; Plocksties et al., 2021; Grottemeyer et al., 2024; Fleischer et al., 2020).

Limitations. Firmware v0.5 delivers the 130 Hz setting as 142.5 Hz and leaves a net charge of 26–35 % of the stimulating-phase charge per pulse into 1 k Ω ; this must be corrected before prolonged in-vivo stimulation. Below compliance, the finite output impedance of the Howland pumps (about 0.9 M Ω worst case with 0.1 % resistors) lets delivered current fall by up to 3–8 % into the loads measured here (Tucker et al., 2013), so amplitude settings should be read against the measured load and the bench measurements rather than as absolute currents. The two channels share amplitude and timing, and the 80 Hz frequency floor excludes the low-frequency protocols of comparative and therapeutic interest (Creed et al., 2011, 2015). Finally, the bench measurements cover one pulse width into two loads, and the impedance data come from five electrodes in three mice.

Future development. The schematic, firmware, application and protocol are released so that others can reproduce or adapt the platform (Supplementary material). Several extensions are firmware-level within the present hardware: computing the stimulation period in timer ticks rather than whole milliseconds, which would deliver 130 Hz and other frequencies exactly; calibrating the phase-timing compensation and recovery amplitude against bench measurements so that the two phases carry equal charge; independent per-channel timing; a wider frequency range; a selectable recovery ratio; and over-the-air firmware update. At the hardware level, on-board sensing of delivered current or electrode voltage would report the stimulation actually delivered and track electrode impedance over the course of an experiment, supporting amplitude titration in each animal.

8. Conclusions

FLEX-DBS is a head-mounted, bilateral, constant-current stimulator with real-time smartphone control, intended for experiments in which parameters must be set, changed and verified at the cage. Its measured power consumption permits a projected three days of continuous operation per cell pair; firmware v0.5 requires improved charge balancing before prolonged in-vivo stimulation. Its ± 5 V compliance rails deliver roughly 56–131 μ A into implanted platinum electrodes with pulse-derived effective loads of 32–80 k Ω , so the electrode load, not the programmable range, sets usable amplitude in vivo.

Figures

Figure 1. FLEX-DBS architecture. Functional blocks used to describe rodent stimulators, as implemented in FLEX-DBS. Zinc-air cells feed a boost converter that generates the +5 V rail; an inverter derives -5 V, and a regulator derives 3.3 V for the BLE microcontroller. The microcontroller sets pulse timing, commands amplitude through a reference and DAC, and controls the output switches. The DAC drives two Howland current pumps on ± 5 V, one per hemisphere, whose outputs pass through the switches and output filters to bilateral electrodes with a common return. A Hall-effect sensor wakes the device when a magnet is passed over it, and parameters are set from an iOS application over BLE. Components are listed in Table 1.




Figure 2. FLEX-DBS hardware. (A) Assembled device viewed from above; scale bar, 10 mm. P, break-away programming tab carrying the Tag-Connect TC2050 footprint, which can be cut off after firmware is loaded. (B) Rendering of the device from below with the snap-on shroud, showing the two zinc-air cell holders and the electrode connector. The board measures 19.5 mm × 22.5 mm excluding the programming tab, and the assembled device is 8.72 mm thick.




Figure 3. MouseCap iOS application. (Left) Continuous mode: amplitude (percent of full scale and nominal current into 1 k Ω), pulse duration and frequency sliders; device ID, firmware version and battery indicator; activation toggle, Sync, LED and Read controls. (Right) Burst mode: burst period, intra-burst frequency and burst duration with unit selection. Representative settings are shown (50 %, 90 μ s, 130 Hz; 30 s burst period, 10 s burst duration). Displayed values are settings; delivered values are given in Table 2.




Figure 4. In-vivo electrode impedance and the compliance envelope. (A) Impedance of implanted platinum electrodes from 1 to 8 weeks after implantation, a pulse-derived estimate of the effective load computed as pulse voltage over delivered current with 10 μA , 450 μs pulses (five readings averaged per electrode and session). Points show the mean $\pm$ SD across five electrodes from three mice; three of eight implanted electrodes were excluded (Section 3.2). (B) Top: largest regulated current of FLEX-DBS as a function of load impedance, $I_{\text{max}} = 4.6 \text{ V}/(|Z| + 2.66 \text{ k}\Omega)$, with the swing measured into 47 $\text{k}\Omega$. The gray band spans the range of weekly mean impedances in (A), 43–54 $\text{k}\Omega$, and the dashed lines project it to the corresponding current range, 81–101 μA ; the dotted line marks the 100 μA reference protocol. Bottom: weekly mean $\pm$ SD impedance on the same impedance axis, colored from week 1 (bottom) to week 8 (top).





Figure 5. Bench output into 1 k Ω and 47 k Ω loads. Both outputs of a FLEX-DBS device (firmware v0.5) were loaded with 1 k Ω , or with a nominal 47 k Ω within the in-vivo load range, and one output was recorded at 500 kHz for ~ 11 s at each of three amplitude settings (10, 50 and 100 %; 180 μ s, 130 Hz). Current is the voltage across the load divided by the load resistance, after a 38 μ s median filter that removes range-switching artifacts of the meter. (A) Median pulse at each setting into 1 k Ω (1545–1602 pulses); the 5th–95th percentile band lies within the line width. Shading marks the set stimulating (180 μ s) and recovery (900 μ s) phases. (B) Mean plateau current of the stimulating phase against the amplitude setting into 1 k Ω (filled) and 47 k Ω (open). The dotted line marks the 92.6 μ A compliance limit into 47 k Ω ; the 10 % point at 47 k Ω is reduced by slow edges. (C) Charge in each phase of the median pulse at 1 k Ω (solid) and 47 k Ω (hatched), and the mean net charge over a full period (labeled; nC, nanocoulombs). At every setting and load the delivered frequency was 142.5 Hz; into 1 k Ω the stimulating phase lasted 238–254 μ s and the recovery phase 854–878 μ s.



Supplementary material

- **S1.** Circuit schematic of the FLEX-DBS board (PDF).
- **S2.** Firmware for the BGM220S (Silicon Labs Simplicity Studio project), v0.5. Repository: <https://github.com/Neurotech-Hub/Creed-DBS-SiLabs>

- **S3.** MouseCap iOS application source. Repository: <https://github.com/Neurotech-Hub/MouseCap-iOS>
- **S4.** BLE protocol specification (MCU_BLE_PROTOCOL.md in S3): service and characteristic UUIDs, command grammar, parameter keys and ranges, and response format.
- **S5.** Shroud design (Fusion 360): <https://a360.co/3TqHAxf>
- **S6.** Electrode holder design (Fusion 360): <https://a360.co/4rEBmq2>
- **S7.** Extended comparison table (Table S7, below): programmable ranges, dimensions and release status for the systems in Table 4.

Table S7. Extended comparison of FLEX-DBS with published wireless rodent stimulators (full version of Table 4). Values for published systems are as reported by the authors; blank cells, and sizes omitted from the mass column, are not reported in the source. Where a source gives two values, the second is shown in parentheses with its location. CC, constant current; CV, constant voltage.

System	Species tested	Mass with battery; size	Channels	Output	Supply / compliance	Amplitude, pulse width, frequency; waveform	Parameter control	Current draw; operating duration	Open release
FLEX-DBS (this work)	Mouse	3.71 g with shroud (two zinc-air cells); 19.5 × 22.5 × 8.72 mm	2; shared amplitude and timing[†]	CC	±5 V rails; ~4.6 V swing (measured)	0–625 µA ideal (compliance-limited in vivo); 90–600 µs set; ~83–167 Hz delivered; asymmetric biphasic, 1:5 recovery; continuous or burst[†]	Real-time BLE from an iOS app; autonomous after disconnect[†]	3.15–3.42 mA stimulating; ~3 d per cell pair (projected)	Schematic, firmware, app, protocol (S1–S4)
t-IPG, Paulat et al. (2026)	Mouse (s-IPG also in rats and mice)	0.9 g (s-IPG 1.6 g); 5.3 mm thick	2, time-delayed	CC	3 V lithium cell, direct	1–100 µA, 50–700 µs, 2–257 Hz; cathodic phase with long low-amplitude anodic phase; theta- and beta-burst modes	Predefined paradigms via near-field transponder	21.3 µA maximum; 49 d voltage-compliant	Partial (GitHub)
STELLA, Plocksties et al. (2021)	Rat (proposed for mice >20 g)	4.0 g encapsulated (CR1225), Ø17.0 × 9.0 mm; 2.6 g (CR1216), Ø15.5 × 7.5 mm	2, synchronized	CC	Boost 3.1–3.7 V; 2.2–2.8 V at electrode	42–100 µA, 1 µs–100 % duty, 10–5000 Hz; monophasic, passive charge balance	Firmware set before implantation; Hall sensor steps through presets	7.6–8.3 µA; ≥12 wk in vitro, 42 d in vivo	Yes, open license (GitHub)
Grotemeyer et al. (2024)	Mouse	2 g; 18 × 16 × 5 mm with housing	1	CC	3 V (two 1.5 V cells)	10–500 µA, 60–500 µs, 10–200 Hz; monophasic, passive discharge	Cable programmer, reprogrammable after implantation; reed switch on/off	~20 µA; 52 d in vitro	Analysis code only; commercialized
Fleischer et al. (2020)	Mouse	2.8 g; board 9 × 9 × 1 mm (abstract: 10 × 10 mm)	1	CC	3 V (two V364 cells)	0–500 µA (text: up to 300 µA), 60–500 µs, 10–200 Hz (text: 10–500 Hz); monophasic, passive discharge	Programmed before mounting; switch on/off	~20 µA; ~30 d in vitro	
de Haas et al. (2012)	Mouse	2.1 g with batteries and lead; Ø8 × 30 mm	2 (bilateral), pulses alternate between channels	CC (adaptive series resistance)	4.65 V (three 337 silver-oxide cells); regulates into 15–45 kΩ	20–100 µA, 60 µs, 131 Hz fixed; symmetric biphasic	Amplitude set by reprogramming in a fixture (code table and resistor changes); magnet on/off; IR LED status	15 d standby, 10 h stimulating	
Alpaugh et al. (2019)	Mouse	4.7 g	1	CC	3 V (two 393 cells); 2.1 V output headroom	Fixed 149 µA, ~103 µs, ~130 Hz; balanced biphasic	Preprogrammed via external circuit; no radio	~2 wk per cell set, ≥30 d with weekly exchange	Component list only
Kouzani et al. (2013)	Rat (designed for mice)	3.27 g (head-mount)	1	CC	3.1 V (two silver-oxide cells)	Fixed 200 µA, 90 µs, 130 Hz; monophasic, capacitor-coupled	Preprogrammed; changes require reflashing or a resistor change	~870 µA; 12.3 d on bench, 7 d in vivo	Schematic and pseudocode

System	Species tested	Mass with battery; size	Channels	Output	Supply / compliance	Amplitude, pulse width, frequency; waveform	Parameter control	Current draw; operating duration	Open release
Pinnell et al. (2018)	Rat	2.8 g with battery and head cap (text: 2.7 g); device Ø12.5 × 5 mm	2	CC	12.29 V regulated	20 µA–2 mA, 10 µs–100 % duty, 0.1–5000 Hz; monophasic or biphasic; dual-frequency burst	Wired programmer; amplitude by potentiometer; magnet on/off	35 µA in low-power state; ~30 h stimulating	Design files and assembly instructions (Figshare)
Burton et al. (2021)	Rat	0.046 g, battery-free	1 bipolar electrode	CV	1.5–5.5 V (regulated)	1.5–5.5 V, ≥20 µs pulses, up to 25 kHz; biphasic	Real time via modulation of RF power	9.35 mW while stimulating; >36 d in vivo with RF power	
Shen et al. (2026)	Rat	12.5 g (7.5 g battery); 34 × 42 × 15 mm with housing	Not stated; used unilaterally	CV	3.7 V Li-ion	2.3–3 V, 40–340 µs, 80–150 Hz; biphasic	Real-time BLE (MATLAB interface)	≥300 h on 400 mAh	

[†]New paradigm enabling.

Author contributions

RDG implemented the experiments, performed the impedance bench testing and carried out animal handling and testing. MCC conceived and designed the experimental approach. MG designed the hardware, carried out the technical implementation, and performed the electrical bench testing and analysis. All authors contributed to writing the manuscript.

Competing interests

The authors declare no competing interests.

Funding

[Pending.]

Data and code availability

The circuit schematic is provided as Supplementary material S1. Firmware, iOS application source and the BLE protocol specification are available in the repositories listed as S2–S4, and the shroud design is available at <https://a360.co/3TqHAXf>. The impedance data underlying Figure 4 are available from the corresponding author on request.

Acknowledgments

We thank the Washington University Neurotech Hub for technical assistance with 3D design and hardware fabrication.

References

- Aleksandrova, L.R., Creed, M.C., Fletcher, P.J., Lobo, D.S.S., Hamani, C., Nobrega, J.N., 2013. Deep brain stimulation of the subthalamic nucleus increases premature responding in a rat gambling task. *Behavioural Brain Research* 245, 76–82. doi:10.1016/j.bbr.2013.02.011.
- Alpaugh, M., Saint-Pierre, M., Dubois, M., Aubé, B., Arsenault, D., Kriz, J., Cicchetti, A., Cicchetti, F., 2019. A novel wireless brain stimulation device for long-term use in freely moving mice. *Scientific Reports* 9, 6444. doi:10.1038/s41598-019-42910-7.
- Aulehner, K., Bray, J., Koska, I., Pace, C., Palme, R., Kreuzer, M., Platt, B., Fenzl, T., Potschka, H., 2022. The impact of tethered recording techniques on activity and sleep patterns in rats. *Scientific Reports* 12, 3179. doi:10.1038/s41598-022-06307-3.
- Burton, A., Won, S.M., Sohrabi, A.K., Stuart, T., Amirhossein, A., Kim, J.U., Park, Y., Gabros, A., Rogers, J.A., Vitale, F., Richardson, A.G., Gutruf, P., 2021. Wireless, battery-free, and fully implantable electrical neurostimulation in freely moving rodents. *Microsystems & Nanoengineering* 7, 62. doi:10.1038/s41378-021-00294-7.
- Cermak, N., Wilson, M.A., Schiller, J., Newman, J.P., 2019. Stimjim: open source hardware for precise electrical stimulation. *bioRxiv preprint* 757716. doi:10.1101/757716.

- Creed, M., 2018. Current and emerging neuromodulation therapies for addiction: insight from pre-clinical studies. *Current Opinion in Neurobiology* 49, 168–174. doi:10.1016/j.conb.2018.02.015.
- Creed, M., Hamani, C., Nobrega, J.N., 2011. Deep brain stimulation of the subthalamic or entopeduncular nucleus attenuates vacuous chewing movements in a rodent model of tardive dyskinesia. *European Neuropsychopharmacology* 21, 393–400. doi:10.1016/j.euroneuro.2010.06.012.
- Creed, M., Pascoli, V.J., Lüscher, C., 2015. Refining deep brain stimulation to emulate optogenetic treatment of synaptic pathology. *Science* 347, 659–664. doi:10.1126/science.1260776.
- Creed, M.C., Hamani, C., Nobrega, J.N., 2012. Early gene mapping after deep brain stimulation in a rat model of tardive dyskinesia: comparison with transient local inactivation. *European Neuropsychopharmacology* 22, 506–517. doi:10.1016/j.euroneuro.2011.11.004.
- Creed, M.C., Hamani, C., Nobrega, J.N., 2013. Effects of repeated deep brain stimulation on depressive- and anxiety-like behavior in rats: comparing entopeduncular and subthalamic nuclei. *Brain Stimulation* 6, 506–514. doi:10.1016/j.brs.2012.09.012.
- Ewing, S.G., Porr, B., Riddell, J., Winter, C., Grace, A.A., 2013. SaBer DBS: a fully programmable, rechargeable, bilateral, charge-balanced preclinical microstimulator for long-term neural stimulation. *Journal of Neuroscience Methods* 213, 228–235. doi:10.1016/j.jneumeth.2012.12.008.
- Fasano, A., Helmich, R.C., 2019. Tremor habituation to deep brain stimulation: underlying mechanisms and solutions. *Movement Disorders* 34, 1761–1773. doi:10.1002/mds.27821.
- Fleischer, M., Endres, H., Sendtner, M., Volkmann, J., 2020. Development of a fully implantable stimulator for deep brain stimulation in mice. *Frontiers in Neuroscience* 14, 726. doi:10.3389/fnins.2020.00726.
- Grottemeyer, A., Petschner, T., Peach, R., Hoehl, D., Knauer, T., Thomas, U., Endres, H., Blum, R., Sendtner, M., Volkmann, J., Ip, C.W., 2024. Standardized wireless deep brain stimulation system for mice. *npj Parkinson's Disease* 10, 153. doi:10.1038/s41531-024-00767-2.
- de Haas, R., Struikmans, R., van der Plasse, G., van Kerkhof, L., Brakkee, J.H., Kas, M.J.H., Westenberg, H.G.M., 2012. Wireless implantable micro-stimulation device for high frequency bilateral deep brain stimulation in freely moving mice. *Journal of Neuroscience Methods* 209, 113–119. doi:10.1016/j.jneumeth.2012.05.028.
- Jiang, Z., Huxter, J.R., Bowyer, S.A., Blockeel, A.J., Butler, J., Imtiaz, S.A., Wafford, K.A., Phillips, K.G., Tricklebank, M.D., Marston, H.M., Rodriguez-Villegas, E., 2017. TaiNi: maximizing research output whilst improving animals' welfare in neurophysiology experiments. *Scientific Reports* 7, 8086. doi:10.1038/s41598-017-08078-8.
- Knotkova, H., Hamani, C., Sivanesan, E., Le Beuffe, M.F.E., Moon, J.Y., Cohen, S.P., Huntoon, M.A., 2021. Neuromodulation for chronic pain. *The Lancet* 397, 2111–2124. doi:10.1016/S0140-6736(21)00794-7.
- Koo, B., Weiland, J., 2018. Experimental factors effecting stability of electrochemical impedance spectroscopy measurements, in: 2018 40th Annual International Conference of the IEEE Engineering in Medicine and Biology Society (EMBC), pp. 2949–2952. doi:10.1109/EMBC.2018.8512973.
- Kouzani, A.Z., Abulseoud, O.A., Tye, S.J., Hosain, M.K., Berk, M., 2013. A low power micro deep brain stimulation device for murine preclinical research. *IEEE Journal of Translational Engineering in Health and Medicine* 1, 1500109. doi:10.1109/JTEHM.2013.2264093.
- Krauss, J.K., Lipsman, N., Aziz, T., Boutet, A., Brown, P., Chang, J.W., Davidson, B., Grill, W.M., Hariz, M.I., Horn, A., Schulder, M., Mammis, A., Tass, P.A., Volkmann, J., Lozano, A.M., 2021. Technology of deep brain stimulation: current status and future directions. *Nature Reviews Neurology* 17, 75–87.

- doi:10.1038/s41582-020-00426-z.
- Kupsch, A., Benecke, R., Müller, J., Trottenberg, T., Schneider, G.H., Poewe, W., Eisner, W., Wolters, A., Müller, J.U., Deuschl, G., Pinski, M.O., Skogseid, I.M., Roeste, G.K., Vollmer-Haase, J., Brentrup, A., Krause, M., Tronnier, V., Schnitzler, A., Voges, J., Nikkhah, G., Vesper, J., Naumann, M., Volkmann, J., 2006. Pallidal deep-brain stimulation in primary generalized or segmental dystonia. *New England Journal of Medicine* 355, 1978–1990. doi:10.1056/NEJMoa063618.
- Lozano, A.M., Lipsman, N., Bergman, H., Brown, P., Chabardes, S., Chang, J.W., Matthews, K., McIntyre, C.C., Schlaepfer, T.E., Schulder, M., Temel, Y., Volkmann, J., Krauss, J.K., 2019. Deep brain stimulation: current challenges and future directions. *Nature Reviews Neurology* 15, 148–160. doi:10.1038/s41582-018-0128-2.
- Merrill, D.R., Bikson, M., Jefferys, J.G.R., 2005. Electrical stimulation of excitable tissue: design of efficacious and safe protocols. *Journal of Neuroscience Methods* 141, 171–198. doi:10.1016/j.jneumeth.2004.10.020.
- Murphy, C., Matikainen-Ankney, B., Chang, Y.H., Copits, B., Creed, M.C., 2021. Optogenetically-inspired neuromodulation: translating basic discoveries into therapeutic strategies, in: *International Review of Neurobiology*. Academic Press. volume 159, pp. 187–219. doi:10.1016/bs.irn.2021.06.002.
- Paulat, R., Koschützke, L., Haumesser, J., Maurer, L., Altschüler, J., Tang, H., Hounchonou, H., Daugardt, A., Harnack, D., Just, V., Schulz, G., Harms, C., Kühn, A.A., Wenger, N., van Riesen, C., 2026. Wireless lightweight implantable pulse generators enable chronic dual-target deep brain stimulation in rodent disease models. *Research Square preprint*. doi:10.21203/rs.3.rs-9019884/v1.
- Pinnell, R.C., Pereira de Vasconcelos, A., Cassel, J.C., Hofmann, U.G., 2018. A miniaturized, programmable deep-brain stimulator for group-housing and water maze use. *Frontiers in Neuroscience* 12, 231. doi:10.3389/fnins.2018.00231.
- Plocksties, F., Kober, M., Niemann, C., Heller, J., Fauser, M., Nüssel, M., Uster, F., Franz, D., Zwar, M., Lüttig, A., Kröger, J., Harloff, J., Schulz, A., Richter, A., Köhling, R., Timmermann, D., Storch, A., 2021. The software defined implantable modular platform (STELLA) for preclinical deep brain stimulation research in rodents. *Journal of Neural Engineering* 18, 056032. doi:10.1088/1741-2552/ac23e1.
- Shen, Y., Zhao, D., Lv, Y., Liu, Y., Chen, Y., Zhang, Y., Chen, S., 2026. A wearable deep brain stimulation system for behavioral studies in rodents. *Frontiers in Neuroscience* 19, 1707636. doi:10.3389/fnins.2025.1707636.
- Texas Instruments, 2008. AN-1515 A comprehensive study of the Howland current pump. Application Report SNOA474A. Texas Instruments. URL: <https://www.ti.com/lit/an/snoa474a/snoa474a.pdf>. revised April 2013.
- Tucker, A.S., Fox, R.M., Sadleir, R.J., 2013. Biocompatible, high precision, wideband, improved Howland current source with lead-lag compensation. *IEEE Transactions on Biomedical Circuits and Systems* 7, 63–70. doi:10.1109/TBCAS.2012.2199114.
- Vachez, Y.M., Creed, M.C., 2020. Deep brain stimulation of the subthalamic nucleus modulates reward-related behavior: a systematic review. *Frontiers in Human Neuroscience* 14, 578564. doi:10.3389/fnhum.2020.578564.