ASSIGNMENT 2

NIKHIL LOHAR

1 Question

Derive a Canonical POS expression for a Boolean function G, represented by the following truth table:

X	Y	Z	G(X,Y,Z)
0	0	0	0
0	0	1	0
0	1	0	1
0	1	1	0
1	0	0	1
1	0	1	1
1	1	0	0
1	1	1	1

SOLUTION: $G = (X + Y + Z).(X + Y + \bar{Z}). \ (X + \bar{Y} + \bar{Z}).(\bar{X} + \bar{Y} + Z)$
Minimization Using K-Map : $G = (X + Y).(X + \bar{Z}).(\bar{X} + \bar{Y} + Z)$

Figure 1: POS for G

1.1 Implement NAND Logic in SOP Form

$$X.Z + \overline{X}.Y.\overline{Z} + X.\overline{Y}$$

Output Using NAND Gates.

;