

Per-Unit QC Checklist — 2-Part ProMini EEprom Logger

Print **one copy per logger** and keep it with the unit through the batch. Stage numbers match [INSTRUCTIONS.md](#). Record actual measured values — the calibration constant and sleep current are unique per chip and cannot be reconstructed later.

Unit ID	Batch	Builder	Date started
U____			

Stage sign-off

✓	Stage	Check	Result / value
☐	1	Bootloader OK (01_UploadBlink heartbeat before any mods)	
☐	1	Regulator + power-LED resistor removed; UART header on	
☐	1	01_UploadBlink re-run after mods (onboard D13 blinks, any colour)	
☐	1	RGB LED fitted: all 3 colours rotate in 01_UploadBlink	
☐	1	NTC/LDR circuit soldered (D6 10k ref, D7 NTC, D8 300Ω, D9 LDR, 104 cap)	
☐	2	RTC module: charge resistor, LED resistor, VCC leg, 32 kHz pin removed	
☐	2	VCC bridged to Vbat side at diode	
☐	3	02_I2C_Scanner → CORE CHECK: PASS (0x68 + 0x57)	
☐	3	03_RTC_Test → all 4 PASS after clock set (T)	OSF cleared: Y / N
☐	3	04_EEprom_Test → PASS	mismatches: ____ / 4096
☐	3	Clock survives 1 min on coin cell only (OSF still clear)	
☐	4	05_VccCa1 constant recorded → entered via menu [10]	constant: ____
☐	4	06_SleepCurrent measured	__ μA (target ≤ 2)
☐	4	BURN-IN profile flashed; clock + interval set; START [6]	interval: ____ min
☐	4	Burn-in window	start: _ end : _
☐	4	Burn-in download clean (no gaps/resets, battery curve flat)	records: ____
☐	5	Sensors wired; 02_I2C_Scanner sees 0x76 + 0x23	
☐	5	07_SensorTest : temp rises to touch, lux drops when covered	
☐	5	[OPT] External EEprom fitted: 02 sees 0x50; 04 ALL PASS	size: ____k
☐	5	Profile flashed; startup lists 8 bytes/rec, 5 channels	☐ DEPLOY ☐ DEPLOY-XL
☐	5	Coin cell hot-glued; final 1-h shakedown download clean	

Final

Status	☐ PASSED — ready to deploy	☐ REWORK: _____	☐ REJECTED
--------	---	--	-----------------------------------

Notes (clone chip? resoldered joints? odd readings?):

Signed off by	Date