

WildBits rc16 | Byte-order review

Existing RTL layout and planned 6809 big-endian corrections

NOT FIXED IN RC16 / PLANNED - NO RTL CHANGES MADE

Register / scope	Existing rc16 mapping	Planned mapping	wildbits.d label impact
WM8776 command K2 + Jr2 16-bit write	FE70 = bits 7:0 FE71 = bits 15:8 FE72 = start transfer	FE70 = bits 15:8 FE71 = bits 7:0 Keep FE72 trigger.	CODECCmdLo/Hi match current RTL. Swap their offsets with the RTL; current Lo=0, Hi=1.
Optical keyboard count K2 optical scanner 12-bit read	FE12 = bits 7:0 FE13 = bits 11:8 (upper nibble zero)	FE12 = bits 11:8 FE13 = bits 7:0	OKB.CntLo/Hi match current RTL. Swap offsets 2 and 3. Update byte-load order in readers.
VICKY version / subversion K2 + Jr2 16-bit reads	FFDC = version low FFDD = version high FFDE = subversion low FFDF = subversion high	FFDC = version high FFDD = version low FFDE = subversion high FFDF = subversion low	VKY_VERSION_LO/Hi and VKY_SUBVER_LO/Hi match RTL. Swap \$1C/\$1D and \$1E/\$1F offsets.
Master control K2 + Jr2 Two control bytes	FFC0 = control 0 (enable flags, named L) FFC1 = control 1 (mode flags, named H)	Proposed H at FFC0; L at FFC1. Move the complete control-byte functions.	MASTER_CTRL_REG_L/H match existing byte locations. L/H imply a word, but RTL treats them as separate controls.
Layer control K2 + Jr2 16-bit control output	FFC2 = low byte FFC3 = high byte RTL output = {reg[3], reg[2]}	FFC2 = high byte FFC3 = low byte	VKY_LAYER_CTRL_L/H match current RTL. Swap offsets 2 and 3 and preserve layer-field meaning.

Label conflicts: No current value-to-RTL mismatch was found in these groups. Their low-first layout conflicts with the desired 6809 word order. Changing only wildbits.d would misdescribe rc16. Most pairs use sequential rmb declarations: moving lines changes offsets. Update RTL, definitions and callers together.

RTL: CODEC_Interface8.v:61-64; OpticalKeyboardScanner.v:195-196;
TinyVickyControl_Registers.v:83-86,155-158,171,233-250. Definitions: wildbits.d.

Source review: 2026-09-14 | Addresses are CPU addresses in hex | Planned release not assigned