

Sumoroboti programmeerimine eesti keeles

Liikumine

viivitus(1000);	Eelnevat käsku täidetakse 1000 millisekundit (1000ms=1sek)
stopp();	Robot jääb seisma
edasi();	Robot sõidab otse edasi
tagasi();	Robot sõidab tagurpidi
paremale();	Robot sõidab paremale
vasakule();	Robot sõidab vasakule

Edasijõudnutele

viivitus(SEKUND*0.5);	Eelnevat käsku täidetakse 500 millisekundit ehk pool sekundit (Vihje: võib ka kasutada SEKUND*0.2 või teisi väärtusi)
paremMootor(suund, kiirus);	Roboti parema mootori kiiruse seadmine. Tuleb määrata suund ja kiirus protsentides. <ul style="list-style-type: none">• suund > EDASI või TAGASI• kiirus > 0% kuni 100%
vasakMootor(suund, kiirus);	Roboti vasaku mootori kiiruse seadmine. Tuleb määrata suund ja kiirus protsentides. <ul style="list-style-type: none">• suund > EDASI või TAGASI• kiirus > 0% kuni 100%

Vastane

VASTANE_PAREM	Robot näeb vastast parema anduriga
VASTANE_VASAK	Robot näeb vastast vasaku anduriga
VASTANE_EES	Robot näeb vastast nii vasaku kui ka parema anduriga

Joon

ALL_PAREM	Roboti põhja all olev parempoolne andur
ALL_VASAK	Roboti põhja all olev vasakpoolne andur
ALL_KESKMINE	Roboti põhja all olev keskmine andur

Lihtne väljakul püsimise programm

```
if (ALL_VASAK) {  
    paremale();  
    viivitus(1000);  
} else if (ALL_PAREM) {  
    vasakule();  
    viivitus(1000);  
}
```

Programmeerimine

Programmi struktuur

Sumoroboti programmeerimiseks kasutame arduino keskkonda. Arduino keskkonnas tuleb kasutada järgnevat programmi struktuuri:

```
void setup() {  
    // ühekordne programm, siia sisse kirjutatud kood  
    // käivitatakse ainult korra roboti käivitumisel, enne loop() funktsiooni  
}  
  
void loop() {  
    // lõpmatu programm, siia sisse kirjutatud kood  
    // käivitatakse lõpmatu arv kordi, peale setup() funktsiooni  
}
```



Vajalike teekide lisamine



Sumoroboti juhtimiseks peame lisama Sumoroboti ja Servo teegid, mis sisaldavad vajalikke funktsioone, et sumorobotit juhtida. Selleks vajuta arduino keskkonnas järgnevaid nuppe menüüst:

- 1)  2)  3) 
4)  5)  6) 

Seejärel on võimalik kasutada esimesel lehel toodud funktsioone Arduino programmi struktuuriga.




Programmi kompileerimine ja laadimine

Kui programm on valmis, siis vajuta  nuppu menüüst, et see kompileerida. Veendu, et näed vasakul all nurgas järgnevat teadet: .

Juhul, kui Arduino leidis programmis vigu, annab ta järgmise veateate  ja nimetab allpool mustas kastis ka probleemid. Sellel juhul kontrolli oma kood üle ning raskuste korral kutsu appi juhendaja. Lõpuks, kui saad rohelise teate, et kõik on korras, vajuta  menüüst nuppu ja programm laetakse Sumorobotisse.

Näiteprogrammid

Kahtluse korral saab ka proovida näiteprogramme, need leiab järgnevate menüü nupuvajutustega:

- 1)  2)  3) 

Sealt tuleb valida sobiv näide EE lõpuga.

Lõbusat programmeerimist!

English Sumorobot programming guide

Movement

delay(1000) ;	The previous command is carried out for 1000 milliseconds (1000ms=1sek)
stop();	The robot stops
forward();	The robot moves forward
backward();	The robot moves backwards
right();	The robot moves to the right
left();	The robot moves to the left

Advanced

delay(SECOND*0.5);	The previous command is carried out for 500 milliseconds or half a second (Tip: you can use SECOND*0.2 or other values)
rightMotor(direction, speed);	Setting the speed of the right motor. The direction and speed (in percentage) must be specified. <ul style="list-style-type: none">• suund > FORWARD või BACKWARD• kiirus > 0% to 100%
leftMotor(direction, speed);	Setting the speed of the left motor. The direction and speed (in percentage) must be specified. <ul style="list-style-type: none">• suund > FORWARD või BACKWARD• kiirus > 0% kuni 100%

Opponent

OPPONENT_RIGHT	The robot sees the opponent with the right sensor
OPPONENT_LEFT	The robot sees the opponent with the left sensor
OPPONENT_FRONT	The robot sees the opponent with both the left and right sensor

Line

BOTTOM_RIGHT	The right sensor under the robot
BOTTOM_LEFT	The left sensor under the robot
BOTTOM_MIDDLE	The middle sensor under the robot

Basic program to stay on the field

```
if (BOTTOM_LEFT) {  
    right();  
    delay(1000);  
} else if (BOTTOM_RIGHT) {  
    left();  
    delay(1000);  
}
```

Programming

Program structure

To program the Sumorobot we use the Arduino environment. In the Arduino environment we have to use the following program structure:



```
void setup() {  
  // one time program, this program is executed once  
  // after the robot is turned on, before the loop() function  
}  
  
void loop() {  
  // endless program, this program is executed infinite  
  // number of times, after the setup() function  
}
```



Adding necessary libraries

For controlling the Sumorobot we need to add the Sumorobot and Servo library, which contain necessary functions to control the Sumorobot. For that click on the following menu buttons:

- 1)  2)  3) 
4)  5)  6) 




Compiling and uploading

When the program is ready, then push  from the menu, to compile the program. Be sure that you see the following message on the down left corner: .

In case Arduino found bugs in your program, you will see this message:  and it will also list the problems below in the black box. In this case recheck your program and if in doubt ask the supervisor for help. Finally, when you get the green message, that everything is fine, then press  from the menu and the program will be uploaded to the Sumorobot.

Example programs

After that we are able to use the functions listed above on the first page with the Arduino program structure. There are also example programs available, if in doubt. They can be found by pressing the following menu buttons:

- 1)  2)  3) 

From there you need to choose the examples ending with EN.

Happy programming!