Basic Introduction

Accessing Documents

General Information

STREAM

DELTA PRO

DELTA 2

DELTA 2 MAX

Smart Home Panel

Smart Plug

PowerStream Micro-inverter

Wave Air Conditioner

Glacier

Power Kits

PowerOcean

DELTA Pro Ultra

DELTA Pro 3

Smart Home Panel II

River 2 Pro

Code package download

Support

Smart Plug

HTTP communication mode

Set & Get Quota

How to transfer request parameters by these two HTTP API.

PUT: /iot-open/sign/device/quota: SetCmdRequest

GET: /iot-open/sign/device/quota: GetCmdRequest, GetCmdResponse

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse

Relay switch(0: off, 1: on)	{
	"sn": "HW52ZDH1RF3J0033",
	"cmdCode": "WN511_SOCKET_SET_PLUG_SWITCH_MESSAGE",
	"params": {
	"plugSwitch": 0
	}
	}
		{
		"sn": "HW52ZDH1RF3J0033",
		"params": {
		"quotas": [
		"2_1.switchSta"
		]
		}
		}
			{
			"code": "0",
			"message": "Success",
			"data": {
			"2_1.switchSta": false
			},
			"tid": ""
			}

Indicator light brightness adjustment(rgb brightness: 0-1023 (the larger the value, the higher the brightness); default value: 1023)	{
	"sn": "HW52ZDH1RF3J0033",
	"cmdCode": "WN511_SOCKET_SET_BRIGHTNESS_PACK",
	"params": {
	"brightness": 1000
	}
	}
		{
		"sn": "HW52ZDH1RF3J0033",
		"params": {
		"quotas": [
		"2_1.brightness"
		]
		}
		}
			{
			"code": "0",
			"message": "Success",
			"data": {
			"2_1.brightness": 1000
			},
			"tid": ""
			}

Deleting scheduled tasks(taskIndex: 0-9)	{ "sn":	{ "sn":	{ "code":

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse

	"HW52ZDH1RF3J0033",
	
	"cmdCode": "WN511_SOCKET_DELETE_TIME_TASK",
	
	"params": {
	
	"taskIndex": 1
	}
	}
		"HW52ZDH1RF3J0033",
		
		"params": {
		
		"quotas": [
		
		"2_2.task5"
		]
		}
		}
			"0",
			
			"message": "Success",
			"data": {
			
			"2_2.task5": {
			
			"taskIndex": 4,
			
			"type": 0,
			
			"timeRange": {
			
			"isConfig": false,
			
			"timeData": 0,
			
			"timeMode": 0,
			
			"startTime": {
			
			"sec": 0,
			
			"week": 0,
			
			"min": 0,
			
			"hour": 0,
			
			"month": 0,
			
			"year": 0,
			
			"day": 0
			
			},
			
			"stopTime": {
			
			"sec": 0,
			
			"week": 0,
			
			"min": 0,
			
			"hour": 0,
			
			"month": 0,
			
			"year": 0,
			
			"day": 0
			
			},
			
			"isEnable": false
			
			}
			}
			},
			"tid": ""
			}

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse

GetAllQuotaResponse

How to transfer request parameters by this HTTP API.

GET: /iot-open/sign/device/quota/all: GetAllQuotaResponse

heartbeat(2_1)

Field	Field's Type	Description
2_1.switchSta	int	Smart plug switch status
2_1.country	int	Country
2_1.temp	int	Smart plug temperature
2_1.town	int	City
2_1.freq	int	Operating frequency (Hz)
2_1.updateTime	int	Update time
2_1.warnCode	int	Smart plug warning code
2_1.current	int	Operating current (mA)
2_1.maxCur	int	Maximum output current: 0.1 A
2_1.watts	int	Operating output power: 0.1 W
2_1.brightness	int	RGB light brightness: 0–1023 (the larger the value, the higher the brightness)
2_1.volt	int	Operating voltage (V)
2_1.errCode	int	Error code

task(2_2)

Field	Field's Type	Description
2_2.task	json	Scheduled task
2_2.taskIndex	int	Task coding

Field	Field's Type	Description
2_2.type	int	Task type: 1: prioritize power supply; 2: prioritize power storage
2_2.timeRange	json	Time configuration
2_2.isEnable	boolean	Whether to enable: 0: no; 1: yes
2_2.isConfig	boolean	Whether to configure: 0: no; 1: yes
2_2.timeData	int	mode == 1, bit0-bit6 represents Monday to Saturday respectively; mode == 2, bit0-bit30 represents the 1st to the 31st
2_2.timeMode	int	Scheduled mode: 0: daily; 1: weekly; 2: monthly; 3: do not repeat
2_2.startTime	int	Task start time
2_2.stopTime	int	Task end time

MQTT communication mode

Set & Set Reply

Usage of Topic	Topic	From	To
Set device function	/open/${certificateAccount}/${sn}/set	app	device
Reply to the set result	/open/${certificateAccount}/${sn}/set_reply	device	app

Full Format Example

Set Data Format	Set Reply Data Format
{ "id": 123,	

Set Data Format	Set Reply Data Format
`{ "version": "1.0", "cmdCode": "WN511_SET_SUPPLY_PRIORITY_PACK", "params": { "supplyPriority": 1 } }`	

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo	Observation Indicator
Relay switch(0: off, 1: on)	`{ "id": 123456789, "version": "1.0", "cmdCode": "WN511_SOCKET_SET_PLUG_SWITCH_MESSAGE", "params": { "plugSwitch": 0 } }`	`{ "id": 123456789, "data": { "ack": 0 } }`	switchSta
Indicator light brightness adjustment(rgb brightness: 0-1023 (the larger the value, the higher the brightness); default value: 1023)	`{ "id": 123456789, "version": "1.0", "cmdCode": "WN511_SOCKET_SET_BRIGHTNESS_PACK", "params": { "brightness": 1000 } }`	`{ "data": { "ack": 0 }, "id": 123456789 }`	brightness
Deletiing scheduled task(taskIndex: 0-9)	`{ "id":`	`{ "data":`	

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo	Observation Indicator

	123456789,
	"version": "1.0",
	"cmdCode": "WN511_SOCKET_DELETE_TIME_TASK",
	"params": {
	"taskIndex": 1
	}
	}
		{
		"result": 1
		},
		"id": 123456789
		}	

Report Device Quota

Usage of Topic	Topic	From	To
Report device quota	/open/${certificateAccount}/${sn}/quota	device	app

Please see HTTP GetAllQuotaResponse and Set & Set Reply for the fields definition.

Example

heartbeat(2_1)


```
{
    "cmdId": 1,
    "cmdFunc": 2,
    "param": {
        "lanState": 3,
        "country": 17230,
        "selfMac": 487292708,
        "stackMinFree": 40,
        "resetCount": 3,
        "freq": 50,
        "warnCode": 0,
        "resetReason": 1,
        "current": 450,
        "watts": 10,
        "runTime": 279924,
        "switchSta": false,
        "temp": 39,
        "stackFree": 70,
        "parentMac": 0,
        "town": 0,
        "meshLayel": 0,
        "updateTime": "2023-09-16 16:45:03",
        "meshId": 16130048,
        "rtcResetReason": 1,
        "maxCur": 0,
        "brightness": 1023,
        "heartbeatFrequency": 2,
        "errCode": 0,
        "volt": 233,
        "maxWatts": 2500
```

```
    }
}
```

task(2_2)

```
{
    "cmdId": 2,
    "cmdFunc": 2,
    "param": {
        "task1": {
            "taskIndex": 0,
            "type": 0,
            "timeRange": {
                "isConfig": false,
                "timeData": 0,
                "timeMode": 0,
                "startTime": {
                    "sec": 0,
                    "week": 0,
                    "min": 0,
                    "hour": 0,
                    "month": 0,
                    "year": 0,
                    "day": 0
                },
                "stopTime": {
                    "sec": 0,
                    "week": 0,
                    "min": 0,
                    "hour": 0,
                    "month": 0,
                    "year": 0,
                    "day": 0
                },
                "isEnable": false
            },
            "task2": {
                ...
            },
            ...
        }
    }
}
```

Report Device status

Usage of Topic	Topic	From	To
Report Device status	/open/${certificateAccount}/${sn}/status	device	app

Message Format

```
{
    "id": "123456789",
    "version": "1.0",
    "timestamp": 1634841971000,
    "params": {
        "status": 0
    }
}
```

Field

Field	Field Type	Description
status	int	Device online or not0: No, 1: Yes

Was this page helpful?

YES NO

Was this page helpful?

We'd like to hear from you.Click here to give your feedback or suggestions.