

TEK4090 – Introduction to Modern Control

Assignment 1

Due: September 18 2025, 13:15

1. (10 points) Suppose that $v_1, \dots, v_m$ is linearly independent in V , and that $w \in V$. Show that

$$v_1, \dots, v_m, w \text{ is linearly independent} \iff w \notin \text{span}(v_1, \dots, v_m). \quad (1)$$

Ans: I will show that $i) \rightarrow ii)$ and then that $ii) \rightarrow i)$

Assume $v_1, \dots, v_m, w$ is lin. indep.

Pf by contradiction:

$$\begin{aligned} w &\in \text{span}(v_1, \dots, v_m) \\ w &= \alpha_1 v_1 + \dots + \alpha_m v_m \\ 0 &= \alpha_1 v_1 + \dots + \alpha_m v_m + (-1)w \end{aligned}$$

This contradicts that $v_1, \dots, v_m, w$ is linearly independent, because for any combination of indep. vectors, they must equal if and only if all coefficients $\alpha_1, \dots, \alpha_m = 0$. Since we have that the coefficient of w is equal to $-1 \neq 0$, we have that vectors $v_1, \dots, v_m, w$ are indep. and thus, $w \notin \text{span}(v_1, \dots, v_m)$

will now prove that $ii) \rightarrow i)$. Will also use proof by contradiction. Assume that $w \in \text{span}(v_1, \dots, v_m)$. This means that w can be written as a linear combination of the vectors in $\text{span}(v_1, \dots, v_m)$

$$w = \alpha_1 v_1 + \dots + \alpha_m v_m$$

This means that by definition, the list $(v_1, \dots, v_m, w)$ is dependent, and this is our contradiction. Thus, for $v_1, \dots, v_m, w$ to be independent, $w \notin \text{span}(v_1, \dots, v_m)$ has to be true

2. (10 points) Let $A, B \in \mathbb{R}^{n \times n}$, and define the *trace* of A as $\text{tr}(A) = \sum_{i=1}^n A_{ii}$. Show that

$$\frac{d\text{tr}(AB)}{dA} = B^T. \quad (2)$$

Hint: Find $\frac{d\text{tr}(AB)}{dA_{ij}}$.

3. (15 points) Suppose that $T : V \mapsto V$ is a linear map, and suppose that $S : V \mapsto V$ is an invertible linear map.

- (a) Prove that T and $S^{-1}TS$ have the same eigenvalues
- (b) Describe the relationship between the eigenvectors of T and the eigenvectors of $S^{-1}TS$.

4. (30 points) Consider the feedback block diagram:

- (a) Find the transfer function from d to y .
- (b) Suppose the plant has transfer function

$$P(s) = \frac{(s+1)}{s^2 - 4s + 13} \quad (3)$$

What are the poles of $P(s)$? What can you infer about the stability of the (open-loop) plant $P(s)$?

- (c) Suppose $C(s)$ is given by

$$C(s) = \frac{1}{s} \quad (4)$$

Does $C(s)$ stabilize the feedback system?

- (d) Now, suppose the plant and controller are given by

$$P(s) = \frac{10}{(s+1)}, \quad C(s) = \frac{K}{s}. \quad (5)$$

Find the values of K for which the feedback loop is stable.

- (e) Fix a value of K such that the system in part (??) is stable, and suppose the system is subject to a disturbance $D(s) = 100$. What will the final value of y be?

5. (10 points) Consider the standard feedback system with


$$C(s) = K, \quad P(s) = \frac{s^2 + 1}{(s^2 + 2)(s - 2)} \quad (6)$$

- (a) Sketch the Nyquist plot of $P(s)$. Include correct asymptotes to infinity and to the origin.

Ans: Include the figure for the nyquist plot for P(s)

- (b) Indicate the number of encirclements (and their orientations) of all possible critical points.

Ans: To indicate the number of encirclements, I want to talk about the Principle of the argument
Suppose we have the D contour. An illustration is given here.



From Classical Control (Francis), its stated that when the characteristic polynomial has no right hand poles (RHP), then the system is stable. It can be shown that for a feedback system like we are dealing with now, the characteristic polynomial is equal to

$$1 + KP(s) = 0$$

Since $C(s) = K$ where K is the gain. The loop gain is defined as the sum of the gain, where gain is explained as the amplified rate of the error between reference and output before its sent into the plant.

- If K is too small, then the system will have large error of steady states and will become too weak
- amplify the gain too much, and the gain is too aggressive, and the loop is destabilized. In our case, the poles of $1 + KP(s) = 0$ moves into the RHP
- At some critical gain, the system is marginally unstable, where the poles are located on the imaginary axis.

So what is gain margin? We will get to this

Now, the characteristic polynomial is:

(c) For what range of K is the feedback system stable?

Fig. 1: Bode Plot for Question (??)

- (15 points) Consider the standard feedback system with $C(s) = K$. The Bode plot of $P(s)$ is given in Figure 1 (magnitude in absolute units, not dB; phase in degrees). The phase starts at -180° and ends at -270° . You are also given that $P(s)$ has exactly one pole in the right half-plane. For what range of gains K is the feedback system stable?
- (10 points) Consider the feedback system:

with

$$P(s) = \frac{s+2}{s^2+2}, \quad C(s) = \frac{1}{s}. \quad (7)$$

Sketch the Nyquist plot of PC . How many encirclements are required of the critical point for feedback stability? Determine the range of real gains K for stability of the feedback system.

8. (10 points) Repeat the previous question with,

$$P(s) = \frac{s^2+1}{(s+1)(s^2+s+1)}, \quad C(s) = 1. \quad (8)$$