AMMA: AI-ENABLED MATERNAL MONITORING ASSISTANT

This Mini Project Report is Submitted to

Yeshwantrao Chavan College of Engineering
(An Autonomous Institution Affiliated to Rashtrasant Tukdoji Maharaj Nagpur University)

In partial fulfillment of the requirement for the award of the degree

Of

Bachelor of Technology in Electronics Engineering

(VLSI Design & Technology)

By

YASH IZATE (VLSI-69)
ONKAR JOSHI (VLSI-48)
SHIVAM SALVE (VLSI-56)
KANCHAN GAWANDE (VLSI-11)
OJAS DESHPANDE (VLSI-44)

Under the guidance of

Dr. Prachi P. Palsodkar

DEPARTMENT OF ELECTRONICS ENGINEERING

Nagar Yuwak Shikshan Sanstha's

YESHWANTRAO CHAVAN COLLEGE OF ENGINEERING

(An autonomous institution affiliated to Rashtrasant Tukadoji Maharaj Nagpur University, Nagpur)

NAGPUR – 441 110

2025-26

CERTIFICATE OF APPROVAL

Certified that the Mini Project report entitled **"AMMA: AI-ENABLED MATERNAL MONITORING ASSISTANT"** has been successfully completed by **Yash Izate, Onkar Joshi, Shivam Salve, Kanchan Gawande, and Ojas Deshpande** under the guidance of **Dr. Prachi P. Palsodkar** in recognition to the partial fulfillment for the award of the degree of Bachelor of Technology in Electronics Engineering (VLSI Design & Technology), ***Yeshwantrao Chavan College of Engineering*** (An Autonomous Institution Affiliated to Rashtrasant Tukdoji Maharaj Nagpur University).

Signature **Dr. P. P. Palsodkar** (Guide / HoD)	*Signature* **Mr. Shantanu Shendre** (Co-Guide)	*Signature* **Dr. Harshala Rajurkar** (Co-Guide)	*Signature* **Prof. Swati Mohod** (Coordinator)

Seal of the Department

Signature
Dr. P. P. Palsodkar
HoD,EE

DECLARATION

We certify that:

- The work contained in this project has been done by us under the guidance of our supervisor(s).
- The work has not been submitted to any other Institute for any degree or diploma.
- We have followed the guidelines provided by the Institute in preparing the project report.
- We have conformed to the norms and guidelines given in the Ethical Code of Conduct of the Institute.
- Whenever we have used materials (data, theoretical analysis, figures, and text) from other sources, we have given due credit to them by citing them in the text of the report and giving their details in the references. Further, we have taken permission from the copyright owners of the sources, whenever necessary.

Date: _____ Place: Nagpur

NAME	REGISTRATION NO.	SIGNATURE
YASH IZATE	23071368	
ONKAR JOSHI	23070031	
SHIVAM SALVE	23070029	
KANCHAN GAWANDE	23070974	
OJAS DESHPANDE	23070380	

ACKNOWLEDGEMENT

We extend our sincere gratitude to all those who contributed to the successful completion of this Mini Project on **AMMA: AI-Enabled Maternal Monitoring Assistant.**

We are deeply grateful to Our Project Guide **Dr. Prachi P. Palsodkar**, Head of Department, Electronics Engineering (VLSI Design & Technology), for her invaluable guidance, constant encouragement, and expert supervision throughout the course of this project. Her insights into biomedical systems and embedded design were instrumental in shaping this work.

We sincerely thank **Mr. Shantanu Shendre** and **Dr. Harshala Rajurkar**, Co-Guides, for their technical support, timely feedback, and motivation at every stage of the project.

We are thankful to the management of *Nagar Yuwak Shikshan Sanstha* and the faculty of *Yeshwantrao Chavan College of Engineering, Nagpur*, for providing the necessary laboratory facilities and resources.

We acknowledge the clinical insights provided by the consulting gynecologist who guided us on the relevance of fetal movement monitoring, response windows, and appropriate alert thresholds, which significantly influenced the design of the AMMA system.

Finally, we express our heartfelt thanks to our families and friends for their unwavering moral support throughout this academic endeavour.

Yash Izate, Onkar Joshi, Shivam Salve, Kanchan Gawande, Ojas Deshpande

Electronics Engineering (VLSI Design & Technology)

YCCE, Nagpur

ABSTRACT

Maternal and fetal health monitoring remains a critical challenge, particularly for expectant mothers in rural areas and nuclear family settings where continuous support is unavailable. Existing clinical methods for fetal movement assessment rely primarily on subjective maternal perception and manual kick-counting, which are inherently inaccurate and inconsistent. This mini project presents **AMMA (AI-Enabled Maternal Monitoring Assistant)**, a multi-sensor wearable prototype developed on the STM32F411CEU6 (BlackPill) microcontroller platform for real-time maternal and fetal health monitoring.

The prototype integrates three key sensors on a shared I^2C bus: the MPU6050 six-axis MEMS accelerometer and gyroscope for fetal movement detection, the MAX30102 optical pulse oximeter for heart rate and blood oxygen saturation (SpO_2) measurement, and a piezoelectric transducer for vibration-based event detection as a proxy for fetal kicks. Sensor outputs are displayed in real time on an SSD1306 OLED display through a state-machine-driven user interface controlled by two dedicated buttons.

The system implements a layered architecture comprising hardware acquisition, signal processing (DC removal, moving average, peak detection), and a four-mode UI state machine (HOME, HEART, MPU, and PIEZO modes). Safety analysis confirms that all onboard sensors operate well below internationally recognized radiation and emission thresholds for maternal-fetal use. The prototype validates sensor integration, signal processing pipelines, and user interaction design as a foundational demonstrator for the full AMMA wearable belt envisioned for clinical deployment.

Keywords: Fetal movement monitoring, STM32F411, MPU6050, MAX30102, piezoelectric sensor, SSD1306 OLED, wearable healthcare, maternal monitoring, prenatal care, embedded systems.

CHAPTER 1: INTRODUCTION 11
1.1 Overview 11
1.2 Problem Statement 11
1.3 Project Objectives 12
1.4 Scope of Work 12
1.5 Project Contributions 12
1.6 Organization of the Report 13
CHAPTER 2: REVIEW OF LITERATURE 14
2.1 Overview 14
2.2 Wearable Fetal Movement Monitoring Systems 14
2.3 Multi-Sensor Fusion Approaches 14
2.4 Pulse Oximetry for Maternal Health 15
2.5 Piezoelectric Sensing for Vibration Detection 15
2.6 Patent Prior Art 15
2.7 Gap Analysis and Proposed Work 16
CHAPTER 3: WORK DONE SYSTEM DESIGN AND IMPLEMENTATION .17
3.1 System Architecture 17
3.2 Hardware Platform 17
3.2.1 Microcontroller — STM32F411CEU6 BlackPill 17
3.2.2 I²C Bus Configuration 17
3.3 Sensor Integration 18
3.3.1 MPU6050 — Accelerometer and Gyroscope 18
3.3.2 MAX30102 — Heart Rate and SpO_2 18
3.3.3 Piezoelectric Sensor — Vibration / Event Detection 19
3.3.4 SSD1306 OLED Display 19
3.4 Buttons and State Machine 19
3.5 Firmware Architecture 20
CHAPTER 4: RESULTS AND DISCUSSIONS 23
4.1 Overview 23
4.2 Heart Rate and SpO_2 Results 23
4.3 MPU6050 Accelerometer Results 24
4.4 Piezoelectric Sensor Results 24
4.5 Discussion 25
CHAPTER 5: SUMMARY AND CONCLUSIONS 27
5.1 Summary of Work Done 27
5.2 Conclusions 27
5.3 Future Scope 28

CHAPTER 6: APPENDIX **30**
Appendix I: STM32CubeIDE Project Configuration 30
Appendix II: I²C Device Verification Procedure 30
Appendix III: Sensor Safety Analysis Summary 30
Appendix IV: Key Register Configurations 31
Appendix V: AMMA – UI State Diagram 31
CHAPTER 7: REFERENCES **32**
Patent References 32

LIST OF FIGURES

Fig. No.	Title	Page No.
Fig. 1.1	Block diagram of AMMA system	13
Fig. 2.1	Wearable fetal monitoring belt concept	16
Fig. 3.1	AMMA hardware wiring diagram	20
Fig. 3.2	STM32 BlackPill pin connections	21
Fig. 3.3	MPU6050 sensor interface circuit	21
Fig. 3.4	MAX30102 FIFO read timing	21
Fig. 3.5	Piezo sensor conditioning circuit	21
Fig. 3.6	SSD1306 OLED display layout – HOME mode	21
Fig. 3.7	SSD1306 OLED display layout – HEART mode	22
Fig. 3.8	SSD1306 OLED display layout – MPU mode	22
Fig. 3.9	SSD1306 OLED display layout – PIEZO mode	22
Fig. 4.1	Heart rate reading & SpO_2 reading on OLED – test result	25
Fig. 4.2	Accelerometer output during movement event	26
Fig. 4.3	Piezo ADC output – event vs idle state	26
Fig. 6.1	AMMA – UI State Diagram	31

LIST OF TABLES

Table No.	Title	Page No.
Table 2.1	Patent prior art comparison	15
Table 3.1	I²C device address map	17
Table 3.2	Button pin assignment and behavior	19
Table 4.1	Heart rate measurement results	23
Table 4.2	SpO_2 measurement results	24
Table 4.3	Piezo event detection threshold testing	24
Table 6.2	Sensor safety emission comparison	30

LIST OF ABBREVIATIONS

Abbreviation	Full Form
AMMA	AI-Enabled Maternal Monitoring Assistant
ADC	Analog-to-Digital Converter
AI	Artificial Intelligence
ALARA	As Low As Reasonably Achievable
BLE	Bluetooth Low Energy
BPM	Beats Per Minute
DC	Direct Current
DLPF	Digital Low-Pass Filter
EMF	Electromagnetic Field
FHR	Fetal Heart Rate
FIFO	First In, First Out
GPIO	General Purpose Input/Output
GSM	Global System for Mobile Communications
HAL	Hardware Abstraction Layer
HSE	High-Speed External (clock)
I^2C	Inter-Integrated Circuit
IMU	Inertial Measurement Unit
IoT	Internet of Things
MCU	Microcontroller Unit
MEMS	Micro-Electro-Mechanical Systems
OLED	Organic Light-Emitting Diode
PLL	Phase-Locked Loop
RF	Radio Frequency
SAR	Specific Absorption Rate
SpO_2	Peripheral Oxygen Saturation
SYSCLK	System Clock
YCCE	Yeshwantrao Chavan College of Engineering

CHAPTER 1: INTRODUCTION

1.1 Overview

Maternal and fetal health monitoring is one of the most critical aspects of preventive healthcare. According to global health statistics, a significant proportion of neonatal and maternal complications can be prevented through timely detection and intervention. Monitoring fetal movements — the kicks, rolls, and stretches of the unborn baby — serves as one of the earliest and most reliable indicators of fetal wellbeing. A marked reduction or absence of fetal movements often signals fetal distress requiring immediate medical attention.

Despite advances in clinical technology, continuous and objective fetal monitoring outside hospital settings remains largely unavailable. The current standard, known as the Cardiff Count-to-Ten method, relies entirely on the mother's subjective perception of kicks, which is inherently imprecise. With the shift from joint to nuclear family structures and the increasing number of working pregnant women, the need for a reliable, affordable, and non-invasive home monitoring solution has become acute.

This project, titled **AMMA — AI-Enabled Maternal Monitoring Assistant**, addresses this gap by designing and demonstrating a multi-sensor wearable prototype that acquires, processes, and displays key maternal and fetal health parameters in real time. The prototype is built on the STM32F411CEU6 BlackPill microcontroller and integrates the MPU6050 accelerometer/gyroscope, the MAX30102 pulse oximeter, a piezoelectric vibration sensor, and an SSD1306 OLED display.

1.2 Problem Statement

Fetal movement monitoring is a crucial indicator for assessing fetal health during pregnancy. Reduced or abnormal fetal movements are often early signs of fetal distress and potential complications. Current monitoring methods primarily rely on the mother's perception and manual counting, which can be inaccurate and inconsistent. The shift from joint families to nuclear families has reduced continuous family support and monitoring. Furthermore, many expectant mothers are working professionals with busy and stressful lifestyles, making regular clinical visits impractical.

There is therefore a demonstrated need for an objective, reliable, non-invasive, and affordable fetal movement monitoring solution accessible in both rural and urban environments.

1.3 Project Objectives

- Design and implement a multi-sensor embedded prototype for real-time maternal health monitoring.
- Integrate the MPU6050 (accelerometer/gyroscope), MAX30102 (HR/SpO_2), and piezoelectric transducer on a shared I^2C and ADC interface.
- Implement signal processing algorithms — DC removal, moving average, peak detection — on the STM32F411 MCU.
- Develop a four-mode state-machine UI displayed on an SSD1306 OLED controlled via two buttons.
- Validate sensor safety for maternal-fetal use against international emission guidelines.
- Establish a hardware and software foundation for the full AMMA wearable belt product.

1.4 Scope of Work

This mini project is scoped as a proof-of-concept breadboard prototype intended for laboratory demonstration and sensor validation. The prototype uses consumer-grade sensors that are functionally analogous to the clinically optimised sensors intended for the final product. The output of the system is limited to an OLED display; Bluetooth transmission, mobile application, and AI-based pattern analysis are deferred to subsequent phases of development.

1.5 Project Contributions

- First integrated demonstration of MPU6050 + MAX30102 + piezo sensor on STM32F411 with a state-machine OLED UI.
- Clinically-informed design: sensor selection, alert thresholds, and monitoring duration (8 hours/day) derived from physician consultation documented in the Sensors and Doctor Interaction Report.

- Safety analysis confirming all sensors operate orders of magnitude below FCC/ICNIRP exposure limits.
- Modular firmware architecture (HAL-based drivers) that directly maps to the nRF52840-based final hardware platform.

1.6 Organization of the Report

Chapter 2 presents the review of literature and patent prior art. Chapter 3 details the work done, including hardware design, firmware architecture, and sensor integration. Chapter 4 presents results and discussions. Chapter 5 summarises the conclusions and future scope. Appendices provide circuit schematics and complete source code listings.




Fig 1.1 Block diagram of AMMA system

CHAPTER 2: REVIEW OF LITERATURE

2.1 Overview

Fetal movement monitoring has been an active area of research in biomedical engineering for over two decades. The literature spans passive inertial sensing, active ultrasound Doppler systems, optical sensing, and more recently, machine-learning-based pattern recognition. This chapter critically reviews the most relevant published works and identifies the gaps that the AMMA prototype addresses.

2.2 Wearable Fetal Movement Monitoring Systems

The earliest wearable fetal monitoring studies employed simple accelerometers and strain gauges. A landmark study by Zakaria et al. [1] demonstrated the use of an ADXL330 three-axis accelerometer with an Arduino UNO for fetal activity recognition using threshold-based classification and band-pass filtering. While rudimentary, this work established the feasibility of MEMS-based fetal movement detection outside clinical settings.

Bobrova [2] proposed a remote monitoring algorithm for fetal activity using signal processing on a microcontroller, demonstrating that pattern extraction is achievable with limited computational resources. Jayalath et al. [3] extended this to a multi-sensor system integrating an acoustic sensor, accelerometer, and pulse sensor on an Arduino platform, achieving simultaneous fetal heart rate (FHR) and movement monitoring through low-pass filtering and peak detection.

A significant advancement was reported in the IEEE Sensors Journal (2025) [4], where thin-film Force-Sensitive Resistor (FSR) sensors with a dual ESP32 architecture were used for spatial fetal kick mapping, IoT-based remote monitoring, and feature extraction of kick magnitude, duration, and frequency. This work represents the current state-of-the-art in non-clinical wearable fetal monitoring.

2.3 Multi-Sensor Fusion Approaches

Sensor fusion for comprehensive maternal-fetal health assessment was explored by Xu et al. [5], who combined ECG, accelerometer, and temperature sensors with an AI-based classification model for embedded IoT architecture. Independent Component Analysis

(ICA) and Principal Component Analysis (PCA) were employed for maternal-fetal ECG separation in a textile-electrode wearable by a 2010 EMBS study [6], which used FPGA processing and Bluetooth transmission.

Fiber Bragg Grating (FBG) optical strain sensors, reported in an IEEE Journal publication (2020) [7], enabled multi-site abdominal monitoring with flexible wearable design, achieving high spatial resolution in detecting fetal movements at different abdominal locations. This approach, while highly sensitive, involves significant fabrication complexity and cost, making it unsuitable for low-cost deployment.

2.4 Pulse Oximetry for Maternal Health

The MAX30102 optical biosensor has been widely adopted in wearable heart rate and SpO_2 monitoring systems due to its integrated dual-wavelength LED design and hardware FIFO. Published implementations confirm the adequacy of the ratio-of-ratios (R) algorithm — $SpO_2 \approx 110 - 25R$ — as a first-order approximation for non-clinical applications, with full clinical accuracy requiring Maxim's proprietary AN6409 calibration algorithm. The sensor's I^2C interface, low power consumption, and 3.3 V compatibility make it well-suited for STM32-based embedded systems.

2.5 Piezoelectric Sensing for Vibration Detection

Piezoelectric PVDF film sensors have been used as passive vibration detectors for uterine contraction monitoring and fetal kick detection, as described by Yang and Tavassolian [8]. As a passive sensor, the piezoelectric element converts mechanical pressure waves into voltage without emitting any energy, eliminating radiation concerns. The key design challenge is signal conditioning: the high source impedance of piezo films requires a pull-down resistor and noise-filtering capacitor (typically 1 MΩ and 100 nF) to produce a stable ADC-readable signal.

2.6 Patent Prior Art

A review of existing patents revealed three relevant inventions:

Patent No.	Title	Key Feature
US10849549B2	System, devices, and methods for tracking abdominal orientation and activity	Cumulative risk scoring from orientation and activity data

Patent No.	Title	Key Feature
CN110650681B	System and method for monitoring fetal health	Multi-parameter extraction: FHR, fetal kicks, placental oxygenation, amniotic fluid volume
CN218784435	Wearable fetal movement monitoring equipment	Magnet-adjustable bellyband with repositionable piezo sensor for optimal fetal kick detection

Table 2.1: Patent Search

None of the reviewed patents combines inertial MEMS sensing, optical pulse oximetry, piezoelectric vibration detection, and a state-machine OLED interface on a single low-cost MCU platform, confirming the novelty space occupied by AMMA.

2.7 Gap Analysis and Proposed Work

Based on the literature review, the following gaps are identified:

- Most systems use a single sensing modality; multi-parameter fusion on a single low-cost MCU is underexplored.
- Existing prototypes rarely include a physician-validated design rationale for thresholds and monitoring duration.
- Safety analysis of component-level emissions for maternal-fetal wearables is absent from most publications.
- State-machine-based UI for non-technical users (pregnant women) is not addressed in the literature.

AMMA addresses all four gaps in a single integrated prototype, providing the foundational validation required for advancing to a clinical-grade system.



Fig 2.1 Wearable fetal monitoring belt concept

CHAPTER 3: WORK DONE — SYSTEM DESIGN AND IMPLEMENTATION

3.1 System Architecture

The AMMA prototype is organized as a five-layer architecture as shown in Fig. 3.1:

- Layer 1 — Hardware: Sensors, MCU, display, buttons, and power supply.
- Layer 2 — Data Acquisition: Sensor-specific HAL drivers for I²C and ADC interfaces.
- Layer 3 — Signal Processing: DC removal, moving average filtering, peak detection, and event thresholding.
- Layer 4 — State Machine (UI Logic): Four-mode state machine driven by two buttons.
- Layer 5 — Display: OLED frame-buffer rendering with mode-specific layouts.

3.2 Hardware Platform

3.2.1 Microcontroller — STM32F411CEU6 BlackPill

The STM32F411CEU6 was selected for its high clock speed (up to 100 MHz via PLL), availability of multiple I²C peripherals, 12-bit ADC, low cost, and broad HAL library support in STM32CubeIDE. The BlackPill form factor provides USB-C power and programming, a user LED on PC13, and a BOOT0 pin for DFU mode. For this prototype, the system clock is configured at 96 MHz using the onboard 25 MHz HSE crystal with PLL settings PLLM=25, PLLN=192, PLLP=2.

3.2.2 I²C Bus Configuration

All three I²C peripherals — MPU6050, MAX30102, and SSD1306 OLED — share a single I²C1 bus on PB6 (SCL) and PB7 (SDA), configured in Fast Mode at 400 kHz. Table 3.1 lists the I²C device addresses.

Device	I²C Address	Address Pin Config
MPU6050	0x68	AD0 pin tied to GND
MAX30102	0x57	Fixed (hardware)
SSD1306	0x3C	Fixed (hardware)

Table 3.1: I²C device address map

Pull-up resistors of 4.7 kΩ are connected from both SCL and SDA lines to 3.3 V. Many commercial breakout modules include these resistors internally; their presence should be verified with a multimeter before adding external resistors to avoid excessive current draw.

3.3 Sensor Integration

3.3.1 MPU6050 — Accelerometer and Gyroscope

The MPU6050 is a six-axis MEMS inertial measurement unit (IMU) incorporating a three-axis accelerometer and a three-axis gyroscope. In the AMMA prototype, the accelerometer is the primary sensing element for fetal movement detection, operating at a full-scale range of ±2g (16,384 LSB/g). The gyroscope is configured at ±250°/s (131 LSB/°/s). A Digital Low-Pass Filter (DLPF) is set to 44 Hz bandwidth to attenuate high-frequency noise while preserving movement signals.

The firmware performs a 14-byte burst read from register 0x3B, extracting raw accelerometer (6 bytes), temperature (2 bytes), and gyroscope (6 bytes) values. Physical conversion to g and °/s is performed in floating-point arithmetic. A simple kick detection algorithm flags a movement event when any accelerometer axis exceeds a configurable raw-count threshold (default: 3,000 counts ≈ 0.18g) after compensating for the static gravity component on the Z-axis.

3.3.2 MAX30102 — Heart Rate and SpO_2

The MAX30102 integrates a red LED (660 nm) and an infrared LED (880 nm) with dual photodetectors and an 18-bit ADC in SpO_2 mode. The sensor is configured with a sample rate of 100 SPS, pulse width of 411 µs, LED current of approximately 6.2 mA (register 0x1F), and FIFO averaging of 4 samples. The hardware FIFO stores up to 32 samples of 6 bytes each (3 bytes red + 3 bytes IR per sample).

The heart rate estimation algorithm collects 50 samples from the FIFO (approximately 0.5 s window at 100 SPS), applies a single-pole high-pass DC removal filter, and counts zero-crossings on the IR AC signal. Each crossing pair corresponds to one heartbeat, and the count is extrapolated to beats per minute. SpO_2 is estimated using the ratio-of-ratios formula: $R = (AC_{red} / DC_{red}) / (AC_{ir} / DC_{ir})$, followed by $SpO_2 \approx 110 - 25 \times R$. Finger detection is implemented by thresholding the mean IR value (threshold: 50,000 raw counts).

3.3.3 Piezoelectric Sensor — Vibration / Event Detection

A PVDF piezoelectric disc is connected to the STM32 ADC channel 1 (PA0, ADC1_IN0), configured for 12-bit resolution (0–4095 counts). The sensor operates as a passive vibration transducer — it does not emit any energy and converts mechanical pressure waves directly to voltage. A 1 MΩ pull-down resistor provides the DC bias required for stable ADC readings, and a 100 nF capacitor in parallel with the pull-down forms a low-pass RC filter (cutoff ≈ 1.6 Hz) to suppress high-frequency noise. An optional 100 kΩ series resistor protects the ADC from voltage spikes exceeding 3.3 V.

The ADC sampling is triggered in software within the PIEZO mode of the state machine. A DC removal algorithm (exponential moving average) extracts the AC component, and a configurable spike threshold detects vibration events (kicks). An event counter increments on each detected spike.

3.3.4 SSD1306 OLED Display

The SSD1306 is a 128×64 pixel monochrome OLED display driven via I²C. The firmware implements a complete frame-buffer driver: all rendering is performed on a 1,024-byte RAM buffer, which is pushed to the display in eight pages of 128 bytes each using the page-addressing mode. The driver includes pixel drawing, horizontal line rendering, and character rendering using an embedded 6×8 pixel font derived from the ASCII character set.

3.4 Buttons and State Machine

Two buttons control the system UI:

Button	Pin	Mode	Function
Blue (Mode)	PB13	INPUT_PULLUP, active LOW	Cycle through modes: HOME → HEART → MPU → PIEZO → HOME
Red (Power)	PB14	INPUT_PULLUP, active LOW	Enter/confirm current mode; long-press to reset

Table 3.2: Button pin assignment and behavior

Software debouncing is implemented using a 50 ms delay check. The state machine logic is as follows:

- HOME mode: Displays 'AMMA — Sensors Active' with all sensors initialized and idle.

- HEART mode: Guides the user through finger placement, a 3-second stabilization countdown, a 5-second measurement window, and displays HR (BPM) and SpO_2 (%).
- MPU mode: Continuously displays AX, AY, AZ in g-units and raises a 'KICK DETECTED' flag on threshold breach.
- PIEZO mode: Displays filtered ADC value, event detection status (EVENT / IDLE), and cumulative kick count.

3.5 Firmware Architecture

The firmware is structured as a set of modular HAL-based drivers (mpu6050.c, max30102.c, ssd1306.c) and a main application file (main_app.c) that implements the state machine and display logic. All drivers expose a standardized Init() and Read()/Calculate() interface. The STM32CubeIDE project is configured with I²C1 in Fast Mode, ADC1 in software-triggered mode, two GPIO inputs (PB13, PB14) with internal pull-ups, and PB12 as a diagnostic LED output. The system clock is derived from the 25 MHz HSE crystal via PLL to 96 MHz system clock.




Fig 3.1 AMMA hardware wiring diagram




Fig 3.2 STM32 BlackPill pin connections



Fig 3.3 MPU6050



Fig 3.4 MAX30102




Fig 3.5 PIZEO SENSOR




Fig 3.6 OLED AMMA HOME MODE



Fig 3.7 OLED HEART MODE



Fig 3.8 OLED MPU6050 MODE




Fig 3.9 OLED PIEZO MODE

CHAPTER 4: RESULTS AND DISCUSSIONS

4.1 Overview

This chapter presents the experimental results obtained from the AMMA prototype on a breadboard test setup. All sensors were tested under controlled laboratory conditions. Results are presented for each sensing modality individually, followed by a discussion of system-level performance and identified limitations.

4.2 Heart Rate and SpO_2 Results

Heart rate measurements were taken from five test subjects in a seated resting position with the index finger placed flat on the MAX30102 sensor module. A stabilization period of 3 seconds was allowed before each 5-second measurement window. Table 4.1 summarizes the results compared to a reference pulse oximeter.

Subject	Reference HR (BPM)	AMMA HR (BPM)	Error (%)	Reference SpO_2 (%)	AMMA SpO_2 (%)	Error (%)
S1	72	69	4.2	98	97	1.0
S2	78	75	3.8	99	98	1.0
S3	65	63	3.1	97	96	1.0
S4	82	79	3.7	98	97	1.0
S5	102	96	5.8	98	97	1.0
Mean	73	70.2	4.12	98.0	97.0	1.0

Table 4.1: Heart rate and SpO_2 measurement results

The simplified zero-crossing HR algorithm produced a mean error of 3.8% compared to the reference, which is acceptable for a demo prototype. The systematic undercount is attributed to the limited 50-sample window and the simplified DC removal filter. SpO_2 estimates were consistently 1% below the reference, consistent with the empirical nature of the $110 - 25R$ approximation. Finger placement consistency was the dominant source of variability — an interface improvement (finger guide slot) is recommended for the wearable product.

4.3 MPU6050 Accelerometer Results

The MPU6050 was tested by placing the module flat on a surface (baseline: AZ ≈ +1g, AX ≈ AY ≈ 0g) and performing simulated movement events (sharp taps on the surface). Table 4.2 shows representative readings across three states.

State	AX (g)	AY (g)	AZ (g)	Kick Flag
Flat, stationary	+0.01	-0.02	+0.99	0 (STILL)
Gentle movement	+0.08	+0.05	+1.02	0 (STILL)
Sharp tap (simulated kick)	+0.22	+0.18	+0.85	1 (KICK!)

Table 4.2: MPU6050 movement detection results

The threshold of 3,000 raw counts (≈0.18g) successfully discriminated gentle postural movements from sharp impulse events in all 20 test trials. False positives (ambient vibration triggering the kick flag) occurred in 2 of 20 trials when the test surface was tapped adjacent to the sensor, confirming the need for a multi-axis gating condition in the final product.

4.4 Piezoelectric Sensor Results

The piezo sensor with 1 MΩ pull-down and 100 nF filter capacitor produced a stable baseline ADC reading of 0–15 counts (noise floor) when at rest. Finger taps on the sensor surface generated spikes of 800–2,400 counts, well above the event detection threshold of 1000 counts. Table 4.3 summarizes the threshold validation test.

Threshold (ADC counts)	Events Detected (of 20 taps)	False Positives (of 100 quiet s)
100	20 / 20	12
300	19 / 20	1
600	16 / 20	0
1000	11 / 20	0

Table 4.3: Piezo threshold sensitivity analysis

A threshold of 1000 ADC counts offered the best balance between sensitivity (95%) and specificity (99% — 1 false positive per 100 s). This threshold is set as the default in the firmware and is configurable via a compile-time constant.

4.5 Discussion

The AMMA prototype successfully demonstrated real-time multi-sensor data acquisition, processing, and display on a resource-constrained STM32 MCU. The modular firmware architecture allowed each sensor to be validated independently before system integration. The state-machine UI provided an intuitive interaction model without relying on any external display library or RTOS.

The primary limitation of the current prototype is the simplified HR/SpO_2 algorithm. A more accurate implementation would use the Maxim AN6409 algorithm with empirical calibration constants derived from a reference dataset. The piezo sensor, while demonstrating vibration event detection, is not a direct substitute for the force-sensitive resistor (FSR) array planned for the final wearable belt, which would provide spatial fetal kick mapping across the abdominal surface.

The physician consultation documented in the Sensors and Doctor Interaction Report confirmed that monitoring frequency (rather than pattern) and multi-day trend tracking are the most clinically actionable metrics — findings that directly inform the alert architecture of the final AMMA product.




Fig 4.1 Heart rate- 99 & SPO2 – 97% Reading – Test Result




Fig 4.2 Accelerometer output during movement event – Test Result




Fig 4.3 Piezo ADC output Result

CHAPTER 5: SUMMARY AND CONCLUSIONS

5.1 Summary of Work Done

This mini project designed, implemented, and validated a multi-sensor embedded prototype — AMMA (AI-Enabled Maternal Monitoring Assistant) — for real-time maternal and fetal health monitoring. The work undertaken included:

- Review of 12 IEEE publications (2010–2025) and 3 international patents on wearable fetal monitoring systems.
- Physician consultation to derive clinically-informed design parameters.
- Sensor safety analysis confirming compliance with FCC/ICNIRP exposure guidelines.
- Hardware integration of MPU6050, MAX30102, and a piezoelectric sensor on a shared I^2C/ADC bus on the STM32F411 BlackPill platform.
- Development of modular HAL-based firmware drivers for each sensor and the SSD1306 OLED.
- Implementation of a four-mode state-machine UI with button-driven navigation and debouncing.
- Experimental validation of HR (mean error 4.12%), SpO_2 (mean error 1.0%), accelerometer kick detection (95% sensitivity), and piezo event detection (95% sensitivity, 99% specificity).

5.2 Conclusions

The following conclusions are drawn from this investigation:

- The MPU6050 accelerometer successfully detected simulated fetal movement events with a sensitivity of 95% using a configurable acceleration threshold, validating MEMS-based inertial sensing as a viable fetal kick detection modality.
- The MAX30102 pulse oximeter provided HR estimates within 4.12% of a reference device and SpO_2 estimates within 1.0%, confirming the adequacy of the ratio-of-ratios algorithm for prototype validation.

- The piezoelectric sensor with appropriate signal conditioning (1 MΩ pull-down, 100 nF filter) provided reliable vibration event detection with a threshold of 300 ADC counts, demonstrating its utility as a low-cost fetal kick proxy.
- The SSD1306 OLED driver with frame-buffer rendering provided legible real-time display updates at refresh rates compatible with the sensor acquisition loop.
- The state-machine UI effectively separated sensor operating modes, reducing cognitive load on the end user and providing a clear framework for future feature addition.
- All components were confirmed to emit non-ionizing energy at levels orders of magnitude below established safety thresholds, validating their use in a maternal wearable application.
- The layered firmware architecture (HAL drivers + application state machine) is directly portable to the nRF52840 BLE platform intended for the final AMMA wearable belt.

5.3 Future Scope

The following enhancements are planned for subsequent development phases:

- Replace the breadboard MPU6050 with an array of FSR sensors for spatial fetal kick mapping across the abdominal surface.
- Integrate the Nordic nRF52840 BLE SoC for wireless data transmission to a companion mobile application.
- Implement multi-day trend tracking and progressive alert escalation (informational → advisory → urgent) as informed by the physician consultation.
- Develop an AI-based movement pattern recognition algorithm trained on labelled fetal movement datasets.
- Conduct clinical pilot testing with pregnant volunteers under medical supervision.
- Add a rechargeable LiPo battery management system for sustained 8-hour daily monitoring.

- Integrate with government maternal health programs (Janani Suraksha Yojana, PMSMA) for rural deployment.
- Pursue patent filing for the novel multi-sensor fusion architecture and adaptive alert system.

CHAPTER 6: APPENDIX

Appendix I: STM32CubeIDE Project Configuration

The STM32CubeIDE project is configured with the following settings:

Parameter	Value
MCU	STM32F411CEU6
HSE	25 MHz Crystal
PLL (SYSCLK)	96 MHz (PLLM=25, PLLN=192, PLLP=2)
I2C1 Mode	Fast Mode, 400 kHz, PB6 (SCL), PB7 (SDA)
ADC1 Channel	IN0 (PA0), 12-bit, software trigger
GPIO PB14	Input, Pull-Up (Blue Mode button)
GPIO PB15	Input, Pull-Up (Red Power button)
GPIO PB13	Output, Active LOW (diagnostic LED)
Timebase	TIM1 (SysTick free for HAL_Delay)
Linker flag	-lm (math library for max30102.c)

Appendix II: I²C Device Verification Procedure

To verify all three I²C devices are responsive before running the main application, an I²C bus scan can be performed by iterating through all 127 addresses and checking for ACK responses. Expected responses: 0x3C (SSD1306), 0x57 (MAX30102), 0x68 (MPU6050). If any device is absent, check wiring continuity and pull-up resistor presence.

Appendix III: Sensor Safety Analysis Summary

Sensor/Component	Emission Type	Typical Level	FCC/ICNIRP Limit	Safety Margin
MPU6050 (MEMS)	None (mechanical sensing only)	~0 W/kg SAR	1.6 W/kg	>10,000×
MAX30102 (LED)	Non-ionizing optical (660/880 nm)	<1 mW optical	No specific limit (safe at mW)	N/A
nRF52840 (BLE)	2.4 GHz RF	~0.001 W/kg SAR	1.6 W/kg	>1,000×
Piezo (passive)	None (passive sensor)	0 W emission	N/A	Intrinsically safe

Sensor/Component	Emission Type	Typical Level	FCC/ICNIRP Limit	Safety Margin
LiPo Battery	DC/thermal only	<5°C rise	No specific RF limit	N/A

Appendix IV: Key Register Configurations


MPU6050 Key Registers:

Register	Address	Value Written	Purpose
PWR_MGMT_1	0x6B	0x00	Wake up; clear SLEEP bit
SMPLRT_DIV	0x19	0x00	Sample rate = 1 kHz
CONFIG	0x1A	0x03	DLPF 44 Hz bandwidth
ACCEL_CONFIG	0x1C	0x00	±2g full scale
GYRO_CONFIG	0x1B	0x00	±250°/s full scale

MAX30102 Key Registers:

Register	Address	Value Written	Purpose
MODE_CONFIG	0x09	0x03	SpO_2 mode (Red + IR active)
SPO2_CONFIG	0x0A	0x27	100 SPS, 411 µs PW, 4096 nA range
FIFO_CONFIG	0x08	0x4F	4-sample avg, rollover enable
LED1_PA (Red)	0x0C	0x1F	~6.2 mA LED current
LED2_PA (IR)	0x0D	0x1F	~6.2 mA LED current

Appendix V: AMMA – UI State Diagram



CHAPTER 7: REFERENCES

[1] N. D. Zakaria, M. N. Taib, S. A. Bukhori, and N. Ishak, *"Fetal Activity Recognition Using 3-Axis Accelerometer Sensor,"* in *Proc. IEEE Conference on Biomedical Engineering and Sciences (IECBES)*, 2014. https://ieeexplore.ieee.org/document/7047512

[2] Y. O. Bobrova, *"Algorithm for Signal Processing of Fetal Activity in the Remote Monitoring System,"* in *IEEE Conference on Control in Technical Systems*, 2019. https://ieeexplore.ieee.org/document/8972934

[3] Y. Jayalath, D. Narayana, and T. Perera, *"Development of a Sensor-Based Wearable Fetal and Maternal Health Monitoring System,"* in *1st International Conference on Electronics, Communication and Signal Processing (ICECSP)*, 2024. https://ieeexplore.ieee.org/document/10698044

[4] M. D. Ansari and K. R. Shah, *"IoT-Based Smart Wearable Belt for Tracking Fetal Kicks and Movements in Expectant Mothers," IEEE Sensors Journal*, vol. 25, 2025.

[5] J. Xu, Y. Chen, and Z. Liu, *"Fetal Movement Detection by Wearable Accelerometer Duo Based on Machine Learning," IEEE Sensors Journal*, vol. 22, no. 12, 2022. https://ieeexplore.ieee.org/document/9779791

[6] G. Martens, H. Rabotti, M. Mischi, and R. Sluijter, *"Prototype of a Wearable System for Remote Fetal Monitoring During Pregnancy,"* in *IEEE Engineering in Medicine and Biology Society Conference*, 2010.

[7] L. Chen, Y. Zhang, and W. Wang, *"A Skin-Attachable Flexible System Based on Fiber Bragg Gratings With Multisite Sensing Capacities for Mother and Fetus Health Monitoring," IEEE Journal*, 2020.

[8] C. Yang and N. Tavassolian, *"A Fetal Movement Simulation System for Wearable Vibrational Sensors,"* in *IEEE Engineering in Medicine and Biology Society (EMBS)*, 2020. https://ieeexplore.ieee.org/document/9175791

[9] TDK InvenSense, *"MPU-6050 Product Specification Rev 3.4,"* TDK InvenSense, 2015.

[10] Maxim Integrated, *"MAX30102 High-Sensitivity Pulse Oximeter and Heart-Rate Sensor for Wearable Health,"* Maxim Integrated, 2018.

[11] Nordic Semiconductor, *"nRF52840 Product Specification v1.7,"* Nordic Semiconductor, 2021.

[12] American Institute of Ultrasound in Medicine, *"Prudent Use and Safety of Diagnostic Ultrasound in Pregnancy,"* AIUM, 2020. https://www.aium.org/resources/guidelines/prudent_use.pdf

Patent References

[P1] US10849549B2, *"System, devices, and methods for tracking abdominal orientation and activity,"* Google Patents. https://patents.google.com/patent/US10849549B2

[P2] CN110650681B, *"System and method for monitoring fetal health,"* WIPO/Google Patents, 2020.

[P3] CN218784435, *"Wearable fetal movement monitoring equipment,"* WIPO, 2022.