

Pluto_MSK_Modem address map

- Absolute Address: 0x0
- Base Offset: 0x0
- Size: 0x43C00090

Offset	Identifier	Name
0x43C00000	pluto_msk_regs	Pluto MSK Registers

pluto_msk_regs address map

- Absolute Address: 0x43C00000
- Base Offset: 0x43C00000
- Size: 0x90

MSK Modem Configuration and Status Registers

Offset	Identifier	Name
0x00	Hash_ID_Low	Pluto MSK FPGA Hash ID - Lower 32-bits
0x04	Hash_ID_High	Pluto MSK FPGA Hash ID - Upper 32-bits
0x08	MSK_Init	MSK Modem Control 0
0x0C	MSK_Control	MSK Modem Control 1
0x10	MSK_Status	MSK Modem Status 0
0x14	Tx_Bit_Count	MSK Modem Status 1
0x18	Tx_Enable_Count	MSK Modem Status 2
0x1C	Fb_FreqWord	Bitrate NCO Frequency Control Word
0x20	TX_F1_FreqWord	Tx F1 NCO Frequency Control Word
0x24	TX_F2_FreqWord	Tx F2 NCO Frequency Control Word
0x28	RX_F1_FreqWord	Rx F1 NCO Frequency Control Word
0x2C	RX_F2_FreqWord	Rx F2 NCO Frequency Control Word
0x30	LPF_Config_0	PI Controller Configuration and Low-pass Filter Configuration
0x34	LPF_Config_1	PI Controller Configuration Configuration Register 1
0x38	Tx_Data_Width	Modem Tx Input Data Width
0x3C	Rx_Data_Width	Modem Rx Output Data Width
0x40	PRBS_Control	PRBS Control 0
0x44	PRBS_Initial_State	PRBS Control 1
0x48	PRBS_Polynomial	PRBS Control 2
0x4C	PRBS_Error_Mask	PRBS Control 3
0x50	PRBS_Bit_Count	PRBS Status 0
0x54	PRBS_Error_Count	PRBS Status 1
0x58	LPF_Accum_F1	F1 PI Controller Accumulator
0x5C	LPF_Accum_F2	F2 PI Controller Accumulator
0x60	axis_xfer_count	MSK Modem Status 3
0x64	Rx_Sample_Discard	Rx Sample Discard

Offset	Identifier	Name
0x68	LPF_Config_2	PI Controller Configuration Configuration Register 2
0x6C	f1_nco_adjust	F1 NCO Frequency Adjust
0x70	f2_nco_adjust	F2 NCO Frequency Adjust
0x74	f1_error	F1 Error Value
0x78	f2_error	F2 Error Value
0x7C	Tx_Sync_Ctrl	Transmitter Sync Control
0x80	Tx_Sync_Cnt	Transmitter Sync Duration
0x84	lowpass_ema_alpha	Exponential Moving Average Alpha
0x88	lowpass_ema_alpha	Exponential Moving Average Alpha
0x8C	rx_power	Receive Power

Hash_ID_Low register

- Absolute Address: 0x43C00000
- Base Offset: 0x0
- Size: 0x4

Bits	Identifier	Access	Reset	Name
31:0	hash_id_lo	r	0xAAAA5555	Hash ID Lower 32-bits

hash_id_lo field Lower 32-bits of Pluto MSK FPGA Hash ID

Hash_ID_High register

- Absolute Address: 0x43C00004
- Base Offset: 0x4
- Size: 0x4

Bits	Identifier	Access	Reset	Name
31:0	hash_id_hi	r	0x5555AAAA	Hash ID Upper 32-bits

hash_id_hi field Upper 32-bits of Pluto MSK FPGA Hash ID

MSK_Init register

- Absolute Address: 0x43C00008
- Base Offset: 0x8
- Size: 0x4

Synchronous initialization of MSK Modem functions, does not affect configuration registers.

Bits	Identifier	Access	Reset	Name
0	txrxinit	rw	0x1	Tx/Rx Init Enable
1	txinit	rw	0x1	Tx Init Enable
2	rxinit	rw	0x1	Rx Init Enable

txrxinit field 0 -> Normal modem operation 1 -> Initialize Tx and Rx

txinit field 0 -> Normal Tx operation 1 -> Initialize Tx

rxinit field 0 -> Normal Rx operation 1 -> Initialize Rx

MSK_Control register

- Absolute Address: 0x43C0000C
- Base Offset: 0xC
- Size: 0x4

MSK Modem Configuration and Control

Bits	Identifier	Access	Reset	Name
0	ptt	rw	0x0	Push-to-Talk Enable
1	loopback_ena	rw	0x0	Modem Loopback Enable
2	rx_invert	rw	0x0	Rx Data Invert Enable
3	clear_counts	rw	0x0	Clear Status Counters

ptt field 0 -> PTT Disabled 1 -> PTT Enabled

loopback_ena field 0 -> Modem loopback disabled 1 -> Modem loopback enabled

rx_invert field 0 -> Rx data normal 1 -> Rx data inverted

clear_counts field Clear Tx Bit Counter and Tx Enable Counter

MSK_Status register

- Absolute Address: 0x43C00010
- Base Offset: 0x10
- Size: 0x4

Modem status bits

Bits	Identifier	Access	Reset	Name
0	demod_sync_lock	r	0x0	Demodulator Sync Status
1	tx_enable	r	0x0	AD9363 DAC Interface Tx Enable Input Active
2	rx_enable	r	0x0	AD9363 ADC Interface Rx Enable Input Active
3	tx_axis_valid	r	0x0	Tx S_AXIS_VALID

demod_sync_lock field Demodulator Sync Status - not currently implemented

tx_enable field 1 -> Data to DAC Enabled 0 -> Data to DAC Disabled

rx_enable field 1 -> Data from ADC Enabled 0 -> Data from ADC Disabled

tx_axis_valid field 1 -> S_AXIS_VALID Enabled 0 -> S_AXIS_VALID Disabled

Tx_Bit_Count register

- Absolute Address: 0x43C00014
- Base Offset: 0x14
- Size: 0x4

Modem status data

Bits	Identifier	Access	Reset	Name
31:0	tx_bit_counter	r	0x0	Tx Bit Count

tx_bit_counter field Count of data requests made by modem

Tx_Enable_Count register

- Absolute Address: 0x43C00018
- Base Offset: 0x18
- Size: 0x4

Modem status data

Bits	Identifier	Access	Reset	Name
31:0	tx_ena_counter	r	0x0	Tx Enable Count

tx_ena_counter field Number of clocks on which Tx Enable is active

Fb_FreqWord register

- Absolute Address: 0x43C0001C
- Base Offset: 0x1C
- Size: 0x4

Set Modem Data Rate

Bits	Identifier	Access	Reset	Name
31:0	config_data	rw	0x0	Frequency Control Word

config_data field Sets the center frequency of the NCO as $FW = F_n * 2^{32}/F_s$, where F_n is the desired NCO frequency, and F_s is the NCO sample rate

TX_F1_FreqWord register

- Absolute Address: 0x43C00020
- Base Offset: 0x20
- Size: 0x4

Set Modulator F1 Frequency

Bits	Identifier	Access	Reset	Name
31:0	config_data	rw	0x0	Frequency Control Word

config_data field Sets the center frequency of the NCO as $FW = F_n * 2^{32}/F_s$, where F_n is the desired NCO frequency, and F_s is the NCO sample rate

TX_F2_FreqWord register

- Absolute Address: 0x43C00024
- Base Offset: 0x24
- Size: 0x4

Set Modulator F2 Frequency

Bits	Identifier	Access	Reset	Name
31:0	config_data	rw	0x0	Frequency Control Word

config_data field Sets the center frequency of the NCO as $FW = F_n * 2^{32}/F_s$, where F_n is the desired NCO frequency, and F_s is the NCO sample rate

RX_F1_FreqWord register

- Absolute Address: 0x43C00028
- Base Offset: 0x28
- Size: 0x4

Set Demodulator F1 Frequency

Bits	Identifier	Access	Reset	Name
31:0	config_data	rw	0x0	Frequency Control Word

config_data field Sets the center frequency of the NCO as $FW = F_n * 2^{32}/F_s$, where F_n is the desired NCO frequency, and F_s is the NCO sample rate

RX_F2_FreqWord register

- Absolute Address: 0x43C0002C
- Base Offset: 0x2C
- Size: 0x4

Set Demodulator F2 Frequency

Bits	Identifier	Access	Reset	Name
31:0	config_data	rw	0x0	Frequency Control Word

config_data field Sets the center frequency of the NCO as $FW = F_n * 2^{32}/F_s$, where F_n is the desired NCO frequency, and F_s is the NCO sample rate

LPF_Config_0 register

- Absolute Address: 0x43C00030
- Base Offset: 0x30
- Size: 0x4

Configure PI controller and low-pass filter

Bits	Identifier	Access	Reset	Name
0	lpf_freeze	rw	0x0	Freeze the accumulator's current value
1	lpf_zero	rw	0x0	Hold the PI Accumulator at zero
7:2	prbs_reserved	w	0x0	—
31:8	lpf_alpha	rw	0x0	Lowpass IIR filter alpha

lpf_freeze field 0 -> Normal operation 1 -> Freeze current value

lpf_zero field 0 -> Normal operation 1 -> Zero and hold accumulator

lpf_alpha field Value controls the filter rolloff

LPF_Config_1 register

- Absolute Address: 0x43C00034
- Base Offset: 0x34
- Size: 0x4

Configures PI Controller I-gain and divisor

Bits	Identifier	Access	Reset	Name
23:0	i_gain	rw	0x0	Integral Gain Value
31:24	i_shift	rw	0x0	Integral Gain Bit Shift

i_gain field Value m of 0-16,777,215 sets the integral multiplier

i_shift field Value n of 0-32 sets the integral divisor as 2^{-n}

Tx_Data_Width register

- Absolute Address: 0x43C00038
- Base Offset: 0x38
- Size: 0x4

Set the parallel data width of the parallel-to-serial converter

Bits	Identifier	Access	Reset	Name
7:0	data_width	rw	0x8	Modem input/output data width

data_width field Set the data width of the modem input/output

Rx_Data_Width register

- Absolute Address: 0x43C0003C
- Base Offset: 0x3C
- Size: 0x4

Set the parallel data width of the serial-to-parallel converter

Bits	Identifier	Access	Reset	Name
7:0	data_width	rw	0x8	Modem input/output data width

data_width field Set the data width of the modem input/output

PRBS_Control register

- Absolute Address: 0x43C00040
- Base Offset: 0x40
- Size: 0x4

Configures operation of the PRBS Generator and Monitor

Bits	Identifier	Access	Reset	Name
0	prbs_sel	rw	0x0	PRBS Data Select
1	prbs_error_insert	w	0x0	PRBS Error Insert
2	prbs_clear	w	0x0	PRBS Clear Counters
3	prbs_manual_sync	w	0x0	PRBS Manual Sync
15:4	prbs_reserved	w	0x0	—
31:16	prbs_sync_threshold	w	0x0	PRBS Auto Sync Threshold

prbs_sel field 0 -> Select Normal Tx Data 1 -> Select PRBS Tx Data

prbs_error_insert field 0 -> 1 : Insert bit error in Tx data (both Normal and PRBS) 1 -> 0 : Insert bit error in Tx data (both Normal and PRBS)

prbs_clear field 0 -> 1 : Clear PRBS Counters 1 -> 0 : Clear PRBS Counters

prbs_manual_sync field 0 -> 1 : Synchronize PRBS monitor 1 -> 0 : Synchronize PRBS monitor

prbs_sync_threshold field 0 : Auto Sync Disabled N > 0 : Auto sync after N errors

PRBS_Initial_State register

- Absolute Address: 0x43C00044
- Base Offset: 0x44
- Size: 0x4

PRBS Initial State

Bits	Identifier	Access	Reset	Name
31:0	config_data	rw	0x0	PRBS Seed

config_data field Sets the starting value of the PRBS generator

PRBS__Polynomial register

- Absolute Address: 0x43C00048
- Base Offset: 0x48
- Size: 0x4

PRBS Polynomial

Bits	Identifier	Access	Reset	Name
31:0	config_data	rw	0x0	PRBS Polynomial

config_data field Bit positions set to ‘1’ indicate polynomial feedback positions

PRBS__Error_Mask register

- Absolute Address: 0x43C0004C
- Base Offset: 0x4C
- Size: 0x4

PRBS Error Mask

Bits	Identifier	Access	Reset	Name
31:0	config_data	rw	0x0	PRBS Error Mask

config_data field Bit positions set to ‘1’ indicate bits that are inverted when a bit error is inserted

PRBS__Bit_Count register

- Absolute Address: 0x43C00050
- Base Offset: 0x50
- Size: 0x4

PRBS Bits Received

Bits	Identifier	Access	Reset	Name
31:0	status_data	r	0x0	PRBS Bits Received

status_data field Number of bits received by the PRBS monitor since last BER can be calculated as the ratio of received bits to errored-bits

PRBS_Error_Count register

- Absolute Address: 0x43C00054
- Base Offset: 0x54
- Size: 0x4

PRBS Bit Errors

Bits	Identifier	Access	Reset	Name
31:0	status_data	r	0x0	PRBS Bit Errors

status_data field Number of errored-bits received by the PRBS monitor since last sync BER can be calculated as the ratio of received bits to errored-bits

LPF_Accum_F1 register

- Absolute Address: 0x43C00058
- Base Offset: 0x58
- Size: 0x4

Value of the F1 PI Controller Accumulator

Bits	Identifier	Access	Reset	Name
31:0	status_data	r	0x0	PI Controller Accumulator Value

status_data field PI Controller Accumulator Value

LPF_Accum_F2 register

- Absolute Address: 0x43C0005C
- Base Offset: 0x5C
- Size: 0x4

Value of the F2 PI Controller Accumulator

Bits	Identifier	Access	Reset	Name
31:0	status_data	r	0x0	PI Controller Accumulator Value

status_data field PI Controller Accumulator Value

axis_xfer_count register

- Absolute Address: 0x43C00060
- Base Offset: 0x60
- Size: 0x4

Modem status data

Bits	Identifier	Access	Reset	Name
31:0	xfer_count	r	0x0	S_AXIS Transfers

xfer_count field Number completed S_AXIS transfers

Rx_Sample_Discard register

- Absolute Address: 0x43C00064
- Base Offset: 0x64
- Size: 0x4

Configure samples discard operation for demodulator

Bits	Identifier	Access	Reset	Name
7:0	rx_sample_discard	rw	0x0	Rx Sample Discard Value
15:8	rx_nco_discard	rw	0x0	Rx NCO Sample Discard Value

rx_sample_discard field Number of Rx samples to discard

rx_nco_discard field Number of NCO samples to discard

LPF_Config_2 register

- Absolute Address: 0x43C00068
- Base Offset: 0x68
- Size: 0x4

Configures PI Controller I-gain and divisor

Bits	Identifier	Access	Reset	Name
23:0	p_gain	rw	0x0	Proportional Gain Value
31:24	p_shift	rw	0x0	Proportional Gain Bit Shift

p_gain field Value m of 0-16,777,215 sets the proportional multiplier

p_shift field Value n of 0-32 sets the proportional divisor as 2^n

f1_nco_adjust register

- Absolute Address: 0x43C0006C
- Base Offset: 0x6C
- Size: 0x4

Frequency offset applied to the F1 NCO

Bits	Identifier	Access	Reset	Name
31:0	data	r	0x0	F1 NCO Frequency Adjust

data field Frequency offset applied to the F1 NCO

f2_nco_adjust register

- Absolute Address: 0x43C00070
- Base Offset: 0x70
- Size: 0x4

Frequency offset applied to the F2 NCO

Bits	Identifier	Access	Reset	Name
31:0	data	r	0x0	F2 NCO Frequency Adjust

data field Frequency offset applied to the F2 NCO

f1_error register

- Absolute Address: 0x43C00074
- Base Offset: 0x74
- Size: 0x4

Error value of the F1 Costas loop after each active bit period

Bits	Identifier	Access	Reset	Name
31:0	data	r	0x0	F1 Error Value

data field Error value of the F1 Costas loop after each active bit period

f2_error register

- Absolute Address: 0x43C00078
- Base Offset: 0x78
- Size: 0x4

Error value of the F2 Costas loop after each active bit period

Bits	Identifier	Access	Reset	Name
31:0	data	r	0x0	F2 Error Value

data field Error value of the F2 Costas loop after each active bit period

Tx_Sync_Ctrl register

- Absolute Address: 0x43C0007C
- Base Offset: 0x7C
- Size: 0x4

Provides control bits for generation of transmitter synchronization patterns

Bits	Identifier	Access	Reset	Name
0	tx_sync_ena	rw	0x0	Tx Sync Enable
1	tx_sync_force	rw	0x0	Tx Sync Force
2	tx_sync_f1	rw	0x0	Tx F1 Sync Enable
3	tx_sync_f2	rw	0x0	Tx F2 Sync Enable

tx_sync_ena field 0 -> Disable sync transmission 1 -> Enable sync transmission when PTT is asserted

tx_sync_force field 0 : Normal operation) 1 : Transmit synchronization pattern)

tx_sync_f1 field Enables/Disables transmission of F1 tone for receiver synchronization 0 : F1 tone transmission disabled 1 : F1 tone transmission enabled Both F1 and F2 can be enabled at the same time

tx_sync_f2 field Enables/Disables transmission of F2 tone for receiver synchronization 0 : F2 tone transmission disabled 1 : F2 tone transmission enabled Both F1 and F2 can be enabled at the same time

Tx_Sync_Cnt register

- Absolute Address: 0x43C00080
- Base Offset: 0x80
- Size: 0x4

Sets the duration of the synchronization tones when enabled

Bits	Identifier	Access	Reset	Name
23:0	tx_sync_cnt	rw	0x0	Tx sync duration

tx_sync_cnt field Value from 0x00_0000 to 0xFF_FFFF. This value represents the number bit-times the synchronization signal should be sent after PTT is asserted.

lowpass_ema_alpha1 register

- Absolute Address: 0x43C00084
- Base Offset: 0x84
- Size: 0x4

Sets the alpha for the EMA

Bits	Identifier	Access	Reset	Name
17:0	alpha	rw	0x0	EMA alpha

alpha field Value from 0x0_0000 to 0x3_FFFF represent the EMA alpha

lowpass_ema_alpha2 register

- Absolute Address: 0x43C00088
- Base Offset: 0x88
- Size: 0x4

Sets the alpha for the EMA

Bits	Identifier	Access	Reset	Name
17:0	alpha	rw	0x0	EMA alpha

alpha field Value from 0x0_0000 to 0x3_FFFF represent the EMA alpha

rx_power register

- Absolute Address: 0x43C0008C
- Base Offset: 0x8C
- Size: 0x4

Receive power computed from I/Q ssamples

Bits	Identifier	Access	Reset	Name
22:0	rx_power	r	0x0	Receive Power

rx_power field Value that represent the RMS power of the incoming I;