CIRCUIT main board — schematic status

All nine sheets are drawn as DRAFTS. Each sheet lists, in its header note, what is from memory and must be confirmed.

Biggest open items: display FPC pin order (placeholder), MCU power-pin network, charger and regulator values, backlight LED topology. Nothing here has been through an electrical rules check or a human review.

Signals between sheets use global labels. No routing before this schematic is complete and reviewed.

USB-C input, CC, ESD

File: usb.kicad_sch

Haptics, buttons, debug

File: hmi.kicad_sch

Main MCU STM32U5G9

File: mcu.kicad_sch

Battery, charger, 3V3, load switches

File: power.kicad_sch

Secure element

File: secure.kicad_sch

BLE module

File: ble.kicad_sch

NFC tag and antenna

File: nfc.kicad_sch

Display, touch, backlight

File: display.kicad_sch


DRAFT — generated by hardware/scripts/gen_schematic.py — not reviewed

Sheet: /
File: circuit.kicad_sch

Title: Circuit main board

Size: A3	Date:	**Rev: A0-draft**
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 1/9

USB-C INPUT (5 V sink, USB 2.0 device, no Power Delivery)
- R1/R2: 5.1k Rd on each CC pin separately (USB Type-C sink requirement).
- USB_CC1/USB_CC2 go to MCU ADC inputs to read source current (0.5/1.5/3 A).
- U2 clamps D+/D- and VBUS. Both pins of each I/O pair are one node: route through the part.
- C1 kept small: a sink may present at most 10 uF on VBUS.
TODO before review: 20 V-tolerant CC protection (TPD4S311-class, no library symbol yet);
VBUS over-voltage is handled by the charger input rating - confirm from charger datasheet;
shield-to-ground scheme (R3) to be decided with the enclosure ESD path.



DRAFT - generated by hardware/scripts/gen_schematic.py - not reviewed

Sheet: /USB-C input, CC, ESD/
File: usb.kicad_sch


Title: USB-C input, CC, ESD


Size: A3	Date:	**Rev: A0-draft**
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 2/9


HAPTICS: DRV2605L drives an 8 mm LRA from +3V3 (kept powered; EN low gives microamp shutdown and keeps I2C active). Pull-up sets
R4 holds EN low while the MCU is in reset. Pin 6 (VDD/NC) left open — CHECK datasheet.
C2/C3 values (1 uF) are defaults — CHECK datasheet.


BUTTONS: active-low, I2C bus-independent.
The MCU reads BTN_CONFIRM_N directly in the secure world; it is the only signing approval input.
BTN_POWER_RAW also goes to the charger push-button input (power sheet, not drawn yet).
Switch and TVS part numbers TBD (candidates: Panasonic EVQ-P7 side-push; 0402 ESD diode).


DEBUG: Tag-Connect TC2030-NL pads,
no connector fitted. Internal only.
Production: debug locked in the MCU;
pads not reachable with the case closed.















TAMPER: two case-open switch positions. Closed to GND when the case is shut; pulled up to the MCU backup rail.



DRAFT — generated by hardware/scripts/gen_schematic.py — not reviewed

Sheet: /Haptics, buttons, debug/
File: hmi.kicad_sch

Title: Haptics, buttons, debug


Size: A3	Date:	Rev: A0-draft
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 3/9

MAIN MCU: STM32U5G9NJH6Q, TFBGA-216 13x13 mm, 0.8 mm pitch. Pin functions are taken from the KiCad library's alternate-function data. Every ball not listed in PINMAP is left unconnected (spare GPIO).


MUST BE CONFIRMED AGAINST THE DATASHEET AND AN5373 BEFORE REVIEW (st.com was not reachable):
1. SMPS network: L1 value and the capacitor on each VDD11 ball (C20-C22).
2. VDD11USB: whether it is tied to VDD11 (R20 fitted) or only decoupled (R20 not fitted).
3. DSI unused: required connection of VDDDSI, VDD11DSI/VCAPDSI and the DSI balls.
4. VBAT: tied to +3V3 through R21 for now; becomes the coin-cell backup rail if tamper-in-storage is adopted.
5. HSE 16 MHz (as on ST's dev kit) is assumed valid for the USB HS PHY; crystal load capacitors C30-C33 are placeholders.
6. Decoupling count and values (C10-C19, C23-C29) are defaults.

Nets ending in another sheet that is not drawn yet (display, touch, secure element, BLE, NFC, charger) are single-ended for now.


Decoupling: C10-C19 at VDD balls; C24/C25 VDDIO2; C26 VDDUSB; C27 VDDSMPS; C28 VDDDSI




Core supply (internal SMPS) - values TBD from datasheet




Analog supply and reference



Reset and boot




Clocks: 16 MHz HSE, 32.768 kHz LSE (load capacitors depend on the crystals chosen)



I2C pull-ups (touch bus pulls to the switched LCD rail so it cannot back-power the panel)





DRAFT - generated by hardware/scripts/gen_schematic.py - not reviewed


Sheet: /Main MCU STM32U5G9/
File: mcu.kicad_sch


Title: Main MCU STM32U5G9

Size: A2	Date:	Rev: A0-draft
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 4/9


POWER: USB VBUS -> BQ24075 power-path charger -> VSYS -> TPS63001 buck-boost -> +3V3 (always on).
Load switches gate the display rail and the BLE module rail. Battery voltage is read through a 1M/1M divider.
Defaults with the MCU unpowered: EN1 = EN2 = 0 -> 100 mA input limit (safe on any USB port). MCU raises EN1 for 500 mA,
or EN2 for the R31 limit after reading the CC pins.


VALUES FROM MEMORY OF TI DATASHEETS - CONFIRM: R30 (ISET, 890/R = 0.5 A), R31 (ILIM, 1610/R = 1.0 A), TMR left open = default
safety timers, R32 = 10k in place of a pack NTC (use the pack's NTC if it has one), TPS63001 L2 and capacitors, CT capacitors.
Battery connector polarity MUST be checked against the chosen cell. No VBUS over-voltage switch is fitted: BQ24075 input rating relied on.








Load switches (off by default) and battery sense














3.3 V buck-boost (fixed-output TPS63001, power-save enabled)










DRAFT - generated by hardware/scripts/gen_schematic.py - not reviewed


Sheet: /Battery, charger, 3V3, load switches/
File: power.kicad_sch

Title: Battery, charger, 3V3, load switches

Size: A3	Date:	**Rev: A0-draft**
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 5/9

SECURE ELEMENT: Infineon OPTIGA Trust M V3 (SLS32AIA010MK, PG-USON-10 3x3 mm) on its own I2C bus.
Holds the DWalletCap authority key, gates the storage key behind the PIN, provides device attestation and counters.
Pin-to-pad mapping and the tying of unused pads to ground follow Adafruit's published Trust M breakout (open hardware);
CONFIRM against the Infineon datasheet, including the footprint's exposed-pad size.
Bus pull-ups are on the MCU sheet. SE_RST_N lets the MCU reset the part.






DRAFT - generated by hardware/scripts/gen_schematic.py - not reviewed


Sheet: /Secure element/
File: secure.kicad_sch

Title: Secure element


Size: A3	Date:	**Rev: A0-draft**
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 6/9

BLE: Raytac MDBT50Q-1MV2 (nRF52840, chip antenna) used only as an untrusted serial transport.
Chosen over the nRF54L15 module of the Phase 1 proposal because its symbol and footprint are in the reviewed KiCad library.
Rail +3V3_BLE is switched by the MCU. Firmware must drive the UART and reset lines low or high-Z while the rail is off.
UART pins are arbitrary nRF GPIOs (set in the module firmware). VDD and VDDH tied (normal-voltage mode), USB and DC/DC pins unused.
J5 programs the module. Keep copper and components out of the antenna keep-out in the Raytac layout guide.





Signal direction (names are from the MCU's point of view):
BLE_UART_TX MCU -> module P0.08
BLE_UART_RX module P0.06 -> MCU
BLE_UART_RTS MCU -> module P0.07
BLE_UART_CTS module P0.05 -> MCU
BLE_WAKE   module P0.13 -> MCU wake-up pin




DRAFT - generated by hardware/scripts/gen_schematic.py - not reviewed


Sheet: /BLE module/
File: ble.kicad_sch


Title: BLE module

Size: A3 | Date: | **Rev: A0-draft**
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4 | Id: 7/9

NFC: ST25DV04K dynamic tag (ISO 15693 / NFC Type 5), I2C on the system bus. The phone is the reader.
Chosen over NTAG I2C plus because its symbol is in the reviewed KiCad library; ST25DV04KC is the current revision — confirm pin compatibility.
Powered from +3V3 (not switched) so it never loads the shared I2C bus. GPO is open-drain -> NFC_FD wakes the MCU on RF field.
Antenna: FPC coil on the rear cover with ferrite, connected at J6. C56 is a tuning position, fitted only after measuring in the enclosure.
No secrets are ever written to this tag: it carries a signed pairing payload only.








DRAFT — generated by hardware/scripts/gen_schematic.py — not reviewed


Sheet: /NFC tag and antenna/
File: nfc.kicad_sch

Title: NFC tag and antenna


Size: A3	Date:	**Rev: A0-draft**
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 8/9


DISPLAY: 3.5 in IPS 320x480 driven as RGB565 from the MCU's LTDC, with SPI for controller set-up.
!! J7 and J8 PIN ORDER IS A PLACEHOLDER. No panel datasheet could be opened. The signal SET is complete; the ORDER must be
re-mapped to the purchased panel's FPC pinout (and connector pin count / top-bottom contact) before layout.
Unused low-order colour bits and interface-select (IM) straps are panel-specific and not shown.
BACKLIGHT: TPS61165 boost assumes the panel's LEDs are one SERIES string (R46 = 200 mV / I_LED -> 20 mA). If the panel's LEDs
are in parallel this circuit is wrong and is replaced by a low-side PWM switch. Values from memory - confirm.














DRAFT - generated by hardware/scripts/gen_schematic.py - not reviewed

Sheet: /Display, touch, backlight/
File: display.kicad_sch

Title: Display, touch, backlight

Size: A3	Date:	Rev: A0-draft
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 9/9