CORKTOWN AUDIO WORKS

BENCH REPORT

17241 Prairie St, Detroit, MI 48221 | (313) 555-0147 | kofi@corktownaudio.com

SKU **CAW-1121**

Unit Yamaha CR-620 AM/FM stereo receiver, silver faceplate

Bench date 2026-08-26 **Technician** Kofi Mensah

INCOMING CONDITION

First power-up on the dim-bulb tester: the bulb flared and settled, idle draw normal, sound on both channels. Every dial and meter lamp lit. Volume and tone pots scratchy, input selector crackling between positions. Idle bias and DC offset had drifted from the service manual values, and the tuning meter sat off centre on strong FM stations.

WORK PERFORMED

1. Pots and switches cleaned with DeoxIT and worked through their full travel: volume, balance, bass and treble; input selector, tape monitor and speaker switches.
2. Dial and meter lamps checked: all working, none replaced.
3. Idle bias set on both channels to the service manual value, rechecked after a 30 minute warm-up.
4. DC offset set at the speaker terminals: under 8 mV on both channels (readings below).
5. Tuner aligned on the signal generator: FM IF, discriminator and stereo decoder. AM checked across the band.
6. Signal and tuning meters checked against the generator: both accurate.

MEASUREMENTS *(8 ohm resistive dummy load, both channels driven)*

Measurement	Conditions	Left	Right	Target	Result
Output power	1 kHz sine, 19.0 V RMS	45 W	45 W	45 W/ch into 8 ohms	PASS
THD	1 kHz sine at 45 W/ch	0.03%	0.04%	under 0.05%	PASS
DC offset	no signal, after warm-up	5 mV	7 mV	under 10 mV	PASS

FUNCTIONAL CHECKS

Check	Notes	Result
FM tuner	Aligned. Stereo lamp lights and holds on WRCJ 90.9.	PASS
AM tuner	Clean reception on WWJ 950, no whistle or hum.	PASS
Signal and tuning meters	Both accurate. Tuning needle centres on the station.	PASS
Phono, aux, tape monitor	Clean on both channels. Phono quiet with the volume well up.	PASS
Volume, balance, tone	Quiet through full rotation after cleaning.	PASS
Speaker switches, phones	Both speaker outputs and the headphone jack switch cleanly.	PASS
Burn-in	2 hours at 1/8 power into the dummy load. Bias and offset unchanged.	PASS

RESULT

PASS

All functions to spec.

Ready for master photos and grading.

SIGNED OFF

Kofi Mensah

Technician, 2026-08-26