German International University
Faculty of Informatics and Computer Science
Information Security
Dr. Marwa Zamzam
Thomas Safwat
Peter Wafik
Salma Abu Zaid
Mohamed Wael

Task 1 : DES Encryption with CBC Mode

Deadline: Friday, 14 March 2025, 11:59 PM

---

1 Introduction

In this task, your group of three will implement a Python function to encrypt any plaintext, such as "Hello DES in CBC Mode,üsing the DES algorithm in CBC mode. You'll start with a 64-bit block and 16 round keys (48 bits each), running 16 rounds of DES encryption, and then scale it up for larger messages.

2 Details

You're given a starter Python notebook with tables for permutations and 16 round keys to work with.

Your task:

- Build a DES function that encrypts a 64-bit block over 16 rounds. For each round, clearly show the output of every step (e.g., expansion, key mixing, substitution, permutation) in a readable format. After the 16th round, swap the halves and apply the final permutation, displaying those results too.
- Extend it to encrypt any plaintext (e.g., "Hello DES in CBC Mode") in CBC mode by splitting it into 64-bit blocks, padding if needed, and chaining with an IV. Show the key steps for each block's encryption.

The notebook has a sample IV and some helper tools if you need them.

3 Submission

Your group of three students should include all names and IDs in a comment at the top of your notebook. Submit one Python notebook (.ipynb) with your DES function, CBC mode setup, and output for a sample plaintext like "Hello DES in CBC Mode,"clearly showing each step's results for all rounds. Name your notebook after your team, e.g., `TeamAlpha.ipynb`. Upload it via:
`https://forms.gle/vinP2p1Wd1N81FPS9`

The Initial Permutation: IP

58	50	42	34	26	18	10	2
60	52	44	36	28	20	12	4
62	54	46	38	30	22	14	6
64	56	48	40	32	24	16	8
57	49	41	33	25	17	9	1
59	51	43	35	27	19	11	3
61	53	45	37	29	21	13	5
63	55	47	39	31	23	15	7

Figuur 1: Initial permutation

DES Supplementary Material
E- Bit selection table

E BIT-SELECTION TABLE

32	1	2	3	4	5
4	5	6	7	8	9
8	9	10	11	12	13
12	13	14	15	16	17
16	17	18	19	20	21
20	21	22	23	24	25
24	25	26	27	28	29
28	29	30	31	32	1

Expand 32 bit R_{n-1} to 48 bit

Figuur 2: E bit selection

The 4×16 substitution table for S-box S_1															
14	4	13	1	2	15	11	8	3	10	6	12	5	9	0	7
0	15	7	4	14	2	13	1	10	6	12	11	9	5	3	8
4	1	14	8	13	6	2	11	15	12	9	7	3	10	5	0
15	12	8	2	4	9	1	7	5	11	3	14	10	0	6	13
S-box S_2															
15	1	8	14	6	11	3	4	9	7	2	13	12	0	5	10
3	13	4	7	15	2	8	14	12	0	1	10	6	9	11	5
0	14	7	11	10	4	13	1	5	8	12	6	9	3	2	15
13	8	10	1	3	15	4	2	11	6	7	12	0	5	14	9
S-box S_3															
10	0	9	14	6	3	15	5	1	13	12	7	11	4	2	8
13	7	0	9	3	4	6	10	2	8	5	14	12	11	15	1
13	6	4	9	8	15	3	0	11	1	2	12	5	10	14	7
1	10	13	0	6	9	8	7	4	15	14	3	11	5	2	12
S-box S_4															
7	13	14	3	0	6	9	10	1	2	8	5	11	12	4	15
13	8	11	5	6	15	0	3	4	7	2	12	1	10	14	9
10	6	9	0	12	11	7	13	15	1	3	14	5	2	8	4
3	15	0	6	10	1	13	8	9	4	5	11	12	7	2	14
S-box S_5															
2	12	4	1	7	10	11	6	8	5	3	15	13	0	14	9
14	11	2	12	4	7	13	1	5	0	15	10	3	9	8	6
4	2	1	11	10	13	7	8	15	9	12	5	6	3	0	14
11	8	12	7	1	14	2	13	6	15	0	9	10	4	5	3
S-box S_6															
12	1	10	15	9	2	6	8	0	13	3	4	14	7	5	11
10	15	4	2	7	12	9	5	6	1	13	14	0	11	3	8
9	14	15	5	2	8	12	3	7	0	4	10	1	13	11	6
4	3	2	12	9	5	15	10	11	14	1	7	6	0	8	13
S-box S_7															
4	11	2	14	15	0	8	13	3	12	9	7	5	10	6	1
13	0	11	7	4	9	1	10	14	3	5	12	2	15	8	6
1	4	11	13	12	3	7	14	10	15	6	8	0	5	9	2
6	11	13	8	1	4	10	7	9	5	0	15	14	2	3	12
S-box S_8															
13	2	8	4	6	15	11	1	10	9	3	14	5	0	12	7
1	15	13	8	10	3	7	4	12	5	6	11	0	14	9	2
7	11	4	1	9	12	14	2	0	6	10	13	15	3	5	8
2	1	14	7	4	10	8	13	15	12	9	0	3	5	6	11

Figuur 3: S-boxes

P Box

Table 3.7 Permutation Function P

16	7	20	21
29	12	28	17
1	15	23	26
5	18	31	10
2	8	24	14
32	27	3	9
19	13	30	6
22	11	4	25

Figuur 4: Permutation function

40	8	48	16	56	24	64	32
39	7	47	15	55	23	63	31
38	6	46	14	54	22	62	30
37	5	45	13	53	21	61	29
36	4	44	12	52	20	60	28
35	3	43	11	51	19	59	27
34	2	42	10	50	18	58	26
33	1	41	9	49	17	57	25

Figuur 5: Final permutation table