SIEMENS

SIMATIC

TIA Portal Openness Hardware parameters

System Manual

Additional information

05/2021
Additional Information

Legal information

Warning notice system

This manual contains notices you have to observe in order to ensure your personal safety, as well as to prevent damage to property. The notices referring to your personal safety are highlighted in the manual by a safety alert symbol, notices referring only to property damage have no safety alert symbol. These notices shown below are graded according to the degree of danger.

⚠ **DANGER**
indicates that death or severe personal injury **will** result if proper precautions are not taken.

⚠ **WARNING**
indicates that death or severe personal injury **may** result if proper precautions are not taken.

⚠ **CAUTION**
indicates that minor personal injury can result if proper precautions are not taken.

NOTICE
indicates that property damage can result if proper precautions are not taken.

If more than one degree of danger is present, the warning notice representing the highest degree of danger will be used. A notice warning of injury to persons with a safety alert symbol may also include a warning relating to property damage.

Qualified Personnel

The product/system described in this documentation may be operated only by **personnel qualified** for the specific task in accordance with the relevant documentation, in particular its warning notices and safety instructions. Qualified personnel are those who, based on their training and experience, are capable of identifying risks and avoiding potential hazards when working with these products/systems.

Proper use of Siemens products

Note the following:

⚠ **WARNING**
Siemens products may only be used for the applications described in the catalog and in the relevant technical documentation. If products and components from other manufacturers are used, these must be recommended or approved by Siemens. Proper transport, storage, installation, assembly, commissioning, operation and maintenance are required to ensure that the products operate safely and without any problems. The permissible ambient conditions must be complied with. The information in the relevant documentation must be observed.

Trademarks

All names identified by ® are registered trademarks of Siemens AG. The remaining trademarks in this publication may be trademarks whose use by third parties for their own purposes could violate the rights of the owner.

Disclaimer of Liability

We have reviewed the contents of this publication to ensure consistency with the hardware and software described. Since variance cannot be precluded entirely, we cannot guarantee full consistency. However, the information in this publication is reviewed regularly and any necessary corrections are included in subsequent editions.

Siemens AG
Digital Industries
Postfach 48 48
90026 NÜRNBERG
GERMANY

Document order number: Additional Information
Ⓟ 03/2021 Subject to change

Copyright © Siemens AG 2021.
All rights reserved

Table of contents

1

Parameter of hardware modules

S7 1500	(198)
S7 1500 - DTF modules	(54)
S7 1500 - R/H modules	(86)
S7 1500 - Siplus modules	(177)
PN Driver	(7)
PC Station Plus	(20)
ET200SP - Interface modules	(27)
ET200SP - DI modules	(163)
ET200SP - DQ modules	(105)
ET200SP - AI modules	(161)
ET200SP - AQ moules	(21)
ET200SP - CM PtP / TM modules	(8)
ET200SP - TM modules	(128)
ET200SP - Virtual modules	(1)
Energy meter modules	(37)
ET200SP - Motorstarters	(1471)
ET200SP - IO Link modules	(8)
ET200SP - ASi modules	(153)
ET200SP - Fail-safe IO modules	(52)
ET200SP - Special modules	(6)
SIWAREX modules	(2)
ET 200AL modules	(96)
ET 200eco - PN / IO Link modules	(6)
ET 200Pro - IM /IO modules	(5)
ET 200pro - CMIOLink	(1)
Coupler	(4)
SCALANCE modules	(13)
Openness for SCALANCE	(30)
Openness for SIMATIC Ident	(52)
Ident modules	(193)
HMI Keypanel	(10)
Simocode modules	(59)
Sentron modules	(162)

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0					
	InterfaceType	Int32			
	InterfaceOperatingModes	Int32			
	Label	String			
	DpWatchdog	Boolean	Watchdog		
	Name	String	Name		
	Author	String	Author		
	Comment	String	Comment		
	Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
	DpOperatingMode	UInt64	Operating mode		
				1	DpMaster
				2	DpSlave
	TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
				2	AsSlave
				1	AsMaster
				0	None
	TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
				0	None
				1	Value1Second
				2	Value10Seconds
				3	Value1Minute
				4	Value10Minutes
				5	Value1Hour
				6	Value12Hours
				7	Value24Hours
	DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
	TypeName	String	InvariantTypeName		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Index		
Module					
	DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
	PositionNumber	Int32	Index		
	Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Comment	String	Comment		
Module - 6ES7 51*-***-*AB0 - V2.9**						
		NetworkFaultsAsMaintenance	Boolean			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		WebserverUpdateInterval	UInt64	Update interval		
		SystemPowerSupplyExternal	UInt64	General		
					0	NoConnectionToExternal24VSupply
					1	ConnectionToExternal24VSupply
		Name	String	Name		
		WebserverActivate	Boolean			
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					3	SimaticOpcUaS71500Large

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
					2	SimaticOpcUaS71500Medium
					1	SimaticOpcUaS71500Small
					0	NoLicense
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					34	UtcPlus0200Istanbul
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					15	UtcMinus0330Newfoundland
					72	UtcMinus0400Santiago
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					71	UtcMinus0400Cuiaba
					70	UtcMinus0400AtlanticStandardTimeCanada
					69	UtcMinus0400Asuncion
					112	UtcMinus0400Caracas
					13	UtcMinus0430Caracas
					12	UtcMinus0500IndianaEast
					11	UtcMinus0500EasternStandardTimeUsaCanada

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
					10	UtcMinus0500BogotaLimaQuito
					9	UtcMinus0600Saskatchewan
					83	UtcPlus0200Damascus
					82	UtcPlus0200Beirut
					28	UtcPlus0200AthensBucharest
					81	UtcPlus0100Windhoek
					80	UtcPlus0100WestCentralAfrica
					79	UtcPlus0100TripoliOld
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					23	UtcMonroviaReykjavik
					78	UtcCoordinatedUniversalTime
					113	UtcPlus0300Istanbul
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					22	UtcDublinEdinburghLisbonLondon
					21	UtcCasablanca
					20	UtcMinus0100CapeVerde
					19	UtcMinus0100Azores
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					76	UtcMinus0300Salvador
					75	UtcMinus0300Montevideo
					74	UtcMinus0300Greenland
					73	UtcMinus0300CayenneFortaleza
					17	UtcMinus0300BuenosAires
					16	UtcMinus0300Brasilia
					68	UtcMinus0600CentralAmerica
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					7	UtcMinus0600CentralStandardTimeUsaCanada
					6	UtcMinus0700MountainStandardTimeUsaCanada
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					5	UtcMinus0700Arizona

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
					107	UtcMinus0800PacificStandardTimeUsaCanada
					106	UtcMinus0800PacificStandardTimeMexico
					3	UtcMinus0900Alaska
					2	UtcMinus1000Hawaii
					65	UtcMinus1100MidwayIslands
					0	UtcMinus1200EniwetokKwajalein
					77	UtcMinus0200MidMinusatlantic
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					111	UtcPlus1000Magadan
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					114	UtcPlus1100Magadan114
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					12	December
					11	November
					10	October
					9	September
					8	August
					7	July
					6	June
					5	May
					4	April
					3	March
					2	February
					1	January
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					2	StartupCpuIfMismatch
					1	StartupCpuOnlyIfCompatible
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
					4	Hours
					3	Minutes
					2	Seconds
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		MacRtLicensePurchased	UInt64	Type of purchased license		
					0	NoLicense
					1	LicenseMacBasic
					2	LicenseMacAdvanced
		HostAndDomainnameActive	Boolan	Enable host and domain name		
		HostnameConfiguration	UInt32	Hostname configuration		
					0	Disabled
					1	SetHostnameAtDevice

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9					
				2	SetHostnameInProject
				3	SetHostnameRemotely
	HostnameIdenticalToDeviceNameActive	Boolean	Hostname identical to device name		
	Hostname	String	Hostname		
	DomainConfiguration	UInt32	Domain configuration		
				0	Disabled
				1	SetDomainAtDevice
				2	SetDomainInProject
				3	SetDomainRemotely
	Domain	String	Domain configuration		
	FullName	String	Full Name		
	PnDnsConfigNameResolve	Int32			
	TimeSynchronizationNtpV2	UInt32	Enable time synchronization via NTP server		
				0	Disabled
				1	SetServersAtDevice
				2	SetServersInProject
				3	SetServersRemotely
	TimeSynchronizationServer1	String	Server 1		
	TimeSynchronizationServer2	String	Server 2		
	TimeSynchronizationServer3	String	Server 3		
	TimeSynchronizationServer4	String	Server 4		
	TimeSynchronizationUpdateInterval	UInt64	Update interval		
SIMATIC Memory Card					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
	DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
	PositionNumber	Int32	Index		
Display					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					3600	Value1Hour
					1800	Value30Minutes
					900	Value15Minutes
					600	Value10Minutes
					300	Value5Minutes
					120	Value2Minutes
					60	Value1Minute
					0	Disabled
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9					
				1	AsMaster
				2	AsSlave
	TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
				0	None
				1	Value1Second
				2	Value10Seconds
				3	Value1Minute
				4	Value10Minutes
				5	Value1Hour
				6	Value12Hours
				7	Value24Hours
	Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
	PositionNumber	Int32	Index		
Virtual interface					
	InterfaceType	Int32			
	Label	String			
	Comment	String	Comment		
	Author	String	Author		
	Name	String	Name		
	PositionNumber	Int32	Index		
IO Interface					
	PnSendClock	Int64			
	IECV22LLDPMode	Boolean			
	DeviceReplacementWithoutExchangeableMedium	Boolean			
	OverwriteDeviceNames	Boolean			
	LoadLimitation	Boolean			
	DiagnosticsCommunicationError	Boolean			
	KeepAlivesInterval	UInt32			
	CalculatedBandwidthForCyclicIoData	Int32			
	MaxBandwidthForCyclicIoData	Int32			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
		Comment	String	Comment		
		IsIoController	Boolean	IO controller		
		IsIoDevice	Boolean	IO device		
		ParameterAssignmentOfPnInterfaceByHigherLevel	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					1	Active
					0	Deactivated
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		OptionalIoDevice	Boolean	Optional IO-Device		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
		PositionNumber	Int32	Index		
	IRT Interface					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Comment	String	Comment		
		IsIoController	Boolean	IO controller		
		IsIoDevice	Boolean	IO device		
		ParameterAssignmentOfPnInterfaceByHigherLevel	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		OptionalIoDevice	Boolean	Optional IO-Device		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.9						
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
			Int32			
		Label	String			
		DpWatchdog	Boolean	Watchdog		
		Name	String	Name		
		Author	String	Author		
		Comment	String	Comment		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					2	AsSlave
					1	AsMaster
					0	None
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		TypeName	String	InvariantTypeName		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
Module						
		DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
		PositionNumber	Int32	Index		
		Name	String	Name		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Comment	String	Comment		
Module - 6ES7 51*-***-*AB0 - V2.8**						
		NetworkFaultsAsMaintenance	Boolean			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		WebserverUpdateInterval	UInt64	Update interval		
		SystemPowerSupplyExternal	UInt64	General		
					0	NoConnectionToExternal24VSupply
					1	ConnectionToExternal24VSupply
		Name	String	Name		
		WebserverActivate	Boolean			
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					3	SimaticOpcUaS71500Large

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8						
					2	SimaticOpcUaS71500Medium
					1	SimaticOpcUaS71500Small
					0	NoLicense
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					34	UtcPlus0200Istanbul
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					15	UtcMinus0330Newfoundland
					72	UtcMinus0400Santiago
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					71	UtcMinus0400Cuiaba
					70	UtcMinus0400AtlanticStandardTimeCanada
					69	UtcMinus0400Asuncion
					112	UtcMinus0400Caracas
					13	UtcMinus0430Caracas
					12	UtcMinus0500IndianaEast
					11	UtcMinus0500EasternStandardTimeUsaCanada

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8						
					10	UtcMinus0500BogotaLimaQuito
					9	UtcMinus0600Saskatchewan
					83	UtcPlus0200Damascus
					82	UtcPlus0200Beirut
					28	UtcPlus0200AthensBucharest
					81	UtcPlus0100Windhoek
					80	UtcPlus0100WestCentralAfrica
					79	UtcPlus0100TripoliOld
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					23	UtcMonroviaReykjavik
					78	UtcCoordinatedUniversalTime
					113	UtcPlus0300Istanbul
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8						
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					22	UtcDublinEdinburghLisbonLondon
					21	UtcCasablanca
					20	UtcMinus0100CapeVerde
					19	UtcMinus0100Azores
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					76	UtcMinus0300Salvador
					75	UtcMinus0300Montevideo
					74	UtcMinus0300Greenland
					73	UtcMinus0300CayenneFortaleza
					17	UtcMinus0300BuenosAires
					16	UtcMinus0300Brasilia
					68	UtcMinus0600CentralAmerica
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					7	UtcMinus0600CentralStandardTimeUsaCanada
					6	UtcMinus0700MountainStandardTimeUsaCanada
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					5	UtcMinus0700Arizona

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8						
					107	UtcMinus0800PacificStandardTimeUsaCanada
					106	UtcMinus0800PacificStandardTimeMexico
					3	UtcMinus0900Alaska
					2	UtcMinus1000Hawaii
					65	UtcMinus1100MidwayIslands
					0	UtcMinus1200EniwetokKwajalein
					77	UtcMinus0200MidMinusatlantic
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					111	UtcPlus1000Magadan
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					114	UtcPlus1100Magadan114
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8					
	TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
	TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
	TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
				1	First
				2	Second
				3	Third
				4	Fourth
				5	Last
	TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
				1	Sunday
				2	Monday
				3	Tuesday
				4	Wednesday
				5	Thursday
				6	Friday
				7	Saturday
	TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
				12	December
				11	November
				10	October
				9	September
				8	August
				7	July
				6	June
				5	May
				4	April
				3	March
				2	February
				1	January
	TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
				0	Midnight
				1	Value0100AM
				2	Value0200AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8						
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8						
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8					
				17	Value0500PM
				18	Value0600PM
				19	Value0700PM
				20	Value0800PM
				21	Value0900PM
				22	Value1000PM
				23	Value1100PM
	ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
	ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
	ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
	ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
	StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
				0	NoRestartRemainInStopMode
				1	WarmRestartRun
				3	WarmRestartOperatingModeBeforePowerOff
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
				2	StartupCpuIfMismatch
				1	StartupCpuOnlyIfCompatible
	CycleMaximumCycleTime	UInt64	Maximum cycle time		
	CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
	CycleMinimumCycleTime	UInt64	Minimum cycle time		
				4	Hours
				3	Minutes
				2	Seconds
	CycleCommunicationLoad	UInt64	Cycle load due to communication		
SIMATIC Memory Card					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
	DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
	PositionNumber	Int32	Index		
Display					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					3600	Value1Hour
					1800	Value30Minutes
					900	Value15Minutes
					600	Value10Minutes
					300	Value5Minutes
					120	Value2Minutes
					60	Value1Minute
					0	Disabled
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8						
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8					
	DpOperatingMode	UInt64	Operating mode		
				1	DpMaster
	TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
				0	None
				1	AsMaster
				2	AsSlave
	TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
				0	None
				1	Value1Second
				2	Value10Seconds
				3	Value1Minute
				4	Value10Minutes
				5	Value1Hour
				6	Value12Hours
				7	Value24Hours
	Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
	PositionNumber	Int32	Index		
Virtual interface					
	InterfaceType	Int32			
	Label	String			
	Comment	String	Comment		
	Author	String	Author		
	Name	String	Name		
	PositionNumber	Int32	Index		
IO Interface					
	PnSendClock	Int64			
	IECV22LLDPMode	Boolean			
	DeviceReplacementWithoutExchangeableMedium	Boolean			
	OverwriteDeviceNames	Boolean			
	LoadLimitation	Boolean			
	DiagnosticsCommunicationError	Boolean			
	KeepAlivesInterval	UInt32			
	CalculatedBandwidthForCyclicIoData	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8						
		MaxBandwidthForCyclicIoData	Int32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Comment	String	Comment		
		IsIoController	Boolean	IO controller		
		IsIoDevice	Boolean	IO device		
		ParameterAssignmentOfPnInterfaceByHigherLevel	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					1	Active
					0	Deactivated
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		OptionalIoDevice	Boolean	Optional IO-Device		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8						
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
		PositionNumber	Int32	Index		
	IRT Interface					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Comment	String	Comment		
		IsIoController	Boolean	IO controller		
		IsIoDevice	Boolean	IO device		
		ParameterAssignmentOfPnInterfaceByHigherLevel	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		OptionalIoDevice	Boolean	Optional IO-Device		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.8						
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		ShortDesignation	String	Short designation		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		DpWatchdog	Boolean	Watchdog		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module						
		DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		

Channel	Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-***-*AB0 - V2.6**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		TypeName	String	InvariantTypeName		
		WebserverActivate	Boolean			
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
					1	Value1X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
					2	Value2X
					3	Value3X
					4	Value4X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
					51	Value51X
					52	Value52X
					53	Value53X
					54	Value54X
					55	Value55X
					56	Value56X
					57	Value57X
					58	Value58X
					59	Value59X
					60	Value60X
					61	Value61X
					62	Value62X
					63	Value63X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
					64	Value64X
					65	Value65X
					66	Value66X
					67	Value67X
					68	Value68X
					69	Value69X
					70	Value70X
					71	Value71X
					72	Value72X
					73	Value73X
					74	Value74X
					75	Value75X
					76	Value76X
					77	Value77X
					78	Value78X
					79	Value79X
					80	Value80X
					81	Value81X
					82	Value82X
					83	Value83X
					84	Value84X
					85	Value85X
					86	Value86X
					87	Value87X
					88	Value88X
					89	Value89X
					90	Value90X
					91	Value91X
					92	Value92X
					93	Value93X
					94	Value94X
					95	Value95X
					96	Value96X
					97	Value97X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
					98	Value98X
					99	Value99X
					100	Value100X
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					77	UtcMinus0200MidMinusatlantic
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					34	UtcPlus0200Istanbul
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					113	UtcPlus0300Istanbul
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					111	UtcPlus1000Magadan
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					114	UtcPlus1100Magadan114
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	SIMATIC Memory Card					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		PositionNumber	Int32	Index		
	Display					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6					
				10	Value10Seconds
				15	Value15Seconds
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
	DisplayTimeToStandbyMode	UInt64	Time to standby mode		
				0	Disabled
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
				600	Value10Minutes
				900	Value15Minutes
				1800	Value30Minutes
	DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
				0	Disabled
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
				600	Value10Minutes
				900	Value15Minutes
				1800	Value30Minutes
	DisplayDefaultLanguage	UInt64	Default language on display		
				0	English
				1	German
				2	Italian
				3	French
				4	Spanish
				5	ChineseSimplified
				6	Japanese
				7	Korean
				8	Russian

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
					9	Turkish
					10	PortugueseBrazil
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		OptionalIoDevice	Boolean	Optional IO-Device		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.6						
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module						
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					
	ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
				0	Deactivated
				1	Active
	Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
	TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
				0	Deactivated
				1	Active
	TimeSynchronizationServer1	String	Server 1		
	TimeSynchronizationServer2	String	Server 2		
	TimeSynchronizationServer3	String	Server 3		
	TimeSynchronizationServer4	String	Server 4		
	TimeSynchronizationUpdateInterval	UInt64	Update interval		
	AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
	UseWebServerForInterface	Boolean	Enable Web server using this interface		
	IsIoDevice	Boolean	IO device		
	PrioritizedStartupIDevice	Boolean	Prioritized startup		
	OptionalIoDevice	Boolean	Optional IO-Device		
Port					
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		ShortDesignation	String	Short designation		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		DpWatchdog	Boolean	Watchdog		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module						
		DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-***-*AB0 - V2.5**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		TypeName	String	InvariantTypeName		
		WebserverActivate	Boolean			
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
					1	Value1X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
					2	Value2X
					3	Value3X
					4	Value4X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
					51	Value51X
					52	Value52X
					53	Value53X
					54	Value54X
					55	Value55X
					56	Value56X
					57	Value57X
					58	Value58X
					59	Value59X
					60	Value60X
					61	Value61X
					62	Value62X
					63	Value63X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
					64	Value64X
					65	Value65X
					66	Value66X
					67	Value67X
					68	Value68X
					69	Value69X
					70	Value70X
					71	Value71X
					72	Value72X
					73	Value73X
					74	Value74X
					75	Value75X
					76	Value76X
					77	Value77X
					78	Value78X
					79	Value79X
					80	Value80X
					81	Value81X
					82	Value82X
					83	Value83X
					84	Value84X
					85	Value85X
					86	Value86X
					87	Value87X
					88	Value88X
					89	Value89X
					90	Value90X
					91	Value91X
					92	Value92X
					93	Value93X
					94	Value94X
					95	Value95X
					96	Value96X
					97	Value97X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
					98	Value98X
					99	Value99X
					100	Value100X
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5					
				76	UtcMinus0300Salvador
				105	UtcMinus0200CoordinatedUniversalTimeMinus02
				77	UtcMinus0200MidMinusatlantic
				19	UtcMinus0100Azores
				20	UtcMinus0100CapeVerde
				21	UtcCasablanca
				22	UtcDublinEdinburghLisbonLondon
				78	UtcCoordinatedUniversalTime
				23	UtcMonroviaReykjavik
				24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
				27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
				25	UtcPlus0100BrusselsCopenhagenMadridParis
				26	UtcPlus0100SarajevoSkopjeWarsawZagreb
				79	UtcPlus0100TripoliOld
				80	UtcPlus0100WestCentralAfrica
				81	UtcPlus0100Windhoek
				28	UtcPlus0200AthensBucharest
				82	UtcPlus0200Beirut
				83	UtcPlus0200Damascus
				29	UtcPlus0200HararePretoria
				32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
				34	UtcPlus0200Istanbul
				30	UtcPlus0200Jerusalem
				31	UtcPlus0200Cairo
				33	UtcPlus0200EasternEurope
				101	UtcPlus0100Tripoli
				102	UtcPlus0300Amman
				116	UtcPlus0200Kaliningrad
				113	UtcPlus0300Istanbul
				84	UtcPlus0300AmmanOld
				35	UtcPlus0300Baghdad
				85	UtcPlus0300KaliningradMinsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5					
				96	UtcPlus0900OsakaSapporoTokyo
				97	UtcPlus0900Seoul
				54	UtcPlus0930AdelaideDarwin
				55	UtcPlus0930Darwin
				56	UtcPlus1000BrisbaneCanberraMelbourneSydney
				57	UtcPlus1000CanberraMelbourneSydney
				58	UtcPlus1000GuamPortMoresby
				59	UtcPlus1000Hobart
				98	UtcPlus1000Yakutsk
				110	UtcPlus1000Vladivostok
				111	UtcPlus1000Magadan
				60	UtcPlus1100SolomonIslandsNewCaledonia
				61	UtcPlus1100Vladivostok
				114	UtcPlus1100Magadan114
				62	UtcPlus1200AucklandWellington
				64	UtcPlus1200Fiji
				99	UtcPlus1200CoordinatedUniversalTimePlus12
				63	UtcPlus1100Magadan
				100	UtcPlus1300Nukualofa
				1	UtcPlus1300Samoa
	TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
	TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
	TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
				1	First
				2	Second
				3	Third
				4	Fourth
				5	Last
	TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
				1	Sunday
				2	Monday
				3	Tuesday
				4	Wednesday
				5	Thursday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	SIMATIC Memory Card					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		PositionNumber	Int32	Index		
	Display					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
					9	Turkish
					10	PortugueseBrazil
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		OptionalIoDevice	Boolean	Optional IO-Device		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X3]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.5						
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		ShortDesignation	String	Short designation		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		DpWatchdog	Boolean	Watchdog		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module						
		DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-***-*AB0 - V2.1**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		TypeName	String	InvariantTypeName		
		WebserverActivate	Boolean			
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
					51	Value51X
					52	Value52X
					53	Value53X
					54	Value54X
					55	Value55X
					56	Value56X
					57	Value57X
					58	Value58X
					59	Value59X
					60	Value60X
					61	Value61X
					62	Value62X
					63	Value63X
					64	Value64X
					65	Value65X
					66	Value66X
					67	Value67X
					68	Value68X
					69	Value69X
					70	Value70X
					71	Value71X
					72	Value72X
					73	Value73X
					74	Value74X
					75	Value75X
					76	Value76X
					77	Value77X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
					78	Value78X
					79	Value79X
					80	Value80X
					81	Value81X
					82	Value82X
					83	Value83X
					84	Value84X
					85	Value85X
					86	Value86X
					87	Value87X
					88	Value88X
					89	Value89X
					90	Value90X
					91	Value91X
					92	Value92X
					93	Value93X
					94	Value94X
					95	Value95X
					96	Value96X
					97	Value97X
					98	Value98X
					99	Value99X
					100	Value100X
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1					
				105	UtcMinus0200CoordinatedUniversalTimeMinus02
				77	UtcMinus0200MidMinusatlantic
				19	UtcMinus0100Azores
				20	UtcMinus0100CapeVerde
				21	UtcCasablanca
				22	UtcDublinEdinburghLisbonLondon
				78	UtcCoordinatedUniversalTime
				23	UtcMonroviaReykjavik
				24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
				27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
				25	UtcPlus0100BrusselsCopenhagenMadridParis
				26	UtcPlus0100SarajevoSkopjeWarsawZagreb
				79	UtcPlus0100TripoliOld
				80	UtcPlus0100WestCentralAfrica
				81	UtcPlus0100Windhoek
				28	UtcPlus0200AthensBucharest
				82	UtcPlus0200Beirut
				83	UtcPlus0200Damascus
				29	UtcPlus0200HararePretoria
				32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
				30	UtcPlus0200Jerusalem
				31	UtcPlus0200Cairo
				33	UtcPlus0200EasternEurope
				101	UtcPlus0100Tripoli
				102	UtcPlus0300Amman
				116	UtcPlus0200Kaliningrad
				84	UtcPlus0300AmmanOld
				35	UtcPlus0300Baghdad
				85	UtcPlus0300KaliningradMinsk
				117	UtcPlus0300MoscowStDotPetersburgVolgograd
				36	UtcPlus0300KuwaitRiyadh
				37	UtcPlus0300Nairobi

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupConfigurationTimeout	UInt64	Configuration time		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	SIMATIC Memory Card					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		PositionNumber	Int32	Index		
	Display					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1					
				10	Value10Seconds
				15	Value15Seconds
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
	DisplayTimeToStandbyMode	UInt64	Time to standby mode		
				0	Disabled
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
				600	Value10Minutes
				900	Value15Minutes
				1800	Value30Minutes
	DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
				0	Disabled
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
				600	Value10Minutes
				900	Value15Minutes
				1800	Value30Minutes
	DisplayDefaultLanguage	UInt64	Default language on display		
				0	English
				1	German
				2	Italian
				3	French
				4	Spanish
				5	ChineseSimplified
				6	Japanese
				7	Korean
				8	Russian

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
					9	Turkish
					10	PortugueseBrazil
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X3]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.1						
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		ShortDesignation	String	Short designation		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		DpWatchdog	Boolean	Watchdog		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
	ET200Pro\Submodules\CPU\Power_Submodule\MDD_PowerSubmodule_2.0					
		DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-***-*AB0 - V2.0**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
					51	Value51X
					52	Value52X
					53	Value53X
					54	Value54X
					55	Value55X
					56	Value56X
					57	Value57X
					58	Value58X
					59	Value59X
					60	Value60X
					61	Value61X
					62	Value62X
					63	Value63X
					64	Value64X
					65	Value65X
					66	Value66X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
					67	Value67X
					68	Value68X
					69	Value69X
					70	Value70X
					71	Value71X
					72	Value72X
					73	Value73X
					74	Value74X
					75	Value75X
					76	Value76X
					77	Value77X
					78	Value78X
					79	Value79X
					80	Value80X
					81	Value81X
					82	Value82X
					83	Value83X
					84	Value84X
					85	Value85X
					86	Value86X
					87	Value87X
					88	Value88X
					89	Value89X
					90	Value90X
					91	Value91X
					92	Value92X
					93	Value93X
					94	Value94X
					95	Value95X
					96	Value96X
					97	Value97X
					98	Value98X
					99	Value99X
					100	Value100X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					77	UtcMinus0200MidMinusatlantic
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0					
				23	UtcMonroviaReykjavik
				24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
				27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
				25	UtcPlus0100BrusselsCopenhagenMadridParis
				26	UtcPlus0100SarajevoSkopjeWarsawZagreb
				79	UtcPlus0100TripoliOld
				80	UtcPlus0100WestCentralAfrica
				81	UtcPlus0100Windhoek
				28	UtcPlus0200AthensBucharest
				82	UtcPlus0200Beirut
				83	UtcPlus0200Damascus
				29	UtcPlus0200HararePretoria
				32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
				30	UtcPlus0200Jerusalem
				31	UtcPlus0200Cairo
				33	UtcPlus0200EasternEurope
				101	UtcPlus0100Tripoli
				102	UtcPlus0300Amman
				116	UtcPlus0200Kaliningrad
				84	UtcPlus0300AmmanOld
				35	UtcPlus0300Baghdad
				85	UtcPlus0300KaliningradMinsk
				117	UtcPlus0300MoscowStDotPetersburgVolgograd
				36	UtcPlus0300KuwaitRiyadh
				37	UtcPlus0300Nairobi
				38	UtcPlus0330Teheran
				40	UtcPlus0400AbuDhabiMuscat
				41	UtcPlus0400Baku
				86	UtcPlus0400Yerevan
				119	UtcPlus0400MoscowStDotPetersburgVolgograd
				87	UtcPlus0400PortLouis
				42	UtcPlus0400Tbilisi
				43	UtcPlus0430Kabul

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					60	UtcPlus1100SolomonIslandsNewCaledonia

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
					61	UtcPlus1100Vladivostok
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0					
				6	Value0600AM
				7	Value0700AM
				8	Value0800AM
				9	Value0900AM
				10	Value1000AM
				11	Value1100AM
				12	Value1200PM
				13	Value0100PM
				14	Value0200PM
				15	Value0300PM
				16	Value0400PM
				17	Value0500PM
				18	Value0600PM
				19	Value0700PM
				20	Value0800PM
				21	Value0900PM
				22	Value1000PM
				23	Value1100PM
	StartupConfigurationTimeout	UInt64	Configuration time		
	StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
				0	NoRestartRemainInStopMode
				1	WarmRestartRun
				3	WarmRestartOperatingModeBeforePowerOff
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	CycleMaximumCycleTime	UInt64	Maximum cycle time		
	CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
	CycleMinimumCycleTime	UInt64	Minimum cycle time		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
SIMATIC Memory Card					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		PositionNumber	Int32	Index		
	Display					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V2.0						
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X3]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		PositionNumber	Int32	Index		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0					
	InterfaceType	Int32			
	InterfaceOperatingModes	Int32			
	Label	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DpOperatingMode	UInt64	Operating mode		
				1	DpMaster
				2	DpSlave
	TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
				0	None
				1	AsMaster
				2	AsSlave
	ShortDesignation	String	Short designation		
	Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
	TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
				0	None
				1	Value1Second
				2	Value10Seconds
				3	Value1Minute
				4	Value10Minutes
				5	Value1Hour
				6	Value12Hours
				7	Value24Hours
	DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
	DpWatchdog	Boolean	Watchdog		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Index		
	TypeName	String	InvariantTypeName		
Module - 6ES7 51*-***-*AB0 - V1.8**					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.8						
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		StartupConfigurationTimeout	UInt64	Configuration time		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.8						
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.8					
				23	UtcMonroviaReykjavik
				24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
				27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
				25	UtcPlus0100BrusselsCopenhagenMadridParis
				26	UtcPlus0100SarajevoSkopjeWarsawZagreb
				79	UtcPlus0100TripoliOld
				80	UtcPlus0100WestCentralAfrica
				81	UtcPlus0100Windhoek
				28	UtcPlus0200AthensBucharest
				82	UtcPlus0200Beirut
				83	UtcPlus0200Damascus
				29	UtcPlus0200HararePretoria
				32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
				30	UtcPlus0200Jerusalem
				31	UtcPlus0200Cairo
				33	UtcPlus0200EasternEurope
				101	UtcPlus0100Tripoli
				102	UtcPlus0300Amman
				84	UtcPlus0300AmmanOld
				35	UtcPlus0300Baghdad
				36	UtcPlus0300KuwaitRiyadh
				37	UtcPlus0300Nairobi
				38	UtcPlus0330Teheran
				40	UtcPlus0400AbuDhabiMuscat
				41	UtcPlus0400Baku
				86	UtcPlus0400Yerevan
				87	UtcPlus0400PortLouis
				42	UtcPlus0400Tbilisi
				43	UtcPlus0430Kabul
				45	UtcPlus0500AshgabatTashkent
				44	UtcPlus0500IslamabadKarachi
				46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
				88	UtcPlus0530SriJayawardenepura

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.8						
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.8					
				108	UtcPlus0800Irkutsk
				53	UtcPlus0900Irkutsk
				109	UtcPlus0900Yakutsk
				98	UtcPlus1000Yakutsk
				110	UtcPlus1000Vladivostok
				61	UtcPlus1100Vladivostok
				63	UtcPlus1100Magadan
				13	UtcMinus0430Caracas
				112	UtcMinus0400Caracas
				34	UtcPlus0200Istanbul
				113	UtcPlus0300Istanbul
				111	UtcPlus1000Magadan
				114	UtcPlus1100Magadan114
				90	UtcPlus0600Yekaterinburg
	TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
	TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
	TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
				1	First
				2	Second
				3	Third
				4	Fourth
				5	Last
	TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
				1	Sunday
				2	Monday
				3	Tuesday
				4	Wednesday
				5	Thursday
				6	Friday
				7	Saturday
	TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
				1	January
				2	February
				3	March

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.8						
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.8						
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.8					
				6	Value0600AM
				7	Value0700AM
				8	Value0800AM
				9	Value0900AM
				10	Value1000AM
				11	Value1100AM
				12	Value1200PM
				13	Value0100PM
				14	Value0200PM
				15	Value0300PM
				16	Value0400PM
				17	Value0500PM
				18	Value0600PM
				19	Value0700PM
				20	Value0800PM
				21	Value0900PM
				22	Value1000PM
				23	Value1100PM
	StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
				0	NoRestartRemainInStopMode
				1	WarmRestartRun
				3	WarmRestartOperatingModeBeforePowerOff
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	CycleMaximumCycleTime	UInt64	Maximum cycle time		
	CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
	CycleMinimumCycleTime	UInt64	Minimum cycle time		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
SIMATIC Memory Card					
	Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.8						
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Display					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.8						
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.8						
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		ShortDesignation	String	Short designation		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		DpWatchdog	Boolean	Watchdog		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module - 6ES7 51*-***-*AB0 - V1.7**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		StartupConfigurationTimeout	UInt64	Configuration time		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7					
				27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
				25	UtcPlus0100BrusselsCopenhagenMadridParis
				26	UtcPlus0100SarajevoSkopjeWarsawZagreb
				79	UtcPlus0100TripoliOld
				80	UtcPlus0100WestCentralAfrica
				81	UtcPlus0100Windhoek
				28	UtcPlus0200AthensBucharest
				82	UtcPlus0200Beirut
				83	UtcPlus0200Damascus
				29	UtcPlus0200HararePretoria
				32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
				30	UtcPlus0200Jerusalem
				31	UtcPlus0200Cairo
				33	UtcPlus0200EasternEurope
				101	UtcPlus0100Tripoli
				102	UtcPlus0300Amman
				84	UtcPlus0300AmmanOld
				35	UtcPlus0300Baghdad
				36	UtcPlus0300KuwaitRiyadh
				37	UtcPlus0300Nairobi
				38	UtcPlus0330Teheran
				40	UtcPlus0400AbuDhabiMuscat
				41	UtcPlus0400Baku
				86	UtcPlus0400Yerevan
				87	UtcPlus0400PortLouis
				42	UtcPlus0400Tbilisi
				43	UtcPlus0430Kabul
				45	UtcPlus0500AshgabatTashkent
				44	UtcPlus0500IslamabadKarachi
				46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
				88	UtcPlus0530SriJayawardenepura
				47	UtcPlus0545Nepal
				48	UtcPlus0600Astana

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					89	UtcPlus0600Daka

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
					90	UtcPlus0600Yekaterinburg
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	SIMATIC Memory Card					
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Display					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		OptionalIoDevice	Boolean	Optional IO-Device		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X3]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.7						
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0					
	InterfaceType	Int32			
	InterfaceOperatingModes	Int32			
	Label	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DpOperatingMode	UInt64	Operating mode		
				1	DpMaster
				2	DpSlave
	TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
				0	None
				1	AsMaster
				2	AsSlave
	ShortDesignation	String	Short designation		
	Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
	TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
				0	None
				1	Value1Second
				2	Value10Seconds
				3	Value1Minute
				4	Value10Minutes
				5	Value1Hour
				6	Value12Hours
				7	Value24Hours
	DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
	DpWatchdog	Boolean	Watchdog		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Index		
	TypeName	String	InvariantTypeName		
Module - 6ES7 51*-***-*AB0 - V1.6**					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					0	Deactivated
					1	Active
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		StartupConfigurationTimeout	UInt64	Configuration time		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6					
				15	Value0300PM
				16	Value0400PM
				17	Value0500PM
				18	Value0600PM
				19	Value0700PM
				20	Value0800PM
				21	Value0900PM
				22	Value1000PM
				23	Value1100PM
	StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
				0	NoRestartRemainInStopMode
				1	WarmRestartRun
				3	WarmRestartOperatingModeBeforePowerOff
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	CycleMaximumCycleTime	UInt64	Maximum cycle time		
	CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
	CycleMinimumCycleTime	UInt64	Minimum cycle time		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
SIMATIC Memory Card					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
Display					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DisplayTimeToStandbyMode	UInt64	Time to standby mode		
				0	Disabled

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6					
				5	Value5Seconds
				10	Value10Seconds
				15	Value15Seconds
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
	DisplayProtection	Boolean	Enable display protection		
	DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
				0	Disabled
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
				600	Value10Minutes
				900	Value15Minutes
				1800	Value30Minutes
				3600	Value1Hour
	PositionNumber	Int32	Index		
DP interface					
	InterfaceType	Int32			
	InterfaceOperatingModes	Int32			
	Label	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DpOperatingMode	UInt64	Operating mode		
				1	DpMaster
	TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
				0	None
				1	AsMaster
				2	AsSlave
	Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
	TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
				0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6					
PROFINET interface [X3]					
	IECV22LLDPMode	Boolean			
	DiagnosticsCommunicationError	Boolean			
	KeepAlivesInterval	UInt32			
	LoadLimitation	Boolean			
	KeepAlivesInterval	UInt32			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
	UseWebServerForInterface	Boolean	Enable Web server using this interface		
	TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
				0	Deactivated
				1	Active
	TimeSynchronizationServer1	String	Server 1		
	TimeSynchronizationServer2	String	Server 2		
	TimeSynchronizationServer3	String	Server 3		
	TimeSynchronizationServer4	String	Server 4		
	TimeSynchronizationUpdateInterval	UInt64	Update interval		
	PositionNumber	Int32	Index		
	PortActivation	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAndDuplex	Int32			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.6						
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-***-*AB0 - V1.5**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					0	Deactivated
					1	Active
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		StartupConfigurationTimeout	UInt64	Configuration time		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5					
				67	UtcMinus0700ChihuahuaLaPazMazatlan
				6	UtcMinus0700MountainStandardTimeUsaCanada
				7	UtcMinus0600CentralStandardTimeUsaCanada
				8	UtcMinus0600GuadalajaraMexicoCityMonterrey
				68	UtcMinus0600CentralAmerica
				9	UtcMinus0600Saskatchewan
				10	UtcMinus0500BogotaLimaQuito
				11	UtcMinus0500EasternStandardTimeUsaCanada
				12	UtcMinus0500IndianaEast
				69	UtcMinus0400Asuncion
				70	UtcMinus0400AtlanticStandardTimeCanada
				71	UtcMinus0400Cuiaba
				14	UtcMinus0400GeorgetownLaPazManausSanJuan
				72	UtcMinus0400Santiago
				15	UtcMinus0330Newfoundland
				16	UtcMinus0300Brasilia
				17	UtcMinus0300BuenosAires
				73	UtcMinus0300CayenneFortaleza
				74	UtcMinus0300Greenland
				75	UtcMinus0300Montevideo
				76	UtcMinus0300Salvador
				105	UtcMinus0200CoordinatedUniversalTimeMinus02
				19	UtcMinus0100Azores
				20	UtcMinus0100CapeVerde
				21	UtcCasablanca
				22	UtcDublinEdinburghLisbonLondon
				78	UtcCoordinatedUniversalTime
				23	UtcMonroviaReykjavik
				24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
				27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
				25	UtcPlus0100BrusselsCopenhagenMadridParis
				26	UtcPlus0100SarajevoSkopjeWarsawZagreb

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5						
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5						
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5					
				61	UtcPlus1100Vladivostok
				63	UtcPlus1100Magadan
				13	UtcMinus0430Caracas
				112	UtcMinus0400Caracas
				34	UtcPlus0200Istanbul
				113	UtcPlus0300Istanbul
				111	UtcPlus1000Magadan
				114	UtcPlus1100Magadan114
	TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
	TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
	TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
				1	First
				2	Second
				3	Third
				4	Fourth
				5	Last
	TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
				1	Sunday
				2	Monday
				3	Tuesday
				4	Wednesday
				5	Thursday
				6	Friday
				7	Saturday
	TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
				1	January
				2	February
				3	March
				4	April
				5	May
				6	June
				7	July
				8	August
				9	September

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5						
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5						
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5					
				12	Value1200PM
				13	Value0100PM
				14	Value0200PM
				15	Value0300PM
				16	Value0400PM
				17	Value0500PM
				18	Value0600PM
				19	Value0700PM
				20	Value0800PM
				21	Value0900PM
				22	Value1000PM
				23	Value1100PM
	StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
				0	NoRestartRemainInStopMode
				1	WarmRestartRun
				3	WarmRestartOperatingModeBeforePowerOff
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	CycleMaximumCycleTime	UInt64	Maximum cycle time		
	CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
	CycleMinimumCycleTime	UInt64	Minimum cycle time		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
SIMATIC Memory Card					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
Display					
	Author	String	Author		
	Comment	String	Comment		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5						
		Name	String	Name		
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5					
				2	Value2Seconds
				3	Value3Seconds
				4	Value4Seconds
				5	Value5Seconds
				10	Value10Seconds
				15	Value15Seconds
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
	DisplayProtection	Boolean	Enable display protection		
	DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
				0	Disabled
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
				600	Value10Minutes
				900	Value15Minutes
				1800	Value30Minutes
				3600	Value1Hour
	PositionNumber	Int32	Index		
DP interface					
	InterfaceType	Int32			
	InterfaceOperatingModes	Int32			
	Label	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DpOperatingMode	UInt64	Operating mode		
				1	DpMaster
	TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
				0	None
				1	AsMaster
				2	AsSlave

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5						
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X3]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5						
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5						
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5						
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.5						
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-***-*AB0 - V1.1**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupConfigurationTimeout	UInt64	Configuration time		
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1						
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1						
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1						
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1						
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1						
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1						
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1					
				15	Value0300PM
				16	Value0400PM
				17	Value0500PM
				18	Value0600PM
				19	Value0700PM
				20	Value0800PM
				21	Value0900PM
				22	Value1000PM
				23	Value1100PM
	StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
				0	NoRestartRemainInStopMode
				1	WarmRestartRun
				3	WarmRestartOperatingModeBeforePowerOff
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	CycleMaximumCycleTime	UInt64	Maximum cycle time		
	CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
	CycleMinimumCycleTime	UInt64	Minimum cycle time		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
SIMATIC Memory Card					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
Display					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DisplayTimeToStandbyMode	UInt64	Time to standby mode		
				0	Disabled

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1						
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
		DisplayProtection	Boolean	Enable display protection		
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1						
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1						
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1						
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.1						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-***-*AB0 - V1.0**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupConfigurationTimeout	UInt64	Configuration time		
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0						
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0						
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0						
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0						
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0						
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0						
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0						
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	SIMATIC Memory Card					
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0					
	Name	String	Name		
	PositionNumber	Int32	Index		
Display					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DisplayTimeToStandbyMode	UInt64	Time to standby mode		
				0	Disabled
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
				600	Value10Minutes
				900	Value15Minutes
				1800	Value30Minutes
	DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
				0	Disabled
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
				600	Value10Minutes
				900	Value15Minutes
				1800	Value30Minutes
	DisplayDefaultLanguage	UInt64	Default language on display		
				0	English
				1	German
				2	Italian
				3	French
				4	Spanish
				5	ChineseSimplified
	DisplayProtection	Boolean	Enable display protection		
	PositionNumber	Int32	Index		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0					
DP interface					
	InterfaceType	Int32			
	InterfaceOperatingModes	Int32			
	Label	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DpOperatingMode	UInt64	Operating mode		
				1	DpMaster
	TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
				0	None
				1	AsMaster
				2	AsSlave
	TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
				0	None
				1	Value1Second
				2	Value10Seconds
				3	Value1Minute
				4	Value10Minutes
				5	Value1Hour
				6	Value12Hours
				7	Value24Hours
	PositionNumber	Int32	Index		
PROFINET interface [X2]					
	IECV22LLDPMode	Boolean			
	DiagnosticsCommunicationError	Boolean			
	KeepAlivesInterval	UInt32			
	LoadLimitation	Boolean			
	KeepAlivesInterval	UInt32			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0						
		Comment	String	Comment		
		Name	String	Name		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0						
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevel	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*****-*AB0 - V1.0						
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.9						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		SystemPowerSupplyExternal	UInt64	General		
					0	NoConnectionToExternal24VSupply
					1	ConnectionToExternal24VSupply
		Failsafe_DefaultFmonitoringTimeCentral	UInt64	Default F-monitoring time for central F-I/O		
		Failsafe_CentralFSourceAddress	UInt64	Central F-source address		
		Failsafe_FCapabilityActivated	Boolean	F-capability activated		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		WebserverActivate	Boolean			
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.9						
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		WebserverUpdateInterval	UInt64	Update interval		
SIMATIC Memory Card						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		PositionNumber	Int32	Index		
Submodules						
		Name	String			
		PlcCommunicationCertificate	UInt32			
		CommunicationMode	UInt32			
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					34	UtcPlus0200Istanbul
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					15	UtcMinus0330Newfoundland
					72	UtcMinus0400Santiago

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.9						
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					71	UtcMinus0400Cuiaba
					70	UtcMinus0400AtlanticStandardTimeCanada
					69	UtcMinus0400Asuncion
					112	UtcMinus0400Caracas
					13	UtcMinus0430Caracas
					12	UtcMinus0500IndianaEast
					11	UtcMinus0500EasternStandardTimeUsaCanada
					10	UtcMinus0500BogotaLimaQuito
					9	UtcMinus0600Saskatchewan
					83	UtcPlus0200Damascus
					82	UtcPlus0200Beirut
					28	UtcPlus0200AthensBucharest
					81	UtcPlus0100Windhoek
					80	UtcPlus0100WestCentralAfrica
					79	UtcPlus0100TripoliOld
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					23	UtcMonroviaReykjavik
					78	UtcCoordinatedUniversalTime
					113	UtcPlus0300Istanbul
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.9						
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					22	UtcDublinEdinburghLisbonLondon
					21	UtcCasablanca
					20	UtcMinus0100CapeVerde
					19	UtcMinus0100Azores
					77	UtcMinus0200MidMinusatlantic
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					76	UtcMinus0300Salvador
					75	UtcMinus0300Montevideo
					74	UtcMinus0300Greenland
					73	UtcMinus0300CayenneFortaleza
					17	UtcMinus0300BuenosAires
					16	UtcMinus0300Brasilia

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					68	UtcMinus0600CentralAmerica

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.9						
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					7	UtcMinus0600CentralStandardTimeUsaCanada
					6	UtcMinus0700MountainStandardTimeUsaCanada
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					5	UtcMinus0700Arizona
					107	UtcMinus0800PacificStandardTimeUsaCanada
					106	UtcMinus0800PacificStandardTimeMexico
					3	UtcMinus0900Alaska
					2	UtcMinus1000Hawaii
					65	UtcMinus1100MidwayIslands
					0	UtcMinus1200EniwetokKwajalein
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					111	UtcPlus1000Magadan
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					114	UtcPlus1100Magadan114
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.9						
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.9						
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.9					
				5	Thursday
				6	Friday
				7	Saturday
	TimeOfDayStandardTimeStartMonth	UInt64	of		
				1	January
				2	February
				3	March
				4	April
				5	May
				6	June
				7	July
				8	August
				9	September
				10	October
				11	November
				12	December
	TimeOfDayStandardTimeStartHour	UInt64	at		
				0	Midnight
				1	Value0100AM
				2	Value0200AM
				3	Value0300AM
				4	Value0400AM
				5	Value0500AM
				6	Value0600AM
				7	Value0700AM
				8	Value0800AM
				9	Value0900AM
				10	Value1000AM
				11	Value1100AM
				12	Value1200PM
				13	Value0100PM
				14	Value0200PM
				15	Value0300PM
				16	Value0400PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.9						
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
	Submodules					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Name	String			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					7	Value24Hours
					6	Value12Hours
					5	Value1Hour
					4	Value10Minutes

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.9						
					3	Value1Minute
					2	Value10Seconds
					1	Value1Second
					0	None
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
Module - 6ES7 615-7DF10-0AB0 - V2.9						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		Failsafe_DefaultFmonitoringTimeCentral	UInt64	Default F-monitoring time for central F-I/O		
		Failsafe_CentralFSourceAddress	UInt64	Central F-source address		
		Failsafe_FCapabilityActivated	Boolean	F-capability activated		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		WebserverActivate	Boolean			
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.9						
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		WebserverUpdateInterval	UInt64	Update interval		
	SIMATIC Memory Card					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		PositionNumber	Int32	Index		
	Submodules					
		Name	String			
		PlcCommunicationCertificate	UInt32			
		CommunicationMode	UInt32			
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					34	UtcPlus0200Istanbul
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.9						
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					15	UtcMinus0330Newfoundland
					72	UtcMinus0400Santiago
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					71	UtcMinus0400Cuiaba
					70	UtcMinus0400AtlanticStandardTimeCanada
					69	UtcMinus0400Asuncion
					112	UtcMinus0400Caracas
					13	UtcMinus0430Caracas
					12	UtcMinus0500IndianaEast
					11	UtcMinus0500EasternStandardTimeUsaCanada
					10	UtcMinus0500BogotaLimaQuito
					9	UtcMinus0600Saskatchewan
					83	UtcPlus0200Damascus
					82	UtcPlus0200Beirut
					28	UtcPlus0200AthensBucharest
					81	UtcPlus0100Windhoek
					80	UtcPlus0100WestCentralAfrica
					79	UtcPlus0100TripoliOld
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					23	UtcMonroviaReykjavik
					78	UtcCoordinatedUniversalTime
					113	UtcPlus0300Istanbul
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.9						
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					22	UtcDublinEdinburghLisbonLondon
					21	UtcCasablanca
					20	UtcMinus0100CapeVerde
					19	UtcMinus0100Azores
					77	UtcMinus0200MidMinusatlantic
					105	UtcMinus0200CoordinatedUniversalTimeMinus02

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					76	UtcMinus0300Salvador

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.9						
					75	UtcMinus0300Montevideo
					74	UtcMinus0300Greenland
					73	UtcMinus0300CayenneFortaleza
					17	UtcMinus0300BuenosAires
					16	UtcMinus0300Brasilia
					68	UtcMinus0600CentralAmerica
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					7	UtcMinus0600CentralStandardTimeUsaCanada
					6	UtcMinus0700MountainStandardTimeUsaCanada
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					5	UtcMinus0700Arizona
					107	UtcMinus0800PacificStandardTimeUsaCanada
					106	UtcMinus0800PacificStandardTimeMexico
					3	UtcMinus0900Alaska
					2	UtcMinus1000Hawaii
					65	UtcMinus1100MidwayIslands
					0	UtcMinus1200EniwetokKwajalein
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					111	UtcPlus1000Magadan

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.9					
				60	UtcPlus1100SolomonIslandsNewCaledonia
				61	UtcPlus1100Vladivostok
				114	UtcPlus1100Magadan114
				62	UtcPlus1200AucklandWellington
				64	UtcPlus1200Fiji
				99	UtcPlus1200CoordinatedUniversalTimePlus12
				63	UtcPlus1100Magadan
				100	UtcPlus1300Nukualofa
				1	UtcPlus1300Samoa
	TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
	TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
	TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
				1	First
				2	Second
				3	Third
				4	Fourth
				5	Last
	TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
				1	Sunday
				2	Monday
				3	Tuesday
				4	Wednesday
				5	Thursday
				6	Friday
				7	Saturday
	TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
				1	January
				2	February
				3	March
				4	April
				5	May
				6	June
				7	July
				8	August

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.9						
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.9						
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.9					
				11	Value1100AM
				12	Value1200PM
				13	Value0100PM
				14	Value0200PM
				15	Value0300PM
				16	Value0400PM
				17	Value0500PM
				18	Value0600PM
				19	Value0700PM
				20	Value0800PM
				21	Value0900PM
				22	Value1000PM
				23	Value1100PM
	ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
	ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
	ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
	ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
				2	Seconds
				3	Minutes
				4	Hours
	CycleCommunicationLoad	UInt64	Cycle load due to communication		
Submodules					
	InterfaceType	Int32			
	InterfaceOperatingModes	Int32			
	Label	String			
	Name	String			
	Comment	String	Comment		
	Author	String	Author		
	Name	String	Name		
	DpOperatingMode	UInt64	Operating mode		
				1	DpMaster
	TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
				0	None
				1	AsMaster

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.9						
					2	AsSlave
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					7	Value24Hours
					6	Value12Hours
					5	Value1Hour
					4	Value10Minutes
					3	Value1Minute
					2	Value10Seconds
					1	Value1Second
					0	None
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					2	StartupCpuIfMismatch
					1	StartupCpuOnlyIfCompatible
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
Module						
		Name	String			
		PositionNumber	Int32	Index		
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
Module						
		IECV22LLDPMode	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		IsIoDevice	Boolean	IO device		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		OptionalIoDevice	Boolean	Optional IO-Device		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Name	String			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
Module						
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		TransmissionRateAndDuplex	Int32			
		EndOfTopologyDiscovery	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortActivation	Boolean			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
Module						
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		OptionalIoDevice	Boolean	Optional IO-Device		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.8						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		WebserverUpdateInterval	UInt64	Update interval		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		Failsafe_DefaultFmonitoringTimeCentral	UInt64	Default F-monitoring time for central F-I/O		
		Failsafe_CentralFSourceAddress	UInt64	Central F-source address		
		Failsafe_FCapabilityActivated	Boolean	F-capability activated		
		WebserverActivate	Boolean			
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TimeSynchronizationDriveActive	Boolean	Eom_Property_03230		
		PositionNumber	Int32	Slot		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.8						
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
	SIMATIC Memory Card					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		PositionNumber	Int32	Index		
	Submodules					
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.8					
				68	UtcMinus0600CentralAmerica
				9	UtcMinus0600Saskatchewan
				10	UtcMinus0500BogotaLimaQuito
				11	UtcMinus0500EasternStandardTimeUsaCanada
				12	UtcMinus0500IndianaEast
				69	UtcMinus0400Asuncion
				70	UtcMinus0400AtlanticStandardTimeCanada
				71	UtcMinus0400Cuiaba
				14	UtcMinus0400GeorgetownLaPazManausSanJuan
				72	UtcMinus0400Santiago
				15	UtcMinus0330Newfoundland
				16	UtcMinus0300Brasilia
				17	UtcMinus0300BuenosAires
				73	UtcMinus0300CayenneFortaleza
				74	UtcMinus0300Greenland
				75	UtcMinus0300Montevideo
				76	UtcMinus0300Salvador
				105	UtcMinus0200CoordinatedUniversalTimeMinus02
				19	UtcMinus0100Azores
				20	UtcMinus0100CapeVerde
				21	UtcCasablanca
				22	UtcDublinEdinburghLisbonLondon
				78	UtcCoordinatedUniversalTime
				23	UtcMonroviaReykjavik
				24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
				27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
				25	UtcPlus0100BrusselsCopenhagenMadridParis
				26	UtcPlus0100SarajevoSkopjeWarsawZagreb
				79	UtcPlus0100TripoliOld
				80	UtcPlus0100WestCentralAfrica
				81	UtcPlus0100Windhoek
				28	UtcPlus0200AthensBucharest

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.8						
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.8						
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.8					
				34	UtcPlus0200Istanbul
				113	UtcPlus0300Istanbul
				111	UtcPlus1000Magadan
				114	UtcPlus1100Magadan114
	TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
	TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
	TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
				1	First
				2	Second
				3	Third
				4	Fourth
				5	Last
	TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
				1	Sunday
				2	Monday
				3	Tuesday
				4	Wednesday
				5	Thursday
				6	Friday
				7	Saturday
	TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
				1	January
				2	February
				3	March
				4	April
				5	May
				6	June
				7	July
				8	August
				9	September
				10	October
				11	November
				12	December

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.8						
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.8						
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.8						
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
	Submodules					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		PositionNumber	Int32	Index		
	Submodules					
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-4DF10-0AB0 - V2.8						
		Name	String	Name		
		Comment	String	Comment		
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	Index		
	Submodules					
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
		PositionNumber	Int32	Index		
Module - 6ES7 615-7DF10-0AB0 - V2.8						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		WebserverUpdateInterval	UInt64	Update interval		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		Failsafe_DefaultFmonitoringTimeCentral	UInt64	Default F-monitoring time for central F-I/O		
		Failsafe_CentralFSourceAddress	UInt64	Central F-source address		
		Failsafe_FCapabilityActivated	Boolean	F-capability activated		
		WebserverActivate	Boolean			
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.8					
	FirmwareVersion	String	Firmware version		
	TimeSynchronizationDriveActive	Boolean	Eom_Property_03230		
	PositionNumber	Int32	Slot		
	CentralAlarmManagement	Boolean	Central alarm management in the PLC		
	ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
	OpcUaRequiredLicense	UInt64	Type of required license		
				0	NoLicense
				1	SimaticOpcUaS71500Small
				2	SimaticOpcUaS71500Medium
				3	SimaticOpcUaS71500Large
	OpcUaPurchasedLicense	UInt64	Type of purchased license		
				0	NoLicense
				1	SimaticOpcUaS71500Small
				2	SimaticOpcUaS71500Medium
				3	SimaticOpcUaS71500Large
	ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
				0	NoLicense
				5	Value5X
	EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
	EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
SIMATIC Memory Card					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
	DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
	PositionNumber	Int32	Index		
Submodules					
	SystemMemoryByte	Boolean	Enable the use of system memory byte		
	SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
	ClockMemoryByte	Boolean	Enable the use of clock memory byte		
	ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
	TimeOfDayLocalTimeZone	UInt64	Time zone		
				0	UtcMinus1200EniwetokKwajalein

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.8						
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					23	UtcMonroviaReykjavik

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.8					
				24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
				27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
				25	UtcPlus0100BrusselsCopenhagenMadridParis
				26	UtcPlus0100SarajevoSkopjeWarsawZagreb
				79	UtcPlus0100TripoliOld
				80	UtcPlus0100WestCentralAfrica
				81	UtcPlus0100Windhoek
				28	UtcPlus0200AthensBucharest
				82	UtcPlus0200Beirut
				83	UtcPlus0200Damascus
				29	UtcPlus0200HararePretoria
				32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
				30	UtcPlus0200Jerusalem
				31	UtcPlus0200Cairo
				33	UtcPlus0200EasternEurope
				101	UtcPlus0100Tripoli
				102	UtcPlus0300Amman
				84	UtcPlus0300AmmanOld
				35	UtcPlus0300Baghdad
				36	UtcPlus0300KuwaitRiyadh
				37	UtcPlus0300Nairobi
				38	UtcPlus0330Teheran
				40	UtcPlus0400AbuDhabiMuscat
				41	UtcPlus0400Baku
				86	UtcPlus0400Yerevan
				87	UtcPlus0400PortLouis
				42	UtcPlus0400Tbilisi
				43	UtcPlus0430Kabul
				45	UtcPlus0500AshgabatTashkent
				44	UtcPlus0500IslamabadKarachi
				46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
				88	UtcPlus0530SriJayawardenepura
				47	UtcPlus0545Nepal

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.8						
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.8						
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.8						
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.8						
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.8						
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
	Submodules					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 615-7DF10-0AB0 - V2.8						
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		PositionNumber	Int32	Index		
	Submodules					
		Author	String	Author		
		Name	String	Name		
		Comment	String	Comment		
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	Index		
	Submodules					
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
		PositionNumber	Int32	Index		
Module						
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		OptionalIoDevice	Boolean	Optional IO-Device		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
Module						
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
Module						
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					
	AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
	UseWebServerForInterface	Boolean	Enable Web server using this interface		
	IsIoDevice	Boolean	IO device		
	PrioritizedStartupIDevice	Boolean	Prioritized startup		
	OptionalIoDevice	Boolean	Optional IO-Device		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Comment	String	Comment		
	Author	String	Author		
	Name	String	Name		
Module					
	SharedDeviceAccessConfigured	Boolean			
	PulseWidthModulationFrequency	UInt64	Base frequency pulse width modulation		
				1	Value01Kilohertz
				2	Value02Kilohertz
				3	Value04Kilohertz
				4	Value08Kilohertz
				5	Value16Kilohertz
				0	None
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	HighSpeedOutput	Boolean	High-speed output		
	OperatingMode	UInt64	Operating mode		
				34	TimerDI

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					
				52	DigitalInput
				283	OversamplingInput
				31	PeriodMeasurement
				8	TimerDQ
				276	DigitalOutput
				282	OversamplingOutput
				7	PulseWidthModulation
	InputDelay	UInt64	Input delay		
				34	Value125Microseconds
				33	Value001Microseconds
	Invert	Boolean	Invert		
Channel 1					
	HighSpeedOutput	Boolean	High-speed output		
	OperatingMode	UInt64	Operating mode		
				34	TimerDI
				52	DigitalInput
				283	OversamplingInput
				31	PeriodMeasurement
				8	TimerDQ
				276	DigitalOutput
				282	OversamplingOutput
				7	PulseWidthModulation
	InputDelay	UInt64	Input delay		
				34	Value125Microseconds
				33	Value001Microseconds
	Invert	Boolean	Invert		
Channel 2					
	HighSpeedOutput	Boolean	High-speed output		
	OperatingMode	UInt64	Operating mode		
				34	TimerDI
				52	DigitalInput
				283	OversamplingInput
				31	PeriodMeasurement
				8	TimerDQ

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					
				276	DigitalOutput
				282	OversamplingOutput
				7	PulseWidthModulation
	InputDelay	UInt64	Input delay		
				34	Value125Microseconds
				33	Value001Microseconds
	Invert	Boolean	Invert		
Channel 3					
	HighSpeedOutput	Boolean	High-speed output		
	OperatingMode	UInt64	Operating mode		
				34	TimerDI
				52	DigitalInput
				283	OversamplingInput
				31	PeriodMeasurement
				8	TimerDQ
				276	DigitalOutput
				282	OversamplingOutput
				7	PulseWidthModulation
	InputDelay	UInt64	Input delay		
				34	Value125Microseconds
				33	Value001Microseconds
	Invert	Boolean	Invert		
Channel 4					
	HighSpeedOutput	Boolean	High-speed output		
	OperatingMode	UInt64	Operating mode		
				34	TimerDI
				52	DigitalInput
				283	OversamplingInput
				31	PeriodMeasurement
				8	TimerDQ
				276	DigitalOutput
				282	OversamplingOutput
				7	PulseWidthModulation
	Invert	Boolean	Invert		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		InputDelay	UInt64	Input delay		
					34	Value125Microseconds
					33	Value001Microseconds
	Channel 5					
		HighSpeedOutput	Boolean	High-speed output		
		OperatingMode	UInt64	Operating mode		
					34	TimerDI
					52	DigitalInput
					283	OversamplingInput
					31	PeriodMeasurement
					8	TimerDQ
					276	DigitalOutput
					282	OversamplingOutput
					7	PulseWidthModulation
		Invert	Boolean	Invert		
		InputDelay	UInt64	Input delay		
					34	Value125Microseconds
					33	Value001Microseconds
	Channel 6					
		HighSpeedOutput	Boolean	High-speed output		
		OperatingMode	UInt64	Operating mode		
					34	TimerDI
					52	DigitalInput
					283	OversamplingInput
					31	PeriodMeasurement
					8	TimerDQ
					276	DigitalOutput
					282	OversamplingOutput
					7	PulseWidthModulation
		Invert	Boolean	Invert		
		InputDelay	UInt64	Input delay		
					34	Value125Microseconds
					33	Value001Microseconds
	Channel 7					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		HighSpeedOutput	Boolean	High-speed output		
		OperatingMode	UInt64	Operating mode		
					34	TimerDI
					52	DigitalInput
					283	OversamplingInput
					31	PeriodMeasurement
					8	TimerDQ
					276	DigitalOutput
					282	OversamplingOutput
					7	PulseWidthModulation
		Invert	Boolean	Invert		
		InputDelay	UInt64	Input delay		
					34	Value125Microseconds
					33	Value001Microseconds

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R*-*AB0 - V2.9**						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.9						
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.9						
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.9						
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.9						
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.9						
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.9						
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.9						
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.9					
	ClockMemoryByte	Boolean	Enable the use of clock memory byte		
	ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
	ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
	ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
				2	Seconds
				3	Minutes
				4	Hours
	StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
				0	NoRestartRemainInStopMode
				1	WarmRestartRun
				3	WarmRestartOperatingModeBeforePowerOff
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
	CycleMaximumCycleTime	UInt64	Maximum cycle time		
	CycleMinimumCycleTime	UInt64	Minimum cycle time		
	Comment	String	Comment		
	Author	String	Author		
	Name	String	Name		
	MacRtLicensePurchased	UInt64	Type of purchased license		
				0	NoLicense
				1	LicenseMacBasic
				2	LicenseMacAdvanced
SIMATIC Memory Card					
	DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
	DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
Display					
	DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
				0	Disabled
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.9						
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		ProtectionPassword	String	Password		
		ProtectionConfirmPassword	String	Confirm password		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.9						
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
Module - 6ES7 51*-*H*-*AB0 - V2.9**						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.9						
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		PositionNumber	Int32	Index		
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.9						
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.9						
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.9						
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.9						
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.9						
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.9						
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.9						
					22	Value1000PM
					23	Value1100PM
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
		MacRtLicensePurchased	UInt64	Type of purchased license		
					0	NoLicense
					1	LicenseMacBasic
					2	LicenseMacAdvanced
		PnDnsConfigNameResolve	Int32			
		TimeSynchronizationNtpV2	UInt32	Enable time synchronization via NTP server		
					0	Disabled
					2	SetServersInProject

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.9						
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
	SIMATIC Memory Card					
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
	Display					
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		ProtectionPassword	String	Password		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.9						
		ProtectionConfirmPassword	String	Confirm password		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
	Synchronization interface [X3]					
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
	Synchronization interface [X4]					
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
	S71500\Submodules\CPU\CpuHSync\MDD_CpuHSyncInterface_X5_2.9					
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
Module - 6ES7 960-1*B00-0AA5						

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 960-1*B00-0AA5						
		SharedDeviceAccessConfigured	Boolean			
		Name	String	Name		
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
Module						
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Comment	String	Comment		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
	Submodules					
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
Module						
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
	Submodules					
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
Module						
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					
	Author	String	Author		
	Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
	Name	String	Name		
	TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
				0	Deactivated
	TimeSynchronizationServer1	String	Server 1		
	TimeSynchronizationServer2	String	Server 2		
	TimeSynchronizationServer3	String	Server 3		
	TimeSynchronizationServer4	String	Server 4		
	TimeSynchronizationUpdateInterval	UInt64	Update interval		
Submodules					
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Comment	String	Comment		
	Author	String	Author		
	Name	String	Name		
Module					
	IECV22LLDPMode	Boolean			
	DiagnosticsCommunicationError	Boolean			
	KeepAlivesInterval	UInt32			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Author	String	Author		
		Name	String	Name		
	Submodules					
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R*-*AB0 - V2.8**						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8						
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8						
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8						
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8						
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8						
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8						
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8						
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8					
	ClockMemoryByte	Boolean	Enable the use of clock memory byte		
	ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
	ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
	ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
				2	Seconds
				3	Minutes
				4	Hours
	StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
				0	NoRestartRemainInStopMode
				1	WarmRestartRun
				3	WarmRestartOperatingModeBeforePowerOff
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
	CycleMaximumCycleTime	UInt64	Maximum cycle time		
	CycleMinimumCycleTime	UInt64	Minimum cycle time		
	Comment	String	Comment		
	Author	String	Author		
	Name	String	Name		
SIMATIC Memory Card					
	DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
	DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
Display					
	DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
				0	Disabled
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
				600	Value10Minutes
				900	Value15Minutes
				1800	Value30Minutes

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8						
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		ProtectionPassword	String	Password		
		ProtectionConfirmPassword	String	Confirm password		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8						
					1800	Value30Minutes
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8						
	PROFINET interface [X1]					
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Comment	String	Comment		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.8						
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
Module - 6ES7 51*-*H*-*AB0 - V2.8**						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8						
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		PositionNumber	Int32	Index		
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8						
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8						
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8						
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8					
	TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
	TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
	TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
				1	First
				2	Second
				3	Third
				4	Fourth
				5	Last
	TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
				1	Sunday
				2	Monday
				3	Tuesday
				4	Wednesday
				5	Thursday
				6	Friday
				7	Saturday
	TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
				1	January
				2	February
				3	March
				4	April
				5	May
				6	June
				7	July
				8	August
				9	September
				10	October
				11	November
				12	December
	TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
				0	Midnight
				1	Value0100AM
				2	Value0200AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8						
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8						
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8						
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
	SIMATIC Memory Card					
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8						
	Display					
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		ProtectionPassword	String	Password		
		ProtectionConfirmPassword	String	Confirm password		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8						
					1800	Value30Minutes
					3600	Value1Hour
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
	Synchronization interface [X3]					
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
	Synchronization interface [X4]					
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
	PROFINET interface [X1]					
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8						
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Comment	String	Comment		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.8						
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Author	String	Author		
		Name	String	Name		
Module - 6ES7 960-1*B00-0AA5						
		SharedDeviceAccessConfigured	Boolean			
		Name	String	Name		
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 960-1*B00-0AA5						
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R*-*AB0 - V2.6**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
					51	Value51X
					52	Value52X
					53	Value53X
					54	Value54X
					55	Value55X
					56	Value56X
					57	Value57X
					58	Value58X
					59	Value59X
					60	Value60X
					61	Value61X
					62	Value62X
					63	Value63X
					64	Value64X
					65	Value65X
					66	Value66X
					67	Value67X
					68	Value68X
					69	Value69X
					70	Value70X
					71	Value71X
					72	Value72X
					73	Value73X
					74	Value74X
					75	Value75X
					76	Value76X
					77	Value77X
					78	Value78X
					79	Value79X
					80	Value80X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					81	Value81X
					82	Value82X
					83	Value83X
					84	Value84X
					85	Value85X
					86	Value86X
					87	Value87X
					88	Value88X
					89	Value89X
					90	Value90X
					91	Value91X
					92	Value92X
					93	Value93X
					94	Value94X
					95	Value95X
					96	Value96X
					97	Value97X
					98	Value98X
					99	Value99X
					100	Value100X
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					77	UtcMinus0200MidMinusatlantic
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					34	UtcPlus0200Istanbul
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					113	UtcPlus0300Istanbul
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					111	UtcPlus1000Magadan
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					114	UtcPlus1100Magadan114
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	SIMATIC Memory Card					
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
	Display					
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		ProtectionPassword	String	Password		
		ProtectionConfirmPassword	String	Confirm password		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
	PROFINET interface [X1]					
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*R***-*AB0 - V2.6						
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module - 6ES7 51*-*H*-*AB0 - V2.6**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
		AdditionalInformation	String	Additional information		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
					51	Value51X
					52	Value52X
					53	Value53X
					54	Value54X
					55	Value55X
					56	Value56X
					57	Value57X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					58	Value58X
					59	Value59X
					60	Value60X
					61	Value61X
					62	Value62X
					63	Value63X
					64	Value64X
					65	Value65X
					66	Value66X
					67	Value67X
					68	Value68X
					69	Value69X
					70	Value70X
					71	Value71X
					72	Value72X
					73	Value73X
					74	Value74X
					75	Value75X
					76	Value76X
					77	Value77X
					78	Value78X
					79	Value79X
					80	Value80X
					81	Value81X
					82	Value82X
					83	Value83X
					84	Value84X
					85	Value85X
					86	Value86X
					87	Value87X
					88	Value88X
					89	Value89X
					90	Value90X
					91	Value91X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					92	Value92X
					93	Value93X
					94	Value94X
					95	Value95X
					96	Value96X
					97	Value97X
					98	Value98X
					99	Value99X
					100	Value100X
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					77	UtcMinus0200MidMinusatlantic
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					34	UtcPlus0200Istanbul
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					116	UtcPlus0200Kaliningrad
					113	UtcPlus0300Istanbul
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					111	UtcPlus1000Magadan
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					114	UtcPlus1100Magadan114
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	SIMATIC Memory Card					
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
	Display					
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		ProtectionPassword	String	Password		
		ProtectionConfirmPassword	String	Confirm password		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					1800	Value30Minutes
					3600	Value1Hour
	Synchronization interface [X3]					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
	Synchronization interface [X4]					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
	PROFINET interface [X1]					
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 51*-*H***-*AB0 - V2.6						
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module - 6ES7 960-1*B00-0AA5						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		DpWatchdog	Boolean	Watchdog		
		Name	String	Name		
		Author	String	Author		
		Comment	String	Comment		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					2	AsSlave
					1	AsMaster
					0	None
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		TypeName	String	InvariantTypeName		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
Module						
		DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
		PositionNumber	Int32	Index		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Comment	String	Comment		
Module - 6AG1 51*-***-*AB0 - V2.9**						
		NetworkFaultsAsMaintenance	Boolean			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		WebserverUpdateInterval	UInt64	Update interval		
		SystemPowerSupplyExternal	UInt64	General		
					0	NoConnectionToExternal24VSupply
					1	ConnectionToExternal24VSupply
		Name	String	Name		
		WebserverActivate	Boolean			
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					3	SimaticOpcUaS71500Large

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.9						
					2	SimaticOpcUaS71500Medium
					1	SimaticOpcUaS71500Small
					0	NoLicense
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					34	UtcPlus0200Istanbul
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					15	UtcMinus0330Newfoundland
					72	UtcMinus0400Santiago
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					71	UtcMinus0400Cuiaba
					70	UtcMinus0400AtlanticStandardTimeCanada
					69	UtcMinus0400Asuncion
					112	UtcMinus0400Caracas
					13	UtcMinus0430Caracas
					12	UtcMinus0500IndianaEast
					11	UtcMinus0500EasternStandardTimeUsaCanada

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.9						
					10	UtcMinus0500BogotaLimaQuito
					9	UtcMinus0600Saskatchewan
					83	UtcPlus0200Damascus
					82	UtcPlus0200Beirut
					28	UtcPlus0200AthensBucharest
					81	UtcPlus0100Windhoek
					80	UtcPlus0100WestCentralAfrica
					79	UtcPlus0100TripoliOld
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					23	UtcMonroviaReykjavik
					78	UtcCoordinatedUniversalTime
					113	UtcPlus0300Istanbul
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.9						
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					22	UtcDublinEdinburghLisbonLondon
					21	UtcCasablanca
					20	UtcMinus0100CapeVerde
					19	UtcMinus0100Azores
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					76	UtcMinus0300Salvador
					75	UtcMinus0300Montevideo
					74	UtcMinus0300Greenland
					73	UtcMinus0300CayenneFortaleza
					17	UtcMinus0300BuenosAires
					16	UtcMinus0300Brasilia
					68	UtcMinus0600CentralAmerica
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					7	UtcMinus0600CentralStandardTimeUsaCanada
					6	UtcMinus0700MountainStandardTimeUsaCanada
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					5	UtcMinus0700Arizona

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.9						
					107	UtcMinus0800PacificStandardTimeUsaCanada
					106	UtcMinus0800PacificStandardTimeMexico
					3	UtcMinus0900Alaska
					2	UtcMinus1000Hawaii
					65	UtcMinus1100MidwayIslands
					0	UtcMinus1200EniwetokKwajalein
					77	UtcMinus0200MidMinusatlantic
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					111	UtcPlus1000Magadan
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					114	UtcPlus1100Magadan114
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.9						
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					12	December
					11	November
					10	October
					9	September
					8	August
					7	July
					6	June
					5	May
					4	April
					3	March
					2	February
					1	January
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.9						
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.9						
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.9						
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					2	StartupCpuIfMismatch
					1	StartupCpuOnlyIfCompatible
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
					4	Hours
					3	Minutes
					2	Seconds
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		MacRtLicensePurchased	UInt64	Type of purchased license		
					0	NoLicense
					1	LicenseMacBasic
					2	LicenseMacAdvanced
		HostAndDomainnameActive	Boolan	Enable host and domain name		
		HostnameConfiguration	UInt32	Hostname configuration		
					0	Disabled
					1	SetHostnameAtDevice

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.9						
					2	SetHostnameInProject
					3	SetHostnameRemotely
		HostnameIdenticalToDeviceNameActive	Boolean	Hostname identical to device name		
		Hostname	String	Hostname		
		DomainConfiguration	UInt32	Domain configuration		
					0	Disabled
					1	SetDomainAtDevice
					2	SetDomainInProject
					3	SetDomainRemotely
		Domain	String	Domain configuration		
		FullName	String	Full Name		
		PnDnsConfigNameResolve	Int32			
		TimeSynchronizationNtpV2	UInt32	Enable time synchronization via NTP server		
					0	Disabled
					1	SetServersAtDevice
					2	SetServersInProject
					3	SetServersRemotely
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
	SIMATIC Memory Card					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		DpWatchdog	Boolean	Watchdog		
		Name	String	Name		
		Author	String	Author		
		Comment	String	Comment		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					2	AsSlave
					1	AsMaster
					0	None
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		TypeName	String	InvariantTypeName		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
Module						
		DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
		PositionNumber	Int32	Index		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Comment	String	Comment		
Module - 6AG1 51*-***-*AB0 - V2.8**						
		NetworkFaultsAsMaintenance	Boolean			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		WebserverUpdateInterval	UInt64	Update interval		
		SystemPowerSupplyExternal	UInt64	General		
					0	NoConnectionToExternal24VSupply
					1	ConnectionToExternal24VSupply
		Name	String	Name		
		WebserverActivate	Boolean			
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					3	SimaticOpcUaS71500Large

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.8						
					2	SimaticOpcUaS71500Medium
					1	SimaticOpcUaS71500Small
					0	NoLicense
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					34	UtcPlus0200Istanbul
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					15	UtcMinus0330Newfoundland
					72	UtcMinus0400Santiago
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					71	UtcMinus0400Cuiaba
					70	UtcMinus0400AtlanticStandardTimeCanada
					69	UtcMinus0400Asuncion
					112	UtcMinus0400Caracas
					13	UtcMinus0430Caracas
					12	UtcMinus0500IndianaEast
					11	UtcMinus0500EasternStandardTimeUsaCanada

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.8						
					10	UtcMinus0500BogotaLimaQuito
					9	UtcMinus0600Saskatchewan
					83	UtcPlus0200Damascus
					82	UtcPlus0200Beirut
					28	UtcPlus0200AthensBucharest
					81	UtcPlus0100Windhoek
					80	UtcPlus0100WestCentralAfrica
					79	UtcPlus0100TripoliOld
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					23	UtcMonroviaReykjavik
					78	UtcCoordinatedUniversalTime
					113	UtcPlus0300Istanbul
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.8						
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					22	UtcDublinEdinburghLisbonLondon
					21	UtcCasablanca
					20	UtcMinus0100CapeVerde
					19	UtcMinus0100Azores
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					76	UtcMinus0300Salvador
					75	UtcMinus0300Montevideo
					74	UtcMinus0300Greenland
					73	UtcMinus0300CayenneFortaleza
					17	UtcMinus0300BuenosAires
					16	UtcMinus0300Brasilia
					68	UtcMinus0600CentralAmerica
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					7	UtcMinus0600CentralStandardTimeUsaCanada
					6	UtcMinus0700MountainStandardTimeUsaCanada
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					5	UtcMinus0700Arizona

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.8						
					107	UtcMinus0800PacificStandardTimeUsaCanada
					106	UtcMinus0800PacificStandardTimeMexico
					3	UtcMinus0900Alaska
					2	UtcMinus1000Hawaii
					65	UtcMinus1100MidwayIslands
					0	UtcMinus1200EniwetokKwajalein
					77	UtcMinus0200MidMinusatlantic
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					111	UtcPlus1000Magadan
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					114	UtcPlus1100Magadan114
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.8						
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					12	December
					11	November
					10	October
					9	September
					8	August
					7	July
					6	June
					5	May
					4	April
					3	March
					2	February
					1	January
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.8						
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.8						
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.8						
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					2	StartupCpuIfMismatch
					1	StartupCpuOnlyIfCompatible
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
					4	Hours
					3	Minutes
					2	Seconds
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
	SIMATIC Memory Card					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		PositionNumber	Int32	Index		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		ShortDesignation	String	Short designation		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		DpWatchdog	Boolean	Watchdog		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module						
		DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-***-*AB0 - V2.6**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		TypeName	String	InvariantTypeName		
		WebserverActivate	Boolean			
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
					1	Value1X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					2	Value2X
					3	Value3X
					4	Value4X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
					51	Value51X
					52	Value52X
					53	Value53X
					54	Value54X
					55	Value55X
					56	Value56X
					57	Value57X
					58	Value58X
					59	Value59X
					60	Value60X
					61	Value61X
					62	Value62X
					63	Value63X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					64	Value64X
					65	Value65X
					66	Value66X
					67	Value67X
					68	Value68X
					69	Value69X
					70	Value70X
					71	Value71X
					72	Value72X
					73	Value73X
					74	Value74X
					75	Value75X
					76	Value76X
					77	Value77X
					78	Value78X
					79	Value79X
					80	Value80X
					81	Value81X
					82	Value82X
					83	Value83X
					84	Value84X
					85	Value85X
					86	Value86X
					87	Value87X
					88	Value88X
					89	Value89X
					90	Value90X
					91	Value91X
					92	Value92X
					93	Value93X
					94	Value94X
					95	Value95X
					96	Value96X
					97	Value97X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					98	Value98X
					99	Value99X
					100	Value100X
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					77	UtcMinus0200MidMinusatlantic
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					34	UtcPlus0200Istanbul
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					113	UtcPlus0300Istanbul
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					111	UtcPlus1000Magadan
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					114	UtcPlus1100Magadan114
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	SIMATIC Memory Card					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsAgingSimaticMemoryCard	Boolean	Aging of the SIMATIC memory card		
		DiagnosticsAgingSimaticMemoryCardThreshold	UInt64	Threshold value		
		PositionNumber	Int32	Index		
	Display					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayWriteAccess	Boolean	Enable write access		
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
					9	Turkish
					10	PortugueseBrazil
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		OptionalIoDevice	Boolean	Optional IO-Device		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X3]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	OPC UA					
		Name	String	Name		
		PositionNumber	Int32	Index		
		OpcUaStandardServerInterface	Boolean	Enable standard SIMATIC server interface		
		OpcUaMaxSessionTimeout	UInt32	Max. session timeout:		
		OpcUaMaxSessions	UInt32	Max. number of OPC UA sessions:		
		OpcUaMaxRegisteredNodes	UInt32	Max. number of registered nodes:		
		OpcUaMaxMonitoredItems	UInt32	Max. number of monitored items:		
		OpcUaExportArrayMembers	Boolean	Export array elements as separate nodes		
		OpcUaClient	Boolean	Enable OPC UA client		
		OpcUaApplicationName	String	Application name		
		OpcUaServer	Boolean	Activate OPC UA server		
		OpcUaPort	UInt64	Port		
		OpcUaMinimumSamplingInterval	UInt64	Minimum sampling interval:		
		OpcUaMinimumPublishingInterval	UInt64	Minimum publishing interval:		
		OpcUaGuestAuthentication	Boolean	Enable guest authentication		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.6						
		OpcUaPasswordAuthentication	Boolean	Enable user name and password authentication		
		OpcUaAutoAcceptAllClientCertificates	Boolean	AutoAcceptClient		
		OpcUaSecurityPolicies	UInt64			
					0	NoneSelected
					1	OpcUaSecurityPoliciesNone
					2	OpcUaSecurityPolicies128RSAS
					4	OpcUaSecurityPolicies128RSASE
					8	OpcUaSecurityPolicies256S
					16	OpcUaSecurityPolicies256SE
					32	OpcUaSecurityPolicies256SHAS
					64	OpcUaSecurityPolicies256SHASE
		OpcUaUmacUserConfiguration	Boolean	Enable additional user management via project security settings		
		OpcUaDeprecatedTypeDictionary	Boolean	Activate TypeDictionary		
Module						
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		OptionalIoDevice	Boolean	Optional IO-Device		
	Port					
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		ShortDesignation	String	Short designation		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		DpWatchdog	Boolean	Watchdog		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module						
		DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-***-*AB0 - V2.5**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		TypeName	String	InvariantTypeName		
		WebserverActivate	Boolean			
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
					1	Value1X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
					2	Value2X
					3	Value3X
					4	Value4X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
					51	Value51X
					52	Value52X
					53	Value53X
					54	Value54X
					55	Value55X
					56	Value56X
					57	Value57X
					58	Value58X
					59	Value59X
					60	Value60X
					61	Value61X
					62	Value62X
					63	Value63X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
					64	Value64X
					65	Value65X
					66	Value66X
					67	Value67X
					68	Value68X
					69	Value69X
					70	Value70X
					71	Value71X
					72	Value72X
					73	Value73X
					74	Value74X
					75	Value75X
					76	Value76X
					77	Value77X
					78	Value78X
					79	Value79X
					80	Value80X
					81	Value81X
					82	Value82X
					83	Value83X
					84	Value84X
					85	Value85X
					86	Value86X
					87	Value87X
					88	Value88X
					89	Value89X
					90	Value90X
					91	Value91X
					92	Value92X
					93	Value93X
					94	Value94X
					95	Value95X
					96	Value96X
					97	Value97X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
					98	Value98X
					99	Value99X
					100	Value100X
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					77	UtcMinus0200MidMinusatlantic
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					34	UtcPlus0200Istanbul
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					113	UtcPlus0300Istanbul
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					111	UtcPlus1000Magadan
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					114	UtcPlus1100Magadan114
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupConfigurationTimeout	UInt64	ParameterizationTime		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.5						
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		ShortDesignation	String	Short designation		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		DpWatchdog	Boolean	Watchdog		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module						
		DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-***-*AB0 - V2.1**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		TypeName	String	InvariantTypeName		
		WebserverActivate	Boolean			
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
					51	Value51X
					52	Value52X
					53	Value53X
					54	Value54X
					55	Value55X
					56	Value56X
					57	Value57X
					58	Value58X
					59	Value59X
					60	Value60X
					61	Value61X
					62	Value62X
					63	Value63X
					64	Value64X
					65	Value65X
					66	Value66X
					67	Value67X
					68	Value68X
					69	Value69X
					70	Value70X
					71	Value71X
					72	Value72X
					73	Value73X
					74	Value74X
					75	Value75X
					76	Value76X
					77	Value77X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
					78	Value78X
					79	Value79X
					80	Value80X
					81	Value81X
					82	Value82X
					83	Value83X
					84	Value84X
					85	Value85X
					86	Value86X
					87	Value87X
					88	Value88X
					89	Value89X
					90	Value90X
					91	Value91X
					92	Value92X
					93	Value93X
					94	Value94X
					95	Value95X
					96	Value96X
					97	Value97X
					98	Value98X
					99	Value99X
					100	Value100X
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					77	UtcMinus0200MidMinusatlantic
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					60	UtcPlus1100SolomonIslandsNewCaledonia
					61	UtcPlus1100Vladivostok
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupConfigurationTimeout	UInt64	Configuration time		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.1						
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		ShortDesignation	String	Short designation		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		DpWatchdog	Boolean	Watchdog		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module						
		DiagnosticsNoLoadVoltage	Boolean	No supply voltage 2L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-***-*AB0 - V2.0**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
					51	Value51X
					52	Value52X
					53	Value53X
					54	Value54X
					55	Value55X
					56	Value56X
					57	Value57X
					58	Value58X
					59	Value59X
					60	Value60X
					61	Value61X
					62	Value62X
					63	Value63X
					64	Value64X
					65	Value65X
					66	Value66X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
					67	Value67X
					68	Value68X
					69	Value69X
					70	Value70X
					71	Value71X
					72	Value72X
					73	Value73X
					74	Value74X
					75	Value75X
					76	Value76X
					77	Value77X
					78	Value78X
					79	Value79X
					80	Value80X
					81	Value81X
					82	Value82X
					83	Value83X
					84	Value84X
					85	Value85X
					86	Value86X
					87	Value87X
					88	Value88X
					89	Value89X
					90	Value90X
					91	Value91X
					92	Value92X
					93	Value93X
					94	Value94X
					95	Value95X
					96	Value96X
					97	Value97X
					98	Value98X
					99	Value99X
					100	Value100X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
					0	NoLicense
					1	Value1X
					2	Value2X
					3	Value3X
					4	Value4X
					5	Value5X
					6	Value6X
					7	Value7X
					8	Value8X
					9	Value9X
					10	Value10X
					11	Value11X
					12	Value12X
					13	Value13X
					14	Value14X
					15	Value15X
					16	Value16X
					17	Value17X
					18	Value18X
					19	Value19X
					20	Value20X
					21	Value21X
					22	Value22X
					23	Value23X
					24	Value24X
					25	Value25X
					26	Value26X
					27	Value27X
					28	Value28X
					29	Value29X
					30	Value30X
					31	Value31X
					32	Value32X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
					33	Value33X
					34	Value34X
					35	Value35X
					36	Value36X
					37	Value37X
					38	Value38X
					39	Value39X
					40	Value40X
					41	Value41X
					42	Value42X
					43	Value43X
					44	Value44X
					45	Value45X
					46	Value46X
					47	Value47X
					48	Value48X
					49	Value49X
					50	Value50X
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					77	UtcMinus0200MidMinusatlantic
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					116	UtcPlus0200Kaliningrad
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					118	UtcPlus0500Yekaterinburg
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					60	UtcPlus1100SolomonIslandsNewCaledonia

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
					61	UtcPlus1100Vladivostok
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					63	UtcPlus1100Magadan
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V2.0						
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupConfigurationTimeout	UInt64	Configuration time		
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0					
	InterfaceType	Int32			
	InterfaceOperatingModes	Int32			
	Label	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DpOperatingMode	UInt64	Operating mode		
				1	DpMaster
				2	DpSlave
	TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
				0	None
				1	AsMaster
				2	AsSlave
	ShortDesignation	String	Short designation		
	Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
	TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
				0	None
				1	Value1Second
				2	Value10Seconds
				3	Value1Minute
				4	Value10Minutes
				5	Value1Hour
				6	Value12Hours
				7	Value24Hours
	DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
	DpWatchdog	Boolean	Watchdog		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Index		
	TypeName	String	InvariantTypeName		
Module - 6AG1 51*-***-*AB0 - V1.8**					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		StartupConfigurationTimeout	UInt64	Configuration time		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
					90	UtcPlus0600Yekaterinburg
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	SIMATIC Memory Card					
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Display					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X3]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.8						
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		ShortDesignation	String	Short designation		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		DpWatchdog	Boolean	Watchdog		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module - 6AG1 51*-***-*AB0 - V1.7**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		StartupConfigurationTimeout	UInt64	Configuration time		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		ProtectionSummarizeSecurityEventsOnHighLoad	Boolean	Summarize security events in case of high message volume		
		ProtectionIntervalForSummarizeOfSecurityEvents	UInt64	Length of an interval		
		ProtectionUnitForSummarizeOfSecurityEvents	UInt64	Unit		
					2	Seconds
					3	Minutes
					4	Hours
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					89	UtcPlus0600Daka

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
					90	UtcPlus0600Yekaterinburg
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					1	Active
					0	Deactivated
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	SIMATIC Memory Card					
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Display					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		OptionalIoDevice	Boolean	Optional IO-Device		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X3]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.7						
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 545-5DA00-0AB0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
					2	DpSlave
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		ShortDesignation	String	Short designation		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		DpUseForTestCommissioningRouting	Boolean	Test, commissioning and routing		
		DpWatchdog	Boolean	Watchdog		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module - 6AG1 51*-***-*AB0 - V1.6**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					0	Deactivated
					1	Active
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		StartupConfigurationTimeout	UInt64	Configuration time		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	SIMATIC Memory Card					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Display					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
					5	Value5Seconds
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
	PROFINET interface [X3]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.6						
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-***-*AB0 - V1.5**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ConfigurationControl	Boolean	Allow to reconfigure the device via the user program		
					0	Deactivated
					1	Active
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		StartupConfigurationTimeout	UInt64	Configuration time		
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5					
				12	Value1200PM
				13	Value0100PM
				14	Value0200PM
				15	Value0300PM
				16	Value0400PM
				17	Value0500PM
				18	Value0600PM
				19	Value0700PM
				20	Value0800PM
				21	Value0900PM
				22	Value1000PM
				23	Value1100PM
	StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
				0	NoRestartRemainInStopMode
				1	WarmRestartRun
				3	WarmRestartOperatingModeBeforePowerOff
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	CycleMaximumCycleTime	UInt64	Maximum cycle time		
	CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
	CycleMinimumCycleTime	UInt64	Minimum cycle time		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
SIMATIC Memory Card					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
Display					
	Author	String	Author		
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
		Name	String	Name		
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
					6	Japanese
					7	Korean
					8	Russian
					9	Turkish
					10	PortugueseBrazil
		DisplayUpdateInterval	UInt64	Time until update		
					0	Disabled
					1	Value1Second

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
					2	Value2Seconds
					3	Value3Seconds
					4	Value4Seconds
					5	Value5Seconds
					10	Value10Seconds
					15	Value15Seconds
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
		DisplayProtection	Boolean	Enable display protection		
		DisplayAutoLogOffTime	UInt64	Time until automatic logoff		
					0	Disabled
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
					3600	Value1Hour
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X3]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.5						
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-***-*AB0 - V1.1**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupConfigurationTimeout	UInt64	Configuration time		
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada
					7	UtcMinus0600CentralStandardTimeUsaCanada

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	SIMATIC Memory Card					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Display					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DisplayTimeToStandbyMode	UInt64	Time to standby mode		
					0	Disabled

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
					0	Disabled
					30	Value30Seconds
					60	Value1Minute
					120	Value2Minutes
					300	Value5Minutes
					600	Value10Minutes
					900	Value15Minutes
					1800	Value30Minutes
		DisplayDefaultLanguage	UInt64	Default language on display		
					0	English
					1	German
					2	Italian
					3	French
					4	Spanish
					5	ChineseSimplified
		DisplayProtection	Boolean	Enable display protection		
		PositionNumber	Int32	Index		
	DP interface					
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
					0	None
					1	AsMaster
					2	AsSlave
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		PositionNumber	Int32	Index		
	PROFINET interface [X2]					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevelIo	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.1						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-***-*AB0 - V1.0**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		SystemPowerSupplyExternal	UInt64	General		
					1	ConnectionToExternal24VSupply
					0	NoConnectionToExternal24VSupply
		ShortDesignation	String	Short designation		
		WebserverActivate	Boolean	Activate web server on this module		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverUpdateInterval	UInt64	Update interval		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupConfigurationTimeout	UInt64	Configuration time		
		CycleCommunicationLoad	UInt64	Cycle load due to communication		
		ProtectionEnablePutGetCommunication	Boolean	Permit access with PUT/GET communication from remote partner		
		NetworkFaultsAsMaintenance	Boolean			
		SystemMemoryByte	Boolean	Enable the use of system memory byte		
		SystemMemoryByteAddress	UInt64	Address of system memory byte (MBx)		
		ClockMemoryByte	Boolean	Enable the use of clock memory byte		
		ClockMemoryByteAddress	UInt64	Address of clock memory byte (MBx)		
		TimeOfDayLocalTimeZone	UInt64	Time zone		
					0	UtcMinus1200EniwetokKwajalein
					65	UtcMinus1100MidwayIslands
					2	UtcMinus1000Hawaii
					3	UtcMinus0900Alaska
					106	UtcMinus0800PacificStandardTimeMexico
					107	UtcMinus0800PacificStandardTimeUsaCanada
					5	UtcMinus0700Arizona
					67	UtcMinus0700ChihuahuaLaPazMazatlan
					6	UtcMinus0700MountainStandardTimeUsaCanada

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0						
					7	UtcMinus0600CentralStandardTimeUsaCanada
					8	UtcMinus0600GuadalajaraMexicoCityMonterrey
					68	UtcMinus0600CentralAmerica
					9	UtcMinus0600Saskatchewan
					10	UtcMinus0500BogotaLimaQuito
					11	UtcMinus0500EasternStandardTimeUsaCanada
					12	UtcMinus0500IndianaEast
					69	UtcMinus0400Asuncion
					70	UtcMinus0400AtlanticStandardTimeCanada
					71	UtcMinus0400Cuiaba
					14	UtcMinus0400GeorgetownLaPazManausSanJuan
					72	UtcMinus0400Santiago
					15	UtcMinus0330Newfoundland
					16	UtcMinus0300Brasilia
					17	UtcMinus0300BuenosAires
					73	UtcMinus0300CayenneFortaleza
					74	UtcMinus0300Greenland
					75	UtcMinus0300Montevideo
					76	UtcMinus0300Salvador
					105	UtcMinus0200CoordinatedUniversalTimeMinus02
					19	UtcMinus0100Azores
					20	UtcMinus0100CapeVerde
					21	UtcCasablanca
					22	UtcDublinEdinburghLisbonLondon
					78	UtcCoordinatedUniversalTime
					23	UtcMonroviaReykjavik
					24	UtcPlus0100AmsterdamBerlinBernRomeStockholmVienna
					27	UtcPlus0100BelgradeBratislavaBudapestLjubljanaPrague
					25	UtcPlus0100BrusselsCopenhagenMadridParis
					26	UtcPlus0100SarajevoSkopjeWarsawZagreb
					79	UtcPlus0100TripoliOld

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0						
					80	UtcPlus0100WestCentralAfrica
					81	UtcPlus0100Windhoek
					28	UtcPlus0200AthensBucharest
					82	UtcPlus0200Beirut
					83	UtcPlus0200Damascus
					29	UtcPlus0200HararePretoria
					32	UtcPlus0200HelsinkiKievRigaSofiaTallinnWilna
					30	UtcPlus0200Jerusalem
					31	UtcPlus0200Cairo
					33	UtcPlus0200EasternEurope
					101	UtcPlus0100Tripoli
					102	UtcPlus0300Amman
					84	UtcPlus0300AmmanOld
					35	UtcPlus0300Baghdad
					36	UtcPlus0300KuwaitRiyadh
					37	UtcPlus0300Nairobi
					38	UtcPlus0330Teheran
					40	UtcPlus0400AbuDhabiMuscat
					41	UtcPlus0400Baku
					86	UtcPlus0400Yerevan
					87	UtcPlus0400PortLouis
					42	UtcPlus0400Tbilisi
					43	UtcPlus0430Kabul
					45	UtcPlus0500AshgabatTashkent
					44	UtcPlus0500IslamabadKarachi
					46	UtcPlus0530MumbaiKolkataChennaiNewDelhi
					88	UtcPlus0530SriJayawardenepura
					47	UtcPlus0545Nepal
					48	UtcPlus0600Astana
					89	UtcPlus0600Daka
					49	UtcPlus0630YangonRangoon
					50	UtcPlus0700BangkokHanoiJakarta
					93	UtcPlus0800KualaLumpurSingapore

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0						
					51	UtcPlus0800BeijingChongqingHongKongUrumchi
					52	UtcPlus0800Perth
					94	UtcPlus0800Taipei
					95	UtcPlus0800UlaanbaatarUlanBator
					96	UtcPlus0900OsakaSapporoTokyo
					97	UtcPlus0900Seoul
					54	UtcPlus0930AdelaideDarwin
					55	UtcPlus0930Darwin
					56	UtcPlus1000BrisbaneCanberraMelbourneSydney
					57	UtcPlus1000CanberraMelbourneSydney
					58	UtcPlus1000GuamPortMoresby
					59	UtcPlus1000Hobart
					60	UtcPlus1100SolomonIslandsNewCaledonia
					62	UtcPlus1200AucklandWellington
					64	UtcPlus1200Fiji
					99	UtcPlus1200CoordinatedUniversalTimePlus12
					100	UtcPlus1300Nukualofa
					1	UtcPlus1300Samoa
					77	UtcMinus0200MidMinusatlantic
					116	UtcPlus0200Kaliningrad
					85	UtcPlus0300KaliningradMinsk
					117	UtcPlus0300MoscowStDotPetersburgVolgograd
					119	UtcPlus0400MoscowStDotPetersburgVolgograd
					118	UtcPlus0500Yekaterinburg
					90	UtcPlus0600Yekaterinburg
					115	UtcPlus0600Novosibirsk
					91	UtcPlus0700Novosibirsk
					120	UtcPlus0700Krasnoyarsk
					92	UtcPlus0800Krasnoyarsk
					108	UtcPlus0800Irkutsk
					53	UtcPlus0900Irkutsk
					109	UtcPlus0900Yakutsk
					98	UtcPlus1000Yakutsk

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0						
					110	UtcPlus1000Vladivostok
					61	UtcPlus1100Vladivostok
					63	UtcPlus1100Magadan
					13	UtcMinus0430Caracas
					112	UtcMinus0400Caracas
					34	UtcPlus0200Istanbul
					113	UtcPlus0300Istanbul
					111	UtcPlus1000Magadan
					114	UtcPlus1100Magadan114
		TimeOfDayActivateDaylightSavingTime	Boolean	Activate daylight saving time		
		TimeOfDayDaylightSavingTimeOffset	UInt64	Difference between standard and daylight saving time		
		TimeOfDayDaylightSavingTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second
					3	Third
					4	Fourth
					5	Last
		TimeOfDayDaylightSavingTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayDaylightSavingTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0						
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayDaylightSavingTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		TimeOfDayStandardTimeStartWeek	UInt64	Selection of the week		
					1	First
					2	Second

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0						
					3	Third
					4	Fourth
					5	Last
		TimeOfDayStandardTimeStartWeekday	UInt64	Selection of the weekday		
					1	Sunday
					2	Monday
					3	Tuesday
					4	Wednesday
					5	Thursday
					6	Friday
					7	Saturday
		TimeOfDayStandardTimeStartMonth	UInt64	of		
					1	January
					2	February
					3	March
					4	April
					5	May
					6	June
					7	July
					8	August
					9	September
					10	October
					11	November
					12	December
		TimeOfDayStandardTimeStartHour	UInt64	at		
					0	Midnight
					1	Value0100AM
					2	Value0200AM
					3	Value0300AM
					4	Value0400AM
					5	Value0500AM
					6	Value0600AM
					7	Value0700AM

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0						
					8	Value0800AM
					9	Value0900AM
					10	Value1000AM
					11	Value1100AM
					12	Value1200PM
					13	Value0100PM
					14	Value0200PM
					15	Value0300PM
					16	Value0400PM
					17	Value0500PM
					18	Value0600PM
					19	Value0700PM
					20	Value0800PM
					21	Value0900PM
					22	Value1000PM
					23	Value1100PM
		StartupActionAfterPowerOn	UInt64	Startup after POWER ON		
					0	NoRestartRemainInStopMode
					1	WarmRestartRun
					3	WarmRestartOperatingModeBeforePowerOff
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual configuration		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		CycleMaximumCycleTime	UInt64	Maximum cycle time		
		CycleEnableMinimumCycleTime	Boolean	Enable minimum cycle time for cyclic OBs		
		CycleMinimumCycleTime	UInt64	Minimum cycle time		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	SIMATIC Memory Card					
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0					
	Name	String	Name		
	PositionNumber	Int32	Index		
Display					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DisplayTimeToStandbyMode	UInt64	Time to standby mode		
				0	Disabled
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
				600	Value10Minutes
				900	Value15Minutes
				1800	Value30Minutes
	DisplayTimeToEnergySavingMode	UInt64	Time to energy saving mode		
				0	Disabled
				30	Value30Seconds
				60	Value1Minute
				120	Value2Minutes
				300	Value5Minutes
				600	Value10Minutes
				900	Value15Minutes
				1800	Value30Minutes
	DisplayDefaultLanguage	UInt64	Default language on display		
				0	English
				1	German
				2	Italian
				3	French
				4	Spanish
				5	ChineseSimplified
	DisplayProtection	Boolean	Enable display protection		
	PositionNumber	Int32	Index		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0					
DP interface					
	InterfaceType	Int32			
	InterfaceOperatingModes	Int32			
	Label	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DpOperatingMode	UInt64	Operating mode		
				1	DpMaster
	TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
				0	None
				1	AsMaster
				2	AsSlave
	TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
				0	None
				1	Value1Second
				2	Value10Seconds
				3	Value1Minute
				4	Value10Minutes
				5	Value1Hour
				6	Value12Hours
				7	Value24Hours
	PositionNumber	Int32	Index		
PROFINET interface [X2]					
	IECV22LLDPMode	Boolean			
	DiagnosticsCommunicationError	Boolean			
	KeepAlivesInterval	UInt32			
	LoadLimitation	Boolean			
	KeepAlivesInterval	UInt32			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0						
		Comment	String	Comment		
		Name	String	Name		
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		PositionNumber	Int32	Index		
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	PROFINET interface [X1]					
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0						
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		IsIoController	Boolean	IO controller		
		ParameterAssignmentOfPnInterfaceByHigherLevel	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		UseWebServerForInterface	Boolean	Enable Web server using this interface		
		TimeSynchronizationNtp	Boolean	Enable time synchronization via NTP server		
					0	Deactivated
					1	Active
		TimeSynchronizationServer1	String	Server 1		
		TimeSynchronizationServer2	String	Server 2		
		TimeSynchronizationServer3	String	Server 3		
		TimeSynchronizationServer4	String	Server 4		
		TimeSynchronizationUpdateInterval	UInt64	Update interval		
		IsIoDevice	Boolean	IO device		
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		PositionNumber	Int32	Index		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AG1 51*-*****-*AB0 - V1.0						
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Linux - V2.2					
	PnSendClock	Int64			
	IECV22LLDPMode	Boolean			
	DeviceReplacementWithoutExchangeableMedium	Boolean			
	OverwriteDeviceNames	Boolean			
	LoadLimitation	Boolean			
	DiagnosticsCommunicationError	Boolean			
	KeepAlivesInterval	UInt32			
	KeepAlivesInterval	UInt32			
	CalculatedBandwidthForCyclicIoData	Int32			
	MaxBandwidthForCyclicIoData	Int32			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
Port_Linux_Submodule_V2.2					
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
Module - CP1625 Host - V2.2					
	IECV22LLDPMode	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - CP1625 Host - V2.2						
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		AutomaticMinimum	Boolean			
		DelayTime	Double			
		ApplicationCycle	Double			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
	Port_Host_Submodule_V2.2					
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - CP1625 Host - V2.2					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
Module - IoT20x0 - V2.2					
	PnSendClock	Int64			
	IECV22LLDPMode	Boolean			
	DeviceReplacementWithoutExchangeableMedium	Boolean			
	OverwriteDeviceNames	Boolean			
	LoadLimitation	Boolean			
	DiagnosticsCommunicationError	Boolean			
	KeepAlivesInterval	UInt32			
	KeepAlivesInterval	UInt32			
	CalculatedBandwidthForCyclicIoData	Int32			
	MaxBandwidthForCyclicIoData	Int32			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
Port_IoT20x0_Submodule_V2.2					
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - IoT20x0 - V2.2						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module - Linux Native - V2.2						
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
	Port_Linux_Native_Submodule_V2.2					
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Linux Native - V2.2						
		Comment	String	Comment		
		Name	String	Name		
Module - CP1625 Stand-alone - V2.2						
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		AutomaticMinimum	Boolean			
		DelayTime	Double			
		ApplicationCycle	Double			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
	Port_Stand_alone_Submodule_V2.2					
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - CP1625 Stand-alone - V2.2						
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module - Windows - V2.2						
		PnSendClock	Int64			
		IECV22LLDPMode	Boolean			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		LoadLimitation	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		KeepAlivesInterval	UInt32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MaxBandwidthForCyclicIoData	Int32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
	Port_WinPcap_Submodule_V2.2					
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Windows - V2.2						
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GK1 562-3AA00 - V7.1.2						
		SharedDeviceAccessConfigured	Boolean			
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Name	String			
		ShortDesignation	String	Short designation		
		TimeOfDayTypeOfSynchronizationOnDp	UInt64	Synchronization type		
		InterfaceAssignmentType	UInt32	InterfaceAssignmentType		
		InterfaceLabel	String	InterfaceLabel		
		IpcExpansion	String	Selected IPC expansion (HW)		
		Name	String	Name		
		Author	String	Author		
		FirmwareVersion	String	Firmware version		
		OrderNumber	String	Article number		
		DpOperatingMode	UInt64	Operating mode		
					1	DpMaster
		TimeOfDayTimeIntervalOnDp	UInt64	Time interval		
					0	None
					1	Value1Second
					2	Value10Seconds
					3	Value1Minute
					4	Value10Minutes
					5	Value1Hour
					6	Value12Hours
					7	Value24Hours
		Comment	String	Comment		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		OnBoardCpAssigment	UInt64	Use interface for		
					0	None
		HardwareResource	UInt32	Hardware resource		
Module - Cp1625Assigned_1508 - V1.3						
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Cp1625Assigned_1508 - V1.3						
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceAssignmentType	UInt32	InterfaceAssignmentType		
		InterfaceLabel	String	InterfaceLabel		
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		OrderNumber	String	Article number		
		IsIoController	Boolean	IO controller		
		IsIoDevice	Boolean	IO device		
		ParameterAssignmentOfPnInterfaceByHigherLevel	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		OptionalIoDevice	Boolean	Optional IO-Device		
		InterfaceIndex	String	Index		
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
Module - Cp1625Assigned - V1.3						

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Cp1625Assigned - V1.3					
	IECV22LLDPMode	Boolean			
	LoadLimitation	Boolean			
	PnSendClock	Int64			
	DeviceReplacementWithoutExchangeableMedium	Boolean			
	OverwriteDeviceNames	Boolean			
	DiagnosticsCommunicationError	Boolean			
	KeepAlivesInterval	UInt32			
	MaxBandwidthForCyclicIoData	Int32			
	CalculatedBandwidthForCyclicIoData	Int32			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	KeepAlivesInterval	UInt32			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceAssignmentType	UInt32	InterfaceAssignmentType		
	InterfaceLabel	String	InterfaceLabel		
	InterfaceType	Int32			
	Name	String			
	FirmwareVersion	String	Firmware version		
	OrderNumber	String	Article number		
	Comment	String	Comment		
	IsIoController	Boolean	IO controller		
	IsIoDevice	Boolean	IO device		
	ParameterAssignmentOfPnInterfaceByHigherLevel	Boolean	Parameter assignment of PN interface by higher-level IO controller		
				0	Deactivated
				1	Active
	PrioritizedStartupIDevice	Boolean	Prioritized startup		
	Author	String	Author		
	Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
	OptionalIoDevice	Boolean	Optional IO-Device		
	InterfaceIndex	String	Index		
	AssetManagementViaUserProgram	Boolean	Enable asset management via user program		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		InterfaceAssignmentType	UInt32	InterfaceAssignmentType		
		InterfaceLabel	String	InterfaceLabel		
		Name	String			
		Comment	String	Comment		
		IsIoController	Boolean	IO controller		
		IsIoDevice	Boolean	IO device		
		ParameterAssignmentOfPnInterfaceByHigherLevel	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		OptionalIoDevice	Boolean	Optional IO-Device		
		OnBoardCpAssigment	UInt64	Use interface for		
					0	None
		InterfaceIndex	String	Index		
		HardwareResource	UInt32	Hardware resource		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
Module - SpringVille - V21.9						
		IECV22LLDPMode	Boolean			
		LoadLimitation	Boolean			
		PnSendClock	Int64			
		DeviceReplacementWithoutExchangeableMedium	Boolean			
		OverwriteDeviceNames	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		MaxBandwidthForCyclicIoData	Int32			
		CalculatedBandwidthForCyclicIoData	Int32			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceAssignmentType	UInt32	InterfaceAssignmentType		
		InterfaceLabel	String	InterfaceLabel		
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		IpcExpansion	String	Selected IPC expansion (HW)		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		OrderNumber	String	Article number		
		IsIoController	Boolean	IO controller		
		IsIoDevice	Boolean	IO device		
		ParameterAssignmentOfPnInterfaceByHigherLevel	Boolean	Parameter assignment of PN interface by higher-level IO controller		
					0	Deactivated
					1	Active
		PrioritizedStartupIDevice	Boolean	Prioritized startup		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeDecentral	UInt64	Default F-monitoring time for F-I/O of this interface		
		OptionalIoDevice	Boolean	Optional IO-Device		
		OnBoardCpAssigment	UInt64	Use interface for		
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - SpringVille - V21.9						
		AssetManagementViaUserProgram	Boolean	Enable asset management via user program		
Module - 6ES7 672-5DC11-0YA0 - V21.9						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Index	UInt32	Index		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		RetentiveDataMemoryUsage	UInt32	Retentive data memory		
					1	NvramOfThePcSystem
					0	PcMassStorage
		HardwareLEDUsage	Boolean			
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 672-5DC11-0YA0 - V21.9						
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		WebserverUpdateInterval	UInt64	Update interval		
Module - 6ES7 672-5SC11-0YA0 - V21.9						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Index	UInt32	Index		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeCentral	UInt64	Default F-monitoring time for central F-I/O		
		RetentiveDataMemoryUsage	UInt32	Retentive data memory		
					0	PcMassStorage
					1	NvramOfThePcSystem
		Failsafe_CentralFSourceAddress	UInt64	Central F-source address		
		HardwareLEDUsage	Boolean			
		Failsafe_FCapabilityActivated	Boolean	F-capability activated		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 672-5SC11-0YA0 - V21.9						
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		WebserverUpdateInterval	UInt64	Update interval		
	Submodule					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Author	String	Author		
Module - 6ES7 672-5VC11-0YA0 - V21.9						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Index	UInt32	Index		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 672-5VC11-0YA0 - V21.9						
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		RetentiveDataMemoryUsage	UInt32	Retentive data memory		
					1	NvramOfThePcSystem
					0	PcMassStorage
		HardwareLEDUsage	Boolean			
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		WebserverUpdateInterval	UInt64	Update interval		
Module - 6ES7 672-5WC11-0YA0 - V21.9						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Index	UInt32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 672-5WC11-0YA0 - V21.9						
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		Failsafe_DefaultFmonitoringTimeCentral	UInt64	Default F-monitoring time for central F-I/O		
		RetentiveDataMemoryUsage	UInt32	Retentive data memory		
					0	PcMassStorage
					1	NvramOfThePcSystem
		Failsafe_CentralFSourceAddress	UInt64	Central F-source address		
		HardwareLEDUsage	Boolean			
		Failsafe_FCapabilityActivated	Boolean	F-capability activated		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		ConfigurationControl	Boolean	Allow reconfiguration of device via the user program		
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 672-5WC11-0YA0 - V21.9						
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		WebserverUpdateInterval	UInt64	Update interval		
	Submodule					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Author	String	Author		
Module - 6ES7 672-7AC01-0YA0 - V21.9						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Index	UInt32	Index		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		RetentiveDataMemoryUsage	UInt32	Retentive data memory		
					0	PcMassStorage
					1	NvramOfThePcSystem
		AutomaticStartAfterBootingThePc	Boolean	Automatic start after booting the PC		
		HardwareLEDUsage	Boolean			
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 672-7AC01-0YA0 - V21.9						
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		WebserverUpdateInterval	UInt64	Update interval		
Module - 6ES7 672-7FC01-0YA0 - V21.9						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Index	UInt32	Index		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		RetentiveDataMemoryUsage	UInt32	Retentive data memory		
					0	PcMassStorage
					1	NvramOfThePcSystem
		Failsafe_CentralFSourceAddress	UInt64	Central F-source address		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 672-7FC01-0YA0 - V21.9						
		AutomaticStartAfterBootingThePc	Boolean	Automatic start after booting the PC		
		HardwareLEDUsage	Boolean			
		Failsafe_FCapabilityActivated	Boolean	F-capability activated		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		WebserverUpdateInterval	UInt64	Update interval		
	Submodule					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 672-7FC01-0YA0 - V21.9						
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Author	String	Author		
Module - 6ES7 672-8AC01-0YA0 - V21.9						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Index	UInt32	Index		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		RetentiveDataMemoryUsage	UInt32	Retentive data memory		
					0	PcMassStorage
					1	NvramOfThePcSystem
		AutomaticStartAfterBootingThePc	Boolean	Automatic start after booting the PC		
		HardwareLEDUsage	Boolean			
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 672-8AC01-0YA0 - V21.9						
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		WebserverUpdateInterval	UInt64	Update interval		
Module - 6ES7 672-8FC01-0YA0 - V21.9						
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Index	UInt32	Index		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Author	String	Author		
		RetentiveDataMemoryUsage	UInt32	Retentive data memory		
					0	PcMassStorage
					1	NvramOfThePcSystem
		Failsafe_CentralFSourceAddress	UInt64	Central F-source address		
		AutomaticStartAfterBootingThePc	Boolean	Automatic start after booting the PC		
		HardwareLEDUsage	Boolean			
		Failsafe_FCapabilityActivated	Boolean	F-capability activated		
		CentralAlarmManagement	Boolean	Central alarm management in the PLC		
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverAutomaticUpdate	Boolean	Enable automatic update		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage
					1	Awp1
		OpcUaRequiredLicense	UInt64	Type of required license		
					0	NoLicense

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 672-8FC01-0YA0 - V21.9						
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		OpcUaPurchasedLicense	UInt64	Type of purchased license		
					0	NoLicense
					1	SimaticOpcUaS71500Small
					2	SimaticOpcUaS71500Medium
					3	SimaticOpcUaS71500Large
		ProDiagUsedLicenses	UInt64	Used ProDiag licenses		
					0	NoLicense
					5	Value5X
		EnergySuitePurchasedLicense5	UInt64	License type '5 energy objects'		
		EnergySuitePurchasedLicense10	UInt64	License type '10 energy objects'		
		WebserverUpdateInterval	UInt64	Update interval		
	Submodule					
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Author	String	Author		
Module - 6ES7 677-2DBx2-0xB0 - V21.9						
		Name	String			
		ShortDesignation	String	Short designation		
	Rack					
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 677-2DBx2-0xB0 - V21.9					
	Name	String			
	WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
	WebserverActivate	Boolean			
	WebserverUpdateInterval	UInt64	Update interval		
	WebserverEntryPage	UInt64	Select entry page		
				0	IntroPage
Module - 6ES7 677-2DBx2-0xx0 - V21.9					
	Name	String			
	ShortDesignation	String	Short designation		
Rack					
	NetworkFaultsAsMaintenance	Boolean			
	WebserverCertificate	Object			
	Name	String			
	WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
	WebserverActivate	Boolean			
	WebserverUpdateInterval	UInt64	Update interval		
	WebserverEntryPage	UInt64	Select entry page		
				0	IntroPage
Module - 6ES7 677-2DBx3-0xB0 - V21.9					
	Name	String			
	ShortDesignation	String	Short designation		
Rack					
	NetworkFaultsAsMaintenance	Boolean			
	WebserverCertificate	Object			
	Name	String			
	WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
	WebserverActivate	Boolean			
	WebserverUpdateInterval	UInt64	Update interval		
	WebserverEntryPage	UInt64	Select entry page		
				0	IntroPage
Module - 6ES7 677-2SBx2-0xB0 - V21.9					
	Name	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 677-2SBx2-0xB0 - V21.9					
Rack					
	NetworkFaultsAsMaintenance	Boolean			
	WebserverCertificate	Object			
	Name	String			
	WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
	WebserverActivate	Boolean			
	WebserverUpdateInterval	UInt64	Update interval		
	WebserverEntryPage	UInt64	Select entry page		
				0	IntroPage
Module - 6ES7 677-2SBx2-0xx0 - V21.9					
	Name	String			
Rack					
	NetworkFaultsAsMaintenance	Boolean			
	WebserverCertificate	Object			
	Name	String			
	WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
	WebserverActivate	Boolean			
	WebserverUpdateInterval	UInt64	Update interval		
	WebserverEntryPage	UInt64	Select entry page		
				0	IntroPage
Module - 6ES7 677-2SBx3-0xB0 - V21.9					
	Name	String			
Rack					
	NetworkFaultsAsMaintenance	Boolean			
	WebserverCertificate	Object			
	Name	String			
	WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
	WebserverActivate	Boolean			
	WebserverUpdateInterval	UInt64	Update interval		
	WebserverEntryPage	UInt64	Select entry page		
				0	IntroPage
Module - 6ES7 677-2VBx2-0xB0 - V21.9					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 677-2VBx2-0xB0 - V21.9					
	Name	String			
Rack					
	NetworkFaultsAsMaintenance	Boolean			
	WebserverCertificate	Object			
	Name	String			
	WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
	WebserverActivate	Boolean			
	WebserverUpdateInterval	UInt64	Update interval		
	WebserverEntryPage	UInt64	Select entry page		
				0	IntroPage
Module - 6ES7 677-2VBx2-0xx0 - V21.9					
	Name	String			
Rack					
	NetworkFaultsAsMaintenance	Boolean			
	WebserverCertificate	Object			
	Name	String			
	WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
	WebserverActivate	Boolean			
	WebserverUpdateInterval	UInt64	Update interval		
	WebserverEntryPage	UInt64	Select entry page		
				0	IntroPage
Module - 6ES7 677-2WBx2-0xB0 - V21.9					
	Name	String			
Rack					
	NetworkFaultsAsMaintenance	Boolean			
	WebserverCertificate	Object			
	Name	String			
	WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
	WebserverActivate	Boolean			
	WebserverUpdateInterval	UInt64	Update interval		
	WebserverEntryPage	UInt64	Select entry page		
				0	IntroPage

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 677-2WBx2-0xx0 - V21.9						
		Name	String			
	Rack					
		NetworkFaultsAsMaintenance	Boolean			
		WebserverCertificate	Object			
		Name	String			
		WebserverHttpsOnly	Boolean	Permit access only with HTTPS		
		WebserverActivate	Boolean			
		WebserverUpdateInterval	UInt64	Update interval		
		WebserverEntryPage	UInt64	Select entry page		
					0	IntroPage

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module - 6ES7 155-6BU00-0CN0 - V1.1						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		DpProtocolMode	UInt64	DP interrupt mode		
					5	S7Compatible
					7	DpV1
					4	DpV0
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OptionHandling	Boolean	Allow to reconfigure the device via the user program		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		StartupIfPresetConfigurationDoesNotMatchActualC	Boolean	Operation if preset configuration does not match actual configuration		
		DiagnosticsInterrupt	Boolean	Diagnostics interrupt (OB82)		
		PullPlugInterrupt	Boolean	Remove/insert interrupt (OB83)		
		DpWatchdog	Boolean	Watchdog activated		
		HardwareInterrupt	Boolean	Hardware interrupts (OB40 to OB 47)		
Module - 6ES7 155-6BU00-0CN0 - V3.0						

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6BU00-0CN0 - V3.0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		DpProtocolMode	UInt64	DP interrupt mode		
					5	S7Compatible
					7	DpV1
					4	DpV0
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OptionHandling	Boolean	Allow to reconfigure the device via the user program		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		StartupIfPresetConfigurationDoesNotMatchActualC	Boolean	Operation if preset configuration does not match actual configuration		
		DiagnosticsInterrupt	Boolean	Diagnostics interrupt (OB82)		
		PullPlugInterrupt	Boolean	Remove/insert interrupt (OB83)		
		DpWatchdog	Boolean	Watchdog activated		
		HardwareInterrupt	Boolean	Hardware interrupts (OB40 to OB 47)		
Module - 6ES7 155-6BU00-0CN0 - V3.1						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6BU00-0CN0 - V3.1						
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		DpProtocolMode	UInt64	DP interrupt mode		
					5	S7Compatible
					7	DpV1
					4	DpV0
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OptionHandling	Boolean	Allow to reconfigure the device via the user program		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		StartupIfPresetConfigurationDoesNotMatchActualC	Boolean	Operation if preset configuration does not match actual configuration		
		DiagnosticsInterrupt	Boolean	Diagnostics interrupt (OB82)		
		PullPlugInterrupt	Boolean	Remove/insert interrupt (OB83)		
		DpWatchdog	Boolean	Watchdog activated		
		HardwareInterrupt	Boolean	Hardware interrupts (OB40 to OB 47)		
Module - 6ES7 155-6BU01-0CN0 - V4.2						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6BU01-0CN0 - V4.2						
		DpProtocolMode	UInt64	DP interrupt mode		
					5	S7Compatible
					7	DpV1
					4	DpV0
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OptionHandling	Boolean	Allow to reconfigure the device via the user program		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		StartupIfPresetConfigurationDoesNotMatchActualC	Boolean	Operation if preset configuration does not match actual configuration		
		DiagnosticsInterrupt	Boolean	Diagnostics interrupt (OB82)		
		PullPlugInterrupt	Boolean	Remove/insert interrupt (OB83)		
		DpWatchdog	Boolean	Watchdog activated		
		HardwareInterrupt	Boolean	Hardware interrupts (OB40 to OB 47)		
Module - 6ES7 155-6AR00-0AN0 - V3.2						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AR00-0AN0 - V3.2						
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Head Submodule					
		Name	String	Name		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PositionNumber	Int32	Index		
		OptionHandling	Boolean	Allow to reconfigure the device via the user program		
	Interface					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU00-0BN0 - V1.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	Slot		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0BN0 - V1.0					
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Head Submodule					
	Name	String	Name		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Index		
	OptionHandling	Boolean	Allow to reconfigure the device via the user program		
	DiagnosticsNoLoadVoltage	Boolean	Group diagnostics: Missing supply voltage L+		
	StatusBytes	Boolean	Activate status bytes		
Interface					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU00-0BN0 - V1.1					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0BN0 - V1.1					
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	TypeName	String	InvariantTypeName		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Head Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String	Name		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Index		
	OptionHandling	Boolean	Allow to reconfigure the device via the user program		
Interface					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU00-0BN0 - V3.1					
	SharedDeviceAccessConfigured	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0BN0 - V3.1					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	TypeName	String	InvariantTypeName		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Head Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String	Name		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Index		
	OptionHandling	Boolean	Allow to reconfigure the device via the user program		
Interface					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String	Name		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0BN0 - V3.1					
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU00-0BN0 - V3.3					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	TypeName	String	InvariantTypeName		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Head Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String	Name		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Index		
	OptionHandling	Boolean	Allow to reconfigure the device via the user program		
Interface					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0BN0 - V3.3					
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU00-0CN0 - V2.1					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
Head Submodule					
	Name	String	Name		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Index		
	OptionHandling	Boolean	Allow to reconfigure the device via the user program		
Interface					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0CN0 - V2.1					
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	IsochronousMode	Boolean			
	IsochronousTiToCalculationMode	Int32			
	IsochronousTi	Double			
	IsochronousTo	Double			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU00-0CN0 - V2.2					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
Head Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String	Name		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0CN0 - V2.2						
		OptionHandling	Boolean	Allow to reconfigure the device via the user program		
	Interface					
		IECV22LLDPMode	Boolean			
		SharedDeviceAccessConfigured	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		IsochronousMode	Boolean			
		IsochronousTiToCalculationMode	Int32			
		IsochronousTi	Double			
		IsochronousTo	Double			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU00-0CN0 - V3.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0CN0 - V3.0					
Head Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String	Name		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Index		
	OptionHandling	Boolean	Allow to reconfigure the device via the user program		
Interface					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	IsochronousMode	Boolean			
	IsochronousTiToCalculationMode	Int32			
	IsochronousTi	Double			
	IsochronousTo	Double			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU00-0CN0 - V3.1					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0CN0 - V3.1						
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Head Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String	Name		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PositionNumber	Int32	Index		
		OptionHandling	Boolean	Allow to reconfigure the device via the user program		
	Interface					
		IECV22LLDPMode	Boolean			
		SharedDeviceAccessConfigured	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		IsochronousMode	Boolean			
		IsochronousTiToCalculationMode	Int32			
		IsochronousTi	Double			
		IsochronousTo	Double			
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0CN0 - V3.1						
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU00-0CN0 - V3.3						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Head Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String	Name		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PositionNumber	Int32	Index		
		OptionHandling	Boolean	Allow to reconfigure the device via the user program		
	Interface					
		IECV22LLDPMode	Boolean			
		SharedDeviceAccessConfigured	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0CN0 - V3.3						
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		IsochronousMode	Boolean			
		IsochronousTiToCalculationMode	Int32			
		IsochronousTi	Double			
		IsochronousTo	Double			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU00-0CN0 - V4.2						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Head Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String	Name		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PositionNumber	Int32	Index		
		OptionHandling	Boolean	Allow to reconfigure the device via the user program		
	Interface					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0CN0 - V4.2						
		IECV22LLDPMode	Boolean			
		SharedDeviceAccessConfigured	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		IsochronousMode	Boolean			
		IsochronousTiToCalculationMode	Int32			
		IsochronousTi	Double			
		IsochronousTo	Double			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU00-0DN0 - V4.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Head Submodule					
		SharedDeviceAccessConfigured	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU00-0DN0 - V4.0					
	Name	String	Name		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Index		
	OptionHandling	Boolean	Allow to reconfigure the device via the user program		
Interface					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	IsochronousMode	Boolean			
	IsochronousTiToCalculationMode	Int32			
	IsochronousTi	Double			
	IsochronousTo	Double			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU01-0BN0 - V4.1					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU01-0BN0 - V4.1					
	AdditionalInformation	String	Additional information		
	TypeName	String	InvariantTypeName		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Head Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String	Name		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Index		
	OptionHandling	Boolean	Allow to reconfigure the device via the user program		
Interface					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU01-0CN0 - V4.2					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU01-0CN0 - V4.2						
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Head Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String	Name		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PositionNumber	Int32	Index		
		OptionHandling	Boolean	Allow to reconfigure the device via the user program		
		DiagnosticsUnderflowVoltage	Boolean	Undervoltage		
	Interface					
		IECV22LLDPMode	Boolean			
		SharedDeviceAccessConfigured	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		IsochronousMode	Boolean			
		IsochronousTiToCalculationMode	Int32			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU01-0CN0 - V4.2					
	IsochronousTi	Double			
	IsochronousTo	Double			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Module - 6ES7 155-6AU30-0CN0 - V4.2					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
Head Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String	Name		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Index		
	OptionHandling	Boolean	Allow to reconfigure the device via the user program		
	DiagnosticsUnderflowVoltage	Boolean	Undervoltage		
Interface					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 155-6AU30-0CN0 - V4.2						
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		IsochronousMode	Boolean			
		IsochronousTiToCalculationMode	Int32			
		IsochronousTi	Double			
		IsochronousTo	Double			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
Module - 6ES5 710-8MAx1						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module - 6ES7 193-6AF00-0AA0 - V0.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		OrderNumber	String	Article number		
		ShortDesignation	String	Short designation		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	PositionNumber		
Module - 6ES7 193-6AR00-0AA0 - V0.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		OrderNumber	String	Article number		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 193-6AR00-0AA0 - V0.0						
		ShortDesignation	String	Short designation		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	PositionNumber		
Module - 6ES7 193-6AP00-0AA0 - V0.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		OrderNumber	String	Article number		
		ShortDesignation	String	Short designation		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	PositionNumber		
Module - 6ES7 193-6AG00-0AA0 - V0.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		OrderNumber	String	Article number		
		ShortDesignation	String	Short designation		
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	PositionNumber		
		FirmwareVersion	String	Firmware version		
		PlantDesignation	String	IdentificationAkz		
		LocationIdentifier	String	IdentificationOkz		
		InstallationDate	DateTime	IdentificationInstallationDate		
		AdditionalInformation	String	IdentificationDescription		
Module - 6ES7 193-6AG20-0AA0 - V0.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		OrderNumber	String	Article number		
		ShortDesignation	String	Short designation		
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	PositionNumber		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 193-6AG20-0AA0 - V0.0						
		FirmwareVersion	String	Firmware version		
		PlantDesignation	String	IdentificationAkz		
		LocationIdentifier	String	IdentificationOkz		
		InstallationDate	DateTime	IdentificationInstallationDate		
		AdditionalInformation	String	IdentificationDescription		
Module - 6ES7 193-6AG40-0AA0 - V0.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		OrderNumber	String	Article number		
		ShortDesignation	String	Short designation		
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	PositionNumber		
		FirmwareVersion	String	Firmware version		
		PlantDesignation	String	IdentificationAkz		
		LocationIdentifier	String	IdentificationOkz		
		InstallationDate	DateTime	IdentificationInstallationDate		
		AdditionalInformation	String	IdentificationDescription		
Module - 6ES7 193-6AP20-0AA0 - V0.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		OrderNumber	String	Article number		
		ShortDesignation	String	Short designation		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	PositionNumber		
Module - 6ES7 193-6AP40-0AA0 - V0.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		OrderNumber	String	Article number		
		ShortDesignation	String	Short designation		
		FirmwareVersion	String	Firmware version		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 193-6AP40-0AA0 - V0.0						
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	PositionNumber		
Module - 193-6AF00-0AA0 - V0.0						
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module - 193-6AP00-0AA0 - V0.0						
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 193-6AP00-0AA0 - V0.0						
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module - 193-6AG00-0AA0 - V0.0						
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module - 193-6AR00-0AA0 - V0.0						
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 193-6AR00-0AA0 - V0.0						
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0AA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0AA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0AA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0AA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0AA0 - V1.0					
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Module - 6ES7 131-6BF00-0BA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0BA0 - V1.0						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		FirmwareVersion	String	Firmware version		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0BA0 - V1.0					
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Module - 6ES7 131-6BF00-0BA0 - V1.1					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0BA0 - V1.1						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		EnableValueStatus	Boolean	Value status		
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
Module - 6ES7 131-6BF00-0CA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.0						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		FirmwareVersion	String	Firmware version		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.0					
				1	Active
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsWireBreak	Boolean	Wire break		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	PulseStretching	UInt64	Pulse stretching		
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.0						
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.0						
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					1	Value0Dot5s
					2	Value1s
					3	Value2s

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.0						
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.0						
		PulseStretching	UInt64	Pulse stretching		
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.0					
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	PulseStretching	UInt64	Pulse stretching		
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.0						
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.0						
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
Module - 6ES7 131-6BF00-0CA0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		EnableValueStatus	Boolean	Value status		
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.1						
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsWireBreak	Boolean	Wire break		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.1					
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	PulseStretching	UInt64	Pulse stretching		
				4	Value0Dot05s
				5	Value0Dot1s
				6	Value0Dot2s
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.1						
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.1						
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.1						
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.1					
	PulseStretching	UInt64	Pulse stretching		
				4	Value0Dot05s
				5	Value0Dot1s
				6	Value0Dot2s
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 5					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.1						
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.1					
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	PulseStretching	UInt64	Pulse stretching		
				4	Value0Dot05s
				5	Value0Dot1s
				6	Value0Dot2s
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.1						
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
Module - 6ES7 131-6BF00-0CA0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.2						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		SharedDeviceCopyOfModule	UInt64			
					0	None
					1	Value1AdditionalCopyOfAnInput
					2	Value2AdditionalCopiesOfAnInput
					3	Value3AdditionalCopiesOfAnInput
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		EnableValueStatus	Boolean	Value status		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsWireBreak	Boolean	Wire break		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.2						
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.2					
	PulseStretching	UInt64	Pulse stretching		
				4	Value0Dot05s
				5	Value0Dot1s
				6	Value0Dot2s
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.2						
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.2					
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	PulseStretching	UInt64	Pulse stretching		
				4	Value0Dot05s
				5	Value0Dot1s
				6	Value0Dot2s
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.2						
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.2						
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.2						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.2						
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V1.2						
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
Module - 6ES7 131-6BF00-0CA0 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		ModuleDistribution	UInt64	Module distribution		
					0	None
					12	Value2SubmodulesWith4DigitalInputs
					13	Value4SubmodulesWith2DigitalInputs
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		EnableValueStatus	Boolean	Value status		
		Name	String	Name		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V2.0						
		SharedDeviceCopyOfModule	UInt64			
					0	None
					1	Value1AdditionalCopyOfAnInput
					2	Value2AdditionalCopiesOfAnInput
					3	Value3AdditionalCopiesOfAnInput
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String	Name		
		Comment	String	Comment		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		PositionNumber	Int32	Index		
	Channel 0					
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V2.0					
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsWireBreak	Boolean	Wire break		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	PulseStretching	UInt64	Pulse stretching		
				4	Value0Dot05s
				5	Value0Dot1s
				6	Value0Dot2s
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V2.0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	PulseStretching	UInt64	Pulse stretching		
				4	Value0Dot05s
				5	Value0Dot1s
				6	Value0Dot2s
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V2.0						
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V2.0						
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V2.0					
	PulseStretching	UInt64	Pulse stretching		
				4	Value0Dot05s
				5	Value0Dot1s
				6	Value0Dot2s
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V2.0						
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V2.0					
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	PulseStretching	UInt64	Pulse stretching		
				4	Value0Dot05s
				5	Value0Dot1s
				6	Value0Dot2s
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 6					
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V2.0						
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 7					
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V2.0						
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0CA0 - V2.0						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
Module - 6ES7 131-6BF00-0DA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		EnableValueStatus	Boolean	Value status		
		TypeName	String	InvariantTypeName		
		OperatingMode	UInt64	Mode		
					23	Counting
					24	DiOversampling
		OversamplingInterval	Int64	Scan_Rate		
		OversamplingRate	UInt64	EOM_Sample_Rate		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PositionNumber	Int32	Slot		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0						
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge
		MainCountingDirection	UInt64	Count direction		
					1	Forward
					2	Backward
		FunctionDI	UInt64	Set function of DI		
					6	DigitalInputWithoutFunction
					0	GateStartOrStopLevelTriggered
					7	InvertDirection
		CountingLowLimit	Int64	Low counting limit		
		ComparisonValue1	Int64	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		SetOutputDO	UInt64	Set output DQ		
					0	OffDqEqualTo0

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0						
					7	OffDqEqualTo1
					5	BetweenComparisonValue0And1
					6	NotBetweenComparisonValue0And1
		HardwareInterruptRisingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_IncreasingArray		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_FallingArray		
					0	Deactivated
					1	Active
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
	Channel 1					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge
		MainCountingDirection	UInt64	Count direction		
					1	Forward
					2	Backward
		FunctionDI	UInt64	Set function of DI		
					6	DigitalInputWithoutFunction
					0	GateStartOrStopLevelTriggered
					7	InvertDirection
		CountingLowLimit	Int64	Low counting limit		
		ComparisonValue1	Int64	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		SetOutputDO	UInt64	Set output DQ		
					0	OffDqEqualTo0
					7	OffDqEqualTo1
					5	BetweenComparisonValue0And1
					6	NotBetweenComparisonValue0And1
		HardwareInterruptRisingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_IncreasingArray		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_FallingArray		
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0						
					1	Active
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0						
		MainCountingDirection	UInt64	Count direction		
					1	Forward
					2	Backward
		FunctionDI	UInt64	Set function of DI		
					6	DigitalInputWithoutFunction
					0	GateStartOrStopLevelTriggered
					7	InvertDirection
		CountingLowLimit	Int64	Low counting limit		
		ComparisonValue1	Int64	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		SetOutputDO	UInt64	Set output DQ		
					0	OffDqEqualTo0
					7	OffDqEqualTo1
					5	BetweenComparisonValue0And1
					6	NotBetweenComparisonValue0And1
		HardwareInterruptRisingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_IncreasingArray		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_FallingArray		
					0	Deactivated
					1	Active
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0						
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge
		MainCountingDirection	UInt64	Count direction		
					1	Forward
					2	Backward
		FunctionDI	UInt64	Set function of DI		
					6	DigitalInputWithoutFunction
					0	GateStartOrStopLevelTriggered
					7	InvertDirection
		CountingLowLimit	Int64	Low counting limit		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0						
		ComparisonValue1	Int64	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		SetOutputDO	UInt64	Set output DQ		
					0	OffDqEqualTo0
					7	OffDqEqualTo1
					5	BetweenComparisonValue0And1
					6	NotBetweenComparisonValue0And1
		HardwareInterruptRisingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_IncreasingArray		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_FallingArray		
					0	Deactivated
					1	Active
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0					
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	CountingHighLimit	Int64	High counting limit		
	CountingStartValue	Int64	Start value		
Channel 4					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	HardwareInterruptRisingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_IncreasingArray		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_FallingArray		
				0	Deactivated
				1	Active
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0						
					15	None
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		HardwareInterruptRisingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_IncreasingArray		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_FallingArray		
					0	Deactivated
					1	Active
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0					
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	PulseStretching	UInt64	Pulse stretching		
				4	Value0Dot05s
				5	Value0Dot1s
				6	Value0Dot2s
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	HardwareInterruptRisingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_IncreasingArray		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_FallingArray		
				0	Deactivated
				1	Active
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0					
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	PulseStretching	UInt64	Pulse stretching		
				4	Value0Dot05s
				5	Value0Dot1s
				6	Value0Dot2s
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	HardwareInterruptRisingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_IncreasingArray		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Id_Enable_ProcessAlarm_Centres_FallingArray		
				0	Deactivated
				1	Active
	ChannelActivated	Boolean	Channel activated		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF00-0DA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		PulseStretching	UInt64	Pulse stretching		
					4	Value0Dot05s
					5	Value0Dot1s
					6	Value0Dot2s
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
Module - 6ES7 131-6BF01-0AA0 - V0.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF01-0AA0 - V0.0						
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	Index		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF01-0AA0 - V0.0					
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF01-0AA0 - V0.0					
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF01-0AA0 - V0.0						
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF01-0AA0 - V0.0					
				0	Manual
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Module - 6ES7 131-6BF01-0BA0 - V0.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	EnableValueStatus	Boolean	Value status		
	Name	String	Name		
	Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF01-0BA0 - V0.0					
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	PositionNumber	Int32	Index		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	ReactionToError	UInt64	Input values with module failure		
				2	SubstituteValue0
				1	KeepLastValue
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF01-0BA0 - V0.0						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF01-0BA0 - V0.0						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF01-0BA0 - V0.0						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF01-0BA0 - V0.0					
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Module - 6ES7 131-6BF60-0AA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF60-0AA0 - V1.0						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		FirmwareVersion	String	Firmware version		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF60-0AA0 - V1.0					
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF60-0AA0 - V1.0					
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF60-0AA0 - V1.0					
Channel 5					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF60-0AA0 - V1.0					
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Module - 6ES7 131-6BF61-0AA0 - V0.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF61-0AA0 - V0.0					
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	PositionNumber	Int32	Index		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	ReactionToError	UInt64	Input values with module failure		
				2	SubstituteValue0
				1	KeepLastValue
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF61-0AA0 - V0.0					
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF61-0AA0 - V0.0					
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 5					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF61-0AA0 - V0.0					
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BF61-0AA0 - V0.0						
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
Module - 6ES7 131-6BH00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		FirmwareVersion	String	Firmware version		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.0						
		OrderNumber	String	Article number		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		DiagnosticsWireBreak	Boolean	Wire break		
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.0					
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
Module - 6ES7 131-6BH00-0BA0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		EnableValueStatus	Boolean	Value status		
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.1						
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		DiagnosticsWireBreak	Boolean	Wire break		
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.1					
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
Module - 6ES7 131-6BH01-0BA0 - V0.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		EnableValueStatus	Boolean	Value status		
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH01-0BA0 - V0.0					
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	PositionNumber	Int32	Index		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsWireBreak	Boolean	Wire break		
	ReactionToError	UInt64	Input values with module failure		
				2	SubstituteValue0
				1	KeepLastValue
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH01-0BA0 - V0.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH01-0BA0 - V0.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH01-0BA0 - V0.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH01-0BA0 - V0.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH01-0BA0 - V0.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH01-0BA0 - V0.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH01-0BA0 - V0.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6BH01-0BA0 - V0.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
Module - 6ES7 131-6CF00-0AU0 - V0.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6CF00-0AU0 - V0.0						
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	Index		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6CF00-0AU0 - V0.0					
	ChannelActivated	Boolean	Channel activated		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 5					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Module - 6ES7 131-6FD00-0BB1 - V1.0					
	SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6FD00-0BB1 - V1.0						
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		EnableValueStatus	Boolean	Value status		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
	Channel 1					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6FD00-0BB1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelActivated	Boolean	Channel activated		
Module - 6ES7 131-6FD01-0BB1 - V0.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		EnableValueStatus	Boolean	Value status		
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		TypeName	String	InvariantTypeName		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6FD01-0BB1 - V0.0					
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	PositionNumber	Int32	Index		
	ReactionToError	UInt64	Input values with module failure		
				2	SubstituteValue0
				1	KeepLastValue
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelActivated	Boolean	Channel activated		
Module - 6ES7 131-6TF00-0CA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	EnableValueStatus	Boolean	Value status		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		FirmwareVersion	String	Firmware version		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		DiagnosticsChatterError	Boolean	Chatter error		
		DiagnosticsChangeoverError	Boolean	Changeover error		
		SensorType	UInt64	Sensor type		
					12	NoSensor
					1	NamurSensor
					2	SingleContactUnwired
					3	SingleContactWiredWith10Kilohms
					4	NamurChangeoverContact
					5	ChangeoverUnwired

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					6	ChangeoverWiredWith10Kilohms
		DigitalInputDirection	UInt64	Digital input		
					0	Normal
					1	Inverted
		ChatterMonitoring	UInt64	Chatter monitoring		
					0	Deactivated
					32	Value2SignalChanges
					2	Value3SignalChanges
					3	Value4SignalChanges
					4	Value5SignalChanges
					5	Value6SignalChanges
					6	Value7SignalChanges
					7	Value8SignalChanges
					8	Value9SignalChanges
					9	Value10SignalChanges
					10	Value11SignalChanges
					11	Value12SignalChanges
					12	Value13SignalChanges
					13	Value14SignalChanges
					14	Value15SignalChanges
					15	Value16SignalChanges
					16	Value17SignalChanges
					17	Value18SignalChanges
					18	Value19SignalChanges
					19	Value20SignalChanges
					20	Value21SignalChanges
					21	Value22SignalChanges
					22	Value23SignalChanges
					23	Value24SignalChanges
					24	Value25SignalChanges
					25	Value26SignalChanges
					26	Value27SignalChanges
					27	Value28SignalChanges
					28	Value29SignalChanges

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					29	Value30SignalChanges
					30	Value31SignalChanges
					31	Value32SignalChanges
		MonitoringWindow	UInt64	Monitoring window		
					0	Value0Dot5
					1	Value1
					2	Value2
					3	Value3
					4	Value4
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					30	Value30
					31	Value31
					32	Value32
					33	Value33
					34	Value34
					35	Value35
					36	Value36
					37	Value37
					38	Value38
					39	Value39
					40	Value40
					41	Value41
					42	Value42
					43	Value43
					44	Value44
					45	Value45
					46	Value46
					47	Value47
					48	Value48
					49	Value49
					50	Value50
					51	Value51
					52	Value52
					53	Value53
					54	Value54
					55	Value55
					56	Value56
					57	Value57
					58	Value58
					59	Value59
					60	Value60
					61	Value61
					62	Value62
					63	Value63

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					64	Value64
					65	Value65
					66	Value66
					67	Value67
					68	Value68
					69	Value69
					70	Value70
					71	Value71
					72	Value72
					73	Value73
					74	Value74
					75	Value75
					76	Value76
					77	Value77
					78	Value78
					79	Value79
					80	Value80
					81	Value81
					82	Value82
					83	Value83
					84	Value84
					85	Value85
					86	Value86
					87	Value87
					88	Value88
					89	Value89
					90	Value90
					91	Value91
					92	Value92
					93	Value93
					94	Value94
					95	Value95
					96	Value96
					97	Value97

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0					
				98	Value98
				99	Value99
				100	Value100
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsWireBreak	Boolean	Wire break		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	PulseStretching	UInt64	Pulse stretching		
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	DiagnosticsChatterError	Boolean	Chatter error		
	DiagnosticsChangeoverError	Boolean	Changeover error		
	SensorType	UInt64	Sensor type		
				12	NoSensor
				1	NamurSensor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					2	SingleContactUnwired
					3	SingleContactWiredWith10Kilohms
					4	NamurChangeoverContact
					5	ChangeoverUnwired
					6	ChangeoverWiredWith10Kilohms
		DigitalInputDirection	UInt64	Digital input		
					0	Normal
					1	Inverted
		ChatterMonitoring	UInt64	Chatter monitoring		
					0	Deactivated
					32	Value2SignalChanges
					2	Value3SignalChanges
					3	Value4SignalChanges
					4	Value5SignalChanges
					5	Value6SignalChanges
					6	Value7SignalChanges
					7	Value8SignalChanges
					8	Value9SignalChanges
					9	Value10SignalChanges
					10	Value11SignalChanges
					11	Value12SignalChanges
					12	Value13SignalChanges
					13	Value14SignalChanges
					14	Value15SignalChanges
					15	Value16SignalChanges
					16	Value17SignalChanges
					17	Value18SignalChanges
					18	Value19SignalChanges
					19	Value20SignalChanges
					20	Value21SignalChanges
					21	Value22SignalChanges
					22	Value23SignalChanges
					23	Value24SignalChanges
					24	Value25SignalChanges

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					25	Value26SignalChanges
					26	Value27SignalChanges
					27	Value28SignalChanges
					28	Value29SignalChanges
					29	Value30SignalChanges
					30	Value31SignalChanges
					31	Value32SignalChanges
		MonitoringWindow	UInt64	Monitoring window		
					0	Value0Dot5
					1	Value1
					2	Value2
					3	Value3
					4	Value4
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					32	Value32
					33	Value33
					34	Value34
					35	Value35
					36	Value36
					37	Value37
					38	Value38
					39	Value39
					40	Value40
					41	Value41
					42	Value42
					43	Value43
					44	Value44
					45	Value45
					46	Value46
					47	Value47
					48	Value48
					49	Value49
					50	Value50
					51	Value51
					52	Value52
					53	Value53
					54	Value54
					55	Value55
					56	Value56
					57	Value57
					58	Value58
					59	Value59

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					60	Value60
					61	Value61
					62	Value62
					63	Value63
					64	Value64
					65	Value65
					66	Value66
					67	Value67
					68	Value68
					69	Value69
					70	Value70
					71	Value71
					72	Value72
					73	Value73
					74	Value74
					75	Value75
					76	Value76
					77	Value77
					78	Value78
					79	Value79
					80	Value80
					81	Value81
					82	Value82
					83	Value83
					84	Value84
					85	Value85
					86	Value86
					87	Value87
					88	Value88
					89	Value89
					90	Value90
					91	Value91
					92	Value92
					93	Value93

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0					
				94	Value94
				95	Value95
				96	Value96
				97	Value97
				98	Value98
				99	Value99
				100	Value100
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	PulseStretching	UInt64	Pulse stretching		
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	DiagnosticsChatterError	Boolean	Chatter error		
	DiagnosticsChangeoverError	Boolean	Changeover error		
	SensorType	UInt64	Sensor type		
				12	NoSensor

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0					
				1	NamurSensor
				2	SingleContactUnwired
				3	SingleContactWiredWith10Kilohms
				4	NamurChangeoverContact
				5	ChangeoverUnwired
				6	ChangeoverWiredWith10Kilohms
	DigitalInputDirection	UInt64	Digital input		
				0	Normal
				1	Inverted
	ChatterMonitoring	UInt64	Chatter monitoring		
				0	Deactivated
				32	Value2SignalChanges
				2	Value3SignalChanges
				3	Value4SignalChanges
				4	Value5SignalChanges
				5	Value6SignalChanges
				6	Value7SignalChanges
				7	Value8SignalChanges
				8	Value9SignalChanges
				9	Value10SignalChanges
				10	Value11SignalChanges
				11	Value12SignalChanges
				12	Value13SignalChanges
				13	Value14SignalChanges
				14	Value15SignalChanges
				15	Value16SignalChanges
				16	Value17SignalChanges
				17	Value18SignalChanges
				18	Value19SignalChanges
				19	Value20SignalChanges
				20	Value21SignalChanges
				21	Value22SignalChanges
				22	Value23SignalChanges
				23	Value24SignalChanges

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					24	Value25SignalChanges
					25	Value26SignalChanges
					26	Value27SignalChanges
					27	Value28SignalChanges
					28	Value29SignalChanges
					29	Value30SignalChanges
					30	Value31SignalChanges
					31	Value32SignalChanges
		MonitoringWindow	UInt64	Monitoring window		
					0	Value0Dot5
					1	Value1
					2	Value2
					3	Value3
					4	Value4
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					32	Value32
					33	Value33
					34	Value34
					35	Value35
					36	Value36
					37	Value37
					38	Value38
					39	Value39
					40	Value40
					41	Value41
					42	Value42
					43	Value43
					44	Value44
					45	Value45
					46	Value46
					47	Value47
					48	Value48
					49	Value49
					50	Value50
					51	Value51
					52	Value52
					53	Value53
					54	Value54
					55	Value55
					56	Value56
					57	Value57
					58	Value58

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					59	Value59
					60	Value60
					61	Value61
					62	Value62
					63	Value63
					64	Value64
					65	Value65
					66	Value66
					67	Value67
					68	Value68
					69	Value69
					70	Value70
					71	Value71
					72	Value72
					73	Value73
					74	Value74
					75	Value75
					76	Value76
					77	Value77
					78	Value78
					79	Value79
					80	Value80
					81	Value81
					82	Value82
					83	Value83
					84	Value84
					85	Value85
					86	Value86
					87	Value87
					88	Value88
					89	Value89
					90	Value90
					91	Value91
					92	Value92

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0					
				93	Value93
				94	Value94
				95	Value95
				96	Value96
				97	Value97
				98	Value98
				99	Value99
				100	Value100
	HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
				0	Deactivated
				1	Active
	HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
	HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
	HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
	HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
	HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
	HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	PulseStretching	UInt64	Pulse stretching		
				1	Value0Dot5s
				2	Value1s
				3	Value2s
				0	None
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
		DiagnosticsChatterError	Boolean	Chatter error		
		DiagnosticsChangeoverError	Boolean	Changeover error		
		SensorType	UInt64	Sensor type		
					12	NoSensor
					1	NamurSensor
					2	SingleContactUnwired
					3	SingleContactWiredWith10Kilohms
					4	NamurChangeoverContact
					5	ChangeoverUnwired
					6	ChangeoverWiredWith10Kilohms
		DigitalInputDirection	UInt64	Digital input		
					0	Normal
					1	Inverted
		ChatterMonitoring	UInt64	Chatter monitoring		
					0	Deactivated
					32	Value2SignalChanges
					2	Value3SignalChanges
					3	Value4SignalChanges
					4	Value5SignalChanges
					5	Value6SignalChanges
					6	Value7SignalChanges
					7	Value8SignalChanges
					8	Value9SignalChanges
					9	Value10SignalChanges
					10	Value11SignalChanges
					11	Value12SignalChanges
					12	Value13SignalChanges
					13	Value14SignalChanges
					14	Value15SignalChanges
					15	Value16SignalChanges
					16	Value17SignalChanges
					17	Value18SignalChanges
					18	Value19SignalChanges
					19	Value20SignalChanges

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					20	Value21SignalChanges
					21	Value22SignalChanges
					22	Value23SignalChanges
					23	Value24SignalChanges
					24	Value25SignalChanges
					25	Value26SignalChanges
					26	Value27SignalChanges
					27	Value28SignalChanges
					28	Value29SignalChanges
					29	Value30SignalChanges
					30	Value31SignalChanges
					31	Value32SignalChanges
		MonitoringWindow	UInt64	Monitoring window		
					0	Value0Dot5
					1	Value1
					2	Value2
					3	Value3
					4	Value4
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					32	Value32
					33	Value33
					34	Value34
					35	Value35
					36	Value36
					37	Value37
					38	Value38
					39	Value39
					40	Value40
					41	Value41
					42	Value42
					43	Value43
					44	Value44
					45	Value45
					46	Value46
					47	Value47
					48	Value48
					49	Value49
					50	Value50
					51	Value51
					52	Value52
					53	Value53
					54	Value54

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					55	Value55
					56	Value56
					57	Value57
					58	Value58
					59	Value59
					60	Value60
					61	Value61
					62	Value62
					63	Value63
					64	Value64
					65	Value65
					66	Value66
					67	Value67
					68	Value68
					69	Value69
					70	Value70
					71	Value71
					72	Value72
					73	Value73
					74	Value74
					75	Value75
					76	Value76
					77	Value77
					78	Value78
					79	Value79
					80	Value80
					81	Value81
					82	Value82
					83	Value83
					84	Value84
					85	Value85
					86	Value86
					87	Value87
					88	Value88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					89	Value89
					90	Value90
					91	Value91
					92	Value92
					93	Value93
					94	Value94
					95	Value95
					96	Value96
					97	Value97
					98	Value98
					99	Value99
					100	Value100
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		DiagnosticsChatterError	Boolean	Chatter error		
		DiagnosticsChangeoverError	Boolean	Changeover error		
		SensorType	UInt64	Sensor type		
					12	NoSensor
					1	NamurSensor
					2	SingleContactUnwired
					3	SingleContactWiredWith10Kilohms
					4	NamurChangeoverContact
					5	ChangeoverUnwired
					6	ChangeoverWiredWith10Kilohms
		DigitalInputDirection	UInt64	Digital input		
					0	Normal
					1	Inverted
		ChatterMonitoring	UInt64	Chatter monitoring		
					0	Deactivated
					32	Value2SignalChanges
					2	Value3SignalChanges
					3	Value4SignalChanges
					4	Value5SignalChanges
					5	Value6SignalChanges
					6	Value7SignalChanges
					7	Value8SignalChanges
					8	Value9SignalChanges
					9	Value10SignalChanges
					10	Value11SignalChanges
					11	Value12SignalChanges
					12	Value13SignalChanges
					13	Value14SignalChanges
					14	Value15SignalChanges
					15	Value16SignalChanges
					16	Value17SignalChanges
					17	Value18SignalChanges
					18	Value19SignalChanges

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					19	Value20SignalChanges
					20	Value21SignalChanges
					21	Value22SignalChanges
					22	Value23SignalChanges
					23	Value24SignalChanges
					24	Value25SignalChanges
					25	Value26SignalChanges
					26	Value27SignalChanges
					27	Value28SignalChanges
					28	Value29SignalChanges
					29	Value30SignalChanges
					30	Value31SignalChanges
					31	Value32SignalChanges
		MonitoringWindow	UInt64	Monitoring window		
					0	Value0Dot5
					1	Value1
					2	Value2
					3	Value3
					4	Value4
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					32	Value32
					33	Value33
					34	Value34
					35	Value35
					36	Value36
					37	Value37
					38	Value38
					39	Value39
					40	Value40
					41	Value41
					42	Value42
					43	Value43
					44	Value44
					45	Value45
					46	Value46
					47	Value47
					48	Value48
					49	Value49
					50	Value50
					51	Value51
					52	Value52
					53	Value53

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					54	Value54
					55	Value55
					56	Value56
					57	Value57
					58	Value58
					59	Value59
					60	Value60
					61	Value61
					62	Value62
					63	Value63
					64	Value64
					65	Value65
					66	Value66
					67	Value67
					68	Value68
					69	Value69
					70	Value70
					71	Value71
					72	Value72
					73	Value73
					74	Value74
					75	Value75
					76	Value76
					77	Value77
					78	Value78
					79	Value79
					80	Value80
					81	Value81
					82	Value82
					83	Value83
					84	Value84
					85	Value85
					86	Value86
					87	Value87

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					88	Value88
					89	Value89
					90	Value90
					91	Value91
					92	Value92
					93	Value93
					94	Value94
					95	Value95
					96	Value96
					97	Value97
					98	Value98
					99	Value99
					100	Value100
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		DiagnosticsChatterError	Boolean	Chatter error		
		DiagnosticsChangeoverError	Boolean	Changeover error		
		SensorType	UInt64	Sensor type		
					12	NoSensor
					1	NamurSensor
					2	SingleContactUnwired
					3	SingleContactWiredWith10Kilohms
					4	NamurChangeoverContact
					5	ChangeoverUnwired
					6	ChangeoverWiredWith10Kilohms
		DigitalInputDirection	UInt64	Digital input		
					0	Normal
					1	Inverted
		ChatterMonitoring	UInt64	Chatter monitoring		
					0	Deactivated
					32	Value2SignalChanges
					2	Value3SignalChanges
					3	Value4SignalChanges
					4	Value5SignalChanges
					5	Value6SignalChanges
					6	Value7SignalChanges
					7	Value8SignalChanges
					8	Value9SignalChanges
					9	Value10SignalChanges
					10	Value11SignalChanges
					11	Value12SignalChanges
					12	Value13SignalChanges
					13	Value14SignalChanges

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					14	Value15SignalChanges
					15	Value16SignalChanges
					16	Value17SignalChanges
					17	Value18SignalChanges
					18	Value19SignalChanges
					19	Value20SignalChanges
					20	Value21SignalChanges
					21	Value22SignalChanges
					22	Value23SignalChanges
					23	Value24SignalChanges
					24	Value25SignalChanges
					25	Value26SignalChanges
					26	Value27SignalChanges
					27	Value28SignalChanges
					28	Value29SignalChanges
					29	Value30SignalChanges
					30	Value31SignalChanges
					31	Value32SignalChanges
		MonitoringWindow	UInt64	Monitoring window		
					0	Value0Dot5
					1	Value1
					2	Value2
					3	Value3
					4	Value4
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					32	Value32
					33	Value33
					34	Value34
					35	Value35
					36	Value36
					37	Value37
					38	Value38
					39	Value39
					40	Value40
					41	Value41
					42	Value42
					43	Value43
					44	Value44
					45	Value45
					46	Value46
					47	Value47
					48	Value48

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					49	Value49
					50	Value50
					51	Value51
					52	Value52
					53	Value53
					54	Value54
					55	Value55
					56	Value56
					57	Value57
					58	Value58
					59	Value59
					60	Value60
					61	Value61
					62	Value62
					63	Value63
					64	Value64
					65	Value65
					66	Value66
					67	Value67
					68	Value68
					69	Value69
					70	Value70
					71	Value71
					72	Value72
					73	Value73
					74	Value74
					75	Value75
					76	Value76
					77	Value77
					78	Value78
					79	Value79
					80	Value80
					81	Value81
					82	Value82

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					83	Value83
					84	Value84
					85	Value85
					86	Value86
					87	Value87
					88	Value88
					89	Value89
					90	Value90
					91	Value91
					92	Value92
					93	Value93
					94	Value94
					95	Value95
					96	Value96
					97	Value97
					98	Value98
					99	Value99
					100	Value100
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
		PulseStretching	UInt64	Pulse stretching		
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		DiagnosticsChatterError	Boolean	Chatter error		
		DiagnosticsChangeoverError	Boolean	Changeover error		
		SensorType	UInt64	Sensor type		
					12	NoSensor
					1	NamurSensor
					2	SingleContactUnwired
					3	SingleContactWiredWith10Kilohms
					4	NamurChangeoverContact
					5	ChangeoverUnwired
					6	ChangeoverWiredWith10Kilohms
		DigitalInputDirection	UInt64	Digital input		
					0	Normal
					1	Inverted
		ChatterMonitoring	UInt64	Chatter monitoring		
					0	Deactivated
					32	Value2SignalChanges
					2	Value3SignalChanges
					3	Value4SignalChanges
					4	Value5SignalChanges
					5	Value6SignalChanges
					6	Value7SignalChanges
					7	Value8SignalChanges
					8	Value9SignalChanges
					9	Value10SignalChanges
					10	Value11SignalChanges
					11	Value12SignalChanges

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					12	Value13SignalChanges
					13	Value14SignalChanges
					14	Value15SignalChanges
					15	Value16SignalChanges
					16	Value17SignalChanges
					17	Value18SignalChanges
					18	Value19SignalChanges
					19	Value20SignalChanges
					20	Value21SignalChanges
					21	Value22SignalChanges
					22	Value23SignalChanges
					23	Value24SignalChanges
					24	Value25SignalChanges
					25	Value26SignalChanges
					26	Value27SignalChanges
					27	Value28SignalChanges
					28	Value29SignalChanges
					29	Value30SignalChanges
					30	Value31SignalChanges
					31	Value32SignalChanges
		MonitoringWindow	UInt64	Monitoring window		
					0	Value0Dot5
					1	Value1
					2	Value2
					3	Value3
					4	Value4
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					32	Value32
					33	Value33
					34	Value34
					35	Value35
					36	Value36
					37	Value37
					38	Value38
					39	Value39
					40	Value40
					41	Value41
					42	Value42
					43	Value43
					44	Value44
					45	Value45
					46	Value46

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					47	Value47
					48	Value48
					49	Value49
					50	Value50
					51	Value51
					52	Value52
					53	Value53
					54	Value54
					55	Value55
					56	Value56
					57	Value57
					58	Value58
					59	Value59
					60	Value60
					61	Value61
					62	Value62
					63	Value63
					64	Value64
					65	Value65
					66	Value66
					67	Value67
					68	Value68
					69	Value69
					70	Value70
					71	Value71
					72	Value72
					73	Value73
					74	Value74
					75	Value75
					76	Value76
					77	Value77
					78	Value78
					79	Value79
					80	Value80

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					81	Value81
					82	Value82
					83	Value83
					84	Value84
					85	Value85
					86	Value86
					87	Value87
					88	Value88
					89	Value89
					90	Value90
					91	Value91
					92	Value92
					93	Value93
					94	Value94
					95	Value95
					96	Value96
					97	Value97
					98	Value98
					99	Value99
					100	Value100
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		DiagnosticsChatterError	Boolean	Chatter error		
		DiagnosticsChangeoverError	Boolean	Changeover error		
		SensorType	UInt64	Sensor type		
					12	NoSensor
					1	NamurSensor
					2	SingleContactUnwired
					3	SingleContactWiredWith10Kilohms
					4	NamurChangeoverContact
					5	ChangeoverUnwired
					6	ChangeoverWiredWith10Kilohms
		DigitalInputDirection	UInt64	Digital input		
					0	Normal
					1	Inverted
		ChatterMonitoring	UInt64	Chatter monitoring		
					0	Deactivated
					32	Value2SignalChanges
					2	Value3SignalChanges
					3	Value4SignalChanges
					4	Value5SignalChanges
					5	Value6SignalChanges
					6	Value7SignalChanges
					7	Value8SignalChanges

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					8	Value9SignalChanges
					9	Value10SignalChanges
					10	Value11SignalChanges
					11	Value12SignalChanges
					12	Value13SignalChanges
					13	Value14SignalChanges
					14	Value15SignalChanges
					15	Value16SignalChanges
					16	Value17SignalChanges
					17	Value18SignalChanges
					18	Value19SignalChanges
					19	Value20SignalChanges
					20	Value21SignalChanges
					21	Value22SignalChanges
					22	Value23SignalChanges
					23	Value24SignalChanges
					24	Value25SignalChanges
					25	Value26SignalChanges
					26	Value27SignalChanges
					27	Value28SignalChanges
					28	Value29SignalChanges
					29	Value30SignalChanges
					30	Value31SignalChanges
					31	Value32SignalChanges
		MonitoringWindow	UInt64	Monitoring window		
					0	Value0Dot5
					1	Value1
					2	Value2
					3	Value3
					4	Value4
					5	Value5
					6	Value6
					7	Value7
					8	Value8

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					32	Value32
					33	Value33
					34	Value34
					35	Value35
					36	Value36
					37	Value37
					38	Value38
					39	Value39
					40	Value40
					41	Value41
					42	Value42

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					43	Value43
					44	Value44
					45	Value45
					46	Value46
					47	Value47
					48	Value48
					49	Value49
					50	Value50
					51	Value51
					52	Value52
					53	Value53
					54	Value54
					55	Value55
					56	Value56
					57	Value57
					58	Value58
					59	Value59
					60	Value60
					61	Value61
					62	Value62
					63	Value63
					64	Value64
					65	Value65
					66	Value66
					67	Value67
					68	Value68
					69	Value69
					70	Value70
					71	Value71
					72	Value72
					73	Value73
					74	Value74
					75	Value75
					76	Value76

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
					77	Value77
					78	Value78
					79	Value79
					80	Value80
					81	Value81
					82	Value82
					83	Value83
					84	Value84
					85	Value85
					86	Value86
					87	Value87
					88	Value88
					89	Value89
					90	Value90
					91	Value91
					92	Value92
					93	Value93
					94	Value94
					95	Value95
					96	Value96
					97	Value97
					98	Value98
					99	Value99
					100	Value100
		HardwareInterruptRisingEdgeActive	Boolean	Hardware interrupt on rising edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeActive	Boolean	Hardware interrupt on falling edge		
					0	Deactivated
					1	Active
		HardwareInterruptFallingEdgeEventName	String	*HardwareInterruptFallingEdgeEventName		
		HardwareInterruptFallingEdgeInterrupt	Object	*HardwareInterruptFallingEdgeInterrupt		
		HardwareInterruptFallingEdgePriority	UInt64	*HardwareInterruptFallingEdgePriority		
		HardwareInterruptRisingEdgeEventName	String	*HardwareInterruptRisingEdgeEventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 131-6TF00-0CA0 - V1.0						
		HardwareInterruptRisingEdgeInterrupt	Object	*HardwareInterruptRisingEdgeInterrupt		
		HardwareInterruptRisingEdgePriority	UInt64	*HardwareInterruptRisingEdgePriority		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		PulseStretching	UInt64	Pulse stretching		
					1	Value0Dot5s
					2	Value1s
					3	Value2s
					0	None

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0BA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0BA0 - V1.0						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
Module - 6ES7 132-6BD20-0BA0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0BA0 - V1.1					
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	EnableValueStatus	Boolean	Value status		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0BA0 - V1.1					
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Module - 6ES7 132-6BD20-0CA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0CA0 - V1.0						
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		SharedDeviceCopyOfModule	UInt64			
					0	None
					1	Value1AdditionalCopyOfAnInput
					2	Value2AdditionalCopiesOfAnInput
					3	Value3AdditionalCopiesOfAnInput
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		EnableValueStatus	Boolean	Value status		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0CA0 - V1.0					
				1	KeepLastValue
				11	SubstituteValue1
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0CA0 - V1.0						
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
Module - 6ES7 132-6BD20-0CA0 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		ModuleDistribution	UInt64	Module distribution		
					0	None
					11	Value2SubmodulesWith2DigitalOutputs
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		EnableValueStatus	Boolean	Value status		
		Name	String	Name		
		Comment	String	Comment		
		SharedDeviceCopyOfModule	UInt64			
					0	None
					1	Value1AdditionalCopyOfAnInput
					2	Value2AdditionalCopiesOfAnInput
					3	Value3AdditionalCopiesOfAnInput
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0CA0 - V2.0					
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	Index		
Channel 0					
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	ChannelActivated	Boolean	Channel activated		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
Channel 1					
	ChannelActivated	Boolean	Channel activated		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
Channel 2					
	ChannelActivated	Boolean	Channel activated		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0CA0 - V2.0					
	DiagnosticsWireBreak	Boolean	Wire break		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
Channel 3					
	ChannelActivated	Boolean	Channel activated		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
Module - 6ES7 132-6BD20-0DA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	OperatingMode	UInt64	Mode		
				56	DoOversampling
				7	PulseWidthModulation
	OversamplingInterval	Int64	Scan_Rate		
	OversamplingRate	UInt64	EOM_Sample_Rate		
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0DA0 - V1.0						
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		EnableValueStatus	Boolean	Value status		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsOverflow	Boolean	Overflow		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
					2	SubstituteAValue
		ChannelActivated	Boolean	Channel enabled		
		PulseWidthModulationTimePeriod	UInt64	Pulse width modulation time period		
					0	Off
					4	Value0Dot20ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0DA0 - V1.0						
					7	Value0Dot40ms
					12	Value0Dot93ms
					14	Value1Dot33ms
					21	Value4Dot27ms
					26	Value10Dot67ms
					30	Value21Dot33ms
					33	Value34Dot13ms
					36	Value59Dot73ms
		HoldingTimeValveControl	Double	Holding time valve control		
		PulseWidthModulationDutyCycle	Double			
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
					2	SubstituteAValue
		ChannelActivated	Boolean	Channel enabled		
		PulseWidthModulationTimePeriod	UInt64	Pulse width modulation time period		
					0	Off
					4	Value0Dot20ms
					7	Value0Dot40ms
					12	Value0Dot93ms
					14	Value1Dot33ms
					21	Value4Dot27ms
					26	Value10Dot67ms
					30	Value21Dot33ms
					33	Value34Dot13ms
					36	Value59Dot73ms
		HoldingTimeValveControl	Double	Holding time valve control		
		PulseWidthModulationDutyCycle	Double			
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0DA0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
					2	SubstituteAValue
		ChannelActivated	Boolean	Channel enabled		
		PulseWidthModulationTimePeriod	UInt64	Pulse width modulation time period		
					0	Off
					4	Value0Dot20ms
					7	Value0Dot40ms
					12	Value0Dot93ms
					14	Value1Dot33ms
					21	Value4Dot27ms
					26	Value10Dot67ms
					30	Value21Dot33ms
					33	Value34Dot13ms
					36	Value59Dot73ms
		HoldingTimeValveControl	Double	Holding time valve control		
		PulseWidthModulationDutyCycle	Double			
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
					2	SubstituteAValue
		ChannelActivated	Boolean	Channel enabled		
		PulseWidthModulationTimePeriod	UInt64	Pulse width modulation time period		
					0	Off
					4	Value0Dot20ms
					7	Value0Dot40ms
					12	Value0Dot93ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0DA0 - V1.0						
					14	Value1Dot33ms
					21	Value4Dot27ms
					26	Value10Dot67ms
					30	Value21Dot33ms
					33	Value34Dot13ms
					36	Value59Dot73ms
		HoldingTimeValveControl	Double	Holding time valve control		
		PulseWidthModulationDutyCycle	Double			
Module - 6ES7 132-6BD20-0DA0 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		OperatingMode	UInt64	Mode		
					56	DoOversampling
					7	PulseWidthModulation
					75	ModularCamControl
		OversamplingInterval	Int64	Scan_Rate		
		OversamplingRate	UInt64	EOM_Sample_Rate		
		TypeName	String	InvariantTypeName		
		EncoderSlotNumber	Int64	Encoder module PositionNumber		
		EncoderChannelNumber	UInt64	Publisher_Channel		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0DA0 - V2.0						
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		EnableValueStatus	Boolean	QualityInformation		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsEncoderSourceActive	Boolean	Encoder source diagnostics		
		ModuloActive	Boolean	Modulo		
		Hysteresis	UInt64	Hysteresis		
		ReferencePosition	Int64	Axis reference position		
		MaximumEncoderValue	Int64	Maximum encoder value		
		MinimumEncoderValue	Int64	Minimum encoder value		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsOverflow	Boolean	Overflow		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
					2	SubstituteAValue
		ChannelActivated	Boolean	Channel enabled		
		PulseWidthModulationTimePeriod	UInt64			
					0	Off
					4	Value0Dot20ms
					7	Value0Dot40ms
					12	Value0Dot93ms
					14	Value1Dot33ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0DA0 - V2.0						
					21	Value4Dot27ms
					26	Value10Dot67ms
					30	Value21Dot33ms
					33	Value34Dot13ms
					36	Value59Dot73ms
		HoldingTimeValveControl	Double	Holding time valve control		
		PulseWidthModulationDutyCycle	Double			
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
					2	SubstituteAValue
		ChannelActivated	Boolean	Channel enabled		
		PulseWidthModulationTimePeriod	UInt64			
					0	Off
					4	Value0Dot20ms
					7	Value0Dot40ms
					12	Value0Dot93ms
					14	Value1Dot33ms
					21	Value4Dot27ms
					26	Value10Dot67ms
					30	Value21Dot33ms
					33	Value34Dot13ms
					36	Value59Dot73ms
		HoldingTimeValveControl	Double	Holding time valve control		
		PulseWidthModulationDutyCycle	Double			
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0DA0 - V2.0						
					1	KeepLastValue
					11	SubstituteValue1
					2	SubstituteAValue
		ChannelActivated	Boolean	Channel enabled		
		PulseWidthModulationTimePeriod	UInt64			
					0	Off
					4	Value0Dot20ms
					7	Value0Dot40ms
					12	Value0Dot93ms
					14	Value1Dot33ms
					21	Value4Dot27ms
					26	Value10Dot67ms
					30	Value21Dot33ms
					33	Value34Dot13ms
					36	Value59Dot73ms
		HoldingTimeValveControl	Double	Holding time valve control		
		PulseWidthModulationDutyCycle	Double			
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
					2	SubstituteAValue
		ChannelActivated	Boolean	Channel enabled		
		PulseWidthModulationTimePeriod	UInt64			
					0	Off
					4	Value0Dot20ms
					7	Value0Dot40ms
					12	Value0Dot93ms
					14	Value1Dot33ms
					21	Value4Dot27ms
					26	Value10Dot67ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BD20-0DA0 - V2.0						
					30	Value21Dot33ms
					33	Value34Dot13ms
					36	Value59Dot73ms
		HoldingTimeValveControl	Double	Holding time valve control		
		PulseWidthModulationDutyCycle	Double			
		StartPosition	Int64	Start position		
		EndPosition	Int64	End position		
		ChannelAssignment	UInt64	Channel assignment		
					0	Channel0
					1	Channel1
					2	Channel2
					3	Channel3
		EffectiveDirection	UInt64	Effective direction		
					0	None
					1	Positive
					2	Negative
					3	Both
Module - 6ES7 132-6BF00-0AA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0AA0 - V1.0						
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0AA0 - V1.0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 5					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0AA0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
Module - 6ES7 132-6BF00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0BA0 - V1.0						
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0BA0 - V1.0					
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0BA0 - V1.0						
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0BA0 - V1.0						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
Module - 6ES7 132-6BF00-0BA0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0BA0 - V1.1						
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		EnableValueStatus	Boolean	Value status		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0BA0 - V1.1						
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0BA0 - V1.1					
Channel 5					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 6					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Module - 6ES7 132-6BF00-0CA0 - V1.0					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
	ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.0						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.0					
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
Channel 5					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.0					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
Channel 6					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.0						
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
Module - 6ES7 132-6BF00-0CA0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		EnableValueStatus	Boolean	Value status		
	Submodule					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.1					
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.1					
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
Channel 5					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
Channel 6					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.1					
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
Module - 6ES7 132-6BF00-0CA0 - V1.2					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.2					
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	SharedDeviceCopyOfModule	UInt64			
				0	None
				1	Value1AdditionalCopyOfAnInput
				2	Value2AdditionalCopiesOfAnInput
				3	Value3AdditionalCopiesOfAnInput
	Name	String	Name		
	Comment	String	Comment		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	EnableValueStatus	Boolean	Value status		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	DiagnosticsWireBreak	Boolean	Wire break		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.2						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.2						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.2						
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V1.2						
					1	KeepLastValue
					11	SubstituteValue1
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		DiagnosticsWireBreak	Boolean	Wire break		
Module - 6ES7 132-6BF00-0CA0 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		ModuleDistribution	UInt64	Module distribution		
					0	None
					14	Value2SubmodulesWith4DigitalOutputs
					15	Value4SubmodulesWith2DigitalOutputs
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		EnableValueStatus	Boolean	Value status		
		Name	String	Name		
		Comment	String	Comment		
		SharedDeviceCopyOfModule	UInt64			
					0	None
					1	Value1AdditionalCopyOfAnInput
					2	Value2AdditionalCopiesOfAnInput
					3	Value3AdditionalCopiesOfAnInput
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V2.0						
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		ChannelActivated	Boolean	Channel activated		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelActivated	Boolean	Channel activated		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V2.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelActivated	Boolean	Channel activated		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelActivated	Boolean	Channel activated		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V2.0					
				0	Manual
Channel 4					
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 5					
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 6					
	ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF00-0CA0 - V2.0					
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 7					
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Module - 6ES7 132-6BF01-0AA0 - V0.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF01-0AA0 - V0.0					
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF01-0AA0 - V0.0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF01-0AA0 - V0.0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 5					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 6					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF01-0AA0 - V0.0					
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Module - 6ES7 132-6BF01-0BA0 - V0.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	EnableValueStatus	Boolean	Value status		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF01-0BA0 - V0.0						
		DiagnosticsWireBreak	Boolean	Wire break		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF01-0BA0 - V0.0					
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 5					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF01-0BA0 - V0.0					
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 6					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Module - 6ES7 132-6BF60-0AA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF60-0AA0 - V1.0					
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF60-0AA0 - V1.0						
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF60-0AA0 - V1.0						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF60-0AA0 - V1.0						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
Module - 6ES7 132-6BF61-0AA0 - V0.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		PositionNumber	Int32	Index		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF61-0AA0 - V0.0					
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF61-0AA0 - V0.0						
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BF61-0AA0 - V0.0					
Channel 6					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Module - 6ES7 132-6BH00-0AA0 - V0.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0AA0 - V0.0						
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0AA0 - V0.0					
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0AA0 - V0.0						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0AA0 - V0.0						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0AA0 - V0.0					
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0AA0 - V0.0					
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Module - 6ES7 132-6BH00-0BA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.0					
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.0					
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.0					
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.0					
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Module - 6ES7 132-6BH00-0BA0 - V1.1					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.1						
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		ChannelActivated	Boolean	Channel activated		
		EnableValueStatus	Boolean	Value status		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsWireBreak	Boolean	Wire break		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.1						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.1						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.1					
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.1						
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.1					
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH00-0BA0 - V1.1					
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Module - 6ES7 132-6BH01-0BA0 - V0.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	ChannelActivated	Boolean	Channel activated		
	EnableValueStatus	Boolean	Value status		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsWireBreak	Boolean	Wire break		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToLplus	Boolean	Short circuit to L+		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH01-0BA0 - V0.0					
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH01-0BA0 - V0.0					
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 5					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH01-0BA0 - V0.0					
				1	KeepLastValue
				11	SubstituteValue1
Channel 6					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH01-0BA0 - V0.0						
					11	SubstituteValue1
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH01-0BA0 - V0.0					
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	ChannelActivated	Boolean	Channel activated		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
Channel 15					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6BH01-0BA0 - V0.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
Module - 6ES7 132-6FD00-0BB1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		EnableValueStatus	Boolean	Value status		
	Submodule					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6FD00-0BB1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6FD00-0BB1 - V1.0					
				1	KeepLastValue
				11	SubstituteValue1
Module - 6ES7 132-6FD00-0CU0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	DiagnosticsWireBreak	Boolean	Wire break		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6FD00-0CU0 - V1.0						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
					2	SubstituteAValue
		ChannelActivated	Boolean	Channel enabled		
		DiagnosticsNoSupplyVoltage	Boolean	Diagnostics: No load voltage L		
		DiagnosticsOvertemperature	Boolean	Overtemperature		
		DiagnosticsOverflow	Boolean	Overflow		
		SubstituteValueAnalog	Double	Substitute value		
		TemperatureShutdown	UInt64	Temperature shutdown		
					0	OutputActiveEvenUnderOvertemperatureConditions
					1	OutputDisabledUnderOvertemperatureConditions
		StartupDelay	UInt64	Startup delay		
					0	NoDelay
					1	Value100ms
					2	Value1s
					3	Value2s
					4	Value3s
					5	Value4s
					6	Value5s
					7	Value10s
		OutputFilterUp	UInt64	Output filter up		
					0	NoFilter
					1	Value500ms
					2	Value1s
					3	Value5s
					4	Value10s
					5	Value30s
					6	Value60s
		OutputFilterDown	UInt64	Output filter down		
					0	NoFilter
					1	Value500ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6FD00-0CU0 - V1.0					
				2	Value1s
				3	Value5s
				4	Value10s
				5	Value30s
				6	Value60s
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
				2	SubstituteAValue
	DiagnosticsWireBreak	Boolean	Wire break		
	ChannelActivated	Boolean	Channel enabled		
	DiagnosticsNoSupplyVoltage	Boolean	Diagnostics: No load voltage L		
	DiagnosticsOvertemperature	Boolean	Overtemperature		
	DiagnosticsOverflow	Boolean	Overflow		
	SubstituteValueAnalog	Double	Substitute value		
	TemperatureShutdown	UInt64	Temperature shutdown		
				0	OutputActiveEvenUnderOvertemperatureConditions
				1	OutputDisabledUnderOvertemperatureConditions
	StartupDelay	UInt64	Startup delay		
				0	NoDelay
				1	Value100ms
				2	Value1s
				3	Value2s
				4	Value3s
				5	Value4s
				6	Value5s
				7	Value10s
	OutputFilterUp	UInt64	Output filter up		
				0	NoFilter

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6FD00-0CU0 - V1.0					
				1	Value500ms
				2	Value1s
				3	Value5s
				4	Value10s
				5	Value30s
				6	Value60s
	OutputFilterDown	UInt64	Output filter down		
				0	NoFilter
				1	Value500ms
				2	Value1s
				3	Value5s
				4	Value10s
				5	Value30s
				6	Value60s
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				11	SubstituteValue1
				2	SubstituteAValue
	DiagnosticsWireBreak	Boolean	Wire break		
	ChannelActivated	Boolean	Channel enabled		
	DiagnosticsNoSupplyVoltage	Boolean	Diagnostics: No load voltage L		
	DiagnosticsOvertemperature	Boolean	Overtemperature		
	DiagnosticsOverflow	Boolean	Overflow		
	SubstituteValueAnalog	Double	Substitute value		
	TemperatureShutdown	UInt64	Temperature shutdown		
				0	OutputActiveEvenUnderOvertemperatureConditions
				1	OutputDisabledUnderOvertemperatureConditions
	StartupDelay	UInt64	Startup delay		
				0	NoDelay

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6FD00-0CU0 - V1.0						
					1	Value100ms
					2	Value1s
					3	Value2s
					4	Value3s
					5	Value4s
					6	Value5s
					7	Value10s
		OutputFilterUp	UInt64	Output filter up		
					0	NoFilter
					1	Value500ms
					2	Value1s
					3	Value5s
					4	Value10s
					5	Value30s
					6	Value60s
		OutputFilterDown	UInt64	Output filter down		
					0	NoFilter
					1	Value500ms
					2	Value1s
					3	Value5s
					4	Value10s
					5	Value30s
					6	Value60s
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
					2	SubstituteAValue
		DiagnosticsWireBreak	Boolean	Wire break		
		ChannelActivated	Boolean	Channel enabled		
		DiagnosticsNoSupplyVoltage	Boolean	Diagnostics: No load voltage L		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6FD00-0CU0 - V1.0					
	DiagnosticsOvertemperature	Boolean	Overtemperature		
	DiagnosticsOverflow	Boolean	Overflow		
	SubstituteValueAnalog	Double	Substitute value		
	TemperatureShutdown	UInt64	Temperature shutdown		
				0	OutputActiveEvenUnderOvertemperatureConditions
				1	OutputDisabledUnderOvertemperatureConditions
	StartupDelay	UInt64	Startup delay		
				0	NoDelay
				1	Value100ms
				2	Value1s
				3	Value2s
				4	Value3s
				5	Value4s
				6	Value5s
				7	Value10s
	OutputFilterUp	UInt64	Output filter up		
				0	NoFilter
				1	Value500ms
				2	Value1s
				3	Value5s
				4	Value10s
				5	Value30s
				6	Value60s
	OutputFilterDown	UInt64	Output filter down		
				0	NoFilter
				1	Value500ms
				2	Value1s
				3	Value5s
				4	Value10s
				5	Value30s
				6	Value60s
Module - 6ES7 132-6GD50-0BA0 - V1.0					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6GD50-0BA0 - V1.0						
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		EnableValueStatus	Boolean	Value status		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6GD50-0BA0 - V1.0						
					11	SubstituteValue1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
Module - 6ES7 132-6GD51-0BA0 - V0.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6GD51-0BA0 - V0.0						
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		EnableValueStatus	Boolean	Value status		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6GD51-0BA0 - V0.0						
					1	KeepLastValue
					11	SubstituteValue1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
Module - 6ES7 132-6HD00-0BB0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6HD00-0BB0 - V1.0						
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6HD00-0BB0 - V1.0						
					1	KeepLastValue
					11	SubstituteValue1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
Module - 6ES7 132-6HD00-0BB0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		EnableValueStatus	Boolean	Value status		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6HD00-0BB0 - V1.1						
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6HD00-0BB0 - V1.1					
				1	KeepLastValue
				11	SubstituteValue1
Module - 6ES7 132-6HD00-0BB1 - V1.1					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	EnableValueStatus	Boolean	Value status		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6HD00-0BB1 - V1.1						
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
Module - 6ES7 132-6HD01-0BB1 - V0.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6HD01-0BB1 - V0.0						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		EnableValueStatus	Boolean	Value status		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6HD01-0BB1 - V0.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
Module - 6ES7 132-6MD00-0BB1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6MD00-0BB1 - V1.0						
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		EnableValueStatus	Boolean	Value status		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 132-6MD00-0BB1 - V1.0						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelActivated	Boolean	Channel activated		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					11	SubstituteValue1

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6FB00-0BA1 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	EnableValueStatus	Boolean	Value status		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsUnderflow	Boolean	Underflow		
	PositionNumber	Int32	Index		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6FB00-0BA1 - V1.0						
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
		OperatingRange	UInt64	Measuring range		
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					3	None
					1	Value60
					0	Value50
					10	Value16Dot6
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
		OperatingRange	UInt64	Measuring range		
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6FB00-0BA1 - V1.0						
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					3	None
					1	Value60
					0	Value50
					10	Value16Dot6
Module - 6ES7 134-6FF00-0AA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsUnderflow	Boolean	Underflow		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6FF00-0AA1 - V1.0					
	PositionNumber	Int32	Index		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
	OperatingRange	UInt64	Measuring range		
				11	PlusMinus10V
				52	Value0To10V
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
				18	Value4800
				20	Value60I18Dot75ms
				19	Value50I22Dot5ms
				15	Value16Dot6I67Dot5ms
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	OperatingType	UInt64	Measurement type		
				0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6FF00-0AA1 - V1.0						
					1	Voltage
		OperatingRange	UInt64	Measuring range		
					11	PlusMinus10V
					52	Value0To10V
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
					18	Value4800
					20	Value60I18Dot75ms
					19	Value50I22Dot5ms
					15	Value16Dot6I67Dot5ms
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
		OperatingRange	UInt64	Measuring range		
					11	PlusMinus10V
					52	Value0To10V
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6FF00-0AA1 - V1.0					
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
				18	Value4800
				20	Value60I18Dot75ms
				19	Value50I22Dot5ms
				15	Value16Dot6I67Dot5ms
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
	OperatingRange	UInt64	Measuring range		
				11	PlusMinus10V
				52	Value0To10V
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
				18	Value4800
				20	Value60I18Dot75ms
				19	Value50I22Dot5ms
				15	Value16Dot6I67Dot5ms
Channel 4					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6FF00-0AA1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
		OperatingRange	UInt64	Measuring range		
					11	PlusMinus10V
					52	Value0To10V
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
					18	Value4800
					20	Value60I18Dot75ms
					19	Value50I22Dot5ms
					15	Value16Dot6I67Dot5ms
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6FF00-0AA1 - V1.0					
	OperatingRange	UInt64	Measuring range		
				11	PlusMinus10V
				52	Value0To10V
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
				18	Value4800
				20	Value60I18Dot75ms
				19	Value50I22Dot5ms
				15	Value16Dot6I67Dot5ms
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
	OperatingRange	UInt64	Measuring range		
				11	PlusMinus10V
				52	Value0To10V
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6FF00-0AA1 - V1.0					
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
				18	Value4800
				20	Value60I18Dot75ms
				19	Value50I22Dot5ms
				15	Value16Dot6I67Dot5ms
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
	OperatingRange	UInt64	Measuring range		
				11	PlusMinus10V
				52	Value0To10V
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
				18	Value4800
				20	Value60I18Dot75ms
				19	Value50I22Dot5ms
				15	Value16Dot6I67Dot5ms
Module - 6ES7 134-6GB00-0BA1 - V1.0					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GB00-0BA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GB00-0BA1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					3	None
					1	Value60
					0	Value50
					10	Value16Dot6
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GB00-0BA1 - V1.0						
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					3	None
					1	Value60
					0	Value50
					10	Value16Dot6
Module - 6ES7 134-6GD00-0BA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GD00-0BA1 - V1.0					
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	PositionNumber	Int32	Index		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				3	Current4WireTransducer
				4	Current2WireTransducer
	OperatingRange	UInt64	Measuring range		
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				3	Current4WireTransducer
				4	Current2WireTransducer
	OperatingRange	UInt64	Measuring range		
				17	PlusMinus20mA
				15	Value0To20mA

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GD00-0BA1 - V1.0					
				16	Value4To20mA
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				3	Current4WireTransducer
				4	Current2WireTransducer
	OperatingRange	UInt64	Measuring range		
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GD00-0BA1 - V1.0						
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
Module - 6ES7 134-6GD00-0BA1 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GD00-0BA1 - V1.1						
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GD00-0BA1 - V1.1						
					0	Value50
					10	Value16Dot6
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GD00-0BA1 - V1.1						
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
Module - 6ES7 134-6GD01-0BA1 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GD01-0BA1 - V2.0					
	Name	String	Name		
	ShortDesignation	String	Short designation		
	EnableValueStatus	Boolean	Value status		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				3	Current4WireTransducer

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GD01-0BA1 - V2.0						
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GD01-0BA1 - V2.0					
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				3	Current4WireTransducer
				4	Current2WireTransducer
	OperatingRange	UInt64	Measuring range		
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				3	Current4WireTransducer
				4	Current2WireTransducer
	OperatingRange	UInt64	Measuring range		
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GD01-0BA1 - V2.0						
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
Module - 6ES7 134-6GF00-0AA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GF00-0AA1 - V1.0					
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	PositionNumber	Int32	Index		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				3	Current4WireTransducer
				4	Current2WireTransducer
	OperatingRange	UInt64	Measuring range		
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
				18	Value4800
				20	Value60I18Dot75ms
				19	Value50I22Dot5ms
				15	Value16Dot6I67Dot5ms
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GF00-0AA1 - V1.0					
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				3	Current4WireTransducer
				4	Current2WireTransducer
	OperatingRange	UInt64	Measuring range		
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
				18	Value4800
				20	Value60I18Dot75ms
				19	Value50I22Dot5ms
				15	Value16Dot6I67Dot5ms
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				3	Current4WireTransducer
				4	Current2WireTransducer

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GF00-0AA1 - V1.0						
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
					18	Value4800
					20	Value60I18Dot75ms
					19	Value50I22Dot5ms
					15	Value16Dot6I67Dot5ms
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GF00-0AA1 - V1.0						
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
					18	Value4800
					20	Value60I18Dot75ms
					19	Value50I22Dot5ms
					15	Value16Dot6I67Dot5ms
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
					18	Value4800

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GF00-0AA1 - V1.0						
					20	Value60I18Dot75ms
					19	Value50I22Dot5ms
					15	Value16Dot6I67Dot5ms
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
					18	Value4800
					20	Value60I18Dot75ms
					19	Value50I22Dot5ms
					15	Value16Dot6I67Dot5ms
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GF00-0AA1 - V1.0						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
					18	Value4800
					20	Value60I18Dot75ms
					19	Value50I22Dot5ms
					15	Value16Dot6I67Dot5ms
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					3	Current4WireTransducer
					4	Current2WireTransducer

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6GF00-0AA1 - V1.0						
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
					18	Value4800
					20	Value60I18Dot75ms
					19	Value50I22Dot5ms
					15	Value16Dot6I67Dot5ms
Module - 6ES7 134-6HB00-0CA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V1.0						
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					4	Current2WireTransducer
					3	Current4WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V
					9	PlusMinus5V

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V1.0						
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					5	Value2x
					6	Value4x
					7	Value8x
					8	Value16x
					9	Value32x
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					15	Value16Dot6I67Dot5ms
					19	Value50I22Dot5ms
					20	Value60I18Dot75ms
					5	Value300
					21	Value600
					17	Value1200
					22	Value2400
					18	Value4800
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V1.0						
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					4	Current2WireTransducer
					3	Current4WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V1.0						
		Smoothing	UInt64	Smoothing		
					0	None
					5	Value2x
					6	Value4x
					7	Value8x
					8	Value16x
					9	Value32x
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					15	Value16Dot6I67Dot5ms
					19	Value50I22Dot5ms
					20	Value60I18Dot75ms
					5	Value300
					21	Value600
					17	Value1200
					22	Value2400
					18	Value4800
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V1.0						
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
Module - 6ES7 134-6HB00-0CA1 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		SharedDeviceCopyOfModule	UInt64			
					0	None
					1	Value1AdditionalCopyOfAnInput
					2	Value2AdditionalCopiesOfAnInput
					3	Value3AdditionalCopiesOfAnInput
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OperatingMode	UInt64	EnableScalingOfMeasurementValues		
					73	ScalingMode
					281	Deactivated
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					4	Current2WireTransducer
					3	Current4WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					5	Value2x
					6	Value4x
					7	Value8x

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0						
					8	Value16x
					9	Value32x
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					15	Value16Dot6I67Dot5ms
					19	Value50I22Dot5ms
					20	Value60I18Dot75ms
					5	Value300
					21	Value600
					17	Value1200
					22	Value2400
					18	Value4800
		AdjustMeasuringRange	Boolean	Adjust measuring range		
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		HighLimit	Double	High limit		
		LowLimit	Double	Low limit		
		ScaledHighNominalRangeLimit	Double	Scaled high nominal range limit		
		ScaledLowNominalRangeLimit	Double	Scaled low nominal range limit		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		PhysicalQuantity	UInt64	Physical quantity		
					2	Temperature

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0						
					3	Pressure
					4	Length
					5	Flow
					6	Brightness
					7	Illuminance
					8	Force
					9	Torque
					10	Mass
					11	Current
					12	Voltage
					13	Power
					14	Area
					15	Volume
					16	Angle
					17	Viscosity
					18	Speed
					19	Velocity
					20	Density
					21	Frequency
					1	S7Format
					0	Deactivated
		UnitsOfMeasure	UInt64	Unit of measure		
					0	Deactivated
					9	DegreesCelsius
					10	DegreesFahrenheit
					61	K
					17	Bar
					109	Pa
					53	HPa
					15	At
					16	Atm
					117	Torr
					112	Psi
					11	MicroMeter

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0						
					100	Mm
					23	Cm
					88	Meter
					67	Km
					55	In
					32	Ft
					98	Mile
					74	LPerSecond
					73	LPerMinute
					72	LPerHour
					71	LPerd
					27	CubiccmPerSecond
					26	CubiccmPerMinute
					25	CubiccmPerHour
					24	CubiccmPerd
					97	CubicMeterPerSecond
					96	CubicMeterPerMinute
					95	CubicMeterPerHour
					94	CubicMeterPerd
					42	CubicftPerSecond
					41	CubicftPerMinute
					40	CubicftPerHour
					39	CubicftPerd
					21	BarPerSecond
					20	BarPerMinute
					19	BarPerHour
					18	BarPerd
					50	GalPerSecond
					49	GalPermin
					48	GalPerHour
					47	GalPerd
					83	LbPerSecond
					82	LbPerMinute
					80	LbPerHour

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0						
					78	LbPerd
					22	Cd
					87	Lux
					31	Fc
					103	N
					30	Dyn
					104	Nm
					33	FtLb
					43	G
					62	Kg
					106	Oz
					75	Lb
					116	Ton
					115	T
					14	Ampere
					118	V
					120	W
					69	KW
					119	VA
					52	Hp
					91	SquareMeter
					102	SquareMilliMeter
					59	Squarein
					121	Squareyd
					37	Squareft
					99	SquareMile
					70	L
					93	CubicMeter
					60	Cubicin
					122	Cubicyd
					38	Cubicft
					46	Gal
					29	Cubicdm
					7	Degrees

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0						
					113	Rad
					28	Cp
					108	P
					111	Pl
					63	KgPerMeterSecond
					110	PaSeconds
					65	KgfSecondPerSquareMeter
					86	LbfSecondPerSquareFt
					85	LbfHourPerSquareft
					76	LbPerftSecond
					105	NsPerSquareMeter
					92	SquareMeterPerSecond
					12	OnePerMinute
					51	GradPerSecond
					13	OnePerSecond
					114	RadPerSecond
					8	DegreesPerSecond
					101	MmPerSecond
					90	MeterPerSecond
					89	MeterPerMinute
					68	KmPerHour
					58	InPerSecond
					57	InPerMinute
					56	InPerHour
					36	FtPerSecond
					35	FtPerMinute
					34	FtPerH
					66	KgPerCubicm
					107	OzPerCubicin
					81	LbPerCubicin
					84	LbPerCubicyd
					79	LbPerGal
					77	LbPerbu
					64	KgPerl

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0						
					45	GPerml
					44	GPerCubiccm
					54	Hz
		InverseScaling	Boolean	Inverse scaling		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					4	Current2WireTransducer
					3	Current4WireTransducer
		OperatingRange	UInt64	Measuring range		
					0	Deactivated
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0						
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					5	Value2x
					6	Value4x
					7	Value8x
					8	Value16x
					9	Value32x
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					15	Value16Dot6I67Dot5ms
					19	Value50I22Dot5ms
					20	Value60I18Dot75ms
					5	Value300
					21	Value600
					17	Value1200
					22	Value2400
					18	Value4800
		AdjustMeasuringRange	Boolean	Adjust measuring range		
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		HighLimit	Double	High limit		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0						
		LowLimit	Double	Low limit		
		ScaledHighNominalRangeLimit	Double	Scaled high nominal range limit		
		ScaledLowNominalRangeLimit	Double	Scaled low nominal range limit		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		PhysicalQuantity	UInt64	Physical quantity		
					2	Temperature
					3	Pressure
					4	Length
					5	Flow
					6	Brightness
					7	Illuminance
					8	Force
					9	Torque
					10	Mass
					11	Current
					12	Voltage
					13	Power
					14	Area
					15	Volume
					16	Angle
					17	Viscosity
					18	Speed
					19	Velocity
					20	Density
					21	Frequency
					1	S7Format
					0	Deactivated
		UnitsOfMeasure	UInt64	Unit of measure		
					0	Deactivated
					17	Bar
					109	Pa

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0					
				53	HPa
				15	At
				16	Atm
				117	Torr
				112	Psi
				7	Degrees
				9	DegreesCelsius
				11	MicroMeter
				12	OnePerMinute
				14	Ampere
				22	Cd
				28	Cp
				43	G
				54	Hz
				66	KgPerCubicm
				70	L
				74	LPerSecond
				87	Lux
				91	SquareMeter
				101	MmPerSecond
				103	N
				104	Nm
				118	V
				120	W
				10	DegreesFahrenheit
				30	Dyn
				31	Fc
				33	FtLb
				51	GradPerSecond
				62	Kg
				69	KW
				73	LPerMinute
				90	MeterPerSecond
				93	CubicMeter

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0					
				100	Mm
				102	SquareMilliMeter
				107	OzPerCubicin
				108	P
				113	Rad
				92	SquareMeterPerSecond
				95	CubicMeterPerHour
				94	CubicMeterPerd
				42	CubicftPerSecond
				41	CubicftPerMinute
				40	CubicftPerHour
				39	CubicftPerd
				21	BarPerSecond
				20	BarPerMinute
				19	BarPerHour
				18	BarPerd
				13	OnePerSecond
				23	Cm
				59	Squarein
				60	Cubicin
				61	K
				72	LPerHour
				81	LbPerCubicin
				89	MeterPerMinute
				106	Oz
				111	Pl
				119	VA
				50	GalPerSecond
				49	GalPermin
				48	GalPerHour
				47	GalPerd
				83	LbPerSecond
				82	LbPerMinute
				80	LbPerHour

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0						
					78	LbPerd
					52	Hp
					63	KgPerMeterSecond
					68	KmPerHour
					71	LPerd
					75	Lb
					84	LbPerCubicyd
					88	Meter
					114	RadPerSecond
					121	Squareyd
					122	Cubicyd
					8	DegreesPerSecond
					27	CubiccmPerSecond
					37	Squareft
					38	Cubicft
					58	InPerSecond
					67	Km
					79	LbPerGal
					110	PaSeconds
					116	Ton
					26	CubiccmPerMinute
					46	Gal
					55	In
					57	InPerMinute
					65	KgfSecondPerSquareMeter
					77	LbPerbu
					99	SquareMile
					115	T
					25	CubiccmPerHour
					29	Cubicdm
					32	Ft
					56	InPerHour
					64	KgPerl
					86	LbfSecondPerSquareFt

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0CA1 - V2.0						
					24	CubiccmPerd
					36	FtPerSecond
					45	GPerml
					85	LbfHourPerSquareft
					98	Mile
					35	FtPerMinute
					44	GPerCubiccm
					76	LbPerftSecond
					97	CubicMeterPerSecond
					34	FtPerH
					96	CubicMeterPerMinute
					105	NsPerSquareMeter
		InverseScaling	Boolean	Inverse scaling		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
Module - 6ES7 134-6HB00-0DA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V1.0						
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OversamplingRate	UInt64	Sample_Rate_Modul		
		OversamplingInterval	Int64	Scan_Rate		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V1.0						
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					5	Value2x
					6	Value4x
					7	Value8x
					8	Value16x
					9	Value32x
					10	Value64x
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V1.0						
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 1					
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V1.0						
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					5	Value2x
					6	Value4x
					7	Value8x
					8	Value16x
					9	Value32x
					10	Value64x
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OversamplingRate	UInt64	Sample_Rate_Modul		
		OversamplingInterval	Int64	Scan_Rate		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V1.1						
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					5	Value2x
					6	Value4x
					7	Value8x

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V1.1						
					8	Value16x
					9	Value32x
					10	Value64x
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 1					
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V1.1						
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					5	Value2x
					6	Value4x
					7	Value8x
					8	Value16x
					9	Value32x
					10	Value64x
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V1.1						
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
Module - 6ES7 134-6HB00-0DA1 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OversamplingRate	UInt64	Sample_Rate_Modul		
		OversamplingInterval	Int64	Scan_Rate		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V2.0						
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					5	Value2x
					6	Value4x
					7	Value8x
					8	Value16x
					9	Value32x
					10	Value64x
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 1					
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V2.0						
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					3	Current4WireTransducer
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					5	Value2x
					6	Value4x
					7	Value8x
					8	Value16x
					9	Value32x
					10	Value64x

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HB00-0DA1 - V2.0						
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
Module - 6ES7 134-6HD00-0BA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HD00-0BA1 - V1.0						
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HD00-0BA1 - V1.0						
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					4	Current2WireTransducer

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HD00-0BA1 - V1.0					
	OperatingRange	UInt64	Measuring range		
				15	Value0To20mA
				16	Value4To20mA
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
				4	Current2WireTransducer
	OperatingRange	UInt64	Measuring range		
				15	Value0To20mA
				16	Value4To20mA
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HD00-0BA1 - V1.0						
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
Module - 6ES7 134-6HD00-0BA1 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HD00-0BA1 - V1.1					
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	PositionNumber	Int32	Index		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
				4	Current2WireTransducer
	OperatingRange	UInt64	Measuring range		
				15	Value0To20mA
				16	Value4To20mA
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
				4	Current2WireTransducer

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HD00-0BA1 - V1.1					
	OperatingRange	UInt64	Measuring range		
				15	Value0To20mA
				16	Value4To20mA
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
				4	Current2WireTransducer
	OperatingRange	UInt64	Measuring range		
				15	Value0To20mA
				16	Value4To20mA
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HD00-0BA1 - V1.1						
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					15	Value0To20mA
					16	Value4To20mA
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
Module - 6ES7 134-6HD01-0BA1 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HD01-0BA1 - V2.0						
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					4	Current2WireTransducer

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HD01-0BA1 - V2.0					
	OperatingRange	UInt64	Measuring range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				15	Value0To20mA
				16	Value4To20mA
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong
	InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
				1	Value60
				0	Value50
				10	Value16Dot6
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
				4	Current2WireTransducer
	OperatingRange	UInt64	Measuring range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				15	Value0To20mA
				16	Value4To20mA
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HD01-0BA1 - V2.0						
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6HD01-0BA1 - V2.0						
					4	Current2WireTransducer
		OperatingRange	UInt64	Measuring range		
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
					15	Value0To20mA
					16	Value4To20mA
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
Module - 6ES7 134-6JD00-0CA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0					
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
Channel 0					
	HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
				0	Deactivated
				1	Active
	HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
				0	Deactivated
				1	Active
	HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
				0	Deactivated
				1	Active
	HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
				0	Deactivated
				1	Active
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	DiagnosticsReferenceJunction	Boolean	Reference junction		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
				5	Resistor4Wire

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
					6	Resistor3Wire
					7	Resistor2Wire
					8	ThermalResistor4Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					53	PTC

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
					8	ReferenceChannelOfGroup0
					7	FixedReferenceTemperature
					0	None
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 1					
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					5	Resistor4Wire
					6	Resistor3Wire
					7	Resistor2Wire
					8	ThermalResistor4Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					53	PTC
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					31	Value150Ohm
					32	Value300Ohm

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					8	ReferenceChannelOfGroup0
					7	FixedReferenceTemperature
					0	None
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Value	Double	High limit 1		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 2					
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					5	Resistor4Wire
					6	Resistor3Wire
					7	Resistor2Wire
					8	ThermalResistor4Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					2	PlusMinus50mV
					3	PlusMinus80mV

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
					5	PlusMinus250mV
					7	PlusMinus1V
					53	PTC
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					8	ReferenceChannelOfGroup0
					7	FixedReferenceTemperature
					0	None
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0					
Channel 3					
	HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
				0	Deactivated
				1	Active
	HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
				0	Deactivated
				1	Active
	HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
				0	Deactivated
				1	Active
	HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
				0	Deactivated
				1	Active
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsReferenceJunction	Boolean	Reference junction		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
				5	Resistor4Wire
				6	Resistor3Wire
				7	Resistor2Wire
				8	ThermalResistor4Wire
				9	ThermalResistor3Wire
				25	ThermalResistor2Wire
				10	Thermocouple
	OperatingRange	UInt64	Measuring range		
				40	Pt100ClimaticRange
				44	Ni100ClimaticRange
				46	Pt100StandardRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					53	PTC
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0					
				72	TypeC
				105	TypeTxk
				31	Value150Ohm
				32	Value300Ohm
				33	Value600Ohm
				54	Value3KiloOhm
				34	Value6KiloOhm
	MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
				6	Pt0Dot00385055
				1	Pt0Dot003916
				2	Pt0Dot003902
				3	Pt0Dot003920
				9	Pt0Dot003850
				7	Ni0Dot006180
				8	Ni0Dot006720
				10	LgNi0Dot005
				12	Cu0Dot00427
	TemperatureUnit	UInt64	Temperature unit		
				1	DegreesCelsius
				2	DegreesFahrenheit
				3	Kelvin
	ReferenceJunction	UInt64	Reference junction		
				2	ReferenceChannelOfTheModule
				3	InternalReferenceJunction
				8	ReferenceChannelOfGroup0
				7	FixedReferenceTemperature
				0	None
	MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
	Smoothing	UInt64	Smoothing		
				0	None
				1	Weak
				2	Medium
				3	Strong

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.0						
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
Module - 6ES7 134-6JD00-0CA1 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		DiagnosticsReferenceJunction	Boolean	Reference junction		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					5	Resistor4Wire
					6	Resistor3Wire
					7	Resistor2Wire
					8	ThermalResistor4Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					2	PlusMinus50mV

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					53	PTC
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					8	ReferenceChannelOfGroup0
					7	FixedReferenceTemperature
					0	None
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 1					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					5	Resistor4Wire
					6	Resistor3Wire
					7	Resistor2Wire
					8	ThermalResistor4Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					53	PTC
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
					105	TypeTxk
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					8	ReferenceChannelOfGroup0
					7	FixedReferenceTemperature
					0	None
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 2					
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					5	Resistor4Wire
					6	Resistor3Wire
					7	Resistor2Wire
					8	ThermalResistor4Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					53	PTC
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
					12	Cu0Dot00427
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					8	ReferenceChannelOfGroup0
					7	FixedReferenceTemperature
					0	None
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 3					
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					5	Resistor4Wire
					6	Resistor3Wire
					7	Resistor2Wire
					8	ThermalResistor4Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
					10	Thermocouple

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
		OperatingRange	UInt64	Measuring range		
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					53	PTC
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					8	ReferenceChannelOfGroup0
					7	FixedReferenceTemperature
					0	None
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V1.1						
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
Module - 6ES7 134-6JD00-0CA1 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					7	Resistor2Wire
					6	Resistor3Wire

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
					5	Resistor4Wire
					8	ThermalResistor4Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		ScalableMeasuringRange	Boolean	Active		
		MeasuringRangeResolution	UInt64	Measuring range resolution		
					1	Value2DecimalPlaces
					2	Value3DecimalPlaces
		MeasuringRangeCenter	Int64	Measuring range center		
		MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
		MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0					
	HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
	HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
				6	Pt0Dot00385055
				1	Pt0Dot003916
				2	Pt0Dot003902
				3	Pt0Dot003920
				9	Pt0Dot003850
				7	Ni0Dot006180
				8	Ni0Dot006720
				10	LgNi0Dot005
				12	Cu0Dot00427
	ConductorResistor	Int64	Conductor resistor		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	HardwareInterruptHighLimit1Value	Double	High limit 1		
	HardwareInterruptLowLimit1Value	Double	Low limit 1		
	HardwareInterruptHighLimit2Value	Double	High limit 2		
	HardwareInterruptLowLimit2Value	Double	Low limit 2		
	ScalableMeasuringRange	Boolean	Active		
	MeasuringRangeResolution	UInt64	Measuring range resolution		
				1	Value2DecimalPlaces
				2	Value3DecimalPlaces
	MeasuringRangeCenter	Int64	Measuring range center		
	MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
	MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsReferenceJunction	Boolean	Reference junction		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					7	Resistor2Wire
					6	Resistor3Wire
					5	Resistor4Wire
					8	ThermalResistor4Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0					
	HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
				6	Pt0Dot00385055
				1	Pt0Dot003916
				2	Pt0Dot003902
				3	Pt0Dot003920
				9	Pt0Dot003850
				7	Ni0Dot006180
				8	Ni0Dot006720
				10	LgNi0Dot005
				12	Cu0Dot00427
	ConductorResistor	Int64	Conductor resistor		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	HardwareInterruptHighLimit1Value	Double	High limit 1		
	HardwareInterruptLowLimit1Value	Double	Low limit 1		
	HardwareInterruptHighLimit2Value	Double	High limit 2		
	HardwareInterruptLowLimit2Value	Double	Low limit 2		
	ScalableMeasuringRange	Boolean	Active		
	MeasuringRangeResolution	UInt64	Measuring range resolution		
				1	Value2DecimalPlaces
				2	Value3DecimalPlaces
	MeasuringRangeCenter	Int64	Measuring range center		
	MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
	MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsReferenceJunction	Boolean	Reference junction		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					7	Resistor2Wire
					6	Resistor3Wire
					5	Resistor4Wire
					8	ThermalResistor4Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
					55	Ni120ClimaticRange
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					7	FixedReferenceTemperature

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0					
	MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
				6	Pt0Dot00385055
				1	Pt0Dot003916
				2	Pt0Dot003902
				3	Pt0Dot003920
				9	Pt0Dot003850
				7	Ni0Dot006180
				8	Ni0Dot006720
				10	LgNi0Dot005
				12	Cu0Dot00427
	ConductorResistor	Int64	Conductor resistor		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	HardwareInterruptHighLimit1Value	Double	High limit 1		
	HardwareInterruptLowLimit1Value	Double	Low limit 1		
	HardwareInterruptHighLimit2Value	Double	High limit 2		
	HardwareInterruptLowLimit2Value	Double	Low limit 2		
	ScalableMeasuringRange	Boolean	Active		
	MeasuringRangeResolution	UInt64	Measuring range resolution		
				1	Value2DecimalPlaces
				2	Value3DecimalPlaces
	MeasuringRangeCenter	Int64	Measuring range center		
	MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
	MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsReferenceJunction	Boolean	Reference junction		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					7	Resistor2Wire
					6	Resistor3Wire
					5	Resistor4Wire
					8	ThermalResistor4Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
					55	Ni120ClimaticRange
					74	Cu10ClimaticRange
					77	Cu10StandardRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					7	FixedReferenceTemperature

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0CA1 - V2.0						
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		ConductorResistor	Int64	Conductor resistor		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
Module - 6ES7 134-6JD00-0DA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		EnableValueStatus	Boolean	Value status		
		SharedDeviceCopyOfModule	UInt64			
					0	None
					1	Value1AdditionalCopyOfAnInput
					2	Value2AdditionalCopiesOfAnInput

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0DA1 - V1.0						
					3	Value3AdditionalCopiesOfAnInput
		OperatingMode	UInt64	EnableRealMode		
					74	REALMode
					281	Deactivated
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0DA1 - V1.0						
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					3	InternalReferenceJunction
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0DA1 - V1.0						
					0	Value50
					10	Value16Dot6
					3	None
		ScalableMeasuringRange	Boolean	Active		
		MeasuringRangeResolution	UInt64	Measuring range resolution		
					1	Value2DecimalPlaces
					2	Value3DecimalPlaces
		MeasuringRangeCenter	Int64	Measuring range center		
		MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
		MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
		EnableWireBreakTest	Boolean	Enable wire break test		
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		OutlierSuppression	Boolean	Outlier suppression		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0DA1 - V1.0						
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		ScalableMeasuringRange	Boolean	Active		
		MeasuringRangeResolution	UInt64	Measuring range resolution		
					1	Value2DecimalPlaces
					2	Value3DecimalPlaces
		MeasuringRangeCenter	Int64	Measuring range center		
		MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
		MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0DA1 - V1.0						
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					3	InternalReferenceJunction
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
					3	None
		EnableWireBreakTest	Boolean	Enable wire break test		
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0DA1 - V1.0						
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		OutlierSuppression	Boolean	Outlier suppression		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		ScalableMeasuringRange	Boolean	Active		
		MeasuringRangeResolution	UInt64	Measuring range resolution		
					1	Value2DecimalPlaces
					2	Value3DecimalPlaces
		MeasuringRangeCenter	Int64	Measuring range center		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0DA1 - V1.0						
		MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
		MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					3	InternalReferenceJunction

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0DA1 - V1.0						
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
					3	None
		EnableWireBreakTest	Boolean	Enable wire break test		
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		OutlierSuppression	Boolean	Outlier suppression		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0DA1 - V1.0						
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		ScalableMeasuringRange	Boolean	Active		
		MeasuringRangeResolution	UInt64	Measuring range resolution		
					1	Value2DecimalPlaces
					2	Value3DecimalPlaces
		MeasuringRangeCenter	Int64	Measuring range center		
		MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
		MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0DA1 - V1.0						
					5	PlusMinus250mV
					7	PlusMinus1V
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					3	InternalReferenceJunction
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JD00-0DA1 - V1.0						
					10	Value16Dot6
					3	None
		EnableWireBreakTest	Boolean	Enable wire break test		
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		OutlierSuppression	Boolean	Outlier suppression		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					7	Resistor2Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		ScalableMeasuringRange	Boolean	Active		
		MeasuringRangeResolution	UInt64	Measuring range resolution		
					1	Value2DecimalPlaces
					2	Value3DecimalPlaces
		MeasuringRangeCenter	Int64	Measuring range center		
		MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
		MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0					
	HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
				6	Pt0Dot00385055
				1	Pt0Dot003916
				2	Pt0Dot003902
				3	Pt0Dot003920
				9	Pt0Dot003850
				7	Ni0Dot006180
				8	Ni0Dot006720
				10	LgNi0Dot005
				12	Cu0Dot00427
	ConductorResistor	Int64	Conductor resistor		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	HardwareInterruptHighLimit1Value	Double	High limit 1		
	HardwareInterruptLowLimit1Value	Double	Low limit 1		
	HardwareInterruptHighLimit2Value	Double	High limit 2		
	HardwareInterruptLowLimit2Value	Double	Low limit 2		
	ScalableMeasuringRange	Boolean	Active		
	MeasuringRangeResolution	UInt64	Measuring range resolution		
				1	Value2DecimalPlaces
				2	Value3DecimalPlaces
	MeasuringRangeCenter	Int64	Measuring range center		
	MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
	MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsReferenceJunction	Boolean	Reference junction		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					7	Resistor2Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0					
				7	Ni0Dot006180
				8	Ni0Dot006720
				10	LgNi0Dot005
				12	Cu0Dot00427
	ConductorResistor	Int64	Conductor resistor		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	HardwareInterruptHighLimit1Value	Double	High limit 1		
	HardwareInterruptLowLimit1Value	Double	Low limit 1		
	HardwareInterruptHighLimit2Value	Double	High limit 2		
	HardwareInterruptLowLimit2Value	Double	Low limit 2		
	ScalableMeasuringRange	Boolean	Active		
	MeasuringRangeResolution	UInt64	Measuring range resolution		
				1	Value2DecimalPlaces
				2	Value3DecimalPlaces
	MeasuringRangeCenter	Int64	Measuring range center		
	MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
	MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsReferenceJunction	Boolean	Reference junction		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
				7	Resistor2Wire
				25	ThermalResistor2Wire
				10	Thermocouple

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		ConductorResistor	Int64	Conductor resistor		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		ScalableMeasuringRange	Boolean	Active		
		MeasuringRangeResolution	UInt64	Measuring range resolution		
					1	Value2DecimalPlaces
					2	Value3DecimalPlaces
		MeasuringRangeCenter	Int64	Measuring range center		
		MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
		MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					7	Resistor2Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		ConductorResistor	Int64	Conductor resistor		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1Value	Double	High limit 1		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		ScalableMeasuringRange	Boolean	Active		
		MeasuringRangeResolution	UInt64	Measuring range resolution		
					1	Value2DecimalPlaces
					2	Value3DecimalPlaces
		MeasuringRangeCenter	Int64	Measuring range center		
		MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
		MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					7	Resistor2Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		ConductorResistor	Int64	Conductor resistor		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		ScalableMeasuringRange	Boolean	Active		
		MeasuringRangeResolution	UInt64	Measuring range resolution		
					1	Value2DecimalPlaces
					2	Value3DecimalPlaces

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		MeasuringRangeCenter	Int64	Measuring range center		
		MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
		MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					7	Resistor2Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					3	InternalReferenceJunction
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0					
	HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
	HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
				6	Pt0Dot00385055
				1	Pt0Dot003916
				2	Pt0Dot003902
				3	Pt0Dot003920
				9	Pt0Dot003850
				7	Ni0Dot006180
				8	Ni0Dot006720
				10	LgNi0Dot005
				12	Cu0Dot00427
	ConductorResistor	Int64	Conductor resistor		
	ParameterSettings	UInt64	Parameter settings		
				1	FromTemplate
				0	Manual
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	HardwareInterruptHighLimit1Value	Double	High limit 1		
	HardwareInterruptLowLimit1Value	Double	Low limit 1		
	HardwareInterruptHighLimit2Value	Double	High limit 2		
	HardwareInterruptLowLimit2Value	Double	Low limit 2		
	ScalableMeasuringRange	Boolean	Active		
	MeasuringRangeResolution	UInt64	Measuring range resolution		
				1	Value2DecimalPlaces
				2	Value3DecimalPlaces
	MeasuringRangeCenter	Int64	Measuring range center		
	MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
	MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsReferenceJunction	Boolean	Reference junction		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					7	Resistor2Wire
					25	ThermalResistor2Wire
					10	Thermocouple
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		ConductorResistor	Int64	Conductor resistor		
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		ScalableMeasuringRange	Boolean	Active		
		MeasuringRangeResolution	UInt64	Measuring range resolution		
					1	Value2DecimalPlaces
					2	Value3DecimalPlaces
		MeasuringRangeCenter	Int64	Measuring range center		
		MaximumScalableMeasuringRange	Double	Maximum (scalable measuring range)		
		MinimumScalableMeasuringRange	Double	Minimum (scalable measuring range)		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsReferenceJunction	Boolean	Reference junction		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					7	Resistor2Wire
					25	ThermalResistor2Wire
					10	Thermocouple

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		OperatingRange	UInt64	Measuring range		
					2	PlusMinus50mV
					3	PlusMinus80mV
					5	PlusMinus250mV
					7	PlusMinus1V
					31	Value150Ohm
					32	Value300Ohm
					33	Value600Ohm
					54	Value3KiloOhm
					34	Value6KiloOhm
					53	PTC
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					48	Pt500StandardRange
					49	Pt1000StandardRange
					51	Ni1000StandardRange
					41	Pt200ClimaticRange
					42	Pt500ClimaticRange
					43	Pt1000ClimaticRange
					45	Ni1000ClimaticRange
					47	Pt200StandardRange
					56	Ni120StandardRange
					55	Ni120ClimaticRange
					58	Ni200StandardRange
					57	Ni200ClimaticRange
					59	Ni500StandardRange
					19	Ni500ClimaticRange
					60	LgNi1000ClimaticRange
					61	LgNi1000StandardRange
					20	TypeB
					21	TypeN
					22	TypeE

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					23	TypeR
					24	TypeS
					25	TypeJ
					26	TypeL
					27	TypeT
					28	TypeK
					29	TypeU
					72	TypeC
					105	TypeTxk
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		ReferenceJunction	UInt64	Reference junction		
					0	None
					8	ReferenceChannelOfGroup0
					9	ReferenceChannelOfGroup1
					11	ReferenceChannelOfGroup2
					12	ReferenceChannelOfGroup3
					2	ReferenceChannelOfTheModule
					3	InternalReferenceJunction
					7	FixedReferenceTemperature
		MeasuringFixedReferenceTemperature	Int64	Fixed reference temperature		
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
					1	Active
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					6	Pt0Dot00385055
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
					7	Ni0Dot006180
					8	Ni0Dot006720
					10	LgNi0Dot005
					12	Cu0Dot00427
		ConductorResistor	Int64	Conductor resistor		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6JF00-0CA1 - V2.0						
		ParameterSettings	UInt64	Parameter settings		
					1	FromTemplate
					0	Manual

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6FB00-0BA1 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	EnableValueStatus	Boolean	Value status		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsUnderflow	Boolean	Underflow		
	PositionNumber	Int32	Index		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6FB00-0BA1 - V1.0					
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue
	SubstituteValueAnalog	Double	Output substitute value		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6FB00-0BA1 - V1.0						
		SubstituteValueAnalog	Double	Output substitute value		
Module - 6ES7 135-6GB00-0BA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		PositionNumber	Int32	Index		
	Channel 0					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6GB00-0BA1 - V1.0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	OperatingType	UInt64	Output type		
				0	Deactivated
				2	Current
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue
	SubstituteValueAnalog	Double	Output substitute value		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	OperatingType	UInt64	Output type		
				0	Deactivated
				2	Current
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6GB00-0BA1 - V1.0						
					1	KeepLastValue
					16	OutputSubstituteValue
		SubstituteValueAnalog	Double	Output substitute value		
Module - 6ES7 135-6HB00-0CA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HB00-0CA1 - V1.0					
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue
	SubstituteValueAnalog	Double	Output substitute value		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HB00-0CA1 - V1.0						
		OperatingRange	UInt64	Output range		
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					16	OutputSubstituteValue
		SubstituteValueAnalog	Double	Output substitute value		
Module - 6ES7 135-6HB00-0DA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OversamplingRate	UInt64	Sample_Rate_Modul		
		OversamplingInterval	Int64	Scan_Rate		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HB00-0DA1 - V1.0						
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					16	OutputSubstituteValue
		SubstituteValueAnalog	Double	Output substitute value		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HB00-0DA1 - V1.0					
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue
	SubstituteValueAnalog	Double	Output substitute value		
Module - 6ES7 135-6HB00-0DA1 - V1.1					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	EnableValueStatus	Boolean	Value status		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HB00-0DA1 - V1.1						
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OversamplingRate	UInt64	Sample_Rate_Modul		
		OversamplingInterval	Int64	Scan_Rate		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HB00-0DA1 - V1.1					
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue
	SubstituteValueAnalog	Double	Output substitute value		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HB00-0DA1 - V1.1						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					16	OutputSubstituteValue
		SubstituteValueAnalog	Double	Output substitute value		
Module - 6ES7 135-6HB00-0DA1 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		EnableValueStatus	Boolean	Value status		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OversamplingRate	UInt64	Sample_Rate_Modul		
		OversamplingInterval	Int64	Scan_Rate		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HB00-0DA1 - V2.0					
	PositionNumber	Int32	Index		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue
	SubstituteValueAnalog	Double	Output substitute value		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HB00-0DA1 - V2.0						
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					16	OutputSubstituteValue
		SubstituteValueAnalog	Double	Output substitute value		
Module - 6ES7 135-6HD00-0BA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HD00-0BA1 - V1.0					
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	PositionNumber	Int32	Index		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HD00-0BA1 - V1.0						
		SubstituteValueAnalog	Double	Output substitute value		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					16	OutputSubstituteValue
		SubstituteValueAnalog	Double	Output substitute value		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HD00-0BA1 - V1.0					
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue
	SubstituteValueAnalog	Double	Output substitute value		
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue
	SubstituteValueAnalog	Double	Output substitute value		
Module - 6ES7 135-6HD00-0BA1 - V1.1					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HD00-0BA1 - V1.1					
	EnableValueStatus	Boolean	Value status		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	PositionNumber	Int32	Index		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HD00-0BA1 - V1.1					
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue
	SubstituteValueAnalog	Double	Output substitute value		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current
	OperatingRange	UInt64	Output range		
				11	PlusMinus10V
				9	PlusMinus5V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue
	SubstituteValueAnalog	Double	Output substitute value		
Channel 2					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HD00-0BA1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					16	OutputSubstituteValue
		SubstituteValueAnalog	Double	Output substitute value		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					11	PlusMinus10V
					9	PlusMinus5V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 135-6HD00-0BA1 - V1.1						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					16	OutputSubstituteValue
		SubstituteValueAnalog	Double	Output substitute value		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6AA01-0BA0 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Name	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		Comment	String	Comment		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SendBreakBeforeFrameStart	Boolean	Send break before frame start		
		BreakDuration	UInt64	Break duration		
		TransmissionSendIdleLineAfterBreak	Boolean	Send idle line		
		TransmissionIdleLineTimeAfterBreak	UInt64	Duration of the idle line		
		RtsOnDelay	UInt64	RTS ON delay		
		RtsOffDelay	UInt64	RTS OFF delay		
		SendUpToAndIncludingEndDelimiter	Boolean	Send up to and including end delimiter		
		NumberOfEndDelimiters	UInt64	No. of end delimiters		
		NumberOfAppendedCharacters	UInt64	Number of appended characters		
		StartDetectionOfAReceivedFrame	UInt64	Start detection of a received frame		
					1	StartOnAnyCharacter

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6AA01-0BA0 - V2.0						
					0	StartOnSpecialCondition
		RecognizeStartWithLineBreak	Boolean	After detection of a line break		
		RecognizeStartWithIdleLine	Boolean	After detection of an idle line		
		ReceiveIdleLineTimeAfterBreak	UInt64	Duration of the idle line		
		RecognizeStartWithCharacter	Boolean	After receipt of a start character		
		RecognizeStartWithSequence	Boolean	After detection of a start sequence		
		NumberOfSequences	UInt64	Number of sequences to be defined		
					1	Value1
					2	Value2
					3	Value3
					4	Value4
		RecognizeEndWithMessageTimeout	Boolean	Recognize message end by message timeout		
		EndMessageTimeout	UInt64	Message timeout		
		RecognizeEndWithResponseTimeout	Boolean	Recognize message end by response timeout		
		EndResponseTimeout	UInt64	Response timeout		
		RecognizeEndWithDelayTime	Boolean	After character delay time elapses		
		CharacterDelayTime	UInt64	Character delay time		
		RecognizeEndWithFixedLength	Boolean	After receipt of a fixed frame length		
		MessageEndFixLength	UInt64	Frame length		
		RecognizeEndWithMaximumLength	Boolean	After receipt of a maximum number of characters		
		MessageEndMaxLength	UInt64	Frame length		
		ReadLengthFromMessage	Boolean	Read message length from message		
		OffsetLengthField	UInt64	Offset of length field in message		
		SizeLengthField	UInt64	Size of length field		
					1	Value1
					2	Value2
					4	Value4
		NumberOfCharactersNotCounted	UInt64	Number of characters not counted in length specification		
		RecognizeEndWithSequence	Boolean	After receipt of an end sequence		
		MaximumBufferedReceivedFrames	UInt64	Buffered received frames		
		PreventOverwriting	Boolean	Prevent overwriting		
		ClearReceiveBufferOnStartup	Boolean	Clear receive buffer on startup		
		Priority	UInt64	Priority		
					1	High

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6AA01-0BA0 - V2.0						
					0	Low
		WithBlockCheck	Boolean	With block check (3964R)		
		UseDefaults	Boolean	Use default values		
		ConnectionAttempts	UInt64	Connection attempts		
		TransmissionAttempts	UInt64	Transmission attempts		
		FirstEndDelimiterSender	UInt64			
		SecondEndDelimiterSender	UInt64			
		MessageStartCharacterHex	UInt64			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		CharacterDelayTime3964R	UInt64	Character delay time		
		AcknowledgmentDelay	UInt64	Acknowledgment delay		
		OperatingMode	UInt64	Specification of the operating mode		
					268	Rs232c
					25	FullDuplex4WireOperationPtPConnection
					22	FullDuplex4WireOperationMultipointMaster
					21	FullDuplex4WireOperationMultipointSlave
					20	HalfDuplex2WireOperation
		ReceiveLineInitialState	UInt64	Receive line initial state		
					0	None
					1	SignalRA5VSignalRB0VBreakDetection
					2	SignalRA0VSignalRB5V
		SerialProtocolMode	UInt64	Protocol		
					8	FreeportModbus
					7	Freeport
					49	Value3964R
		PerformanceModeActive	Boolean	Performance mode		
		BaudRate	UInt64	Data transmission rate		
					10	Value300
					12	Value600
					5	Value1200
					6	Value2400
					7	Value4800
					8	Value9600
					9	Value19200

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6AA01-0BA0 - V2.0						
					11	Value38400
					13	Value57600
					15	Value76800
					14	Value115200
					28	Value250000
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
					4	Mark
					5	Space
					6	Any
		DataBits	UInt64	Data bits		
					8	Value8
					7	Value7
		StopBits	UInt64	Stop bits		
					1	Value1
					2	Value2
		DataFlowControl	UInt64	Data flow control		
					0	None
					1	XonOrXoff
					6	HardwareRtsAlwaysOn
					5	HardwareRtsAlwaysOnIgnoreDtrDsr
					4	HardwareRtsAlwaysSwitched
		XonCharacterHex	UInt64	XON character		
		XoffCharacterHex	UInt64	XOFF character		
		WaitForXonAfterXoff	UInt64	Wait for XON after XOFF		
		DiagnosticsWireBreak	Boolean	Activate break detection		
		DiagnosticsInterrupt	Boolean	Enable diagnostics interrupt		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6AA00-0BA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	SubmoduleSlotNumber	UInt64	Slot		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	SerialProtocolMode	UInt64	Protocol		
				49	Value3964R
				8	FreeportModbus
	BaudRate	UInt64	Data transmission rate		
				11	Value38400
				13	Value57600
				15	Value76800
				14	Value115200
				10	Value300
				12	Value600
				5	Value1200

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6AA00-0BA0 - V1.0						
					6	Value2400
					7	Value4800
					8	Value9600
					9	Value19200
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
					4	Mark
					5	Space
					6	Any
		DataBits	UInt64	Data bits		
					8	Value8
					7	Value7
		StopBits	UInt64	Stop bits		
					1	Value1
					2	Value2
		DataFlowControl	UInt64	Data flow control		
					0	None
					1	XonOrXoff
					6	HardwareRtsAlwaysOn
					5	HardwareRtsAlwaysOnIgnoreDtrDsr
					4	HardwareRtsAlwaysSwitched
		XonCharacterHex	UInt64	XON character		
		XoffCharacterHex	UInt64	XOFF character		
		WaitForXonAfterXoff	UInt64	Wait for XON after XOFF		
		DiagnosticsWireBreak	Boolean	Activate break detection		
		SendBreakBeforeFrameStart	Boolean	Send break before frame start		
		BreakDuration	UInt64	Break duration		
		TransmissionSendIdleLineAfterBreak	Boolean	Send idle line		
		TransmissionIdleLineTimeAfterBreak	UInt64	Duration of the idle line		
		RtsOnDelay	UInt64	RTS ON delay		
		RtsOffDelay	UInt64	RTS OFF delay		
		SendUpToAndIncludingEndDelimiter	Boolean	Send up to and including end delimiter		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6AA00-0BA0 - V1.0						
		NumberOfEndDelimiters	UInt64	No. of end delimiters		
		FirstEndDelimiterSender	UInt64	1st end delimiter		
		SecondEndDelimiterSender	UInt64	2nd end delimiter		
		NumberOfAppendedCharacters	UInt64	Number of appended characters		
		StartDetectionOfAReceivedFrame	UInt64	Start detection of a received frame		
					1	StartOnAnyCharacter
					0	StartOnSpecialCondition
		RecognizeStartWithLineBreak	Boolean	After detection of a line break		
		RecognizeStartWithIdleLine	Boolean	After detection of an idle line		
		ReceiveIdleLineTimeAfterBreak	UInt64	Duration of the idle line		
		RecognizeStartWithCharacter	Boolean	After receipt of a start character		
		MessageStartCharacterHex	UInt64	Start character (Hex)		
		RecognizeStartWithSequence	Boolean	After detection of a start sequence		
		NumberOfSequences	UInt64	Number of sequences to be defined		
					1	Value1
					2	Value2
					3	Value3
					4	Value4
		RecognizeEndWithMessageTimeout	Boolean	Recognize message end by message timeout		
		EndMessageTimeout	UInt64	Message timeout		
		RecognizeEndWithResponseTimeout	Boolean	Recognize message end by response timeout		
		EndResponseTimeout	UInt64	Response timeout		
		RecognizeEndWithDelayTime	Boolean	After character delay time elapses		
		CharacterDelayTime	UInt64	Character delay time		
		RecognizeEndWithFixedLength	Boolean	After receipt of a fixed frame length		
		MessageEndFixLength	UInt64	Frame length		
		RecognizeEndWithMaximumLength	Boolean	After receipt of a maximum number of characters		
		MessageEndMaxLength	UInt64	Frame length		
		ReadLengthFromMessage	Boolean	Read message length from message		
		OffsetLengthField	UInt64	Offset of length field in message		
		SizeLengthField	UInt64	Size of length field		
					1	Value1
					2	Value2
					4	Value4

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6AA00-0BA0 - V1.0						
		NumberOfCharactersNotCounted	UInt64	Number of characters not counted in length specification		
		RecognizeEndWithSequence	Boolean	After receipt of an end sequence		
		MaximumBufferedReceivedFrames	UInt64	Buffered received frames		
		PreventOverwriting	Boolean	Prevent overwriting		
		ClearReceiveBufferOnStartup	Boolean	Clear receive buffer on startup		
		OperatingMode	UInt64	Specification of the operating mode		
					25	FullDuplex4WireOperationPtPConnection
					20	HalfDuplex2WireOperation
					268	Rs232c
					22	FullDuplex4WireOperationMultipointMaster
					21	FullDuplex4WireOperationMultipointSlave
		ReceiveLineInitialState	UInt64	Receive line initial state		
					0	None
					1	SignalRA5VSignalRB0VBreakDetection
					2	SignalRA0VSignalRB5V
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		Priority	UInt64	Priority		
					1	High
					0	Low
		WithBlockCheck	Boolean	With block check (3964R)		
		UseDefaults	Boolean	Use default values		
		ConnectionAttempts	UInt64	Connection attempts		
		TransmissionAttempts	UInt64	Transmission attempts		
		CharacterDelayTime3964R	UInt64	Character delay time		
		AcknowledgmentDelay	UInt64	Acknowledgment delay		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
		DiagnosticsInterrupt	Boolean	Enable diagnostics interrupt		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
Submodule Counting/Measurement					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
Channel 0					
	OperatingType	UInt64	Selection of the operating type for the channel 0		
				26	CountingOrPositionInput
				27	Measuring
	FrequencyForCapture	UInt64	Frequency of Capture function		
				0	Once
				1	Periodic
	SignalType	UInt64	Signal type		
				3	IncrementalEncoderABPhaseShifted
				4	IncrementalEncoderABN

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
		InvertDirection	Boolean	Invert direction		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
		SensorType	UInt64	Sensor type		
					10	SourcingOutput
					9	SinkingOutput
					11	PushPull
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI0	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI1	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
		FunctionDI2	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI2	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI2	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI2	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0Measuring	Double	Comparison value 0		
		ComparisonValue1Measuring	Double	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		MeasuredVariable	UInt64	Measured variable		
					0	Frequency
					1	PeriodDuration
					2	Velocity
		UpdateTime	Double	Update time		
		TimeBaseForVelocityMeasurement	UInt64	Time base for velocity measurement		
					0	Value1ms
					1	Value10ms
					2	Value100ms
					3	Value1s
					4	Value60sOr1m
		IncrementsPerUnit	UInt64	Increments per unit		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
		HardwareInterruptUnderflowActive	Boolean	InterruptAtLowerLimit		
		HardwareInterruptNewCaptureValueAvailableActive	Boolean	InterruptCapturedValueAvailable		
		HardwareInterruptSynchronizationActive	Boolean	InterruptSynchronizationOfCounterByExternal		
		HardwareInterruptGateStartActive	Boolean	InterruptGateStart		
		HardwareInterruptGateStopActive	Boolean	InterruptGateStop		
		HardwareInterruptOverflowActive	Boolean	InterruptAtUpperLimit		
		HardwareInterruptDirectionReversalActive	Boolean	InterruptDirectionChanged		
		HardwareInterruptZeroCrossingActive	Boolean	InterruptZeroCrossing		
		HardwareInterruptDQ0CompareActive	Boolean	HWInterruptDO0Compare		
		HardwareInterruptDQ1CompareActive	Boolean	HWInterruptDO1Compare		
		HardwareInterruptNewCaptureValueAvailableEvent	String	*HardwareInterruptCapturedValueAvailableEventName		
		HardwareInterruptNewCaptureValueAvailableInterr	Object	*HardwareInterruptCapturedValueAvailableInterrupt		
		HardwareInterruptNewCaptureValueAvailablePriori	UInt64	*HardwareInterruptCapturedValueAvailablePriority		
		HardwareInterruptDirectionReversalEventName	String	*HardwareInterruptDirectionChangedEventName		
		HardwareInterruptDirectionReversalInterrupt	Object	*HardwareInterruptDirectionChangedInterrupt		
		HardwareInterruptDirectionReversalPriority	UInt64	*HardwareInterruptDirectionChangedPriority		
		HardwareInterruptDQ0CompareEventName	String	*HardwareInterruptDQ0CompareEventName		
		HardwareInterruptDQ0CompareInterrupt	Object	*HardwareInterruptDQ0CompareInterrupt		
		HardwareInterruptDQ0ComparePriority	UInt64	*HardwareInterruptDQ0ComparePriority		
		HardwareInterruptDQ1CompareEventName	String	*HardwareInterruptDQ1CompareEventName		
		HardwareInterruptDQ1CompareInterrupt	Object	*HardwareInterruptDQ1CompareInterrupt		
		HardwareInterruptDQ1ComparePriority	UInt64	*HardwareInterruptDQ1ComparePriority		
		HardwareInterruptGateStartEventName	String	*HardwareInterruptGateStartEventName		
		HardwareInterruptGateStartInterrupt	Object	*HardwareInterruptGateStartInterrupt		
		HardwareInterruptGateStartPriority	UInt64	*HardwareInterruptGateStartPriority		
		HardwareInterruptGateStopEventName	String	*HardwareInterruptGateStopEventName		
		HardwareInterruptGateStopInterrupt	Object	*HardwareInterruptGateStopInterrupt		
		HardwareInterruptGateStopPriority	UInt64	*HardwareInterruptGateStopPriority		
		HardwareInterruptOverflowEventName	String	*HardwareInterruptOverflowEventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
		HardwareInterruptOverflowInterrupt	Object	*HardwareInterruptOverflowInterrupt		
		HardwareInterruptOverflowPriority	UInt64	*HardwareInterruptOverflowPriority		
		HardwareInterruptSynchronizationEventName	String	*HardwareInterruptSynchronizationEventName		
		HardwareInterruptSynchronizationInterrupt	Object	*HardwareInterruptSynchronizationInterrupt		
		HardwareInterruptSynchronizationPriority	UInt64	*HardwareInterruptSynchronizationPriority		
		HardwareInterruptUnderflowEventName	String	*HardwareInterruptUnderflowEventName		
		HardwareInterruptUnderflowInterrupt	Object	*HardwareInterruptUnderflowInterrupt		
		HardwareInterruptUnderflowPriority	UInt64	*HardwareInterruptUnderflowPriority		
		HardwareInterruptZeroCrossingEventName	String	*HardwareInterruptZeroPassEventEventName		
		HardwareInterruptZeroCrossingInterrupt	Object	*HardwareInterruptZeroPassInterrupt		
		HardwareInterruptZeroCrossingPriority	UInt64	*HardwareInterruptZeroPassPriority		
	Submodule Motion Control					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
		InvertDirection	Boolean	Invert direction		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
		SensorType	UInt64	Sensor type		
					10	SourcingOutput
					9	SinkingOutput
					11	PushPull
		SignalSelectionForReferenceMark0	UInt64	Signal selection for reference mark 0		
					1	Di0
					0	SignalNOfIncrementalEncoder
		StepsPerRevolution	UInt64	Steps per revolution		
		ReferenceSpeed	Double	Reference speed		
		FineResolutionIncrementDistance	Double	Fine-resolution increment distance		
		EncoderType	UInt64	Encoder type		
					7	Linear
					8	Rotary
		DistanceBetweenIncrements	UInt64	Distance between increments:		
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		MeasuringInput	UInt64	Measuring input		
					1	DI1
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
		IncrementsPerRevolution	UInt64	Increments per revolution		
		NumberOfRevolutions	UInt64	Number of revolutions		
	Submodule Fast Mode					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3					
Channel 0					
	SignalType	UInt64	Signal type		
				3	IncrementalEncoderABPhaseShifted
				4	IncrementalEncoderABN
				1	PulseAAndDirectionB
				0	PulseA
				2	CountUpACountDownB
	InvertDirection	Boolean	Invert direction		
	SignalEvaluation	UInt64	Signal evaluation		
				0	Single
				1	Double
				2	Quadruple
	FilterFrequency	UInt64	Filter frequency		
				0	Value100Hz
				1	Value200Hz
				2	Value500Hz
				3	Value1kHz
				4	Value2kHz
				5	Value5kHz
				6	Value10kHz
				7	Value20kHz
				8	Value50kHz
				9	Value100kHz
				10	Value200kHz
	SensorType	UInt64	Sensor type		
				10	SourcingOutput
				9	SinkingOutput
				11	PushPull
	DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
	DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				16	OutputSubstituteValue
				1	KeepLastValue
				15	ContinueOperation

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountDirectionForSynchronization	UInt64	Count direction for synchronization		
					0	None
					1	Up
					2	Down
					3	InBothDirections
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		FunctionDI2	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI2	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI2	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.3						
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
Module - 6ES7 138-6AA01-0BA0 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0					
				2	StartupCpuIfMismatch
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
Submodule Counting/Measurement					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
Channel 0					
	OperatingType	UInt64	Selection of the operating type for the channel 0		
				26	CountingOrPositionInput
				27	Measuring
	FrequencyForCapture	UInt64	Frequency of Capture function		
				0	Once
				1	Periodic
	SignalType	UInt64	Signal type		
				3	IncrementalEncoderABPhaseShifted
				4	IncrementalEncoderABN
				1	PulseAAndDirectionB
				0	PulseA
				2	CountUpACountDownB
	InvertDirection	Boolean	Invert direction		
	SignalEvaluation	UInt64	Signal evaluation		
				0	Single
				1	Double
				2	Quadruple

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
		SensorType	UInt64	Sensor type		
					10	SourcingOutput
					9	SinkingOutput
					11	PushPull
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
					1	Periodic
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI0	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI1	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI2	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
		EdgeSelectionDI2	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI2	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI2	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0Measuring	Double	Comparison value 0		
		ComparisonValue1Measuring	Double	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		MeasuredVariable	UInt64	Measured variable		
					0	Frequency
					1	PeriodDuration
					2	Velocity
		UpdateTime	Double	Update time		
		TimeBaseForVelocityMeasurement	UInt64	Time base for velocity measurement		
					0	Value1ms
					1	Value10ms
					2	Value100ms
					3	Value1s
					4	Value60sOr1m
		IncrementsPerUnit	UInt64	Increments per unit		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
		HardwareInterruptUnderflowActive	Boolean	InterruptAtLowerLimit		
		HardwareInterruptNewCaptureValueAvailableActive	Boolean	InterruptCapturedValueAvailable		
		HardwareInterruptSynchronizationActive	Boolean	InterruptSynchronizationOfCounterByExternal		
		HardwareInterruptGateStartActive	Boolean	InterruptGateStart		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
		HardwareInterruptGateStopActive	Boolean	InterruptGateStop		
		HardwareInterruptOverflowActive	Boolean	InterruptAtUpperLimit		
		HardwareInterruptDirectionReversalActive	Boolean	InterruptDirectionChanged		
		HardwareInterruptZeroCrossingActive	Boolean	InterruptZeroCrossing		
		HardwareInterruptDQ0CompareActive	Boolean	HWInterruptDO0Compare		
		HardwareInterruptDQ1CompareActive	Boolean	HWInterruptDO1Compare		
		HardwareInterruptNewCaptureValueAvailableEvent	String	*HardwareInterruptCapturedValueAvailableEventName		
		HardwareInterruptNewCaptureValueAvailableInterr	Object	*HardwareInterruptCapturedValueAvailableInterrupt		
		HardwareInterruptNewCaptureValueAvailablePriori	UInt64	*HardwareInterruptCapturedValueAvailablePriority		
		HardwareInterruptDirectionReversalEventName	String	*HardwareInterruptDirectionChangedEventName		
		HardwareInterruptDirectionReversalInterrupt	Object	*HardwareInterruptDirectionChangedInterrupt		
		HardwareInterruptDirectionReversalPriority	UInt64	*HardwareInterruptDirectionChangedPriority		
		HardwareInterruptDQ0CompareEventName	String	*HardwareInterruptDQ0CompareEventName		
		HardwareInterruptDQ0CompareInterrupt	Object	*HardwareInterruptDQ0CompareInterrupt		
		HardwareInterruptDQ0ComparePriority	UInt64	*HardwareInterruptDQ0ComparePriority		
		HardwareInterruptDQ1CompareEventName	String	*HardwareInterruptDQ1CompareEventName		
		HardwareInterruptDQ1CompareInterrupt	Object	*HardwareInterruptDQ1CompareInterrupt		
		HardwareInterruptDQ1ComparePriority	UInt64	*HardwareInterruptDQ1ComparePriority		
		HardwareInterruptGateStartEventName	String	*HardwareInterruptGateStartEventName		
		HardwareInterruptGateStartInterrupt	Object	*HardwareInterruptGateStartInterrupt		
		HardwareInterruptGateStartPriority	UInt64	*HardwareInterruptGateStartPriority		
		HardwareInterruptGateStopEventName	String	*HardwareInterruptGateStopEventName		
		HardwareInterruptGateStopInterrupt	Object	*HardwareInterruptGateStopInterrupt		
		HardwareInterruptGateStopPriority	UInt64	*HardwareInterruptGateStopPriority		
		HardwareInterruptOverflowEventName	String	*HardwareInterruptOverflowEventName		
		HardwareInterruptOverflowInterrupt	Object	*HardwareInterruptOverflowInterrupt		
		HardwareInterruptOverflowPriority	UInt64	*HardwareInterruptOverflowPriority		
		HardwareInterruptSynchronizationEventName	String	*HardwareInterruptSynchronizationEventName		
		HardwareInterruptSynchronizationInterrupt	Object	*HardwareInterruptSynchronizationInterrupt		
		HardwareInterruptSynchronizationPriority	UInt64	*HardwareInterruptSynchronizationPriority		
		HardwareInterruptUnderflowEventName	String	*HardwareInterruptUnderflowEventName		
		HardwareInterruptUnderflowInterrupt	Object	*HardwareInterruptUnderflowInterrupt		
		HardwareInterruptUnderflowPriority	UInt64	*HardwareInterruptUnderflowPriority		
		HardwareInterruptZeroCrossingEventName	String	*HardwareInterruptZeroPassEventEventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
		HardwareInterruptZeroCrossingInterrupt	Object	*HardwareInterruptZeroPassInterrupt		
		HardwareInterruptZeroCrossingPriority	UInt64	*HardwareInterruptZeroPassPriority		
	Submodule Motion Control					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
		InvertDirection	Boolean	Invert direction		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
		SensorType	UInt64	Sensor type		
					10	SourcingOutput
					9	SinkingOutput
					11	PushPull

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
		SignalSelectionForReferenceMark0	UInt64	Signal selection for reference mark 0		
					1	Di0
					0	SignalNOfIncrementalEncoder
		StepsPerRevolution	UInt64	Steps per revolution		
		ReferenceSpeed	Double	Reference speed		
		FineResolutionIncrementDistance	Double	Fine-resolution increment distance		
		EncoderType	UInt64	Encoder type		
					7	Linear
					8	Rotary
		DistanceBetweenIncrements	UInt64	Distance between increments:		
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		MeasuringInput	UInt64	Measuring input		
					1	DI1
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
		IncrementsPerRevolution	UInt64	Increments per revolution		
		NumberOfRevolutions	UInt64	Number of revolutions		
	Submodule Fast Mode					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
		InvertDirection	Boolean	Invert direction		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
		SensorType	UInt64	Sensor type		
					10	SourcingOutput
					9	SinkingOutput
					11	PushPull
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountDirectionForSynchronization	UInt64	Count direction for synchronization		
					0	None
					1	Up
					2	Down
					3	InBothDirections
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		FunctionDI2	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI2	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI2	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA01-0BA0 - V2.0						
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
Module - 6ES7 138-6AA00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.0						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule Counting/Measurement					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		OperatingType	UInt64	Selection of the operating type for the channel 0		
					26	CountingOrPositionInput
					27	Measuring
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
		InvertDirection	Boolean	Invert direction		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.0						
		SensorType	UInt64	Sensor type		
					10	SourcingOutput
					9	SinkingOutput
					11	PushPull
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.0						
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI0	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.0						
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI1	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI2	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI2	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI2	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI2	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.0						
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0Measuring	Double	Comparison value 0		
		ComparisonValue1Measuring	Double	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.0						
		Hysteresis	UInt64	Hysteresis (in increments)		
		MeasuredVariable	UInt64	Measured variable		
					0	Frequency
					1	PeriodDuration
					2	Velocity
		UpdateTime	Double	Update time		
		TimeBaseForVelocityMeasurement	UInt64	Time base for velocity measurement		
					0	Value1ms
					1	Value10ms
					2	Value100ms
					3	Value1s
					4	Value60sOr1m
		IncrementsPerUnit	UInt64	Increments per unit		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
		HardwareInterruptUnderflowActive	Boolean	InterruptAtLowerLimit		
		HardwareInterruptNewCaptureValueAvailableActive	Boolean	InterruptCapturedValueAvailable		
		HardwareInterruptSynchronizationActive	Boolean	InterruptSynchronizationOfCounterByExternal		
		HardwareInterruptGateStartActive	Boolean	InterruptGateStart		
		HardwareInterruptGateStopActive	Boolean	InterruptGateStop		
		HardwareInterruptOverflowActive	Boolean	InterruptAtUpperLimit		
		HardwareInterruptDirectionReversalActive	Boolean	InterruptDirectionChanged		
		HardwareInterruptZeroCrossingActive	Boolean	InterruptZeroCrossing		
		HardwareInterruptDQ0CompareActive	Boolean	HWInterruptDO0Compare		
		HardwareInterruptDQ1CompareActive	Boolean	HWInterruptDO1Compare		
		HardwareInterruptNewCaptureValueAvailableEvent	String	*HardwareInterruptCapturedValueAvailableEventName		
		HardwareInterruptNewCaptureValueAvailableInterr	Object	*HardwareInterruptCapturedValueAvailableInterrupt		
		HardwareInterruptNewCaptureValueAvailablePriori	UInt64	*HardwareInterruptCapturedValueAvailablePriority		
		HardwareInterruptDirectionReversalEventName	String	*HardwareInterruptDirectionChangedEventName		
		HardwareInterruptDirectionReversalInterrupt	Object	*HardwareInterruptDirectionChangedInterrupt		
		HardwareInterruptDirectionReversalPriority	UInt64	*HardwareInterruptDirectionChangedPriority		
		HardwareInterruptDQ0CompareEventName	String	*HardwareInterruptDQ0CompareEventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.0						
		HardwareInterruptDQ0CompareInterrupt	Object	*HardwareInterruptDQ0CompareInterrupt		
		HardwareInterruptDQ0ComparePriority	UInt64	*HardwareInterruptDQ0ComparePriority		
		HardwareInterruptDQ1CompareEventName	String	*HardwareInterruptDQ1CompareEventName		
		HardwareInterruptDQ1CompareInterrupt	Object	*HardwareInterruptDQ1CompareInterrupt		
		HardwareInterruptDQ1ComparePriority	UInt64	*HardwareInterruptDQ1ComparePriority		
		HardwareInterruptGateStartEventName	String	*HardwareInterruptGateStartEventName		
		HardwareInterruptGateStartInterrupt	Object	*HardwareInterruptGateStartInterrupt		
		HardwareInterruptGateStartPriority	UInt64	*HardwareInterruptGateStartPriority		
		HardwareInterruptGateStopEventName	String	*HardwareInterruptGateStopEventName		
		HardwareInterruptGateStopInterrupt	Object	*HardwareInterruptGateStopInterrupt		
		HardwareInterruptGateStopPriority	UInt64	*HardwareInterruptGateStopPriority		
		HardwareInterruptOverflowEventName	String	*HardwareInterruptOverflowEventName		
		HardwareInterruptOverflowInterrupt	Object	*HardwareInterruptOverflowInterrupt		
		HardwareInterruptOverflowPriority	UInt64	*HardwareInterruptOverflowPriority		
		HardwareInterruptSynchronizationEventName	String	*HardwareInterruptSynchronizationEventName		
		HardwareInterruptSynchronizationInterrupt	Object	*HardwareInterruptSynchronizationInterrupt		
		HardwareInterruptSynchronizationPriority	UInt64	*HardwareInterruptSynchronizationPriority		
		HardwareInterruptUnderflowEventName	String	*HardwareInterruptUnderflowEventName		
		HardwareInterruptUnderflowInterrupt	Object	*HardwareInterruptUnderflowInterrupt		
		HardwareInterruptUnderflowPriority	UInt64	*HardwareInterruptUnderflowPriority		
		HardwareInterruptZeroCrossingEventName	String	*HardwareInterruptZeroPassEventEventName		
		HardwareInterruptZeroCrossingInterrupt	Object	*HardwareInterruptZeroPassInterrupt		
		HardwareInterruptZeroCrossingPriority	UInt64	*HardwareInterruptZeroPassPriority		
	Submodule Motion Control					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.0						
		InvertDirection	Boolean	Invert direction		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
		SensorType	UInt64	Sensor type		
					10	SourcingOutput
					9	SinkingOutput
					11	PushPull
		SignalSelectionForReferenceMark0	UInt64	Signal selection for reference mark 0		
					1	Di0
					0	SignalNOfIncrementalEncoder
		StepsPerRevolution	UInt64	Steps per revolution		
		FineResolutionIncrementDistance	Double	Fine-resolution increment distance		
		EncoderType	UInt64	Encoder type		
					7	Linear
					8	Rotary
		DistanceBetweenIncrements	UInt64	Distance between increments:		
		ReferenceSpeed	Double	Reference speed		
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.0						
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
		IncrementsPerRevolution	UInt64	Increments per revolution		
		NumberOfRevolutions	UInt64	Number of revolutions		
Module - 6ES7 138-6AA00-0BA0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule Counting/Measurement					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		OperatingType	UInt64	Selection of the operating type for the channel 0		
					26	CountingOrPositionInput

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.1						
					27	Measuring
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
		InvertDirection	Boolean	Invert direction		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
		SensorType	UInt64	Sensor type		
					10	SourcingOutput
					9	SinkingOutput
					11	PushPull
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.1						
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.1						
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI0	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.1						
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI1	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI2	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI2	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI2	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI2	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0Measuring	Double	Comparison value 0		
		ComparisonValue1Measuring	Double	Comparison value 1		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.1						
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue 1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		MeasuredVariable	UInt64	Measured variable		
					0	Frequency
					1	PeriodDuration
					2	Velocity
		UpdateTime	Double	Update time		
		TimeBaseForVelocityMeasurement	UInt64	Time base for velocity measurement		
					0	Value1ms
					1	Value10ms
					2	Value100ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.1						
					3	Value1s
					4	Value60sOr1m
		IncrementsPerUnit	UInt64	Increments per unit		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
		HardwareInterruptUnderflowActive	Boolean	InterruptAtLowerLimit		
		HardwareInterruptNewCaptureValueAvailableActive	Boolean	InterruptCapturedValueAvailable		
		HardwareInterruptSynchronizationActive	Boolean	InterruptSynchronizationOfCounterByExternal		
		HardwareInterruptGateStartActive	Boolean	InterruptGateStart		
		HardwareInterruptGateStopActive	Boolean	InterruptGateStop		
		HardwareInterruptOverflowActive	Boolean	InterruptAtUpperLimit		
		HardwareInterruptDirectionReversalActive	Boolean	InterruptDirectionChanged		
		HardwareInterruptZeroCrossingActive	Boolean	InterruptZeroCrossing		
		HardwareInterruptDQ0CompareActive	Boolean	HWInterruptDO0Compare		
		HardwareInterruptDQ1CompareActive	Boolean	HWInterruptDO1Compare		
		HardwareInterruptNewCaptureValueAvailableEvent	String	*HardwareInterruptCapturedValueAvailableEventName		
		HardwareInterruptNewCaptureValueAvailableInterr	Object	*HardwareInterruptCapturedValueAvailableInterrupt		
		HardwareInterruptNewCaptureValueAvailablePriori	UInt64	*HardwareInterruptCapturedValueAvailablePriority		
		HardwareInterruptDirectionReversalEventName	String	*HardwareInterruptDirectionChangedEventName		
		HardwareInterruptDirectionReversalInterrupt	Object	*HardwareInterruptDirectionChangedInterrupt		
		HardwareInterruptDirectionReversalPriority	UInt64	*HardwareInterruptDirectionChangedPriority		
		HardwareInterruptDQ0CompareEventName	String	*HardwareInterruptDQ0CompareEventName		
		HardwareInterruptDQ0CompareInterrupt	Object	*HardwareInterruptDQ0CompareInterrupt		
		HardwareInterruptDQ0ComparePriority	UInt64	*HardwareInterruptDQ0ComparePriority		
		HardwareInterruptDQ1CompareEventName	String	*HardwareInterruptDQ1CompareEventName		
		HardwareInterruptDQ1CompareInterrupt	Object	*HardwareInterruptDQ1CompareInterrupt		
		HardwareInterruptDQ1ComparePriority	UInt64	*HardwareInterruptDQ1ComparePriority		
		HardwareInterruptGateStartEventName	String	*HardwareInterruptGateStartEventName		
		HardwareInterruptGateStartInterrupt	Object	*HardwareInterruptGateStartInterrupt		
		HardwareInterruptGateStartPriority	UInt64	*HardwareInterruptGateStartPriority		
		HardwareInterruptGateStopEventName	String	*HardwareInterruptGateStopEventName		
		HardwareInterruptGateStopInterrupt	Object	*HardwareInterruptGateStopInterrupt		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.1						
		HardwareInterruptGateStopPriority	UInt64	*HardwareInterruptGateStopPriority		
		HardwareInterruptOverflowEventName	String	*HardwareInterruptOverflowEventName		
		HardwareInterruptOverflowInterrupt	Object	*HardwareInterruptOverflowInterrupt		
		HardwareInterruptOverflowPriority	UInt64	*HardwareInterruptOverflowPriority		
		HardwareInterruptSynchronizationEventName	String	*HardwareInterruptSynchronizationEventName		
		HardwareInterruptSynchronizationInterrupt	Object	*HardwareInterruptSynchronizationInterrupt		
		HardwareInterruptSynchronizationPriority	UInt64	*HardwareInterruptSynchronizationPriority		
		HardwareInterruptUnderflowEventName	String	*HardwareInterruptUnderflowEventName		
		HardwareInterruptUnderflowInterrupt	Object	*HardwareInterruptUnderflowInterrupt		
		HardwareInterruptUnderflowPriority	UInt64	*HardwareInterruptUnderflowPriority		
		HardwareInterruptZeroCrossingEventName	String	*HardwareInterruptZeroPassEventEventName		
		HardwareInterruptZeroCrossingInterrupt	Object	*HardwareInterruptZeroPassInterrupt		
		HardwareInterruptZeroCrossingPriority	UInt64	*HardwareInterruptZeroPassPriority		
	Submodule Motion Control					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
		InvertDirection	Boolean	Invert direction		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.1						
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
		SensorType	UInt64	Sensor type		
					10	SourcingOutput
					9	SinkingOutput
					11	PushPull
		SignalSelectionForReferenceMark0	UInt64	Signal selection for reference mark 0		
					1	Di0
					0	SignalNOfIncrementalEncoder
		StepsPerRevolution	UInt64	Steps per revolution		
		FineResolutionIncrementDistance	Double	Fine-resolution increment distance		
		EncoderType	UInt64	Encoder type		
					7	Linear
					8	Rotary
		DistanceBetweenIncrements	UInt64	Distance between increments:		
		ReferenceSpeed	Double	Reference speed		
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
		IncrementsPerRevolution	UInt64	Increments per revolution		
		NumberOfRevolutions	UInt64	Number of revolutions		
Module - 6ES7 138-6AA00-0BA0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule Counting/Measurement					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		OperatingType	UInt64	Selection of the operating type for the channel 0		
					26	CountingOrPositionInput
					27	Measuring
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
		InvertDirection	Boolean	Invert direction		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
		SensorType	UInt64	Sensor type		
					10	SourcingOutput
					9	SinkingOutput
					11	PushPull
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI0	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI1	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI2	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI2	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI2	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI2	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0Measuring	Double	Comparison value 0		
		ComparisonValue1Measuring	Double	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		MeasuredVariable	UInt64	Measured variable		
					0	Frequency
					1	PeriodDuration
					2	Velocity
		UpdateTime	Double	Update time		
		TimeBaseForVelocityMeasurement	UInt64	Time base for velocity measurement		
					0	Value1ms
					1	Value10ms
					2	Value100ms
					3	Value1s
					4	Value60sOr1m
		IncrementsPerUnit	UInt64	Increments per unit		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
		HardwareInterruptUnderflowActive	Boolean	InterruptAtLowerLimit		
		HardwareInterruptNewCaptureValueAvailableActive	Boolean	InterruptCapturedValueAvailable		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
		HardwareInterruptSynchronizationActive	Boolean	InterruptSynchronizationOfCounterByExternal		
		HardwareInterruptGateStartActive	Boolean	InterruptGateStart		
		HardwareInterruptGateStopActive	Boolean	InterruptGateStop		
		HardwareInterruptOverflowActive	Boolean	InterruptAtUpperLimit		
		HardwareInterruptDirectionReversalActive	Boolean	InterruptDirectionChanged		
		HardwareInterruptZeroCrossingActive	Boolean	InterruptZeroCrossing		
		HardwareInterruptDQ0CompareActive	Boolean	HWInterruptDO0Compare		
		HardwareInterruptDQ1CompareActive	Boolean	HWInterruptDO1Compare		
		HardwareInterruptNewCaptureValueAvailableEvent	String	*HardwareInterruptCapturedValueAvailableEventName		
		HardwareInterruptNewCaptureValueAvailableInterr	Object	*HardwareInterruptCapturedValueAvailableInterrupt		
		HardwareInterruptNewCaptureValueAvailablePriori	UInt64	*HardwareInterruptCapturedValueAvailablePriority		
		HardwareInterruptDirectionReversalEventName	String	*HardwareInterruptDirectionChangedEventName		
		HardwareInterruptDirectionReversalInterrupt	Object	*HardwareInterruptDirectionChangedInterrupt		
		HardwareInterruptDirectionReversalPriority	UInt64	*HardwareInterruptDirectionChangedPriority		
		HardwareInterruptDQ0CompareEventName	String	*HardwareInterruptDQ0CompareEventName		
		HardwareInterruptDQ0CompareInterrupt	Object	*HardwareInterruptDQ0CompareInterrupt		
		HardwareInterruptDQ0ComparePriority	UInt64	*HardwareInterruptDQ0ComparePriority		
		HardwareInterruptDQ1CompareEventName	String	*HardwareInterruptDQ1CompareEventName		
		HardwareInterruptDQ1CompareInterrupt	Object	*HardwareInterruptDQ1CompareInterrupt		
		HardwareInterruptDQ1ComparePriority	UInt64	*HardwareInterruptDQ1ComparePriority		
		HardwareInterruptGateStartEventName	String	*HardwareInterruptGateStartEventName		
		HardwareInterruptGateStartInterrupt	Object	*HardwareInterruptGateStartInterrupt		
		HardwareInterruptGateStartPriority	UInt64	*HardwareInterruptGateStartPriority		
		HardwareInterruptGateStopEventName	String	*HardwareInterruptGateStopEventName		
		HardwareInterruptGateStopInterrupt	Object	*HardwareInterruptGateStopInterrupt		
		HardwareInterruptGateStopPriority	UInt64	*HardwareInterruptGateStopPriority		
		HardwareInterruptOverflowEventName	String	*HardwareInterruptOverflowEventName		
		HardwareInterruptOverflowInterrupt	Object	*HardwareInterruptOverflowInterrupt		
		HardwareInterruptOverflowPriority	UInt64	*HardwareInterruptOverflowPriority		
		HardwareInterruptSynchronizationEventName	String	*HardwareInterruptSynchronizationEventName		
		HardwareInterruptSynchronizationInterrupt	Object	*HardwareInterruptSynchronizationInterrupt		
		HardwareInterruptSynchronizationPriority	UInt64	*HardwareInterruptSynchronizationPriority		
		HardwareInterruptUnderflowEventName	String	*HardwareInterruptUnderflowEventName		
		HardwareInterruptUnderflowInterrupt	Object	*HardwareInterruptUnderflowInterrupt		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
		HardwareInterruptUnderflowPriority	UInt64	*HardwareInterruptUnderflowPriority		
		HardwareInterruptZeroCrossingEventName	String	*HardwareInterruptZeroPassEventEventName		
		HardwareInterruptZeroCrossingInterrupt	Object	*HardwareInterruptZeroPassInterrupt		
		HardwareInterruptZeroCrossingPriority	UInt64	*HardwareInterruptZeroPassPriority		
	Submodule Motion Control					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
		InvertDirection	Boolean	Invert direction		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
		SensorType	UInt64	Sensor type		
					10	SourcingOutput

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
					9	SinkingOutput
					11	PushPull
		SignalSelectionForReferenceMark0	UInt64	Signal selection for reference mark 0		
					1	Di0
					0	SignalNOfIncrementalEncoder
		StepsPerRevolution	UInt64	Steps per revolution		
		ReferenceSpeed	Double	Reference speed		
		FineResolutionIncrementDistance	Double	Fine-resolution increment distance		
		EncoderType	UInt64	Encoder type		
					7	Linear
					8	Rotary
		DistanceBetweenIncrements	UInt64	Distance between increments:		
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
		IncrementsPerRevolution	UInt64	Increments per revolution		
		NumberOfRevolutions	UInt64	Number of revolutions		
	Submodule Fast Mode					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
		InvertDirection	Boolean	Invert direction		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
		SensorType	UInt64	Sensor type		
					10	SourcingOutput
					9	SinkingOutput
					11	PushPull
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountDirectionForSynchronization	UInt64	Count direction for synchronization		
					0	None
					1	Up
					2	Down
					3	InBothDirections
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		FunctionDI2	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI2	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI2	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6AA00-0BA0 - V1.2						
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
Module - 6ES7 138-6BA00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule Counting/Measurement					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		OperatingType	UInt64	Selection of the operating type for the channel 0		
					26	CountingOrPositionInput
					27	Measuring
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
					5	AbsoluteEncoderSsi
		InvertDirection	Boolean	Invert direction		
		FrameLength	UInt64	Frame length		
					10	Value10Bit
					11	Value11Bit
					12	Value12Bit
					13	Value13Bit
					14	Value14Bit
					15	Value15Bit
					16	Value16Bit
					17	Value17Bit
					18	Value18Bit
					19	Value19Bit
					20	Value20Bit
					21	Value21Bit
					22	Value22Bit
					23	Value23Bit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
					24	Value24Bit
					25	Value25Bit
					26	Value26Bit
					27	Value27Bit
					28	Value28Bit
					29	Value29Bit
					30	Value30Bit
					31	Value31Bit
					32	Value32Bit
					33	Value33Bit
					34	Value34Bit
					35	Value35Bit
					36	Value36Bit
					37	Value37Bit
					38	Value38Bit
					39	Value39Bit
					40	Value40Bit
		CodeType	UInt64	Code type		
					0	Gray
					1	Dual
		TransmissionRate	UInt64	Transmission rate		
					0	Value125kHz
					1	Value250kHz
					2	Value500kHz
					3	Value1MHz
					4	Value15MHz
					5	Value2MHz
		MonoflopTime	UInt64	Monoflop time		
					4	Automatically
					0	Value16
					1	Value32
					2	Value48
					3	Value64

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
		BitNumberLsbOfPositionValue	UInt64	Bit number LSB of the position value		
		BitNumberMsbOfPositionValue	UInt64	Bit number MSB of the position value		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
					11	Value500kHz
					12	Value1MHz
		InterfaceStandard	UInt64	Interface standard		
					0	Rs422Symmetrical
					1	Ttl5VAsymmetrical
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI0	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI1	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0Measuring	Double	Comparison value 0		
		ComparisonValue1Measuring	Double	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		MeasuredVariable	UInt64	Measured variable		
					0	Frequency
					1	PeriodDuration
					2	Velocity
					3	CompleteSsiFrame
		UpdateTime	Double	Update time		
		TimeBaseForVelocityMeasurement	UInt64	Time base for velocity measurement		
					0	Value1ms
					1	Value10ms
					2	Value100ms
					3	Value1s
					4	Value60sOr1m
		IncrementsPerUnit	UInt64	Increments per unit		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
		HardwareInterruptUnderflowActive	Boolean	InterruptAtLowerLimit		
		HardwareInterruptNewCaptureValueAvailableActive	Boolean	InterruptCapturedValueAvailable		
		HardwareInterruptSynchronizationActive	Boolean	InterruptSynchronizationOfCounterByExternal		
		HardwareInterruptGateStartActive	Boolean	InterruptGateStart		
		HardwareInterruptGateStopActive	Boolean	InterruptGateStop		
		HardwareInterruptOverflowActive	Boolean	InterruptAtUpperLimit		
		HardwareInterruptDirectionReversalActive	Boolean	InterruptDirectionChanged		
		HardwareInterruptZeroCrossingActive	Boolean	InterruptZeroCrossing		
		HardwareInterruptDQ0CompareActive	Boolean	HWInterruptDO0Compare		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
		HardwareInterruptDQ1CompareActive	Boolean	HWInterruptDO1Compare		
		HardwareInterruptNewCaptureValueAvailableEvent	String	*HardwareInterruptCapturedValueAvailableEventName		
		HardwareInterruptNewCaptureValueAvailableInterr	Object	*HardwareInterruptCapturedValueAvailableInterrupt		
		HardwareInterruptNewCaptureValueAvailablePriori	UInt64	*HardwareInterruptCapturedValueAvailablePriority		
		HardwareInterruptDirectionReversalEventName	String	*HardwareInterruptDirectionChangedEventName		
		HardwareInterruptDirectionReversalInterrupt	Object	*HardwareInterruptDirectionChangedInterrupt		
		HardwareInterruptDirectionReversalPriority	UInt64	*HardwareInterruptDirectionChangedPriority		
		HardwareInterruptDQ0CompareEventName	String	*HardwareInterruptDQ0CompareEventName		
		HardwareInterruptDQ0CompareInterrupt	Object	*HardwareInterruptDQ0CompareInterrupt		
		HardwareInterruptDQ0ComparePriority	UInt64	*HardwareInterruptDQ0ComparePriority		
		HardwareInterruptDQ1CompareEventName	String	*HardwareInterruptDQ1CompareEventName		
		HardwareInterruptDQ1CompareInterrupt	Object	*HardwareInterruptDQ1CompareInterrupt		
		HardwareInterruptDQ1ComparePriority	UInt64	*HardwareInterruptDQ1ComparePriority		
		HardwareInterruptGateStartEventName	String	*HardwareInterruptGateStartEventName		
		HardwareInterruptGateStartInterrupt	Object	*HardwareInterruptGateStartInterrupt		
		HardwareInterruptGateStartPriority	UInt64	*HardwareInterruptGateStartPriority		
		HardwareInterruptGateStopEventName	String	*HardwareInterruptGateStopEventName		
		HardwareInterruptGateStopInterrupt	Object	*HardwareInterruptGateStopInterrupt		
		HardwareInterruptGateStopPriority	UInt64	*HardwareInterruptGateStopPriority		
		HardwareInterruptOverflowEventName	String	*HardwareInterruptOverflowEventName		
		HardwareInterruptOverflowInterrupt	Object	*HardwareInterruptOverflowInterrupt		
		HardwareInterruptOverflowPriority	UInt64	*HardwareInterruptOverflowPriority		
		HardwareInterruptSynchronizationEventName	String	*HardwareInterruptSynchronizationEventName		
		HardwareInterruptSynchronizationInterrupt	Object	*HardwareInterruptSynchronizationInterrupt		
		HardwareInterruptSynchronizationPriority	UInt64	*HardwareInterruptSynchronizationPriority		
		HardwareInterruptUnderflowEventName	String	*HardwareInterruptUnderflowEventName		
		HardwareInterruptUnderflowInterrupt	Object	*HardwareInterruptUnderflowInterrupt		
		HardwareInterruptUnderflowPriority	UInt64	*HardwareInterruptUnderflowPriority		
		HardwareInterruptZeroCrossingEventName	String	*HardwareInterruptZeroPassEventEventName		
		HardwareInterruptZeroCrossingInterrupt	Object	*HardwareInterruptZeroPassInterrupt		
		HardwareInterruptZeroCrossingPriority	UInt64	*HardwareInterruptZeroPassPriority		
	Submodule Motion Control					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
					5	AbsoluteEncoderSsi
		InvertDirection	Boolean	Invert direction		
		FrameLength	UInt64	Frame length		
					10	Value10Bit
					11	Value11Bit
					12	Value12Bit
					13	Value13Bit
					14	Value14Bit
					15	Value15Bit
					16	Value16Bit
					17	Value17Bit
					18	Value18Bit
					19	Value19Bit
					20	Value20Bit
					21	Value21Bit
					22	Value22Bit
					23	Value23Bit
					24	Value24Bit
					25	Value25Bit
					26	Value26Bit
					27	Value27Bit
					28	Value28Bit
					29	Value29Bit
					30	Value30Bit
					31	Value31Bit
					32	Value32Bit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
					33	Value33Bit
					34	Value34Bit
					35	Value35Bit
					36	Value36Bit
					37	Value37Bit
					38	Value38Bit
					39	Value39Bit
					40	Value40Bit
		CodeType	UInt64	Code type		
					0	Gray
					1	Dual
		TransmissionRate	UInt64	Transmission rate		
					0	Value125kHz
					1	Value250kHz
					2	Value500kHz
					3	Value1MHz
					4	Value15MHz
					5	Value2MHz
		MonoflopTime	UInt64	Monoflop time		
					4	Automatically
					0	Value16
					1	Value32
					2	Value48
					3	Value64
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
		BitNumberLsbOfPositionValue	UInt64	Bit number LSB of the position value		
		BitNumberMsbOfPositionValue	UInt64	Bit number MSB of the position value		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
					11	Value500kHz
					12	Value1MHz
		SignalSelectionForReferenceMark0	UInt64	Signal selection for reference mark 0		
					1	Di0
					0	SignalNOfIncrementalEncoder
		InterfaceStandard	UInt64	Interface standard		
					0	Rs422Symmetrical
					1	Ttl5VAsymmetrical
		StepsPerRevolution	UInt64	Steps per revolution		
		ReferenceSpeed	Double	Reference speed		
		FineResolutionIncrementDistance	Double	Fine-resolution increment distance		
		EncoderType	UInt64	Encoder type		
					7	Linear
					8	Rotary
		DistanceBetweenIncrements	UInt64	Distance between increments:		
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
		IncrementsPerRevolution	UInt64	Increments per revolution		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.0						
		NumberOfRevolutions	UInt64	Number of revolutions		
Module - 6ES7 138-6BA00-0BA0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule Counting/Measurement					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		OperatingType	UInt64	Selection of the operating type for the channel 0		
					26	CountingOrPositionInput
					27	Measuring
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.1						
					0	PulseA
					2	CountUpACountDownB
					5	AbsoluteEncoderSsi
		InvertDirection	Boolean	Invert direction		
		FrameLength	UInt64	Frame length		
					10	Value10Bit
					11	Value11Bit
					12	Value12Bit
					13	Value13Bit
					14	Value14Bit
					15	Value15Bit
					16	Value16Bit
					17	Value17Bit
					18	Value18Bit
					19	Value19Bit
					20	Value20Bit
					21	Value21Bit
					22	Value22Bit
					23	Value23Bit
					24	Value24Bit
					25	Value25Bit
					26	Value26Bit
					27	Value27Bit
					28	Value28Bit
					29	Value29Bit
					30	Value30Bit
					31	Value31Bit
					32	Value32Bit
					33	Value33Bit
					34	Value34Bit
					35	Value35Bit
					36	Value36Bit
					37	Value37Bit
					38	Value38Bit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.1						
					39	Value39Bit
					40	Value40Bit
		CodeType	UInt64	Code type		
					0	Gray
					1	Dual
		TransmissionRate	UInt64	Transmission rate		
					0	Value125kHz
					1	Value250kHz
					2	Value500kHz
					3	Value1MHz
					4	Value15MHz
					5	Value2MHz
		MonoflopTime	UInt64	Monoflop time		
					4	Automatically
					0	Value16
					1	Value32
					2	Value48
					3	Value64
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
		BitNumberLsbOfPositionValue	UInt64	Bit number LSB of the position value		
		BitNumberMsbOfPositionValue	UInt64	Bit number MSB of the position value		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.1						
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
					11	Value500kHz
					12	Value1MHz
		InterfaceStandard	UInt64	Interface standard		
					0	Rs422Symmetrical
					1	Ttl5VAsymmetrical
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.1						
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.1						
		BehaviorOfCounterValueAfterCaptureDI0	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI1	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0Measuring	Double	Comparison value 0		
		ComparisonValue1Measuring	Double	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.1						
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		MeasuredVariable	UInt64	Measured variable		
					0	Frequency
					1	PeriodDuration
					2	Velocity
					3	CompleteSsiFrame
		UpdateTime	Double	Update time		
		TimeBaseForVelocityMeasurement	UInt64	Time base for velocity measurement		
					0	Value1ms
					1	Value10ms
					2	Value100ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.1						
					3	Value1s
					4	Value60sOr1m
		IncrementsPerUnit	UInt64	Increments per unit		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
		HardwareInterruptUnderflowActive	Boolean	InterruptAtLowerLimit		
		HardwareInterruptNewCaptureValueAvailableActive	Boolean	InterruptCapturedValueAvailable		
		HardwareInterruptSynchronizationActive	Boolean	InterruptSynchronizationOfCounterByExternal		
		HardwareInterruptGateStartActive	Boolean	InterruptGateStart		
		HardwareInterruptGateStopActive	Boolean	InterruptGateStop		
		HardwareInterruptOverflowActive	Boolean	InterruptAtUpperLimit		
		HardwareInterruptDirectionReversalActive	Boolean	InterruptDirectionChanged		
		HardwareInterruptZeroCrossingActive	Boolean	InterruptZeroCrossing		
		HardwareInterruptDQ0CompareActive	Boolean	HWInterruptDO0Compare		
		HardwareInterruptDQ1CompareActive	Boolean	HWInterruptDO1Compare		
		HardwareInterruptNewCaptureValueAvailableEvent	String	*HardwareInterruptCapturedValueAvailableEventName		
		HardwareInterruptNewCaptureValueAvailableInterr	Object	*HardwareInterruptCapturedValueAvailableInterrupt		
		HardwareInterruptNewCaptureValueAvailablePriori	UInt64	*HardwareInterruptCapturedValueAvailablePriority		
		HardwareInterruptDirectionReversalEventName	String	*HardwareInterruptDirectionChangedEventName		
		HardwareInterruptDirectionReversalInterrupt	Object	*HardwareInterruptDirectionChangedInterrupt		
		HardwareInterruptDirectionReversalPriority	UInt64	*HardwareInterruptDirectionChangedPriority		
		HardwareInterruptDQ0CompareEventName	String	*HardwareInterruptDQ0CompareEventName		
		HardwareInterruptDQ0CompareInterrupt	Object	*HardwareInterruptDQ0CompareInterrupt		
		HardwareInterruptDQ0ComparePriority	UInt64	*HardwareInterruptDQ0ComparePriority		
		HardwareInterruptDQ1CompareEventName	String	*HardwareInterruptDQ1CompareEventName		
		HardwareInterruptDQ1CompareInterrupt	Object	*HardwareInterruptDQ1CompareInterrupt		
		HardwareInterruptDQ1ComparePriority	UInt64	*HardwareInterruptDQ1ComparePriority		
		HardwareInterruptGateStartEventName	String	*HardwareInterruptGateStartEventName		
		HardwareInterruptGateStartInterrupt	Object	*HardwareInterruptGateStartInterrupt		
		HardwareInterruptGateStartPriority	UInt64	*HardwareInterruptGateStartPriority		
		HardwareInterruptGateStopEventName	String	*HardwareInterruptGateStopEventName		
		HardwareInterruptGateStopInterrupt	Object	*HardwareInterruptGateStopInterrupt		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.1						
		HardwareInterruptGateStopPriority	UInt64	*HardwareInterruptGateStopPriority		
		HardwareInterruptOverflowEventName	String	*HardwareInterruptOverflowEventName		
		HardwareInterruptOverflowInterrupt	Object	*HardwareInterruptOverflowInterrupt		
		HardwareInterruptOverflowPriority	UInt64	*HardwareInterruptOverflowPriority		
		HardwareInterruptSynchronizationEventName	String	*HardwareInterruptSynchronizationEventName		
		HardwareInterruptSynchronizationInterrupt	Object	*HardwareInterruptSynchronizationInterrupt		
		HardwareInterruptSynchronizationPriority	UInt64	*HardwareInterruptSynchronizationPriority		
		HardwareInterruptUnderflowEventName	String	*HardwareInterruptUnderflowEventName		
		HardwareInterruptUnderflowInterrupt	Object	*HardwareInterruptUnderflowInterrupt		
		HardwareInterruptUnderflowPriority	UInt64	*HardwareInterruptUnderflowPriority		
		HardwareInterruptZeroCrossingEventName	String	*HardwareInterruptZeroPassEventEventName		
		HardwareInterruptZeroCrossingInterrupt	Object	*HardwareInterruptZeroPassInterrupt		
		HardwareInterruptZeroCrossingPriority	UInt64	*HardwareInterruptZeroPassPriority		
	Submodule Motion Control					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
					5	AbsoluteEncoderSsi
		InvertDirection	Boolean	Invert direction		
		FrameLength	UInt64	Frame length		
					10	Value10Bit
					11	Value11Bit
					12	Value12Bit
					13	Value13Bit
					14	Value14Bit
					15	Value15Bit
					16	Value16Bit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.1						
					17	Value17Bit
					18	Value18Bit
					19	Value19Bit
					20	Value20Bit
					21	Value21Bit
					22	Value22Bit
					23	Value23Bit
					24	Value24Bit
					25	Value25Bit
					26	Value26Bit
					27	Value27Bit
					28	Value28Bit
					29	Value29Bit
					30	Value30Bit
					31	Value31Bit
					32	Value32Bit
					33	Value33Bit
					34	Value34Bit
					35	Value35Bit
					36	Value36Bit
					37	Value37Bit
					38	Value38Bit
					39	Value39Bit
					40	Value40Bit
		CodeType	UInt64	Code type		
					0	Gray
					1	Dual
		TransmissionRate	UInt64	Transmission rate		
					0	Value125kHz
					1	Value250kHz
					2	Value500kHz
					3	Value1MHz
					4	Value15MHz
					5	Value2MHz

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.1						
		MonoflopTime	UInt64	Monoflop time		
					4	Automatically
					0	Value16
					1	Value32
					2	Value48
					3	Value64
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
		BitNumberLsbOfPositionValue	UInt64	Bit number LSB of the position value		
		BitNumberMsbOfPositionValue	UInt64	Bit number MSB of the position value		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
					11	Value500kHz
					12	Value1MHz
		SignalSelectionForReferenceMark0	UInt64	Signal selection for reference mark 0		
					1	Di0
					0	SignalNOfIncrementalEncoder

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.1						
		InterfaceStandard	UInt64	Interface standard		
					0	Rs422Symmetrical
					1	Ttl5VAsymmetrical
		StepsPerRevolution	UInt64	Steps per revolution		
		ReferenceSpeed	Double	Reference speed		
		FineResolutionIncrementDistance	Double	Fine-resolution increment distance		
		EncoderType	UInt64	Encoder type		
					7	Linear
					8	Rotary
		DistanceBetweenIncrements	UInt64	Distance between increments:		
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
		IncrementsPerRevolution	UInt64	Increments per revolution		
		NumberOfRevolutions	UInt64	Number of revolutions		
Module - 6ES7 138-6BA00-0BA0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule Counting/Measurement					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		OperatingType	UInt64	Selection of the operating type for the channel 0		
					26	CountingOrPositionInput
					27	Measuring
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
					5	AbsoluteEncoderSsi
		InvertDirection	Boolean	Invert direction		
		FrameLength	UInt64	Frame length		
					10	Value10Bit
					11	Value11Bit
					12	Value12Bit
					13	Value13Bit
					14	Value14Bit
					15	Value15Bit
					16	Value16Bit
					17	Value17Bit
					18	Value18Bit
					19	Value19Bit
					20	Value20Bit
					21	Value21Bit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
					22	Value22Bit
					23	Value23Bit
					24	Value24Bit
					25	Value25Bit
					26	Value26Bit
					27	Value27Bit
					28	Value28Bit
					29	Value29Bit
					30	Value30Bit
					31	Value31Bit
					32	Value32Bit
					33	Value33Bit
					34	Value34Bit
					35	Value35Bit
					36	Value36Bit
					37	Value37Bit
					38	Value38Bit
					39	Value39Bit
					40	Value40Bit
		CodeType	UInt64	Code type		
					0	Gray
					1	Dual
		TransmissionRate	UInt64	Transmission rate		
					0	Value125kHz
					1	Value250kHz
					2	Value500kHz
					3	Value1MHz
					4	Value15MHz
					5	Value2MHz
		MonoflopTime	UInt64	Monoflop time		
					4	Automatically
					0	Value16
					1	Value32
					2	Value48

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
					3	Value64
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
		BitNumberLsbOfPositionValue	UInt64	Bit number LSB of the position value		
		BitNumberMsbOfPositionValue	UInt64	Bit number MSB of the position value		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
					11	Value500kHz
					12	Value1MHz
		InterfaceStandard	UInt64	Interface standard		
					0	Rs422Symmetrical
					1	Ttl5VAsymmetrical
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI0	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI1	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0Measuring	Double	Comparison value 0		
		ComparisonValue1Measuring	Double	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		MeasuredVariable	UInt64	Measured variable		
					0	Frequency
					1	PeriodDuration
					2	Velocity
					3	CompleteSsiFrame
		UpdateTime	Double	Update time		
		TimeBaseForVelocityMeasurement	UInt64	Time base for velocity measurement		
					0	Value1ms
					1	Value10ms
					2	Value100ms
					3	Value1s
					4	Value60sOr1m
		IncrementsPerUnit	UInt64	Increments per unit		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
		HardwareInterruptUnderflowActive	Boolean	InterruptAtLowerLimit		
		HardwareInterruptNewCaptureValueAvailableActive	Boolean	InterruptCapturedValueAvailable		
		HardwareInterruptSynchronizationActive	Boolean	InterruptSynchronizationOfCounterByExternal		
		HardwareInterruptGateStartActive	Boolean	InterruptGateStart		
		HardwareInterruptGateStopActive	Boolean	InterruptGateStop		
		HardwareInterruptOverflowActive	Boolean	InterruptAtUpperLimit		
		HardwareInterruptDirectionReversalActive	Boolean	InterruptDirectionChanged		
		HardwareInterruptZeroCrossingActive	Boolean	InterruptZeroCrossing		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
		HardwareInterruptDQ0CompareActive	Boolean	HWInterruptDO0Compare		
		HardwareInterruptDQ1CompareActive	Boolean	HWInterruptDO1Compare		
		HardwareInterruptNewCaptureValueAvailableEvent	String	*HardwareInterruptCapturedValueAvailableEventName		
		HardwareInterruptNewCaptureValueAvailableInterr	Object	*HardwareInterruptCapturedValueAvailableInterrupt		
		HardwareInterruptNewCaptureValueAvailablePriori	UInt64	*HardwareInterruptCapturedValueAvailablePriority		
		HardwareInterruptDirectionReversalEventName	String	*HardwareInterruptDirectionChangedEventName		
		HardwareInterruptDirectionReversalInterrupt	Object	*HardwareInterruptDirectionChangedInterrupt		
		HardwareInterruptDirectionReversalPriority	UInt64	*HardwareInterruptDirectionChangedPriority		
		HardwareInterruptDQ0CompareEventName	String	*HardwareInterruptDQ0CompareEventName		
		HardwareInterruptDQ0CompareInterrupt	Object	*HardwareInterruptDQ0CompareInterrupt		
		HardwareInterruptDQ0ComparePriority	UInt64	*HardwareInterruptDQ0ComparePriority		
		HardwareInterruptDQ1CompareEventName	String	*HardwareInterruptDQ1CompareEventName		
		HardwareInterruptDQ1CompareInterrupt	Object	*HardwareInterruptDQ1CompareInterrupt		
		HardwareInterruptDQ1ComparePriority	UInt64	*HardwareInterruptDQ1ComparePriority		
		HardwareInterruptGateStartEventName	String	*HardwareInterruptGateStartEventName		
		HardwareInterruptGateStartInterrupt	Object	*HardwareInterruptGateStartInterrupt		
		HardwareInterruptGateStartPriority	UInt64	*HardwareInterruptGateStartPriority		
		HardwareInterruptGateStopEventName	String	*HardwareInterruptGateStopEventName		
		HardwareInterruptGateStopInterrupt	Object	*HardwareInterruptGateStopInterrupt		
		HardwareInterruptGateStopPriority	UInt64	*HardwareInterruptGateStopPriority		
		HardwareInterruptOverflowEventName	String	*HardwareInterruptOverflowEventName		
		HardwareInterruptOverflowInterrupt	Object	*HardwareInterruptOverflowInterrupt		
		HardwareInterruptOverflowPriority	UInt64	*HardwareInterruptOverflowPriority		
		HardwareInterruptSynchronizationEventName	String	*HardwareInterruptSynchronizationEventName		
		HardwareInterruptSynchronizationInterrupt	Object	*HardwareInterruptSynchronizationInterrupt		
		HardwareInterruptSynchronizationPriority	UInt64	*HardwareInterruptSynchronizationPriority		
		HardwareInterruptUnderflowEventName	String	*HardwareInterruptUnderflowEventName		
		HardwareInterruptUnderflowInterrupt	Object	*HardwareInterruptUnderflowInterrupt		
		HardwareInterruptUnderflowPriority	UInt64	*HardwareInterruptUnderflowPriority		
		HardwareInterruptZeroCrossingEventName	String	*HardwareInterruptZeroPassEventEventName		
		HardwareInterruptZeroCrossingInterrupt	Object	*HardwareInterruptZeroPassInterrupt		
		HardwareInterruptZeroCrossingPriority	UInt64	*HardwareInterruptZeroPassPriority		
	Submodule Motion Control					
		SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
					5	AbsoluteEncoderSsi
		InvertDirection	Boolean	Invert direction		
		FrameLength	UInt64	Frame length		
					10	Value10Bit
					11	Value11Bit
					12	Value12Bit
					13	Value13Bit
					14	Value14Bit
					15	Value15Bit
					16	Value16Bit
					17	Value17Bit
					18	Value18Bit
					19	Value19Bit
					20	Value20Bit
					21	Value21Bit
					22	Value22Bit
					23	Value23Bit
					24	Value24Bit
					25	Value25Bit
					26	Value26Bit
					27	Value27Bit
					28	Value28Bit
					29	Value29Bit
					30	Value30Bit
					31	Value31Bit

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2					
				32	Value32Bit
				33	Value33Bit
				34	Value34Bit
				35	Value35Bit
				36	Value36Bit
				37	Value37Bit
				38	Value38Bit
				39	Value39Bit
				40	Value40Bit
	CodeType	UInt64	Code type		
				0	Gray
				1	Dual
	TransmissionRate	UInt64	Transmission rate		
				0	Value125kHz
				1	Value250kHz
				2	Value500kHz
				3	Value1MHz
				4	Value15MHz
				5	Value2MHz
	MonoflopTime	UInt64	Monoflop time		
				4	Automatically
				0	Value16
				1	Value32
				2	Value48
				3	Value64
	Parity	UInt64	Parity		
				0	None
				2	Even
				1	Odd
	BitNumberLsbOfPositionValue	UInt64	Bit number LSB of the position value		
	BitNumberMsbOfPositionValue	UInt64	Bit number MSB of the position value		
	SignalEvaluation	UInt64	Signal evaluation		
				0	Single
				1	Double

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
					11	Value500kHz
					12	Value1MHz
		SignalSelectionForReferenceMark0	UInt64	Signal selection for reference mark 0		
					1	Di0
					0	SignalNOfIncrementalEncoder
		InterfaceStandard	UInt64	Interface standard		
					0	Rs422Symmetrical
					1	Ttl5VAsymmetrical
		StepsPerRevolution	UInt64	Steps per revolution		
		ReferenceSpeed	Double	Reference speed		
		FineResolutionIncrementDistance	Double	Fine-resolution increment distance		
		EncoderType	UInt64	Encoder type		
					7	Linear
					8	Rotary
		DistanceBetweenIncrements	UInt64	Distance between increments:		
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
					1	FastMode
		IncrementsPerRevolution	UInt64	Increments per revolution		
		NumberOfRevolutions	UInt64	Number of revolutions		
	Submodule Fast Mode					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
					5	AbsoluteEncoderSsi
		InvertDirection	Boolean	Invert direction		
		FrameLength	UInt64	Frame length		
					10	Value10Bit
					11	Value11Bit
					12	Value12Bit
					13	Value13Bit
					14	Value14Bit
					15	Value15Bit
					16	Value16Bit
					17	Value17Bit
					18	Value18Bit
					19	Value19Bit
					20	Value20Bit
					21	Value21Bit
					22	Value22Bit
					23	Value23Bit
					24	Value24Bit
					25	Value25Bit
					26	Value26Bit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
					27	Value27Bit
					28	Value28Bit
					29	Value29Bit
					30	Value30Bit
					31	Value31Bit
					32	Value32Bit
					33	Value33Bit
					34	Value34Bit
					35	Value35Bit
					36	Value36Bit
					37	Value37Bit
					38	Value38Bit
					39	Value39Bit
					40	Value40Bit
		CodeType	UInt64	Code type		
					0	Gray
					1	Dual
		TransmissionRate	UInt64	Transmission rate		
					0	Value125kHz
					1	Value250kHz
					2	Value500kHz
					3	Value1MHz
					4	Value15MHz
					5	Value2MHz
		MonoflopTime	UInt64	Monoflop time		
					4	Automatically
					0	Value16
					1	Value32
					2	Value48
					3	Value64
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
		BitNumberLsbOfPositionValue	UInt64	Bit number LSB of the position value		
		BitNumberMsbOfPositionValue	UInt64	Bit number MSB of the position value		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
					11	Value500kHz
					12	Value1MHz
		InterfaceStandard	UInt64	Interface standard		
					0	Rs422Symmetrical
					1	Ttl5VAsymmetrical
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountDirectionForSynchronization	UInt64	Count direction for synchronization		
					0	None
					1	Up
					2	Down
					3	InBothDirections
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.2						
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
Module - 6ES7 138-6CG00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PulseWidthModulationTimePeriod	UInt64	PWM period		
					38	Value10ms
					1	Value5ms
					2	Value2ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6CG00-0BA0 - V1.0						
					3	Value1ms
					37	Value0Dot5ms
					4	Value0Dot20ms
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					2	SubstituteAValue
					1	KeepLastValue
		DiagnosticsInterrupt	Boolean	Enable diagnostic interrupts		
		ConfigurationDQOrDIGroup2	UInt64	Configuration DQ/DI group		
					2	IncrementalEncoderABPhaseShifted
					1	TimerDi2WithEnableInputDi3
					3	TimerDq2WithEnableInputDi2
					0	UseInputOrOutputIndividually
		ConfigurationDQOrDIGroup1	UInt64	Configuration DQ/DI group		
					1	TimerDqWithEnableInput
					0	UseInputOrOutputIndividually
		ConfigurationDQOrDIGroup0	UInt64	Configuration DQ/DI group		
					1	TimerDqWithEnableInput
					0	UseInputOrOutputIndividually
		ModuleUseFromUserProgram	UInt64	Module use from the user program		
					1	UseWithTechnologyObjectMotionControl
					0	UseWithInstructionFromTimeBasedIoLibrary
	Channel 0					
		OperatingMode	UInt64	Operating mode		
					23	Counting
					34	TimerDI
					283	OversamplingInput
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
		HwEnable	UInt64	HW enable		
					1	LevelTriggered

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6CG00-0BA0 - V1.0					
				0	EdgeTriggered
	SelectLevel	UInt32	Edge selection		
				0	ActiveWithHighLevel
				1	ActiveWithLowLevel
				3	AtRisingEdge
				2	AtFallingEdge
	Invert	Boolean			
Channel 1					
	OperatingMode	UInt64	Operating mode		
				34	TimerDI
				283	OversamplingInput
				23	Counting
	InputDelay	UInt64	Input delay		
				15	None
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
	HwEnable	UInt64	HW enable		
				1	LevelTriggered
				0	EdgeTriggered
	SelectLevel	UInt32	Edge selection		
				0	ActiveWithHighLevel
				1	ActiveWithLowLevel
				3	AtRisingEdge
				2	AtFallingEdge
	Invert	Boolean			
Channel 2					
	OperatingMode	UInt64	Operating mode		
				275	IncrementalEncoderABPhaseShifted
				34	TimerDI
				23	Counting
				283	OversamplingInput

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6CG00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
		HwEnable	UInt64	HW enable		
					1	LevelTriggered
					0	EdgeTriggered
		SelectLevel	UInt32	Edge selection		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
					3	AtRisingEdge
					2	AtFallingEdge
		Invert	Boolean			
	Channel 3					
		OperatingMode	UInt64	Operating mode		
					34	TimerDI
					283	OversamplingInput
					23	Counting
					275	IncrementalEncoderABPhaseShifted
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
		HwEnable	UInt64	HW enable		
					1	LevelTriggered
					0	EdgeTriggered
		SelectLevel	UInt32	Edge selection		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
					3	AtRisingEdge

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6CG00-0BA0 - V1.0						
					2	AtFallingEdge
		Invert	Boolean			
	Channel 4					
		OperatingMode	UInt64	Operating mode		
					8	TimerDQ
					282	OversamplingOutput
					7	PulseWidthModulation
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
		HighSpeedOutput	Boolean	High-speed output (0.1 A)		
		Invert	Boolean			
	Channel 5					
		OperatingMode	UInt64	Operating mode		
					8	TimerDQ
					282	OversamplingOutput
					7	PulseWidthModulation
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
		HighSpeedOutput	Boolean	High-speed output (0.1 A)		
		Invert	Boolean			
	Channel 6					
		OperatingMode	UInt64	Operating mode		
					8	TimerDQ
					282	OversamplingOutput
					7	PulseWidthModulation
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
		HighSpeedOutput	Boolean	High-speed output (0.1 A)		
		Invert	Boolean			
	Channel 7					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6CG00-0BA0 - V1.0						
		OperatingMode	UInt64	Operating mode		
					8	TimerDQ
					282	OversamplingOutput
					7	PulseWidthModulation
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
		HighSpeedOutput	Boolean	High-speed output (0.1 A)		
		Invert	Boolean			
	Channel 8					
		OperatingMode	UInt64	Operating mode		
					8	TimerDQ
					282	OversamplingOutput
					7	PulseWidthModulation
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
		HighSpeedOutput	Boolean	High-speed output (0.1 A)		
		Invert	Boolean			
	Channel 9					
		OperatingMode	UInt64	Operating mode		
					8	TimerDQ
					282	OversamplingOutput
					7	PulseWidthModulation
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
		HighSpeedOutput	Boolean	High-speed output (0.1 A)		
		Invert	Boolean			
Module - 6ES7 138-6BA00-0BA0 - V1.3						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule Counting/Measurement					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		OperatingType	UInt64	Selection of the operating type for the channel 0		
					26	CountingOrPositionInput
					27	Measuring
		FrequencyForCapture	UInt64	Frequency of Capture function		
					0	Once
					1	Periodic
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
					5	AbsoluteEncoderSsi

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
		InvertDirection	Boolean	Invert direction		
		FrameLength	UInt64	Frame length		
					10	Value10Bit
					11	Value11Bit
					12	Value12Bit
					13	Value13Bit
					14	Value14Bit
					15	Value15Bit
					16	Value16Bit
					17	Value17Bit
					18	Value18Bit
					19	Value19Bit
					20	Value20Bit
					21	Value21Bit
					22	Value22Bit
					23	Value23Bit
					24	Value24Bit
					25	Value25Bit
					26	Value26Bit
					27	Value27Bit
					28	Value28Bit
					29	Value29Bit
					30	Value30Bit
					31	Value31Bit
					32	Value32Bit
					33	Value33Bit
					34	Value34Bit
					35	Value35Bit
					36	Value36Bit
					37	Value37Bit
					38	Value38Bit
					39	Value39Bit
					40	Value40Bit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
		CodeType	UInt64	Code type		
					0	Gray
					1	Dual
		TransmissionRate	UInt64	Transmission rate		
					0	Value125kHz
					1	Value250kHz
					2	Value500kHz
					3	Value1MHz
					4	Value15MHz
					5	Value2MHz
		MonoflopTime	UInt64	Monoflop time		
					4	Automatically
					0	Value16
					1	Value32
					2	Value48
					3	Value64
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
		BitNumberLsbOfPositionValue	UInt64	Bit number LSB of the position value		
		BitNumberMsbOfPositionValue	UInt64	Bit number MSB of the position value		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
					11	Value500kHz
					12	Value1MHz
		InterfaceStandard	UInt64	Interface standard		
					0	Rs422Symmetrical
					1	Ttl5VAsymmetrical
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI0	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		BehaviorOfCounterValueAfterCaptureDI1	UInt64	Behavior of counter value after Capture		
					0	ContinueCounting
					1	SetToStartValueAndContinueCounting
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0Measuring	Double	Comparison value 0		
		ComparisonValue1Measuring	Double	Comparison value 1		
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		MeasuredVariable	UInt64	Measured variable		
					0	Frequency
					1	PeriodDuration
					2	Velocity
					3	CompleteSsiFrame
		UpdateTime	Double	Update time		
		TimeBaseForVelocityMeasurement	UInt64	Time base for velocity measurement		
					0	Value1ms
					1	Value10ms
					2	Value100ms
					3	Value1s
					4	Value60sOr1m
		IncrementsPerUnit	UInt64	Increments per unit		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
		HardwareInterruptUnderflowActive	Boolean	InterruptAtLowerLimit		
		HardwareInterruptNewCaptureValueAvailableActive	Boolean	InterruptCapturedValueAvailable		
		HardwareInterruptSynchronizationActive	Boolean	InterruptSynchronizationOfCounterByExternal		
		HardwareInterruptGateStartActive	Boolean	InterruptGateStart		
		HardwareInterruptGateStopActive	Boolean	InterruptGateStop		
		HardwareInterruptOverflowActive	Boolean	InterruptAtUpperLimit		
		HardwareInterruptDirectionReversalActive	Boolean	InterruptDirectionChanged		
		HardwareInterruptZeroCrossingActive	Boolean	InterruptZeroCrossing		
		HardwareInterruptDQ0CompareActive	Boolean	HWInterruptDO0Compare		
		HardwareInterruptDQ1CompareActive	Boolean	HWInterruptDO1Compare		
		HardwareInterruptNewCaptureValueAvailableEvent	String	*HardwareInterruptCapturedValueAvailableEventName		
		HardwareInterruptNewCaptureValueAvailableInterr	Object	*HardwareInterruptCapturedValueAvailableInterrupt		
		HardwareInterruptNewCaptureValueAvailablePriori	UInt64	*HardwareInterruptCapturedValueAvailablePriority		
		HardwareInterruptDirectionReversalEventName	String	*HardwareInterruptDirectionChangedEventName		
		HardwareInterruptDirectionReversalInterrupt	Object	*HardwareInterruptDirectionChangedInterrupt		
		HardwareInterruptDirectionReversalPriority	UInt64	*HardwareInterruptDirectionChangedPriority		
		HardwareInterruptDQ0CompareEventName	String	*HardwareInterruptDQ0CompareEventName		
		HardwareInterruptDQ0CompareInterrupt	Object	*HardwareInterruptDQ0CompareInterrupt		
		HardwareInterruptDQ0ComparePriority	UInt64	*HardwareInterruptDQ0ComparePriority		
		HardwareInterruptDQ1CompareEventName	String	*HardwareInterruptDQ1CompareEventName		
		HardwareInterruptDQ1CompareInterrupt	Object	*HardwareInterruptDQ1CompareInterrupt		
		HardwareInterruptDQ1ComparePriority	UInt64	*HardwareInterruptDQ1ComparePriority		
		HardwareInterruptGateStartEventName	String	*HardwareInterruptGateStartEventName		
		HardwareInterruptGateStartInterrupt	Object	*HardwareInterruptGateStartInterrupt		
		HardwareInterruptGateStartPriority	UInt64	*HardwareInterruptGateStartPriority		
		HardwareInterruptGateStopEventName	String	*HardwareInterruptGateStopEventName		
		HardwareInterruptGateStopInterrupt	Object	*HardwareInterruptGateStopInterrupt		
		HardwareInterruptGateStopPriority	UInt64	*HardwareInterruptGateStopPriority		
		HardwareInterruptOverflowEventName	String	*HardwareInterruptOverflowEventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
		HardwareInterruptOverflowInterrupt	Object	*HardwareInterruptOverflowInterrupt		
		HardwareInterruptOverflowPriority	UInt64	*HardwareInterruptOverflowPriority		
		HardwareInterruptSynchronizationEventName	String	*HardwareInterruptSynchronizationEventName		
		HardwareInterruptSynchronizationInterrupt	Object	*HardwareInterruptSynchronizationInterrupt		
		HardwareInterruptSynchronizationPriority	UInt64	*HardwareInterruptSynchronizationPriority		
		HardwareInterruptUnderflowEventName	String	*HardwareInterruptUnderflowEventName		
		HardwareInterruptUnderflowInterrupt	Object	*HardwareInterruptUnderflowInterrupt		
		HardwareInterruptUnderflowPriority	UInt64	*HardwareInterruptUnderflowPriority		
		HardwareInterruptZeroCrossingEventName	String	*HardwareInterruptZeroPassEventEventName		
		HardwareInterruptZeroCrossingInterrupt	Object	*HardwareInterruptZeroPassInterrupt		
		HardwareInterruptZeroCrossingPriority	UInt64	*HardwareInterruptZeroPassPriority		
	Submodule Motion Control					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
	Channel 0					
		SignalType	UInt64	Signal type		
					3	IncrementalEncoderABPhaseShifted
					4	IncrementalEncoderABN
					1	PulseAAndDirectionB
					0	PulseA
					2	CountUpACountDownB
					5	AbsoluteEncoderSsi
		InvertDirection	Boolean	Invert direction		
		FrameLength	UInt64	Frame length		
					10	Value10Bit
					11	Value11Bit
					12	Value12Bit
					13	Value13Bit
					14	Value14Bit
					15	Value15Bit
					16	Value16Bit
					17	Value17Bit
					18	Value18Bit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
					19	Value19Bit
					20	Value20Bit
					21	Value21Bit
					22	Value22Bit
					23	Value23Bit
					24	Value24Bit
					25	Value25Bit
					26	Value26Bit
					27	Value27Bit
					28	Value28Bit
					29	Value29Bit
					30	Value30Bit
					31	Value31Bit
					32	Value32Bit
					33	Value33Bit
					34	Value34Bit
					35	Value35Bit
					36	Value36Bit
					37	Value37Bit
					38	Value38Bit
					39	Value39Bit
					40	Value40Bit
		CodeType	UInt64	Code type		
					0	Gray
					1	Dual
		TransmissionRate	UInt64	Transmission rate		
					0	Value125kHz
					1	Value250kHz
					2	Value500kHz
					3	Value1MHz
					4	Value15MHz
					5	Value2MHz
		MonoflopTime	UInt64	Monoflop time		
					4	Automatically

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
					0	Value16
					1	Value32
					2	Value48
					3	Value64
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
		BitNumberLsbOfPositionValue	UInt64	Bit number LSB of the position value		
		BitNumberMsbOfPositionValue	UInt64	Bit number MSB of the position value		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
					11	Value500kHz
					12	Value1MHz
		SignalSelectionForReferenceMark0	UInt64	Signal selection for reference mark 0		
					1	Di0
					0	SignalNOfIncrementalEncoder
		InterfaceStandard	UInt64	Interface standard		
					0	Rs422Symmetrical
					1	Ttl5VAsymmetrical

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3					
	StepsPerRevolution	UInt64	Steps per revolution		
	ReferenceSpeed	Double	Reference speed		
	FineResolutionIncrementDistance	Double	Fine-resolution increment distance		
	EncoderType	UInt64	Encoder type		
				7	Linear
				8	Rotary
	DistanceBetweenIncrements	UInt64	Distance between increments:		
	DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
	DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
	MeasuringInput	UInt64	Measuring input		
				1	DI1
	OperatingMode	UInt64	Selection of the operating mode for the channel 0		
				277	TechnologyObject
				269	MotionControl
				278	ManualOperation
				1	FastMode
	IncrementsPerRevolution	UInt64	Increments per revolution		
	NumberOfRevolutions	UInt64	Number of revolutions		
Submodule Fast Mode					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
Channel 0					
	SignalType	UInt64	Signal type		
				3	IncrementalEncoderABPhaseShifted
				4	IncrementalEncoderABN
				1	PulseAAndDirectionB
				0	PulseA
				2	CountUpACountDownB
				5	AbsoluteEncoderSsi
	InvertDirection	Boolean	Invert direction		
	FrameLength	UInt64	Frame length		
				10	Value10Bit
				11	Value11Bit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
					12	Value12Bit
					13	Value13Bit
					14	Value14Bit
					15	Value15Bit
					16	Value16Bit
					17	Value17Bit
					18	Value18Bit
					19	Value19Bit
					20	Value20Bit
					21	Value21Bit
					22	Value22Bit
					23	Value23Bit
					24	Value24Bit
					25	Value25Bit
					26	Value26Bit
					27	Value27Bit
					28	Value28Bit
					29	Value29Bit
					30	Value30Bit
					31	Value31Bit
					32	Value32Bit
					33	Value33Bit
					34	Value34Bit
					35	Value35Bit
					36	Value36Bit
					37	Value37Bit
					38	Value38Bit
					39	Value39Bit
					40	Value40Bit
		CodeType	UInt64	Code type		
					0	Gray
					1	Dual
		TransmissionRate	UInt64	Transmission rate		
					0	Value125kHz

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
					1	Value250kHz
					2	Value500kHz
					3	Value1MHz
					4	Value15MHz
					5	Value2MHz
		MonoflopTime	UInt64	Monoflop time		
					4	Automatically
					0	Value16
					1	Value32
					2	Value48
					3	Value64
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
		BitNumberLsbOfPositionValue	UInt64	Bit number LSB of the position value		
		BitNumberMsbOfPositionValue	UInt64	Bit number MSB of the position value		
		SignalEvaluation	UInt64	Signal evaluation		
					0	Single
					1	Double
					2	Quadruple
		FilterFrequency	UInt64	Filter frequency		
					0	Value100Hz
					1	Value200Hz
					2	Value500Hz
					3	Value1kHz
					4	Value2kHz
					5	Value5kHz
					6	Value10kHz
					7	Value20kHz
					8	Value50kHz
					9	Value100kHz
					10	Value200kHz
					11	Value500kHz

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
					12	Value1MHz
		InterfaceStandard	UInt64	Interface standard		
					0	Rs422Symmetrical
					1	Ttl5VAsymmetrical
		DiagnosticsWireBreak	Boolean	Enable diagnostic interrupt on wire break		
		DiagnosticsInterrupt	Boolean	Enable additional diagnostic interrupts		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					1	KeepLastValue
					15	ContinueOperation
		SubstituteValueDQ0	UInt64	Substitute value for DQ0		
					0	Value0
					1	Value1
		SubstituteValueDQ1	UInt64	Substitute value for DQ1		
					0	Value0
					1	Value1
		ReactionToSignalN	UInt64	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
					2	CaptureAtSignalN
		SynchronizationFrequency	UInt64	Frequency of synchronization		
					0	Once
					1	Periodic
		CountDirectionForSynchronization	UInt64	Count direction for synchronization		
					0	None
					1	Up
					2	Down
					3	InBothDirections
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		CountingLowLimit	Int64	Low counting limit		
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
		ResetWhenCountingLimitIsViolated	UInt64	Reset when counting limit is violated		
					1	ToStartValue
					0	ToOppositeCountingLimit
		ReactionToGateStart	UInt64	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		FunctionDI0	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		EdgeSelectionDI0	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI0	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		FunctionDI1	UInt64	Set function of DI		
					0	GateStartOrStopLevelTriggered
					1	GateStartEdgeTriggered

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
					2	GateStopEdgeTriggered
					3	Synchronization
					4	EnableSynchronizationAtSignalN
					5	Capture
					6	DigitalInputWithoutFunction
		EdgeSelectionDI1	UInt64	Edge selection		
					1	AtRisingEdge
					2	AtFallingEdge
					3	AtRisingAndFallingEdge
		SelectLevelDI1	UInt64	Select level		
					0	ActiveWithHighLevel
					1	ActiveWithLowLevel
		SetOutputDQ0	UInt64	Set output		
					1	BetweenComparisonValue0AndHighLimit
					2	BetweenComparisonValue0AndLowLimit
					3	AtComparisonValue0ForAPulseDuration
					5	AfterSetCommandFromCpuUntilCompValue0
					7	MeasuredValueGeaterthanEqualtoComparisonValue0
					6	MeasuredValueLessthanEqualtoComparisonValue0
					0	UseByUserProgram
					8	NoFunction
		ComparisonValue0	Int64	Comparison value 0		
		ComparisonValue1	Int64	Comparison value 1		
		CountDirectionDQ0	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ0	Double	Pulse duration		
		SetOutputDQ1	UInt64	Set output		
					1	BetweenComparisonValue1AndHighLimit
					2	BetweenComparisonValue1AndLowLimit
					4	BetweenComparisonValue0And1
					3	AtComparisonValue1ForAPulseDuration

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6BA00-0BA0 - V1.3						
					5	AfterSetCommandFromCpuUntilCompValue1
					7	MeasuredValueGeaterthanEqualtoComparisonValue1
					6	MeasuredValueLessthanEqualtoComparisonValue1
					9	NotBetweenComparisonValue0And1
					0	UseByUserProgram
					8	NoFunction
		CountDirectionDQ1	UInt64	Count direction		
					3	InBothDirections
					1	Up
					2	Down
		PulseDurationDQ1	Double	Pulse duration		
		Hysteresis	UInt64	Hysteresis (in increments)		
		OperatingMode	UInt64	Selection of the operating mode for the channel 0		
					277	TechnologyObject
					269	MotionControl
					278	ManualOperation
					1	FastMode
Module - 6ES7 138-6DB00-0BB1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6DB00-0BB1 - V1.0						
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		ChannelConfiguration	UInt64	Channel configuration		
					0	Value2Channels2A
					1	Value1Channel4A
	Channel 0					
		HighSpeedOutput	Boolean	High-speed output (0.1 A)		
		FunctionDI	UInt64	Function DI		
					8	Input
					9	HwEnable
					14	LimitSwitch
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		PwmOutputFormat	UInt64	Output format		
					1	S7AnalogValue
					3	Per100
					4	Per1000
					5	Per10000
					2	Value1Hz

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6DB00-0BB1 - V1.0						
		MinimumPulseDuration	UInt64	Minimum pulse duration		
		Period	UInt64	Period duration		
		OnDelay	UInt64	On delay		
		Dithering	Boolean	Dithering		
		InclineOfDitheringRampUp	UInt64	Incline of dithering ramp up		
		InclineOfDitheringRampDown	UInt64	Incline of dithering ramp down		
		DitheringAmplitude	Double	Dithering amplitude		
		DitheringPeriodDuration	UInt64	Dithering period duration		
		CurrentControl	Boolean	Current control		
		ProportionalAction	Boolean	Enable proportional action		
		IntegralAction	Boolean	Enable integral action		
		DerivativeAction	Boolean	Enable derivative action		
		ReferenceValueCurrent	UInt64	Reference value current		
		DeadBandWidth	UInt64	Dead band width		
		ManipulatedValueHighLimit	UInt64	Manipulated value high limit		
		ManipulatedValueLowLimit	UInt64	Manipulated value low limit		
		ProportionalGain	Double	Proportional gain		
		CurrentControlIntegrationTime	Double	Integration time		
		DerivativeActionTime	Double	Derivative action time		
		DerivativeActionDelayTime	Double	Delay time of derivative action		
		DiagnosticsGroup	Boolean	Group diagnostics		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					15	ContinueOperation
		OperatingMode	UInt64	Operating mode		
					264	PulseOutput
					7	PulseWidthModulation
					263	PulseTrain
					265	OnOffDelay
					266	FrequencyOutput
					267	PwmWithDcMotor
		DutyCycle	UInt64	Duty cycle		
		OffDelay	UInt64	Off delay		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6DB00-0BB1 - V1.0						
		SubstituteValueDQA	UInt64			
					0	Value0
					1	Value1
		SubstituteValueDQB	UInt64			
					0	Value0
					1	Value1
		DiagnosticsDQA	Boolean			
		DiagnosticsDQB	Boolean			
		DitheringFrequency	Double			
	Channel 1					
		HighSpeedOutput	Boolean	High-speed output (0.1 A)		
		FunctionDI	UInt64	Function DI		
					8	Input
					9	HwEnable
					14	LimitSwitch
		InputDelay	UInt64	Input delay		
					15	None
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
		PwmOutputFormat	UInt64	Output format		
					1	S7AnalogValue
					3	Per100
					4	Per1000
					5	Per10000
					2	Value1Hz
		MinimumPulseDuration	UInt64	Minimum pulse duration		
		Period	UInt64	Period duration		
		OnDelay	UInt64	On delay		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6DB00-0BB1 - V1.0						
		Dithering	Boolean	Dithering		
		InclineOfDitheringRampUp	UInt64	Incline of dithering ramp up		
		InclineOfDitheringRampDown	UInt64	Incline of dithering ramp down		
		DitheringAmplitude	Double	Dithering amplitude		
		DitheringPeriodDuration	UInt64	Dithering period duration		
		CurrentControl	Boolean	Current control		
		ProportionalAction	Boolean	Enable proportional action		
		IntegralAction	Boolean	Enable integral action		
		DerivativeAction	Boolean	Enable derivative action		
		ReferenceValueCurrent	UInt64	Reference value current		
		DeadBandWidth	UInt64	Dead band width		
		ManipulatedValueHighLimit	UInt64	Manipulated value high limit		
		ManipulatedValueLowLimit	UInt64	Manipulated value low limit		
		ProportionalGain	Double	Proportional gain		
		CurrentControlIntegrationTime	Double	Integration time		
		DerivativeActionTime	Double	Derivative action time		
		DerivativeActionDelayTime	Double	Delay time of derivative action		
		DiagnosticsGroup	Boolean	Group diagnostics		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					16	OutputSubstituteValue
					15	ContinueOperation
		OperatingMode	UInt64	Operating mode		
					264	PulseOutput
					7	PulseWidthModulation
					263	PulseTrain
					265	OnOffDelay
					266	FrequencyOutput
					267	PwmWithDcMotor
		DutyCycle	UInt64	Duty cycle		
		OffDelay	UInt64	Off delay		
		SubstituteValueDQA	UInt64			
					0	Value0
					1	Value1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 138-6DB00-0BB1 - V1.0						
		SubstituteValueDQB	UInt64			
					0	Value0
					1	Value1
		DiagnosticsDQA	Boolean			
		DiagnosticsDQB	Boolean			
		DitheringFrequency	Double			

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - ET200SP.Virtual.Module						
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		PositionNumber	Int32	PositionNumber		
		VirtualType	UInt64	Type		
					1	MsoLocal
		AddSubModules	Int64	Add Submoduletype		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		ActivateDataStatus	Boolean	Data status		
		InputAddressLength	Int64	Input address area		
		OutputAddressLength	Int64	Output address area		
		Comment	String	Comment		
		VirtualSubType	UInt64	Type		
					2	MsoSub
		Name	String	Name		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		ActivateDataStatus	Boolean	Data status		
		InputAddressLength	Int64	Input address area		
		OutputAddressLength	Int64	Output address area		
		Comment	String	Comment		
		VirtualSubType	UInt64	Type		
					1	MsoLocal

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Name	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		TypeName	String	InvariantTypeName		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
		UserDataMappingActive	Boolean	Enable user data mapping		
		ModuleVariant	UInt64	Module version		
					0	Value32BytesIOr12BytesO
					6	EeIndustryMeasuredDataProfileE3
					5	EeIndustryMeasuredDataProfileE2

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					4	EeIndustryMeasuredDataProfileE1
					3	EeIndustryMeasuredDataProfileE0
					1	Value2BytesIOr2BytesO
					2	UserSpecific
		ProcessDataVariant	UInt64	Process data variant		
					128	Hex80
					129	EeIndustryMeasuredDataProfileE0Hex81
					130	EeIndustryMeasuredDataProfileE1Hex82
					131	EeIndustryMeasuredDataProfileE2Hex83
					132	EeIndustryMeasuredDataProfileE3Hex84
					1	UserSpecificUserDataHex01
					2	UserSpecificUserDataHex02
					254	TotalPowersL1l2l3HexFe
					253	ActivePowersL1l2l3HexFd
					252	ReactivePowersL1l2l3HexFc
					251	ApparentPowerL1l2l3HexFb
					250	BasicMeasuredValuesL1l2l3HexFa
					249	TotalEnergyL1l2l3HexF9
					248	EnergyL1HexF8
					247	EnergyL2HexF7
					246	EnergyL3HexF6
					245	BasicVariablesThreePhaseMeasurementL1l2l3HexF5
					244	ReactivePowerCompensationL1l2l3HexF4
					240	QualityValuesThreePhaseMeasurementL1l2l3HexF0
					239	EnergyL1l2l3OverflowCounterHexEf
					159	BasicVariablesSinglePhaseMeasurementL1Hex9F
					158	SinglePhaseMeasurementL1WithVoltageScalingValueHex9E
					157	BasicVariablesSinglePhaseMeasurementL2Hex9D
					156	SinglePhaseMeasurementL2WithVoltageScalingValueHex9C

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0					
				155	BasicVariablesSinglePhaseMeasurementL3Hex9B
				154	SinglePhaseMeasurementL3WithVoltageScalingValueHex9A
				227	EeIndustryMeasuredDataProfileE3HexE3
				226	EeIndustryMeasuredDataProfileE2HexE2
				225	EeIndustryMeasuredDataProfileE1HexE1
				224	EeIndustryMeasuredDataProfileE0HexE0
	ConnectionType	UInt64	Connection type		
				0	None
				1	Value1P2w1Phase2Wire
				2	Value3P4w3Phase4Wire
				4	Value3P4w13Phase4WireSymmetricalLoad
				5	Value3X1p2w3X1PhaseEach2Conductors
				6	Value2P3w2Phase3Wire
				7	Value3P3w3Phase3Wire
				8	Value3P3w13Phase3WireSymmetricalLoad
	LineFrequency	UInt64	Line frequency		
				2	Value50Hz
				1	Value60Hz
	EndValueEnergyCounter	UInt64	End value energy meter		
				0	NoEndValueCountIndefinitely
				1	CountPeriodicallyTo10Dot3
				2	CountPeriodicallyTo10Dot6
				3	CountPeriodicallyTo10Dot9
				4	CountPeriodicallyTo10Dot12
				5	CountPeriodicallyTo10Dot15
	GateControlActive	Boolean	Energy meter gate		
				0	Deactivated
				1	Active
	MinimumAndMaximumValueCalculationActive	Boolean	Minimum and maximum value calculation		
	MinimumAndMaximumValueCalculationGateActiv	Boolean	Minimum and maximum value calculation gate		
	CurrentMeasurement	UInt64	Current measurement		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					1	NeutralCurrentMeasurement
					2	NeutralCurrentCalculation
		NeutralConductorCurrentTransformerPrimaryCurr	UInt64	Current transformer primary current		
		NeutralConductorCurrentTransformerSecondaryCu	UInt64	Current transformer secondary current		
					1	Value1A
					2	Value5A
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		OperatingRange	UInt64	Voltage measuring range		
					111	Value100V
					112	Value110V
					113	Value115V
					114	Value120V
					115	Value127V
					116	Value190V
					117	Value200V
					118	Value208V
					119	Value220V
					120	Value230V
					121	Value240V
					122	Value277V
					125	Value300V
		HardwareInterruptEventName	String	HardwareInterruptEventName		
		HardwareInterruptOB	Object	HardwareInterruptInterrupt		
		HardwareInterruptPriority	UInt64	HardwareInterruptPriority		
		HardwareInterruptActive	Boolean	ActivateHWInterrupt		
					0	PseudoDeactivated
					1	PseudoActive
	Channel 0					
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		NominalValueCurrent	UInt32	Nominal value current		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0					
	NominalValueVoltage	UInt32	Nominal value voltage		
	ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	OperatingHoursCounterActive	Boolean	Operating hours counter		
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
	CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
				0	Value1A
				2	Value5A
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
	TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
	LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
Channel 1					
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	NominalValueCurrent	UInt32	Nominal value current		
	NominalValueVoltage	UInt32	Nominal value voltage		
	ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	OperatingHoursCounterActive	Boolean	Operating hours counter		
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
	CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
				0	Value1A
				2	Value5A
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
	TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0					
	LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
Channel 2					
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	NominalValueCurrent	UInt32	Nominal value current		
	NominalValueVoltage	UInt32	Nominal value voltage		
	ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	OperatingHoursCounterActive	Boolean	Operating hours counter		
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
	CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
				0	Value1A
				2	Value5A
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
	TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
	LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
	MappingId	int64			
	MappingMeasuredVariable	string			
	MappingUnit	string			
	MappingDataType	string			
	MappingIAddress	int64			
	MappingMinValue	string			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		MappingMaxValue	string			
		MappingId	int64			
		MappingMeasuredVariable	string			
		MappingUnit	string			
		MappingDataType	string			
		MappingIAddress	int64			
		MappingMinValue	string			
		MappingMaxValue	string			
		MappingId	int64			
		MappingMeasuredVariable	string			
		MappingUnit	string			
		MappingDataType	string			
		MappingMinValue	string			
		MappingMaxValue	string			
		MappingByteOffset	int64			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Name	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		TypeName	String	InvariantTypeName		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		PositionNumber	Int32	Index		
		Name	String	Name		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		Comment	String	Comment		
		UserDataMappingActive	Boolean	Enable user data mapping		
		ModuleVariant	UInt64	Module version		
					0	Value32BytesIOr12BytesO
					6	EeIndustryMeasuredDataProfileE3
					5	EeIndustryMeasuredDataProfileE2
					4	EeIndustryMeasuredDataProfileE1
					3	EeIndustryMeasuredDataProfileE0
					1	Value2BytesIOr2BytesO
					2	UserSpecific
		ProcessDataVariant	UInt64	Process data variant		
					128	Hex80
					129	EeIndustryMeasuredDataProfileE0Hex81
					130	EeIndustryMeasuredDataProfileE1Hex82
					131	EeIndustryMeasuredDataProfileE2Hex83
					132	EeIndustryMeasuredDataProfileE3Hex84
					1	UserSpecificUserDataHex01
					2	UserSpecificUserDataHex02
					254	TotalPowersL1l2l3HexFe
					253	ActivePowersL1l2l3HexFd
					252	ReactivePowersL1l2l3HexFc
					251	ApparentPowerL1l2l3HexFb
					250	BasicMeasuredValuesL1l2l3HexFa
					249	TotalEnergyL1l2l3HexF9
					248	EnergyL1HexF8
					247	EnergyL2HexF7
					246	EnergyL3HexF6
					245	BasicVariablesThreePhaseMeasurementL1l2l3HexF5
					244	ReactivePowerCompensationL1l2l3HexF4
					240	QualityValuesThreePhaseMeasurementL1l2l3HexF0
					239	EnergyL1l2l3OverflowCounterHexEf

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0					
				159	BasicVariablesSinglePhaseMeasurementL1Hex9F
				158	SinglePhaseMeasurementL1WithVoltageScalingValueHex9E
				157	BasicVariablesSinglePhaseMeasurementL2Hex9D
				156	SinglePhaseMeasurementL2WithVoltageScalingValueHex9C
				155	BasicVariablesSinglePhaseMeasurementL3Hex9B
				154	SinglePhaseMeasurementL3WithVoltageScalingValueHex9A
				227	EeIndustryMeasuredDataProfileE3HexE3
				226	EeIndustryMeasuredDataProfileE2HexE2
				225	EeIndustryMeasuredDataProfileE1HexE1
				224	EeIndustryMeasuredDataProfileE0HexE0
	ConnectionType	UInt64	Connection type		
				0	None
				1	Value1P2w1Phase2Wire
				2	Value3P4w3Phase4Wire
				3	Value3P4wi3PhaseCurrentMeasurement4Wire
				4	Value3P4w13Phase4WireSymmetricalLoad
				5	Value3X1p2w3X1PhaseEach2Conductors
				6	Value2P3w2Phase3Wire
				7	Value3P3w3Phase3Wire
				8	Value3P3w13Phase3WireSymmetricalLoad
	LineFrequency	UInt64	Line frequency		
				2	Value50Hz
				1	Value60Hz
	EndValueEnergyCounter	UInt64	End value energy meter		
				0	NoEndValueCountIndefinitely
				1	CountPeriodicallyTo10Dot3
				2	CountPeriodicallyTo10Dot6
				3	CountPeriodicallyTo10Dot9
				4	CountPeriodicallyTo10Dot12

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					5	CountPeriodicallyTo10Dot15
		GateControlActive	Boolean	Energy meter gate		
					0	Deactivated
					1	Active
		MinimumAndMaximumValueCalculationActive	Boolean	Minimum and maximum value calculation		
		MinimumAndMaximumValueCalculationGateActiv	Boolean	Minimum and maximum value calculation gate		
		PowerQualityAnalysisFunctionsActive	Boolean	Power quality analysis functions		
		ResidualCurrentAnalysisActive	Boolean	Residual current analysis		
		CurrentMeasurement	UInt64	Current measurement		
					0	Deactivated
					1	NeutralCurrentMeasurement
					2	NeutralCurrentCalculation
		NeutralConductorCurrentTransformerPrimaryCurr	UInt64	Current transformer primary current		
		NeutralConductorCurrentTransformerSecondaryCu	UInt64	Current transformer secondary current		
					1	Value1A
					2	Value5A
		OperatingRange	UInt64	Voltage measuring range		
					111	Value100V
					112	Value110V
					113	Value115V
					114	Value120V
					115	Value127V
					116	Value190V
					117	Value200V
					118	Value208V
					119	Value220V
					120	Value230V
					121	Value240V
					122	Value277V
					125	Value300V
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		HardwareInterruptEventName	String	HardwareInterruptEventName		
		HardwareInterruptOB	Object	HardwareInterruptInterrupt		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		HardwareInterruptPriority	UInt64	HardwareInterruptPriority		
		HardwareInterruptActive	Boolean	ActivateHWInterrupt		
					1	PseudoActive
					0	PseudoDeactivated
	Channel 0					
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		NominalValueCurrent	UInt32	Nominal value current		
		NominalValueVoltage	UInt32	Nominal value voltage		
		ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		OperatingHoursCounterActive	Boolean	Operating hours counter		
		OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
		CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
		CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
					0	Value1A
					2	Value5A
		TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
		TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		OvercurrentDetectionActive	Boolean	Detect overcurrent		
		OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
		DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
		VoltageDipLimitValue	UInt32	Voltage dip limit value		
		VoltageSwellLimitValue	UInt32	Voltage swell limit value		
		NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
		HarmonicsAnalysisActive	Boolean	Analyse harmonics		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		
		DetectPeakValueCurrentActive	Boolean	Detect peak value current		
		ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
	Channel 1					
		OvercurrentDetectionActive	Boolean	Detect overcurrent		
		OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
		DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
		VoltageDipLimitValue	UInt32	Voltage dip limit value		
		VoltageSwellLimitValue	UInt32	Voltage swell limit value		
		NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		NominalValueCurrent	UInt32	Nominal value current		
		NominalValueVoltage	UInt32	Nominal value voltage		
		ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		OperatingHoursCounterActive	Boolean	Operating hours counter		
		OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
		CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
		CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
					0	Value1A
					2	Value5A
		TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
		TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		HarmonicsAnalysisActive	Boolean	Analyse harmonics		
		DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		DetectPeakValueCurrentActive	Boolean	Detect peak value current		
		ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
	Channel 2					
		OvercurrentDetectionActive	Boolean	Detect overcurrent		
		OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
		DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
		VoltageDipLimitValue	UInt32	Voltage dip limit value		
		VoltageSwellLimitValue	UInt32	Voltage swell limit value		
		NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		NominalValueCurrent	UInt32	Nominal value current		
		NominalValueVoltage	UInt32	Nominal value voltage		
		ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		OperatingHoursCounterActive	Boolean	Operating hours counter		
		OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
		CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
		CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
					0	Value1A
					2	Value5A
		TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
		TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		HarmonicsAnalysisActive	Boolean	Analyse harmonics		
		DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		
		DetectPeakValueCurrentActive	Boolean	Detect peak value current		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
		MappingId	int64			
		MappingMeasuredVariable	string			
		MappingUnit	string			
		MappingDataType	string			
		MappingIAddress	int64			
		MappingMinValue	string			
		MappingMaxValue	string			
		MappingId	int64			
		MappingMeasuredVariable	string			
		MappingUnit	string			
		MappingDataType	string			
		MappingIAddress	int64			
		MappingMinValue	string			
		MappingMaxValue	string			
		MappingId	int64			
		MappingMeasuredVariable	string			
		MappingUnit	string			
		MappingDataType	string			
		MappingMinValue	string			
		MappingMaxValue	string			
		MappingByteOffset	int64			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
		RecordingActive	bool			
					0	Deactivated
					1	Activate
		RecordingInterval	uint64			
		CategoryStartTrigger	uint32			
					8	DiagnosticsInterruptL1
					9	DiagnosticsInterruptL2
					10	DiagnosticsInterruptL3
					11	DqMeasuredValueRecording
					0	NotUsed
					1	PowerQualityAnalysisQualifier
					2	QualifierL1
					5	QualifierL1l2l3
					3	QualifierL2
					4	QualifierL3
					6	StatusEnergyCounters
					7	StatusLimitViolation
		RecordingMode	uint32			
					0	Disable
					1	RingBuffer
					2	Single
		StartTrigger	uint32			
					225	Bit0Id225
					226	Bit1Id226
					227	Bit2Id227
					228	Bit3Id228
					229	Bit4Id229
					230	Bit5Id230
					231	Bit6Id231
					232	Bit7Id232
					160	ChannelIsTemporarilyUnavailableId160
					192	ChannelIsTemporarilyUnavailableId192
					224	ChannelIsTemporarilyUnavailableId224

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					12	CurrentPeakL1EventOccuredId012
					20	CurrentPeakL2EventOccuredId020
					28	CurrentPeakL3EventOccuredId028
					113	Gw1Id113
					122	Gw10Id122
					123	Gw11Id123
					124	Gw12Id124
					125	Gw13Id125
					126	Gw14Id126
					127	Gw15Id127
					128	Gw16Id128
					114	Gw2Id114
					115	Gw3Id115
					116	Gw4Id116
					117	Gw5Id117
					118	Gw6Id118
					119	Gw7Id119
					120	Gw8Id120
					121	Gw9Id121
					151	HardwareInterruptLostId151
					183	HardwareInterruptLostId183
					215	HardwareInterruptLostId215
					95	HarmonicAnalysisIsRunningId095
					34	MeasuredValuesIl1OkId034
					82	MeasuredValuesIl1OkId082
					50	MeasuredValuesIl2OkId050
					84	MeasuredValuesIl2OkId084
					66	MeasuredValuesIl3OkId066
					86	MeasuredValuesIl3OkId086
					33	MeasuredValuesUl1OkId033
					81	MeasuredValuesUl1OkId081
					49	MeasuredValuesUl2OkId049
					83	MeasuredValuesUl2OkId083

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					65	MeasuredValuesUl3OkId065
					85	MeasuredValuesUl3OkId085
					0	NotUsedId000
					48	OperatingQuadrantL1HighId048
					88	OperatingQuadrantL1HighId088
					47	OperatingQuadrantL1LowId047
					87	OperatingQuadrantL1LowId087
					64	OperatingQuadrantL2HighId064
					90	OperatingQuadrantL2HighId090
					63	OperatingQuadrantL2LowId063
					89	OperatingQuadrantL2LowId089
					80	OperatingQuadrantL3HighId080
					92	OperatingQuadrantL3HighId092
					79	OperatingQuadrantL3LowId079
					91	OperatingQuadrantL3LowId091
					16	OvercurrentL1EventActiveId016
					13	OvercurrentL1EventOccuredId013
					24	OvercurrentL2EventActiveId024
					21	OvercurrentL2EventOccuredId021
					32	OvercurrentL3EventActiveId032
					29	OvercurrentL3EventOccuredId029
					98	OverflowActiveEnergyExportL1Id098
					103	OverflowActiveEnergyExportL2Id103
					108	OverflowActiveEnergyExportL3Id108
					97	OverflowActiveEnergyImportL1Id097
					102	OverflowActiveEnergyImportL2Id102
					107	OverflowActiveEnergyImportL3Id107
					101	OverflowApparentEnergyL1Id101
					106	OverflowApparentEnergyL2Id106
					111	OverflowApparentEnergyL3Id111
					136	OverflowCalculatedValuesId136
					168	OverflowCalculatedValuesId168
					200	OverflowCalculatedValuesId200

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					100	OverflowReactiveEnergyExportL1Id100
					105	OverflowReactiveEnergyExportL2Id105
					110	OverflowReactiveEnergyExportL3Id110
					99	OverflowReactiveEnergyImportL1Id099
					104	OverflowReactiveEnergyImportL2Id104
					109	OverflowReactiveEnergyImportL3Id109
					132	OverflowVoltageId132
					164	OverflowVoltageId164
					196	OverflowVoltageId196
					133	OverloadId133
					165	OverloadId165
					197	OverloadId197
					145	ParameterAssignmentErrorId145
					177	ParameterAssignmentErrorId177
					209	ParameterAssignmentErrorId209
					155	PoorQualityId155
					187	PoorQualityId187
					219	PoorQualityId219
					94	RotatoryFieldStatusHighId094
					93	RotatoryFieldStatusLowId093
					1	StatusOfHarmonicsAnalysisBit0Id001
					2	StatusOfHarmonicsAnalysisBit1Id002
					3	StatusOfHarmonicsAnalysisBit2Id003
					4	StatusOfHarmonicsAnalysisBit3Id004
					5	StatusOfHarmonicsAnalysisBit4Id005
					6	StatusOfHarmonicsAnalysisBit5Id006
					146	SupplyVoltageMissingId146
					178	SupplyVoltageMissingId178
					210	SupplyVoltageMissingId210
					96	TimeOfDaySynchronizationOkId096
					131	UnderflowVoltageId131
					163	UnderflowVoltageId163
					195	UnderflowVoltageId195

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					14	VoltageDipL1EventActiveId014
					9	VoltageDipL1EventOccuredId009
					22	VoltageDipL2EventActiveId022
					17	VoltageDipL2EventOccuredId017
					30	VoltageDipL3EventActiveId030
					25	VoltageDipL3EventOccuredId025
					11	VoltagePeakL1EventOccuredId011
					19	VoltagePeakL2EventOccuredId019
					27	VoltagePeakL3EventOccuredId027
					15	VoltageSwellL1EventActiveId015
					10	VoltageSwellL1EventOccuredId010
					23	VoltageSwellL2EventActiveId023
					18	VoltageSwellL2EventOccuredId018
					31	VoltageSwellL3EventActiveId031
					26	VoltageSwellL3EventOccuredId026
		CategoryStopTrigger	uint32			
					0	NotUsed
					8	DiagnosticsInterruptL1
					9	DiagnosticsInterruptL2
					10	DiagnosticsInterruptL3
					11	DqMeasuredValueRecording
					1	PowerQualityAnalysisQualifier
					2	QualifierL1
					5	QualifierL1l2l3
					3	QualifierL2
					4	QualifierL3
					6	StatusEnergyCounters
					7	StatusLimitViolation
		StopTrigger	uint32			
					225	Bit0Id225
					226	Bit1Id226
					227	Bit2Id227
					228	Bit3Id228

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					229	Bit4Id229
					230	Bit5Id230
					231	Bit6Id231
					232	Bit7Id232
					160	ChannelIsTemporarilyUnavailableId160
					192	ChannelIsTemporarilyUnavailableId192
					224	ChannelIsTemporarilyUnavailableId224
					12	CurrentPeakL1EventOccuredId012
					20	CurrentPeakL2EventOccuredId020
					28	CurrentPeakL3EventOccuredId028
					113	Gw1Id113
					122	Gw10Id122
					123	Gw11Id123
					124	Gw12Id124
					125	Gw13Id125
					126	Gw14Id126
					127	Gw15Id127
					128	Gw16Id128
					114	Gw2Id114
					115	Gw3Id115
					116	Gw4Id116
					117	Gw5Id117
					118	Gw6Id118
					119	Gw7Id119
					120	Gw8Id120
					121	Gw9Id121
					151	HardwareInterruptLostId151
					183	HardwareInterruptLostId183
					215	HardwareInterruptLostId215
					95	HarmonicAnalysisIsRunningId095
					34	MeasuredValuesIl1OkId034
					82	MeasuredValuesIl1OkId082
					50	MeasuredValuesIl2OkId050

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					84	MeasuredValuesIl2OkId084
					66	MeasuredValuesIl3OkId066
					86	MeasuredValuesIl3OkId086
					33	MeasuredValuesUl1OkId033
					81	MeasuredValuesUl1OkId081
					49	MeasuredValuesUl2OkId049
					83	MeasuredValuesUl2OkId083
					65	MeasuredValuesUl3OkId065
					85	MeasuredValuesUl3OkId085
					0	NotUsedId000
					48	OperatingQuadrantL1HighId048
					88	OperatingQuadrantL1HighId088
					47	OperatingQuadrantL1LowId047
					87	OperatingQuadrantL1LowId087
					64	OperatingQuadrantL2HighId064
					90	OperatingQuadrantL2HighId090
					63	OperatingQuadrantL2LowId063
					89	OperatingQuadrantL2LowId089
					80	OperatingQuadrantL3HighId080
					92	OperatingQuadrantL3HighId092
					79	OperatingQuadrantL3LowId079
					91	OperatingQuadrantL3LowId091
					16	OvercurrentL1EventActiveId016
					13	OvercurrentL1EventOccuredId013
					24	OvercurrentL2EventActiveId024
					21	OvercurrentL2EventOccuredId021
					32	OvercurrentL3EventActiveId032
					29	OvercurrentL3EventOccuredId029
					98	OverflowActiveEnergyExportL1Id098
					103	OverflowActiveEnergyExportL2Id103
					108	OverflowActiveEnergyExportL3Id108
					97	OverflowActiveEnergyImportL1Id097
					102	OverflowActiveEnergyImportL2Id102

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					107	OverflowActiveEnergyImportL3Id107
					101	OverflowApparentEnergyL1Id101
					106	OverflowApparentEnergyL2Id106
					111	OverflowApparentEnergyL3Id111
					136	OverflowCalculatedValuesId136
					168	OverflowCalculatedValuesId168
					200	OverflowCalculatedValuesId200
					100	OverflowReactiveEnergyExportL1Id100
					105	OverflowReactiveEnergyExportL2Id105
					110	OverflowReactiveEnergyExportL3Id110
					99	OverflowReactiveEnergyImportL1Id099
					104	OverflowReactiveEnergyImportL2Id104
					109	OverflowReactiveEnergyImportL3Id109
					132	OverflowVoltageId132
					164	OverflowVoltageId164
					196	OverflowVoltageId196
					133	OverloadId133
					165	OverloadId165
					197	OverloadId197
					145	ParameterAssignmentErrorId145
					177	ParameterAssignmentErrorId177
					209	ParameterAssignmentErrorId209
					155	PoorQualityId155
					187	PoorQualityId187
					219	PoorQualityId219
					94	RotatoryFieldStatusHighId094
					93	RotatoryFieldStatusLowId093
					1	StatusOfHarmonicsAnalysisBit0Id001
					2	StatusOfHarmonicsAnalysisBit1Id002
					3	StatusOfHarmonicsAnalysisBit2Id003
					4	StatusOfHarmonicsAnalysisBit3Id004
					5	StatusOfHarmonicsAnalysisBit4Id005
					6	StatusOfHarmonicsAnalysisBit5Id006

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					146	SupplyVoltageMissingId146
					178	SupplyVoltageMissingId178
					210	SupplyVoltageMissingId210
					96	TimeOfDaySynchronizationOkId096
					131	UnderflowVoltageId131
					163	UnderflowVoltageId163
					195	UnderflowVoltageId195
					14	VoltageDipL1EventActiveId014
					9	VoltageDipL1EventOccuredId009
					22	VoltageDipL2EventActiveId022
					17	VoltageDipL2EventOccuredId017
					30	VoltageDipL3EventActiveId030
					25	VoltageDipL3EventOccuredId025
					11	VoltagePeakL1EventOccuredId011
					19	VoltagePeakL2EventOccuredId019
					27	VoltagePeakL3EventOccuredId027
					15	VoltageSwellL1EventActiveId015
					10	VoltageSwellL1EventOccuredId010
					23	VoltageSwellL2EventActiveId023
					18	VoltageSwellL2EventOccuredId018
					31	VoltageSwellL3EventActiveId031
					26	VoltageSwellL3EventOccuredId026
		HardwareInterruptMeasuredValueRecordingActive	bool			
					1	Activate
					0	Deactivated
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					5	Module
					4	NeutralConductor
		RecordingActive	bool			
					0	Deactivated
					1	Activate
		RecordingInterval	uint64			
		CategoryStartTrigger	uint32			
					8	DiagnosticsInterruptL1
					9	DiagnosticsInterruptL2
					10	DiagnosticsInterruptL3
					11	DqMeasuredValueRecording
					0	NotUsed
					1	PowerQualityAnalysisQualifier
					2	QualifierL1
					5	QualifierL1l2l3
					3	QualifierL2
					4	QualifierL3
					6	StatusEnergyCounters
					7	StatusLimitViolation
		RecordingMode	uint32			
					0	Disable
					1	RingBuffer
					2	Single
		StartTrigger	uint32			
					225	Bit0Id225
					226	Bit1Id226
					227	Bit2Id227
					228	Bit3Id228
					229	Bit4Id229
					230	Bit5Id230
					231	Bit6Id231
					232	Bit7Id232
					160	ChannelIsTemporarilyUnavailableId160

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					192	ChannelIsTemporarilyUnavailableId192
					224	ChannelIsTemporarilyUnavailableId224
					12	CurrentPeakL1EventOccuredId012
					20	CurrentPeakL2EventOccuredId020
					28	CurrentPeakL3EventOccuredId028
					113	Gw1Id113
					122	Gw10Id122
					123	Gw11Id123
					124	Gw12Id124
					125	Gw13Id125
					126	Gw14Id126
					127	Gw15Id127
					128	Gw16Id128
					114	Gw2Id114
					115	Gw3Id115
					116	Gw4Id116
					117	Gw5Id117
					118	Gw6Id118
					119	Gw7Id119
					120	Gw8Id120
					121	Gw9Id121
					151	HardwareInterruptLostId151
					183	HardwareInterruptLostId183
					215	HardwareInterruptLostId215
					95	HarmonicAnalysisIsRunningId095
					34	MeasuredValuesIl1OkId034
					82	MeasuredValuesIl1OkId082
					50	MeasuredValuesIl2OkId050
					84	MeasuredValuesIl2OkId084
					66	MeasuredValuesIl3OkId066
					86	MeasuredValuesIl3OkId086
					33	MeasuredValuesUl1OkId033
					81	MeasuredValuesUl1OkId081

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					49	MeasuredValuesUl2OkId049
					83	MeasuredValuesUl2OkId083
					65	MeasuredValuesUl3OkId065
					85	MeasuredValuesUl3OkId085
					0	NotUsedId000
					48	OperatingQuadrantL1HighId048
					88	OperatingQuadrantL1HighId088
					47	OperatingQuadrantL1LowId047
					87	OperatingQuadrantL1LowId087
					64	OperatingQuadrantL2HighId064
					90	OperatingQuadrantL2HighId090
					63	OperatingQuadrantL2LowId063
					89	OperatingQuadrantL2LowId089
					80	OperatingQuadrantL3HighId080
					92	OperatingQuadrantL3HighId092
					79	OperatingQuadrantL3LowId079
					91	OperatingQuadrantL3LowId091
					16	OvercurrentL1EventActiveId016
					13	OvercurrentL1EventOccuredId013
					24	OvercurrentL2EventActiveId024
					21	OvercurrentL2EventOccuredId021
					32	OvercurrentL3EventActiveId032
					29	OvercurrentL3EventOccuredId029
					98	OverflowActiveEnergyExportL1Id098
					103	OverflowActiveEnergyExportL2Id103
					108	OverflowActiveEnergyExportL3Id108
					97	OverflowActiveEnergyImportL1Id097
					102	OverflowActiveEnergyImportL2Id102
					107	OverflowActiveEnergyImportL3Id107
					101	OverflowApparentEnergyL1Id101
					106	OverflowApparentEnergyL2Id106
					111	OverflowApparentEnergyL3Id111
					136	OverflowCalculatedValuesId136

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					168	OverflowCalculatedValuesId168
					200	OverflowCalculatedValuesId200
					100	OverflowReactiveEnergyExportL1Id100
					105	OverflowReactiveEnergyExportL2Id105
					110	OverflowReactiveEnergyExportL3Id110
					99	OverflowReactiveEnergyImportL1Id099
					104	OverflowReactiveEnergyImportL2Id104
					109	OverflowReactiveEnergyImportL3Id109
					132	OverflowVoltageId132
					164	OverflowVoltageId164
					196	OverflowVoltageId196
					133	OverloadId133
					165	OverloadId165
					197	OverloadId197
					145	ParameterAssignmentErrorId145
					177	ParameterAssignmentErrorId177
					209	ParameterAssignmentErrorId209
					155	PoorQualityId155
					187	PoorQualityId187
					219	PoorQualityId219
					94	RotatoryFieldStatusHighId094
					93	RotatoryFieldStatusLowId093
					1	StatusOfHarmonicsAnalysisBit0Id001
					2	StatusOfHarmonicsAnalysisBit1Id002
					3	StatusOfHarmonicsAnalysisBit2Id003
					4	StatusOfHarmonicsAnalysisBit3Id004
					5	StatusOfHarmonicsAnalysisBit4Id005
					6	StatusOfHarmonicsAnalysisBit5Id006
					146	SupplyVoltageMissingId146
					178	SupplyVoltageMissingId178
					210	SupplyVoltageMissingId210
					96	TimeOfDaySynchronizationOkId096
					131	UnderflowVoltageId131

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					163	UnderflowVoltageId163
					195	UnderflowVoltageId195
					14	VoltageDipL1EventActiveId014
					9	VoltageDipL1EventOccuredId009
					22	VoltageDipL2EventActiveId022
					17	VoltageDipL2EventOccuredId017
					30	VoltageDipL3EventActiveId030
					25	VoltageDipL3EventOccuredId025
					11	VoltagePeakL1EventOccuredId011
					19	VoltagePeakL2EventOccuredId019
					27	VoltagePeakL3EventOccuredId027
					15	VoltageSwellL1EventActiveId015
					10	VoltageSwellL1EventOccuredId010
					23	VoltageSwellL2EventActiveId023
					18	VoltageSwellL2EventOccuredId018
					31	VoltageSwellL3EventActiveId031
					26	VoltageSwellL3EventOccuredId026
		CategoryStopTrigger	uint32			
					0	NotUsed
					8	DiagnosticsInterruptL1
					9	DiagnosticsInterruptL2
					10	DiagnosticsInterruptL3
					11	DqMeasuredValueRecording
					1	PowerQualityAnalysisQualifier
					2	QualifierL1
					5	QualifierL1l2l3
					3	QualifierL2
					4	QualifierL3
					6	StatusEnergyCounters
					7	StatusLimitViolation
		StopTrigger	uint32			
					225	Bit0Id225
					226	Bit1Id226

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					227	Bit2Id227
					228	Bit3Id228
					229	Bit4Id229
					230	Bit5Id230
					231	Bit6Id231
					232	Bit7Id232
					160	ChannelIsTemporarilyUnavailableId160
					192	ChannelIsTemporarilyUnavailableId192
					224	ChannelIsTemporarilyUnavailableId224
					12	CurrentPeakL1EventOccuredId012
					20	CurrentPeakL2EventOccuredId020
					28	CurrentPeakL3EventOccuredId028
					113	Gw1Id113
					122	Gw10Id122
					123	Gw11Id123
					124	Gw12Id124
					125	Gw13Id125
					126	Gw14Id126
					127	Gw15Id127
					128	Gw16Id128
					114	Gw2Id114
					115	Gw3Id115
					116	Gw4Id116
					117	Gw5Id117
					118	Gw6Id118
					119	Gw7Id119
					120	Gw8Id120
					121	Gw9Id121
					151	HardwareInterruptLostId151
					183	HardwareInterruptLostId183
					215	HardwareInterruptLostId215
					95	HarmonicAnalysisIsRunningId095
					34	MeasuredValuesIl1OkId034

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					82	MeasuredValuesIl1OkId082
					50	MeasuredValuesIl2OkId050
					84	MeasuredValuesIl2OkId084
					66	MeasuredValuesIl3OkId066
					86	MeasuredValuesIl3OkId086
					33	MeasuredValuesUl1OkId033
					81	MeasuredValuesUl1OkId081
					49	MeasuredValuesUl2OkId049
					83	MeasuredValuesUl2OkId083
					65	MeasuredValuesUl3OkId065
					85	MeasuredValuesUl3OkId085
					0	NotUsedId000
					48	OperatingQuadrantL1HighId048
					88	OperatingQuadrantL1HighId088
					47	OperatingQuadrantL1LowId047
					87	OperatingQuadrantL1LowId087
					64	OperatingQuadrantL2HighId064
					90	OperatingQuadrantL2HighId090
					63	OperatingQuadrantL2LowId063
					89	OperatingQuadrantL2LowId089
					80	OperatingQuadrantL3HighId080
					92	OperatingQuadrantL3HighId092
					79	OperatingQuadrantL3LowId079
					91	OperatingQuadrantL3LowId091
					16	OvercurrentL1EventActiveId016
					13	OvercurrentL1EventOccuredId013
					24	OvercurrentL2EventActiveId024
					21	OvercurrentL2EventOccuredId021
					32	OvercurrentL3EventActiveId032
					29	OvercurrentL3EventOccuredId029
					98	OverflowActiveEnergyExportL1Id098
					103	OverflowActiveEnergyExportL2Id103
					108	OverflowActiveEnergyExportL3Id108

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					97	OverflowActiveEnergyImportL1Id097
					102	OverflowActiveEnergyImportL2Id102
					107	OverflowActiveEnergyImportL3Id107
					101	OverflowApparentEnergyL1Id101
					106	OverflowApparentEnergyL2Id106
					111	OverflowApparentEnergyL3Id111
					136	OverflowCalculatedValuesId136
					168	OverflowCalculatedValuesId168
					200	OverflowCalculatedValuesId200
					100	OverflowReactiveEnergyExportL1Id100
					105	OverflowReactiveEnergyExportL2Id105
					110	OverflowReactiveEnergyExportL3Id110
					99	OverflowReactiveEnergyImportL1Id099
					104	OverflowReactiveEnergyImportL2Id104
					109	OverflowReactiveEnergyImportL3Id109
					132	OverflowVoltageId132
					164	OverflowVoltageId164
					196	OverflowVoltageId196
					133	OverloadId133
					165	OverloadId165
					197	OverloadId197
					145	ParameterAssignmentErrorId145
					177	ParameterAssignmentErrorId177
					209	ParameterAssignmentErrorId209
					155	PoorQualityId155
					187	PoorQualityId187
					219	PoorQualityId219
					94	RotatoryFieldStatusHighId094
					93	RotatoryFieldStatusLowId093
					1	StatusOfHarmonicsAnalysisBit0Id001
					2	StatusOfHarmonicsAnalysisBit1Id002
					3	StatusOfHarmonicsAnalysisBit2Id003
					4	StatusOfHarmonicsAnalysisBit3Id004

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0CU0 - V8.0						
					5	StatusOfHarmonicsAnalysisBit4Id005
					6	StatusOfHarmonicsAnalysisBit5Id006
					146	SupplyVoltageMissingId146
					178	SupplyVoltageMissingId178
					210	SupplyVoltageMissingId210
					96	TimeOfDaySynchronizationOkId096
					131	UnderflowVoltageId131
					163	UnderflowVoltageId163
					195	UnderflowVoltageId195
					14	VoltageDipL1EventActiveId014
					9	VoltageDipL1EventOccuredId009
					22	VoltageDipL2EventActiveId022
					17	VoltageDipL2EventOccuredId017
					30	VoltageDipL3EventActiveId030
					25	VoltageDipL3EventOccuredId025
					11	VoltagePeakL1EventOccuredId011
					19	VoltagePeakL2EventOccuredId019
					27	VoltagePeakL3EventOccuredId027
					15	VoltageSwellL1EventActiveId015
					10	VoltageSwellL1EventOccuredId010
					23	VoltageSwellL2EventActiveId023
					18	VoltageSwellL2EventOccuredId018
					31	VoltageSwellL3EventActiveId031
					26	VoltageSwellL3EventOccuredId026
		HardwareInterruptMeasuredValueRecordingActive	bool			
					1	Activate
					0	Deactivated
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Name	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		TypeName	String	InvariantTypeName		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
		UserDataMappingActive	Boolean	Enable user data mapping		
		ModuleVariant	UInt64	Module version		
					0	Value32BytesIOr12BytesO
					6	EeIndustryMeasuredDataProfileE3
					5	EeIndustryMeasuredDataProfileE2
					4	EeIndustryMeasuredDataProfileE1
					3	EeIndustryMeasuredDataProfileE0
					1	Value2BytesIOr2BytesO
					2	UserSpecific

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		ProcessDataVariant	UInt64	Process data variant		
					128	Hex80
					129	EeIndustryMeasuredDataProfileE0Hex81
					130	EeIndustryMeasuredDataProfileE1Hex82
					131	EeIndustryMeasuredDataProfileE2Hex83
					132	EeIndustryMeasuredDataProfileE3Hex84
					1	UserSpecificUserDataHex01
					2	UserSpecificUserDataHex02
					254	TotalPowersL1l2l3HexFe
					253	ActivePowersL1l2l3HexFd
					252	ReactivePowersL1l2l3HexFc
					251	ApparentPowerL1l2l3HexFb
					250	BasicMeasuredValuesL1l2l3HexFa
					249	TotalEnergyL1l2l3HexF9
					248	EnergyL1HexF8
					247	EnergyL2HexF7
					246	EnergyL3HexF6
					245	BasicVariablesThreePhaseMeasurementL1l2l3HexF5
					244	ReactivePowerCompensationL1l2l3HexF4
					240	QualityValuesThreePhaseMeasurementL1l2l3HexF0
					239	EnergyL1l2l3OverflowCounterHexEf
					159	BasicVariablesSinglePhaseMeasurementL1Hex9F
					158	SinglePhaseMeasurementL1WithVoltageScalingValueHex9E
					157	BasicVariablesSinglePhaseMeasurementL2Hex9D
					156	SinglePhaseMeasurementL2WithVoltageScalingValueHex9C
					155	BasicVariablesSinglePhaseMeasurementL3Hex9B
					154	SinglePhaseMeasurementL3WithVoltageScalingValueHex9A

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					227	EeIndustryMeasuredDataProfileE3HexE3

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					226	EeIndustryMeasuredDataProfileE2HexE2
					225	EeIndustryMeasuredDataProfileE1HexE1
					224	EeIndustryMeasuredDataProfileE0HexE0
		ConnectionType	UInt64	Connection type		
					0	None
					1	Value1P2w1Phase2Wire
					2	Value3P4w3Phase4Wire
					4	Value3P4w13Phase4WireSymmetricalLoad
					5	Value3X1p2w3X1PhaseEach2Conductors
					6	Value2P3w2Phase3Wire
					7	Value3P3w3Phase3Wire
					8	Value3P3w13Phase3WireSymmetricalLoad
		LineFrequency	UInt64	Line frequency		
					2	Value50Hz
					1	Value60Hz
		EndValueEnergyCounter	UInt64	End value energy meter		
					0	NoEndValueCountIndefinitely
					1	CountPeriodicallyTo10Dot3
					2	CountPeriodicallyTo10Dot6
					3	CountPeriodicallyTo10Dot9
					4	CountPeriodicallyTo10Dot12
					5	CountPeriodicallyTo10Dot15
		CurrentTransformerForL1L2L3AndNeutralConducto	UInt64	Current transformer for L1, L2, L3 and neutral conductor		
					1	RogowskiCoil
					0	CurrentToVoltageConverter
		GateControlActive	Boolean	Energy meter gate		
					0	Deactivated
					1	Active
		MinimumAndMaximumValueCalculationActive	Boolean	Minimum and maximum value calculation		
		MinimumAndMaximumValueCalculationGateActiv	Boolean	Minimum and maximum value calculation gate		
		CurrentMeasurement	UInt64	Current measurement		
					0	Deactivated
					1	NeutralCurrentMeasurement

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					2	NeutralCurrentCalculation
		NeutralConductorCurrentTransformerPrimaryRate	UInt64	Current transformer primary rated current		
		NeutralConductorCurrentTransformerSecondaryVo	UInt64	Current transformer secondary voltage		
		OperatingRange	UInt64	Voltage measuring range		
					111	Value100V
					112	Value110V
					113	Value115V
					114	Value120V
					115	Value127V
					116	Value190V
					117	Value200V
					118	Value208V
					119	Value220V
					120	Value230V
					121	Value240V
					122	Value277V
					125	Value300V
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		HardwareInterruptEventName	String	HardwareInterruptEventName		
		HardwareInterruptOB	Object	HardwareInterruptInterrupt		
		HardwareInterruptPriority	UInt64	HardwareInterruptPriority		
		HardwareInterruptActive	Boolean	ActivateHWInterrupt		
					1	PseudoActive
					0	PseudoDeactivated
	Channel 0					
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		NominalValueCurrent	UInt32	Nominal value current		
		NominalValueVoltage	UInt32	Nominal value voltage		
		ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		OperatingHoursCounterActive	Boolean	Operating hours counter		
		OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
		TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
		TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		CurrentTransformerSecondaryVoltage	UInt32	Current transformer secondary voltage		
		CurrentTransformerPrimaryRatedCurrent	UInt32	Current transformer primary rated current		
		ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
	Channel 1					
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		NominalValueCurrent	UInt32	Nominal value current		
		NominalValueVoltage	UInt32	Nominal value voltage		
		ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		OperatingHoursCounterActive	Boolean	Operating hours counter		
		OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
		TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
		TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		CurrentTransformerSecondaryVoltage	UInt32	Current transformer secondary voltage		
		CurrentTransformerPrimaryRatedCurrent	UInt32	Current transformer primary rated current		
		ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
	Channel 2					
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		NominalValueCurrent	UInt32	Nominal value current		
		NominalValueVoltage	UInt32	Nominal value voltage		
		ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		OperatingHoursCounterActive	Boolean	Operating hours counter		
		OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
		TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
		TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		CurrentTransformerSecondaryVoltage	UInt32	Current transformer secondary voltage		
		CurrentTransformerPrimaryRatedCurrent	UInt32	Current transformer primary rated current		
		ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
		MappingId	int64			
		MappingMeasuredVariable	string			
		MappingUnit	string			
		MappingDataType	string			
		MappingIAddress	int64			
		MappingMinValue	string			
		MappingMaxValue	string			
		MappingId	int64			
		MappingMeasuredVariable	string			
		MappingUnit	string			
		MappingDataType	string			
		MappingIAddress	int64			
		MappingMinValue	string			
		MappingMaxValue	string			
		MappingId	int64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		MappingMeasuredVariable	string			
		MappingUnit	string			
		MappingDataType	string			
		MappingMinValue	string			
		MappingMaxValue	string			
		MappingByteOffset	int64			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0BU0 - V8.0						
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Name	String			
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		TypeName	String	InvariantTypeName		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
		UserDataMappingActive	Boolean	Enable user data mapping		
		ModuleVariant	UInt64	Module version		
					0	Value32BytesIOr12BytesO
					6	EeIndustryMeasuredDataProfileE3
					5	EeIndustryMeasuredDataProfileE2
					4	EeIndustryMeasuredDataProfileE1
					3	EeIndustryMeasuredDataProfileE0
					1	Value2BytesIOr2BytesO
					2	UserSpecific

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		ProcessDataVariant	UInt64	Process data variant		
					128	Hex80
					129	EeIndustryMeasuredDataProfileE0Hex81
					130	EeIndustryMeasuredDataProfileE1Hex82
					131	EeIndustryMeasuredDataProfileE2Hex83
					132	EeIndustryMeasuredDataProfileE3Hex84
					1	UserSpecificUserDataHex01
					2	UserSpecificUserDataHex02
					254	TotalPowersL1l2l3HexFe
					253	ActivePowersL1l2l3HexFd
					252	ReactivePowersL1l2l3HexFc
					251	ApparentPowerL1l2l3HexFb
					250	BasicMeasuredValuesL1l2l3HexFa
					249	TotalEnergyL1l2l3HexF9
					248	EnergyL1HexF8
					247	EnergyL2HexF7
					246	EnergyL3HexF6
					245	BasicVariablesThreePhaseMeasurementL1l2l3HexF5
					244	ReactivePowerCompensationL1l2l3HexF4
					240	QualityValuesThreePhaseMeasurementL1l2l3HexF0
					239	EnergyL1l2l3OverflowCounterHexEf
					159	BasicVariablesSinglePhaseMeasurementL1Hex9F
					158	SinglePhaseMeasurementL1WithVoltageScalingValueHex9E
					157	BasicVariablesSinglePhaseMeasurementL2Hex9D
					156	SinglePhaseMeasurementL2WithVoltageScalingValueHex9C
					155	BasicVariablesSinglePhaseMeasurementL3Hex9B
					154	SinglePhaseMeasurementL3WithVoltageScalingValueHex9A

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					227	EeIndustryMeasuredDataProfileE3HexE3

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0					
				226	EeIndustryMeasuredDataProfileE2HexE2
				225	EeIndustryMeasuredDataProfileE1HexE1
				224	EeIndustryMeasuredDataProfileE0HexE0
	ConnectionType	UInt64	Connection type		
				0	None
				1	Value1P2w1Phase2Wire
				2	Value3P4w3Phase4Wire
				3	Value3P4wi3PhaseCurrentMeasurement4Wire
				4	Value3P4w13Phase4WireSymmetricalLoad
				5	Value3X1p2w3X1PhaseEach2Conductors
				6	Value2P3w2Phase3Wire
				7	Value3P3w3Phase3Wire
				8	Value3P3w13Phase3WireSymmetricalLoad
	LineFrequency	UInt64	Line frequency		
				2	Value50Hz
				1	Value60Hz
	EndValueEnergyCounter	UInt64	End value energy meter		
				0	NoEndValueCountIndefinitely
				1	CountPeriodicallyTo10Dot3
				2	CountPeriodicallyTo10Dot6
				3	CountPeriodicallyTo10Dot9
				4	CountPeriodicallyTo10Dot12
				5	CountPeriodicallyTo10Dot15
	CurrentTransformerForL1L2L3AndNeutralConducto	UInt64	Current transformer for L1, L2, L3 and neutral conductor		
				1	RogowskiCoil
				0	CurrentToVoltageConverter
	GateControlActive	Boolean	Energy meter gate		
				0	Deactivated
				1	Active
	MinimumAndMaximumValueCalculationActive	Boolean	Minimum and maximum value calculation		
	MinimumAndMaximumValueCalculationGateActiv	Boolean	Minimum and maximum value calculation gate		
	PowerQualityAnalysisFunctionsActive	Boolean	Power quality analysis functions		
	ResidualCurrentAnalysisActive	Boolean	Residual current analysis		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		CurrentMeasurement	UInt64	Current measurement		
					0	Deactivated
					1	NeutralCurrentMeasurement
					2	NeutralCurrentCalculation
		NeutralConductorCurrentTransformerPrimaryRate	UInt64	Current transformer primary rated current		
		NeutralConductorCurrentTransformerSecondaryVo	UInt64	Current transformer secondary voltage		
		OperatingRange	UInt64	Voltage measuring range		
					111	Value100V
					112	Value110V
					113	Value115V
					114	Value120V
					115	Value127V
					116	Value190V
					117	Value200V
					118	Value208V
					119	Value220V
					120	Value230V
					121	Value240V
					122	Value277V
					125	Value300V
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		HardwareInterruptEventName	String	HardwareInterruptEventName		
		HardwareInterruptOB	Object	HardwareInterruptInterrupt		
		HardwareInterruptPriority	UInt64	HardwareInterruptPriority		
		HardwareInterruptActive	Boolean	ActivateHWInterrupt		
					0	PseudoDeactivated
					1	PseudoActive
	Channel 0					
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0					
	NominalValueCurrent	UInt32	Nominal value current		
	NominalValueVoltage	UInt32	Nominal value voltage		
	ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	OperatingHoursCounterActive	Boolean	Operating hours counter		
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
	TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
	LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	OvercurrentDetectionActive	Boolean	Detect overcurrent		
	OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
	DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
	VoltageDipLimitValue	UInt32	Voltage dip limit value		
	VoltageSwellLimitValue	UInt32	Voltage swell limit value		
	NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
	HarmonicsAnalysisActive	Boolean	Analyse harmonics		
	DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		
	DetectPeakValueCurrentActive	Boolean	Detect peak value current		
	CurrentTransformerSecondaryVoltage	UInt32	Current transformer secondary voltage		
	CurrentTransformerPrimaryRatedCurrent	UInt32	Current transformer primary rated current		
	ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
Channel 1					
	OvercurrentDetectionActive	Boolean	Detect overcurrent		
	OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
	DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
	VoltageDipLimitValue	UInt32	Voltage dip limit value		
	VoltageSwellLimitValue	UInt32	Voltage swell limit value		
	NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		NominalValueCurrent	UInt32	Nominal value current		
		NominalValueVoltage	UInt32	Nominal value voltage		
		ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		OperatingHoursCounterActive	Boolean	Operating hours counter		
		OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
		TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
		TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		HarmonicsAnalysisActive	Boolean	Analyse harmonics		
		DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		
		DetectPeakValueCurrentActive	Boolean	Detect peak value current		
		CurrentTransformerSecondaryVoltage	UInt32	Current transformer secondary voltage		
		CurrentTransformerPrimaryRatedCurrent	UInt32	Current transformer primary rated current		
		ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
	Channel 2					
		OvercurrentDetectionActive	Boolean	Detect overcurrent		
		OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
		DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
		VoltageDipLimitValue	UInt32	Voltage dip limit value		
		VoltageSwellLimitValue	UInt32	Voltage swell limit value		
		NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		NominalValueCurrent	UInt32	Nominal value current		
		NominalValueVoltage	UInt32	Nominal value voltage		
		ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		OperatingHoursCounterActive	Boolean	Operating hours counter		
		OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
		TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
		TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		HarmonicsAnalysisActive	Boolean	Analyse harmonics		
		DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		
		DetectPeakValueCurrentActive	Boolean	Detect peak value current		
		CurrentTransformerSecondaryVoltage	UInt32	Current transformer secondary voltage		
		CurrentTransformerPrimaryRatedCurrent	UInt32	Current transformer primary rated current		
		ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
		MappingId	int64			
		MappingMeasuredVariable	string			
		MappingUnit	string			
		MappingDataType	string			
		MappingIAddress	int64			
		MappingMinValue	string			
		MappingMaxValue	string			
		MappingId	int64			
		MappingMeasuredVariable	string			
		MappingUnit	string			
		MappingDataType	string			
		MappingIAddress	int64			
		MappingMinValue	string			
		MappingMaxValue	string			
		MappingId	int64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		MappingMeasuredVariable	string			
		MappingUnit	string			
		MappingDataType	string			
		MappingMinValue	string			
		MappingMaxValue	string			
		MappingByteOffset	int64			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		LimitValue	double			
		LimitValueType	uint32			
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	uint32			
		DelayTimeForLimitMonitoring	uint32			
					1	Value1S
					10	Value10S
					2	Value2S
					3	Value3S
					4	Value4S
					5	Value5S
					6	Value6S
					7	Value7S
					8	Value8S
					9	Value9S
					0	None
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		LimitMonitoringActive	bool			
					0	Deactivated
					1	Activate
		LimitMonitoringGateActive	bool			
		HardwareInterruptLimitActive	bool			
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		RecordingActive	bool			
					0	Deactivated
					1	Activate
		RecordingInterval	uint64			
		CategoryStartTrigger	uint32			
					8	DiagnosticsInterruptL1
					9	DiagnosticsInterruptL2
					10	DiagnosticsInterruptL3
					11	DqMeasuredValueRecording
					0	NotUsed
					1	PowerQualityAnalysisQualifier
					2	QualifierL1
					5	QualifierL1l2l3
					3	QualifierL2
					4	QualifierL3
					6	StatusEnergyCounters
					7	StatusLimitViolation

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		RecordingMode	uint32			
					0	Disable
					1	RingBuffer
					2	Single
		StartTrigger	uint32			
					225	Bit0Id225
					226	Bit1Id226
					227	Bit2Id227
					228	Bit3Id228
					229	Bit4Id229
					230	Bit5Id230
					231	Bit6Id231
					232	Bit7Id232
					160	ChannelIsTemporarilyUnavailableId160
					192	ChannelIsTemporarilyUnavailableId192
					224	ChannelIsTemporarilyUnavailableId224
					12	CurrentPeakL1EventOccuredId012
					20	CurrentPeakL2EventOccuredId020
					28	CurrentPeakL3EventOccuredId028
					113	Gw1Id113
					122	Gw10Id122
					123	Gw11Id123
					124	Gw12Id124
					125	Gw13Id125
					126	Gw14Id126
					127	Gw15Id127
					128	Gw16Id128
					114	Gw2Id114
					115	Gw3Id115
					116	Gw4Id116
					117	Gw5Id117
					118	Gw6Id118
					119	Gw7Id119

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					120	Gw8Id120
					121	Gw9Id121
					151	HardwareInterruptLostId151
					183	HardwareInterruptLostId183
					215	HardwareInterruptLostId215
					95	HarmonicAnalysisIsRunningId095
					34	MeasuredValuesIl1OkId034
					82	MeasuredValuesIl1OkId082
					50	MeasuredValuesIl2OkId050
					84	MeasuredValuesIl2OkId084
					66	MeasuredValuesIl3OkId066
					86	MeasuredValuesIl3OkId086
					33	MeasuredValuesUl1OkId033
					81	MeasuredValuesUl1OkId081
					49	MeasuredValuesUl2OkId049
					83	MeasuredValuesUl2OkId083
					65	MeasuredValuesUl3OkId065
					85	MeasuredValuesUl3OkId085
					0	NotUsedId000
					48	OperatingQuadrantL1HighId048
					88	OperatingQuadrantL1HighId088
					47	OperatingQuadrantL1LowId047
					87	OperatingQuadrantL1LowId087
					64	OperatingQuadrantL2HighId064
					90	OperatingQuadrantL2HighId090
					63	OperatingQuadrantL2LowId063
					89	OperatingQuadrantL2LowId089
					80	OperatingQuadrantL3HighId080
					92	OperatingQuadrantL3HighId092
					79	OperatingQuadrantL3LowId079
					91	OperatingQuadrantL3LowId091
					16	OvercurrentL1EventActiveId016
					13	OvercurrentL1EventOccuredId013

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					24	OvercurrentL2EventActiveId024
					21	OvercurrentL2EventOccuredId021
					32	OvercurrentL3EventActiveId032
					29	OvercurrentL3EventOccuredId029
					98	OverflowActiveEnergyExportL1Id098
					103	OverflowActiveEnergyExportL2Id103
					108	OverflowActiveEnergyExportL3Id108
					97	OverflowActiveEnergyImportL1Id097
					102	OverflowActiveEnergyImportL2Id102
					107	OverflowActiveEnergyImportL3Id107
					101	OverflowApparentEnergyL1Id101
					106	OverflowApparentEnergyL2Id106
					111	OverflowApparentEnergyL3Id111
					136	OverflowCalculatedValuesId136
					168	OverflowCalculatedValuesId168
					200	OverflowCalculatedValuesId200
					100	OverflowReactiveEnergyExportL1Id100
					105	OverflowReactiveEnergyExportL2Id105
					110	OverflowReactiveEnergyExportL3Id110
					99	OverflowReactiveEnergyImportL1Id099
					104	OverflowReactiveEnergyImportL2Id104
					109	OverflowReactiveEnergyImportL3Id109
					132	OverflowVoltageId132
					164	OverflowVoltageId164
					196	OverflowVoltageId196
					133	OverloadId133
					165	OverloadId165
					197	OverloadId197
					145	ParameterAssignmentErrorId145
					177	ParameterAssignmentErrorId177
					209	ParameterAssignmentErrorId209
					155	PoorQualityId155
					187	PoorQualityId187

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					219	PoorQualityId219
					94	RotatoryFieldStatusHighId094
					93	RotatoryFieldStatusLowId093
					1	StatusOfHarmonicsAnalysisBit0Id001
					2	StatusOfHarmonicsAnalysisBit1Id002
					3	StatusOfHarmonicsAnalysisBit2Id003
					4	StatusOfHarmonicsAnalysisBit3Id004
					5	StatusOfHarmonicsAnalysisBit4Id005
					6	StatusOfHarmonicsAnalysisBit5Id006
					146	SupplyVoltageMissingId146
					178	SupplyVoltageMissingId178
					210	SupplyVoltageMissingId210
					96	TimeOfDaySynchronizationOkId096
					131	UnderflowVoltageId131
					163	UnderflowVoltageId163
					195	UnderflowVoltageId195
					14	VoltageDipL1EventActiveId014
					9	VoltageDipL1EventOccuredId009
					22	VoltageDipL2EventActiveId022
					17	VoltageDipL2EventOccuredId017
					30	VoltageDipL3EventActiveId030
					25	VoltageDipL3EventOccuredId025
					11	VoltagePeakL1EventOccuredId011
					19	VoltagePeakL2EventOccuredId019
					27	VoltagePeakL3EventOccuredId027
					15	VoltageSwellL1EventActiveId015
					10	VoltageSwellL1EventOccuredId010
					23	VoltageSwellL2EventActiveId023
					18	VoltageSwellL2EventOccuredId018
					31	VoltageSwellL3EventActiveId031
					26	VoltageSwellL3EventOccuredId026
		CategoryStopTrigger	uint32			
					0	NotUsed

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					8	DiagnosticsInterruptL1
					9	DiagnosticsInterruptL2
					10	DiagnosticsInterruptL3
					11	DqMeasuredValueRecording
					1	PowerQualityAnalysisQualifier
					2	QualifierL1
					5	QualifierL1l2l3
					3	QualifierL2
					4	QualifierL3
					6	StatusEnergyCounters
					7	StatusLimitViolation
		StopTrigger	uint32			
					225	Bit0Id225
					226	Bit1Id226
					227	Bit2Id227
					228	Bit3Id228
					229	Bit4Id229
					230	Bit5Id230
					231	Bit6Id231
					232	Bit7Id232
					160	ChannelIsTemporarilyUnavailableId160
					192	ChannelIsTemporarilyUnavailableId192
					224	ChannelIsTemporarilyUnavailableId224
					12	CurrentPeakL1EventOccuredId012
					20	CurrentPeakL2EventOccuredId020
					28	CurrentPeakL3EventOccuredId028
					113	Gw1Id113
					122	Gw10Id122
					123	Gw11Id123
					124	Gw12Id124
					125	Gw13Id125
					126	Gw14Id126
					127	Gw15Id127

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					128	Gw16Id128
					114	Gw2Id114
					115	Gw3Id115
					116	Gw4Id116
					117	Gw5Id117
					118	Gw6Id118
					119	Gw7Id119
					120	Gw8Id120
					121	Gw9Id121
					151	HardwareInterruptLostId151
					183	HardwareInterruptLostId183
					215	HardwareInterruptLostId215
					95	HarmonicAnalysisIsRunningId095
					34	MeasuredValuesIl1OkId034
					82	MeasuredValuesIl1OkId082
					50	MeasuredValuesIl2OkId050
					84	MeasuredValuesIl2OkId084
					66	MeasuredValuesIl3OkId066
					86	MeasuredValuesIl3OkId086
					33	MeasuredValuesUl1OkId033
					81	MeasuredValuesUl1OkId081
					49	MeasuredValuesUl2OkId049
					83	MeasuredValuesUl2OkId083
					65	MeasuredValuesUl3OkId065
					85	MeasuredValuesUl3OkId085
					0	NotUsedId000
					48	OperatingQuadrantL1HighId048
					88	OperatingQuadrantL1HighId088
					47	OperatingQuadrantL1LowId047
					87	OperatingQuadrantL1LowId087
					64	OperatingQuadrantL2HighId064
					90	OperatingQuadrantL2HighId090
					63	OperatingQuadrantL2LowId063

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					89	OperatingQuadrantL2LowId089
					80	OperatingQuadrantL3HighId080
					92	OperatingQuadrantL3HighId092
					79	OperatingQuadrantL3LowId079
					91	OperatingQuadrantL3LowId091
					16	OvercurrentL1EventActiveId016
					13	OvercurrentL1EventOccuredId013
					24	OvercurrentL2EventActiveId024
					21	OvercurrentL2EventOccuredId021
					32	OvercurrentL3EventActiveId032
					29	OvercurrentL3EventOccuredId029
					98	OverflowActiveEnergyExportL1Id098
					103	OverflowActiveEnergyExportL2Id103
					108	OverflowActiveEnergyExportL3Id108
					97	OverflowActiveEnergyImportL1Id097
					102	OverflowActiveEnergyImportL2Id102
					107	OverflowActiveEnergyImportL3Id107
					101	OverflowApparentEnergyL1Id101
					106	OverflowApparentEnergyL2Id106
					111	OverflowApparentEnergyL3Id111
					136	OverflowCalculatedValuesId136
					168	OverflowCalculatedValuesId168
					200	OverflowCalculatedValuesId200
					100	OverflowReactiveEnergyExportL1Id100
					105	OverflowReactiveEnergyExportL2Id105
					110	OverflowReactiveEnergyExportL3Id110
					99	OverflowReactiveEnergyImportL1Id099
					104	OverflowReactiveEnergyImportL2Id104
					109	OverflowReactiveEnergyImportL3Id109
					132	OverflowVoltageId132
					164	OverflowVoltageId164
					196	OverflowVoltageId196
					133	OverloadId133

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					165	OverloadId165
					197	OverloadId197
					145	ParameterAssignmentErrorId145
					177	ParameterAssignmentErrorId177
					209	ParameterAssignmentErrorId209
					155	PoorQualityId155
					187	PoorQualityId187
					219	PoorQualityId219
					94	RotatoryFieldStatusHighId094
					93	RotatoryFieldStatusLowId093
					1	StatusOfHarmonicsAnalysisBit0Id001
					2	StatusOfHarmonicsAnalysisBit1Id002
					3	StatusOfHarmonicsAnalysisBit2Id003
					4	StatusOfHarmonicsAnalysisBit3Id004
					5	StatusOfHarmonicsAnalysisBit4Id005
					6	StatusOfHarmonicsAnalysisBit5Id006
					146	SupplyVoltageMissingId146
					178	SupplyVoltageMissingId178
					210	SupplyVoltageMissingId210
					96	TimeOfDaySynchronizationOkId096
					131	UnderflowVoltageId131
					163	UnderflowVoltageId163
					195	UnderflowVoltageId195
					14	VoltageDipL1EventActiveId014
					9	VoltageDipL1EventOccuredId009
					22	VoltageDipL2EventActiveId022
					17	VoltageDipL2EventOccuredId017
					30	VoltageDipL3EventActiveId030
					25	VoltageDipL3EventOccuredId025
					11	VoltagePeakL1EventOccuredId011
					19	VoltagePeakL2EventOccuredId019
					27	VoltagePeakL3EventOccuredId027
					15	VoltageSwellL1EventActiveId015

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					10	VoltageSwellL1EventOccuredId010
					23	VoltageSwellL2EventActiveId023
					18	VoltageSwellL2EventOccuredId018
					31	VoltageSwellL3EventActiveId031
					26	VoltageSwellL3EventOccuredId026
		HardwareInterruptMeasuredValueRecordingActive	bool			
					1	Activate
					0	Deactivated
		Category	uint64			
					4	Energies
					3	Powers
					5	QualityData
					6	Other
					2	Voltages
					1	Currents
					7	PowerQualityValues
					8	Harmonics
					0	None
		SubCategory	uint64			
					0	None
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					13	General
					19	PowerFactors
					20	PhaseAngles

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					21	ActiveFactorsCosPhi
					22	Asymmetries
					23	TotalHarmonicDistortions
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					15	Frequencies
					14	LimitMonitoring
					16	OperatingHoursCounter
		MeasurementID	uint64			
		RelationMeasuredVariable	uint64			
					0	Disable
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					5	Module
					4	NeutralConductor
		RecordingActive	bool			
					0	Deactivated
					1	Activate
		RecordingInterval	uint64			
		CategoryStartTrigger	uint32			
					8	DiagnosticsInterruptL1
					9	DiagnosticsInterruptL2
					10	DiagnosticsInterruptL3
					11	DqMeasuredValueRecording
					0	NotUsed
					1	PowerQualityAnalysisQualifier
					2	QualifierL1
					5	QualifierL1l2l3
					3	QualifierL2
					4	QualifierL3

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					6	StatusEnergyCounters
					7	StatusLimitViolation
		RecordingMode	uint32			
					0	Disable
					1	RingBuffer
					2	Single
		StartTrigger	uint32			
					225	Bit0Id225
					226	Bit1Id226
					227	Bit2Id227
					228	Bit3Id228
					229	Bit4Id229
					230	Bit5Id230
					231	Bit6Id231
					232	Bit7Id232
					160	ChannelIsTemporarilyUnavailableId160
					192	ChannelIsTemporarilyUnavailableId192
					224	ChannelIsTemporarilyUnavailableId224
					12	CurrentPeakL1EventOccuredId012
					20	CurrentPeakL2EventOccuredId020
					28	CurrentPeakL3EventOccuredId028
					113	Gw1Id113
					122	Gw10Id122
					123	Gw11Id123
					124	Gw12Id124
					125	Gw13Id125
					126	Gw14Id126
					127	Gw15Id127
					128	Gw16Id128
					114	Gw2Id114
					115	Gw3Id115
					116	Gw4Id116
					117	Gw5Id117

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					118	Gw6Id118
					119	Gw7Id119
					120	Gw8Id120
					121	Gw9Id121
					151	HardwareInterruptLostId151
					183	HardwareInterruptLostId183
					215	HardwareInterruptLostId215
					95	HarmonicAnalysisIsRunningId095
					34	MeasuredValuesIl1OkId034
					82	MeasuredValuesIl1OkId082
					50	MeasuredValuesIl2OkId050
					84	MeasuredValuesIl2OkId084
					66	MeasuredValuesIl3OkId066
					86	MeasuredValuesIl3OkId086
					33	MeasuredValuesUl1OkId033
					81	MeasuredValuesUl1OkId081
					49	MeasuredValuesUl2OkId049
					83	MeasuredValuesUl2OkId083
					65	MeasuredValuesUl3OkId065
					85	MeasuredValuesUl3OkId085
					0	NotUsedId000
					48	OperatingQuadrantL1HighId048
					88	OperatingQuadrantL1HighId088
					47	OperatingQuadrantL1LowId047
					87	OperatingQuadrantL1LowId087
					64	OperatingQuadrantL2HighId064
					90	OperatingQuadrantL2HighId090
					63	OperatingQuadrantL2LowId063
					89	OperatingQuadrantL2LowId089
					80	OperatingQuadrantL3HighId080
					92	OperatingQuadrantL3HighId092
					79	OperatingQuadrantL3LowId079
					91	OperatingQuadrantL3LowId091

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					16	OvercurrentL1EventActiveId016
					13	OvercurrentL1EventOccuredId013
					24	OvercurrentL2EventActiveId024
					21	OvercurrentL2EventOccuredId021
					32	OvercurrentL3EventActiveId032
					29	OvercurrentL3EventOccuredId029
					98	OverflowActiveEnergyExportL1Id098
					103	OverflowActiveEnergyExportL2Id103
					108	OverflowActiveEnergyExportL3Id108
					97	OverflowActiveEnergyImportL1Id097
					102	OverflowActiveEnergyImportL2Id102
					107	OverflowActiveEnergyImportL3Id107
					101	OverflowApparentEnergyL1Id101
					106	OverflowApparentEnergyL2Id106
					111	OverflowApparentEnergyL3Id111
					136	OverflowCalculatedValuesId136
					168	OverflowCalculatedValuesId168
					200	OverflowCalculatedValuesId200
					100	OverflowReactiveEnergyExportL1Id100
					105	OverflowReactiveEnergyExportL2Id105
					110	OverflowReactiveEnergyExportL3Id110
					99	OverflowReactiveEnergyImportL1Id099
					104	OverflowReactiveEnergyImportL2Id104
					109	OverflowReactiveEnergyImportL3Id109
					132	OverflowVoltageId132
					164	OverflowVoltageId164
					196	OverflowVoltageId196
					133	OverloadId133
					165	OverloadId165
					197	OverloadId197
					145	ParameterAssignmentErrorId145
					177	ParameterAssignmentErrorId177
					209	ParameterAssignmentErrorId209

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					155	PoorQualityId155
					187	PoorQualityId187
					219	PoorQualityId219
					94	RotatoryFieldStatusHighId094
					93	RotatoryFieldStatusLowId093
					1	StatusOfHarmonicsAnalysisBit0Id001
					2	StatusOfHarmonicsAnalysisBit1Id002
					3	StatusOfHarmonicsAnalysisBit2Id003
					4	StatusOfHarmonicsAnalysisBit3Id004
					5	StatusOfHarmonicsAnalysisBit4Id005
					6	StatusOfHarmonicsAnalysisBit5Id006
					146	SupplyVoltageMissingId146
					178	SupplyVoltageMissingId178
					210	SupplyVoltageMissingId210
					96	TimeOfDaySynchronizationOkId096
					131	UnderflowVoltageId131
					163	UnderflowVoltageId163
					195	UnderflowVoltageId195
					14	VoltageDipL1EventActiveId014
					9	VoltageDipL1EventOccuredId009
					22	VoltageDipL2EventActiveId022
					17	VoltageDipL2EventOccuredId017
					30	VoltageDipL3EventActiveId030
					25	VoltageDipL3EventOccuredId025
					11	VoltagePeakL1EventOccuredId011
					19	VoltagePeakL2EventOccuredId019
					27	VoltagePeakL3EventOccuredId027
					15	VoltageSwellL1EventActiveId015
					10	VoltageSwellL1EventOccuredId010
					23	VoltageSwellL2EventActiveId023
					18	VoltageSwellL2EventOccuredId018
					31	VoltageSwellL3EventActiveId031
					26	VoltageSwellL3EventOccuredId026

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
		CategoryStopTrigger	uint32			
					0	NotUsed
					8	DiagnosticsInterruptL1
					9	DiagnosticsInterruptL2
					10	DiagnosticsInterruptL3
					11	DqMeasuredValueRecording
					1	PowerQualityAnalysisQualifier
					2	QualifierL1
					5	QualifierL1l2l3
					3	QualifierL2
					4	QualifierL3
					6	StatusEnergyCounters
					7	StatusLimitViolation
		StopTrigger	uint32			
					225	Bit0Id225
					226	Bit1Id226
					227	Bit2Id227
					228	Bit3Id228
					229	Bit4Id229
					230	Bit5Id230
					231	Bit6Id231
					232	Bit7Id232
					160	ChannelIsTemporarilyUnavailableId160
					192	ChannelIsTemporarilyUnavailableId192
					224	ChannelIsTemporarilyUnavailableId224
					12	CurrentPeakL1EventOccuredId012
					20	CurrentPeakL2EventOccuredId020
					28	CurrentPeakL3EventOccuredId028
					113	Gw1Id113
					122	Gw10Id122
					123	Gw11Id123
					124	Gw12Id124
					125	Gw13Id125

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0					
				126	Gw14Id126
				127	Gw15Id127
				128	Gw16Id128
				114	Gw2Id114
				115	Gw3Id115
				116	Gw4Id116
				117	Gw5Id117
				118	Gw6Id118
				119	Gw7Id119
				120	Gw8Id120
				121	Gw9Id121
				151	HardwareInterruptLostId151
				183	HardwareInterruptLostId183
				215	HardwareInterruptLostId215
				95	HarmonicAnalysisIsRunningId095
				34	MeasuredValuesIl1OkId034
				82	MeasuredValuesIl1OkId082
				50	MeasuredValuesIl2OkId050
				84	MeasuredValuesIl2OkId084
				66	MeasuredValuesIl3OkId066
				86	MeasuredValuesIl3OkId086
				33	MeasuredValuesUl1OkId033
				81	MeasuredValuesUl1OkId081
				49	MeasuredValuesUl2OkId049
				83	MeasuredValuesUl2OkId083
				65	MeasuredValuesUl3OkId065
				85	MeasuredValuesUl3OkId085
				0	NotUsedId000
				48	OperatingQuadrantL1HighId048
				88	OperatingQuadrantL1HighId088
				47	OperatingQuadrantL1LowId047
				87	OperatingQuadrantL1LowId087
				64	OperatingQuadrantL2HighId064

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					90	OperatingQuadrantL2HighId090
					63	OperatingQuadrantL2LowId063
					89	OperatingQuadrantL2LowId089
					80	OperatingQuadrantL3HighId080
					92	OperatingQuadrantL3HighId092
					79	OperatingQuadrantL3LowId079
					91	OperatingQuadrantL3LowId091
					16	OvercurrentL1EventActiveId016
					13	OvercurrentL1EventOccuredId013
					24	OvercurrentL2EventActiveId024
					21	OvercurrentL2EventOccuredId021
					32	OvercurrentL3EventActiveId032
					29	OvercurrentL3EventOccuredId029
					98	OverflowActiveEnergyExportL1Id098
					103	OverflowActiveEnergyExportL2Id103
					108	OverflowActiveEnergyExportL3Id108
					97	OverflowActiveEnergyImportL1Id097
					102	OverflowActiveEnergyImportL2Id102
					107	OverflowActiveEnergyImportL3Id107
					101	OverflowApparentEnergyL1Id101
					106	OverflowApparentEnergyL2Id106
					111	OverflowApparentEnergyL3Id111
					136	OverflowCalculatedValuesId136
					168	OverflowCalculatedValuesId168
					200	OverflowCalculatedValuesId200
					100	OverflowReactiveEnergyExportL1Id100
					105	OverflowReactiveEnergyExportL2Id105
					110	OverflowReactiveEnergyExportL3Id110
					99	OverflowReactiveEnergyImportL1Id099
					104	OverflowReactiveEnergyImportL2Id104
					109	OverflowReactiveEnergyImportL3Id109
					132	OverflowVoltageId132
					164	OverflowVoltageId164

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					196	OverflowVoltageId196
					133	OverloadId133
					165	OverloadId165
					197	OverloadId197
					145	ParameterAssignmentErrorId145
					177	ParameterAssignmentErrorId177
					209	ParameterAssignmentErrorId209
					155	PoorQualityId155
					187	PoorQualityId187
					219	PoorQualityId219
					94	RotatoryFieldStatusHighId094
					93	RotatoryFieldStatusLowId093
					1	StatusOfHarmonicsAnalysisBit0Id001
					2	StatusOfHarmonicsAnalysisBit1Id002
					3	StatusOfHarmonicsAnalysisBit2Id003
					4	StatusOfHarmonicsAnalysisBit3Id004
					5	StatusOfHarmonicsAnalysisBit4Id005
					6	StatusOfHarmonicsAnalysisBit5Id006
					146	SupplyVoltageMissingId146
					178	SupplyVoltageMissingId178
					210	SupplyVoltageMissingId210
					96	TimeOfDaySynchronizationOkId096
					131	UnderflowVoltageId131
					163	UnderflowVoltageId163
					195	UnderflowVoltageId195
					14	VoltageDipL1EventActiveId014
					9	VoltageDipL1EventOccuredId009
					22	VoltageDipL2EventActiveId022
					17	VoltageDipL2EventOccuredId017
					30	VoltageDipL3EventActiveId030
					25	VoltageDipL3EventOccuredId025
					11	VoltagePeakL1EventOccuredId011
					19	VoltagePeakL2EventOccuredId019

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA21-0CU0 - V8.0						
					27	VoltagePeakL3EventOccuredId027
					15	VoltageSwellL1EventActiveId015
					10	VoltageSwellL1EventOccuredId010
					23	VoltageSwellL2EventActiveId023
					18	VoltageSwellL2EventOccuredId018
					31	VoltageSwellL3EventActiveId031
					26	VoltageSwellL3EventOccuredId026
		HardwareInterruptMeasuredValueRecordingActive	bool			
					1	Activate
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0CU0 - V6.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
		HardwareInterruptActive	Boolean	Hardware interrupt		
					1	PseudoActive
					0	PseudoDeactivated
		HardwareInterruptEventName	String			
		HardwareInterruptOB				
		HardwareInterruptPriority	UInt64			
		PositionNumber	Int32	Index		
		ConnectionType	UInt64	Connection type		
					0	None
					1	Value1P2w1Phase2Wire

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0CU0 - V6.0						
					2	Value3P4w3Phase4Wire
					3	Value3P4wi3PhaseCurrentMeasurement4Wire
					4	Value3P4w13Phase4WireSymmetricalLoad
					5	Value3X1p2w3X1PhaseEach2Conductors
					6	Value2P3w2Phase3Wire
					7	Value3P3w3Phase3Wire
					8	Value3P3w13Phase3WireSymmetricalLoad
		OperatingRange	UInt64	Voltage measuring range		
					111	Value100V
					112	Value110V
					113	Value115V
					114	Value120V
					115	Value127V
					116	Value190V
					117	Value200V
					118	Value208V
					119	Value220V
					120	Value230V
					121	Value240V
					122	Value277V
		LineFrequency	UInt64	Line frequency		
					2	Value50Hz
					1	Value60Hz
		EndValueEnergyCounter	UInt64	End value energy meter		
					0	NoEndValueCountIndefinitely
					1	CountPeriodicallyTo10Dot3
					2	CountPeriodicallyTo10Dot6
					3	CountPeriodicallyTo10Dot9
					4	CountPeriodicallyTo10Dot12
					5	CountPeriodicallyTo10Dot15
		GateControlActive	Boolean	Energy meter gate		
					0	Deactivated
					1	Active
		MinimumAndMaximumValueCalculationActive	Boolean	Minimum and maximum value calculation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0CU0 - V6.0						
		MinimumAndMaximumValueCalculationGateActive	Boolean	Minimum and maximum value calculation gate		
		PowerQualityAnalysisFunctionsActive	Boolean	Power quality analysis functions		
		ResidualCurrentAnalysisActive	Boolean	Residual current analysis		
		CurrentMeasurement	UInt64	Current measurement		
					0	Deactivated
					1	NeutralCurrentMeasurement
					2	NeutralCurrentCalculation
		NeutralConductorCurrentTransformerPrimaryCurre	UInt64	Current transformer primary current		
		NeutralConductorCurrentTransformerSecondaryCur	UInt64	Current transformer secondary current		
					1	Value1A
					2	Value5A
		UserDataMappingActive	Boolean	Enable user data mapping		
		ModuleVariant	UInt64	Module version		
					0	Value32BytesIOr12BytesO
					6	EeIndustryMeasuredDataProfileE3
					5	EeIndustryMeasuredDataProfileE2
					4	EeIndustryMeasuredDataProfileE1
					3	EeIndustryMeasuredDataProfileE0
					1	Value2BytesIOr2BytesO
					2	UserSpecific
		ProcessDataVariant	UInt64	Process data variant		
					128	Hex80
					129	EeIndustryMeasuredDataProfileE0Hex81
					130	EeIndustryMeasuredDataProfileE1Hex82
					131	EeIndustryMeasuredDataProfileE2Hex83
					132	EeIndustryMeasuredDataProfileE3Hex84
					1	UserSpecificUserDataHex01
					2	UserSpecificUserDataHex02
					254	TotalPowersL1l2l3HexFe
					253	ActivePowersL1l2l3HexFd
					252	ReactivePowersL1l2l3HexFc
					251	ApparentPowerL1l2l3HexFb
					250	BasicMeasuredValuesL1l2l3HexFa
					249	TotalEnergyL1l2l3HexF9

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0CU0 - V6.0						
					248	EnergyL1HexF8
					247	EnergyL2HexF7
					246	EnergyL3HexF6
					245	BasicVariablesThreePhaseMeasurementL1l2l3HexF5
					244	ReactivePowerCompensationL1l2l3HexF4
					240	QualityValuesThreePhaseMeasurementL1l2l3HexF0
					239	EnergyL1l2l3OverflowCounterHexEf
					159	BasicVariablesSinglePhaseMeasurementL1Hex9F
					158	SinglePhaseMeasurementL1WithVoltageScalingValueHex9E
					157	BasicVariablesSinglePhaseMeasurementL2Hex9D
					156	SinglePhaseMeasurementL2WithVoltageScalingValueHex9C
					155	BasicVariablesSinglePhaseMeasurementL3Hex9B
					154	SinglePhaseMeasurementL3WithVoltageScalingValueHex9A
					227	EeIndustryMeasuredDataProfileE3HexE3
					226	EeIndustryMeasuredDataProfileE2HexE2
					225	EeIndustryMeasuredDataProfileE1HexE1
					224	EeIndustryMeasuredDataProfileE0HexE0
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		NominalValueCurrent	UInt32	Nominal value current		
		NominalValueVoltage	UInt32	Nominal value voltage		
		ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0CU0 - V6.0					
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	OperatingHoursCounterActive	Boolean	Operating hours counter		
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
	CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
				0	Value1A
				2	Value5A
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
	TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
	LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	OvercurrentDetectionActive	Boolean	Detect overcurrent		
	OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
	DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
	VoltageDipLimitValue	UInt32	Voltage dip limit value		
	VoltageSwellLimitValue	UInt32	Voltage swell limit value		
	NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
	HarmonicsAnalysisActive	Boolean	Analyse harmonics		
	DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		
	DetectPeakValueCurrentActive	Boolean	Detect peak value current		
Channel 1					
	ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
	OvercurrentDetectionActive	Boolean	Detect overcurrent		
	OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
	DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
	VoltageDipLimitValue	UInt32	Voltage dip limit value		
	VoltageSwellLimitValue	UInt32	Voltage swell limit value		
	NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0CU0 - V6.0					
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	NominalValueCurrent	UInt32	Nominal value current		
	NominalValueVoltage	UInt32	Nominal value voltage		
	ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	OperatingHoursCounterActive	Boolean	Operating hours counter		
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
	CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
				0	Value1A
				2	Value5A
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
	TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
	LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	HarmonicsAnalysisActive	Boolean	Analyse harmonics		
	DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		
	DetectPeakValueCurrentActive	Boolean	Detect peak value current		
Channel 2					
	ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
	OvercurrentDetectionActive	Boolean	Detect overcurrent		
	OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
	DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
	VoltageDipLimitValue	UInt32	Voltage dip limit value		
	VoltageSwellLimitValue	UInt32	Voltage swell limit value		
	NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	NominalValueCurrent	UInt32	Nominal value current		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0CU0 - V6.0						
		NominalValueVoltage	UInt32	Nominal value voltage		
		ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		OperatingHoursCounterActive	Boolean	Operating hours counter		
		OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
		CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
		CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
					0	Value1A
					2	Value5A
		TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
		TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		HarmonicsAnalysisActive	Boolean	Analyse harmonics		
		DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		
		DetectPeakValueCurrentActive	Boolean	Detect peak value current		
		LimitMonitoringActive	Boolean	Limit monitoring		
		RelationMeasuredVariable	UInt64	Relation measured variable		
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					4	NeutralConductor
					5	Module
		Category	UInt64	Category		
					1	Currents
					2	Voltages
					3	Powers
					4	Energies
					6	Other
					7	PowerQualityValues
					8	Harmonics

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0CU0 - V6.0						
		SubCategory	UInt64	Subcategory		
					1	LineConductorCurrent
					3	LineToNeutralVoltageLN
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					16	OperatingHoursCounter
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					23	TotalHarmonicDistortions
					25	Qualifier
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					2	NeutralConductorCurrent
					4	LineToLineVoltageLL
					14	LimitMonitoring
					15	Frequencies
					17	Times
					22	Asymmetries
		MeasurementID	UInt64	Measured variable		
		LimitMonitoringGateActive	Boolean	Limit monitoring gate		
		HardwareInterruptLimitActive	Boolean	Hardware interrupt		
		LimitValue	Double	Limit		
		LimitValueType	UInt32	Type		
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	UInt32	Hysteresis for limit monitoring		
		DelayTimeForLimitMonitoring	UInt32	Delay time for limit monitoring		
					0	None
					1	Value1S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0CU0 - V6.0						
					2	Value2S
					3	Value3S
					10	Value10S
					9	Value9S
					8	Value8S
					7	Value7S
					6	Value6S
					5	Value5S
					4	Value4S
		MappingId	Int64	ID		
		MappingMeasuredVariable	String	Measured variable		
		MappingUnit	String	Unit		
		MappingDataType	String	Data type		
		MappingIAddress	Int64	I address		
		MappingMinValue	String	Min. value		
		MappingMaxValue	String	Max. value		
		MappingId	Int64	ID		
		MappingMeasuredVariable	String	Measured variable		
		MappingUnit	String	Unit		
		MappingDataType	String	Data type		
		MappingIAddress	Int64	I address		
		MappingMinValue	String	Min. value		
		MappingMaxValue	String	Max. value		
		MappingId	Int64	ID		
		MappingMeasuredVariable	String	Measured variable		
		MappingUnit	String	Unit		
		MappingDataType	String	Data type		
		MappingByteOffset	Int64	Byte offset		
		MappingMinValue	String	Min. value		
		MappingMaxValue	String	Max. value		
Module - 6ES7 134-6PA20-0CU0 - V6.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0CU0 - V6.0					
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
	HardwareInterruptActive	Boolean	Hardware interrupt		
				1	PseudoActive
				0	PseudoDeactivated
	HardwareInterruptEventName	String			
	HardwareInterruptOB				
	HardwareInterruptPriority	UInt64			
	PositionNumber	Int32	Index		
	ConnectionType	UInt64	Connection type		
				0	None
				1	Value1P2w1Phase2Wire
				2	Value3P4w3Phase4Wire
				3	Value3P4wi3PhaseCurrentMeasurement4Wire
				4	Value3P4w13Phase4WireSymmetricalLoad

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0CU0 - V6.0						
					5	Value3X1p2w3X1PhaseEach2Conductors
					6	Value2P3w2Phase3Wire
					7	Value3P3w3Phase3Wire
					8	Value3P3w13Phase3WireSymmetricalLoad
		OperatingRange	UInt64	Voltage measuring range		
					111	Value100V
					112	Value110V
					113	Value115V
					114	Value120V
					115	Value127V
					116	Value190V
					117	Value200V
					118	Value208V
					119	Value220V
					120	Value230V
					121	Value240V
					122	Value277V
		LineFrequency	UInt64	Line frequency		
					2	Value50Hz
					1	Value60Hz
		EndValueEnergyCounter	UInt64	End value energy meter		
					0	NoEndValueCountIndefinitely
					1	CountPeriodicallyTo10Dot3
					2	CountPeriodicallyTo10Dot6
					3	CountPeriodicallyTo10Dot9
					4	CountPeriodicallyTo10Dot12
					5	CountPeriodicallyTo10Dot15
		CurrentTransformerForL1L2L3AndNeutralConducto	UInt64	Current transformer for L1, L2, L3 and neutral conductor		
					1	RogowskiCoil
					0	CurrentToVoltageConverter
		GateControlActive	Boolean	Energy meter gate		
					0	Deactivated
					1	Active
		MinimumAndMaximumValueCalculationActive	Boolean	Minimum and maximum value calculation		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0CU0 - V6.0						
		MinimumAndMaximumValueCalculationGateActive	Boolean	Minimum and maximum value calculation gate		
		PowerQualityAnalysisFunctionsActive	Boolean	Power quality analysis functions		
		ResidualCurrentAnalysisActive	Boolean	Residual current analysis		
		CurrentMeasurement	UInt64	Current measurement		
					0	Deactivated
					1	NeutralCurrentMeasurement
					2	NeutralCurrentCalculation
		NeutralConductorCurrentTransformerPrimaryRated	UInt64	Current transformer primary rated current		
		NeutralConductorCurrentTransformerSecondaryVol	UInt64	Current transformer secondary voltage		
		UserDataMappingActive	Boolean	Enable user data mapping		
		ModuleVariant	UInt64	Module version		
					0	Value32BytesIOr12BytesO
					6	EeIndustryMeasuredDataProfileE3
					5	EeIndustryMeasuredDataProfileE2
					4	EeIndustryMeasuredDataProfileE1
					3	EeIndustryMeasuredDataProfileE0
					1	Value2BytesIOr2BytesO
					2	UserSpecific
		ProcessDataVariant	UInt64	Process data variant		
					128	Hex80
					129	EeIndustryMeasuredDataProfileE0Hex81
					130	EeIndustryMeasuredDataProfileE1Hex82
					131	EeIndustryMeasuredDataProfileE2Hex83
					132	EeIndustryMeasuredDataProfileE3Hex84
					1	UserSpecificUserDataHex01
					2	UserSpecificUserDataHex02
					254	TotalPowersL1l2l3HexFe
					253	ActivePowersL1l2l3HexFd
					252	ReactivePowersL1l2l3HexFc
					251	ApparentPowerL1l2l3HexFb
					250	BasicMeasuredValuesL1l2l3HexFa
					249	TotalEnergyL1l2l3HexF9
					248	EnergyL1HexF8
					247	EnergyL2HexF7

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0CU0 - V6.0					
				246	EnergyL3HexF6
				245	BasicVariablesThreePhaseMeasurementL1l2l3HexF5
				244	ReactivePowerCompensationL1l2l3HexF4
				240	QualityValuesThreePhaseMeasurementL1l2l3HexF0
				239	EnergyL1l2l3OverflowCounterHexEf
				159	BasicVariablesSinglePhaseMeasurementL1Hex9F
				158	SinglePhaseMeasurementL1WithVoltageScalingValueHex9E
				157	BasicVariablesSinglePhaseMeasurementL2Hex9D
				156	SinglePhaseMeasurementL2WithVoltageScalingValueHex9C
				155	BasicVariablesSinglePhaseMeasurementL3Hex9B
				154	SinglePhaseMeasurementL3WithVoltageScalingValueHex9A
				227	EeIndustryMeasuredDataProfileE3HexE3
				226	EeIndustryMeasuredDataProfileE2HexE2
				225	EeIndustryMeasuredDataProfileE1HexE1
				224	EeIndustryMeasuredDataProfileE0HexE0
	Name	String	Name		
	Comment	String	Comment		
Channel 0					
	ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	NominalValueCurrent	UInt32	Nominal value current		
	NominalValueVoltage	UInt32	Nominal value voltage		
	ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	OperatingHoursCounterActive	Boolean	Operating hours counter		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0CU0 - V6.0					
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
	TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
	LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	OvercurrentDetectionActive	Boolean	Detect overcurrent		
	OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
	DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
	VoltageDipLimitValue	UInt32	Voltage dip limit value		
	VoltageSwellLimitValue	UInt32	Voltage swell limit value		
	NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
	HarmonicsAnalysisActive	Boolean	Analyse harmonics		
	DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		
	DetectPeakValueCurrentActive	Boolean	Detect peak value current		
	CurrentTransformerSecondaryVoltage	UInt32	Current transformer secondary voltage		
	CurrentTransformerPrimaryRatedCurrent	UInt32	Current transformer primary rated current		
Channel 1					
	ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
	OvercurrentDetectionActive	Boolean	Detect overcurrent		
	OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
	DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
	VoltageDipLimitValue	UInt32	Voltage dip limit value		
	VoltageSwellLimitValue	UInt32	Voltage swell limit value		
	NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	NominalValueCurrent	UInt32	Nominal value current		
	NominalValueVoltage	UInt32	Nominal value voltage		
	ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0CU0 - V6.0					
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	OperatingHoursCounterActive	Boolean	Operating hours counter		
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
	TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
	LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	HarmonicsAnalysisActive	Boolean	Analyse harmonics		
	DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		
	DetectPeakValueCurrentActive	Boolean	Detect peak value current		
	CurrentTransformerSecondaryVoltage	UInt32	Current transformer secondary voltage		
	CurrentTransformerPrimaryRatedCurrent	UInt32	Current transformer primary rated current		
Channel 2					
	ToleranceFactorOvervoltageUndervoltageRatio	Int32	Tolerance factor overvoltage / undervoltage		
	OvercurrentDetectionActive	Boolean	Detect overcurrent		
	OvercurrentThresholdValue	UInt32	Overcurrent threshold value		
	DetectVoltageDipOrSwellActive	Boolean	Detect voltage dip / swell		
	VoltageDipLimitValue	UInt32	Voltage dip limit value		
	VoltageSwellLimitValue	UInt32	Voltage swell limit value		
	NumberOfCyclesForVoltageSwellAndDipAnalysis	UInt32	Number of cycles for voltage swell and dip analysis		
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsPowerQualityActive	Boolean	Diagnostics power quality		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	NominalValueCurrent	UInt32	Nominal value current		
	NominalValueVoltage	UInt32	Nominal value voltage		
	ToleranceFactorOvercurrent	UInt32	Tolerance factor overcurrent		
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	OperatingHoursCounterActive	Boolean	Operating hours counter		
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0CU0 - V6.0						
		TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		HarmonicsAnalysisActive	Boolean	Analyse harmonics		
		DetectPeakValueVoltageActive	Boolean	Detect peak value voltage		
		DetectPeakValueCurrentActive	Boolean	Detect peak value current		
		CurrentTransformerSecondaryVoltage	UInt32	Current transformer secondary voltage		
		CurrentTransformerPrimaryRatedCurrent	UInt32	Current transformer primary rated current		
		LimitMonitoringActive	Boolean	Limit monitoring		
		RelationMeasuredVariable	UInt64	Relation measured variable		
					1	LineConductor1
					2	LineConductor2
					3	LineConductor3
					4	NeutralConductor
					5	Module
		Category	UInt64	Category		
					1	Currents
					2	Voltages
					3	Powers
					4	Energies
					6	Other
					7	PowerQualityValues
					8	Harmonics
		SubCategory	UInt64	Subcategory		
					1	LineConductorCurrent
					3	LineToNeutralVoltageLN
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0CU0 - V6.0						
					16	OperatingHoursCounter
					19	PowerFactors
					20	PhaseAngles
					21	ActiveFactorsCosPhi
					23	TotalHarmonicDistortions
					25	Qualifier
					26	HarmonicOfTheLineToNeutralVoltageLN
					28	HarmonicOfTheLineConductorCurrent
					2	NeutralConductorCurrent
					4	LineToLineVoltageLL
					14	LimitMonitoring
					15	Frequencies
					17	Times
					22	Asymmetries
		MeasurementID	UInt64	Measured variable		
		LimitMonitoringGateActive	Boolean	Limit monitoring gate		
		HardwareInterruptLimitActive	Boolean	Hardware interrupt		
		LimitValue	Double	Limit		
		LimitValueType	UInt32	Type		
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	UInt32	Hysteresis for limit monitoring		
		DelayTimeForLimitMonitoring	UInt32	Delay time for limit monitoring		
					0	None
					1	Value1S
					2	Value2S
					3	Value3S
					10	Value10S
					9	Value9S
					8	Value8S
					7	Value7S
					6	Value6S
					5	Value5S
					4	Value4S

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0CU0 - V6.0						
		MappingId	Int64	ID		
		MappingMeasuredVariable	String	Measured variable		
		MappingUnit	String	Unit		
		MappingDataType	String	Data type		
		MappingIAddress	Int64	I address		
		MappingMinValue	String	Min. value		
		MappingMaxValue	String	Max. value		
		MappingId	Int64	ID		
		MappingMeasuredVariable	String	Measured variable		
		MappingUnit	String	Unit		
		MappingDataType	String	Data type		
		MappingIAddress	Int64	I address		
		MappingMinValue	String	Min. value		
		MappingMaxValue	String	Max. value		
		MappingId	Int64	ID		
		MappingMeasuredVariable	String	Measured variable		
		MappingUnit	String	Unit		
		MappingDataType	String	Data type		
		MappingByteOffset	Int64	Byte offset		
		MappingMinValue	String	Min. value		
		MappingMaxValue	String	Max. value		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0BD0 - V4.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	LineVoltageDiagnosticsActive	Boolean	Line voltage diagnostics		
	LineVoltageTolerance	UInt32	Line voltage tolerance		
	LineFrequency	UInt64	Line frequency		
				2	Value50Hz
				1	Value60Hz
	ModuleVariant	UInt64	Module version		
				0	Value32BytesIOr12BytesO
				6	EeIndustryMeasuredDataProfileE3
				5	EeIndustryMeasuredDataProfileE2
				4	EeIndustryMeasuredDataProfileE1
				3	EeIndustryMeasuredDataProfileE0

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0BD0 - V4.0						
					1	Value2BytesIOr2BytesO
					2	UserSpecific
		ProcessDataVariant	UInt64	Process data variant		
					129	EeIndustryMeasuredDataProfileE0Hex81
					130	EeIndustryMeasuredDataProfileE1Hex82
					131	EeIndustryMeasuredDataProfileE2Hex83
					132	EeIndustryMeasuredDataProfileE3Hex84
					1	UserSpecificUserDataHex01
					254	TotalPowersL1l2l3HexFe
					253	ActivePowersL1l2l3HexFd
					252	ReactivePowersL1l2l3HexFc
					251	ApparentPowerL1l2l3HexFb
					250	BasicMeasuredValuesL1l2l3HexFa
					249	TotalEnergyL1l2l3HexF9
					248	EnergyL1HexF8
					247	EnergyL2HexF7
					246	EnergyL3HexF6
					245	BasicVariablesThreePhaseMeasurementL1l2l3HexF5
					240	QualityValuesThreePhaseMeasurementL1l2l3HexF0
					239	EnergyL1l2l3OverflowCounterHexEf
					159	BasicVariablesSinglePhaseMeasurementL1Hex9F
					158	SinglePhaseMeasurementL1WithVoltageScalingValueHex9E
					157	BasicVariablesSinglePhaseMeasurementL2Hex9D
					156	SinglePhaseMeasurementL2WithVoltageScalingValueHex9C
					155	BasicVariablesSinglePhaseMeasurementL3Hex9B
					154	SinglePhaseMeasurementL3WithVoltageScalingValueHex9A
					227	EeIndustryMeasuredDataProfileE3HexE3
					226	EeIndustryMeasuredDataProfileE2HexE2
					225	EeIndustryMeasuredDataProfileE1HexE1

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0BD0 - V4.0						
					224	EeIndustryMeasuredDataProfileE0HexE0
		GateControlActive	Boolean	Energy meter gate		
					0	Deactivated
					1	Active
		MinimumAndMaximumValueCalculationActive	Boolean	Minimum and maximum value calculation		
		UserDataMappingActive	Boolean	Enable user data mapping		
		EndValueEnergyCounter	UInt64	End value energy meter		
					0	NoEndValueCountIndefinitely
					1	CountPeriodicallyTo10Dot3
					2	CountPeriodicallyTo10Dot6
					3	CountPeriodicallyTo10Dot9
					4	CountPeriodicallyTo10Dot12
					5	CountPeriodicallyTo10Dot15
		HardwareInterruptActive	Boolean	Hardware interrupt		
					1	PseudoActive
					0	PseudoDeactivated
		HardwareInterruptEventName	String			
		HardwareInterruptOB				
		HardwareInterruptPriority	UInt64			
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
		ConnectionType	UInt64	Connection type		
					0	None
					1	Value1P2w1Phase2Wire
					2	Value3P4w3Phase4Wire
					4	Value3P4w13Phase4WireSymmetricalLoad
					5	Value3X1p2w3X1PhaseEach2Conductors
					6	Value2P3w2Phase3Wire
		OperatingRange	UInt64	Voltage measuring range		
					111	Value100V
					120	Value230V
					121	Value240V
					122	Value277V

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0BD0 - V4.0					
				112	Value110V
				113	Value115V
				114	Value120V
				115	Value127V
				116	Value190V
				117	Value200V
				118	Value208V
				119	Value220V
Channel 0					
	DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
	CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
				0	Value1A
				2	Value5A
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	OperatingHoursCounterActive	Boolean	Operating hours counter		
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
	TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
	LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
Channel 1					
	DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0BD0 - V4.0					
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
	CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
				0	Value1A
				2	Value5A
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	OperatingHoursCounterActive	Boolean	Operating hours counter		
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
	TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
	LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
Channel 2					
	DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
	CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
				0	Value1A
				2	Value5A
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	OperatingHoursCounterActive	Boolean	Operating hours counter		
	OperatingHoursCounterGateActive	Boolean	Operating hours counter gate		
	TransformerPrimaryVoltage	UInt32	Transformer primary voltage		
	TransformerSecondaryVoltage	UInt32	Transformer secondary voltage		
	LowLimitCurrentMeasurement	UInt32	Low limit current measurement		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0BD0 - V4.0						
		LimitMonitoringActive	Boolean	Limit monitoring		
		Category	UInt64	Category		
					1	Currents
					2	Voltages
					3	Powers
					4	Energies
					5	QualityData
					6	Other
		SubCategory	UInt64	Subcategory		
					1	LineConductorCurrent
					2	NeutralConductorCurrent
					3	LineToNeutralVoltageLN
					4	LineToLineVoltageLL
					5	ApparentPowers
					6	ActivePowers
					7	ReactivePowers
					8	PowerFactorsOrPhaseAngle
					9	ApparentEnergies
					10	ActiveEnergies
					11	ReactiveEnergies
					12	MeasuredVariableRelatedQualityData
					14	LimitMonitoring
					15	Frequencies
					16	OperatingHoursCounter
		MeasurementID	UInt64	Measured variable		
		LimitMonitoringGateActive	Boolean	Limit monitoring gate		
		HardwareInterruptLimitActive	Boolean	Hardware interrupt		
		LimitValue	Double	Limit		
		LimitValueType	UInt32	Type		
					0	HighLimit
					1	LowLimit
		HysteresisForLimitMonitoring	Double	Hysteresis for limit monitoring		
		DelayTimeForLimitMonitoring	UInt32	Delay time for limit monitoring		
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA20-0BD0 - V4.0						
					1	Value1S
					2	Value2S
					3	Value3S
					10	Value10S
					9	Value9S
					8	Value8S
					7	Value7S
					6	Value6S
					5	Value5S
					4	Value4S
		MappingId	Int64	ID		
		MappingMeasuredVariable	String	Measured variable		
		MappingUnit	String	Unit		
		MappingDataType	String	Data type		
		MappingIAddress	Int64	I address		
		MappingMinValue	String	Min. value		
		MappingMaxValue	String	Max. value		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0BD0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		LineVoltageDiagnosticsActive	Boolean	Line voltage diagnostics		
		LineVoltageTolerance	UInt32	Line voltage tolerance		
		LineFrequency	UInt64	Line frequency		
					2	Value50Hz
					1	Value60Hz
		GateControlActive	Boolean	Energy meter gate		
					0	Deactivated
					1	Active
		Name	String	Name		
		Comment	String	Comment		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0BD0 - V1.0						
		ConnectionType	UInt64	Connection type		
					0	None
					2	Value3P4w3Phase4Wire
					1	Value1P2w1Phase2Wire
		OperatingRange	UInt64	Voltage measuring range		
					111	Value100V
					112	Value110V
					113	Value115V
					114	Value120V
					115	Value127V
					116	Value190V
					117	Value200V
					118	Value208V
					119	Value220V
					120	Value230V
		ModuleVariant	UInt64	Module version		
					0	Value32BytesIOr12BytesO
					1	Value2BytesIOr2BytesO
		ProcessDataVariant	UInt64	Process data variant		
					248	EnergyL1HexF8
					247	EnergyL2HexF7
					246	EnergyL3HexF6
					159	BasicVariablesSinglePhaseMeasurementL1Hex9F
					254	TotalPowersL1l2l3HexFe
					253	ActivePowersL1l2l3HexFd
					252	ReactivePowersL1l2l3HexFc
					251	ApparentPowerL1l2l3HexFb
					250	BasicMeasuredValuesL1l2l3HexFa
					249	TotalEnergyL1l2l3HexF9
					245	BasicVariablesThreePhaseMeasurementL1l2l3HexF5
		PositionNumber	Int32	Index		
	Channel 0					
		DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0BD0 - V1.0						
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
					0	Value1A
					2	Value5A
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		CurrentTransformerPrimaryCurrent	UInt32	Current transformer transfer factor		
	Channel 1					
		DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
					0	Value1A
					2	Value5A
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
		CurrentTransformerPrimaryCurrent	UInt32	Current transformer transfer factor		
	Channel 2					
		DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0BD0 - V1.0					
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
				0	Value1A
				2	Value5A
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
	CurrentTransformerPrimaryCurrent	UInt32	Current transformer transfer factor		
Module - 6ES7 134-6PA00-0BD0 - V2.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	LineVoltageDiagnosticsActive	Boolean	Line voltage diagnostics		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0BD0 - V2.0						
		LineVoltageTolerance	UInt32	Line voltage tolerance		
		LineFrequency	UInt64	Line frequency		
					2	Value50Hz
					1	Value60Hz
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		GateControlActive	Boolean	Energy meter gate		
					0	Deactivated
					1	Active
		Name	String	Name		
		Comment	String	Comment		
		ConnectionType	UInt64	Connection type		
					0	None
					2	Value3P4w3Phase4Wire
					1	Value1P2w1Phase2Wire
		OperatingRange	UInt64	Voltage measuring range		
					111	Value100V
					112	Value110V
					113	Value115V
					114	Value120V
					115	Value127V
					116	Value190V
					117	Value200V
					118	Value208V
					119	Value220V
					120	Value230V
		ModuleVariant	UInt64	Module version		
					0	Value32BytesIOr12BytesO
					1	Value2BytesIOr2BytesO
		ProcessDataVariant	UInt64	Process data variant		
					248	EnergyL1HexF8
					247	EnergyL2HexF7
					246	EnergyL3HexF6
					159	BasicVariablesSinglePhaseMeasurementL1Hex9F

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					254	TotalPowersL1l2l3HexFe

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0BD0 - V2.0					
				253	ActivePowersL1l2l3HexFd
				252	ReactivePowersL1l2l3HexFc
				251	ApparentPowerL1l2l3HexFb
				250	BasicMeasuredValuesL1l2l3HexFa
				249	TotalEnergyL1l2l3HexF9
				245	BasicVariablesThreePhaseMeasurementL1l2l3HexF5
	PositionNumber	Int32	Index		
Channel 0					
	DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
	CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
				0	Value1A
				2	Value5A
	ReverseCurrentDirection	UInt32	Reverse current direction		
				0	Deactivated
				1	Activated
Channel 1					
	DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		
	DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
	DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
	DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
	ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		
	ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
	DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
	CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
	CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
				0	Value1A

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					2	Value5A

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA00-0BD0 - V2.0						
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
	Channel 2					
		DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
		CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
					0	Value1A
					2	Value5A
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
Module - 6ES7 134-6PA01-0BD0 - V3.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BD0 - V3.0						
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
Submodule						
		SharedDeviceAccessConfigured	Boolean			
		LineVoltageDiagnosticsActive	Boolean	Line voltage diagnostics		
		LineVoltageTolerance	UInt32	Line voltage tolerance		
		LineFrequency	UInt64	Line frequency		
					2	Value50Hz
					1	Value60Hz
		LowLimitCurrentMeasurement	UInt32	Low limit current measurement		
		GateControlActive	Boolean	Energy meter gate		
					0	Deactivated
					1	Active
		Name	String	Name		
		Comment	String	Comment		
		ConnectionType	UInt64	Connection type		
					0	None
					2	Value3P4w3Phase4Wire
					1	Value1P2w1Phase2Wire
		OperatingRange	UInt64	Voltage measuring range		
					111	Value100V
					112	Value110V
					113	Value115V
					114	Value120V
					115	Value127V
					116	Value190V
					117	Value200V
					118	Value208V
					119	Value220V
					120	Value230V

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BD0 - V3.0						
		ModuleVariant	UInt64	Module version		
					0	Value32BytesIOr12BytesO
					1	Value2BytesIOr2BytesO
		ProcessDataVariant	UInt64	Process data variant		
					248	EnergyL1HexF8
					247	EnergyL2HexF7
					246	EnergyL3HexF6
					159	BasicVariablesSinglePhaseMeasurementL1Hex9F
					254	TotalPowersL1l2l3HexFe
					253	ActivePowersL1l2l3HexFd
					252	ReactivePowersL1l2l3HexFc
					251	ApparentPowerL1l2l3HexFb
					250	BasicMeasuredValuesL1l2l3HexFa
					249	TotalEnergyL1l2l3HexF9
					245	BasicVariablesThreePhaseMeasurementL1l2l3HexF5
		PositionNumber	Int32	Index		
	Channel 0					
		DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
		CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
					0	Value1A
					2	Value5A
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
	Channel 1					
		DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 134-6PA01-0BD0 - V3.0						
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
		CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
					0	Value1A
					2	Value5A
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated
	Channel 2					
		DiagnosticsReachLimitVoltageActive	Boolean	Diagnostics of low limit voltage		
		DiagnosticsOverflowVoltageActive	Boolean	Diagnostics overflow voltage		
		DiagnosticsUnderflowVoltage	Boolean	Diagnostics underflow voltage		
		DiagnosticsOverflowCurrentActive	Boolean	Diagnostics overflow current		
		ToleranceValueOvercurrent	UInt64	Tolerance value overcurrent		
		ToleranceTimeOvercurrent	UInt32	Tolerance time overcurrent		
		DiagnosticsOverflowCumulativeValuesActive	Boolean	Diagnostics overflow cumulative values		
		CurrentTransformerPrimaryCurrent	UInt32	Current transformer primary current		
		CurrentTransformerSecondaryCurrent	UInt64	Current transformer secondary current		
					0	Value1A
					2	Value5A
		ReverseCurrentDirection	UInt32	Reverse current direction		
					0	Deactivated
					1	Activated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2					
				94	Value293Dot75
				95	Value296Dot88
				96	Value300Dot00
				97	Value303Dot13
				98	Value306Dot25
				99	Value309Dot38
	ResponseToAsymmetry	UInt64	Response to asymmetry		
				0	Warn
				1	Trip
	Input1Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input1Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input1Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				13	ColdRun
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2					
				52	Limit52
				53	Limit53
				54	Limit54
				55	Limit55
				56	Limit56
				57	Limit57
				58	Limit58
				59	Limit59
				60	Limit60
				61	Limit61
				62	Limit62
				63	Limit63
				64	Limit64
				65	Limit65
				66	Limit66
				67	Limit67
				68	Limit68
				69	Limit69
				70	Limit70
				71	Limit71
				72	Limit72
				73	Limit73
				74	Limit74
				75	Limit75
				76	Limit76
				77	Limit77
				78	Limit78
				79	Limit79
				80	Limit80
				81	Limit81
				82	Limit82
				83	Limit83
				84	Limit84

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2					
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				13	ColdRun
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
	Input2Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input2Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input2Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				13	ColdRun
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2						
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2					
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 16					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2					
Channel 17					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 18					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 19					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 20					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 21					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 22					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 23					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 24					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 25					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 26					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 27					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2					
Channel 28					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 29					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 30					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 31					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 4					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 5					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AA00-0CP0 - V1.2					
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0AB00-0CP0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	TypeName	String	InvariantTypeName		
	ShortDesignation	String	Short designation		
	Author	String	Author		
	PositionNumber	Int32	Slot		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0					
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 16					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 17					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0					
Channel 18					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 19					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 20					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 21					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 22					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 23					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 24					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 25					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 26					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 27					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 28					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0					
Channel 29					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 30					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 31					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Channel 5					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Channel 6					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0					
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0AB00-0CP0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	TypeName	String	InvariantTypeName		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	RatedOperationalCurrentIe	Double	Rated operational current Ie		
	LoadType	UInt64	Load type		
				0	ThreePhaseMotor

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0					
				37	Value115Dot63
				38	Value118Dot75
				39	Value121Dot88
				40	Value125
				41	Value128Dot13
				42	Value131Dot25
				43	Value134Dot38
				44	Value137Dot50
				45	Value140Dot63
				46	Value143Dot75
				47	Value146Dot88
				48	Value150
				49	Value153Dot13
				50	Value156Dot25
				51	Value159Dot38
				52	Value162Dot50
				53	Value165Dot63
				54	Value168Dot75
				55	Value171Dot88
				56	Value175
				57	Value178Dot13
				58	Value181Dot25
				59	Value184Dot38
				60	Value187Dot50
				61	Value190Dot63
				62	Value193Dot75
				63	Value196Dot88
				64	Value200
				65	Value203Dot13
				66	Value206Dot25
				67	Value209Dot38
				68	Value212Dot50
				69	Value215Dot63

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0					
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
				13	ColdRun
	DiagnosticsGroupFault	Boolean	Group fault diagnostics		
				1	Active
				0	Deactivated
	DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
				1	Active
				0	Deactivated
	ReactionToCpuStop	UInt64	Response to CPU/master STOP		
				18	SubstituteValue0
				1	KeepLastValue
	Author	String	Author		
	PositionNumber	Int32	Slot		
	PlantDesignation	String	Plant designation		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	LocationIdentifier	String	Location identifier		
	Name	String	Name		
	Comment	String	Comment		
	ShortDesignation	String	Short designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0					
				127	Value396Dot88
				128	Value400Dot00
				121	Value378Dot13
	ResponseToAsymmetry	UInt64	Response to asymmetry		
				0	Warn
				1	Trip
	Input1Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input1Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input1Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
				13	ColdRun
	Input2Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0AB00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AB00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1					
				55	Limit55
				56	Limit56
				57	Limit57
				58	Limit58
				59	Limit59
				60	Limit60
				61	Limit61
				62	Limit62
				63	Limit63
				64	Limit64
				65	Limit65
				66	Limit66
				67	Limit67
				68	Limit68
				69	Limit69
				70	Limit70
				71	Limit71
				72	Limit72
				73	Limit73
				74	Limit74
				75	Limit75
				76	Limit76
				77	Limit77
				78	Limit78
				79	Limit79
				80	Limit80
				81	Limit81
				82	Limit82
				83	Limit83
				84	Limit84
				85	Limit85
				86	Limit86
				87	Limit87

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1					
				114	Value356Dot25
				115	Value359Dot38
				116	Value362Dot50
				117	Value365Dot63
				118	Value368Dot75
				119	Value371Dot88
				120	Value375Dot00
				122	Value381Dot25
				123	Value384Dot38
				124	Value387Dot50
				125	Value390Dot63
				126	Value393Dot75
				127	Value396Dot88
				128	Value400Dot00
	ResponseToAsymmetry	UInt64	Response to asymmetry		
				0	Warn
				1	Trip
	Input1Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input1Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input1Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1					
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
				13	ColdRun
	Input2Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input2Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input2Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
				13	ColdRun
	Input3Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1					
	AdditionalInformation	String	Additional information		
	LocationIdentifier	String	Location identifier		
	Name	String	Name		
	Comment	String	Comment		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AB00-0CP0 - V1.1					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	RatedOperationalCurrentIe	Double	Rated operational current Ie		
	LoadType	UInt64	Load type		
				0	ThreePhaseMotor
				1	OnePhaseMotor
	TrippingClass	UInt64	Tripping class		
				3	Class510A
				0	Class10
	PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
				0	Limit0
				1	Limit1
				2	Limit2
				3	Limit3
				4	Limit4
				5	Limit5
				6	Limit6
				7	Limit7
				8	Limit8
				9	Limit9

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1						
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1					
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
				13	ColdRun
	Input3Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input3Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input3Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.1					
				13	ColdRun
	DiagnosticsGroupFault	Boolean	Group fault diagnostics		
				1	Active
				0	Deactivated
	DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
				1	Active
				0	Deactivated
	ReactionToCpuStop	UInt64	Response to CPU/master STOP		
				18	SubstituteValue0
				1	KeepLastValue
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PositionNumber	Int32	Slot		
	PlantDesignation	String	Plant designation		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	LocationIdentifier	String	Location identifier		
	Name	String	Name		
	Comment	String	Comment		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AB00-0CP0 - V1.2					
	SharedDeviceAccessConfigured	Boolean			
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
				0	Limit0
				1	Limit1
				2	Limit2

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2					
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				13	ColdRun
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
	Input3Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input3Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input3Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				13	ColdRun
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2					
	DiagnosticsGroupFault	Boolean	Group fault diagnostics		
				1	Active
				0	Deactivated
	DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
				1	Active
				0	Deactivated
	ReactionToCpuStop	UInt64	Response to CPU/master STOP		
				18	SubstituteValue0
				1	KeepLastValue
	ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
				0	Active
				1	Deactivated
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AB00-0CP0 - V1.2					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
				0	Limit0
				1	Limit1
				2	Limit2
				3	Limit3
				4	Limit4
				5	Limit5
				6	Limit6
				7	Limit7
				8	Limit8
				9	Limit9
				10	Limit10

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2					
				44	Limit44
				45	Limit45
				46	Limit46
				47	Limit47
				48	Limit48
				49	Limit49
				50	Limit50
				51	Limit51
				52	Limit52
				53	Limit53
				54	Limit54
				55	Limit55
				56	Limit56
				57	Limit57
				58	Limit58
				59	Limit59
				60	Limit60
				61	Limit61
				62	Limit62
				63	Limit63
				64	Limit64
				65	Limit65
				66	Limit66
				67	Limit67
				68	Limit68
				69	Limit69
				70	Limit70
				71	Limit71
				72	Limit72
				73	Limit73
				74	Limit74
				75	Limit75
				76	Limit76

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2					
				9	MotorCcw
				11	QuickStop
				12	TripReset
				13	ColdRun
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
	Input3Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input3Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input3Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				13	ColdRun
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
	DiagnosticsGroupFault	Boolean	Group fault diagnostics		
				1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AB00-0CP0 - V1.2						
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0					
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 4					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 5					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0					
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 16					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 17					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 18					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 19					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 20					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 21					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 22					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0					
Channel 23					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 24					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 25					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 26					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 27					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 28					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 29					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 30					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 31					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0					
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Channel 5					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Channel 6					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0					
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0AC00-0CP0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	RatedOperationalCurrentIe	Double	Rated operational current Ie		
	LoadType	UInt64	Load type		
				0	ThreePhaseMotor
				1	OnePhaseMotor
	TrippingClass	UInt64	Tripping class		
				3	Class510A
				0	Class10
	PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
				0	Limit0
				1	Limit1
				2	Limit2
				3	Limit3
				4	Limit4
				5	Limit5
				6	Limit6
				7	Limit7
				8	Limit8
				9	Limit9

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0					
				51	Value159Dot38
				52	Value162Dot50
				53	Value165Dot63
				54	Value168Dot75
				55	Value171Dot88
				56	Value175
				57	Value178Dot13
				58	Value181Dot25
				59	Value184Dot38
				60	Value187Dot50
				61	Value190Dot63
				62	Value193Dot75
				63	Value196Dot88
				64	Value200
				65	Value203Dot13
				66	Value206Dot25
				67	Value209Dot38
				68	Value212Dot50
				69	Value215Dot63
				70	Value218Dot75
				71	Value221Dot88
				72	Value225
				73	Value228Dot13
				74	Value231Dot25
				75	Value234Dot38
				76	Value237Dot50
				77	Value240Dot63
				78	Value243Dot75
				79	Value246Dot88
				80	Value250
				81	Value253Dot13
				82	Value256Dot25
				83	Value259Dot38

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0					
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
				13	ColdRun
	Input3Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input3Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input3Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0					
				13	ColdRun
	DiagnosticsGroupFault	Boolean	Group fault diagnostics		
				1	Active
				0	Deactivated
	DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
				1	Active
				0	Deactivated
	ReactionToCpuStop	UInt64	Response to CPU/master STOP		
				18	SubstituteValue0
				1	KeepLastValue
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PositionNumber	Int32	Slot		
	PlantDesignation	String	Plant designation		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	LocationIdentifier	String	Location identifier		
	Name	String	Name		
	Comment	String	Comment		
	FirmwareVersion	String	Firmware version		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	TypeName	String	InvariantTypeName		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0AC00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AC00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1					
				125	Value390Dot63
				126	Value393Dot75
				127	Value396Dot88
				128	Value400Dot00
	ResponseToAsymmetry	UInt64	Response to asymmetry		
				0	Warn
				1	Trip
	Input1Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input1Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input1Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
				13	ColdRun
	Input2Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1					
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
				13	ColdRun
	DiagnosticsGroupFault	Boolean	Group fault diagnostics		
				1	Active
				0	Deactivated
	DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
				1	Active
				0	Deactivated
	ReactionToCpuStop	UInt64	Response to CPU/master STOP		
				18	SubstituteValue0
				1	KeepLastValue
	Author	String	Author		
	PositionNumber	Int32	Slot		
	PlantDesignation	String	Plant designation		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	LocationIdentifier	String	Location identifier		
	Name	String	Name		
	Comment	String	Comment		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AC00-0CP0 - V1.1					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.1						
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AC00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2					
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				13	ColdRun
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
	Input3Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input3Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input3Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				13	ColdRun
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2					
				38	OperationalTripEndPositionCcw
	DiagnosticsGroupFault	Boolean	Group fault diagnostics		
				1	Active
				0	Deactivated
	DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
				1	Active
				0	Deactivated
	ReactionToCpuStop	UInt64	Response to CPU/master STOP		
				18	SubstituteValue0
				1	KeepLastValue
	ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
				0	None
				1	Warn
	ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
				0	Active
				1	Deactivated
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AC00-0CP0 - V1.2					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
				0	Limit0
				1	Limit1
				2	Limit2
				3	Limit3
				4	Limit4
				5	Limit5
				6	Limit6

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2					
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				13	ColdRun
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
	Input3Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input3Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input3Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				13	ColdRun
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AC00-0CP0 - V1.2						
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0					
				73	Value228Dot13
				74	Value231Dot25
				75	Value234Dot38
				76	Value237Dot50
				77	Value240Dot63
				78	Value243Dot75
				79	Value246Dot88
				80	Value250
				81	Value253Dot13
				82	Value256Dot25
				83	Value259Dot38
				84	Value262Dot50
				85	Value265Dot63
				86	Value268Dot75
				87	Value271Dot88
				88	Value275
				89	Value278Dot13
				90	Value281Dot25
				91	Value284Dot38
				92	Value287Dot50
				93	Value290Dot63
				94	Value293Dot75
				95	Value296Dot88
				96	Value300
				97	Value303Dot13
				98	Value306Dot25
				99	Value309Dot38
				100	Value312Dot50
				101	Value315Dot63
				102	Value318Dot75
				103	Value321Dot88
				104	Value325
				105	Value328Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0					
				125	Value390Dot63
				126	Value393Dot75
				127	Value396Dot88
				128	Value400Dot00
	ResponseToAsymmetry	UInt64	Response to asymmetry		
				0	Warn
				1	Trip
	Input1Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive
	Input1Level	UInt64	Level		
				0	NormallyClosed
				1	NormallyOpen
	Input1Action	UInt64	Action		
				0	NoAction
				1	TripWithoutRestart
				2	TripWithRestart
				3	TripEndPositionCw
				4	TripEndPositionCcw
				5	GroupWarning
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
				13	ColdRun
	Input2Signal	UInt64	Signal		
				0	NonRetentive
				1	Retentive

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0					
				7	EmergencyStart
				8	MotorCw
				9	MotorCcw
				11	QuickStop
				12	TripReset
				14	QuickStopClockwise
				15	QuickStopCounterclockwise
				37	OperationalTripEndPositionCw
				38	OperationalTripEndPositionCcw
				13	ColdRun
	DiagnosticsGroupFault	Boolean	Group fault diagnostics		
				1	Active
				0	Deactivated
	DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
				1	Active
				0	Deactivated
	ReactionToCpuStop	UInt64	Response to CPU/master STOP		
				18	SubstituteValue0
				1	KeepLastValue
	Author	String	Author		
	PositionNumber	Int32	Slot		
	PlantDesignation	String	Plant designation		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	LocationIdentifier	String	Location identifier		
	Name	String	Name		
	Comment	String	Comment		
	FirmwareVersion	String	Firmware version		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	TypeName	String	InvariantTypeName		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0					
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 4					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 5					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0					
Channel 22					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 23					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 24					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 25					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 26					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 27					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 28					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 29					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 30					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 31					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0					
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Channel 5					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Channel 6					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0					
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0AD00-0CP0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	RatedOperationalCurrentIe	Double	Rated operational current Ie		
	LoadType	UInt64	Load type		
				0	ThreePhaseMotor
				1	OnePhaseMotor
	TrippingClass	UInt64	Tripping class		
				3	Class510A
				0	Class10
	PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
				0	Limit0
				1	Limit1
				2	Limit2
				3	Limit3
				4	Limit4
				5	Limit5
				6	Limit6

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 23					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 24					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 25					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 26					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 27					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 28					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 29					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 30					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 31					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 308-0AD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0AD00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AD00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel

Module - 3RK1 308-0AD00-0CP0 - V1.1						
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0AD00-0CP0 - V1.1						
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun

Module - 3RK1 308-0AD00-0CP0 - V1.1						
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		Author	String	Author		
		PositionNumber	Int32	Slot		

Module - 3RK1 308-0AD00-0CP0 - V1.1						
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AD00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn

Module - 3RK1 308-0AD00-0CP0 - V1.1						
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5

Module - 3RK1 308-0AD00-0CP0 - V1.1						
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw

Module - 3RK1 308-0AD00-0CP0 - V1.1						
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Module - 3RK1 308-0AD00-0CP0 - V1.1						
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		

Module - 3RK1 308-0AD00-0CP0 - V1.1						
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AD00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0AD00-0CP0 - V1.2						
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AD00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff

Module - 3RK1 308-0AD00-0CP0 - V1.2						
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Module - 3RK1 308-0AD00-0CP0 - V1.2						
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450

Module - 3RK1 308-0AD00-0CP0 - V1.2						
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AE00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AE00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99

Module - 3RK1 308-0AE00-0CP0 - V1.1						
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100

Module - 3RK1 308-0AE00-0CP0 - V1.1						
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0AE00-0CP0 - V1.1						
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AE00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn

Module - 3RK1 308-0AE00-0CP0 - V1.1						
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0

Module - 3RK1 308-0AE00-0CP0 - V1.1						
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AE00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel

Module - 3RK1 308-0AE00-0CP0 - V1.2						
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Module - 3RK1 308-0AE00-0CP0 - V1.2						
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0AE00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			

Module - 3RK1 308-0AE00-0CP0 - V1.2						
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99

Module - 3RK1 308-0AE00-0CP0 - V1.2						
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0AE00-0CP0 - V1.2						
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000

Module - 3RK1 308-0AE00-0CP0 - V1.2						
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CA00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5

Module - 3RK1 308-0CA00-0CP0 - V1.2						
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn

Module - 3RK1 308-0CA00-0CP0 - V1.2						
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw

Module - 3RK1 308-0CA00-0CP0 - V1.2						
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	PositionNumber		

Module - 3RK1 308-0CA00-0CP0 - V1.2						
		Name	String	Name		
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0CA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0CA00-0CP0 - V1.2						
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					

Module - 3RK1 308-0CA00-0CP0 - V1.2						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

Module - 3RK1 308-0CA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0CA00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0CA00-0CP0 - V1.2						
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450

Module - 3RK1 308-0CA00-0CP0 - V1.2						
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0CA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0CA00-0CP0 - V1.2						
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					

Module - 3RK1 308-0CA00-0CP0 - V1.2						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

Module - 3RK1 308-0CA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0CA00-0CP0 - V1.2						
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0CB00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CB00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99

Module - 3RK1 308-0CB00-0CP0 - V1.0						
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100

Module - 3RK1 308-0CB00-0CP0 - V1.0						
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0CB00-0CP0 - V1.0						
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CB00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes

Module - 3RK1 308-0CB00-0CP0 - V1.0						
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Module - 3RK1 308-0CB00-0CP0 - V1.0						
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active

Module - 3RK1 308-0CB00-0CP0 - V1.0						
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CB00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes

Module - 3RK1 308-0CB00-0CP0 - V1.2						
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Module - 3RK1 308-0CB00-0CP0 - V1.2						
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CB00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0CB00-0CP0 - V1.2						
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38

Module - 3RK1 308-0CB00-0CP0 - V1.2						
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550

Module - 3RK1 308-0CB00-0CP0 - V1.2						
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		

Module - 3RK1 308-0CC00-0CP0 - V1.0						
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0CC00-0CP0 - V1.0						
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		

Module - 3RK1 308-0CC00-0CP0 - V1.0						
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13

Module - 3RK1 308-0CC00-0CP0 - V1.0						
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset

Module - 3RK1 308-0CC00-0CP0 - V1.0						
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0CC00-0CP0 - V1.0						
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		

Module - 3RK1 308-0CC00-0CP0 - V1.0						
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CC00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn

Module - 3RK1 308-0CC00-0CP0 - V1.2						
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0CC00-0CP0 - V1.2						
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CC00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes

Module - 3RK1 308-0CC00-0CP0 - V1.2						
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue

Module - 3RK1 308-0CC00-0CP0 - V1.2						
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200

Module - 3RK1 308-0CC00-0CP0 - V1.2						
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CD00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CD00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		

Module - 3RK1 308-0CD00-0CP0 - V1.0						
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			

Module - 3RK1 308-0CD00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

Module - 3RK1 308-0CD00-0CP0 - V1.0						
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

Module - 3RK1 308-0CD00-0CP0 - V1.0						
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CD00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		

Module - 3RK1 308-0CD00-0CP0 - V1.2						
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Module - 3RK1 308-0CD00-0CP0 - V1.2						
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CD00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0CD00-0CP0 - V1.2						
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn

Module - 3RK1 308-0CD00-0CP0 - V1.2						
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00

Module - 3RK1 308-0CD00-0CP0 - V1.2						
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0CD00-0CP0 - V1.2						
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit

Module - 3RK1 308-0CD00-0CP0 - V1.2						
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

Module - 3RK1 308-0CD00-0CP0 - V1.2						
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CE00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CE00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99

Module - 3RK1 308-0CE00-0CP0 - V1.0						
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100

Module - 3RK1 308-0CE00-0CP0 - V1.0						
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0CE00-0CP0 - V1.0						
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CE00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes

Module - 3RK1 308-0CE00-0CP0 - V1.0						
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Module - 3RK1 308-0CE00-0CP0 - V1.0						
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active

Module - 3RK1 308-0CE00-0CP0 - V1.0						
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CE00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes

Module - 3RK1 308-0CE00-0CP0 - V1.2						
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Module - 3RK1 308-0CE00-0CP0 - V1.2						
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0CE00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0CE00-0CP0 - V1.2						
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38

Module - 3RK1 308-0CE00-0CP0 - V1.2						
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550

Module - 3RK1 308-0CE00-0CP0 - V1.2						
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BA00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00

Module - 3RK1 308-0BA00-0CP0 - V1.2						
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0BA00-0CP0 - V1.2						
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					

Module - 3RK1 308-0BA00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0BA00-0CP0 - V1.2						
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					

Module - 3RK1 308-0BA00-0CP0 - V1.2						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

Module - 3RK1 308-0BA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0BA00-0CP0 - V1.2						
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0BA00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Module - 3RK1 308-0BA00-0CP0 - V1.2						
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300

Module - 3RK1 308-0BA00-0CP0 - V1.2						
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0BA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0BA00-0CP0 - V1.2						
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					

Module - 3RK1 308-0BA00-0CP0 - V1.2						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

Module - 3RK1 308-0BA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0BA00-0CP0 - V1.2						
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0BB00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0BB00-0CP0 - V1.0						
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0BB00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0BB00-0CP0 - V1.0						
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0BB00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise

Module - 3RK1 308-0BB00-0CP0 - V1.0						
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0BB00-0CP0 - V1.0						
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0BB00-0CP0 - V1.0						
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					

Module - 3RK1 308-0BB00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0BB00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BB00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel

Module - 3RK1 308-0BB00-0CP0 - V1.1						
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0BB00-0CP0 - V1.1						
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun

Module - 3RK1 308-0BB00-0CP0 - V1.1						
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		Author	String	Author		
		PositionNumber	Int32	Slot		

Module - 3RK1 308-0BB00-0CP0 - V1.1						
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BB00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0BB00-0CP0 - V1.1						
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise

Module - 3RK1 308-0BB00-0CP0 - V1.1						
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0BB00-0CP0 - V1.1						
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		

Module - 3RK1 308-0BB00-0CP0 - V1.1						
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BB00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13

Module - 3RK1 308-0BB00-0CP0 - V1.2						
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip

Module - 3RK1 308-0BB00-0CP0 - V1.2						
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BB00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed

Module - 3RK1 308-0BB00-0CP0 - V1.2						
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated

Module - 3RK1 308-0BB00-0CP0 - V1.2						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500

Module - 3RK1 308-0BB00-0CP0 - V1.2						
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0BC00-0CP0 - V1.0						
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0BC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0BC00-0CP0 - V1.0						
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise

Module - 3RK1 308-0BC00-0CP0 - V1.0						
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0BC00-0CP0 - V1.0						
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0BC00-0CP0 - V1.0						
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					

Module - 3RK1 308-0BC00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0BC00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BC00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel

Module - 3RK1 308-0BC00-0CP0 - V1.1						
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0BC00-0CP0 - V1.1						
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun

Module - 3RK1 308-0BC00-0CP0 - V1.1						
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		Author	String	Author		
		PositionNumber	Int32	Slot		

Module - 3RK1 308-0BC00-0CP0 - V1.1						
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BC00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0BC00-0CP0 - V1.1						
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise

Module - 3RK1 308-0BC00-0CP0 - V1.1						
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0BC00-0CP0 - V1.1						
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		

Module - 3RK1 308-0BC00-0CP0 - V1.1						
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BC00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13

Module - 3RK1 308-0BC00-0CP0 - V1.2						
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip

Module - 3RK1 308-0BC00-0CP0 - V1.2						
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BC00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed

Module - 3RK1 308-0BC00-0CP0 - V1.2						
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated

Module - 3RK1 308-0BC00-0CP0 - V1.2						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500

Module - 3RK1 308-0BC00-0CP0 - V1.2						
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BD00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0BD00-0CP0 - V1.0						
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0BD00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0BD00-0CP0 - V1.0						
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0BD00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise

Module - 3RK1 308-0BD00-0CP0 - V1.0						
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0BD00-0CP0 - V1.0						
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0BD00-0CP0 - V1.0						
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					

Module - 3RK1 308-0BD00-0CP0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0BD00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BD00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel

Module - 3RK1 308-0BD00-0CP0 - V1.1						
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0BD00-0CP0 - V1.1						
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun

Module - 3RK1 308-0BD00-0CP0 - V1.1						
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		Author	String	Author		
		PositionNumber	Int32	Slot		

Module - 3RK1 308-0BD00-0CP0 - V1.1						
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BD00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0BD00-0CP0 - V1.1						
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise

Module - 3RK1 308-0BD00-0CP0 - V1.1						
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0BD00-0CP0 - V1.1						
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		

Module - 3RK1 308-0BD00-0CP0 - V1.1						
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BD00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13

Module - 3RK1 308-0BD00-0CP0 - V1.2						
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip

Module - 3RK1 308-0BD00-0CP0 - V1.2						
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BD00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed

Module - 3RK1 308-0BD00-0CP0 - V1.2						
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated

Module - 3RK1 308-0BD00-0CP0 - V1.2						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500

Module - 3RK1 308-0BD00-0CP0 - V1.2						
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BE00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BE00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn

Module - 3RK1 308-0BE00-0CP0 - V1.1						
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		Author	String	Author		

Module - 3RK1 308-0BE00-0CP0 - V1.1						
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BE00-0CP0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13

Module - 3RK1 308-0BE00-0CP0 - V1.1						
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset

Module - 3RK1 308-0BE00-0CP0 - V1.1						
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0BE00-0CP0 - V1.1						
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		

Module - 3RK1 308-0BE00-0CP0 - V1.1						
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BE00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13

Module - 3RK1 308-0BE00-0CP0 - V1.2						
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip

Module - 3RK1 308-0BE00-0CP0 - V1.2						
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0BE00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed

Module - 3RK1 308-0BE00-0CP0 - V1.2						
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated

Module - 3RK1 308-0BE00-0CP0 - V1.2						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500

Module - 3RK1 308-0BE00-0CP0 - V1.2						
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DA00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0DA00-0CP0 - V1.2						
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip

Module - 3RK1 308-0DA00-0CP0 - V1.2						
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0DA00-0CP0 - V1.2						
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					

Module - 3RK1 308-0DA00-0CP0 - V1.2						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0DA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0DA00-0CP0 - V1.2						
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 3RK1 308-0DA00-0CP0 - V1.2						

Module - 3RK1 308-0DA00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		

Module - 3RK1 308-0DA00-0CP0 - V1.2						
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated

Module - 3RK1 308-0DA00-0CP0 - V1.2						
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900

Module - 3RK1 308-0DA00-0CP0 - V1.2						
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		TypeName	String	InvariantTypeName		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Module - 3RK1 308-0DA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Module - 3RK1 308-0DA00-0CP0 - V1.2						
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					

Module - 3RK1 308-0DA00-0CP0 - V1.2						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

Module - 3RK1 308-0DA00-0CP0 - V1.2						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Module - 3RK1 308-0DB00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DB00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel

Module - 3RK1 308-0DB00-0CP0 - V1.0						
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0DB00-0CP0 - V1.0						
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun

Module - 3RK1 308-0DB00-0CP0 - V1.0						
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					1	Warn
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DB00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn

Module - 3RK1 308-0DB00-0CP0 - V1.0						
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0

Module - 3RK1 308-0DB00-0CP0 - V1.0						
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DB00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0DB00-0CP0 - V1.2						
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			

Module - 3RK1 308-0DB00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		

Module - 3RK1 308-0DB00-0CP0 - V1.2						
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated

Module - 3RK1 308-0DB00-0CP0 - V1.2						
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900

Module - 3RK1 308-0DB00-0CP0 - V1.2						
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DC00-0CP0 - V1.0						

Module - 3RK1 308-0DC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0DC00-0CP0 - V1.0						
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			

Module - 3RK1 308-0DC00-0CP0 - V1.0						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Module - 3RK1 308-0DC00-0CP0 - V1.0						
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart

Module - 3RK1 308-0DC00-0CP0 - V1.0						
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					

Module - 3RK1 308-0DC00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DC00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		

Module - 3RK1 308-0DC00-0CP0 - V1.2						
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated

Module - 3RK1 308-0DC00-0CP0 - V1.2						
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DC00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart

Module - 3RK1 308-0DC00-0CP0 - V1.2						
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		

Module - 3RK1 308-0DC00-0CP0 - V1.2						
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			

Module - 3RK1 308-0DD00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DD00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel

Module - 3RK1 308-0DD00-0CP0 - V1.0						
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0DD00-0CP0 - V1.0						
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun

Module - 3RK1 308-0DD00-0CP0 - V1.0						
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					1	Warn
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DD00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn

Module - 3RK1 308-0DD00-0CP0 - V1.0						
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0

Module - 3RK1 308-0DD00-0CP0 - V1.0						
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DD00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		

Module - 3RK1 308-0DD00-0CP0 - V1.2						
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			

Module - 3RK1 308-0DD00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		

Module - 3RK1 308-0DD00-0CP0 - V1.2						
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated

Module - 3RK1 308-0DD00-0CP0 - V1.2						
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900

Module - 3RK1 308-0DD00-0CP0 - V1.2						
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DE00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		ShortDesignation	String	Short designation		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DE00-0CP0 - V1.0						

Module - 3RK1 308-0DE00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		TypeName	String	InvariantTypeName		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750
					16	Value800

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					128	Value400Dot00
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen

Module - 3RK1 308-0DE00-0CP0 - V1.0						
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DE00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			

Module - 3RK1 308-0DE00-0CP0 - V1.0						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					13	Value650
					15	Value750

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					12	Value600
					14	Value700
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		HighLimitCurrent	UInt64	Upper current limit		
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					121	Value378Dot13
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive

Module - 3RK1 308-0DE00-0CP0 - V1.0						
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart

Module - 3RK1 308-0DE00-0CP0 - V1.0						
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
					13	ColdRun
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					

Module - 3RK1 308-0DE00-0CP0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DE00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		

Module - 3RK1 308-0DE00-0CP0 - V1.2						
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		Name	String	Name		
		Comment	String	Comment		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated

Module - 3RK1 308-0DE00-0CP0 - V1.2						
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
Module - 3RK1 308-0DE00-0CP0 - V1.2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		PrewarningLimitForMotorHeating	UInt64	Prewarning limit for motor heating		
					0	Limit0
					1	Limit1
					2	Limit2
					3	Limit3
					4	Limit4
					5	Limit5
					6	Limit6
					7	Limit7
					8	Limit8
					9	Limit9
					10	Limit10
					11	Limit11

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					12	Limit12
					13	Limit13
					14	Limit14
					15	Limit15
					16	Limit16
					17	Limit17
					18	Limit18
					19	Limit19
					20	Limit20
					21	Limit21
					22	Limit22
					23	Limit23
					24	Limit24
					25	Limit25
					26	Limit26
					27	Limit27
					28	Limit28
					29	Limit29
					30	Limit30
					31	Limit31
					32	Limit32
					33	Limit33
					34	Limit34
					35	Limit35
					36	Limit36
					37	Limit37
					38	Limit38
					39	Limit39
					40	Limit40
					41	Limit41
					42	Limit42
					43	Limit43
					44	Limit44
					45	Limit45

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					46	Limit46
					47	Limit47
					48	Limit48
					49	Limit49
					50	Limit50
					51	Limit51
					52	Limit52
					53	Limit53
					54	Limit54
					55	Limit55
					56	Limit56
					57	Limit57
					58	Limit58
					59	Limit59
					60	Limit60
					61	Limit61
					62	Limit62
					63	Limit63
					64	Limit64
					65	Limit65
					66	Limit66
					67	Limit67
					68	Limit68
					69	Limit69
					70	Limit70
					71	Limit71
					72	Limit72
					73	Limit73
					74	Limit74
					75	Limit75
					76	Limit76
					77	Limit77
					78	Limit78
					79	Limit79

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					80	Limit80
					81	Limit81
					82	Limit82
					83	Limit83
					84	Limit84
					85	Limit85
					86	Limit86
					87	Limit87
					88	Limit88
					89	Limit89
					90	Limit90
					91	Limit91
					92	Limit92
					93	Limit93
					94	Limit94
					95	Limit95
					96	Limit96
					97	Limit97
					98	Limit98
					99	Limit99
		BlockingTime	UInt64	Blocking time		
					2	Value1Dot0
					3	Value1Dot5
					4	Value2Dot0
					5	Value2Dot5
					6	Value3Dot0
					7	Value3Dot5
					8	Value4Dot0
					9	Value4Dot5
					10	Value5Dot0
					11	Value5Dot5
					12	Value6Dot0
					13	Value6Dot5
					14	Value7Dot0

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					15	Value7Dot5
		LowerCurrentLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		LowerCurrentWarningLimit	UInt64	Lower current warning limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
		UpperCurrentWarningLimitDeactivated	Boolean	Limit deactivated		
		UpperCurrentWarningLimit	UInt64	Upper current warning limit		
					16	Value50

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150
					49	Value153Dot13
					50	Value156Dot25

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88
					56	Value175
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275
					89	Value278Dot13
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
					100	Value312Dot50
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					119	Value371Dot88
					120	Value375
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400
					121	Value378Dot13
		UpperCurrentLimitDeactivated	Boolean	Limit deactivated		
		Author	String	Author		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
		RatedOperationalCurrentIe	Double	Rated operational current Ie		
		LoadType	UInt64	Load type		
					0	ThreePhaseMotor
					1	OnePhaseMotor
		ExMotor	UInt64	EX motor application		
					0	No
					1	Yes
		TrippingClass	UInt64	Tripping class		
					3	Class510A
					0	Class10
					15	ClassOff
		ResponseToOverload	UInt64	Response to overload thermal motor model		
					0	ShutdownWithoutRestart
					1	ShutdownWithRestart
					2	Warn
		ResponseToThermalMotorModelAtRestart	UInt64	Response of thermal motor model at restart		
					0	RestartWithLastValueOfThermalMotorModel

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					1	ResetThermalMotorModel
		ResponseToResidualCurrentDetection	UInt64	Response to residual current detection		
					1	Trip
					0	Warn
		LowLimitCurrent	UInt64	Lower current limit		
					6	Value18Dot75
					7	Value21Dot88
					8	Value25Dot00
					9	Value28Dot13
					10	Value31Dot25
					11	Value34Dot38
					12	Value37Dot50
					13	Value40Dot63
					14	Value43Dot75
					15	Value46Dot88
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
		HighLimitCurrent	UInt64	Upper current limit		
					100	Value312Dot50

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					101	Value315Dot63
					102	Value318Dot75
					103	Value321Dot88
					104	Value325Dot00
					105	Value328Dot13
					106	Value331Dot25
					107	Value334Dot38
					108	Value337Dot50
					109	Value340Dot63
					110	Value343Dot75
					111	Value346Dot88
					112	Value350Dot00
					113	Value353Dot13
					114	Value356Dot25
					115	Value359Dot38
					116	Value362Dot50
					117	Value365Dot63
					118	Value368Dot75
					119	Value371Dot88
					120	Value375Dot00
					121	Value378Dot13
					122	Value381Dot25
					123	Value384Dot38
					124	Value387Dot50
					125	Value390Dot63
					126	Value393Dot75
					127	Value396Dot88
					128	Value400Dot00
					16	Value50Dot00
					17	Value53Dot13
					18	Value56Dot25
					19	Value59Dot38
					20	Value62Dot50
					21	Value65Dot63

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					22	Value68Dot75
					23	Value71Dot88
					24	Value75Dot00
					25	Value78Dot13
					26	Value81Dot25
					27	Value84Dot38
					28	Value87Dot50
					29	Value90Dot63
					30	Value93Dot75
					31	Value96Dot88
					32	Value100Dot00
					33	Value103Dot13
					34	Value106Dot25
					35	Value109Dot38
					36	Value112Dot50
					37	Value115Dot63
					38	Value118Dot75
					39	Value121Dot88
					40	Value125Dot00
					41	Value128Dot13
					42	Value131Dot25
					43	Value134Dot38
					44	Value137Dot50
					45	Value140Dot63
					46	Value143Dot75
					47	Value146Dot88
					48	Value150Dot00
					49	Value153Dot13
					50	Value156Dot25
					51	Value159Dot38
					52	Value162Dot50
					53	Value165Dot63
					54	Value168Dot75
					55	Value171Dot88

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					56	Value175Dot00
					57	Value178Dot13
					58	Value181Dot25
					59	Value184Dot38
					60	Value187Dot50
					61	Value190Dot63
					62	Value193Dot75
					63	Value196Dot88
					64	Value200Dot00
					65	Value203Dot13
					66	Value206Dot25
					67	Value209Dot38
					68	Value212Dot50
					69	Value215Dot63
					70	Value218Dot75
					71	Value221Dot88
					72	Value225Dot00
					73	Value228Dot13
					74	Value231Dot25
					75	Value234Dot38
					76	Value237Dot50
					77	Value240Dot63
					78	Value243Dot75
					79	Value246Dot88
					80	Value250Dot00
					81	Value253Dot13
					82	Value256Dot25
					83	Value259Dot38
					84	Value262Dot50
					85	Value265Dot63
					86	Value268Dot75
					87	Value271Dot88
					88	Value275Dot00
					89	Value278Dot13

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					90	Value281Dot25
					91	Value284Dot38
					92	Value287Dot50
					93	Value290Dot63
					94	Value293Dot75
					95	Value296Dot88
					96	Value300Dot00
					97	Value303Dot13
					98	Value306Dot25
					99	Value309Dot38
		ResponseToAsymmetry	UInt64	Response to asymmetry		
					0	Warn
					1	Trip
		Input1Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input1Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input1Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input2Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input2Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input2Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		Input3Signal	UInt64	Signal		
					0	NonRetentive
					1	Retentive
		Input3Level	UInt64	Level		
					0	NormallyClosed
					1	NormallyOpen
		Input3Action	UInt64	Action		
					0	NoAction
					1	TripWithoutRestart

Module - 3RK1 308-0DE00-0CP0 - V1.2						
					2	TripWithRestart
					3	TripEndPositionCw
					4	TripEndPositionCcw
					5	GroupWarning
					7	EmergencyStart
					8	MotorCw
					9	MotorCcw
					11	QuickStop
					12	TripReset
					13	ColdRun
					14	QuickStopClockwise
					15	QuickStopCounterclockwise
					37	OperationalTripEndPositionCw
					38	OperationalTripEndPositionCcw
		DiagnosticsGroupFault	Boolean	Group fault diagnostics		
					1	Active
					0	Deactivated
		DiagnosticsGroupWarning	Boolean	Group warning diagnostics		
					1	Active
					0	Deactivated
		ReactionToCpuStop	UInt64	Response to CPU/master STOP		
					18	SubstituteValue0
					1	KeepLastValue
		ResponseToSafetyRelatedSwitchOff	UInt64	Response to safety-oriented switch-off		
					0	None
					1	Warn
		ElectronicsSupplyVoltageLowActive	Boolean	Electronics supply voltage too low		
					0	Active
					1	Deactivated
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		Name	String	Name		
		Comment	String	Comment		

Module - 3RK1 308-0DE00-0CP0 - V1.2						
		BlockingCurrent	UInt64	Blocking current		
					3	Value150
					4	Value200
					5	Value250
					6	Value300
					7	Value350
					8	Value400
					9	Value450
					10	Value500
					11	Value550
					12	Value600
					13	Value650
					14	Value700
					15	Value750
					16	Value800
					17	Value850
					18	Value900
					19	Value950
					20	Value1000
					21	Value1050
					22	Value1100
					23	Value1150
					24	Value1200
					25	Value1250
					26	Value1300
					27	Value1350
					28	Value1400
					29	Value1450
					30	Value1500
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6BD00-0BA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
				1	Active
				0	Deactivated
	DiagnosticsPort1	Boolean	Port 1		
				0	Deactivated
				1	Active
	DiagnosticsPort2	Boolean	Port 2		
				0	Deactivated
				1	Active

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6BD00-0BA0 - V1.0					
	DiagnosticsPort3	Boolean	Port 3		
				0	Deactivated
				1	Active
	DiagnosticsPort4	Boolean	Port 4		
				0	Deactivated
				1	Active
	PositionNumber	Int32	Index		
Module - 6ES7 137-6BD00-0BA0 - V2.0					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
				0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6BD00-0BA0 - V2.0						
					1	Active
		DiagnosticsPort1	Boolean	Port 1		
					0	Deactivated
					1	Active
		DiagnosticsPort2	Boolean	Port 2		
					0	Deactivated
					1	Active
		DiagnosticsPort3	Boolean	Port 3		
					0	Deactivated
					1	Active
		DiagnosticsPort4	Boolean	Port 4		
					0	Deactivated
					1	Active
		InputOrOutputType	UInt64	Input/output type - Input/output		
					1	Value1
					2	Value2
					8	Value8
					16	Value16
					32	Value32
		PositionNumber	Int32	Index		
Module - 6ES7 137-6BD00-0BA0 - V2.1						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6BD00-0BA0 - V2.1						
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
					0	Deactivated
					1	Active
		DiagnosticsPort1	Boolean	Port 1		
					0	Deactivated
					1	Active
		DiagnosticsPort2	Boolean	Port 2		
					0	Deactivated
					1	Active
		DiagnosticsPort3	Boolean	Port 3		
					0	Deactivated
					1	Active
		DiagnosticsPort4	Boolean	Port 4		
					0	Deactivated
					1	Active
		InputOrOutputType	UInt64	Input/output type - Input/output		
					33	Value1And1
					146	Value2And2
					148	Value8And8
					145	Value16And16
					147	Value32And32
					64	Value64And64

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6BD00-0BA0 - V2.1					
				144	Value144And128
	PositionNumber	Int32	Index		
Module - 6ES7 137-6BD00-0BA0 - V2.2					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	TypeName	String	InvariantTypeName		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage L+		
				0	Deactivated
				1	Active
	DiagnosticsPort1	Boolean	Port 1		
				0	Deactivated
				1	Active

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6BD00-0BA0 - V2.2						
		DiagnosticsPort2	Boolean	Port 2		
					0	Deactivated
					1	Active
		DiagnosticsPort3	Boolean	Port 3		
					0	Deactivated
					1	Active
		DiagnosticsPort4	Boolean	Port 4		
					0	Deactivated
					1	Active
		PositionNumber	Int32	Index		
		InputOrOutputType	UInt64			
					4	Value4And4
					149	Value8And0
					148	Value8And8
					12	Value12And8
					145	Value16And16
					20	Value20And16
					147	Value32And32
					153	Value36And32
					64	Value64And64
					154	Value68And64
					144	Value144And128
		PortModePort1	UInt64	Operating mode		
					7	Deactivated
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di
					4	Dq
		InputDataLengthPort1	UInt64	Input data length (without PQI)		
		OutputDataLengthPort1	UInt64	Output data length		
		VendorIdPort1	UInt64	Vendor ID		
		DeviceIdPort1	UInt64	Device ID		
		PortModePort2	UInt64	Operating mode		
					7	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6BD00-0BA0 - V2.2						
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di
					4	Dq
		InputDataLengthPort2	UInt64	Input data length (without PQI)		
		OutputDataLengthPort2	UInt64	Output data length		
		VendorIdPort2	UInt64	Vendor ID		
		DeviceIdPort2	UInt64	Device ID		
		PortModePort3	UInt64	Operating mode		
					7	Deactivated
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di
					4	Dq
		InputDataLengthPort3	UInt64	Input data length (without PQI)		
		OutputDataLengthPort3	UInt64	Output data length		
		VendorIdPort3	UInt64	Vendor ID		
		DeviceIdPort3	UInt64	Device ID		
		PortModePort4	UInt64	Operating mode		
					7	Deactivated
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di
					4	Dq
		InputDataLengthPort4	UInt64	Input data length (without PQI)		
		OutputDataLengthPort4	UInt64	Output data length		
		VendorIdPort4	UInt64	Vendor ID		
		DeviceIdPort4	UInt64	Device ID		
		PortQualifierInformation	Boolean	Port Qualifier Information (PQI)		
		ConfigurationWithoutS7PCT	Boolean	Configuration without S7-PCT		
		InspectionOrBackupLevelPort1	UInt64	Inspection / backup level		
					5	TypeCompatibleV1Dot1WithBackupandRestore
					7	TypeCompatibleV1Dot1WithRestore
					1	SameTypeV1Dot0WithoutBackupRestore

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 137-6BD00-0BA0 - V2.2						
					2	TypeCompatibleV1Dot1WithoutBackupandRestore
		InspectionOrBackupLevelPort2	UInt64	Inspection / backup level		
					5	TypeCompatibleV1Dot1WithBackupandRestore
					7	TypeCompatibleV1Dot1WithRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupandRestore
		InspectionOrBackupLevelPort3	UInt64	Inspection / backup level		
					5	TypeCompatibleV1Dot1WithBackupandRestore
					7	TypeCompatibleV1Dot1WithRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupandRestore
		InspectionOrBackupLevelPort4	UInt64	Inspection / backup level		
					5	TypeCompatibleV1Dot1WithBackupandRestore
					7	TypeCompatibleV1Dot1WithRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupandRestore

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				2	StartupCpuIfMismatch
				1	StartupCpuOnlyIfCompatible
				0	FromCpu
	Comment	String	Comment		
	FirmwareVersion	String	Firmware version		
	PositionNumber	Int32	Slot		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
I/O Submodule					
	SharedDeviceAccessConfigured	Boolean			
	PositionNumber	Int32	Index		
	Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
				1	Manual
				0	Automatic
	Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
	Failsafe_FIODBName	String	F-I/O DB-name		
	Failsafe_FParameterSignatureWithoutAddresses	UInt64	F-parameter signature (without addresses)		
	Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
	Failsafe_FMonitoringtime	UInt64	F-monitoring time		
	Failsafe_FSourceAddress	UInt64	F-source address		
	Failsafe_FDestinationAddress	UInt64	F-destination address		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_BehaviorAfterChannelFault	UInt64	Behavior after channel fault		
				0	PassivateTheEntireModule
				1	PassivateChannel
	Failsafe_FPassivation	UInt64	RIOforFA safety		
	Failsafe_FParVersion	UInt64	PROFIsafe mode		
				1	V2mode
	Failsafe_FCRCSeed	UInt64	PROFIsafe protocol version		
	Failsafe_FParameterSignatureWithAddresses	UInt64	F-parameter signature (with addresses)		
	Name	String	Name		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				1	Active
				0	Deactivated
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				0	Value1oo1Evaluation
				1	Value1oo2EvaluationEquivalent
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				150	Value150ms
				140	Value140ms
				130	Value130ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
				120	Value120ms
				110	Value110ms
				100	Value100ms
				90	Value90ms
				80	Value80ms
				70	Value70ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 4					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation
		Failsafe_InputDelay	UInt64	Input delay		
					0	Value0ms
					50	Value50ms
					60	Value60ms
					70	Value70ms
					80	Value80ms
					90	Value90ms
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms
		Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
					0	DiscrepancyTimeFinite
					1	DiscrepancyTimeInfinite
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
					0	Deactivated
					1	SequenceMonitoringAscending
					2	SequenceMonitoringDescending
		Failsafe_StartupTest	Boolean	Start-up test		
					0	Deactivated
					1	Active

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 5					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation
		Failsafe_InputDelay	UInt64	Input delay		
					0	Value0ms
					50	Value50ms
					60	Value60ms
					70	Value70ms
					80	Value80ms
					90	Value90ms
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms
		Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
					0	DiscrepancyTimeFinite
					1	DiscrepancyTimeInfinite
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
					0	Deactivated
					1	SequenceMonitoringAscending
					2	SequenceMonitoringDescending
		Failsafe_StartupTest	Boolean	Start-up test		
					0	Deactivated
					1	Active

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation
		Failsafe_InputDelay	UInt64	Input delay		
					0	Value0ms
					50	Value50ms
					60	Value60ms
					70	Value70ms
					80	Value80ms
					90	Value90ms
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms
		Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
					0	DiscrepancyTimeFinite
					1	DiscrepancyTimeInfinite
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
					0	Deactivated
					1	SequenceMonitoringAscending
					2	SequenceMonitoringDescending
		Failsafe_StartupTest	Boolean	Start-up test		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					1	SupplyValue0
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					1	Test0SignalNecessary
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation
		Failsafe_InputDelay	UInt64	Input delay		
					0	Value0ms
					50	Value50ms
					60	Value60ms
					70	Value70ms
					80	Value80ms
					90	Value90ms
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms
		Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
					0	DiscrepancyTimeFinite
					1	DiscrepancyTimeInfinite
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 16					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 17					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 18					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 19					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation
		Failsafe_InputDelay	UInt64	Input delay		
					0	Value0ms
					50	Value50ms
					60	Value60ms
					70	Value70ms
					80	Value80ms
					90	Value90ms
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms
		Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
					0	DiscrepancyTimeFinite
					1	DiscrepancyTimeInfinite
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
					0	Deactivated
					1	SequenceMonitoringAscending
					2	SequenceMonitoringDescending
		Failsafe_StartupTest	Boolean	Start-up test		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					1	SupplyValue0
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					1	Test0SignalNecessary
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation
		Failsafe_InputDelay	UInt64	Input delay		
					0	Value0ms
					50	Value50ms
					60	Value60ms
					70	Value70ms
					80	Value80ms
					90	Value90ms
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms
		Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
					0	DiscrepancyTimeFinite
					1	DiscrepancyTimeInfinite
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
					0	Deactivated
					1	SequenceMonitoringAscending
					2	SequenceMonitoringDescending
		Failsafe_StartupTest	Boolean	Start-up test		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					1	SupplyValue0
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					1	Test0SignalNecessary
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation
		Failsafe_InputDelay	UInt64	Input delay		
					0	Value0ms
					50	Value50ms
					60	Value60ms
					70	Value70ms
					80	Value80ms
					90	Value90ms
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 22					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 23					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 24					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation
		Failsafe_InputDelay	UInt64	Input delay		
					0	Value0ms
					50	Value50ms
					60	Value60ms
					70	Value70ms
					80	Value80ms
					90	Value90ms
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms
		Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
					0	DiscrepancyTimeFinite
					1	DiscrepancyTimeInfinite
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
					0	Deactivated
					1	SequenceMonitoringAscending
					2	SequenceMonitoringDescending
		Failsafe_StartupTest	Boolean	Start-up test		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					1	SupplyValue0
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					1	Test0SignalNecessary
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation
		Failsafe_InputDelay	UInt64	Input delay		
					0	Value0ms
					50	Value50ms
					60	Value60ms
					70	Value70ms
					80	Value80ms
					90	Value90ms
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms
		Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
					0	DiscrepancyTimeFinite
					1	DiscrepancyTimeInfinite
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 26					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 27					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms
		Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
					0	DiscrepancyTimeFinite
					1	DiscrepancyTimeInfinite
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
					0	Deactivated
					1	SequenceMonitoringAscending
					2	SequenceMonitoringDescending
		Failsafe_StartupTest	Boolean	Start-up test		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					1	SupplyValue0
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					1	Test0SignalNecessary
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 29					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation
		Failsafe_InputDelay	UInt64	Input delay		
					0	Value0ms
					50	Value50ms
					60	Value60ms
					70	Value70ms
					80	Value80ms
					90	Value90ms
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms
		Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
					0	DiscrepancyTimeFinite
					1	DiscrepancyTimeInfinite
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
					0	Deactivated
					1	SequenceMonitoringAscending
					2	SequenceMonitoringDescending
		Failsafe_StartupTest	Boolean	Start-up test		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					1	SupplyValue0
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					1	Test0SignalNecessary
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activate input monitoring		
					0	Deactivated
					1	Active
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					1	Value1oo2EvaluationEquivalent
					0	Value1oo1Evaluation
		Failsafe_InputDelay	UInt64	Input delay		
					0	Value0ms
					50	Value50ms
					60	Value60ms
					70	Value70ms
					80	Value80ms
					90	Value90ms
					100	Value100ms
					110	Value110ms
					120	Value120ms
					130	Value130ms
					140	Value140ms
					150	Value150ms
		Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
					0	Deactivated
					1	Active
		Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
					0	DiscrepancyTimeFinite
					1	DiscrepancyTimeInfinite
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 31					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Failsafe_Activated	Boolean	Activate input monitoring		
				0	Deactivated
				1	Active
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				1	Value1oo2EvaluationEquivalent
				0	Value1oo1Evaluation
	Failsafe_InputDelay	UInt64	Input delay		
				0	Value0ms
				50	Value50ms
				60	Value60ms
				70	Value70ms
				80	Value80ms
				90	Value90ms
				100	Value100ms
				110	Value110ms
				120	Value120ms
				130	Value130ms
				140	Value140ms
				150	Value150ms

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	Failsafe_DiscrepancyMonitoring	UInt64	Discrepancy monitoring		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyTimeUnlimited	Boolean	Discrepancy time infinite		
				0	DiscrepancyTimeFinite
				1	DiscrepancyTimeInfinite
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_SequenceMonitoring	UInt64	Sequence monitoring		
				0	Deactivated
				1	SequenceMonitoringAscending
				2	SequenceMonitoringDescending
	Failsafe_StartupTest	Boolean	Start-up test		
				0	Deactivated
				1	Active
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				1	SupplyValue0
	Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
				1	Test0SignalNecessary
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Failsafe_Activated	Boolean	Activate output control		
				0	Deactivated
				1	Active
	Failsafe_AsiAddress	UInt64	AS-i address		
				0	Value0
				1	Value1
				2	Value2
				3	Value3
				5	Value5
				6	Value6
				7	Value7
				8	Value8
				9	Value9

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Failsafe_Activated	Boolean	Activate output control		
				0	Deactivated
				1	Active
	Failsafe_AsiAddress	UInt64	AS-i address		
				0	Value0
				1	Value1
				2	Value2
				3	Value3
				5	Value5
				6	Value6
				7	Value7
				8	Value8
				9	Value9
				10	Value10
				11	Value11
				12	Value12
				13	Value13
				14	Value14
				15	Value15
				16	Value16
				17	Value17
				18	Value18
				19	Value19
				20	Value20
				21	Value21
				22	Value22
				23	Value23
				24	Value24
				25	Value25
				26	Value26
				27	Value27

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18
					19	Value19
					20	Value20
					21	Value21
					22	Value22
					23	Value23
					24	Value24

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0						
					25	Value25
					26	Value26
					27	Value27
					28	Value28
					29	Value29
					30	Value30
					31	Value31
					4	Value4
		Failsafe_AuxAddress	String	Output address fault acknowledgment		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activate output control		
					0	Deactivated
					1	Active
		Failsafe_AsiAddress	UInt64	AS-i address		
					0	Value0
					1	Value1
					2	Value2
					3	Value3
					5	Value5
					6	Value6
					7	Value7
					8	Value8
					9	Value9
					10	Value10
					11	Value11
					12	Value12
					13	Value13
					14	Value14
					15	Value15
					16	Value16
					17	Value17
					18	Value18

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
				19	Value19
				20	Value20
				21	Value21
				22	Value22
				23	Value23
				24	Value24
				25	Value25
				26	Value26
				27	Value27
				28	Value28
				29	Value29
				30	Value30
				31	Value31
				4	Value4
	Failsafe_AuxAddress	String	Output address fault acknowledgment		
Channel 16					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 17					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 18					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 19					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 20					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 21					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 22					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 136-6SC00-0BC1 - V1.0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 23					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 24					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 25					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 26					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 27					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 28					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 29					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 30					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 31					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
AS-i Interface Submodule					
	InterfaceType	Int32			
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - 3RK7 137-6SA00-0BC1 - V1.0					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	I/O Submodule					
		Name	String	Name		
		PositionNumber	Int32	Index		
		AsiDiagnosticsConfigError	Boolean	Diagnostic interrupt if AS-i configuration error		
		AsiDiagnosticsCableFault	Boolean	Diagnostic interrupt if AS-i cable fault		
		AsiAutoAddressProgramming	Boolean	Automatic address programming		
		AsiGroundFaultDetection	Boolean	Ground fault monitoring activated		
		LengthOfIORange	UInt64	Reserved length		
					4	Value4Byte
					8	Value8Byte
					12	Value12Byte
					16	Value16Byte
					20	Value20Byte
					24	Value24Byte

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
					28	Value28Byte
					32	Value32Byte
					64	Value64Byte
					96	Value96Byte
					128	Value128Byte
					160	Value160Byte
					192	Value192Byte
					224	Value224Byte
					256	Value256Byte
					288	Value288Byte
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 16					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 17					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 18					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 19					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 20					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 21					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 22					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 23					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 24					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 25					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 26					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 27					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 28					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 29					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 30					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 32					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 33					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 34					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 35					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 36					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 37					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 38					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 39					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 40					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 41					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 42					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 43					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 44					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 45					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 46					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 47					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 48					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 49					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 50					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 51					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 52					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 53					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 54					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 55					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 56					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 57					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 58					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 59					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 60					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 61					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 62					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 63					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 64					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 65					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 66					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 67					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 68					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 69					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 70					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 71					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 72					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 73					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 74					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 75					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 76					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 77					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 78					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 79					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 80					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 81					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 82					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 83					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 84					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 85					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 86					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 87					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 88					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 89					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 90					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 91					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 92					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 93					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 94					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 95					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 96					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 97					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 98					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 99					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 100					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 101					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 102					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 103					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 104					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 105					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 106					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 107					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 108					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 109					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 110					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 111					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 112					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 113					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 114					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 115					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 116					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 117					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 118					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 119					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 120					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 121					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 122					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 123					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 124					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 125					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 126					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 127					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 128					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 129					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 130					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 131					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 132					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 133					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 134					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 135					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 136					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 137					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 138					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 139					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 140					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 141					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 142					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 143					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 144					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 145					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 146					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 147					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 148					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 149					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 150					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 151					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 152					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 153					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 154					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 155					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 156					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 157					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 158					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 159					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 160					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 161					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 162					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 163					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 164					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 165					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 166					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 167					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 168					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 169					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 170					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 171					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 172					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 173					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 174					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 175					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 176					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 177					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 178					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 179					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 180					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 181					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 182					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 183					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 184					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 185					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 186					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 187					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 188					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 189					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 190					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 191					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 192					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 193					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 194					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 195					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 196					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 197					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 198					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 199					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 200					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 201					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 202					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 203					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 204					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 205					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 206					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 207					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 208					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 209					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 210					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 211					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 212					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 213					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 214					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 215					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 216					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 217					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 218					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 219					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 220					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 221					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 222					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 223					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 224					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 225					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 226					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 227					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 228					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 229					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 230					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 231					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 232					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 233					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 234					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 235					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 236					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 237					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 238					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 239					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 240					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 241					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 242					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 243					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 244					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 245					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 246					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 247					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 248					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 249					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 250					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 251					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 252					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 253					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 254					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 255					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 1					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 24					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 25					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 26					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 27					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 28					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 29					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 30					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 31					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 32					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 33					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 34					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 35					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 36					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 37					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 38					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 39					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 40					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 41					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 42					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 43					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 44					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 45					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 46					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 47					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 48					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 49					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 50					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 51					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 52					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 53					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 54					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 55					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 56					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 57					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 58					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 59					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 60					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 61					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 62					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 63					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 64					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 65					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 66					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 67					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 68					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 69					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 70					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 71					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 72					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 73					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 74					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 75					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 76					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 77					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 78					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 79					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 80					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 81					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 82					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 83					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 84					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 85					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 86					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 87					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 88					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 89					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 90					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 91					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 92					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 93					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 94					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 95					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 96					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 97					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 98					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 99					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 100					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 101					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 102					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 103					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 104					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 105					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 106					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 107					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 108					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 109					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 110					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 111					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 112					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 113					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 114					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 115					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 116					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 117					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 118					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 119					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 120					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 121					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 122					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 123					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 124					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 125					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 126					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 127					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 128					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 129					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 130					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 131					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 132					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 133					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 134					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 135					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 136					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 137					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 138					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 139					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 140					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 141					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 142					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 143					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 144					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 145					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 146					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 147					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 148					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 149					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 150					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 151					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 152					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 153					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 154					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 155					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 156					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 157					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 158					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 159					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 160					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 161					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 162					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 163					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 164					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 165					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 166					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 167					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 168					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 169					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 170					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 171					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 172					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 173					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 174					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 175					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 176					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 177					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 178					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 179					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 180					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 181					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 182					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 183					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 184					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 185					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 186					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 187					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 188					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 189					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 190					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 191					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 192					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 193					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 194					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 195					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 196					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 197					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 198					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 199					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 200					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 201					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 202					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 203					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 204					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 205					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 206					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 207					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 208					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 209					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 210					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 211					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 212					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 213					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 214					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 215					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 216					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 217					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 218					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 219					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 220					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 221					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 222					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 223					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 224					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 225					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 226					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 227					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0					
Channel 228					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 229					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 230					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 231					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 232					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 233					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 234					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 235					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 236					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 237					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 238					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 239					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 240					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 241					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 242					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 243					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 244					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 245					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 246					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 247					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 248					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 249					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 250					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 251					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 252					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 253					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 254					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 255					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	AS-i Interface Submodule					
		InterfaceType	Int32			
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	I/O Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String	Name		
		StatusInfoActivate	Boolean	Process image for status information		
		StatusInfoStartAddressByte	UInt64	Start address - byte		
		StatusInfoStartAddressBit	Int64	Start address - bit		
		StatusInfoDIAG	String	DIAG		
		StatusInfoCFGOK	String	CFGOK		
		StatusInfoCM	String	CM		
		StatusInfoEFD	String	EFD		
		PositionNumber	Int32	Index		
		AsiDiagnosticsConfigError	Boolean	Diagnostic interrupt if AS-i configuration error		
		AsiDiagnosticsCableFault	Boolean	Diagnostic interrupt if AS-i cable fault		
		AsiAutoAddressProgramming	Boolean	Automatic address programming		
		AsiGroundFaultDetection	Boolean	Ground fault monitoring activated		
		AsiAutoID1Assignment	Boolean	Automatic ID1 code assignment		
		AsiMultipleAddressDetection	UInt64	Double address detection		
					2	ActivatedForAsi24V
					1	ActivatedForAsi30V
					0	Deactivated
		LengthOfIORange	UInt64	Reserved length		
					4	Value4Byte
					8	Value8Byte
					12	Value12Byte
					16	Value16Byte
					20	Value20Byte
					24	Value24Byte

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
					28	Value28Byte
					32	Value32Byte
					64	Value64Byte
					96	Value96Byte
					128	Value128Byte
					160	Value160Byte
					192	Value192Byte
					224	Value224Byte
					256	Value256Byte
					288	Value288Byte
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 16					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 17					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 18					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 19					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 24					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 25					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 26					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 27					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 28					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 29					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 30					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 31					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 32					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 33					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 34					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 35					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 36					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 37					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 38					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 39					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 40					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 41					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 42					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 43					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 44					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 45					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 46					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 47					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 48					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 49					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 50					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 51					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 52					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 53					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 54					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 55					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 56					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 57					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 58					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 59					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 60					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 61					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 62					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 63					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 64					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 65					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 66					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 67					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 68					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 69					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 70					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 71					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 72					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 73					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 74					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 75					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 76					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 77					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 78					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 79					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 80					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 81					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 82					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 83					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 84					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 85					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 86					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 87					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 88					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 89					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 90					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 91					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 92					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 93					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 94					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 95					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 96					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 97					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 98					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 99					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 100					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 101					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 102					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 103					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 104					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 105					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 106					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 107					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 108					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 109					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 110					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 111					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 112					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 113					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 114					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 115					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 116					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 117					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 118					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 119					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 120					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 121					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 122					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 123					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 124					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 125					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 126					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 127					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 128					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 129					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 130					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 131					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 132					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 133					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 134					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 135					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 136					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 137					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 138					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 139					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 140					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 141					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 142					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 143					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 144					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 145					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 146					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 147					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 148					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 149					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 150					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 151					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 152					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 153					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 154					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 155					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 156					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 157					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 158					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 159					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 160					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 161					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 162					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 163					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 164					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 165					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 166					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 167					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 168					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 169					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 170					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 171					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 172					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 173					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 174					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 175					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 176					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 177					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 178					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 179					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 180					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 181					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 182					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 183					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 184					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 185					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 186					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 187					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 188					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 189					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 190					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 191					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 192					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 193					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 194					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 195					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 196					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 197					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 198					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 199					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 200					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 201					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 202					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 203					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 204					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 205					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 206					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 207					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 208					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 209					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 210					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 211					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 212					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 213					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 214					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 215					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 216					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 217					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 218					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 219					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 220					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 221					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 222					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 223					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 224					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 225					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 226					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 227					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 228					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 229					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 230					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 231					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 232					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 233					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 234					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 235					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 236					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 237					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 238					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 239					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 240					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 241					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 242					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 243					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 244					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 245					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 246					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 247					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 248					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 249					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 250					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 251					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 252					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 253					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 254					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 255					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 1					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 16					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 17					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 18					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 19					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 20					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 21					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 22					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 23					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 24					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 25					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 26					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 27					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 28					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 29					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 30					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 31					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 32					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 33					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 34					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 35					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 36					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 37					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 38					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 39					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 40					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 41					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 42					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 43					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 44					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 45					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 46					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 47					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 48					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 49					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 50					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 51					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 52					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 53					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 54					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 55					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 56					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 57					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 58					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 59					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 60					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 61					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 62					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 63					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 64					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 65					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 66					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 67					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 68					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 69					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 70					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 71					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 72					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 73					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 74					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 75					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 76					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 77					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 78					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 79					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 80					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 81					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 82					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 83					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 84					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 85					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 86					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 87					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 88					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 89					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 90					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 91					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 92					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 93					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 94					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 95					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 96					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 97					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 98					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 99					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 100					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 101					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 102					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 103					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 104					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 105					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 106					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 107					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 108					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 109					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 110					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 111					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 112					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 113					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 114					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 115					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 116					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 117					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 118					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 119					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 120					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 121					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 122					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 123					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 124					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 125					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 126					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 127					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 128					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 129					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 130					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 131					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 132					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 133					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 134					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 135					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 136					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 137					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 138					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 139					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 140					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 141					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 142					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 143					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 144					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 145					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 146					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 147					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 148					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 149					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 150					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 151					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 152					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 153					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 154					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 155					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 156					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 157					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 158					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 159					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 160					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 161					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 162					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 163					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 164					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 165					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 166					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 167					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 168					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 169					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 170					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 171					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 172					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 173					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 174					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 175					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 176					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 177					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 178					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 179					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 180					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 181					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 182					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 183					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 184					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 185					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 186					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 187					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 188					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 189					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 190					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 191					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 192					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 193					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 194					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 195					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 196					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 197					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 198					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 199					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 200					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 201					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 202					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 203					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 204					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 205					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 206					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 207					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 208					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 209					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 210					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 211					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 212					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 213					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 214					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 215					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 216					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 217					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 218					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 219					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 220					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 221					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 222					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 223					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 224					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 225					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 226					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 227					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1					
Channel 228					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 229					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 230					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 231					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 232					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 233					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 234					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 235					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 236					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 237					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 238					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 239					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 240					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 241					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 242					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 243					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 244					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 245					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 246					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 247					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 248					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 249					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 250					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK7 137-6SA00-0BC1 - V1.1						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 251					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 252					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 253					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 254					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 255					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	AS-i Interface Submodule					
		InterfaceType	Int32			
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6PA00-0BC0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	FirmwareVersion	String	Firmware version		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	TypeName	String	InvariantTypeName		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	Name	String	Name		
	Comment	String	Comment		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Failsafe_MaximumTestPeriod	UInt64	Maximum test period		
				0	Value100sec
				1	Value1000sec
	Failsafe_ShortCircuitTest_0	Boolean	Short-circuit test		
				0	Deactivated
				1	Active
	Failsafe_TimeForShortCircuitTest_0	Double	Time for short-circuit test		
	Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
	Failsafe_ShortCircuitTest_1	Boolean	Short-circuit test		
				0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6PA00-0BC0 - V1.0						
					1	Active
		Failsafe_TimeForShortCircuitTest_1	Double	Time for short-circuit test		
		Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
		Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
		Failsafe_FParameterSignatureWithoutAddresses	UInt64	F-parameter signature (without addresses)		
		Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
					0	Automatic
					1	Manual
		Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
		Failsafe_FIODBName	String	F-I/O DB-name		
		Failsafe_FSourceAddress	UInt64	F-source address		
		Failsafe_FMonitoringtime	UInt64	F-monitoring time		
		Failsafe_FDestinationAddress	UInt64	F-destination address		
		Failsafe_BehaviorAfterChannelFault	UInt64	Behavior after channel fault		
					0	PassivateTheEntireModule
					1	PassivateChannel
		Failsafe_FParameterSignatureWithAddresses	UInt64	F-parameter signature (with addresses)		
		Failsafe_FPassivation	UInt64	RIOforFA safety		
		Failsafe_FParVersion	UInt64	PROFIsafe mode		
					0	V1mode
					1	V2mode
		Failsafe_FCRCSeed	UInt64	PROFIsafe protocol version		
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0,1					
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					0	Value1oo1Evaluation
					1	Value1oo2EvaluationEquivalent
					2	Value1oo2EvaluationNonEquivalent
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					0	SupplyLastValidValue
					1	SupplyValue0

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6PA00-0BC0 - V1.0						
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					0	Test0SignalNotNecessary
					1	Test0SignalNecessary
	Channel 0					
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0
					1	SensorSupply1
					2	SensorSupply2
		Failsafe_InputDelay	UInt64	Input delay		
					1	Value0dot4ms
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					10	Value10ms
					12	Value12dot8ms
					20	Value20ms
		Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
					0	Deactivated
					1	Active
		Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
		Failsafe_MonitoringWindow	UInt64	Monitoring window		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6PA00-0BC0 - V1.0						
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0
					1	SensorSupply1
					2	SensorSupply2
		Failsafe_InputDelay	UInt64	Input delay		
					1	Value0dot4ms
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					10	Value10ms
					12	Value12dot8ms
					20	Value20ms
		Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
					0	Deactivated
					1	Active
		Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
		Failsafe_MonitoringWindow	UInt64	Monitoring window		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 0					
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_ControlOfOutput	UInt64	Control of output		
					0	FCPU
					1	FCPUAndOnboardFDI
		Failsafe_OutputType	UInt64	Output type		
					0	PMSwitching
					1	PPSwitching
		Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time dark test		
		Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6PA00-0BC0 - V1.0						
		Failsafe_ActivatedLightTest	Boolean	Activated light test		
					0	Deactivated
					1	Active
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Module - 6ES7 136-6AA00-0CA1 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		FirmwareVersion	String	Firmware version		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
					0	FromCpu
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	Index		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6AA00-0CA1 - V1.0						
		Failsafe_ReintegrationAfterChannelFault	UInt64	Reintegration after channel fault		
					0	Adjustable
					1	AllChannelsAutomatically
					2	AllChannelsManually
		Failsafe_InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					0	Value50Hz
					1	Value60Hz
		Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
		Failsafe_FMonitoringtime	UInt64	F-monitoring time		
		Failsafe_FParameterSignatureWithoutAddresses	UInt64	F-parameter signature (without addresses)		
		Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
					0	Automatic
					1	Manual
		Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
		Failsafe_FIODBName	String	F-I/O DB-name		
		Failsafe_FSourceAddress	UInt64	F-source address		
		Failsafe_FParameterSignatureWithAddresses	UInt64	F-parameter signature (with addresses)		
		Failsafe_FDestinationAddress	UInt64	F-destination address		
		Failsafe_BehaviorAfterChannelFault	UInt64	Behavior after channel fault		
					0	PassivateTheEntireModule
					1	PassivateChannel
		Failsafe_FPassivation	UInt64	RIOforFA safety		
		Failsafe_FParVersion	UInt64	PROFIsafe mode		
					0	V1mode
					1	V2mode
		Failsafe_FCRCSeed	UInt64	PROFIsafe protocol version		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0,2					
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					0	Value1oo1Evaluation
					1	Value1oo2EvaluationEquivalent

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6AA00-0CA1 - V1.0					
	Failsafe_UnitValue	UInt64	Unit value		
				0	Min
				1	Max
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_ToleranceWindowAbsolute	Double	Tolerance window abs.		
	Failsafe_ToleranceWindowRelative	Double	Tolerance window rel.		
Channel 1,3					
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				0	Value1oo1Evaluation
				1	Value1oo2EvaluationEquivalent
	Failsafe_UnitValue	UInt64	Unit value		
				0	Min
				1	Max
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
	Failsafe_ToleranceWindowAbsolute	Double	Tolerance window abs.		
	Failsafe_ToleranceWindowRelative	Double	Tolerance window rel.		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	Failsafe_Activated	Boolean	Activated		
				0	Deactivated
				1	Active
	Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
				0	Manual
				1	Automatic
	Failsafe_MeasuringRange	UInt64	Measuring range		
				0	Value0To20
				1	Value4To20
	Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
				0	Deactivated
				1	Active
	Failsafe_Smoothing	UInt64	Smoothing		
				0	Value1x

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6AA00-0CA1 - V1.0						
					1	Value2x
					2	Value4x
					3	Value8x
					4	Value16x
					5	Value32x
					6	Value64x
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
		Failsafe_MeasuringRange	UInt64	Measuring range		
					0	Value0To20
					1	Value4To20
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
		Failsafe_Smoothing	UInt64	Smoothing		
					0	Value1x
					1	Value2x
					2	Value4x
					3	Value8x
					4	Value16x
					5	Value32x
					6	Value64x
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6AA00-0CA1 - V1.0						
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
		Failsafe_MeasuringRange	UInt64	Measuring range		
					0	Value0To20
					1	Value4To20
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
		Failsafe_Smoothing	UInt64	Smoothing		
					0	Value1x
					1	Value2x
					2	Value4x
					3	Value8x
					4	Value16x
					5	Value32x
					6	Value64x
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
		Failsafe_MeasuringRange	UInt64	Measuring range		
					0	Value0To20
					1	Value4To20

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6AA00-0CA1 - V1.0						
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
		Failsafe_Smoothing	UInt64	Smoothing		
					0	Value1x
					1	Value2x
					2	Value4x
					3	Value8x
					4	Value16x
					5	Value32x
					6	Value64x
Module - 6ES7 136-6DC00-0CA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		FirmwareVersion	String	Firmware version		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6DC00-0CA0 - V1.0						
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	Index		
		Failsafe_MaximumTestPeriod	UInt64	Maximum test period		
					0	Value100sec
					1	Value1000sec
		Failsafe_DisableDarkTestFor48Hours	Boolean	Disable dark test for 48 hours		
					0	Deactivated
					1	Active
		Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
		Failsafe_FParameterSignatureWithoutAddresses	UInt64	F-parameter signature (without addresses)		
		Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
					0	Automatic
					1	Manual
		Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
		Failsafe_FIODBName	String	F-I/O DB-name		
		Failsafe_FSourceAddress	UInt64	F-source address		
		Failsafe_FParameterSignatureWithAddresses	UInt64	F-parameter signature (with addresses)		
		Failsafe_FMonitoringtime	UInt64	F-monitoring time		
		Failsafe_FDestinationAddress	UInt64	F-destination address		
		Failsafe_BehaviorAfterChannelFault	UInt64	Behavior after channel fault		
					0	PassivateTheEntireModule
					1	PassivateChannel
		Failsafe_ReintegrationAfterChannelFault	UInt64	Reintegration after channel fault		
					1	AllChannelsAutomatically
					2	AllChannelsManually
					0	Adjustable
		Failsafe_FPassivation	UInt64	RIOforFA safety		
		Failsafe_FParVersion	UInt64	PROFIsafe mode		
					0	V1mode
					1	V2mode
		Failsafe_FCRCSeed	UInt64	PROFIsafe protocol version		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6DC00-0CA0 - V1.0						
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activated		
					1	Active
		Failsafe_MaxReadbackTimeLightTestAndDarkTest	UInt64	Max. readback time light test / dark test		
					0	Value08Or10ms
					1	Value30Or50ms
		Failsafe_ActivatedLightTest	Boolean	Activated light test		
					1	Active
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activated		
					1	Active
		Failsafe_MaxReadbackTimeLightTestAndDarkTest	UInt64	Max. readback time light test / dark test		
					0	Value08Or10ms
					1	Value30Or50ms
		Failsafe_ActivatedLightTest	Boolean	Activated light test		
					1	Active
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activated		
					1	Active

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6DC00-0CA0 - V1.0					
	Failsafe_MaxReadbackTimeLightTestAndDarkTest	UInt64	Max. readback time light test / dark test		
				0	Value08Or10ms
				1	Value30Or50ms
	Failsafe_ActivatedLightTest	Boolean	Activated light test		
				1	Active
	Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
				0	Manual
				1	Automatic
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Failsafe_Activated	Boolean	Activated		
				1	Active
	Failsafe_MaxReadbackTimeLightTestAndDarkTest	UInt64	Max. readback time light test / dark test		
				0	Value08Or10ms
				1	Value30Or50ms
	Failsafe_ActivatedLightTest	Boolean	Activated light test		
				1	Active
	Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
				0	Manual
				1	Automatic
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Failsafe_Activated	Boolean	Activated		
				1	Active
	Failsafe_MaxReadbackTimeLightTestAndDarkTest	UInt64	Max. readback time light test / dark test		
				0	Value08Or10ms
				1	Value30Or50ms
	Failsafe_ActivatedLightTest	Boolean	Activated light test		
				1	Active
	Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
				0	Manual

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6DC00-0CA0 - V1.0						
					1	Automatic
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		Failsafe_Activated	Boolean	Activated		
					1	Active
		Failsafe_MaxReadbackTimeLightTestAndDarkTest	UInt64	Max. readback time light test / dark test		
					0	Value08Or10ms
					1	Value30Or50ms
		Failsafe_ActivatedLightTest	Boolean	Activated light test		
					1	Active
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		Failsafe_Activated	Boolean	Activated		
					1	Active
		Failsafe_MaxReadbackTimeLightTestAndDarkTest	UInt64	Max. readback time light test / dark test		
					0	Value08Or10ms
					1	Value30Or50ms
		Failsafe_ActivatedLightTest	Boolean	Activated light test		
					1	Active
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		Failsafe_Activated	Boolean	Activated		
					1	Active

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6DC00-0CA0 - V1.0						
		Failsafe_MaxReadbackTimeLightTestAndDarkTest	UInt64	Max. readback time light test / dark test		
					0	Value08Or10ms
					1	Value30Or50ms
		Failsafe_ActivatedLightTest	Boolean	Activated light test		
					1	Active
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
Module - 6ES7 136-6DB00-0CA0 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Name	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6DB00-0CA0 - V2.0						
		Name	String			
		Failsafe_MaximumTestPeriod	UInt64	Maximum test period		
					0	Value100sec
					1	Value1000sec
		PositionNumber	Int32	Index		
		Failsafe_DisableDarkTestMaxSIL2_CAT3_PLd	Boolean	Disable Dark Test (max. SIL2, CAT3, PLd)		
					0	Deactivated
					1	Active
		Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
		Failsafe_FParameterSignatureWithoutAddresses	UInt64	F-parameter signature (without addresses)		
		Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
					0	Automatic
					1	Manual
		Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
		Failsafe_FIODBName	String	F-I/O DB-name		
		Failsafe_FSourceAddress	UInt64	F-source address		
		Failsafe_FMonitoringtime	UInt64	F-monitoring time		
		Failsafe_FDestinationAddress	UInt64	F-destination address		
		Failsafe_BehaviorAfterChannelFault	UInt64	Behavior after channel fault		
					0	PassivateTheEntireModule
					1	PassivateChannel
		Failsafe_FParameterSignatureWithAddresses	UInt64	F-parameter signature (with addresses)		
		Failsafe_FPassivation	UInt64	RIOforFA safety		
		Failsafe_FParVersion	UInt64	PROFIsafe mode		
					1	V2mode
		Failsafe_FCRCSeed	UInt64	PROFIsafe protocol version		
		Name	String	Name		
		Comment	String	Comment		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6DB00-0CA0 - V2.0					
				1	Active
	Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		
	Failsafe_ActivatedLightTest	Boolean	Activated light test		
				0	Deactivated
				1	Active
	Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
				0	Deactivated
				1	Active
	Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time, dark test and switch-off test		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Failsafe_Activated	Boolean	Activated		
				0	Deactivated
				1	Active
	Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		
	Failsafe_ActivatedLightTest	Boolean	Activated light test		
				0	Deactivated
				1	Active
	Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
				0	Deactivated
				1	Active
	Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time, dark test and switch-off test		
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Failsafe_Activated	Boolean	Activated		
				0	Deactivated
				1	Active
	Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		
	Failsafe_ActivatedLightTest	Boolean	Activated light test		
				0	Deactivated
				1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6DB00-0CA0 - V2.0						
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
		Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time, dark test and switch-off test		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		
		Failsafe_ActivatedLightTest	Boolean	Activated light test		
					0	Deactivated
					1	Active
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
		Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time, dark test and switch-off test		
Module - 6ES7 146-5FF00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 146-5FF00-0BA0 - V1.0						
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Failsafe_ShortCircuitDiagnosticActive	Boolean	Short-circuit test		
					0	Disable
					1	Enable
		Failsafe_ShortCircuitTestInterval	UInt64	Interval for short-circuit test		
					9	Value12Dot8
					11	Value25Dot6
					12	Value51Dot2
					13	Value102Dot4
					14	Value204Dot8
					15	Value409Dot6
					16	Value819Dot2
		Failsafe_ShortCircuitTestDuration	UInt64	Duration of short-circuit test		
					5	Value1Dot6
					6	Value3Dot2
					7	Value6Dot4
					9	Value12Dot8
		Failsafe_MaximumTestPeriod	UInt64	Maximum test period		
					0	Value100sec
					1	Value1000sec
	Channel 0,2					
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					0	Value1oo1Evaluation
					1	Value1oo2EvaluationEquivalent
					3	Value1oo2Evaluation2Channel3WireNonEquivalent

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 146-5FF00-0BA0 - V1.0						
					4	Value1oo2Evaluation2Channel4WireNonEquivalent
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					0	SupplyLastValidValue
					1	SupplyValue0
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					0	Test0SignalNotNecessary
					1	Test0SignalNecessary
	Channel 1,3					
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					0	Value1oo1Evaluation
					1	Value1oo2EvaluationEquivalent
					3	Value1oo2Evaluation2Channel3WireNonEquivalent
					4	Value1oo2Evaluation2Channel4WireNonEquivalent
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					0	SupplyLastValidValue
					1	SupplyValue0
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					0	Test0SignalNotNecessary
					1	Test0SignalNecessary
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_InputDelay	UInt64	Input filter		
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 146-5FF00-0BA0 - V1.0						
					6	Value6dot4ms
					12	Value12dot8ms
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
		Failsafe_SensorSupply	UInt64	Sensor supply		
					9	External
					10	Internal
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_InputDelay	UInt64	Input filter		
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					12	Value12dot8ms
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
		Failsafe_SensorSupply	UInt64	Sensor supply		
					9	External
					10	Internal
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 146-5FF00-0BA0 - V1.0						
		Failsafe_InputDelay	UInt64	Input filter		
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					12	Value12dot8ms
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
		Failsafe_SensorSupply	UInt64	Sensor supply		
					9	External
					10	Internal
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_InputDelay	UInt64	Input filter		
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					12	Value12dot8ms
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
		Failsafe_SensorSupply	UInt64	Sensor supply		
					9	External
					10	Internal
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 146-5FF00-0BA0 - V1.0					
	Failsafe_DiagnosisWireBreak	Boolean	Wire break		
				0	Deactivated
				1	Active
	Failsafe_Activated	Boolean	Activated		
				0	Deactivated
				1	Active
	Failsafe_DisableDarkTestMaxSIL2_CAT3_PLd	Boolean	Disable Dark Test (max. SIL2, CAT3, PLd)		
				0	Deactivated
				1	Active
	Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
				0	Manual
				1	Automatic
	Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time		
	Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Failsafe_DiagnosisWireBreak	Boolean	Wire break		
				0	Deactivated
				1	Active
	Failsafe_Activated	Boolean	Activated		
				0	Deactivated
				1	Active
	Failsafe_DisableDarkTestMaxSIL2_CAT3_PLd	Boolean	Disable Dark Test (max. SIL2, CAT3, PLd)		
				0	Deactivated
				1	Active
	Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
				0	Manual
				1	Automatic
	Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time		
	Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		
Module - 6ES7 136-6AB00-0CA1 - V1.0					
	SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6AB00-0CA1 - V1.0						
		BaseUnit	String			
		Name	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		TypeName	String	InvariantTypeName		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
		Failsafe_FMonitoringtime	UInt64	F-monitoring time		
		Failsafe_FParameterSignatureWithoutAddresses	UInt64	F-parameter signature (without addresses)		
		Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
					0	Automatic
					1	Manual
		Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
		Failsafe_FIODBName	String	F-I/O DB-name		
		Failsafe_FSourceAddress	UInt64	F-source address		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6AB00-0CA1 - V1.0						
		Failsafe_FParameterSignatureWithAddresses	UInt64	F-parameter signature (with addresses)		
		Name	String	Name		
		Comment	String	Comment		
		Failsafe_FDestinationAddress	UInt64	F-destination address		
		Failsafe_BehaviorAfterChannelFault	UInt64	Behavior after channel fault		
					0	PassivateTheEntireModule
					1	PassivateChannel
		Failsafe_ReintegrationAfterChannelFault	UInt64	Reintegration after channel fault		
					1	AllChannelsAutomatically
					2	AllChannelsManually
					0	Adjustable
		Failsafe_FPassivation	UInt64	RIOforFA safety		
					1	Channel
					0	DeviceModule
		Failsafe_FParVersion	UInt64	PROFIsafe mode		
					1	V2mode
		Failsafe_FCRCSeed	UInt64	PROFIsafe protocol version		
					1	CRCSeed32
					0	CRCSeed16
		Failsafe_InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					0	Value50Hz
					1	Value60Hz
	Channel 0,2					
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					0	Value1oo1Evaluation
					1	Value1oo2EvaluationEquivalent
		Failsafe_UnitValue	UInt64	Unit value		
					0	Min
					1	Max
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_ToleranceWindowAbsolute	Double	Tolerance window abs.		
		Failsafe_ToleranceWindowRelative	Double	Tolerance window rel.		
	Channel 1,3					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6AB00-0CA1 - V1.0						
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					0	Value1oo1Evaluation
					1	Value1oo2EvaluationEquivalent
		Failsafe_UnitValue	UInt64	Unit value		
					0	Min
					1	Max
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_ToleranceWindowAbsolute	Double	Tolerance window abs.		
		Failsafe_ToleranceWindowRelative	Double	Tolerance window rel.		
	Channel 0					
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
		Failsafe_MeasuringRange	UInt64	Measuring range		
					2	Value0To10
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
		Failsafe_Smoothing	UInt64	Smoothing		
					0	Value1x
					1	Value2x
					2	Value4x
					3	Value8x
					4	Value16x
					5	Value32x
					6	Value64x
	Channel 1					
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6AB00-0CA1 - V1.0						
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
		Failsafe_MeasuringRange	UInt64	Measuring range		
					2	Value0To10
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
		Failsafe_Smoothing	UInt64	Smoothing		
					0	Value1x
					1	Value2x
					2	Value4x
					3	Value8x
					4	Value16x
					5	Value32x
					6	Value64x
	Channel 2					
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
		Failsafe_MeasuringRange	UInt64	Measuring range		
					2	Value0To10
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
		Failsafe_Smoothing	UInt64	Smoothing		
					0	Value1x
					1	Value2x
					2	Value4x
					3	Value8x

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6AB00-0CA1 - V1.0						
					4	Value16x
					5	Value32x
					6	Value64x
	Channel 3					
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_ChannelFailureAcknowledge	UInt64	Channel failure acknowledge		
					0	Manual
					1	Automatic
		Failsafe_MeasuringRange	UInt64	Measuring range		
					2	Value0To10
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
		Failsafe_Smoothing	UInt64	Smoothing		
					0	Value1x
					1	Value2x
					2	Value4x
					3	Value8x
					4	Value16x
					5	Value32x
					6	Value64x
Module - 6ES7 136-6CB00-0CA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Name	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		TypeName	String	InvariantTypeName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6CB00-0CA0 - V1.0						
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
		Failsafe_FMonitoringtime	UInt64	F-monitoring time		
		Failsafe_FParameterSignatureWithoutAddresses	UInt64	F-parameter signature (without addresses)		
		Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
					0	Automatic
					1	Manual
		Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
		Failsafe_FIODBName	String	F-I/O DB-name		
		Failsafe_FSourceAddress	UInt64	F-source address		
		Failsafe_FParameterSignatureWithAddresses	UInt64	F-parameter signature (with addresses)		
		Name	String	Name		
		Comment	String	Comment		
		Failsafe_FPassivation	UInt64	RIOforFA safety		
					0	DeviceModule
					1	Channel
		Failsafe_FDestinationAddress	UInt64	F-destination address		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6CB00-0CA0 - V1.0						
		Failsafe_BehaviorAfterChannelFault	UInt64	Behavior after channel fault		
					0	PassivateTheEntireModule
		Failsafe_ReintegrationAfterChannelFault	UInt64	Reintegration after channel fault		
					2	AllChannelsManually
		Failsafe_FParVersion	UInt64	PROFIsafe mode		
					1	V2mode
		Failsafe_FCRCSeed	UInt64	PROFIsafe protocol version		
					1	CRCSeed32
					0	CRCSeed16
		Failsafe_Activated	Boolean	Activated		
					1	Active
		Failsafe_CountValue	byte	Counting/Position input		
					1	IntegerCountValue
		Failsafe_CounterMeasuredValue	byte	Measuring		
					1	MeasuredValue
		Failsafe_SignalMonitoring	byte	Signal Monitoring		
					0	No
					1	Yes
		Failsafe_EncoderSignalType	byte	Signal type		
					0	SinCosEncoderABN
					1	SinCosEncoderAB
		Failsafe_EncoderInvertDirection	byte	Invert direction		
					0	NotInverted
					1	Inverted
		Failsafe_EncoderPulsesPerRotation	UInt64	Pulses per rotation		
		Failsafe_EncoderSignalEvaluation	byte	Signal Evaluation		
					2	Quadruple
		Failsafe_EncoderReactionToSignalN	byte	Reaction to signal N		
					0	NoReactionToSignalN
					1	SynchronizationAtSignalN
		Failsafe_ReactionToCountingLimit	byte	Reaction to violation of a counting limit		
					0	ContinueCountingOperation
					1	DiscontinueCountingOperation

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6CB00-0CA0 - V1.0						
		Failsafe_ResetReactionAtCountingLimit	byte	Reset when counting limit is violated		
					0	StartValue
					1	ToOppositeCountingLimit
		Failsafe_CounterReactionToGate	byte	Reaction to gate start		
					0	SetToStartValue
					1	ContinueWithCurrentValue
		Failsafe_MeasuredValueMeasuredVariable	byte	Measured value		
					0	Frequency
					1	Velocity
					2	PeriodDuration
		Failsafe_MeasuredValueUpdateTime	UInt64	Update time		
		Failsafe_MeasuredValueTimeBaseForVelocityMea	byte	Time base for velocity measurement		
					0	Value1Millisecond
					1	Value10Milliseconds
					2	Value100Milliseconds
					3	Value1Second
					4	Value60Seconds
		Failsafe_MeasuredValueCountsPerUnit	UInt64	Counts per unit for velocity measurement		
		Failsafe_SafeOperatingStopActive	byte	Safety Function - Safe Stop		
					0	Disabled
					1	Enabled
		Failsafe_SafeOperatingStopStandstillTolerance	UInt64	Standstill tolerance		
		Failsafe_SafeDirectionActive	byte	Safety Function - Safe Direction		
					0	Disabled
					1	Enabled
		Failsafe_SafeDirectionMonitoringTolerance	UInt64	Monitoring tolerance		
		Failsafe_SafetyLimitedSpeedActive	byte	Safety Function - Limited Speed		
					0	Disabled
					1	Enabled
		Failsafe_SafetyLimitedSpeedMaximumSpeedLimit	UInt64	Speed limit		
		Failsafe_ReactionToCpuStop	byte	Reaction to CPU STOP		
					0	ContinueCountingOperation
					1	DiscontinueCountingOperation

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6CB00-0CA0 - V1.0						
		Failsafe_CounterHighCountingLimit	Int64	High counting limit		
		Failsafe_CounterStartValue	Int64	Start value		
		Failsafe_CounterLowCountingLimit	Int64	Low counting limit		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6PA00-0BC0 - V2.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	FirmwareVersion	String	Firmware version		
	Name	String	Name		
	Comment	String	Comment		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Failsafe_MaximumTestPeriod	UInt64	Maximum test period		
				0	Value100sec
				1	Value1000sec
	Failsafe_ShortCircuitTest_0	Boolean	Short-circuit test		
				0	Deactivated
				1	Active
	Failsafe_TimeForShortCircuitTest_0	Double	Time for short-circuit test		
	Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
	Failsafe_ShortCircuitTest_1	Boolean	Short-circuit test		
				0	Deactivated

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6PA00-0BC0 - V2.0					
				1	Active
	Failsafe_TimeForShortCircuitTest_1	Double	Time for short-circuit test		
	Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
	PositionNumber	Int32	Index		
	Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
	Failsafe_FParameterSignatureWithoutAddresses	UInt64	F-parameter signature (without addresses)		
	Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
				0	Automatic
				1	Manual
	Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
	Failsafe_FIODBName	String	F-I/O DB-name		
	Failsafe_FSourceAddress	UInt64	F-source address		
	Failsafe_FMonitoringtime	UInt64	F-monitoring time		
	Failsafe_FDestinationAddress	UInt64	F-destination address		
	Failsafe_BehaviorAfterChannelFault	UInt64	Behavior after channel fault		
				0	PassivateTheEntireModule
				1	PassivateChannel
	Failsafe_FParameterSignatureWithAddresses	UInt64	F-parameter signature (with addresses)		
	Failsafe_FPassivation	UInt64	RIOforFA safety		
	Failsafe_FParVersion	UInt64	PROFIsafe mode		
				1	V2mode
	Failsafe_FCRCSeed	UInt64	PROFIsafe protocol version		
	Name	String	Name		
	Comment	String	Comment		
Channel 0,1					
	Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
				0	Value1oo1Evaluation
				1	Value1oo2EvaluationEquivalent
				2	Value1oo2EvaluationNonEquivalent
	Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
				0	SupplyLastValidValue
				1	SupplyValue0
	Failsafe_DiscrepancyTime	UInt64	Discrepancy time		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6PA00-0BC0 - V2.0						
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					0	Test0SignalNotNecessary
					1	Test0SignalNecessary
	Channel 0					
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0
					1	SensorSupply1
					2	SensorSupply2
		Failsafe_InputDelay	UInt64	Input delay		
					1	Value0dot4ms
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					10	Value10ms
					12	Value12dot8ms
					20	Value20ms
		Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
					0	Deactivated
					1	Active
		Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
		Failsafe_MonitoringWindow	UInt64	Monitoring window		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6PA00-0BC0 - V2.0					
				1	SensorSupply1
				2	SensorSupply2
	Failsafe_InputDelay	UInt64	Input delay		
				1	Value0dot4ms
				2	Value0dot8ms
				3	Value1dot6ms
				4	Value3dot2ms
				6	Value6dot4ms
				10	Value10ms
				12	Value12dot8ms
				20	Value20ms
	Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
				0	Deactivated
				1	Active
	Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
	Failsafe_MonitoringWindow	UInt64	Monitoring window		
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 0					
	Failsafe_ControlOfOutput	UInt64	Control of output		
				0	FCPU
				1	FCPUAndOnboardFDI
	Failsafe_OutputType	UInt64	Output type		
				0	PMSwitching
				1	PPSwitching
	Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		
	Failsafe_ActivatedLightTest	Boolean	Activated light test		
				0	Deactivated
				1	Active
	Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
				0	Deactivated
				1	Active
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6PA00-0BC0 - V2.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time, dark test and switch-off test		
		Failsafe_DisableDarkTestMaxSIL2_CAT3_PLd	Boolean	Disable Dark Test (max. SIL2, CAT3, PLd)		
					0	Deactivated
					1	Active
Module - 6ES7 136-6BA00-0CA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		TypeName	String	InvariantTypeName		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6BA00-0CA0 - V1.0						
		Failsafe_ShortCircuitTest_0	Boolean	Short-circuit test		
					0	Deactivated
					1	Active
		Failsafe_TimeForShortCircuitTest_0	Double	Time for short-circuit test		
		Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
		Failsafe_ShortCircuitTest_1	Boolean	Short-circuit test		
					0	Deactivated
					1	Active
		Failsafe_TimeForShortCircuitTest_1	Double	Time for short-circuit test		
		Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
		Failsafe_ShortCircuitTest_2	Boolean	Short-circuit test		
					0	Deactivated
					1	Active
		Failsafe_TimeForShortCircuitTest_2	Double	Time for short-circuit test		
		Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
		Failsafe_ShortCircuitTest_3	Boolean	Short-circuit test		
					0	Deactivated
					1	Active
		Failsafe_TimeForShortCircuitTest_3	Double	Time for short-circuit test		
		Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
		Failsafe_ShortCircuitTest_4	Boolean	Short-circuit test		
					0	Deactivated
					1	Active
		Failsafe_TimeForShortCircuitTest_4	Double	Time for short-circuit test		
		Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
		Failsafe_ShortCircuitTest_5	Boolean	Short-circuit test		
					0	Deactivated
					1	Active
		Failsafe_TimeForShortCircuitTest_5	Double	Time for short-circuit test		
		Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
		Failsafe_ShortCircuitTest_6	Boolean	Short-circuit test		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6BA00-0CA0 - V1.0						
		Failsafe_TimeForShortCircuitTest_6	Double	Time for short-circuit test		
		Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
		Failsafe_ShortCircuitTest_7	Boolean	Short-circuit test		
					0	Deactivated
					1	Active
		Failsafe_TimeForShortCircuitTest_7	Double	Time for short-circuit test		
		Failsafe_StartupTimeOfSensorAfterShortCircuitTes	Double	Startup time of sensor after short-circuit test		
		Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
		Failsafe_FParameterSignatureWithoutAddresses	UInt64	F-parameter signature (without addresses)		
		Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
					0	Automatic
					1	Manual
		Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
		Failsafe_FIODBName	String	F-I/O DB-name		
		Failsafe_FMonitoringtime	UInt64	F-monitoring time		
		Failsafe_FSourceAddress	UInt64	F-source address		
		Failsafe_FDestinationAddress	UInt64	F-destination address		
		Failsafe_BehaviorAfterChannelFault	UInt64	Behavior after channel fault		
					0	PassivateTheEntireModule
					1	PassivateChannel
		Failsafe_FParameterSignatureWithAddresses	UInt64	F-parameter signature (with addresses)		
		Failsafe_FPassivation	UInt64	RIOforFA safety		
		Failsafe_FParVersion	UInt64	PROFIsafe mode		
					0	V1mode
					1	V2mode
		Failsafe_FCRCSeed	UInt64	PROFIsafe protocol version		
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0,4					
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					0	Value1oo1Evaluation
					1	Value1oo2EvaluationEquivalent

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6BA00-0CA0 - V1.0						
					2	Value1oo2EvaluationNonEquivalent
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					0	SupplyLastValidValue
					1	SupplyValue0
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					0	Test0SignalNotNecessary
					1	Test0SignalNecessary
	Channel 1,5					
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					0	Value1oo1Evaluation
					1	Value1oo2EvaluationEquivalent
					2	Value1oo2EvaluationNonEquivalent
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					0	SupplyLastValidValue
					1	SupplyValue0
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					0	Test0SignalNotNecessary
					1	Test0SignalNecessary
	Channel 2,6					
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					0	Value1oo1Evaluation
					1	Value1oo2EvaluationEquivalent
					2	Value1oo2EvaluationNonEquivalent
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					0	SupplyLastValidValue
					1	SupplyValue0
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					0	Test0SignalNotNecessary
					1	Test0SignalNecessary
	Channel 3,7					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6BA00-0CA0 - V1.0						
		Failsafe_SensorEvaluation	UInt64	Sensor evaluation		
					0	Value1oo1Evaluation
					1	Value1oo2EvaluationEquivalent
					2	Value1oo2EvaluationNonEquivalent
		Failsafe_DiscrepancyBehavior	UInt64	Discrepancy behavior		
					0	SupplyLastValidValue
					1	SupplyValue0
		Failsafe_DiscrepancyTime	UInt64	Discrepancy time		
		Failsafe_ReintegrationAfterDiscrepancyError	UInt64	Reintegration after discrepancy error		
					0	Test0SignalNotNecessary
					1	Test0SignalNecessary
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0
					1	SensorSupply1
					2	SensorSupply2
					3	SensorSupply3
					4	SensorSupply4
					5	SensorSupply5
					6	SensorSupply6
					7	SensorSupply7
					8	ExternalSensorSupply
		Failsafe_InputDelay	UInt64	Input delay		
					1	Value0dot4ms
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6BA00-0CA0 - V1.0						
					10	Value10ms
					12	Value12dot8ms
					20	Value20ms
		Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
					0	Deactivated
					1	Active
		Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
		Failsafe_MonitoringWindow	UInt64	Monitoring window		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0
					1	SensorSupply1
					2	SensorSupply2
					3	SensorSupply3
					4	SensorSupply4
					5	SensorSupply5
					6	SensorSupply6
					7	SensorSupply7
					8	ExternalSensorSupply
		Failsafe_InputDelay	UInt64	Input delay		
					1	Value0dot4ms
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					10	Value10ms
					12	Value12dot8ms
					20	Value20ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6BA00-0CA0 - V1.0						
		Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
					0	Deactivated
					1	Active
		Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
		Failsafe_MonitoringWindow	UInt64	Monitoring window		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0
					1	SensorSupply1
					2	SensorSupply2
					3	SensorSupply3
					4	SensorSupply4
					5	SensorSupply5
					6	SensorSupply6
					7	SensorSupply7
					8	ExternalSensorSupply
		Failsafe_InputDelay	UInt64	Input delay		
					1	Value0dot4ms
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					10	Value10ms
					12	Value12dot8ms
					20	Value20ms
		Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6BA00-0CA0 - V1.0						
		Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
		Failsafe_MonitoringWindow	UInt64	Monitoring window		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0
					1	SensorSupply1
					2	SensorSupply2
					3	SensorSupply3
					4	SensorSupply4
					5	SensorSupply5
					6	SensorSupply6
					7	SensorSupply7
					8	ExternalSensorSupply
		Failsafe_InputDelay	UInt64	Input delay		
					1	Value0dot4ms
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					10	Value10ms
					12	Value12dot8ms
					20	Value20ms
		Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
					0	Deactivated
					1	Active
		Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
		Failsafe_MonitoringWindow	UInt64	Monitoring window		
	Channel 4					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6BA00-0CA0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0
					1	SensorSupply1
					2	SensorSupply2
					3	SensorSupply3
					4	SensorSupply4
					5	SensorSupply5
					6	SensorSupply6
					7	SensorSupply7
					8	ExternalSensorSupply
		Failsafe_InputDelay	UInt64	Input delay		
					1	Value0dot4ms
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					10	Value10ms
					12	Value12dot8ms
					20	Value20ms
		Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
					0	Deactivated
					1	Active
		Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
		Failsafe_MonitoringWindow	UInt64	Monitoring window		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6BA00-0CA0 - V1.0						
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0
					1	SensorSupply1
					2	SensorSupply2
					3	SensorSupply3
					4	SensorSupply4
					5	SensorSupply5
					6	SensorSupply6
					7	SensorSupply7
					8	ExternalSensorSupply
		Failsafe_InputDelay	UInt64	Input delay		
					1	Value0dot4ms
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					10	Value10ms
					12	Value12dot8ms
					20	Value20ms
		Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
					0	Deactivated
					1	Active
		Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
		Failsafe_MonitoringWindow	UInt64	Monitoring window		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6BA00-0CA0 - V1.0						
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0
					1	SensorSupply1
					2	SensorSupply2
					3	SensorSupply3
					4	SensorSupply4
					5	SensorSupply5
					6	SensorSupply6
					7	SensorSupply7
					8	ExternalSensorSupply
		Failsafe_InputDelay	UInt64	Input delay		
					1	Value0dot4ms
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					10	Value10ms
					12	Value12dot8ms
					20	Value20ms
		Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
					0	Deactivated
					1	Active
		Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
		Failsafe_MonitoringWindow	UInt64	Monitoring window		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_SensorSupply	UInt64	Sensor supply		
					0	SensorSupply0
					1	SensorSupply1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6BA00-0CA0 - V1.0						
					2	SensorSupply2
					3	SensorSupply3
					4	SensorSupply4
					5	SensorSupply5
					6	SensorSupply6
					7	SensorSupply7
					8	ExternalSensorSupply
		Failsafe_InputDelay	UInt64	Input delay		
					1	Value0dot4ms
					2	Value0dot8ms
					3	Value1dot6ms
					4	Value3dot2ms
					6	Value6dot4ms
					10	Value10ms
					12	Value12dot8ms
					20	Value20ms
		Failsafe_ChatterMonitoring	Boolean	Chatter monitoring		
					0	Deactivated
					1	Active
		Failsafe_NumberOfSignalChanges	UInt64	Number of signal changes		
		Failsafe_MonitoringWindow	UInt64	Monitoring window		
Module - 6ES7 136-6DB00-0CA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		Author	String	Author		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		FirmwareVersion	String	Firmware version		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6DB00-0CA0 - V1.0						
		TypeName	String	InvariantTypeName		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Failsafe_MaximumTestPeriod	UInt64	Maximum test period		
					0	Value100sec
					1	Value1000sec
		Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
		Failsafe_FParameterSignatureWithoutAddresses	UInt64	F-parameter signature (without addresses)		
		Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
					0	Automatic
					1	Manual
		Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
		Failsafe_FIODBName	String	F-I/O DB-name		
		Failsafe_FSourceAddress	UInt64	F-source address		
		Failsafe_FMonitoringtime	UInt64	F-monitoring time		
		Failsafe_FDestinationAddress	UInt64	F-destination address		
		Failsafe_BehaviorAfterChannelFault	UInt64	Behavior after channel fault		
					1	PassivateChannel
					0	PassivateTheEntireModule
		Failsafe_FParameterSignatureWithAddresses	UInt64	F-parameter signature (with addresses)		
		Failsafe_FPassivation	UInt64	RIOforFA safety		
		Failsafe_FParVersion	UInt64	PROFIsafe mode		
					0	V1mode
					1	V2mode

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6DB00-0CA0 - V1.0						
		Failsafe_FCRCSeed	UInt64	PROFIsafe protocol version		
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time dark test		
		Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		
		Failsafe_ActivatedLightTest	Boolean	Activated light test		
					0	Deactivated
					1	Active
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		Failsafe_Activated	Boolean	Activated		
					0	Deactivated
					1	Active
		Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time dark test		
		Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		
		Failsafe_ActivatedLightTest	Boolean	Activated light test		
					0	Deactivated
					1	Active
		Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
					0	Deactivated
					1	Active
	Channel 2					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6DB00-0CA0 - V1.0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Failsafe_Activated	Boolean	Activated		
				0	Deactivated
				1	Active
	Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time dark test		
	Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		
	Failsafe_ActivatedLightTest	Boolean	Activated light test		
				0	Deactivated
				1	Active
	Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
				0	Deactivated
				1	Active
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Failsafe_Activated	Boolean	Activated		
				0	Deactivated
				1	Active
	Failsafe_MaxReadbackTimeDarkTest	Double	Max. readback time dark test		
	Failsafe_MaxReadbackTimeSwitchOnTest	Double	Max. readback time switch on test		
	Failsafe_ActivatedLightTest	Boolean	Activated light test		
				0	Deactivated
				1	Active
	Failsafe_DiagnosisWireBreak	Boolean	Diagnosis: Wire break		
				0	Deactivated
				1	Active
Module - 6ES7 136-6RA00-0BF0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	BaseUnit	String			
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 136-6RA00-0BF0 - V1.0						
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		FirmwareVersion	String	Firmware version		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		TypeName	String	InvariantTypeName		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		Name	String	Name		
		Comment	String	Comment		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES714x-xxxxx-0AA0					
	Author	String	Author		
	Name	String	Name		
	TypeName	String	InvariantTypeName		
	PositionNumber	Int32	Index		
Module - 6ES7 193-6AS00-0AA0 - V0.0					
	SharedDeviceAccessConfigured	Boolean			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	Name	String	Name		
	Comment	String	Comment		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String	Name		
	PositionNumber	Int32	Index		
Module - 3RK1 908-1CA00-0BP0					
	SharedDeviceAccessConfigured	Boolean			
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	Name	String	Name		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3RK1 908-1CA00-0BP0					
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Module - 6ES7 133-6CV15-1AM0					
	SharedDeviceAccessConfigured	Boolean			
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	PositionNumber	Int32	Index		
	Name	String	Name		
	Comment	String	Comment		
Module - 6ES7 133-6CV20-1AM0					
	SharedDeviceAccessConfigured	Boolean			
	PotentialGroup	UInt64	Potential group		
				0	DarkBaseUnit
				1	LightBaseUnit
	TypeName	String	InvariantTypeName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 133-6CV20-1AM0						
		Author	String	Author		
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		PositionNumber	Int32	Index		
		Name	String	Name		
		Comment	String	Comment		
Module - 6ES7 193-6TP00-0TN0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
Module - 6ES7 193-6TP00-0TP0						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 193-6TP00-0TP0						
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
Module - 6ES7 193-6TP00-0TP1						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
Module - 6ES7 193-6TP00-0TP2						
		SharedDeviceAccessConfigured	Boolean			
		BaseUnit	String			
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		PotentialGroup	UInt64	Potential group		
					0	DarkBaseUnit
					1	LightBaseUnit
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 193-6PA00-0AA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	Name	String	Name		
	Comment	String	Comment		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	DiagnosticsNoSupplyVoltage	Boolean	Group diagnostics: Missing supply voltage L+		
	VoltageState	UInt64	Status of voltages		
				0	NoStatusAvailable
				1	StatusOfSupplyVoltageLPlus
				2	StatusOfSupplyVoltageLPlusAndFeedbackVoltage
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	Index		
Module - 6ES7 193-6PA00-0AA0 - V1.1					
	SharedDeviceAccessConfigured	Boolean			
	TypeName	String	InvariantTypeName		
	Author	String	Author		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 193-6PA00-0AA0 - V1.1						
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		Name	String	Name		
		Comment	String	Comment		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		DiagnosticsNoSupplyVoltage	Boolean	Group diagnostics: Missing supply voltage L+		
		VoltageState	UInt64	Status of voltages		
					0	NoStatusAvailable
					1	StatusOfSupplyVoltageLPlus
					2	StatusOfSupplyVoltageLPlusAndFeedbackVoltage
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
Module						
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 7MH4 138-6AA00-0BA0					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	TypeName	String	InvariantTypeName		
	PotentialGroup	UInt64			
				0	DarkBaseUnit
				1	LightBaseUnit
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
	TypeName	String	InvariantTypeName		
	DiagnosticsInterrupt	Boolean	Diagnostics interrupt		
	HardwareInterrupt	Boolean	Hardware interrupt		
	HardwareInterruptHighLimit1Active	Boolean	HwInterruptActivated_x		
				1	Active
				0	Deactivated
	HardwareInterruptLowLimit1Active	Boolean	HwInterruptActivated_x		
				0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 7MH4 138-6AA00-0BA0						
					1	Active
		HardwareInterruptHighLimit2Active	Boolean	HwInterruptActivated_x		
					0	Deactivated
					1	Active
		HardwareInterruptLowLimit2Active	Boolean	HwInterruptActivated_x		
					0	Deactivated
					1	Active
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptForSiwarexHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptForSiwarexHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptForSiwarexHighLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptForSiwarexHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptForSiwarexHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptForSiwarexHighLimit2Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptForSiwarexLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptForSiwarexLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptForSiwarexLowLimit1Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptForSiwarexLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptForSiwarexLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptForSiwarexLowLimit2Priority		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 147-5JD00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage 2L+		
					1	Active
					0	Deactivated
		DiagnosticsPort1	Boolean	Port 1		
					1	Active
					0	Deactivated
		DiagnosticsPort2	Boolean	Port 2		
					1	Active
					0	Deactivated
		DiagnosticsPort3	Boolean	Port 3		
					1	Active
					0	Deactivated

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 147-5JD00-0BA0 - V1.0						
		DiagnosticsPort4	Boolean	Port 4		
					1	Active
					0	Deactivated
		InputOrOutputType	UInt64	Input/output type - Input/output		
					1	Value1
					2	Value2
					8	Value8
					16	Value16
					32	Value32
					152	Value4
		PositionNumber	Int32	Index		
Module - 6ES7 147-5JD00-0BA0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage 2L+		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 147-5JD00-0BA0 - V1.1						
		DiagnosticsPort1	Boolean	Port 1		
		DiagnosticsPort2	Boolean	Port 2		
		DiagnosticsPort3	Boolean	Port 3		
		DiagnosticsPort4	Boolean	Port 4		
		PositionNumber	Int32	Index		
		InputOrOutputType	UInt64			
					149	Value8And0
					148	Value8And8
					12	Value12And8
					145	Value16And16
					20	Value20And16
					147	Value32And32
					4	Value4And4
		PortModePort1	UInt64	Operating mode		
					7	Deactivated
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di
					4	Dq
		InputDataLengthPort1	UInt64	Input data length (without PQI)		
		OutputDataLengthPort1	UInt64	Output data length		
		VendorIdPort1	UInt64	Vendor ID		
		DeviceIdPort1	UInt64	Device ID		
		PortModePort2	UInt64	Operating mode		
					7	Deactivated
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di
					4	Dq
		InputDataLengthPort2	UInt64	Input data length (without PQI)		
		OutputDataLengthPort2	UInt64	Output data length		
		VendorIdPort2	UInt64	Vendor ID		
		DeviceIdPort2	UInt64	Device ID		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 147-5JD00-0BA0 - V1.1						
		PortModePort3	UInt64	Operating mode		
					7	Deactivated
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di
					4	Dq
		InputDataLengthPort3	UInt64	Input data length (without PQI)		
		OutputDataLengthPort3	UInt64	Output data length		
		VendorIdPort3	UInt64	Vendor ID		
		DeviceIdPort3	UInt64	Device ID		
		PortModePort4	UInt64	Operating mode		
					7	Deactivated
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di
					4	Dq
		InputDataLengthPort4	UInt64	Input data length (without PQI)		
		OutputDataLengthPort4	UInt64	Output data length		
		VendorIdPort4	UInt64	Vendor ID		
		DeviceIdPort4	UInt64	Device ID		
		PortQualifierInformation	Boolean	Port Qualifier Information (PQI)		
		ConfigurationWithoutS7PCT	Boolean	Configuration without S7-PCT		
		InspectionOrBackupLevelPort1	UInt64	Inspection / backup level		
					5	TypeCompatibleV1Dot1WithBackupandRestore
					7	TypeCompatibleV1Dot1WithRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupandRestore
		InspectionOrBackupLevelPort2	UInt64	Inspection / backup level		
					5	TypeCompatibleV1Dot1WithBackupandRestore
					7	TypeCompatibleV1Dot1WithRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupandRestore

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 147-5JD00-0BA0 - V1.1						
		InspectionOrBackupLevelPort3	UInt64	Inspection / backup level		
					5	TypeCompatibleV1Dot1WithBackupandRestore
					7	TypeCompatibleV1Dot1WithRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupandRestore
		InspectionOrBackupLevelPort4	UInt64	Inspection / backup level		
					5	TypeCompatibleV1Dot1WithBackupandRestore
					7	TypeCompatibleV1Dot1WithRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupandRestore
Module - ET-Con Sub-Receiver - 1.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		OrderNumber	String	Article number		
		ShortDesignation	String	Short designation		
Module - ET-Con Sub-Receiver						
		Name	String	Name		
Module - 6ES7 144-5KD00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					3	Current4WireTransducer

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0						
					4	Current2WireTransducer
					6	Resistor3Wire
					7	Resistor2Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
		OperatingRange	UInt64	Measuring range		
					10	Value1To5V
					52	Value0To10V
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					31	Value150Ohm
					32	Value300Ohm
					0	Deactivated
					15	Value0To20mA
					16	Value4To20mA
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					0	Deactivated
					7	Ni0Dot006180
					8	Ni0Dot006720
					4	Pt0Dot003851
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
					4	Deactivated
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					6	Value3600

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0						
					1	Value60
					0	Value50
					10	Value16Dot6
					3	None
		EnableValueStatus	Boolean	Value status		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		TemperatureUnit	UInt64	Temperature unit		
					1	DegreesCelsius
					2	DegreesFahrenheit
					3	Kelvin
		PositionNumber	Int32	Index		
	Channel 0					
		ParameterSettings	UInt64	Channel template		
					1	FromTemplate
					0	Manual
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0						
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					3	Current4WireTransducer
					4	Current2WireTransducer
					6	Resistor3Wire
					7	Resistor2Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
		OperatingRange	UInt64	Measuring range		
					10	Value1To5V
					52	Value0To10V
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					31	Value150Ohm
					32	Value300Ohm
					0	Deactivated
					15	Value0To20mA
					16	Value4To20mA
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					0	Deactivated
					7	Ni0Dot006180
					8	Ni0Dot006720
					4	Pt0Dot003851
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0						
					2	Medium
					3	Strong
					4	Deactivated
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					6	Value3600
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0						
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 1					
		ParameterSettings	UInt64	Channel template		
					1	FromTemplate
					0	Manual
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					3	Current4WireTransducer
					4	Current2WireTransducer
					6	Resistor3Wire
					7	Resistor2Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
		OperatingRange	UInt64	Measuring range		
					10	Value1To5V
					52	Value0To10V
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					31	Value150Ohm
					32	Value300Ohm
					0	Deactivated
					15	Value0To20mA
					16	Value4To20mA

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0						
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					0	Deactivated
					7	Ni0Dot006180
					8	Ni0Dot006720
					4	Pt0Dot003851
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
					4	Deactivated
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					6	Value3600
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0					
				0	Deactivated
	HardwareInterruptLowLimit2Value	Double	Low limit 2		
	ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
	HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
	HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
	HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
	HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
	HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
	HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
	HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
	HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
	HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
	HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
	HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
	HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
Channel 2					
	ParameterSettings	UInt64	Channel template		
				1	FromTemplate
				0	Manual
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Measurement type		
				0	Deactivated
				1	Voltage
				3	Current4WireTransducer
				4	Current2WireTransducer
				6	Resistor3Wire
				7	Resistor2Wire
				9	ThermalResistor3Wire
				25	ThermalResistor2Wire

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0						
		OperatingRange	UInt64	Measuring range		
					10	Value1To5V
					52	Value0To10V
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					31	Value150Ohm
					32	Value300Ohm
					0	Deactivated
					15	Value0To20mA
					16	Value4To20mA
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					0	Deactivated
					7	Ni0Dot006180
					8	Ni0Dot006720
					4	Pt0Dot003851
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
		Smoothing	UInt64	Smoothing		
					0	None
					1	Weak
					2	Medium
					3	Strong
					4	Deactivated
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					6	Value3600
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0						
					0	Deactivated
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
	Channel 3					
		ParameterSettings	UInt64	Channel template		
					1	FromTemplate
					0	Manual
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0						
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Measurement type		
					0	Deactivated
					1	Voltage
					3	Current4WireTransducer
					4	Current2WireTransducer
					6	Resistor3Wire
					7	Resistor2Wire
					9	ThermalResistor3Wire
					25	ThermalResistor2Wire
		OperatingRange	UInt64	Measuring range		
					10	Value1To5V
					52	Value0To10V
					40	Pt100ClimaticRange
					44	Ni100ClimaticRange
					46	Pt100StandardRange
					50	Ni100StandardRange
					31	Value150Ohm
					32	Value300Ohm
					0	Deactivated
					15	Value0To20mA
					16	Value4To20mA
		MeasuringTemperatureCoefficient	UInt64	Temperature coefficient		
					0	Deactivated
					7	Ni0Dot006180
					8	Ni0Dot006720
					4	Pt0Dot003851
					1	Pt0Dot003916
					2	Pt0Dot003902
					3	Pt0Dot003920
					9	Pt0Dot003850
		Smoothing	UInt64	Smoothing		
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0						
					1	Weak
					2	Medium
					3	Strong
					4	Deactivated
		InterferenceFrequencySuppression	UInt64	Interference frequency suppression		
					6	Value3600
					1	Value60
					0	Value50
					10	Value16Dot6
		HardwareInterruptHighLimit1Active	Boolean	Hardware interrupt high limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit1Value	Double	High limit 1		
		HardwareInterruptLowLimit1Active	Boolean	Hardware interrupt low limit 1		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit1Value	Double	Low limit 1		
		HardwareInterruptHighLimit2Active	Boolean	Hardware interrupt high limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptHighLimit2Value	Double	High limit 2		
		HardwareInterruptLowLimit2Active	Boolean	Hardware interrupt low limit 2		
					1	Active
					0	Deactivated
		HardwareInterruptLowLimit2Value	Double	Low limit 2		
		ChannelAddress	Int64	*GetChannelAddressForAnalogInput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogInput()		
		HardwareInterruptHighLimit1EventName	String	*HardwareInterruptHighLimit1EventName		
		HardwareInterruptHighLimit1Interrupt	Object	*HardwareInterruptHighLimit1Interrupt		
		HardwareInterruptHighLimit1Priority	UInt64	*HardwareInterruptHighLimit1Priority		
		HardwareInterruptLowLimit1EventName	String	*HardwareInterruptLowLimit1EventName		
		HardwareInterruptLowLimit1Interrupt	Object	*HardwareInterruptLowLimit1Interrupt		
		HardwareInterruptLowLimit1Priority	UInt64	*HardwareInterruptLowLimit1Priority		
		HardwareInterruptHighLimit2EventName	String	*HardwareInterruptHighLimit2EventName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 144-5KD00-0BA0 - V1.0						
		HardwareInterruptHighLimit2Interrupt	Object	*HardwareInterruptHighLimit2Interrupt		
		HardwareInterruptHighLimit2Priority	UInt64	*HardwareInterruptHighLimit2Priority		
		HardwareInterruptLowLimit2EventName	String	*HardwareInterruptLowLimit2EventName		
		HardwareInterruptLowLimit2Interrupt	Object	*HardwareInterruptLowLimit2Interrupt		
		HardwareInterruptLowLimit2Priority	UInt64	*HardwareInterruptLowLimit2Priority		
Module - 6ES7 145-5ND00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		EnableValueStatus	Boolean	Value status		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		TypeName	String	InvariantTypeName		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					0	Deactivated
					11	PlusMinus10V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		SubstituteValueAnalog	Double	Substitute value		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0					
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				2	SubstituteAValue
				12	Deactivated
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit of actuator supply to ground		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	ParameterSettings	UInt64	Channel template		
				1	FromTemplate
				0	Manual
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current
	OperatingRange	UInt64	Output range		
				0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0						
					11	PlusMinus10V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
					12	Deactivated
		SubstituteValueAnalog	Double	Substitute value		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		ParameterSettings	UInt64	Channel template		
					1	FromTemplate
					0	Manual
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					0	Deactivated
					11	PlusMinus10V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0						
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
					12	Deactivated
		SubstituteValueAnalog	Double	Substitute value		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		ParameterSettings	UInt64	Channel template		
					1	FromTemplate
					0	Manual
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					0	Deactivated
					11	PlusMinus10V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
					12	Deactivated
		SubstituteValueAnalog	Double	Substitute value		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0					
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	ParameterSettings	UInt64	Channel template		
				1	FromTemplate
				0	Manual
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current
	OperatingRange	UInt64	Output range		
				0	Deactivated
				11	PlusMinus10V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				2	SubstituteAValue
				12	Deactivated
	SubstituteValueAnalog	Double	Substitute value		
Module - 6ES7 145-5ND00-0BA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	EnableValueStatus	Boolean	Value status		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0						
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					0	Deactivated
					11	PlusMinus10V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		SubstituteValueAnalog	Double	Substitute value		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
					12	Deactivated
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0					
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit of actuator supply to ground		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	ParameterSettings	UInt64	Channel template		
				1	FromTemplate
				0	Manual
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current
	OperatingRange	UInt64	Output range		
				0	Deactivated
				11	PlusMinus10V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				2	SubstituteAValue
				12	Deactivated
	SubstituteValueAnalog	Double	Substitute value		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0					
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	ParameterSettings	UInt64	Channel template		
				1	FromTemplate
				0	Manual
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	DiagnosticsOverflow	Boolean	Overflow		
	DiagnosticsUnderflow	Boolean	Underflow		
	DiagnosticsWireBreak	Boolean	Wire break		
	OperatingType	UInt64	Output type		
				0	Deactivated
				1	Voltage
				2	Current
	OperatingRange	UInt64	Output range		
				0	Deactivated
				11	PlusMinus10V
				52	Value0To10V
				10	Value1To5V
				17	PlusMinus20mA
				15	Value0To20mA
				16	Value4To20mA
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				2	SubstituteAValue
				12	Deactivated
	SubstituteValueAnalog	Double	Substitute value		
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
	ParameterSettings	UInt64	Channel template		
				1	FromTemplate
				0	Manual

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0						
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					0	Deactivated
					11	PlusMinus10V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
					12	Deactivated
		SubstituteValueAnalog	Double	Substitute value		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		ParameterSettings	UInt64	Channel template		
					1	FromTemplate
					0	Manual
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Output type		
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0						
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					0	Deactivated
					11	PlusMinus10V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
					12	Deactivated
		SubstituteValueAnalog	Double	Substitute value		
Module - 6ES7 145-5ND00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		EnableValueStatus	Boolean	Value status		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					0	Deactivated
					11	PlusMinus10V

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0						
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		SubstituteValueAnalog	Double	Substitute value		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
					12	Deactivated
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit of actuator supply to ground		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		ParameterSettings	UInt64	Channel template		
					1	FromTemplate
					0	Manual

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0						
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					0	Deactivated
					11	PlusMinus10V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
					12	Deactivated
		SubstituteValueAnalog	Double	Substitute value		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		ParameterSettings	UInt64	Channel template		
					1	FromTemplate
					0	Manual
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Output type		
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0						
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					0	Deactivated
					11	PlusMinus10V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
					12	Deactivated
		SubstituteValueAnalog	Double	Substitute value		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		ParameterSettings	UInt64	Channel template		
					1	FromTemplate
					0	Manual
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					0	Deactivated
					11	PlusMinus10V
					52	Value0To10V

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0						
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
					12	Deactivated
		SubstituteValueAnalog	Double	Substitute value		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForAnalogOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForAnalogOutput()		
		ParameterSettings	UInt64	Channel template		
					1	FromTemplate
					0	Manual
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		DiagnosticsOverflow	Boolean	Overflow		
		DiagnosticsUnderflow	Boolean	Underflow		
		DiagnosticsWireBreak	Boolean	Wire break		
		OperatingType	UInt64	Output type		
					0	Deactivated
					1	Voltage
					2	Current
		OperatingRange	UInt64	Output range		
					0	Deactivated
					11	PlusMinus10V
					52	Value0To10V
					10	Value1To5V
					17	PlusMinus20mA
					15	Value0To20mA
					16	Value4To20mA
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 145-5ND00-0BA0 - V1.0					
				1	KeepLastValue
				2	SubstituteAValue
				12	Deactivated
	SubstituteValueAnalog	Double	Substitute value		
Module - 6ES7 141-5AF00-0BA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	EnableValueStatus	Boolean	Value status		
	ShortDesignation	String	Short designation		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	TypeName	String	InvariantTypeName		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	ReactionToError	UInt64	Input values with module failure		
				2	SubstituteValue0
				1	KeepLastValue
	PositionNumber	Int32	Index		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 141-5AF00-0BA0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 6					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Module - 6ES7 141-5AH00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		EnableValueStatus	Boolean	Value status		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		TypeName	String	InvariantTypeName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 141-5AH00-0BA0 - V1.0						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 4					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 141-5AH00-0BA0 - V1.0					
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 8					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 9					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 10					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Module - 6ES7 141-5BF00-0BA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 141-5BF00-0BA0 - V1.0						
		Name	String	Name		
		EnableValueStatus	Boolean	Value status		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 3					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 141-5BF00-0BA0 - V1.0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 4					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 5					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 6					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Module - 6ES7 143-5AF00-0BA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	EnableValueStatus	Boolean	Value status		
	ShortDesignation	String	Short designation		
	StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
				0	FromCpu
				1	StartupCpuOnlyIfCompatible
				2	StartupCpuIfMismatch
	TypeName	String	InvariantTypeName		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
Submodule					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AF00-0BA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	Comment	String	Comment		
	Name	String	Name		
	DiagnosticsNoSupplyVoltage	Boolean	No supply voltage 2L+		
	DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP		
				6	Shutdown
				1	KeepLastValue
				2	SubstituteAValue
	ReactionToError	UInt64	Input values with module failure		
				2	SubstituteValue0
				1	KeepLastValue
	PositionNumber	Int32	Index		
Channel 0					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelTypeForIO	UInt64	Channel type for I/O		
				0	DigitalInput
				1	DigitalOutput
Channel 1					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelTypeForIO	UInt64	Channel type for I/O		
				0	DigitalInput
				1	DigitalOutput
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelTypeForIO	UInt64	Channel type for I/O		
				0	DigitalInput
				1	DigitalOutput
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AF00-0BA0 - V1.0						
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 5					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AF00-0BA0 - V1.0						
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		EnableValueStatus	Boolean	Value status		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		TypeName	String	InvariantTypeName		
		EnableCounterSelection	Boolean	Enable counter selection		
		CounterConfiguration	UInt64	Counter configuration		
					1	Value2Counters
					2	Value4Counters
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage 2L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		PositionNumber	Int32	Index		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP with DQ		
					6	Shutdown
					1	KeepLastValue
					16	OutputSubstituteValue
	Channel 0					
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		OperatingMode	UInt64	Operating mode		
					23	Counting

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					281	Deactivated
		SetOutputDQ1	UInt64	Set output DQ1		
					10	BetweenComparisonValueAndHighCounterValue
					11	BetweenComparisonValueAndLowCounterValue
		ReactionToCpuStopforDQ1	UInt64			
					4	Continue
					2	SubstituteValue
		SubstituteValueDQ1	UInt64			
					0	Value0
					1	Value1
		BehaviorOfDI4	UInt64	Behavior of DI4		
					0	DigitalInputWithoutFunction
					1	GateStartOrStopLevelTriggered
		InputDelayDI4	UInt64	Input delay		
					0	Value0dot05ms
					1	Value0dot1ms
					2	Value0dot4ms
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms
					7	Value20dot0ms
		BehaviorOfDI5	UInt64	Behavior of DI5		
					0	DigitalInputWithoutFunction
					1	CountDirection
		InputDelayDI5	UInt64	Input delay		
					0	Value0dot05ms
					1	Value0dot1ms
					2	Value0dot4ms
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					7	Value20dot0ms
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		CountDirection	UInt64	Count direction:		
					3	Forward
					2	Backward
		ComparisonValue	Int64	Comparison value		
		CountingLowLimit	Int64	Low counting limit		
		HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
					1	Active
					0	Deactivated
		HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
		HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
		HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 2					
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		OperatingMode	UInt64	Operating mode		
					23	Counting
					281	Deactivated
		SetOutputDQ1	UInt64	Set output DQ3		
					10	BetweenComparisonValueAndHighCounterValue
					11	BetweenComparisonValueAndLowCounterValue
		ReactionToCpuStopforDQ1	UInt64			
					4	Continue
					2	SubstituteValue
		SubstituteValueDQ1	UInt64			
					0	Value0
					1	Value1
		BehaviorOfDI6	UInt64	Behavior of DI6		
					0	DigitalInputWithoutFunction
					1	GateStartOrStopLevelTriggered

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		InputDelayDI6	UInt64	Input delay		
					0	Value0dot05ms
					1	Value0dot1ms
					2	Value0dot4ms
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms
					7	Value20dot0ms
		BehaviorOfDI7	UInt64	Behavior of DI7		
					0	DigitalInputWithoutFunction
					1	CountDirection
		InputDelayDI7	UInt64	Input delay		
					0	Value0dot05ms
					1	Value0dot1ms
					2	Value0dot4ms
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms
					7	Value20dot0ms
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		CountDirection	UInt64	Count direction:		
					3	Forward
					2	Backward
		ComparisonValue	Int64	Comparison value		
		CountingLowLimit	Int64	Low counting limit		
		HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
					0	Deactivated
					1	Active
		HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
		HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
		HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 4					
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		OperatingMode	UInt64	Operating mode		
					23	Counting
					281	Deactivated
		SetOutputDQ1	UInt64	Set output DQ5		
					10	BetweenComparisonValueAndHighCounterValue
					11	BetweenComparisonValueAndLowCounterValue
		ReactionToCpuStopforDQ1	UInt64			
					4	Continue
					2	SubstituteValue
		SubstituteValueDQ1	UInt64			
					0	Value0
					1	Value1
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		CountDirection	UInt64	Count direction:		
					3	Forward
					2	Backward
		ComparisonValue	Int64	Comparison value		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0					
	CountingLowLimit	Int64	Low counting limit		
	HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
				0	Deactivated
				1	Active
	HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
	HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
	HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
Channel 5					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelTypeForIO	UInt64	Channel type for I/O		
				0	DigitalInput
				1	DigitalOutput
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
Channel 6					
	ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
				0	StopCounting
				1	ContinueCounting
	EdgeSelection	UInt64	Edge selection		
				0	AtRisingEdge
				1	AtFallingEdge
	CountingHighLimit	Int64	High counting limit		
	CountingStartValue	Int64	Start value		
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		OperatingMode	UInt64	Operating mode		
					23	Counting
					281	Deactivated
		SetOutputDQ1	UInt64	Set output DQ7		
					10	BetweenComparisonValueAndHighCounterValue
					11	BetweenComparisonValueAndLowCounterValue
		ReactionToCpuStopforDQ1	UInt64			
					4	Continue
					2	SubstituteValue
		SubstituteValueDQ1	UInt64			
					0	Value0
					1	Value1
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		CountDirection	UInt64	Count direction:		
					3	Forward
					2	Backward
		ComparisonValue	Int64	Comparison value		
		CountingLowLimit	Int64	Low counting limit		
		HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
					0	Deactivated
					1	Active

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
		HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
		HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					15	None
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 11					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					1	Value1
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 15					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		EnableValueStatus	Boolean	Value status		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		EnableCounterSelection	Boolean	Enable counter selection		
		CounterConfiguration	UInt64	Counter configuration		
					1	Value2Counters
					2	Value4Counters
					0	None
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage 2L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0					
	ReactionToError	UInt64	Input values with module failure		
				2	SubstituteValue0
				1	KeepLastValue
	PositionNumber	Int32	Index		
	ReactionToCpuStop	UInt64	Reaction to CPU STOP with DQ		
				6	Shutdown
				1	KeepLastValue
				16	OutputSubstituteValue
Channel 0					
	ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
				0	StopCounting
				1	ContinueCounting
	EdgeSelection	UInt64	Edge selection		
				0	AtRisingEdge
				1	AtFallingEdge
	CountingHighLimit	Int64	High counting limit		
	CountingStartValue	Int64	Start value		
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	OperatingMode	UInt64	Operating mode		
				23	Counting
				281	Deactivated
	SetOutputDQ1	UInt64	Set output DQ1		
				10	BetweenComparisonValueAndHighCounterValue
				11	BetweenComparisonValueAndLowCounterValue
	ReactionToCpuStopforDQ1	UInt64			
				4	Continue
				2	SubstituteValue
	SubstituteValueDQ1	UInt64			
				0	Value0
				1	Value1
	BehaviorOfDI4	UInt64	Behavior of DI4		
				0	DigitalInputWithoutFunction

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					1	GateStartOrStopLevelTriggered
		InputDelayDI4	UInt64	Input delay		
					0	Value0dot05ms
					1	Value0dot1ms
					2	Value0dot4ms
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms
					7	Value20dot0ms
		BehaviorOfDI5	UInt64	Behavior of DI5		
					0	DigitalInputWithoutFunction
					1	CountDirection
		InputDelayDI5	UInt64	Input delay		
					0	Value0dot05ms
					1	Value0dot1ms
					2	Value0dot4ms
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms
					7	Value20dot0ms
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					15	None
		CountDirection	UInt64	Count direction:		
					3	Forward
					2	Backward
		ComparisonValue	Int64	Comparison value		
		CountingLowLimit	Int64	Low counting limit		
		HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
					1	Active
					0	Deactivated
		HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
		HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
		HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 2					
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					1	AtFallingEdge
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		OperatingMode	UInt64	Operating mode		
					23	Counting
					281	Deactivated
		SetOutputDQ1	UInt64	Set output DQ3		
					10	BetweenComparisonValueAndHighCounterValue
					11	BetweenComparisonValueAndLowCounterValue
		ReactionToCpuStopforDQ1	UInt64			
					4	Continue
					2	SubstituteValue
		SubstituteValueDQ1	UInt64			
					0	Value0
					1	Value1
		BehaviorOfDI6	UInt64	Behavior of DI6		
					0	DigitalInputWithoutFunction
					1	GateStartOrStopLevelTriggered
		InputDelayDI6	UInt64	Input delay		
					0	Value0dot05ms
					1	Value0dot1ms
					2	Value0dot4ms
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms
					7	Value20dot0ms
		BehaviorOfDI7	UInt64	Behavior of DI7		
					0	DigitalInputWithoutFunction
					1	CountDirection

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		InputDelayDI7	UInt64	Input delay		
					0	Value0dot05ms
					1	Value0dot1ms
					2	Value0dot4ms
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms
					7	Value20dot0ms
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		CountDirection	UInt64	Count direction:		
					3	Forward
					2	Backward
		ComparisonValue	Int64	Comparison value		
		CountingLowLimit	Int64	Low counting limit		
		HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
					0	Deactivated
					1	Active
		HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
		HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
		HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
	Channel 3					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 4					
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		OperatingMode	UInt64	Operating mode		
					23	Counting
					281	Deactivated
		SetOutputDQ1	UInt64	Set output DQ5		
					10	BetweenComparisonValueAndHighCounterValue
					11	BetweenComparisonValueAndLowCounterValue

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		ReactionToCpuStopforDQ1	UInt64			
					4	Continue
					2	SubstituteValue
		SubstituteValueDQ1	UInt64			
					0	Value0
					1	Value1
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		CountDirection	UInt64	Count direction:		
					3	Forward
					2	Backward
		ComparisonValue	Int64	Comparison value		
		CountingLowLimit	Int64	Low counting limit		
		HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
					0	Deactivated
					1	Active
		HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
		HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
		HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 6					
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		OperatingMode	UInt64	Operating mode		
					23	Counting
					281	Deactivated
		SetOutputDQ1	UInt64	Set output DQ7		
					10	BetweenComparisonValueAndHighCounterValue
					11	BetweenComparisonValueAndLowCounterValue
		ReactionToCpuStopforDQ1	UInt64			
					4	Continue
					2	SubstituteValue

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		SubstituteValueDQ1	UInt64			
					0	Value0
					1	Value1
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		CountDirection	UInt64	Count direction:		
					3	Forward
					2	Backward
		ComparisonValue	Int64	Comparison value		
		CountingLowLimit	Int64	Low counting limit		
		HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
					0	Deactivated
					1	Active
		HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
		HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
		HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
	Channel 7					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 12					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
					10	Value20ms
					15	None
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.0					
Channel 11					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
Channel 12					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
Channel 13					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
Channel 14					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
Channel 15					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
Module - 6ES7 143-5AH00-0BA0 - V1.1					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
		Name	String	Name		
		EnableValueStatus	Boolean	Value status		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		TypeName	String	InvariantTypeName		
		EnableCounterSelection	Boolean	Enable counter selection		
		CounterConfiguration	UInt64	Counter configuration		
					1	Value2Counters
					2	Value4Counters
					0	None
		PreConfigurationForDIDQ	UInt64	Pre-configuration for DI/DQ		
					0	None
					3	DQ16
					1	FreeParameterization
					2	DI8AndDQ8
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage 2L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
		PositionNumber	Int32	Index		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP with DQ		
					6	Shutdown
					1	KeepLastValue
					16	OutputSubstituteValue
	Channel 0					
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		OperatingMode	UInt64	Operating mode		
					23	Counting
					281	Deactivated
		SetOutputDQ1	UInt64	Set output DQ1		
					10	BetweenComparisonValueAndHighCounterValue
					11	BetweenComparisonValueAndLowCounterValue
		ReactionToCpuStopforDQ1	UInt64			
					4	Continue
					2	SubstituteValue
		SubstituteValueDQ1	UInt64			
					0	Value0
					1	Value1
		BehaviorOfDI4	UInt64	Behavior of DI4		
					0	DigitalInputWithoutFunction
					1	GateStartOrStopLevelTriggered
		InputDelayDI4	UInt64	Input delay		
					0	Value0dot05ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
					1	Value0dot1ms
					2	Value0dot4ms
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms
					7	Value20dot0ms
		BehaviorOfDI5	UInt64	Behavior of DI5		
					0	DigitalInputWithoutFunction
					1	CountDirection
		InputDelayDI5	UInt64	Input delay		
					0	Value0dot05ms
					1	Value0dot1ms
					2	Value0dot4ms
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms
					7	Value20dot0ms
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		CountDirection	UInt64	Count direction:		
					3	Forward

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
					2	Backward
		ComparisonValue	Int64	Comparison value		
		CountingLowLimit	Int64	Low counting limit		
		HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
					1	Active
					0	Deactivated
		HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
		HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
		HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 2					
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		OperatingMode	UInt64	Operating mode		
					23	Counting
					281	Deactivated
		SetOutputDQ1	UInt64	Set output DQ3		
					10	BetweenComparisonValueAndHighCounterValue
					11	BetweenComparisonValueAndLowCounterValue
		ReactionToCpuStopforDQ1	UInt64			
					4	Continue
					2	SubstituteValue
		SubstituteValueDQ1	UInt64			
					0	Value0
					1	Value1
		BehaviorOfDI6	UInt64	Behavior of DI6		
					0	DigitalInputWithoutFunction
					1	GateStartOrStopLevelTriggered
		InputDelayDI6	UInt64	Input delay		
					0	Value0dot05ms
					1	Value0dot1ms
					2	Value0dot4ms
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms
					7	Value20dot0ms
		BehaviorOfDI7	UInt64	Behavior of DI7		
					0	DigitalInputWithoutFunction
					1	CountDirection
		InputDelayDI7	UInt64	Input delay		
					0	Value0dot05ms
					1	Value0dot1ms
					2	Value0dot4ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
					3	Value0dot8ms
					4	Value1dot6ms
					5	Value3dot2ms
					6	Value12dot8ms
					7	Value20dot0ms
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		CountDirection	UInt64	Count direction:		
					3	Forward
					2	Backward
		ComparisonValue	Int64	Comparison value		
		CountingLowLimit	Int64	Low counting limit		
		HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
					0	Deactivated
					1	Active
		HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
		HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
		HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 4					
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		OperatingMode	UInt64	Operating mode		
					23	Counting
					281	Deactivated
		SetOutputDQ1	UInt64	Set output DQ5		
					10	BetweenComparisonValueAndHighCounterValue
					11	BetweenComparisonValueAndLowCounterValue
		ReactionToCpuStopforDQ1	UInt64			
					4	Continue
					2	SubstituteValue
		SubstituteValueDQ1	UInt64			
					0	Value0

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
					1	Value1
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
		CountDirection	UInt64	Count direction:		
					3	Forward
					2	Backward
		ComparisonValue	Int64	Comparison value		
		CountingLowLimit	Int64	Low counting limit		
		HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
					0	Deactivated
					1	Active
		HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
		HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
		HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
	Channel 5					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 6					
		ReactionToCountingLimit	UInt64	Reaction to violation of a counting limit		
					0	StopCounting
					1	ContinueCounting
		EdgeSelection	UInt64	Edge selection		
					0	AtRisingEdge
					1	AtFallingEdge
		CountingHighLimit	Int64	High counting limit		
		CountingStartValue	Int64	Start value		
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		OperatingMode	UInt64	Operating mode		
					23	Counting
					281	Deactivated
		SetOutputDQ1	UInt64	Set output DQ7		
					10	BetweenComparisonValueAndHighCounterValue
					11	BetweenComparisonValueAndLowCounterValue
		ReactionToCpuStopforDQ1	UInt64			
					4	Continue
					2	SubstituteValue
		SubstituteValueDQ1	UInt64			
					0	Value0
					1	Value1
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1					
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms
				9	Value12Dot8ms
				10	Value20ms
				15	None
	CountDirection	UInt64	Count direction:		
				3	Forward
				2	Backward
	ComparisonValue	Int64	Comparison value		
	CountingLowLimit	Int64	Low counting limit		
	HardwareInterruptDQCompareActive	Boolean	Comparison event for DQ has occurred		
				0	Deactivated
				1	Active
	HardwareInterruptDQCompareEventName	String	*HardwareInterruptDQCompareEventName		
	HardwareInterruptDQCompareInterrupt	Object	*HardwareInterruptDQCompareInterrupt		
	HardwareInterruptDQComparePriority	UInt64	*HardwareInterruptDQComparePriority		
Channel 7					
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	ChannelTypeForIO	UInt64	Channel type for I/O		
				0	DigitalInput
				1	DigitalOutput
	InputDelay	UInt64	Input delay		
				0	Value0Dot05ms
				1	Value0Dot1ms
				3	Value0Dot4ms
				4	Value0Dot8ms
				5	Value1Dot6ms
				6	Value3Dot2ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
					15	None
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 12					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		InputDelay	UInt64	Input delay		
					0	Value0Dot05ms
					1	Value0Dot1ms
					3	Value0Dot4ms
					4	Value0Dot8ms
					5	Value1Dot6ms
					6	Value3Dot2ms
					9	Value12Dot8ms
					10	Value20ms
					15	None
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
					1	Value1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 2					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 3					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 4					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 5					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 6					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 7					
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 8					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 9					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 10					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 11					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 12					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5AH00-0BA0 - V1.1						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 13					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 14					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 15					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
Module - 6ES7 143-5BF00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		EnableValueStatus	Boolean	Value status		
		ShortDesignation	String	Short designation		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5BF00-0BA0 - V1.0						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage 2L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
		ReactionToError	UInt64	Input values with module failure		
					2	SubstituteValue0
					1	KeepLastValue
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
	Channel 1					
		ChannelTypeForIO	UInt64	Channel type for I/O		
					0	DigitalInput
					1	DigitalOutput
		ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5BF00-0BA0 - V1.0					
Channel 2					
	ChannelTypeForIO	UInt64	Channel type for I/O		
				0	DigitalInput
				1	DigitalOutput
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 3					
	ChannelTypeForIO	UInt64	Channel type for I/O		
				0	DigitalInput
				1	DigitalOutput
	ChannelAddress	Int64	*GetChannelAddressForDigitalInput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalInput()		
Channel 0					
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 1					
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 2					
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
Channel 3					
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 143-5BF00-0BA0 - V1.0						
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	Channel 4					
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 5					
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 6					
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	Channel 7					
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
Module - 6ES7 142-5AF00-0BA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		EnableValueStatus	Boolean	Value status		
		ShortDesignation	String	Short designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 142-5AF00-0BA0 - V1.0						
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		TypeName	String	InvariantTypeName		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
	Submodule					
		SharedDeviceAccessConfigured	Boolean			
		Comment	String	Comment		
		Name	String	Name		
		DiagnosticsNoSupplyVoltage	Boolean	No supply voltage 2L+		
		DiagnosticsShortCircuitToGround	Boolean	Short circuit to ground		
		ReactionToCpuStop	UInt64	Reaction to CPU STOP		
					6	Shutdown
					1	KeepLastValue
					2	SubstituteAValue
		PositionNumber	Int32	Index		
	Channel 0					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
	Channel 1					
		ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
		ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
		SubstituteValue	Boolean	Substitute value		
					0	Value0

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 142-5AF00-0BA0 - V1.0					
				1	Value1
Channel 2					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
Channel 3					
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
Channel 4					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
Channel 5					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
Channel 6					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		
	SubstituteValue	Boolean	Substitute value		
				0	Value0
				1	Value1
Channel 7					
	ChannelWidth	UInt64	*GetChannelWidthForDigitalOutput()		
	ChannelAddress	Int64	*GetChannelAddressForDigitalOutput()		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 142-5AF00-0BA0 - V1.0						
		SubstituteValue	Boolean	Substitute value		
					0	Value0
					1	Value1
Module - 6ES714x-xxxxx-0AA0						
		Author	String	Author		
		Name	String	Name		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 148-6JD00-0AB0 - V1.1						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		ActivatePort1	Boolean	Port1_Enable		
		ActivatePort2	Boolean	Port2_Enable		
		ActivatePort3	Boolean	Port3_Enable		
		ActivatePort4	Boolean	Port4_Enable		
	IO-Link Module					
		ShortDesignation	String	Short designation		
		Comment	String	Comment		
		Name	String	Name		
		TypeName	String	InvariantTypeName		
		Comment	String	Comment		
		Name	String	Name		
		TypeName	String	InvariantTypeName		
	Head Submodule					
	Interface Submodule					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 148-6JD00-0AB0 - V1.1						
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		IsochronousMode	Boolean			
		IsochronousTiToCalculationMode	Int32			
		IsochronousTi	Double			
		IsochronousTo	Double			
		Name	String	Name		
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module						
		Comment	String	Comment		
		Name	String	Name		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		PortConfiguration	UInt64	Port type		
					0	DigitalInput
					1	DigitalOutput
					2	IoLink1IOr1OPlusPqi
					3	IoLink2IPlusPqi
					4	IoLink2IOr2OPlusPqi
					5	IoLink4IOr4OPlusPqi
					6	IoLink8IOr8OPlusPqi
					7	IoLink16IOr16OPlusPqi
					8	IoLink32IOr32OPlusPqi
		ConfigurationWithoutS7PCT	Boolean	Autostart (without S7 PCT)		
		PortMode	UInt64	Operating mode		
					0	IoLinkAutostart
					1	IoLinkManual
		DeviceId	UInt64	Device ID		
		InspectionOrBackupLevel	UInt64	Inspection / backup level		
					4	TypeCompatibleV1Dot1WithRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupRestore
					3	TypeCompatibleV1Dot1WithBackupRestore
					0	None
		ActivatePortDiagnostics	Boolean	Diag: Port		
		DiagnosticsNoSupplyVoltage	Boolean	Diag: Missing 2L+		
		VendorId	UInt32	Vendor ID		
		TypeName	String	InvariantTypeName		
		HardwareInterruptEnable	Boolean	Hardware interrupt		
		HardwareInterruptEventName	String	*HardwareInterruptEventName		
		HardwareInterruptOB	Object	*HardwareInterruptOB		
		HardwareInterruptPriority	UInt64	*HardwareInterruptPriority		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 148-6JD00-0AB0 - V1.0					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	TypeName	String	InvariantTypeName		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	ActivatePort1	Boolean	Port1_Enable		
	ActivatePort2	Boolean	Port2_Enable		
	ActivatePort3	Boolean	Port3_Enable		
	ActivatePort4	Boolean	Port4_Enable		
IO-Link Module					
	ShortDesignation	String	Short designation		
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
	TypeName	String	InvariantTypeName		
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
	TypeName	String	InvariantTypeName		
Head Submodule					
Interface Submodule					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 148-6JD00-0AB0 - V1.0						
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		IsochronousMode	Boolean			
		IsochronousTiToCalculationMode	Int32			
		IsochronousTi	Double			
		IsochronousTo	Double			
		Name	String	Name		
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module						
		Comment	String	Comment		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		PortConfiguration	UInt64	Port type		
					8	IoLink32IOr32OPlusPqi
					7	IoLink16IOr16OPlusPqi
					6	IoLink8IOr8OPlusPqi
					5	IoLink4IOr4OPlusPqi
					4	IoLink2IOr2OPlusPqi
					2	IoLink1IOr1OPlusPqi
					0	DigitalInput
					1	DigitalOutput
					3	IoLink2IPlusPqi
		ConfigurationWithoutS7PCT	Boolean	Autostart (without S7 PCT)		
		ActivatePortDiagnostics	Boolean	Diag: Port		
		DiagnosticsNoLoadVoltage	Boolean	Diag: Missing 2L+		
		HardwareInterrupt	Boolean	Enable hardware interrupt		
					1	Active
					0	Deactivated
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 147-4JD00-0AB0 - V1.1						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Name	String	Name		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
		DiagnosticsGroup	Boolean	Group diagnostics		
		DiagnosticsPort1	Boolean	Port 1		
		DiagnosticsPort2	Boolean	Port 2		
		DiagnosticsPort3	Boolean	Port 3		
		DiagnosticsPort4	Boolean	Port 4		
		InputOrOutputType	UInt64			
					4	Value4And4
					149	Value8And0
					148	Value8And8
					12	Value12And8
					145	Value16And16
					20	Value20And16
					147	Value32And32
		PortModePort1	UInt64	Operating mode		
					7	Deactivated
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di
					4	Dq
		InputDataLengthPort1	UInt64	Input data length (without PQI)		
		OutputDataLengthPort1	UInt64	Output data length		
		VendorIdPort1	UInt64	Vendor ID		
		DeviceIdPort1	UInt64	Device ID		
		PortModePort2	UInt64	Operating mode		
					7	Deactivated
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 147-4JD00-0AB0 - V1.1						
					4	Dq
		InputDataLengthPort2	UInt64	Input data length (without PQI)		
		OutputDataLengthPort2	UInt64	Output data length		
		VendorIdPort2	UInt64	Vendor ID		
		DeviceIdPort2	UInt64	Device ID		
		PortModePort3	UInt64	Operating mode		
					7	Deactivated
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di
					4	Dq
		InputDataLengthPort3	UInt64	Input data length (without PQI)		
		OutputDataLengthPort3	UInt64	Output data length		
		VendorIdPort3	UInt64	Vendor ID		
		DeviceIdPort3	UInt64	Device ID		
		PortModePort4	UInt64	Operating mode		
					7	Deactivated
					8	IoLinkAutostart
					1	IoLinkManual
					3	Di
					4	Dq
		InputDataLengthPort4	UInt64	Input data length (without PQI)		
		OutputDataLengthPort4	UInt64	Output data length		
		VendorIdPort4	UInt64	Vendor ID		
		DeviceIdPort4	UInt64	Device ID		
		PortQualifierInformation	Boolean	Port Qualifier Information (PQI)		
		ConfigurationWithoutS7PCT	Boolean	Configuration without S7-PCT		
		InspectionOrBackupLevelPort1	UInt64	Inspection / backup level		
					7	TypeCompatibleV1Dot1WithRestore
					5	TypeCompatibleV1Dot1WithBackupandRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupandRestore

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 147-4JD00-0AB0 - V1.1						
		InspectionOrBackupLevelPort2	UInt64	Inspection / backup level		
					7	TypeCompatibleV1Dot1WithRestore
					5	TypeCompatibleV1Dot1WithBackupandRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupandRestore
		InspectionOrBackupLevelPort3	UInt64	Inspection / backup level		
					7	TypeCompatibleV1Dot1WithRestore
					5	TypeCompatibleV1Dot1WithBackupandRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupandRestore
		InspectionOrBackupLevelPort4	UInt64	Inspection / backup level		
					7	TypeCompatibleV1Dot1WithRestore
					5	TypeCompatibleV1Dot1WithBackupandRestore
					1	SameTypeV1Dot0WithoutBackupRestore
					2	TypeCompatibleV1Dot1WithoutBackupandRestore
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
Module - 6ES7 154-4AB10-0AB0 - V7.1						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 154-4AB10-0AB0 - V7.1					
Integrated Power Module					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Name	String	Name		
	DiagnosticsNoSupplyVoltage	Boolean	Diagnostics: No load voltage L+:		
				0	Deactivated
				1	Active
	PositionNumber	Int32	Slot		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	OptionHandling	Boolean	Allow to reconfigure the device via the user program		
Submodule					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	PortActivation	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 154-4AB10-0AB0 - V7.1						
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 147-4JD00-0AB0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
		TypeName	String	Short designation		
		InputOrOutputType	UInt64	Input/output type - Input/output		
					33	Value1And1
					146	Value2And2
					4	Value4And4
					149	Value8And0
					148	Value8And8
					145	Value16And16
					147	Value32And32
		DiagnosticsGroup	Boolean	Group diagnostics		
		DiagnosticsPort1	Boolean	Port 1		
		DiagnosticsPort2	Boolean	Port 2		
		DiagnosticsPort3	Boolean	Port 3		
		DiagnosticsPort4	Boolean	Port 4		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		TypeName	String	InvariantTypeName		
		GenerateDeviceNamesAutomatically	Boolean	Generate device name automatically		
					0	Manual
					1	Automatic
		IdentificationMode	UInt64	Generate Identification and Maintenance for both sides		
					1	ApplySettingsForBothSidesOfTheCoupler
					0	DefineDifferentSettingForTheSidesOfTheCoupler
		DiagnosticParameterMode	UInt64	Generate Diagnostic for both sides		
					0	DefineDifferentSettingForTheSidesOfTheCoupler
					1	ApplySettingsForBothSidesOfTheCoupler
		ActivateDataStatus	Boolean	Activate data status		
Module - 6ES7 158-3AD10-0XA0 - V4.0						
		SharedDeviceAccessConfigured	Boolean			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location Designation		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
		DiagnosticsVoltageCheckForPS1Active	Boolean	Voltage check PS1		
		DiagnosticsVoltageCheckForPS2Active	Boolean	Voltage check PS2		
		DiagnosticsDataValidityActive	Boolean	Diagnostic Data Validity		
		DiagnosticsErrorInOtherNetworkActive	Boolean	Diagnostics error in other Network		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		DiagnosticsDifferenceInNetworkConfigActive	Boolean	Diagnostics difference network configuration		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 158-3AD10-0XA0 - V4.0					
	DataValidityDisplayDIAActive	Boolean	DataValidityDisplayDia[1]		
Head Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String	Name		
	PositionNumber	Int32	PositionNumber		
Interface					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Module - 6ES7 158-3AD10-0XA0 - V4.2					
	SharedDeviceAccessConfigured	Boolean			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	LocationIdentifier	String	Location Designation		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	TypeName	String	InvariantTypeName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6ES7 158-3AD10-0XA0 - V4.2						
		DiagnosticsVoltageCheckForPS1Active	Boolean	Voltage check PS1		
		DiagnosticsVoltageCheckForPS2Active	Boolean	Voltage check PS2		
		DiagnosticsUnderflowVoltage	Boolean	DiagnosticUndervoltage		
		DiagnosticsDataValidityActive	Boolean	Diagnostic Data Validity		
		DiagnosticsErrorInOtherNetworkActive	Boolean	Diagnostics error in other Network		
		DiagnosticsDifferenceInNetworkConfigActive	Boolean	Diagnostics difference network configuration		
		DataValidityDisplayDIAActive	Boolean	DataValidityDisplayDia[1]		
Head Submodule						
		SharedDeviceAccessConfigured	Boolean			
		Name	String	Name		
		PositionNumber	Int32	PositionNumber		
Interface						
		IECV22LLDPMode	Boolean			
		SharedDeviceAccessConfigured	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
Module - 1.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
	SCALANCE\SCALANCE<devicefamilyname>\DEVICE\MDD_Scalance_SCALANCE<devicefamilyname>					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module - 6GK5 2-*****-**** - newest**						
		Author	String	Author		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		OrderNumber	String	Article number		
		LocationIdentifier	String	Location identifier		
		PlantDesignation	String	Plant designation		
		TypeName	String	InvariantTypeName		
		AdditionalInformation	String	Additional information		
		InstallationDate	DateTime	Installation date		
		Name	String	Name		
		PositionNumber	Int32	Slot		
	Head S	Name	String	Name		
		DiagnosticsRedundantPowerSupply	UInt64	DiagnosticsRedundantPowerSupply		
		Prm_REFDS4Var1	Boolean	DiagnosticsCPlug		
	Interface Submodule					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GK5 2**-*****-**** - newest						
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module - 6GK5 3-*****-**** - newest**						
		Author	String	Author		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		OrderNumber	String	Article number		
		LocationIdentifier	String	Location identifier		
		PlantDesignation	String	Plant designation		
		TypeName	String	InvariantTypeName		
		AdditionalInformation	String	Additional information		
		InstallationDate	DateTime	Installation date		
		Name	String	Name		
		PositionNumber	Int32	Slot		
	Head Submodule					
		Name	String	Name		
		DiagnosticsRedundantPowerSupply	UInt64	DiagnosticsRedundantPowerSupply		
		Prm_REFDS4Var1	Boolean	DiagnosticsCPlug		
	Interface Submodule					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GK5 3**-*****-**** - newest						
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module - 6GK5 4-*****-**** - newest**						
		Author	String	Author		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		OrderNumber	String	Article number		
		LocationIdentifier	String	Location identifier		
		PlantDesignation	String	Plant designation		
		TypeName	String	InvariantTypeName		
		AdditionalInformation	String	Additional information		
		InstallationDate	DateTime	Installation date		
		Name	String	Name		
		PositionNumber	Int32	Slot		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GK5 4**-*****-**** - newest						
	Head Submodule					
		Name	String	Name		
		DiagnosticsRedundantPowerSupply	UInt64	DiagnosticsRedundantPowerSupply		
		Prm_REFDS4Var1	Boolean	DiagnosticsCPlug		
	Interface Submodule					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GK5 4**-*****-**** - newest						
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module - 6GK5 5-*****-**** - newest**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Head Submodule					
		Name	String	Name		
		DiagnosticsRedundantPowerSupply	UInt64	DiagnosticsRedundantPowerSupply		
		Prm_REFDS4Var1	Boolean	DiagnosticsCPlug		
	Interface Submodule					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GK5 5**-*****-**** - newest						
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module - 6GK5 7-*****-**** - newest**						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GK5 7**-*****-**** - newest						
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		TypeName	String	InvariantTypeName		
	Head Submodule					
		Name	String	Name		
		DiagnosticsRedundantPowerSupply	UInt64	DiagnosticsRedundantPowerSupply		
		Prm_REFDS4Var1	Boolean	DiagnosticsCPlug		
	Interface Submodule					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GK5 7**-*****-**** - newest						
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module - 6GK5400-8AS00-8AP2, 6GK54						

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module-6GK5400-8AS00-8AP2,6GK54						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module-6GK5400-8AS00-8AP2, 6GK5408-0GA00-8AP2, 6GK5408-0PA00-8AP2						
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GK5 400-8AS00-8AP2, 6GK5 408-0GA00-8AP2, 6GK5 408-0PA00-8AP2						
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module - 6GK5 991-2**-****						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GK5 991-2****-****						
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
Module - 6GK5 991-4**-****						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GK5 991-4****-****						
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		
	SCALANCE\SFP900Identification\MDD_6GK5_991_1****_****					
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		PositionNumber	Int32	Slot		
		Name	String	Name		
		Comment	String	Comment		

SIEMENS

SIMATIC NET

SCALANCE
Openness for SCALANCE

Programming and Operating Manual

Introduction 1

Conventions 2

DNS Client 3

SNMP Traps 4

NTP Client 5

Syslog Client 6

Link Aggregation 7

03/2021
C79000-G8976-C630-1

Legal information

Warning notice system

This manual contains notices you have to observe in order to ensure your personal safety, as well as to prevent damage to property. The notices referring to your personal safety are highlighted in the manual by a safety alert symbol, notices referring only to property damage have no safety alert symbol. These notices shown below are graded according to the degree of danger.

⚠ **DANGER**
indicates that death or severe personal injury **will** result if proper precautions are not taken.

⚠ **WARNING**
indicates that death or severe personal injury **may** result if proper precautions are not taken.

⚠ **CAUTION**
indicates that minor personal injury can result if proper precautions are not taken.

NOTICE
indicates that property damage can result if proper precautions are not taken.

If more than one degree of danger is present, the warning notice representing the highest degree of danger will be used. A notice warning of injury to persons with a safety alert symbol may also include a warning relating to property damage.

Qualified Personnel

The product/system described in this documentation may be operated only by **personnel qualified** for the specific task in accordance with the relevant documentation, in particular its warning notices and safety instructions. Qualified personnel are those who, based on their training and experience, are capable of identifying risks and avoiding potential hazards when working with these products/systems.

Proper use of Siemens products

Note the following:

⚠ **WARNING**
Siemens products may only be used for the applications described in the catalog and in the relevant technical documentation. If products and components from other manufacturers are used, these must be recommended or approved by Siemens. Proper transport, storage, installation, assembly, commissioning, operation and maintenance are required to ensure that the products operate safely and without any problems. The permissible ambient conditions must be complied with. The information in the relevant documentation must be observed.

Trademarks

All names identified by ® are registered trademarks of Siemens AG. The remaining trademarks in this publication may be trademarks whose use by third parties for their own purposes could violate the rights of the owner.

Disclaimer of Liability

We have reviewed the contents of this publication to ensure consistency with the hardware and software described. Since variance cannot be precluded entirely, we cannot guarantee full consistency. However, the information in this publication is reviewed regularly and any necessary corrections are included in subsequent editions.

Siemens AG
Global Services Information Technology
80200 MÜNCHEN
GERMANY

C79000-G8976-C630-1
Ⓟ 02/2021 Subject to change

Copyright © Siemens AG 2021.
All rights reserved

Table of contents

1 Introduction 5

2 Conventions 7

3 DNS Client 9

3.1 Parameters 9

3.2 Creating a New Row 9

3.3 Deleting a Row 11

3.4 Querying a Parameter 11

4 SNMP Traps 13

4.1 Parameters 13

4.2 Creating a New Row 13

4.3 Deleting a Row 14

4.4 Querying a Parameter 14

4.5 Setting a Parameter 15

5 NTP Client 17

5.1 Parameters 17

5.2 Creating a New Row 17

5.3 Deleting a Row 19

5.4 Querying a Parameter 19

5.5 Setting a Parameter 19

6 Syslog Client 21

6.1 Parameters 21

6.2 Creating a New Row 21

6.3 Deleting a Row 22

6.4 Querying a Parameter 22

6.5 Setting a Parameter 23

7 Link Aggregation 25

7.1 Parameters 25

7.2 Creating a New Row 27

7.3 Deleting a Row 28

7.4 Querying a Parameter 28

7.5 Setting a Parameter 29

7.6 Setting the State of Ports..... 29

Introduction

1

SCALANCE X devices can be configured using TIA Portal Openness. Complex and scalar data types are used for this purpose.

Tables in the TIA Portal are linked with complex data types. The other interface elements are linked with scalar data types.

The following sections describe the four most important applications for complex data types:

- Creating a new row
- Deleting a row
- Querying a parameter
- Setting a parameter

Both scalar and complex data types are used in these applications.

Basic knowledge required

To understand the following contents, general knowledge of automation engineering and identification systems and of TIA Portal Openness is required.

Additional information

You can find detailed information on TIA Portal Openness in the "Automating projects with scripts" help. This help also contains specific programming examples (see also sections "Functions of projects and project data" and "Functions for calling devices, networks and connections").

You can find information on the configuration limits of the devices in the TIA Portal online help (section "Configuring SCALANCE X / W / M").

Requirement

- The Openness application is connected to the TIA Portal.
- A project is open.
- To compile the project, all devices have to be offline.

Validity

This description applies to the following firmware versions and products:

- As of firmware version 4.2, the following SCALANCE devices:
  - SCALANCE XB-200
  - SCALANCE XC-200
  - SCALANCE XF-200
  - SCALANCE XP-200
  - SCALANCE XR-300WG
- As of firmware version 6.2, the following SCALANCE devices:
  - SCALANCE XM-400
  - SCALANCE XR-500

Conventions

2

Commands for configuring complex data types with SCALANCE devices are illustrated according to the following syntax rules:

Convention	Description	Example
Font	All commands are displayed in a non-proportional font.	`var result_create = DNSClientTable.Rows.Create();`
User-defined values	For some parameters, a user-defined value is necessary. Values that need to be defined by you are shown in curly brackets, e.g.: • The number of a row • An IP address • An index • A string, for example a name or a description • A parameter and possibly the value of the parameter Always replace the curly brackets also. They are **not** part of the syntax of TIA Portal Openness.	`DNSClientTable.Rows[{row}].Delete();`
		`item_XM400.SetAttribute("DnsServerAddress", "{IP address}");`
		`item_XM400.SetAttribute("NtpServerIndex", {index value});`
		`LinkAggregationGeneralTable.Rows[{row}].SetAttribute("LinkAggregationCustomName", "{name}");`
		`SNMPTrapsTable.Rows[{row}].SetAttribute("{parameter}", "{value}");`

DNS Client

3

3.1 Parameters

The following table shows the parameters of the DNS Client table:

Parameter name in TIA Portal	Parameter type in TIA Portal	Parameter name in Openness	Parameter type in Openness	Parameter value in Openness	Default access	Description
DNS Client	Table	DnsClientTable	TableData	-	R/W	-
DNS Server Address	Textbox	DnsServerAddress	String	Example: 192.168.3.4	R	Shows the IP address of the DNS server.
Origin	Textbox	DnsClientOrigin	String	manual learned	R	Shows whether the DNS server was configured manually or was assigned by DHCP.

3.2 Creating a New Row

An index is automatically assigned to a new row. If you delete a row and then create a new row, the new row receives the index of the deleted row. A new row is not necessarily added to the end of the table. The index values are sorted in ascending order.

The number of rows you can create depends on the firmware version of the SCALANCE device. If you exceed the maximum number of rows, no error message is output. To ensure that a row has been created, we recommend counting the number of rows.

Note

Values of a row cannot be changed

Once you have created a row, you can no longer change the values of the row.

If the values of a row need to be changed, you have to delete the row and create a new row.

To create a new row in the DNS Client table, follow these steps:

Step	Description	Command
1	Initiate the DNS Client table.	`TableData DNSClientTable = item_XM400.GetAttribute("DnsClientTable") as TableData;`
2	Assign an IP address for the **DnsServerAddress** parameter (scalar data type).	`item_XM400.SetAttribute("DnsServerAddress", "{IP address}");`
3	[Optional] Check the value of the **DnsServerAddress** parameter.	`var DNSServerAddress = item_XM400.GetAttribute("DnsServerAddress");`

Step	Description	Command
4	Create a new row. The IP address configured as scalar data type for the **DnsServerAddress** parameter is transferred to the complex data type of the same name.	`var result_create = DNSClientTable.Rows.Create();`
5	[Optional] Check the number of rows.	`var cnt = DNSClientTable.Rows.Count();`

Example

In this example, three rows are created one after another. The following IP addresses are assigned for the **DnsServerAddress** parameter:

- `192.168.3.9`
- `172.168.3.7`
- `152.168.3.5`

```
TableData DNSClientTable = item_XM400.GetAttribute("DnsClientTable")
as TableData;
item_XM400.SetAttribute("DnsServerAddress", "192.168.3.9");
var DNSServerAddress = item_XM400.GetAttribute("DnsServerAddress");
var result_create = DNSClientTable.Rows.Create();
item_XM400.SetAttribute("DnsServerAddress", "172.168.3.7");
result_create = DNSClientTable.Rows.Create();
item_XM400.SetAttribute("DnsServerAddress", "152.168.3.5");
result_create = DNSClientTable.Rows.Create();
```

Example

Row 1 is deleted first in this example. For more information on deleting a row, see "Deleting a Row (Page 11)".

```
DNSClientTable.Rows[1].Delete();
DNSClientTable = item_XM400.GetAttribute("DnsClientTable") as
TableData;
```

A new row is then created. The new row automatically receives the index of the previously deleted row: 1.

```
item_XM400.SetAttribute("DnsServerAddress", "182.168.3.4");
result_create = DNSClientTable.Rows.Create();
```

3.3 Deleting a Row

To delete a row in the DNS Client table, follow these steps:

Step	Description	Command
1	Delete the required row.	`DNSClientTable.Rows[{row}].Delete();`
2	[Optional] Update the variable.	`DNSClientTable = item_XM400.GetAttribute("DnsClientTable") as TableData;`
3	[Optional] Check the number of rows.	`cnt = DNSClientTable.Rows.Count();`

Example

Row 1 of the DNS Client table is deleted in this example.

```
DNSClientTable.Rows[1].Delete();
DNSClientTable = item_XM400.GetAttribute("DnsClientTable") as
TableData;
```

3.4 Querying a Parameter

To query a parameter of the DNS Client table, execute the following command:

```
var DnsClientAddress_1 =
DNSClientTable.Rows[{row}].GetAttribute("{parameter}");
```

Example

In this example, the **DnsClientAddress** parameter from row 1 of the DNS Client table is queried.

```
var DnsClientAddress_1 =
DNSClientTable.Rows[1].GetAttribute("DnsClientAddress");
```

In this example, the **DnsClientOrigin** parameter from row 1 of the DNS Client table is queried.

```
var DnsClientorigin_1 =
DNSClientTable.Rows[1].GetAttribute("DnsClientOrigin");
```

SNMP Traps

4

4.1 Parameters

The following table shows the parameters of the SNMP Traps table:

Parameter name in TIA Portal	Parameter type in TIA Portal	Parameter name in Openness	Parameter type in Openness	Parameter value in Openness	Default access	Description
SNMP Traps	Table	SnmpTrapsTable	TableData	-	R/W	The table is now available for SCALANCE XM-400 with firmware version 6.4.
Trap Receiver Address	Textbox	SnmpTrapsIpAddress	String	Example: 192.168.3.4	R/W	Enter the IP address or the FQDN (Fully Qualified Domain Name) of the station to which the device sends SNMP traps.
Trap	Checkbox	SnmpTrapTargetStatus	Boolean	true false	R/W	Enable or disable the sending of SNMP traps. Stations that are entered but not selected do not receive SNMP traps.

4.2 Creating a New Row

An index is automatically assigned to a new row. If you delete a row and then create a new row, the new row receives the index of the deleted row. A new row is not necessarily added to the end of the table. The index values are sorted in ascending order.

The number of rows you can create depends on the firmware version of the SCALANCE device. If you exceed the maximum number of rows, no error message is output. To ensure that a row has been created, we recommend counting the number of rows.

To create a new row in the SNMP Traps table, follow these steps:

Step	Description	Command
1	Initiate the SNMP Traps table.	`TableData SNMPTrapsTable = item_XC200.GetAttribute("SnmpTrapsTable") as TableData;`
2	Assign an IP address for the **SnmpTrapsIpAddress** parameter (scalar data type).	`item_XC200.SetAttribute("SnmpTrapsIpAddress", "{IP address}");`

Step	Description	Command
3	Create a new row. The IP address configured as scalar data type for the **SnmpTrapsIpAddress** parameter is transferred to the complex data type of the same name.	`var result_create = SNMPTrapsTable.Rows.Create();`
4	[Optional] Check the number of rows.	`var cnt = SNMPTrapsTable.Rows.Count();`

Example

One row is created in this example. The IP address 192.168.3.4 is assigned for the **SnmpTrapsIpAddress** parameter:

```
TableData SNMPTrapsTable = item_XC200.GetAttribute("SnmpTrapsTable")
as TableData;
item_XC200.SetAttribute("SnmpTrapsIpAddress", "192.168.3.4");
var result_create = SNMPTrapsTable.Rows.Create();
```

4.3 Deleting a Row

To delete a row in the SNMP Traps table, follow these steps:

Step	Description	Command
1	Delete the required row.	`SNMPTrapsTable.Rows[{row}].Delete();`
2	[Optional] Update the variable.	`SNMPTrapsTable = item_XC200.GetAttribute("SnmpTrapsTable") as TableData;`
3	[Optional] Check the number of rows.	`cnt = SNMPTrapsTable.Rows.Count();`

Example

Row 0 of the SNMP Traps table is deleted in this example.

```
SNMPTrapsTable.Rows[0].Delete();
SNMPTrapsTable = item_XC200.GetAttribute("SnmpTrapsTable") as
TableData;
```

4.4 Querying a Parameter

To query a parameter of the SNMP Traps table, execute the following command:

```
var SnmpTrapAddress =
SNMPTrapsTable.Rows[{row}].GetAttribute("{parameter}");
```

Example

In this example, the **SnmpTrapAddress** parameter from row 0 of the SNMP Traps table is queried.

```
var SnmpTrapAddress =
SNMPTrapsTable.Rows[0].GetAttribute("SnmpTrapsIpAddress");
```

4.5 Setting a Parameter

To set a parameter of the SNMP Traps table, execute the following command:

```
SNMPTrapsTable.Rows[{row}].SetAttribute("{parameter}", {value});
```

Example

In this example, the **SnmpTrapTargetStatus** parameter from row 0 of the SNMP Traps table is set to the value **true**.

```
SNMPTrapsTable.Rows[0].SetAttribute("SnmpTrapTargetStatus", true);
```

NTP Client

5

5.1 Parameters

The following table shows the parameters of the NTP Client table:

Parameter name in TIA Portal	Parameter type in TIA Portal	Parameter name in Openness	Parameter type in Openness	Parameter value in Openness	Default access	Description
NTP Client	Table	NtpClientTable	TableData	-	R/W	-
NTP Server Index	Combobox	NtpServerIndex	String	1 2 3 4	R/W	Select the index of the NTP server. The NTP servers are queried in the order of the NTP Server Index. The time of the server that is found first is applied.
NTP Server Address	Textbox	NtpServerAddress	String	Example: 192.168.3.4	R/W	Enter the IPv4 address of the NTP server.
NTP Server Port	Textbox	NtpServerPort	Integer	Example: 123	R/W	Enter the port of the NTP server.
Poll Interval [s]	Textbox	NtpServerPollInterval	Integer	-	R/W	Specify the interval between two time queries. The larger the interval, the more inaccurate the time is. Possible values are 64 to 2592000 seconds (30 days).
Key ID	Textbox	-	-	-	R/W	This parameter is not linked with TIA Portal Openness.
Hash Algorithm	Combobox	-	-	DES MD5 SHA1	R/W	This parameter is not linked with TIA Portal Openness.
Key	Password	-	-	-	R/W	This parameter is not linked with TIA Portal Openness.
Key Confirmation	Password	-	-	-	R/W	This parameter is not linked with TIA Portal Openness.

5.2 Creating a New Row

Not all parameters of the NTP Client table can be configured using TIA Portal Openness. For more information, refer to "Parameters (Page 17)".

The sorting of the NTP Client table is oriented to the **NtpServerIndex** parameter. The index values in this column are sorted in ascending order. When you create a new row, the row is sorted into the existing table according to the index value of the **NtpServerIndex** parameter.

The number of rows you can create depends on the firmware version of the SCALANCE device. If you exceed the maximum number of rows, no error message is output. To ensure that a row has been created, we recommend counting the number of rows.

To create a new row in the NTP Client table, follow these steps:

Step	Description	Command
1	Initiate the NTP Client table.	`TableData NTPClientTable = item_XM400.GetAttribute("NtpClientTable") as TableData;`
2	Assign an index value for the **NtpServerIndex** parameter (scalar data type).	`item_XM400.SetAttribute("NtpServerIndex", {index value});`
3	[Optional] Check the value of the **NtpServerIndex** parameter.	`var NTPServerIndex = item_XM400.GetAttribute("NtpServerIndex");`
4	Create a new row. The index value configured as scalar data type for the **NtpServerIndex** parameter is transferred to the complex data type of the same name.	`var result_create = NTPClientTable.Rows.Create();`
5	[Optional] Check the number of rows.	`var cnt = NTPClientTable.Rows.Count();`

Example

In this example, three rows are created one after another. The following index values are assigned for the **NtpServerIndex** parameter:

- 2
- 3
- 1

```
TableData NTPClientTable = item_XM400.GetAttribute("NtpClientTable")
as TableData;
item_XM400.SetAttribute("NtpServerIndex", 2);
var NTPServerIndex = item_XM400.GetAttribute("NtpServerIndex");
var result_create = NTPClientTable.Rows.Create();
item_XM400.SetAttribute("NtpServerIndex", 3);
result_create = NTPClientTable.Rows.Create();
item_XM400.SetAttribute("NtpServerIndex", 1);
result_create = NTPClientTable.Rows.Create();
```

5.3 Deleting a Row

To delete a row in the NTP Client table, follow these steps:

Step	Description	Command
1	Delete the required row.	`NTPClientTable.Rows[{row}].Delete();`
2	[Optional] Check the number of rows.	`var cnt = NTPClientTable.Rows.Count();`

Example

Row 2 of the NTP Client table is deleted in this example.

```
NTPClientTable.Rows[2].Delete();
```

5.4 Querying a Parameter

To query a parameter of the NTP Client table, execute the following command:

```
var NTPServerAddress_0 =
NTPClientTable.Rows[{row}].GetAttribute("{parameter}");
```

Example

In this example, the **NtpServerAddress** parameter from row 0 of the NTP Client table is queried.

```
var NTPServerAddress_0 =
NTPClientTable.Rows[0].GetAttribute("NtpServerAddress");
```

Example

In this example, the **NtpServerPollInterval** parameter from row 0 of the NTP Client table is queried.

```
var set_NTPServerPollInterval_0 =
NTPClientTable.Rows[0].GetAttribute("NtpServerPollInterval");
```

5.5 Setting a Parameter

To set a parameter of the NTP Client table, execute the following command:

```
NTPClientTable.Rows[{row}].SetAttribute("{parameter}", "{value}");
```

Example

In this example, the **NtpServerAddress** parameter from row 0 of the NTP Client table is set to the value 182.168.2.9.

```
NTPClientTable.Rows[0].SetAttribute("NtpServerAddress",
"182.168.2.9");
```

Example

In this example, the **NtpServerPollInterval** parameter from row 0 of the NTP Client table is set to the value 5.

```
NTPClientTable.Rows[0].SetAttribute("NtpServerPollInterval", 5);
```

Syslog Client

6

6.1 Parameters

The following table shows the parameters of the Syslog Client table:

Parameter name in TIA Portal	Parameter type in TIA Portal	Parameter name in Openness	Parameter type in Openness	Parameter value in Openness	Default access	Description
Syslog Client	Table	SyslogClientTable	TableData	-	R/W	-
Syslog Server Address	Textbox	SyslogServerAddress	String	Example: 192.168.3.4	R/W	Enter the IP address or the FQDN (Fully Qualified Domain Name) of the Syslog server.
Server Port	Textbox	SyslogServerPort	Integer	Example: 514	R/W	Enter the port of the Syslog server being used.

6.2 Creating a New Row

The sorting of the Syslog Client table is oriented to the **SyslogServerAddress** parameter. The IP addresses in this column are sorted in ascending order. When you create a new row, the row is sorted into the existing table according to the IP address of the **SyslogServerAddress** parameter.

The number of rows you can create depends on the firmware version of the SCALANCE device. If you exceed the maximum number of rows, no error message is output. To ensure that a row has been created, we recommend counting the number of rows.

To create a new row in the Syslog Client table, follow these steps:

Step	Description	Command
1	Initiate the Syslog Client table.	`TableData SyslogClientTable = item_XC200.GetAttribute("SyslogClientTable") as TableData;`
2	Assign an IP address for the **SyslogServerAddress** parameter (scalar data type).	`item_XC200.SetAttribute("SyslogServerAddress", "{IP address}");`
3	[Optional] Check the value of the **SyslogServerAddress** parameter.	`var syslogAddress = item_XC200.GetAttribute("SyslogServerAddress");`
4	Create a new row. The IP address configured as scalar data type for the **SyslogServerAddress** parameter is transferred to the complex data type of the same name.	`var result_create = SyslogClientTable.Rows.Create();`
5	[Optional] Check the number of rows.	`var cnt = SyslogClientTable.Rows.Count();`

Example

In this example, two rows are created one after another. The following IP addresses are assigned for the **SyslogServerAddress** parameter:

- 192.158.4.7
- 172.158.4.5

The row with the IP address 172.158.4.5 is sorted in front of the row with IP address 192.158.4.7, even though they were created in a different order.

```
TableData SyslogClientTable =
item_XC200.GetAttribute("SyslogClientTable") asTableData;
item_XC200.SetAttribute("SyslogServerAddress", "192.158.4.7");
var syslogAddress = item_XC200.GetAttribute("SyslogServerAddress");
var result_create = SyslogClientTable.Rows.Create();
item_XC200.SetAttribute("SyslogServerAddress", "172.158.4.5");
result_create = SyslogClientTable.Rows.Create();
```

6.3 Deleting a Row

To delete a row in the Syslog Client table, follow these steps:

Step	Description	Command
1	Delete the required row.	`SyslogClientTable.Rows[{row}].Delete();`
2	[Optional] Check the number of rows.	`cnt = SyslogClientTable.Rows.Count;`

Example

Row 1 of the Syslog Client table is deleted in this example.

```
SyslogClientTable.Rows[1].Delete();
```

6.4 Querying a Parameter

To query a parameter of the Syslog Client table, execute the following command:

```
var serverPort =
SyslogClientTable.Rows[{row}].GetAttribute("{parameter}");
```

Example

In this example, the **SyslogServerPort** parameter from row 1 of the Syslog Client table is queried.

```
var serverPort =
SyslogClientTable.Rows[1].GetAttribute("SyslogServerPort");
```

Example

In this example, the **SyslogServerAddress** parameter from row 1 of the Syslog Client table is queried.

```
var SyslogServerAddress =
SyslogClientTable.Rows[1].GetAttribute("SyslogServerAddress");
```

6.5 Setting a Parameter

To set a parameter of the Syslog Client table, execute the following command:

```
SyslogClientTable.Rows[{row}].SetAttribute("{parameter}", {value});
```

Example

In this example, the **SyslogServerPort** parameter from row 1 of the Syslog Client table is set to the value 502.

```
SyslogClientTable.Rows[1].SetAttribute("SyslogServerPort", 502);
```

Example

In this example, the **SyslogServerAddress** parameter from row 1 of the Syslog Client table is set to the value 122.158.3.6.

```
SyslogClientTable.Rows[1].SetAttribute("SyslogServerAddress",
"122.158.3.6");
```

Link Aggregation

7

7.1 Parameters

The following table shows the parameters of the Link Aggregation table:

Parameter name in TIA Portal	Parameter type in TIA Portal	Parameter name in Openness	Parameter type in Openness	Parameter value in Openness	Default access	Description
Link Aggregation	Table	LinkAggregationTable	TableData	-	R/W	-
Port	Textbox	LinkAggregationPortName	String	-	R	Shows the virtual port number of this link aggregation. This identifier is assigned internally by the firmware.
Link Aggregation Name	Textbox	LinkAggregationCustomName	String	-	R/W	Specify a name for the link aggregation. This name can be specified by the user during configuration. The name is not absolutely necessary but can be useful to distinguish between the various link aggregations.
Status	Checkbox	LinkAggregationAdminStatus	Boolean	true	R/W	Enable or disable the link aggregation.
				false		
MTU	Textbox	LinkAggregationMTU	Integer	-	R/W	Specify the packet size.
LACP	Combobox	LinkAggregationLacpStatus	Enumaration	LinkAggregation LacpStatus.None	R/W	Specify whether LACP frames are sent. • Off Disables the sending of LACP frames. • On Enables the sending of LACP frames.
				LinkAggregation LacpStatus.Off		
				LinkAggregation LacpStatus.On		

Parameter name in TIA Portal	Parameter type in TIA Portal	Parameter name in Openness	Parameter type in Openness	Parameter value in Openness	Default access	Description
Frame Distribution	Combobox	LinkAggregationFrameDistribution	Enumaration	LinkAggregation FrameDistribution.None	R/W	Set the type of distribution of packets to the individual links of an aggregation. • Destination&Source Mac The distribution is based on a combination of the destination and source MAC address. • Destination&Source IP-MAC The distribution is based on a combination of the destination and source IP address and MAC address.
				LinkAggregation FrameDistribution.DestinationSourceMAC		
				LinkAggregation FrameDistribution. DestinationSourceIPMAC		
VLAN Mode	Combobox	LinkAggregationVlanMode	Enumaration	LinkAggregation VlanMode.None	R/W	Specify how the link aggregation is entered in a VLAN: • Hybrid The link aggregation sends tagged and untagged frames. It is not automatically a member of a VLAN. • Trunk The link aggregation only sends tagged frames and is automatically a member of all VLANs. • Access The port belongs to a provider switch that supports the function Q-in-Q VLAN Tunnel.
				LinkAggregation VlanMode.Hybrid		
				LinkAggregation VlanMode.Trunk		
				LinkAggregation VlanMode.Access		

Parameter name in TIA Portal	Parameter type in TIA Portal	Parameter name in Openness	Parameter type in Openness	Parameter value in Openness	Default access	Description
List of ports	Combobox	LinkAggregation-PortList	List<int>	LinkAggregation PortState.None LinkAggregation PortState.Active LinkAggregation PortState.Deactivated LinkAggregation PortState.Passive LinkAggregation PortState.On	R/W	Shows the ports that belong to this link aggregation. The following values can be selected from the drop-down list: • "a" (active) The port sends LACP frames and is only involved in the link aggregation when LACP frames are received. • "-" (deactivated) Link aggregation is disabled. • "p" (passive) The port is only involved in the link aggregation when LACP frames are received. • "o" (on) The port is involved in the link aggregation and does not send any LACP frames.

7.2 Creating a New Row

When you create a new row, the **Port** parameter is filled automatically. The AG1 name is assigned for the first row. For all subsequent rows, the number is increased by 1, i.e. AG2, AG3 etc. The sorting of the Link Aggregation table is based on the **Port** parameter. The names in this column are sorted in ascending order.

If you delete a row and then create a new row, the new row receives the name of the deleted row. A new row is not necessarily added to the end of the table.

The number of rows you can create depends on the firmware version of the SCALANCE device. If you exceed the maximum number of rows, no error message is output. To ensure that a row has been created, we recommend counting the number of rows.

To create a new row in the Link Aggregation table, follow these steps:

Step	Description	Command
1	Initiate the Link Aggregation table.	`TableData LinkAggregationGeneralTable = item_XM400.GetAttribute("LinkAggregationTable") as TableData;`
2	Create a new row.	`var result_create = LinkAggregationGeneralTable.Rows.Create();`
3	[Optional] Check the number of rows.	`var cnt = LinkAggregationGeneralTable.Rows.Count();`

Example

One row is created in this example.

```
TableData LinkAggregationGeneralTable =
item_XM400.GetAttribute("LinkAggregationTable") as TableData;
var result_create = LinkAggregationGeneralTable.Rows.Create();
```

7.3 Deleting a Row

To delete a row in the Link Aggregation table, follow these steps:

Step	Description	Command
1	Delete the required row.	`LinkAggregationGeneralTable.Rows[{row}].Delete();`
2	[Optional] Check the number of rows.	`cnt = LinkAggregationGeneralTable.Rows.Count();`

Example

Row 0 of the Link Aggregation table is deleted in this example.

```
LinkAggregationGeneralTable.Rows[0].Delete();
```

7.4 Querying a Parameter

To query a parameter of the Link Aggregation table, execute the following command:

```
var laPortName =
LinkAggregationGeneralTable.Rows[{row}].GetAttribute("{parameter}");
```

Example

In this example, the **LinkAggregationCustomName** parameter from row 1 of the Link Aggregation table is queried.

```
var LaCustomName =
LinkAggregationGeneralTable.Rows[1].GetAttribute("LinkAggregationCustomName");
```

Example

In this example, the **LinkAggregationVlanMode** parameter from row 1 of the Link Aggregation table is queried.

```
var LaVlanMode =
LinkAggregationGeneralTable.Rows[1].GetAttribute("LinkAggregationVla
nMode");
```

7.5 Setting a Parameter

To set a parameter of the Link Aggregation table, execute the following command:

```
LinkAggregationGeneralTable.Rows[{row}].SetAttribute("{parameter}",
"{value}");
```

Example

In this example, the **LinkAggregationCustomName** parameter from row 1 of the Link Aggregation table is set to the value "Custom Name1".

```
LinkAggregationGeneralTable.Rows[1].SetAttribute("LinkAggregationCus
tomName", "Custom Name1");
```

Example

In this example, the **LinkAggregationVlanMode** parameter from row 1 of the Link Aggregation table is set to the value "LinkAggregationVlanMode.Hybrid".

```
LinkAggregationGeneralTable.Rows[1].SetAttribute("LinkAggregationVla
nMode",LinkAggregationVlanMode.Hybrid);
```

7.6 Setting the State of Ports

When you have created a new row, you need to specify a state for each port. The number of ports depends on your SCALANCE device. The description and the example assume a SCALANCE device with eight ports. For this reason, exactly eight states are set.

To set the state of the ports in the Link Aggregation table, execute the following command:

```
List<int> newPortList_LA = new List<int>() { (int){state}, (int)
{state}, (int){state}, (int){state}, (int){state}, (int){state},
(int){state}, (int){state} };
```

Example

In this example, the state is set in the Link Aggregation table for all eight ports of a SCALANCE device.

```
List<int> newPortList_LA = new List<int>()
{ (int)LinkAggregationPortState.Active,
(int)LinkAggregationPortState.Active,
(int)LinkAggregationPortState.None,
(int)LinkAggregationPortState.None,
(int)LinkAggregationPortState.Passive,
(int)LinkAggregationPortState.None,
(int)LinkAggregationPortState.None,
(int)LinkAggregationPortState.None };
```

SIEMENS

Openness for SIMATIC Ident

Programming and Operating Manual

Openness for SIMATIC Ident 1

ASM 456 2

ASM 475 3

RF120C 4

RF170C 5

RF180C 6

RF166C 7

RF18xC/RF18xCI 8

RF61xR/RF68xR 9

MV400/MV500 10

11/2019

Legal information

Warning notice system

This manual contains notices you have to observe in order to ensure your personal safety, as well as to prevent damage to property. The notices referring to your personal safety are highlighted in the manual by a safety alert symbol, notices referring only to property damage have no safety alert symbol. These notices shown below are graded according to the degree of danger.

⚠ DANGER

indicates that death or severe personal injury **will** result if proper precautions are not taken.

⚠ WARNING

indicates that death or severe personal injury **may** result if proper precautions are not taken.

⚠ CAUTION

indicates that minor personal injury can result if proper precautions are not taken.

NOTICE

indicates that property damage can result if proper precautions are not taken.

If more than one degree of danger is present, the warning notice representing the highest degree of danger will be used. A notice warning of injury to persons with a safety alert symbol may also include a warning relating to property damage.

Qualified Personnel

The product/system described in this documentation may be operated only by **personnel qualified** for the specific task in accordance with the relevant documentation, in particular its warning notices and safety instructions. Qualified personnel are those who, based on their training and experience, are capable of identifying risks and avoiding potential hazards when working with these products/systems.

Proper use of Siemens products

Note the following:

⚠ WARNING

Siemens products may only be used for the applications described in the catalog and in the relevant technical documentation. If products and components from other manufacturers are used, these must be recommended or approved by Siemens. Proper transport, storage, installation, assembly, commissioning, operation and maintenance are required to ensure that the products operate safely and without any problems. The permissible ambient conditions must be complied with. The information in the relevant documentation must be observed.

Trademarks

All names identified by ® are registered trademarks of Siemens AG. The remaining trademarks in this publication may be trademarks whose use by third parties for their own purposes could violate the rights of the owner.

Disclaimer of Liability

We have reviewed the contents of this publication to ensure consistency with the hardware and software described. Since variance cannot be precluded entirely, we cannot guarantee full consistency. However, the information in this publication is reviewed regularly and any necessary corrections are included in subsequent editions.

Siemens AG
Digital Industries
Postfach 48 48
90026 NÜRNBERG
GERMANY

Ⓟ 09/2020 Subject to change

Copyright © Siemens AG 2018 - 2019.
All rights reserved

Table of contents

1 Openness for SIMATIC Ident 5
2 ASM 456 7
3 ASM 475 13
4 RF120C 15
5 RF170C 25
6 RF180C 31
7 RF166C 35
8 RF18xC/RF18xCI 41
9 RF61xR/RF68xR 49
10 MV400/MV500 51

Openness for SIMATIC Ident

1

SIMATIC Ident devices (communication modules, RF600 reader and MV400/MV500 readers) can be configured with TIA Portal Openness. The following sections provide an overview of the module-specific parameters.

Basic knowledge required

The following passages assume you have general knowledge of automation engineering and identification systems, as well as TIA Portal Openness.

Additional information

You can find detailed information on TIA Portal Openness in the help "Automating projects with scripts". This help contains concrete program examples (see sections "Functions of projects and project data" and "Functions for accessing devices, networks and connections").

Requirement

- The Openness application is connected to the TIA Portal.
- A project is open.
- All devices must be offline to compile the project.

ASM 456

2

The Openness parameters for the "ASM 456" module are described below.

Table 2-1 Parameters of the "ASM 456" module; "Word: 2 IN/OUT DP-V1" module

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
User mode	UserMode	ulong	Ident profile/ RFID standard profile	3	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller. • FB 45 / FC 45: Single tag mode FB 45 (PROFIBUS/PROFINET) or FC 45 (PROFIBUS) is used on the controller. • FB 55 / FC 55: Multitag mode. FB 55 (PROFIBUS/PROFINET) or FC 55 (PROFIBUS) is used on the controller. • FC 56 File handler for S7-300 and S7-400
			FB 45 / FC 45	1	R/W	
			FB 55 / FC 55	4	R/W	
			FC 56	5	R/W	

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
MOBY mode	MobyMode	ulong	RF200/RF300/RF600; MV4x0; MOBY U/D	5	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the mode of the communications module. • RF200/RF300/RF600; MV4x0; MOBY U/D • MOBY I/E normal addressing • RF300 filehandler • MOBY U file handler • MOBY I file handler Normal addressing: The transponder is addressed with physical addresses. Filehandler: Prior to use, the transponder needs to be formatted.
			MOBY I/E normal addressing	1	R/W	
			RF300 filehandler	149	R/W	
			MOBY U file handler	133	R/W	
			MOBY I file handler	129	R/W	
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Diagnostics messages	Diagnostic-Messages	int	None	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set whether hardware diagnostics messages will be reported. • None: Apart from standard diagnostics, no other alarms are generated. • Hard errors: Critical hardware errors are reported by the S7 diagnostics. • Hard/soft errors low priority Critical hardware errors and errors that occur during command processing are reported by the S7 diagnostics. The "Ext_Diag" bit is not set. • Hard/soft errors high priority Critical hardware errors and errors that occur during command processing are reported by the S7 diagnostics. The "Ext_Diag" bit is set.
			Hard errors	2	R/W	
			Hard/soft errors low priority	3	R/W	
			Hard/soft errors high priority	5	R/W	
Suppression of Error LED	SuppressionOfErrorLed	int	None	0	R/W	Disabling the Error LED (ERR) of a channel. The communications module has two channels to which the readers / optical readers can be connected. The Error LED of the other channel flashes permanently when only one of the channels is being used. With the help of the suppression, you can disable the Error LED of the unused channel.
			Channel 1	1	R/W	
			Channel 2	2	R/W	

Table 2-2 Parameters of the "ASM 456" module; "RF680R/RF685R" module

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
User mode	UserMode	ulong	Ident profile/ RFID standard profile	3	R	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller.
MOBY mode	MobyMode	ulong	RF680R/ RF685R	32	R	Selection depends on the communications module and Ident system being used. With this parameter, you set the mode of the communications module. • RF680R/RF685R Normal addressing: The transponder is addressed with physical addresses. Filehandler: Prior to use, the transponder needs to be formatted.
Transmission speed	BaudRate	ulong	115.2 kBd	14	R	Selection depends on the communications module and Ident system being used. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Diagnostics messages	Diagnostic-Messages	int	None	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set whether hardware diagnostics messages will be reported. • None: Apart from standard diagnostics, no other alarms are generated. • Hard errors: Critical hardware errors are reported by the S7 diagnostics. • Hard/soft errors low priority Critical hardware errors and errors that occur during command processing are reported by the S7 diagnostics. The "Ext_Diag" bit is not set. • Hard/soft errors high priority Critical hardware errors and errors that occur during command processing are reported by the S7 diagnostics. The "Ext_Diag" bit is set.
			Hard errors	2	R/W	
			Hard/soft errors low priority	3	R/W	
			Hard/soft errors high priority	5	R/W	
Suppression of Error LED	SuppressionOfErrorLed	int	None	0	R/W	Disabling the Error LED (ERR) of a channel. The communications module has two channels to which the readers / optical readers can be connected. The Error LED of the other channel flashes permanently when only one of the channels is being used. With the help of the suppression, you can disable the Error LED of the unused channel.
			Channel 1	1	R/W	
			Channel 2	2	R/W	

ASM 475

3

The Openness parameters for the "ASM 475" module are described below.

Table 3-1 Parameters of the module "ASM 475"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
MOBY mode	MobyMode	ulong	MOBY I/E/F normal addressing	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the mode of the communications module. • MOBY I/E/F normal addressing • MOBY I file handler • RF200/RF300/RF600; MOBY U/D normal addressing • MOBY U file handler Normal addressing: The transponder is addressed with physical addresses. Filehandler: Prior to use, the transponder needs to be formatted.
			MOBY I file handler	129	R/W	
			RF200/RF300/RF600; MOBY U/D normal addressing	5	R/W	
			MOBY U file handler	133	R/W	
Transmission speed	BaudRate	ulong	19200 Bd	9	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57600 Bd	13	R/W	
			115200 Bd	14	R/W	

RF120C

4

The Openness parameters for the "RF120C" module are described below.

Table 4-1 Parameters of the module "RF120C"; parameters of the parameter group "Readers"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Diagnostics messages	Diagnostic-Messages	int	None	1	R/W	With this parameter, you set whether hardware diagnostics messages will be reported. • None: Apart from standard diagnostics, no other alarms are generated. • Hard errors: Critical hardware errors are reported by the S7 diagnostics.
			Hard errors	2	R/W	
User mode	UserMode	ulong	Ident profile	3	R	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • Ident profile The program block for the Ident profile is used on the controller.

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Ident device / system	IdentDeviceOrSystem	int	RF200 general	53	R/W	Selection of the connected Ident device / system. Depending on the selection you make, the "Ident system" parameter group is adapted.
			RF290R	69	R/W	
			RF300 general	85	R/W	
			RF380R	101	R/W	
			MOBY U	5	R/W	
			General Reader	197	R/W	
			Parameters via FB / optical readers	214	R/W	
			RF600 [1]	117	R/W	
			SLG D10S [1]	21	R/W	
			SLG D11S/ D12S [1]	37	R/W	

[1] The sub-parameters of these parameter are not supported by Openness.

The Openness parameters of the parameter group "Ident device/system" are described below.

Table 4-2 Parameters of the module "RF120C"; parameters of the parameter group "Ident device/system: RF200 general"

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. Note that the value specified here is adopted automatically from the device configuration of the connected devices. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Presence check	Presence-Check	ulong	On	1	R/W	On = As soon as there is a transponder in the antenna field of the reader, its presence is reported. Off = The presence check on the FB is suppressed. The antenna on the reader is nevertheless turned on as long as it has not been turned off by a command.
			Off	0	R/W	
Reset ERR LED	ResetErrorLED	int	On	2	R/W	On = the flashing of the error LED on the communications module is reset by each FB reset. Off = the error LED always indicates the last error. The display can only be reset by turning off the communications module.
			Off	0	R/W	
Max. number of transponders	MaxNoOf-Transponders	int	1	<number>	R	Number of transponders expected in the antenna field. The selection depends on the connected device.
Transponder type	Transponder-Type	int	ISO 15693	1	R	Selection of the transponder types used. The selection depends on the connected device.

Table 4-3 Parameters of the module "RF120C"; parameters of the parameter group "Ident device/system: RF290R"

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. Note that the value specified here is adopted automatically from the device configuration of the connected devices. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	
Presence check	Presence-Check	ulong	On	1	R/W	On = As soon as there is a transponder in the antenna field of the reader, its presence is reported. Off = The presence check on the FB is suppressed. The antenna on the reader is nevertheless turned on as long as it has not been turned off by a command.
			Off	0	R/W	
Reset ERR LED	ResetErrorLED	int	On	2	R/W	On = the flashing of the error LED on the communications module is reset by each FB reset. Off = the error LED always indicates the last error. The display can only be reset by turning off the communications module.
			Off	0	R/W	
HF power	RfPower	double	0.50 ... 5.00	<text>	R/W	Setting for the output power of the reader. The selectable values depend on the connected device.

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Max. number of transponders	MaxNoOfTransponders	int	1	<number>	R	Number of transponders expected in the antenna field. The selection depends on the connected device.
Transponder type	TransponderType	int	ISO 15693	1	R	Selection of the transponder types used. The selection depends on the connected device.

Table 4-4 Parameters of the module "RF120C"; parameters of the parameter group "Ident device/system: RF300 general"

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. Note that the value specified here is adopted automatically from the device configuration of the connected devices. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Presence check	Presence-Check	ulong	On	1	R/W	On = As soon as there is a transponder in the antenna field of the reader, its presence is reported. Off (RF field on) = the presence check in the FB is suppressed. The antenna on the reader is nevertheless turned on as long as it has not been turned off by a command. Off (RF field off) = the antenna is turned on only when a command is sent and it then turns itself off again.
			Off (RF field on)	3	R/W	
			Off (RF field off)	2	R/W	
Reset ERR LED	ResetErrorLED	int	On	2	R/W	On = the flashing of the error LED on the communications module is reset by each FB reset. Off = the error LED always indicates the last error. The display can only be reset by turning off the communications module.
			Off	0	R/W	
Max. number of transponders	MaxNoOf-Transponders	int	1	<number>	R	Number of transponders expected in the antenna field. The selection depends on the connected device.
Transponder type	Transponder-Type	int	RF300	5	R/W	Selection of the transponder types used. The selection depends on the connected device.
			ISO 15693	1	R/W	

Table 4-5 Parameters of the module "RF120C"; parameters of the parameter group "Ident device/system: RF380R"

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. Note that the value specified here is adopted automatically from the device configuration of the connected devices. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	
Presence check	Presence-Check	ulong	On	1	R/W	On = As soon as there is a transponder in the antenna field of the reader, its presence is reported. Off (RF field on) = the presence check in the FB is suppressed. The antenna on the reader is nevertheless turned on as long as it has not been turned off by a command. Off (RF field off) = the antenna is turned on only when a command is sent and it then turns itself off again.
			Off (RF field on)	3	R/W	
			Off (RF field off)	2	R/W	
Reset ERR LED	ResetErrorLED	int	On	2	R/W	On = the flashing of the error LED on the communications module is reset by each FB reset. Off = the error LED always indicates the last error. The display can only be reset by turning off the communications module.
			Off	0	R/W	
HF power	RfPower	double	0.50 ... 5.00	<text>	R/W	Setting for the output power of the reader. The selectable values depend on the connected device.

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Max. number of transponders	MaxNoOfTransponders	int	1	<number>	R	Number of transponders expected in the antenna field. The selection depends on the connected device.
Transponder type	TransponderType	int	RF300	5	R/W	Selection of the transponder types used. The selection depends on the connected device.
			ISO 15693	1	R/W	

Table 4-6 Parameters of the module "RF120C"; parameters of the parameter group "Ident device/system: General Reader"

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. Note that the value specified here is adopted automatically from the device configuration of the connected devices. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	
Byte sequence of the reset parameter	ByteSequenceHex	byte[]	[1]	<text>	R/W	Byte sequence of the reset parameter of the reader.

[1] For a detailed description of this parameter, see the following paragraph.

Table 4-7 Parameters of the module "RF120C"; parameters of the parameter group "Ident device/system: Parameters via FB / optical readers"

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. Note that the value specified here is adopted automatically from the device configuration of the connected devices. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	
MOBY mode	MobyMode	ulong	RF200/ RF300/ RF600; MV4x0; MOBY U/D	5	R	With this parameter, you set the mode of the communications module.

The parameter "Byte sequence of the reset parameter"

With this function, you can specify the Reset parameter using a byte array (16). This setting is intended only for trained users.

The following Reset parameters are available:

Table 4-8 Reset parameters

Byte	1	2...5	6	7...8	9	10	11	12	13...14	15	16
Value	0x04	0x00	0x0A	0x00	scanning_ time	param	option_1	distance_ limiting	multitag	field_on_ control	field_on_ time

RF170C

5

The Openness parameters for the "RF170C" module are described below.

Table 5-1 Parameters of the module "RF170C"; parameters of the parameter group "Module parameters"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
User mode	UserMode	ulong	Ident profile/ RFID standard profile	3	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller. • FB 45 / FC 45: Single tag mode FB 45 (PROFIBUS/PROFINET) or FC 45 (PROFIBUS) is used on the controller. • FB 55 / FC 55: Multitag mode. FB 55 (PROFIBUS/PROFINET) or FC 55 (PROFIBUS) is used on the controller.
			FB 45 / FC 45	1	R/W	
			FB 55 / FC 55	4	R/W	

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
MOBY mode	MobyMode	ulong	RF200/RF300/RF600; MV4x0; MOBY U/D	5	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the mode of the communications module. • RF200/RF300/RF600; MV4x0; MOBY U/D • MOBY I/E • MV3xx • Freeport protocol • RF300 filehandler Normal addressing: The transponder is addressed with physical addresses. Filehandler: Prior to use, the transponder needs to be formatted.
			MOBY I/E	1	R/W	
			MV3xx	16	R/W	
			Freeport protocol	17	R/W	
			RF300 filehandler	149	R/W	
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Diagnostics messages	Diagnostic-Messages	int	None	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set whether hardware diagnostics messages will be reported. • None: Apart from standard diagnostics, no other alarms are generated. • Hard errors: Critical hardware errors are reported by the S7 diagnostics.
			Hard errors	2	R/W	
Suppression of Error LED	SuppressionOfErrorLed	int	None	0	R/W	Disabling the Error LED (ERR) of a channel. The communications module has two channels to which the readers / optical readers can be connected. The Error LED of the other channel flashes permanently when only one of the channels is being used. With the help of the suppression, you can disable the Error LED of the unused channel.
			Channel 1	1	R/W	
			Channel 2	2	R/W	
Interface	ModuleInterface	int	RS232	1	R	Selection of the interface type that the connected hardware (reader / optical reader) uses.
			RS422	0	R	

Table 5-2 Parameters of the module "RF170C"; parameters of the parameter group "Freeport protocol"

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Data bits	DataBits	ulong	7	7	R/W	Selection of the number of bits on which a character is represented.
			8	8	R/W	

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Parity	Parity	ulong	None	0	R/W	Parity selection A sequence of data bits can be expanded by a parity bit. With its value "0" or "1", the parity bit is added to the sum of all bits (data bits and parity bits) to form a defined status. This increases data reliability. • None: Data is sent without a parity bit. • Odd: The parity bit is set so that the sum of the data bits (including the parity bit) is odd when the signal state is "1". • Even: The parity bit is set so that the sum of the data bits (including the parity bit) is even when the signal state is "1". • Fixed value 1: The parity bit is set permanently to the value "1". • Fixed value 0: The parity bit is set permanently to the value "0".
			Odd	1	R/W	
			Even	2	R/W	
			Fixed value 1	3	R/W	
			Fixed value 0	7	R/W	
Stop bits	StopBits	ulong	1	1	R/W	Selection of the number of stop bits that indicate the end of a character. The stop bits are appended to every transferred character during transmission.
			2	2	R/W	

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
Specifying end detection	EndDetectionOfAReceivedFrame	ulong	After character delay time elapses	16	R/W	Specifies the end detection of a received frame. • After character delay time elapses: The frame has neither a fixed length nor defined end delimiters. The end of a frame is indicated by a gap in the character sequence. The size of this gap is specified by the character delay time. • On receipt of fixed number of characters: The length of the received frame is always the same. When data is received, the end of the frame is recognized when the set number of characters has been received. • On receipt of the end delimiter(s): At the end of the frame there are one or two defined end delimiters. When data is received, the end of the frame is recognized when the configured end delimiter(s) is/are received.
			On receipt of fixed number of characters	32	R/W	
			On receipt of the end delimiter(s):	49	R/W	
No. of end delimiters	NumberOfEndDelimiters	ulong	1	1	R/W	Selection of the number of end delimiters. A maximum of 2 end delimiters can be configured. When data is received, the end of the frame is recognized when the selected end delimiter combination is received.
			2	2	R/W	
1st end delimiter	FirstEndDelimiterReceiver	ulong	0...7F / 0...FF	<text>	R/W	Entry of the 1st end delimiter of maximum two end delimiters for end criteria "On receipt of the end delimiter(s)". The selected end delimiter or the selected end delimiter combination limits the length of the frame. Parameter value depending on the "Data bits" parameter.

UI parameter	Openness parameter	Data type in Openness	UI parameter value	Openness parameter value	Default access	Description
2nd end delimiter	SecondEndDelimiterReceiver	ulong	0...7F / 0...FF	<text>	R	Entry of the 2nd end delimiter of maximum two end delimiters for end criteria "On receipt of the end delimiter(s)". The selected end delimiter or the selected end delimiter combination limits the length of the frame. Parameter value depending on the "Data bits" parameter.
Frame length	FrameLength	ulong	1...233 / 1...229	<text>	R	Entry of the frame length in bytes for the end criterion "On receipt of fixed number of characters".
Character delay time	CharacterDelayTime	ulong	0...65535	<text>	R	Entry of the time that may elapse until a frame end is recognized. Select the character delay time dependent on the send behavior of your communications partner. Depending on the data transmission speed the character delay time is limited to a minimum value. Note that the ASCII driver also pauses between two telegrams during transmission.

RF180C

6

The Openness parameters for the "RF180C" module are described below.

Table 6-1 Parameters of the module "RF180C"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
User mode	UserMode	ulong	FB 45	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • FB 45: Single tag mode FB 45 (PROFIBUS/PROFINET) is used in the controller. • FB 55: Multitag mode. FB 55 (PROFIBUS/PROFINET) is used on the controller. • FB 56: Multitag mode. FB 56 (PROFIBUS/PROFINET) is used on the controller. • RFID standard profile The program block for the RFID standard profile is used on the controller.
			FB 55	4	R/W	
			FB 56	5	R/W	
			RFID standard profile	3	R/W	

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
MOBY mode	MobyMode	ulong	MOBY I/E normal addressing	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the mode of the communications module. • MOBY I/E normal addressing • MOBY I file handler • RF200/RF300/RF600; MOBY U/D normal addr. • MOBY U file handler • RF300 filehandler Normal addressing: The transponder is addressed with physical addresses. Filehandler: Prior to use, the transponder needs to be formatted.
			MOBY I file handler	129	R/W	
			RF200/RF300/RF600; MV4x0; MOBY U/D normal add.	5	R/W	
			MOBY U file handler	133	R/W	
			RF300 filehandler	149	R/W	
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Diagnostics messages	Diagnostic-Messages	int	None	1	R/W	With this parameter, you set whether hardware diagnostics messages will be reported. • None: Apart from standard diagnostics, no other alarms are generated. • Hard errors: Critical hardware errors are reported by the S7 diagnostics. • Hard/Soft Errors: Critical hardware faults and errors occurring when processing commands are reported by the S7 diagnostics.
			Hard errors	2	R/W	
			Hard/soft errors	4	R/W	
Suppression of Error LED	SuppressionOfErrorLed	int	None	0	R/W	Disabling the Error LED (ERR) of a channel. The communications module has two channels to which the readers / optical readers can be connected. The Error LED of the other channel flashes permanently when only one of the channels is being used. With the help of the suppression, you can disable the Error LED of the unused channel.
			Channel 1	1	R/W	
			Channel 2	2	R/W	

RF166C

7

The Openness parameters for the "RF166C" module are described below.

Table 7-1 Parameters of the module "RF166C"; parameters of the parameter group "Basic parameter"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
User mode	UserMode	ulong	Ident profile/ RFID standard profile	3	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller.

Table 7-2 Parameters of the "RF166C" module; parameters of the submodules of the parameter group "Module parameters"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
CM module						
User mode	UserMode	ulong	FB 45	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • FB 45: Single tag mode FB 45 (PROFIBUS/PROFINET) is used in the controller. • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller.
			Ident profile/ RFID standard profile	3	R/W	

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Reader						
User mode	UserMode	ulong	FB 45	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • FB 45: Single tag mode FB 45 (PROFIBUS/PROFINET) is used in the controller. • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller.
			Ident profile/ RFID standard profile	3	R/W	
MOBY mode	MobyMode	ulong	RF200/RF300/ RF600; MV4x0; MOBY U/D normal add.	5	R	Selection depends on the communications module and Ident system being used. With this parameter, you set the mode of the communications module. • RF200/RF300/RF600; MOBY U/D normal addr. Normal addressing: The transponder is addressed with physical addresses. Filehandler: Prior to use, the transponder needs to be formatted.

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	
Diagnostics messages	Diagnostic-Messages	int	None	1	R/W	With this parameter, you set whether hardware diagnostics messages will be reported. • None: Apart from standard diagnostics, no other alarms are generated. • Hard errors: Critical hardware errors are reported by the S7 diagnostics. • Hard/Soft errors: Critical hardware errors and errors that occur during command processing are reported by the S7 diagnostics.
			Hard errors	2	R/W	
			Hard/soft errors	4	R/W	
RF300						

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
User mode	UserMode	ulong	FB 45	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • FB 45: Single tag mode FB 45 (PROFIBUS/PROFINET) is used in the controller. • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller.
			Ident profile/ RFID standard profile	3	R/W	
Diagnostics messages	Diagnostic-Messages	int	None	1	R/W	With this parameter, you set whether hardware diagnostics messages will be reported. • None: Apart from standard diagnostics, no other alarms are generated. • Hard errors: Critical hardware errors are reported by the S7 diagnostics. • Hard/Soft errors low priority: Critical hardware errors and errors that occur during command processing are reported by the S7 diagnostics.
			Hard errors	2	R/W	
			Hard/soft errors	4	R/W	
RF600						

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
User mode	UserMode	ulong	FB 45	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • FB 45: Single tag mode FB 45 (PROFIBUS/PROFINET) is used in the controller. • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller.
			Ident profile/ RFID standard profile	3	R/W	
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Diagnostics messages	Diagnostic-Messages	int	None	1	R/W	With this parameter, you set whether hardware diagnostics messages will be reported. • None: Apart from standard diagnostics, no other alarms are generated. • Hard errors: Critical hardware errors are reported by the S7 diagnostics. • Hard/Soft errors low priority: Critical hardware errors and errors that occur during command processing are reported by the S7 diagnostics.
			Hard errors	2	R/W	
			Hard/soft errors	4	R/W	

RF18xC/RF18xCI

8

The Openness parameters for the "RF185C/RF186C/RF188C" and the "RF186CI/RF188CI" modules are described below.

Table 8-1 Parameters of the modules "RF18xC/RF18xCI"; parameters of the parameter group "Basic parameter"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
User mode	UserMode	ulong	Ident profile/ RFID standard profile	3	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller.

Table 8-2 Parameters of the "RF18xC/RF18xCI" modules; parameters of the parameter group "Module parameters"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
IID device						
Diagnostic interrupt	Diagnostic-Messages	int	Off	1	R/W	Switching diagnostic messages of the communication modules on and off.
			On	2	R/W	

Table 8-3 Parameters of the "RF185C/RF186C/RF188C" modules; parameters of the submodules of the parameter group "Module parameters"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
CM module						
User mode	UserMode	ulong	FB 45	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • FB 45: Single tag mode FB 45 (PROFIBUS/PROFINET) is used in the controller. • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller.
			Ident profile/ RFID standard profile	3	R/W	
Reader						
User mode	UserMode	ulong	FB 45	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • FB 45: Single tag mode FB 45 (PROFIBUS/PROFINET) is used in the controller. • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller.
			Ident profile/ RFID standard profile	3	R/W	

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
MOBY mode	MobyMode	ulong	RF200/RF300/RF600; MV4x0; MOBY U/D normal add.	5	R	Selection depends on the communications module and Ident system being used. With this parameter, you set the mode of the communications module. • RF200/RF300/RF600; MOBY U/D normal addr. Normal addressing: The transponder is addressed with physical addresses. Filehandler: Prior to use, the transponder needs to be formatted.
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Diagnostics messages	Diagnostic-Messages	int	None	1	R/W	With this parameter, you set whether hardware diagnostics messages will be reported. • None: Apart from standard diagnostics, no other alarms are generated. • Hard errors: Critical hardware errors are reported by the S7 diagnostics. • Hard/Soft Errors: Critical hardware faults and errors occurring when processing commands are reported by the S7 diagnostics.
			Hard errors	2	R/W	
			Hard/soft errors	4	R/W	
IO mode	IIDIoMode	int	Input	2	R/W	With this parameter, you define the mode of the IO interface of the communication module: • Input: Single digital input • Output: Single digital output • IO-Link: Mode for connecting an IO-Link device with digital inputs/outputs.
			Output	3	R/W	
			IO-Link	4	R/W	

Table 8-4 Parameters of the "RF186CI/RF188CI" modules; parameters of the submodules of the parameter group "Module parameters"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
CM module						
User mode	UserMode	ulong	FB 45	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • FB 45: Single tag mode FB 45 (PROFIBUS/PROFINET) is used in the controller. • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller.
			Ident profile/ RFID standard profile	3	R/W	
DI/DO module						
IO mode	IIDIoMode	int	Input	2	R/W	With this parameter, you define the mode of the IO interface of the communication module: • Input: Single digital input • Output: Single digital output • IO-Link: Mode for connecting an IO-Link device with digital inputs/outputs.
			Output	3	R/W	
			IO-Link	4	R/W	
Reader						

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
User mode	UserMode	ulong	FB 45	1	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you select the block: • FB 45: Single tag mode FB 45 (PROFIBUS/PROFINET) is used in the controller. • Ident profile/RFID standard profile: The program block for the Ident profile/RFID standard profile is used on the controller.
			Ident profile/ RFID standard profile	3	R/W	
MOBY mode	MobyMode	ulong	RF200/RF300/ RF600; MV4x0; MOBY U/D normal add.	5	R	Selection depends on the communications module and Ident system being used. With this parameter, you set the mode of the communications module. • RF200/RF300/RF600; MOBY U/D normal addr. Normal addressing: The transponder is addressed with physical addresses. Filehandler: Prior to use, the transponder needs to be formatted.
Transmission speed	BaudRate	ulong	19.2 kBd	9	R/W	Selection depends on the communications module and Ident system being used. With this parameter, you set the transmission speed between the communications module and reader. When the RFID reader is connected: After changing the transmission speed, the reader must be turned off and on again (cycle power). When an optical reader is connected: The transmission speed selected here must match the transmission speed selected in the firmware of the reader.
			57.6 kBd	13	R/W	
			115.2 kBd	14	R/W	

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Diagnostics messages	Diagnostic-Messages	int	None	1	R/W	With this parameter, you set whether hardware diagnostics messages will be reported. • None: Apart from standard diagnostics, no other alarms are generated. • Hard errors: Critical hardware errors are reported by the S7 diagnostics. • Hard/Soft Errors: Critical hardware faults and errors occurring when processing commands are reported by the S7 diagnostics.
			Hard errors	2	R/W	
			Hard/soft errors	4	R/W	

RF61xR/RF68xR

9

The Openness parameters for the "RF61xR/RF68xR" modules are described below.

Table 9-1 Parameters of the modules "RF61xR/RF68xR"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
RFID read points alarm 1	RfidReadPointAlarm1	int	Off	0	R/W	Enabling/disabling read point-related diagnostics messages.
			On	1	R/W	
RFID read points alarm 2	RfidReadPointAlarm2	int	Off	0	R/W	
			On	1	R/W	
RFID read points alarm 3 [1)]	RfidReadPointAlarm3	int	Off	0	R/W	
			On	1	R/W	
RFID read points alarm 4 [1)]	RfidReadPointAlarm4	int	Off	0	R/W	
			On	1	R/W	

[1)] Only with RF680R

MV400/MV500

10

The Openness parameters for the "MV400/MV500" modules are described below.

Table 10-1 Parameters of the modules "MV400/MV500"

Parameters in the configuration (TIA Portal)	Parameters in Openness	Data type in Openness	Parameter value in the configuration (TIA Portal)	Parameter value in Openness	Default access	Description
Function block	FunctionBlock	int	FB79	0	R/W	With this parameter, you select the block: • FB79 Compatible with the "VS130-2" reader; Compatible controllers: S7-300 and S7-400 • Ident profile Complex Ident block with MV-specific blocks; Compatible controllers: S7-300, S7-400, S7-1200 and S7-1500
			Ident profile	1	R/W	

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module						
		Name	String	Name		
		Author	String	Author		
		Comment	String	Comment		
Module - 6GT2 002-0ED00 - V5.0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Name	String			
		DpWatchdog	Boolean	Watchdog activated		
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		DpProtocolMode	UInt64	DP interrupt mode		
					5	S7Compatible
					7	DpV1
					4	DpV0
Module - 6GT2 002-0ED00 - V5.0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0ED00 - V5.0						
		Name	String	Name		
		ShortDesignation	String	Short designation		
		DpProtocolMode	UInt64	DP interrupt mode		
					5	S7Compatible
					7	DpV1
					4	DpV0
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		DpWatchdog	Boolean	Watchdog activated		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
Module						
		Name	String			
		UserMode	UInt64	User Mode		
					3	RfidStandardProfile
					1	Fb45Fc45
					4	Fb55Fc55
					5	Fb56Fc56
		MobyMode	UInt64	MOBY Mode		
					1	MobyIENormalAddressing
					149	RF300FileHandler
					133	MobyUFileHandler
					129	MobyIFileHandler
					5	RF300MobyUDNormalAddressing
		BaudRate	UInt64	Transmission speed		
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
					3	HardOrSoftErrorsLowPriority
					5	HardOrSoftErrorsHighPriority

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		SuppressionOfErrorLed	Int32	Suppression of error LED		
					0	None
					1	Channel1
					2	Channel2
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
Module						
		Name	String			
		UserMode	UInt64	User Mode		
					3	RfidStandardProfile
		MobyMode	UInt64	MOBY Mode		
					32	Rf680rOrRf685r
		BaudRate	UInt64	Transmission speed		
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
					3	HardOrSoftErrorsLowPriority
					5	HardOrSoftErrorsHighPriority
		SuppressionOfErrorLed	Int32	Suppression of error LED		
					0	None
					1	Channel1
					2	Channel2
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
Module						
		Name	String			
		Author	String	Author		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					
	Comment	String	Comment		
	OrderNumber	String	Article number		
	Name	String	Name		
Module					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	OrderNumber	String	Article number		
Module					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
Module					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
Module					
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	Name	String	Name		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Module					
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	Name	String	Name		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	Name	String	Name		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Module					
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	Name	String	Name		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Module					
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	Name	String	Name		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Module					
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	Name	String	Name		
Submodule					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Module - 6GF3420-0A0 - V5.1**					
	Name	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3420-0A**0 - V5.1					
	FunctionBlock	Int32	Function block		
				0	FB79
				1	IdentProfile
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
HeadSubmodule					
	Name	String			
Interface					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Name	String	Name		
	Comment	String	Comment		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	PortActivation	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	TransmissionRateAndDuplex	Int32			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3420-0A**0 - V5.1					
	EndOfSyncDomain	Boolean			
	RingPort	Boolean			
	SignalDelaySelection	Byte[]			
	CableLength	Int32			
	SignalDelayTime	Double			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	AlternativePartnerPorts	Boolean			
	Name	String			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
Module - 6GF3420-0A0 - V5.1**					
	Name	String			
	FunctionBlock	Int32	Function block		
				0	FB79
				1	IdentProfile
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
HeadSubmodule					
	Name	String			
Interface					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3420-0A**0 - V5.1						
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
Module - 6GF3440-*** - V5.1**						
		Name	String			
		FunctionBlock	Int32	Function block		
					0	FB79
					1	IdentProfile
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3440-***** - V5.1						
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	HeadSubmodule					
		Name	String			
	Interface					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3440-***** - V5.1					
	SignalDelayTime	Double			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	AlternativePartnerPorts	Boolean			
	Name	String			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
Module - 6GF3440-*** - V5.1**					
	Name	String			
	FunctionBlock	Int32	Function block		
				0	FB79
				1	IdentProfile
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
HeadSubmodule					
	Name	String			
Interface					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	Label	String			
	InterfaceOperatingModes	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3440-***** - V5.1						
		InterfaceType	Int32			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
Module - 6GF3 540-0CD10 - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3 540-0CD10 - V1.0						
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		FunctionBlock	Int32	Function block		
					0	FB79
					1	IdentProfile
	HeadSubmodule					
		Name	String			
	Interface					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3 540-0CD10 - V1.0						
		AlternativePartnerPorts	Boolean			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
Module - 6GF3 540-0GE10 - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		FunctionBlock	Int32	Function block		
					0	FB79
					1	IdentProfile
	HeadSubmodule					
		Name	String			
	Interface					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3 540-0GE10 - V1.0						
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
Module - 6GF3 540-0HE10 - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		FunctionBlock	Int32	Function block		
					0	FB79

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3 540-0HE10 - V1.0						
					1	IdentProfile
	HeadSubmodule					
		Name	String			
	Interface					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3 540-0HE10 - V1.0						
		PositionNumber	Int32	Slot		
Module - 6GF3 540-0LE10 - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		FunctionBlock	Int32	Function block		
					0	FB79
					1	IdentProfile
	HeadSubmodule					
		Name	String			
	Interface					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3 540-0LE10 - V1.0					
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	TransmissionRateAndDuplex	Int32			
	EndOfSyncDomain	Boolean			
	RingPort	Boolean			
	SignalDelaySelection	Byte[]			
	CableLength	Int32			
	SignalDelayTime	Double			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	AlternativePartnerPorts	Boolean			
	Name	String			
	Name	String	Name		
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
Module - 6GF3 5-***** - V1.0**					
	Name	String			
	FunctionBlock	Int32	Function block		
				0	FB79
				1	IdentProfile
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
HeadSubmodule					
	Name	String			
Interface					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GF3 5**-***** - V1.0						
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		SharedDeviceSendclock	Int32			
		OptionalIoDevice	Boolean			
		NumberOfExternalIoControllers	UInt32			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
Module						
		Name	String			
		Author	String	Author		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					
	Comment	String	Comment		
	Name	String	Name		
Module					
	Name	String	Name		
	Author	String	Author		
	Comment	String	Comment		
Module - 6GT2 002-0EE20 - V1.0					
	InterfaceType	Int32			
	InterfaceOperatingModes	Int32			
	Label	String			
	Name	String			
	DpWatchdog	Boolean	Watchdog activated		
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	StartupIfPresetConfigurationDoesNotMatchActualC	Boolean	Operation if preset configuration does not match actual configuration		
	Name	String	Name		
	PositionNumber	Int32	Slot		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
RF16xC					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Slot		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
	UserMode	UInt64	User mode		
				3	RfidStandardProfile

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		UserMode	UInt64	User mode		
					3	RfidStandardProfile
		BaudRate	UInt64	Transmission speed		
					25	Value1M
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
					4	HardOrSoftErrors
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		OrderNumber	String	Article number		
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		UserMode	UInt64	User Mode		
					3	RfidStandardProfile
					1	Fb45Fc45
		MobyMode	UInt64	MOBY Mode		
					5	RF300MobyUDNormalAddressing
		BaudRate	UInt64	Uebertragungsgeschwindigkeit		
					9	Value19200
					13	Value57600
					14	Value115200
		DiagnosticMessages	Int32	Diagnosemeldungen		
					1	None
					2	HardErrors
					3	HardOrSoftErrorsLowPriority
					5	HardOrSoftErrorsHighPriority
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		UserMode	UInt64	User mode		
					1	Fb45Fc45
					3	RfidStandardProfile
		MobyMode	UInt64	MOBY mode		
					5	RF300MobyUDNormalAddressing
		BaudRate	UInt64	Transmission speed		
					9	Value19200
					13	Value57600

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
					4	HardOrSoftErrors
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		OrderNumber	String	Article number		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		UserMode	UInt64	User Mode		
					3	RfidStandardProfile
		DiagnosticMessages	Int32	Diagnosemeldungen		
					1	None
					2	HardErrors
					3	HardOrSoftErrorsLowPriority
					5	HardOrSoftErrorsHighPriority
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		UserMode	UInt64	User mode		
					3	RfidStandardProfile
		MobyMode	UInt64	MOBY mode		
					32	Rf680rOrRf685r
		BaudRate	UInt64	Transmission speed		
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
					4	HardOrSoftErrors
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		ShortDesignation	String	Short designation		
		UserMode	UInt64	User Mode		
					3	RfidStandardProfile
		BaudRate	UInt64	Uebertragungsgeschwindigkeit		
					14	Value115200
		DiagnosticMessages	Int32	Diagnosemeldungen		
					1	None
					2	HardErrors
					3	HardOrSoftErrorsLowPriority
					5	HardOrSoftErrorsHighPriority
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		OrderNumber	String	Article number		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
Module - 6GT2 002-0JD00 - V2.2					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
RF180C					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	SharedDeviceAccessConfigured	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JD00 - V2.2						
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		EndOfSyncDomain	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Name	String			
		PositionNumber	Int32	Position		
		Comment	String	Comment		
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		UserMode	UInt64	User mode		
					1	Fb45Fc45
					4	Fb55Fc55
					5	Fb56Fc56
					3	RfidStandardProfile
		MobyMode	UInt64	MOBY mode		
					1	MobyIENormalAddressing
					129	MobyIFileHandler
					133	MobyUFileHandler

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JD00 - V2.2						
					149	RF300FileHandler
					5	RF300MobyUDNormalAddressing
		BaudRate	UInt64	Transmission speed		
					9	Value19200
					13	Value57600
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
					4	HardOrSoftErrors
		SuppressionOfErrorLed	Int32	Suppression of Error LED		
					0	None
					1	Channel1
					2	Channel2
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
Module - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		OrderNumber	String	Article number		
		Name	String	Name		
Module						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module - 6GT2 002-0JE10 - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE10 - V1.0						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		UserMode	UInt64	User mode		
					3	RfidStandardProfile
		Author	String	Author		
		Comment	String	Comment		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		UserMode	UInt64	User mode		
					1	Fb45Fc45
					3	RfidStandardProfile
		MobyMode	UInt64	MOBY mode		
					5	RF300MobyUDNormalAddressing
		BaudRate	UInt64	Transmission speed		
					9	Value19200
					13	Value57600
					14	Value115200

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE10 - V1.0						
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
					4	HardOrSoftErrors
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE10 - V1.0					
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
				0	Deactivated
				1	Active
	Author	String	Author		
	Comment	String	Comment		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Module - 6GT2 002-0JE10 - V1.3					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE10 - V1.3						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		UserMode	UInt64	User mode		
					3	RfidStandardProfile
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE10 - V1.3						
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE10 - V1.3						
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
					0	Deactivated
					1	Active
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
Module - 6GT2 002-0JE20 - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		UserMode	UInt64	User mode		
					3	RfidStandardProfile

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE20 - V1.0						
		Author	String	Author		
		Comment	String	Comment		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		UserMode	UInt64	User mode		
					1	Fb45Fc45
					3	RfidStandardProfile
		MobyMode	UInt64	MOBY mode		
					5	RF300MobyUDNormalAddressing
		BaudRate	UInt64	Transmission speed		
					9	Value19200
					13	Value57600
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
					4	HardOrSoftErrors
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE20 - V1.0						
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE20 - V1.0						
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
					0	Deactivated
					1	Active
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
Module - 6GT2 002-0JE20 - V1.3						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE20 - V1.3						
		Name	String			
		UserMode	UInt64	User mode		
					3	RfidStandardProfile
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE20 - V1.3						
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
					0	Deactivated
					1	Active
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
Module - 6GT2 002-0JE50 - V1.1						
		Name	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE50 - V1.1					
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
RF18xC					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	IIDIoMode	Int32	IO mode		
				2	Input
				3	Output
				4	IoLink
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	IIDIoMode	Int32	IO mode		
				2	Input
				3	Output
				4	IoLink
	Author	String	Author		
	Comment	String	Comment		
RF18xC					
	Name	String			
	Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE50 - V1.1						
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		UserMode	UInt64	User mode		
					1	Fb45Fc45
					3	RfidStandardProfile
		MobyMode	UInt64	MOBY mode		
					5	RF300MobyUDNormalAddressing
		BaudRate	UInt64	Transmission speed		
					9	Value19200
					13	Value57600
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
					4	HardOrSoftErrors
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE50 - V1.1						
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE50 - V1.1						
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
					0	Deactivated
					1	Active
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
Module - 6GT2 002-0JE50 - V1.1						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		IIDIoMode	Int32	IO mode		
					2	Input
					3	Output
					4	IoLink

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE50 - V1.1					
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	IIDIoMode	Int32	IO mode		
				2	Input
				3	Output
				4	IoLink
	Author	String	Author		
	Comment	String	Comment		
RF18xC					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	UserMode	UInt64	User mode		
				1	Fb45Fc45
				3	RfidStandardProfile
	MobyMode	UInt64	MOBY mode		
				5	RF300MobyUDNormalAddressing
	BaudRate	UInt64	Transmission speed		
				9	Value19200
				13	Value57600
				14	Value115200
	DiagnosticMessages	Int32	Diagnostic messages		
				1	None
				2	HardErrors
				4	HardOrSoftErrors
	Author	String	Author		
	Comment	String	Comment		
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE50 - V1.1						
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE50 - V1.1						
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
					0	Deactivated
					1	Active
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
Module - 6GT2 002-0JE50 - V1.3						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE50 - V1.3						
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		IIDIoMode	Int32	IO mode		
					2	Input
					3	Output
					4	IoLink
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		IIDIoMode	Int32	IO mode		
					2	Input
					3	Output
					4	IoLink
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE50 - V1.3						
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE50 - V1.3						
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
					0	Deactivated
					1	Active
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
Module - 6GT2 002-0JE40 - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE40 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	UserMode	UInt64	User mode		
				3	RfidStandardProfile
	Author	String	Author		
	Comment	String	Comment		
RF18xC					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	UserMode	UInt64	User mode		
				1	Fb45Fc45
				3	RfidStandardProfile
	MobyMode	UInt64	MOBY mode		
				5	RF300MobyUDNormalAddressing
	BaudRate	UInt64	Transmission speed		
				9	Value19200
				13	Value57600
				14	Value115200
	DiagnosticMessages	Int32	Diagnostic messages		
				1	None
				2	HardErrors
				4	HardOrSoftErrors
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE40 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE40 - V1.0						
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
					0	Deactivated
					1	Active
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
Module - 6GT2 002-0JE40 - V1.3						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF18xC					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE40 - V1.3						
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		UserMode	UInt64	User mode		
					3	RfidStandardProfile
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE40 - V1.3						
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
					0	Deactivated
					1	Active
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE40 - V1.3						
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
Module - 6GT2 002-0JE60 - V1.1						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		IIDIoMode	Int32	IO mode		
					2	Input
					3	Output
					4	IoLink
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		IIDIoMode	Int32	IO mode		
					2	Input
					3	Output
					4	IoLink
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE60 - V1.1						
		Comment	String	Comment		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		UserMode	UInt64	User mode		
					1	Fb45Fc45
					3	RfidStandardProfile
		MobyMode	UInt64	MOBY mode		
					5	RF300MobyUDNormalAddressing
		BaudRate	UInt64	Transmission speed		
					9	Value19200
					13	Value57600
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
					4	HardOrSoftErrors
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE60 - V1.1						
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE60 - V1.1						
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
					0	Deactivated
					1	Active
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
Module - 6GT2 002-0JE60 - V1.1						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE60 - V1.1					
	IIDIoMode	Int32	IO mode		
				2	Input
				3	Output
				4	IoLink
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	IIDIoMode	Int32	IO mode		
				2	Input
				3	Output
				4	IoLink
	Author	String	Author		
	Comment	String	Comment		
RF18xC					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	UserMode	UInt64	User mode		
				1	Fb45Fc45
				3	RfidStandardProfile
	MobyMode	UInt64	MOBY mode		
				5	RF300MobyUDNormalAddressing
	BaudRate	UInt64	Transmission speed		
				9	Value19200
				13	Value57600
				14	Value115200
	DiagnosticMessages	Int32	Diagnostic messages		
				1	None
				2	HardErrors

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE60 - V1.1						
					4	HardOrSoftErrors
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE60 - V1.1						
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
					0	Deactivated
					1	Active
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
Module - 6GT2 002-0JE60 - V1.3						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE60 - V1.3						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF18xC					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		IIDIoMode	Int32	IO mode		
					2	Input
					3	Output
					4	IoLink
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		IIDIoMode	Int32	IO mode		
					2	Input
					3	Output
					4	IoLink
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE60 - V1.3						
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE60 - V1.3						
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostic interrupt		
					0	Deactivated
					1	Active
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		UserMode	UInt64	User mode		
					3	RfidStandardProfile
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		UserMode	UInt64	User mode		
					3	RfidStandardProfile

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0JE60 - V1.3					
	Author	String	Author		
	Comment	String	Comment		
Module					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	UserMode	UInt64	User mode		
				3	RfidStandardProfile
				1	Fb45Fc45
	MobyMode	UInt64	MOBY mode		
				17	FreeportProtocol
	BaudRate	UInt64	Transmission speed		
				9	Value19200
				13	Value57600
				14	Value115200
	DiagnosticMessages	Int32	Diagnostic messages		
				1	None
				2	HardErrors
				4	HardOrSoftErrors
	Parity	UInt64	Parity		
				0	None
				2	Even
				1	Odd
				3	FixedValue1
				7	FixedValue0
	DataBits	UInt64	Data bits		
				7	Value7
				8	Value8

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					
	StopBits	UInt64	Stop bits		
				1	Value1
				2	Value2
	ModuleInterface	Int32	Interface		
				0	Rs422
				1	Rs232
	EndDetectionOfAReceivedFrame	UInt64	End detection		
				49	OnReceiptOfTheEndDelimiters
				32	OnReceiptOfFixedNumberOfCharacters
				16	AfterCharacterDelayTimeElapses
	NumberOfEndDelimiters	UInt64	No. of end delimiters		
				1	Value1
				2	Value2
	FirstEndDelimiterReceiver	UInt64	1st end delimiter		
	SecondEndDelimiterReceiver	UInt64	2nd end delimiter		
	FrameLength	UInt64	Frame length		
	CharacterDelayTime	UInt64	Character delay time		
Module					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	UserMode	UInt64	User mode		
				3	RfidStandardProfile
	BaudRate	UInt64	Transmission speed		
				25	Value1M
	DiagnosticMessages	Int32	Diagnostic messages		
				1	None
				2	HardErrors
				4	HardOrSoftErrors

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
Module - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
Module - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
Module - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		OrderNumber	String	Article number		
		Name	String	Name		
Module - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		OrderNumber	String	Article number		
		Name	String	Name		
Module						

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		IECV22LLDPMode	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module						
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Name	String	Name		
Module - 6GT2 801-5BA30 - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	RF36xR					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		UserMode	UInt64	User mode		
					1	Fb45Fc45
					3	RfidStandardProfile
		DiagnosticMessages	Int32	Diagnostic interrupt		
					1	None
					2	HardErrors
					4	HardOrSoftErrors
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 801-5BA30 - V1.0						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 801-5BA30 - V1.0						
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - V1.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		OrderNumber	String	Article number		
		Name	String	Name		
Module						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module - 6GT2 811-6BC10-2AA0 - V3.2						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group1					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		IECV22LLDPMode	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6BC10-2AA0 - V3.2						
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6BC10-2AA0 - V3.2						
		Author	String	Author		
		Comment	String	Comment		
Module - 6GT2 811-6BC10-2AA0 - V3.2						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group1					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6BC10-2AA0 - V3.2						
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
Module - 6GT2 811-6BC10-0AA0 - V3.2						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6BC10-0AA0 - V3.2						
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group1					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6BC10-0AA0 - V3.2					
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Module - 6GT2 811-6BC10-0AA0 - V3.2					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group1					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	Comment	String	Comment		
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6BC10-0AA0 - V3.2						
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6BC10-0AA0 - V3.2					
				1	On
	Author	String	Author		
	Comment	String	Comment		
Module - 6GT2 811-6BC10-1AA0 - V3.2					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group1					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6BC10-1AA0 - V3.2						
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
Module - 6GT2 811-6BC10-1AA0 - V3.2						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6BC10-1AA0 - V3.2						
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group1					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6BC10-1AA0 - V3.2						
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
Module - 6GT2 811-6CC10-2AA0 - V3.2						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-2AA0 - V3.2					
Group1					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-2AA0 - V3.2						
		PositionNumber	Int32	PositionNumber		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
Module - 6GT2 811-6CC10-2AA0 - V3.2						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Group1					
		Name	String			
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-2AA0 - V3.2						
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-2AA0 - V3.2					
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Module - 6GT2 811-6CC10-2AA0 - V3.2					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	Comment	String	Comment		
Group1					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-2AA0 - V3.2						
		Name	String			
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-2AA0 - V3.2					
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Module - 6GT2 811-6CC10-0AA0 - V3.2					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	Comment	String	Comment		
Group1					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	Comment	String	Comment		
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-0AA0 - V3.2						
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-0AA0 - V3.2					
				1	On
	Author	String	Author		
	Comment	String	Comment		
Module - 6GT2 811-6CC10-0AA0 - V3.2					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	Comment	String	Comment		
Group1					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-0AA0 - V3.2					
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-0AA0 - V3.2						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Group1					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-0AA0 - V3.2					
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Module - 6GT2 811-6CC10-1AA0 - V3.2					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-1AA0 - V3.2						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Group1					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-1AA0 - V3.2					
	Comment	String	Comment		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Module - 6GT2 811-6CC10-1AA0 - V3.2					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-1AA0 - V3.2						
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Group1					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-1AA0 - V3.2					
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Module - 6GT2 811-6CC10-1AA0 - V3.2					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	OrderNumber	String	Article number		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-1AA0 - V3.2						
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Group1					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CC10-1AA0 - V3.2					
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Module - V1.0					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	OrderNumber	String	Article number		
	Name	String	Name		
Module					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
Module - 6GT2 811-6AA10-0AA0 - V1.0					
	Name	String			
	Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V1.0					
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V1.0					
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V1.0						
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
Module - 6GT2 811-6AA10-0AA0 - V1.0						
		Name	String			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V1.0						
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V1.0					
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
Module - 6GT2 811-6AA10-0AA0 - V2.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V2.0					
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V2.0						
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6AA10-0AA0 - V2.0						
		Name	String			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V2.0						
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6AA10-0AA0 - V3.0						
		Name	String			
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V3.0						
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V3.0						
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-0AA0 - V3.0					
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - 6GT2 811-6AA10-4AA0 - V2.2					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-4AA0 - V2.2						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-4AA0 - V2.2						
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6AA10-4AA0 - V2.2						
		Name	String			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-4AA0 - V2.2						
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-4AA0 - V2.2						
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6AA10-4AA0 - V3.0						
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-4AA0 - V3.0						
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-4AA0 - V3.0					
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-4AA0 - V3.0					
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - 6GT2 811-6CA10-4AA0 - V2.2					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-4AA0 - V2.2						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-4AA0 - V2.2						
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6CA10-4AA0 - V2.2						
		Name	String			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-4AA0 - V2.2						
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-4AA0 - V2.2						
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6CA10-4AA0 - V3.0						
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-4AA0 - V3.0						
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-4AA0 - V3.0					
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-4AA0 - V3.0						
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6AA10-1AA0 - V1.0						
		Name	String			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-1AA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-1AA0 - V1.0						
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
Module - 6GT2 811-6AA10-1AA0 - V1.0						
		Name	String			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-1AA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
Group1						
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
Submodules						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
Submodules						
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-1AA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
Module - 6GT2 811-6AA10-1AA0 - V2.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-1AA0 - V2.0						
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-1AA0 - V2.0					
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - 6GT2 811-6AA10-1AA0 - V2.0					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-1AA0 - V2.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-1AA0 - V2.0					
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-1AA0 - V2.0					
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - 6GT2 811-6AA10-1AA0 - V3.0					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-1AA0 - V3.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
Submodules						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
Submodules						
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-1AA0 - V3.0					
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - 6GT2 811-6AA10-2AA0 - V1.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-2AA0 - V1.0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-2AA0 - V1.0					
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
Module - 6GT2 811-6AA10-2AA0 - V1.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-2AA0 - V1.0						
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-2AA0 - V1.0						
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-2AA0 - V2.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-2AA0 - V2.0					
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-2AA0 - V2.0					
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - 6GT2 811-6AA10-2AA0 - V2.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-2AA0 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-2AA0 - V2.0					
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - 6GT2 811-6AA10-2AA0 - V3.0					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-2AA0 - V3.0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6AA10-2AA0 - V3.0						
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6CA10-0AA0 - V1.0						

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V1.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V1.0					
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V1.0						
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
Module - 6GT2 811-6CA10-0AA0 - V1.0						
		Name	String			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V1.0					
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V1.0					
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
Module - 6GT2 811-6CA10-0AA0 - V2.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
Submodules						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
Submodules						
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V2.0						
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6CA10-0AA0 - V2.0						
		Name	String			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V2.0						
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V2.0						
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6CA10-0AA0 - V3.0						

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V3.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V3.0						
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-0AA0 - V3.0					
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - 6GT2 811-6CA10-1AA0 - V1.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-1AA0 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-1AA0 - V1.0					
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
Module - 6GT2 811-6CA10-1AA0 - V1.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-1AA0 - V1.0					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-1AA0 - V1.0						
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
Module - 6GT2 811-6CA10-1AA0 - V2.0						
		Name	String			
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-1AA0 - V2.0					
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-1AA0 - V2.0						
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-1AA0 - V2.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-1AA0 - V2.0					
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-1AA0 - V2.0						
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6CA10-1AA0 - V3.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-1AA0 - V3.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-1AA0 - V3.0					
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - 6GT2 811-6CA10-2AA0 - V1.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-2AA0 - V1.0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-2AA0 - V1.0					
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
Module - 6GT2 811-6CA10-2AA0 - V1.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-2AA0 - V1.0						
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Group1					
		Name	String			
		Comment	String	Comment		
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-2AA0 - V1.0						
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-2AA0 - V2.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-2AA0 - V2.0					
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-2AA0 - V2.0					
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - 6GT2 811-6CA10-2AA0 - V2.0					
	Name	String			
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		
	AdditionalInformation	String	Additional information		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	FirmwareVersion	String	Firmware version		
Group0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-2AA0 - V2.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
	Submodules					
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		RfidReadPointAlarm1	Int32	RFID read point alarm 1		
					0	Off
					1	On
		RfidReadPointAlarm2	Int32	RFID read point alarm 2		
					0	Off
					1	On
		RfidReadPointAlarm3	Int32	RFID read point alarm 3		
					0	Off
					1	On
		RfidReadPointAlarm4	Int32	RFID read point alarm 4		
					0	Off
					1	On
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		IECV22LLDPMode	Boolean			
		PrioritizedStartup	Boolean			
		OptionalIoDevice	Boolean			
		SharedDeviceSendclock	Int32			
		NumberOfExternalIoControllers	UInt32			
		SharedDeviceAccessConfigured	Boolean			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			
		Label	String			
		InterfaceOperatingModes	Int32			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-2AA0 - V2.0						
		InterfaceType	Int32			
		Name	String			
		Comment	String	Comment		
		Name	String	Name		
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		SharedDeviceAccessConfigured	Boolean			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	PositionNumber		
		Name	String	Name		
Module - 6GT2 811-6CA10-2AA0 - V3.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
	Group0					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-2AA0 - V3.0					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Group1					
	Name	String			
	Comment	String	Comment		
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
Submodules					
	SharedDeviceAccessConfigured	Boolean			
	Name	String			
	RfidReadPointAlarm1	Int32	RFID read point alarm 1		
				0	Off
				1	On
	RfidReadPointAlarm2	Int32	RFID read point alarm 2		
				0	Off
				1	On
	RfidReadPointAlarm3	Int32	RFID read point alarm 3		
				0	Off
				1	On
	RfidReadPointAlarm4	Int32	RFID read point alarm 4		
				0	Off
				1	On
	Author	String	Author		
	Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 811-6CA10-2AA0 - V3.0					
Submodules					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	OptionalIoDevice	Boolean			
	SharedDeviceSendclock	Int32			
	NumberOfExternalIoControllers	UInt32			
	SharedDeviceAccessConfigured	Boolean			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Comment	String	Comment		
	Name	String	Name		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	SharedDeviceAccessConfigured	Boolean			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	PositionNumber		
	Name	String	Name		
Module - V1.0					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - V1.0						
		Name	String			
		Name	String	Name		
		Author	String	Author		
		Comment	String	Comment		
		OrderNumber	String	Article number		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0LA00 - V1.0					
	Name	String			
	BaudRate	UInt64	Transmission speed		
				9	Value19200
				13	Value57600
				14	Value115200
	PresenceCheck	UInt64	Presence check		
				3	OffRfFieldOn
				1	On
				2	OffRfFieldOff
				0	Off
	ResetErrorLED	Int32	Reset ERR LED		
				0	Off
				2	On
	MaxNoOfTransponders	Int32	Max. no. of transponders		
	TransponderType	Int32	Transponder type		
				5	Rf300
				1	Iso15693
				0	ICode
	DiagnosticMessages	Int32	Diagnostic messages		
				1	None
				2	HardErrors
	UserMode	UInt64	User mode		
				3	RfidStandardProfile
	RfPower	Double	RF power		
	ByteSequenceHex	Byte[]	Input box for byte sequence (hexadecimal notation)		
	MobyMode	UInt64	MOBY mode		
				5	RF300MobyUDNormalAddressing
	Author	String	Author		
	Comment	String	Comment		
	FirmwareVersion	String	Firmware version		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0LA00 - V1.0						
		AdditionalInformation	String	Additional information		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		TypeName	String	InvariantTypeName		
	Submodule					
		Name	String			
		Name	String	Name		
		Comment	String	Comment		
		PositionNumber	Int32	Index		
Module - 6GT2 002-0LA00 - V2.0						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		UserMode	UInt64	User mode		
					3	RfidStandardProfile
		MobyMode	UInt64	MOBY mode		
					5	RF300MobyUDNormalAddressing
					17	FreeportProtocol
					16	Mv3xx
					49	Rf1000
		BaudRate	UInt64	Transmission speed		
					9	Value19200
					13	Value57600

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0LA00 - V2.0						
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
		ModuleInterface	Int32	Interface		
					0	Rs422
					1	Rs232
		DataBits	UInt64	Data bits		
					7	Value7
					8	Value8
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
		StopBits	UInt64	Stop bits		
					1	Value1
					2	Value2
		EndDetectionOfAReceivedFrame	UInt64	End detection of a received frame		
					49	OnReceiptOfTheEndDelimiters
					32	OnReceiptOfFixedNumberOfCharacters
					16	AfterCharacterDelayTimeElapses
		NumberOfEndDelimiters	UInt64	No. of end delimiters		
					1	Value1
					2	Value2
		FirstEndDelimiterReceiver	UInt64	1st end delimiter		
		SecondEndDelimiterReceiver	UInt64	2nd end delimiter		
		FrameLength	UInt64	Frame length		
		CharacterDelayTime	UInt64	Character delay time		
	Submodule					
		Name	String			
		Name	String	Name		
		Comment	String	Comment		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2002-0HD00 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		UserMode	UInt64	User mode		
					1	Fb45Fc45
					4	Fb55Fc55
					5	Fb56Fc56
					3	RfidStandardProfile
		MobyMode	UInt64	MOBY mode		
					1	MobyIENormalAddressing
					5	RF300MobyUDNormalAddressing
					129	MobyIFileHandler
					133	MobyUFileHandler
		BaudRate	UInt64	Transmission speed		
					9	Value19200
					13	Value57600
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
		TypeName	String	InvariantTypeName		
Module - 6GT2002-0HD00 - V1.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2002-0HD00 - V1.0						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		UserMode	UInt64	User mode		
					1	Fb45Fc45
					4	Fb55Fc55
		MobyMode	UInt64	MOBY mode		
					1	MobyIENormalAddressing
					5	RF300MobyUDNormalAddressing
					129	MobyIFileHandler
					133	MobyUFileHandler
		BaudRate	UInt64	Transmission speed		
					9	Value19200
					13	Value57600
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
Module - 6GT2 002-0HD01 - V3.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0HD01 - V3.0					
	UserMode	UInt64	User mode		
				3	RfidStandardProfile
				1	Fb45Fc45
				4	Fb55Fc55
	MobyMode	UInt64	MOBY mode		
				1	MobyIENormalAddressing
				17	FreeportProtocol
				149	RF300FileHandler
				5	RF300MobyUDNormalAddressing
				16	Mv3xx
	BaudRate	UInt64	Transmission speed		
				9	Value19200
				13	Value57600
				14	Value115200
	DiagnosticMessages	Int32	Diagnostic messages		
				1	None
				2	HardErrors
	SuppressionOfErrorLed	Int32	Suppression of Error LED		
				0	None
				1	Channel1
				2	Channel2
	ModuleInterface	Int32	Interface		
				0	Rs422
				1	Rs232
	DataBits	UInt64	Data bits		
				7	Value7
				8	Value8
	Parity	UInt64	Parity		
				0	None
				2	Even
				1	Odd
				3	FixedValue1
				7	FixedValue0

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0HD01 - V3.0						
		StopBits	UInt64	Stop bits		
					1	Value1
					2	Value2
		EndDetectionOfAReceivedFrame	UInt64	End detection of a received frame		
					49	OnReceiptOfTheEndDelimiters
					32	OnReceiptOfFixedNumberOfCharacters
					16	AfterCharacterDelayTimeElapses
		NumberOfEndDelimiters	UInt64	No. of end delimiters		
					1	Value1
					2	Value2
		FirstEndDelimiterReceiver	UInt64	1st end delimiter		
		SecondEndDelimiterReceiver	UInt64	2nd end delimiter		
		FrameLength	UInt64	Frame length		
		CharacterDelayTime	UInt64	Character delay time		
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
Module - 6GT2 002-0HD01 - V3.0						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DataBits	UInt64	Data bits		
					7	Value7

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0HD01 - V3.0						
					8	Value8
		Parity	UInt64	Parity		
					0	None
					2	Even
					1	Odd
					3	FixedValue1
					7	FixedValue0
		StopBits	UInt64	Stop bits		
					1	Value1
					2	Value2
		EndDetectionOfAReceivedFrame	UInt64	End detection of a received frame		
					49	OnReceiptOfTheEndDelimiters
					32	OnReceiptOfFixedNumberOfCharacters
					16	AfterCharacterDelayTimeElapses
		NumberOfEndDelimiters	UInt64	No. of end delimiters		
					1	Value1
					2	Value2
		FirstEndDelimiterReceiver	UInt64	1st end delimiter		
		SecondEndDelimiterReceiver	UInt64	2nd end delimiter		
		FrameLength	UInt64	Frame length		
		CharacterDelayTime	UInt64	Character delay time		
		UserMode	UInt64	User mode		
					3	RfidStandardProfile
					1	Fb45Fc45
					4	Fb55Fc55
		MobyMode	UInt64	MOBY mode		
					1	MobyIENormalAddressing
					17	FreeportProtocol
					149	RF300FileHandler
					5	RF300MobyUDNormalAddressing
					16	Mv3xx
		BaudRate	UInt64	Transmission speed		
					9	Value19200
					13	Value57600

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0HD01 - V3.0						
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors
		SuppressionOfErrorLed	Int32	Suppression of Error LED		
					0	None
					1	Channel1
					2	Channel2
		ModuleInterface	Int32	Interface		
					0	Rs422
					1	Rs232
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
Module - 6GT2 002-0HD01 - V3.1						
		SharedDeviceAccessConfigured	Boolean			
		Name	String			
		DataBits	UInt64	Data bits		
					7	Value7
					8	Value8
		Parity	UInt64	Parity		
					0	None

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0HD01 - V3.1						
					2	Even
					1	Odd
					3	FixedValue1
					7	FixedValue0
		StopBits	UInt64	Stop bits		
					1	Value1
					2	Value2
		EndDetectionOfAReceivedFrame	UInt64	End detection of a received frame		
					49	OnReceiptOfTheEndDelimiters
					32	OnReceiptOfFixedNumberOfCharacters
					16	AfterCharacterDelayTimeElapses
		NumberOfEndDelimiters	UInt64	No. of end delimiters		
					1	Value1
					2	Value2
		FirstEndDelimiterReceiver	UInt64	1st end delimiter		
		SecondEndDelimiterReceiver	UInt64	2nd end delimiter		
		FrameLength	UInt64	Frame length		
		CharacterDelayTime	UInt64	Character delay time		
		SuppressionOfErrorLed	Int32	Suppression of Error LED		
					0	None
					1	Channel1
					2	Channel2
		ModuleInterface	Int32	Interface		
					0	Rs422
					1	Rs232
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	Slot		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		ShortDesignation	String	Short designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6GT2 002-0HD01 - V3.1						
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		StartupComparisonPresetToActualModule	UInt64	Comparison preset to actual module		
					0	FromCpu
					1	StartupCpuOnlyIfCompatible
					2	StartupCpuIfMismatch
		UserMode	UInt64	User mode		
					3	RfidStandardProfile
					1	Fb45Fc45
					4	Fb55Fc55
		MobyMode	UInt64	MOBY mode		
					1	MobyIENormalAddressing
					17	FreeportProtocol
					149	RF300FileHandler
					5	RF300MobyUDNormalAddressing
					16	Mv3xx
		BaudRate	UInt64	Transmission speed		
					9	Value19200
					13	Value57600
					14	Value115200
		DiagnosticMessages	Int32	Diagnostic messages		
					1	None
					2	HardErrors

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	TypeName	String	InvariantTypeName		
Module - 6AV3 688-3EH47-0AX0 - V01.00.00					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
Submodule					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	PositionNumber	Int32	Slot		
Module - 6AV3 688-3AY36-0AX0 - R01.00.00					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		
	FirmwareVersion	String	Firmware version		
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	PositionNumber	Int32	Slot		
Submodule					
	Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AV3 688-3AY36-0AX0 - R01.00.00					
	Name	String	Name		
	ShortDesignation	String	Short designation		
	PositionNumber	Int32	Slot		
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	DurationOfLightTest	UInt64	Duration of light test		
	Brightness	UInt64	Brightness		
				63	VeryBright
				50	Bright
				25	Medium
				10	Dark
				1	VeryDark
Submodule					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	PositionNumber	Int32	Slot		
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
Module - 6AV3 688-3AF37-0AX0 - R01.00.00					
	Author	String	Author		
	Comment	String	Comment		
	Name	String	Name		
	ShortDesignation	String	Short designation		
	TypeName	String	InvariantTypeName		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Slot		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AV3 688-3AF37-0AX0 - R01.00.00						
		FirmwareVersion	String	Firmware version		
	Submodule					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		PositionNumber	Int32	Slot		
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		DurationOfLightTest	UInt64	Duration of light test		
		Brightness	UInt64	Brightness		
					63	VeryBright
					50	Bright
					25	Medium
					10	Dark
					1	VeryDark
		Terminal0Function	UInt64	Terminal 0 function (IO.0)		
					0	Input
					1	Output
		Terminal1Function	UInt64	Terminal 1 function (IO.1)		
					0	Input
					1	Output
		Terminal2Function	UInt64	Terminal 2 function (IO.2)		
					0	Input
					1	Output
		Terminal3Function	UInt64	Terminal 3 function (IO.3)		
					0	Input
					1	Output
		Terminal4Function	UInt64	Terminal 4 function (IO.4)		
					0	Input
					1	Output

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AV3 688-3AF37-0AX0 - R01.00.00						
		Terminal5Function	UInt64	Terminal 5 function (IO.5)		
					0	Input
					1	Output
		Terminal6Function	UInt64	Terminal 6 function (IO.6)		
					0	Input
					1	Output
		Terminal7Function	UInt64	Terminal 7 function (IO.7)		
					0	Input
					1	Output
	Submodule					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		PositionNumber	Int32	Slot		
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		Failsafe_FBlockID	UInt64	F_Block_ID		
		Failsafe_FParVersion	UInt64	F_Par_Version		
		Failsafe_FDestinationAddress	UInt64	F_Dest_Add		
		Failsafe_FMonitoringtime	UInt64	F_WD_Time		
		Failsafe_FParameterSignatureIndividualParameters	UInt64	F_iPar_CRC		
		Failsafe_FParameterSignatureWithAddresses	UInt64	F_Par_CRC		
		Failsafe_FCheckSeqNr	UInt64	F_Check_SeqNr		
		Failsafe_F_CRC_Length	UInt64	F_CRC_Length		
					0	ThreeByteCRC
		Failsafe_FSourceAddress	UInt64	F_Source_Add		
		Failsafe_FParameterSignatureWithoutAddresses	UInt64	F_Par_CRC_WithoutAddresses		
		Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
					0	Automatic
					1	Manual

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AV3 688-3AF37-0AX0 - R01.00.00					
	Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
	Failsafe_FIODBName	String	F-I/O DB-name		
	Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
	Failsafe_FSIL	UInt64	F_SIL		
				2	SIL3
	EncoderEvaluation	UInt64	Encoder evaluation		
				257	FDisabledDisabled
				54228	F1oo2
				54229	F1oo1
Submodule					
	IECV22LLDPMode	Boolean			
	PrioritizedStartup	Boolean			
	SharedDeviceSendclock	Int32			
	OptionalIoDevice	Boolean			
	NumberOfExternalIoControllers	UInt32			
	MediaRedundancyRole	UInt64			
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	Index		
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	RingPort	Boolean			
	CableName	UInt64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 6AV3 688-3AF37-0AX0 - R01.00.00						
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	PositionNumber		
	Submodule					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		PositionNumber	Int32	Index		
		PlantDesignation	String	Plant designation		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		LocationIdentifier	String	Location identifier		
Module						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		PositionNumber	Int32	Slot		
	Submodule					
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		Failsafe_FBlockID	UInt64	F_Block_ID		
		Failsafe_FParVersion	UInt64	F_Par_Version		
		Failsafe_FDestinationAddress	UInt64	F_Dest_Add		
		Failsafe_FMonitoringtime	UInt64	F_WD_Time		
		Failsafe_FParameterSignatureIndividualParameters	UInt64	F_iPar_CRC		
		Failsafe_FParameterSignatureWithAddresses	UInt64	F_Par_CRC		
		Failsafe_FCheckSeqNr	UInt64	F_Check_SeqNr		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Failsafe_F_CRC_Length	UInt64	F_CRC_Length		
					0	ThreeByteCRC
		Failsafe_FSourceAddress	UInt64	F_Source_Add		
		Failsafe_FParameterSignatureWithoutAddresses	UInt64	F_Par_CRC_WithoutAddresses		
		Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
					0	Automatic
					1	Manual
		Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
		Failsafe_FIODBName	String	F-I/O DB-name		
		Failsafe_ManualAssignmentFMonitoringtime	UInt64	Manual assignment of F-monitoring time		
		Failsafe_FSIL	UInt64	F_SIL		
					2	SIL3
		EncoderEvaluation	UInt64	Encoder evaluation		
					257	FDisabledDisabled
					33924	F1oo1Disabled
					54227	F1oo2Disabled
					21588	F1oo21oo2
					19018	F1oo21oo1
					39064	F1oo11oo1
Module - V1.0						
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		Name	String	Name		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		
		TypeName	String	InvariantTypeName		
Module - V1.0						
		Author	String	Author		
		Comment	String	Comment		
		ShortDesignation	String	Short designation		
		Name	String	Name		
		OrderNumber	String	Article number		
		PositionNumber	Int32	Index		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - V1.0					
	TypeName	String	InvariantTypeName		
Module - V1.0					
	Author	String	Author		
	Comment	String	Comment		
	ShortDesignation	String	Short designation		
	Name	String	Name		
	OrderNumber	String	Article number		
	PositionNumber	Int32	Index		
	TypeName	String	InvariantTypeName		
Submodule					
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	RingPort	Boolean			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	Comment	String	Comment		
	Name	String	Name		
	PositionNumber	Int32	PositionNumber		
Submodule					
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	PortActivation	Boolean			
	AlternativePartnerPorts	Boolean			
	TransmissionRateAndDuplex	Int32			
	RingPort	Boolean			
	CableName	UInt64			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - V1.0						
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	PositionNumber		
	Submodule					
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		PortActivation	Boolean			
		AlternativePartnerPorts	Boolean			
		TransmissionRateAndDuplex	Int32			
		RingPort	Boolean			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		Comment	String	Comment		
		Name	String	Name		
		PositionNumber	Int32	PositionNumber		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3UF7 330-1A*00-0						
		Author	String	Author		
		Comment	String	Comment		
		FirmwareVersion	String	Firmware version		
		Failsafe_FParameterSignatureWithoutAddresses	UInt64	F-parameter signature (without addresses)		
		Failsafe_DIPSwitchSetting	String	DIP-switch setting (9.....0)		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		Failsafe_FParVersion	UInt64	PROFIsafe mode		
					0	V1mode
					1	V2mode
		Failsafe_FMonitoringtime	UInt64	F-monitoring time		
		Failsafe_FDestinationAddress	UInt64	F-destination address		
		Failsafe_FParameterSignatureWithAddresses	UInt64	F-parameter signature (with addresses)		
		Failsafe_BehaviorAfterChannelFault	UInt64	Behavior after channel fault		
					0	PassivateTheEntireModule
					1	PassivateChannel
		Failsafe_ManualAssignmentFIODBNumber	UInt64	F-I/O DB manual number assignment		
					0	Automatic
					1	Manual
		Failsafe_FIODBNumber	UInt64	F-I/O DB-number		
		Failsafe_FIODBName	String	F-I/O DB-name		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Extension modules 3UF7 * **						
		TypeName	String	InvariantTypeName		
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		PositionNumber	Int32	Position number		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0 - any Version**						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Name	String			
		DpWatchdog	Boolean	Watchdog activated		
		SimocodeMarkingInstallationDate	DateTime	Installation date		
		TimeRangeForStarts	UInt32	Time range for starts		
		Author	String	Author		
		Comment	String	Comment		
		SimocodeMarkingPlantIdentifier	String	Plant identifier		
		SimocodeMarkingLocationDesignation	String	Location designation		
		SimocodeMarkingDescription	String	Description		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
		OverwriteIpParameters	Boolean	Overwrite IP parameters in device		
		Network.Address	String	IP address		
		Network.SubnetMask	String	Subnet mask		
		Network.UseRouter	Boolean	Use router		
		Network.RouterAddress	String	Address (gateway)		
		OverwriteDeviceNames	Boolean	Overwrite device name in device		
		OpcUaServer	Boolean	OPC UA server activated		
		WebserverActivate	Boolean	Web server activated		
		WebserverUsername	String	Username		
		TimeSynchronizationNtp	Boolean	Activate NTP synchronization		
		TimeSynchronizationServer1	String	NTP server address		
		TimeSynchronizationTimeShift	Int32	Time shift		
		TimeSynchronizationInterval	Double	Cyclic update interval		
		DiagnosticsTriggeredByDeviceFaults	Boolean	Diagnostics triggered by device faults		
		DiagnosticsTriggeredByTrips	Boolean	Diagnostics triggered by trips		
		DiagnosticsTriggeredByWarnings	Boolean	Diagnostics triggered by warnings		
		DiagnosticsTriggeredByEvents	Boolean	Diagnostics triggered by events		
		StartupParameterBlock	Boolean	Startup parameter block		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		Thermistor	Boolean	Thermistor		
		VoltageDisplay	UInt32	Voltage display		
					0	PhaseVoltage
					1	LineToLineVoltage
		InitializationModule	Boolean	Initialization module		
		ConfigurationErrorDueToMissingOperatorPanel	Boolean	Configuration error due to missing operator panel		
					0	Yes
					1	No
		ApplicationControlFunction	UInt32	Application (control function)		
					0	OverloadRelay
					16	DirectStarter
					17	ReversingStarter
					18	MoldedCaseCircuitBreaker
					32	StarDeltaStarter
					112	SoftStarter
					33	StarDeltaReversingStarter
					48	DahlanderStarter
					49	DahlanderReversingStarter
					64	PoleChangingStarter
					65	PoleChangingReversingStarter
					80	SolenoidValve
					96	Positioner1
					97	Positioner2
					98	Positioner3
					99	Positioner4
					100	Positioner5
					113	SoftStarterWithReversingContactor
		MotorProtectionReset	UInt32	Reset		
					0	Manual
					1	Auto
		MotorProtectionSetCurrentIs1	Double	Set current Is1		
		MotorProtectionIs1TransformationRatioActive	Boolean	Transformation ratio - active		
		MotorProtectionIs1TransformationRatioPrimary	Double	Transformation ratio - primary		
		MotorProtectionIs1TransformationRatioSecondary	UInt32	Transformation ratio - secondary		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		MotorProtectionSetCurrentIs2	Double	Set current Is2		
		MotorProtectionIs2TransformationRatioActive	Boolean	Transformation ratio - active		
		MotorProtectionIs2TransformationRatioPrimary	Double	Transformation ratio - primary		
		MotorProtectionIs2TransformationRatioSecondary	UInt32	Transformation ratio - secondary		
		MotorProtectionClass	UInt32	Class		
					5	Value5
					7	Value7
					10	Value10
					15	Value15
					20	Value20
					25	Value25
					30	Value30
					35	Value35
					40	Value40
		MotorProtectionResponseToTripLevel	UInt32	Response to trip level		
					0	Deactivated
					1	Signal
					2	Warn
					3	Trip
		MotorProtectionCoolingDownPeriod	Double	Cooling down period		
		MotorProtectionPauseTime	Double	Pause time		
		MotorProtectionTypeOfLoad	UInt32	Type of load		
					1	OnePhase
					0	TriPhase
		MotorProtectionResponseToPrewarning	UInt32	Response to prewarning level (I>115%Is)		
					1	Signal
					2	Warn
					0	Deactivated
		MotorProtectionDelayPrewarning	Double	Delay prewarning (I>115%Is)		
		MotorProtectionUnbalanceLevel	UInt32	Level		
		MotorProtectionUnbalanceResponse	UInt32	Response		
					3	Trip
					2	Warn
					1	Signal

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					0	Deactivated
		MotorProtectionUnbalanceDelay	Double	Delay		
		MotorProtectionStalledRotorLevel	UInt32	Level		
		MotorProtectionStalledRotorResponse	UInt32	Response		
					3	Trip
					2	Warn
					1	Signal
					0	Deactivated
		MotorProtectionStalledRotorDelay	Double	Delay		
		ThermistorResponseToTripLevel	UInt32	Response to trip level		
					3	Trip
					2	Warn
					1	Signal
		ThermistorResponseToSensorFault	UInt32	Response to sensor fault		
					3	Trip
					2	Warn
					1	Signal
					0	Deactivated
		DryRunningProtectionBehavior	UInt32	Behavior		
					3	Trip
					0	Deactivated
		DryRunningProtectionTripLevel	Double	Trip Level		
		DryRunningProtectionDelay	Double	Delay		
		DryRunningProtectionStartUpDelay	Double	Start-up bridging time		
		ControlStationModeSelectorS1	UInt32			
		ControlStationModeSelectorS2	UInt32			
		ControlStationLocalControlLocal1On	Boolean	Local 1 ON		
		ControlStationLocalControlLocal1Off	Boolean	Local 1 OFF		
		ControlStationLocalControlLocal2On	Boolean	Local 2 ON		
		ControlStationLocalControlLocal2Off	Boolean	Local 2 OFF		
		ControlStationLocalControlLocal3On	Boolean	Local 3 ON		
		ControlStationLocalControlLocal3Off	Boolean	Local 3 OFF		
		ControlStationLocalControlRemoteOn	Boolean	Remote ON		
		ControlStationLocalControlRemoteOff	Boolean	Remote OFF		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		ControlStationLocalControlReverseFast	UInt32			
		ControlStationLocalControlReverse	UInt32			
		ControlStationLocalControlOff	UInt32			
		ControlStationLocalControlForward	UInt32			
		ControlStationLocalControlForwardFast	UInt32			
		ControlStationPLCPCSLocal1On	Boolean	Local 1 ON		
		ControlStationPLCPCSLocal1Off	Boolean	Local 1 OFF		
		ControlStationPLCPCSLocal2On	Boolean	Local 2 ON		
		ControlStationPLCPCSLocal2Off	Boolean	Local 2 OFF		
		ControlStationPLCPCSLocal3On	Boolean	Local 3 ON		
		ControlStationPLCPCSLocal3Off	Boolean	Local 3 OFF		
		ControlStationPLCPCSRemoteOn	Boolean	Remote ON		
		ControlStationPLCPCSRemoteOff	Boolean	Remote OFF		
		ControlStationPLCPCSReverseFast	UInt32			
		ControlStationPLCPCSReverse	UInt32			
		ControlStationPLCPCSOff	UInt32			
		ControlStationPLCPCSForward	UInt32			
		ControlStationPLCPCSForwardFast	UInt32			
		ControlStationPCLocal1On	Boolean	Local 1 ON		
		ControlStationPCLocal1Off	Boolean	Local 1 OFF		
		ControlStationPCLocal2On	Boolean	Local 2 ON		
		ControlStationPCLocal2Off	Boolean	Local 2 OFF		
		ControlStationPCLocal3On	Boolean	Local 3 ON		
		ControlStationPCLocal3Off	Boolean	Local 3 OFF		
		ControlStationPCRemoteOn	Boolean	Remote ON		
		ControlStationPCRemoteOff	Boolean	Remote OFF		
		ControlStationPCReverseFast	UInt32			
		ControlStationPCReverse	UInt32			
		ControlStationPCOff	UInt32			
		ControlStationPCForward	UInt32			
		ControlStationPCForwardFast	UInt32			
		ControlStationOPLocal1On	Boolean	Local 1 ON		
		ControlStationOPLocal1Off	Boolean	Local 1 OFF		
		ControlStationOPLocal2On	Boolean	Local 2 ON		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		ControlStationOPLocal2Off	Boolean	Local 2 OFF		
		ControlStationOPLocal3On	Boolean	Local 3 ON		
		ControlStationOPLocal3Off	Boolean	Local 3 OFF		
		ControlStationOPRemoteOn	Boolean	Remote ON		
		ControlStationOPRemoteOff	Boolean	Remote OFF		
		ControlStationOPReverseFast	UInt32			
		ControlStationOPReverse	UInt32			
		ControlStationOPOff	UInt32			
		ControlStationOPForward	UInt32			
		ControlStationOPForwardFast	UInt32			
		NonMaintainedCommandMode	Boolean	Non-maintained command mode		
		SaveChangeOverCommand	Boolean	Save change-over command		
		DMFLocalProfisafeSeparateFunctionFromControlFu	Boolean	DM-F LOCAL/PROFIsafe - Separate function from control function		
		TypeOfConsumerLoad	UInt32	Type of consumer load		
					0	Motor
					1	ResistiveLoad
		ControlFunctionReverseFast	UInt32	ON<<		
		ControlFunctionReverse	UInt32			
		ControlFunctionOFF	UInt32			
		ControlFunctionForward	UInt32			
		ControlFunctionForwardFast	UInt32	ON>>		
		ControlFunctionFeedbackON	UInt32	Feedback ON		
		ControlFunctionFeedbackCLOSEDFC	UInt32	Feedback CLOSED (FC)		
		ControlFunctionFeedbackOPENFO	UInt32	Feedback OPEN (FO)		
		ControlFunctionTorqueCLOSEDTC	UInt32	Torque CLOSED (TC)		
		ControlFunctionTorqueOPENTO	UInt32	Torque OPEN (TO)		
		ControlFunctionFeedbackFBTime	Double	Feedback (FB) time		
		ControlFunctionExecutionTime	Double	Execution time		
		ControlFunctionInterlockingTime	Double	Interlocking time		
		ControlFunctionChangeOverPause	Double	Change-over pause		
		ControlFunctionMaxStarTime	UInt32	Max. star time		
		ControlFunctionCurrentMeasuringModuleInstalled	UInt32	Current measuring module installed		
					1	IncomingCable
					0	Delta

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		AMHysteresisPercentOfThreshold	UInt32			
		AM1UpperTripLevel	Double	Trip level		
		AM1UpperTripLevelActiveStatus	UInt32	Trip level active status		
					3	IfMotorIsRunningExceptTpfWithStartupOverride
					2	IfMotorIsRunningExceptTpf
					1	AlwaysExceptWithTpfOn
					0	AlwaysOn
		AM1UpperTripLevelResponse	UInt32	Response to trip level		
					3	Trip
					1	Signal
					0	Deactivated
		AM1UpperTripDelay	Double	Trip delay		
		AM1MarkingTripLevelGt	String	Marking trip level		
		AM1UpperWarningLevel	Double	Warning level		
		AM1UpperWarningLevelActiveStatus	UInt32	Warning level active status		
					3	IfMotorIsRunningExceptTpfWithStartupOverride
					2	IfMotorIsRunningExceptTpf
					1	AlwaysExceptWithTpfOn
					0	AlwaysOn
		AM1UpperWarningLevelResponse	UInt32	Response to warning level		
					2	Warn
					1	Signal
					0	Deactivated
		AM1UpperWarningDelay	Double	Warning delay		
		AM1MarkingWarningLevelGt	String	Marking warning level		
		AM1LowerTripLevel	Double	Trip level		
		AM1LowerTripLevelActiveStatus	UInt32	Trip level active status		
					3	IfMotorIsRunningExceptTpfWithStartupOverride
					2	IfMotorIsRunningExceptTpf
					1	AlwaysExceptWithTpfOn
					0	AlwaysOn
		AM1LowerTripLevelResponse	UInt32	Response to trip level		
					0	Deactivated
					1	Signal

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					3	Trip
		AM1LowerTripDelay	Double	Trip delay		
		AM1MarkingTripLevelLt	String	Marking trip level		
		AM1LowerWarningLevel	Double	Warning level		
		AM1LowerWarningLevelActiveStatus	UInt32	Warning level active status		
					0	AlwaysOn
					1	AlwaysExceptWithTpfOn
					2	IfMotorIsRunningExceptTpf
					3	IfMotorIsRunningExceptTpfWithStartupOverride
		AM1LowerWarningLevelResponse	UInt32	Response to warning level		
					0	Deactivated
					1	Signal
					2	Warn
		AM1LowerWarningDelay	Double	Warning delay		
		AM1MarkingWarningLevelLt	String	Marking warning level		
		AM2UpperTripLevel	Double	Trip level		
		AM2UpperTripLevelActiveStatus	UInt32	Trip level active status		
					3	IfMotorIsRunningExceptTpfWithStartupOverride
					2	IfMotorIsRunningExceptTpf
					1	AlwaysExceptWithTpfOn
					0	AlwaysOn
		AM2UpperTripLevelResponse	UInt32	Response to trip level		
					3	Trip
					1	Signal
					0	Deactivated
		AM2UpperTripDelay	Double	Trip delay		
		AM2MarkingTripLevelGt	String	Marking trip level		
		AM2UpperWarningLevel	Double	Warning level		
		AM2UpperWarningLevelActiveStatus	UInt32	Warning level active status		
					3	IfMotorIsRunningExceptTpfWithStartupOverride
					2	IfMotorIsRunningExceptTpf
					1	AlwaysExceptWithTpfOn
					0	AlwaysOn

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		AM2UpperWarningLevelResponse	UInt32	Response to warning level		
					0	Deactivated
					1	Signal
					2	Warn
		AM2UpperWarningDelay	Double	Warning delay		
		AM2MarkingWarningLevelGt	String	Marking warning level		
		AM2LowerTripLevel	Double	Trip level		
		AM2LowerTripLevelActiveStatus	UInt32	Trip level active status		
					3	IfMotorIsRunningExceptTpfWithStartupOverride
					2	IfMotorIsRunningExceptTpf
					1	AlwaysExceptWithTpfOn
					0	AlwaysOn
		AM2LowerTripLevelResponse	UInt32	Response to trip level		
					3	Trip
					1	Signal
					0	Deactivated
		AM2LowerTripDelay	Double	Trip delay		
		AM2MarkingTripLevelLt	String	Marking trip level		
		AM2LowerWarningLevel	Double	Warning level		
		AM2LowerWarningLevelActiveStatus	UInt32	Warning level active status		
					0	AlwaysOn
					1	AlwaysExceptWithTpfOn
					2	IfMotorIsRunningExceptTpf
					3	IfMotorIsRunningExceptTpfWithStartupOverride
		AM2LowerWarningLevelResponse	UInt32	Response to warning level		
					2	Warn
					1	Signal
					0	Deactivated
		AM2LowerWarningDelay	Double	Warning delay		
		AM2MarkingWarningLevelLt	String	Marking warning level		
		TMHysteresisForTemperature	UInt32	Hysteresis for temperature		
		TM1TripLevel	Double	Trip level T>		
		TM1TripLevelMarking	String	Marking trip level T>		
		TM1WarningLevel	Double	Warning level T>		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		TM1WarningLevelMarking	String	Marking warning level T>		
		TM2TripLevel	Double	Trip level T>		
		TM2TripLevelResponse	UInt32	Response to trip level T>		
					3	Trip
					1	Signal
		TM2TripLevelMarking	String	Marking trip level T>		
		TM2WarningLevel	Double	Warning level T>		
		TM2WarningLevelResponse	UInt32	Response to warning level T>		
					2	Warn
					1	Signal
					0	Deactivated
		TM2WarningLevelMarking	String	Marking warning level T>		
		CurrentLimitsUpperTripLevel	UInt32	Trip level		
		CurrentLimitsUpperTripLevelResponse	UInt32	Response to trip level		
					0	Deactivated
					1	Signal
					3	Trip
		CurrentLimitsUpperTripDelay	Double	Trip delay		
		CurrentLimitsUpperWarningLevel	UInt32	Warning level		
		CurrentLimitsUpperWarningLevelResponse	UInt32	Response to warning level		
					2	Warn
					1	Signal
					0	Deactivated
		CurrentLimitsUpperWarningDelay	Double	Warning delay		
		CurrentLimitsLowerTripLevel	UInt32	Trip level		
		CurrentLimitsLowerTripLevelResponse	UInt32	Response to trip level		
					0	Deactivated
					1	Signal
					3	Trip
		CurrentLimitsLowerTripDelay	Double	Trip delay		
		CurrentLimitsLowerWarningLevel	UInt32	Warning level		
		CurrentLimitsLowerWarningLevelResponse	UInt32	Response to warning level		
					2	Warn
					1	Signal

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					0	Deactivated
		CurrentLimitsLowerWarningDelay	Double	Warning delay		
		HysteresisForCurrentLimits	UInt32	Hysteresis for current limits		
		VoltageLowerTripLevel	UInt32	Trip level		
		TripLevelActiveStatus	UInt32	Trip level active status		
					0	AlwaysOn
					1	AlwaysExceptWithTpfOn
					2	IfMotorIsRunningExceptTpf
		VoltageLowerTripLevelResponse	UInt32	Response to trip level		
					0	Deactivated
					1	Signal
					3	Trip
		VoltageLowerTripDelay	Double	Trip delay		
		VoltageLowerWarningLevel	UInt32	Warning level		
		VoltageLowerWarningLevelActiveStatus	UInt32	Warning level active status		
					0	AlwaysOn
					1	AlwaysExceptWithTpfOn
					2	IfMotorIsRunningExceptTpf
		VoltageLowerWarningLevelResponse	UInt32	Response to warning level		
					2	Warn
					1	Signal
					0	Deactivated
		VoltageLowerWarningDelay	Double	Warning delay		
		VoltageTypeOfLoadForVoltageCosPhiAndPower	UInt32	Type of load for gathering of voltage, Cos-Phi, power		
					0	TriPhase
					1	OnePhase
		VoltageHysteresisForVoltageCosPhiAndPower	UInt32	Hysteresis for voltage, Cos-Phi, power		
		CosPhiLowerTripLevel	UInt32	Trip level		
		CosPhiLowerTripLevelResponse	UInt32	Response to trip level		
					3	Trip
					1	Signal
					0	Deactivated
		CosPhiLowerTripDelay	Double	Trip delay		
		CosPhiLowerWarningLevel	UInt32	Warning level		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		CosPhiLowerWarningLevelResponse	UInt32	Response to warning level		
					2	Warn
					1	Signal
					0	Deactivated
		CosPhiLowerWarningDelay	Double	Warning delay		
		ActivePowerUpperTripLevel	Double	Trip level		
		ActivePowerUpperResponseToTripLevel	UInt32	Response to trip level		
					0	Deactivated
					1	Signal
					3	Trip
		ActivePowerUpperTripDelay	Double	Trip delay		
		ActivePowerUpperWarningLevel	Double	Warning level		
		ActivePowerUpperWarningLevelResponse	UInt32	Response to warning level		
					0	Deactivated
					1	Signal
					2	Warn
		ActivePowerUpperWarningDelay	Double	Warning delay		
		ActivePowerLowerTripLevel	Double	Trip level		
		ActivePowerLowerTripLevelResponse	UInt32	Response to trip level		
					0	Deactivated
					1	Signal
					3	Trip
		ActivePowerLowerTripDelay	Double	Trip delay		
		ActivePowerLowerWarningLevel	Double	Warning level		
		ActivePowerLowerWarningLevelResponse	UInt32	Response to warning level		
					0	Deactivated
					1	Signal
					2	Warn
		ActivePowerLowerWarningDelay	Double	Warning delay		
		OperatingHoursMonitoringLevel	UInt32	Level		
		OperatingHoursMonitoringResponse	UInt32	Response		
					2	Warn
					1	Signal
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		StopTimeOperatingHoursMonitoringLevel	UInt32	Level		
		StopTimeOperatingHoursMonitoringResponse	UInt32	Response		
					2	Warn
					1	Signal
					0	Deactivated
		PermissibleStarts	UInt32	Permissible starts		
		ResponseToOvershoot	UInt32	Response to overshoot		
					3	Trip
					2	Warn
					1	Signal
					0	Deactivated
		ResponseToPrewarning	UInt32	Response to prewarning		
					2	Warn
					1	Signal
					0	Deactivated
		TimeRangeForStartsHours	UInt32	Hours		
		TimeRangeForStartsMinutes	UInt32	Minutes		
		TimeRangeForStartsSeconds	UInt32	Seconds		
		PermissibleStartsInterlockingTimeHours	UInt32	Hours		
		PermissibleStartsInterlockingTimeMinutes	UInt32	Minutes		
		PermissibleStartsInterlockingTimeSeconds	UInt32	Seconds		
		TestInterval	UInt32	Test interval		
		TestResponse	UInt32	Response		
					0	Deactivated
					1	Signal
					2	Warn
		InternalGroundFaultTripLevel	UInt32	Trip level		
		InternalGroundFaultTripResponse	UInt32	Response		
					0	Deactivated
					1	Signal
					3	Trip
					2	Warn
		InternalGroundFaultTripDelay	Double	Delay		
		InternalGroundFaultWarningLevel	UInt32	Warning level		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		InternalGroundFaultWarningResponse	UInt32	Response to warning level		
					0	Deactivated
					1	Signal
					2	Warn
		InternalGroundFaultWarningDelay	Double	Delay		
		InternalGroundFaultHysteresis	UInt32	Hysteresis		
		EMGroundFaultResponse	UInt32	Response		
					0	Signal
					9	Warn
					3	Trip
		EMGroundFaultDelay	UInt32	Delay		
		EMTripLevel	Double	Trip level		
		EMTripLevelActiveStatus	UInt32	Active status of trip level		
					0	AlwaysOn
					2	IfMotorIsRunningExceptTpf
					3	IfMotorIsRunningExceptTpfWithStartupOverride
		EMTripLevelResponse	UInt32	Response to trip level		
					0	Signal
					3	Trip
		EMTripDelay	Double	Delay		
		EMWarningLevel	Double	Warning level		
		EMWarningActiveStatus	UInt32	Active status of warning level		
					0	AlwaysOn
					2	IfMotorIsRunningExceptTpf
					3	IfMotorIsRunningExceptTpfWithStartupOverride
		EMWarningLevelResponse	UInt32	Response to warning level		
					0	Deactivated
					1	Signal
					2	Warn
		EMWarningDelay	Double	Delay		
		EMGroundFaultHysteresis	UInt32	Hysteresis		
		EMGroundFaultSensorFaultResponse	UInt32	Response to sensor fault		
					0	Deactivated
					1	Signal

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					2	Warn
					3	Trip
		BasicUnitInputsDebouncingTimes	UInt32	Debouncing times		
					0	Value6
					1	Value16
					2	Value26
					3	Value36
		DMInputsDebouncingTimes	UInt32			
					0	Value6
					1	Value16
					2	Value26
					3	Value36
		AM1InputsInputSignal	UInt32	Input signal		
					0	Value0To20ma
					1	Value4To20ma
		AM1InputsResponseToOpenCircuit	UInt32	Response to open circuit		
					0	Signal
					2	Warn
					3	Trip
		AM1InputsActiveInputs	UInt32	Active inputs		
					0	Value1Input
					1	Value2Inputs
		TM1InputsSensorType	UInt32	Sensor type		
					0	Pt100
					1	Pt1000
					2	Kty83
					3	Kty84
					4	Ntc
		TM1InputsResponseToSensorFaultOutOfRange	UInt32	Response to sensor fault/ Out of Range		
					0	Deactivated
					1	Signal
					2	Warn
					3	Trip

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		TM1InputsActiveSensors	UInt32	Active sensors		
					0	Value1Sensor
					1	Value2Sensors
					2	Value3Sensors
		AM2InputsInputSignal	UInt32	Input signal		
					0	Value0To20ma
					1	Value4To20ma
		AM2InputsResponseToOpenCircuit	UInt32	Response to open circuit		
					0	Signal
					2	Warn
					3	Trip
		AM2InputsActiveInputs	UInt32	Active inputs		
					0	Value1Input
					1	Value2Inputs
		TM2InputsSensorType	UInt32	Sensor type		
					0	Pt100
					1	Pt1000
					2	Kty83
					3	Kty84
					4	Ntc
		TM2InputsResponseToSensorFaultOutOfRange	UInt32	Response to sensor fault/ Out of Range		
					3	Trip
					2	Warn
					1	Signal
					0	Deactivated
		TM2InputsActiveSensors	UInt32	Active sensors		
					2	Value3Sensors
					1	Value2Sensors
					0	Value1Sensor
		BasicUnitOutput1	UInt32	BU - output 1		
		BasicUnitOutput2	UInt32	BU - output 2		
		BasicUnitOutput3	UInt32	BU - output 3		
		OPLEDGreen1	UInt32	LED green 1		
		OPLEDGreen2	UInt32	LED green 2		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		OPLEDGreen3	UInt32	LED green 3		
		OPLEDGreen4	UInt32	LED green 4		
		OPLEDYellow1	UInt32	LED yellow 1		
		OPLEDYellow2	UInt32	LED yellow 2		
		OPLEDYellow3	UInt32	LED yellow 3		
		DM1Output1	UInt32	DM - output 1		
		DM1Output2	UInt32	DM - output 2		
		DM2Output1	UInt32	DM - output 1		
		DM2Output2	UInt32	DM - output 2		
		AM1OutputsOutputSignal	UInt32	Output signal		
					1	Value4To20ma
					0	Value0To20ma
		AM1OutputsStartValueOfValueRange	UInt32	Start value of value range		
		AM1OutputsEndValueOfValueRange	UInt32	End value of value range		
		AM1OutputsAssignedAnalogOutputValue	UInt32	Assigned analog output value		
		AM2OutputsOutputSignal	UInt32	Output signal		
					1	Value4To20ma
					0	Value0To20ma
		AM2OutputsStartValueOfValueRange	UInt32	Start value of value range		
		AM2OutputsEndValueOfValueRange	UInt32	End value of value range		
		AM2OutputsAssignedAnalogOutputValue	UInt32	Assigned analog output value		
		CyclicSendDataByte0Bit0	UInt32	Bit 0.0		
		CyclicSendDataByte0Bit1	UInt32	Bit 0.1		
		CyclicSendDataByte0Bit2	UInt32	Bit 0.2		
		CyclicSendDataByte0Bit3	UInt32	Bit 0.3		
		CyclicSendDataByte0Bit4	UInt32	Bit 0.4		
		CyclicSendDataByte0Bit5	UInt32	Bit 0.5		
		CyclicSendDataByte0Bit6	UInt32	Bit 0.6		
		CyclicSendDataByte0Bit7	UInt32	Bit 0.7		
		CyclicSendDataByte1Bit0	UInt32	Bit 1.0		
		CyclicSendDataByte1Bit1	UInt32	Bit 1.1		
		CyclicSendDataByte1Bit2	UInt32	Bit 1.2		
		CyclicSendDataByte1Bit3	UInt32	Bit 1.3		
		CyclicSendDataByte1Bit4	UInt32	Bit 1.4		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		CyclicSendDataByte1Bit5	UInt32	Bit 1.5		
		CyclicSendDataByte1Bit6	UInt32	Bit 1.6		
		CyclicSendDataByte1Bit7	UInt32	Bit 1.7		
		CyclicSendDataAnalogValuesByte2to3	UInt32	Byte 2/3 (analog value)		
		CyclicSendDataAnalogValuesByte4to5	UInt32	Input 1: "Byte 4/5"		
		CyclicSendDataAnalogValuesByte6to7	UInt32	Input 2: "Byte 6/7"		
		CyclicSendDataAnalogValuesByte8to9	UInt32	Input 3: "Byte 8/9"		
		CyclicSendDataAnalogValuesByte10to11	UInt32	Input 1: "Byte 10/11"		
		CyclicSendDataAnalogValuesByte12to13	UInt32	Input 2: "Byte 12/13"		
		CyclicSendDataAnalogValuesByte14to15	UInt32	Input 3: "Byte 14/15"		
		CyclicSendDataAnalogValuesByte16to17	UInt32	Input 4: "Byte 16/17"		
		CyclicSendDataAnalogValuesByte18to19	UInt32	Input 5: "Byte 18/19"		
		CyclicSendDataFloatValuesByte2to5	UInt32	Byte 2-5		
					51	ActivePowerPbSignedInverted
					50	ActivePowerPaSigned
					15	FrequencyHz
					14	CosPhi
					13	LineToLineVoltageUl3L1
					18	PhaseVoltageUl3N
					12	LineToLineVoltageUl2L3
					17	PhaseVoltageUl2N
					11	LineToLineVoltageUl1L2
					16	PhaseVoltageUl1N
					10	ApparentPowerS
					9	ActivePowerP
					8	CurrentIL3
					7	CurrentIL2
					6	CurrentIL1
					5	AverageCurrentI
					4	MaxCurrentI
					0	NotConnected
		CyclicSendDataFloatValuesByte6to9	UInt32	Byte 6-9		
					0	NotConnected
					4	MaxCurrentI

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					5	AverageCurrentI
					6	CurrentIL1
					7	CurrentIL2
					8	CurrentIL3
					9	ActivePowerP
					10	ApparentPowerS
					16	PhaseVoltageUl1N
					11	LineToLineVoltageUl1L2
					17	PhaseVoltageUl2N
					12	LineToLineVoltageUl2L3
					18	PhaseVoltageUl3N
					13	LineToLineVoltageUl3L1
					14	CosPhi
					15	FrequencyHz
					50	ActivePowerPaSigned
					51	ActivePowerPbSignedInverted
		CyclicSendDataFloatValuesByte10to13	UInt32	Byte 10-13		
					0	NotConnected
					4	MaxCurrentI
					5	AverageCurrentI
					6	CurrentIL1
					7	CurrentIL2
					8	CurrentIL3
					9	ActivePowerP
					10	ApparentPowerS
					16	PhaseVoltageUl1N
					11	LineToLineVoltageUl1L2
					17	PhaseVoltageUl2N
					12	LineToLineVoltageUl2L3
					18	PhaseVoltageUl3N
					13	LineToLineVoltageUl3L1
					14	CosPhi
					15	FrequencyHz
					50	ActivePowerPaSigned

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					51	ActivePowerPbSignedInverted
		CyclicSendDataFloatValuesByte14to17	UInt32	Byte 14-17		
					0	NotConnected
					4	MaxCurrentI
					5	AverageCurrentI
					6	CurrentIL1
					7	CurrentIL2
					8	CurrentIL3
					9	ActivePowerP
					10	ApparentPowerS
					16	PhaseVoltageUl1N
					11	LineToLineVoltageUl1L2
					17	PhaseVoltageUl2N
					12	LineToLineVoltageUl2L3
					18	PhaseVoltageUl3N
					13	LineToLineVoltageUl3L1
					14	CosPhi
					15	FrequencyHz
					50	ActivePowerPaSigned
					51	ActivePowerPbSignedInverted
		AcyclicSendDataByte0Bit0	UInt32	Bit 0.0		
		AcyclicSendDataByte0Bit1	UInt32	Bit 0.1		
		AcyclicSendDataByte0Bit2	UInt32	Bit 0.2		
		AcyclicSendDataByte0Bit3	UInt32	Bit 0.3		
		AcyclicSendDataByte0Bit4	UInt32	Bit 0.4		
		AcyclicSendDataByte0Bit5	UInt32	Bit 0.5		
		AcyclicSendDataByte0Bit6	UInt32	Bit 0.6		
		AcyclicSendDataByte0Bit7	UInt32	Bit 0.7		
		AcyclicSendDataByte1Bit0	UInt32	Bit 1.0		
		AcyclicSendDataByte1Bit1	UInt32	Bit 1.1		
		AcyclicSendDataByte1Bit2	UInt32	Bit 1.2		
		AcyclicSendDataByte1Bit3	UInt32	Bit 1.3		
		AcyclicSendDataByte1Bit4	UInt32	Bit 1.4		
		AcyclicSendDataByte1Bit5	UInt32	Bit 1.5		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		AcyclicSendDataByte1Bit6	UInt32	Bit 1.6		
		AcyclicSendDataByte1Bit7	UInt32	Bit 1.7		
		TestResetKeysDisabled	Boolean	Test/Reset keys disabled		
		Test1Input	UInt32	Test 1 - input		
		Test2Input	UInt32	Test 2 - input		
		Reset1Input	UInt32	Reset 1 - input		
		Reset2Input	UInt32	Reset 2 - input		
		Reset3Input	UInt32	Reset 3 - input		
		TestPositionFeedbackTPFStandardFunctionsType	UInt32	Type		
					1	NCContact
					0	NOContact
		TestPositionFeedbackTPFInput	UInt32	Test Position Feedback (TPF) - input		
		ExternalFault1Input	UInt32	External fault 1 - input		
		ExternalFault1Reset	UInt32	External fault 1 - reset		
		ExternalFault1Response	UInt32	Response		
					3	Trip
					2	Warn
					0	Signal
		ExternalFault1Type	UInt32	Type		
					1	NcContact
					0	NoContact
		ExternalFault1ActiveStatus	UInt32	Active status		
					1	OnlyWhenMotorOn
					0	Always
		ExternalFault1ResetAlsoByTestResetButtonRS232	Boolean	Test/reset button, RS-232 (panel reset)		
		ExternalFault1ResetAlsoByAutoReset	Boolean	Auto reset		
		ExternalFault1ResetAlsoByRemoteReset123	Boolean	Remote reset, reset 1,2,3		
		ExternalFault1ResetAlsoByOffCommandReset	Boolean	Off command reset		
		ExternalFault1Marking	String	Marking		
		ExternalFault2Input	UInt32	External fault 2 - input		
		ExternalFault2Reset	UInt32	External fault 2 - reset		
		ExternalFault2Response	UInt32	Response		
					3	Trip
					2	Warn

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					0	Signal
		ExternalFault2Type	UInt32	Type		
					1	NcContact
					0	NoContact
		ExternalFault2ActiveStatus	UInt32	Active status		
					1	OnlyWhenMotorOn
					0	Always
		ExternalFault2ResetAlsoByTestResetButtonRS232	Boolean	Test/reset button, RS-232 (panel reset)		
		ExternalFault2ResetAlsoByAutoReset	Boolean	Auto reset		
		ExternalFault2ResetAlsoByRemoteReset123	Boolean	Remote reset, reset 1,2,3		
		ExternalFault2ResetAlsoByOffCommandReset	Boolean	Off command reset		
		ExternalFault2Marking	String	Marking		
		ExternalFault3Input	UInt32	External fault 3 - input		
		ExternalFault3Reset	UInt32	External fault 3 - reset		
		ExternalFault3Response	UInt32	Response		
					3	Trip
					2	Warn
					0	Signal
		ExternalFault3Type	UInt32	Type		
					1	NcContact
					0	NoContact
		ExternalFault3ActiveStatus	UInt32	Active status		
					0	Always
					1	OnlyWhenMotorOn
		ExternalFault3ResetAlsoByTestResetButtonRS232	Boolean	Test/reset button, RS-232 (panel reset)		
		ExternalFault3ResetAlsoByAutoReset	Boolean	Auto reset		
		ExternalFault3ResetAlsoByRemoteReset123	Boolean	Remote reset, reset 1,2,3		
		ExternalFault3ResetAlsoByOffCommandReset	Boolean	Off command reset		
		ExternalFault3Marking	String	Marking		
		ExternalFault4Input	UInt32	External fault 4 - input		
		ExternalFault4Reset	UInt32	External fault 4 - reset		
		ExternalFault4Response	UInt32	Response		
					3	Trip
					2	Warn

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					0	Signal
		ExternalFault4Type	UInt32	Type		
					0	NoContact
					1	NcContact
		ExternalFault4ActiveStatus	UInt32	Active status		
					0	Always
					1	OnlyWhenMotorOn
		ExternalFault4ResetAlsoByTestResetButtonRS232	Boolean	Test/reset button, RS-232 (panel reset)		
		ExternalFault4ResetAlsoByAutoReset	Boolean	Auto reset		
		ExternalFault4ResetAlsoByRemoteReset123	Boolean	Remote reset, reset 1,2,3		
		ExternalFault4ResetAlsoByOffCommandReset	Boolean	Off command reset		
		ExternalFault4Marking	String	Marking		
		ExternalFault5Input	UInt32	External fault 5 - input		
		ExternalFault5Reset	UInt32	External fault 5 - reset		
		ExternalFault5Response	UInt32	Response		
					3	Trip
					2	Warn
					0	Signal
		ExternalFault5Type	UInt32	Type		
					0	NoContact
					1	NcContact
		ExternalFault5ActiveStatus	UInt32	Active status		
					0	Always
					1	OnlyWhenMotorOn
		ExternalFault5ResetAlsoByTestResetButtonRS232	Boolean	Test/reset button, RS-232 (panel reset)		
		ExternalFault5ResetAlsoByAutoReset	Boolean	Auto reset		
		ExternalFault5ResetAlsoByRemoteReset123	Boolean	Remote reset, reset 1,2,3		
		ExternalFault5ResetAlsoByOffCommandReset	Boolean	Off command reset		
		ExternalFault5Marking	String	Marking		
		ExternalFault6Input	UInt32	External fault 6 - input		
		ExternalFault6Reset	UInt32	External fault 6 - reset		
		ExternalFault6Response	UInt32	Response		
					0	Signal
					2	Warn

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					3	Trip
		ExternalFault6Type	UInt32	Type		
					0	NoContact
					1	NcContact
		ExternalFault6ActiveStatus	UInt32	Active status		
					0	Always
					1	OnlyWhenMotorOn
		ExternalFault6ResetAlsoByTestResetButtonRS232	Boolean	Test/reset button, RS-232 (panel reset)		
		ExternalFault6ResetAlsoByAutoReset	Boolean	Auto reset		
		ExternalFault6ResetAlsoByRemoteReset123	Boolean	Remote reset, reset 1,2,3		
		ExternalFault6ResetAlsoByOffCommandReset	Boolean	Off command reset		
		ExternalFault6Marking	String	Marking		
		OperationalProtectionOffResponsePositioner	UInt32	Response positioner		
					0	Closed
					1	Open
		OperationalProtectionOffStandardFunctionsType	UInt32	Type		
					0	NOContact
					1	NCContact
		OperationalProtectionOffInput	UInt32	Operational Protection Off - input		
		PowerFailureMonitoringType	UInt32	Power failure monitoring - type		
					0	Deactivated
					1	ServiceSupplyIsNotInterrupted
		PowerFailureTime	Double	Power failure time		
		PowerFailureRestartTimeDelay	UInt32	Restart time delay		
		PowerFailureMonitoring	UInt32	Control external power failure monitoring		
		EmergencyStartInput	UInt32	Emergency start - input		
		SafetyRelatedTrippingResponse	UInt32	Response		
					0	Deactivated
					1	Signal
					2	Warn
					3	Trip
		SafetyRelatedTrippingReset	UInt32	Reset		
					0	Manual
					1	Auto

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		WatchdogBusMonitoring	Boolean	Bus monitoring		
		WatchdogPLCPCSMonitoring	Boolean	PLC/DCS monitoring		
		WatchdogBusPLCFaultReset	UInt32	Bus/PLC fault - Reset		
					0	Manual
					1	Auto
		WatchdogPLCPCSMonitoringInput	UInt32	PLC/DCS monitoring - input		
		TimeStampingActive	Boolean	Time stamping active		
		TimeStampingInput0	UInt32	Time stamping - input 0		
		TimeStampingInput1	UInt32	Time stamping - input 1		
		TimeStampingInput2	UInt32	Time stamping - input 2		
		TimeStampingInput3	UInt32	Time stamping - input 3		
		TimeStampingInput4	UInt32	Time stamping - input 4		
		TimeStampingInput5	UInt32	Time stamping - input 5		
		TimeStampingInput6	UInt32	Time stamping - input 6		
		TimeStampingInput7	UInt32	Time stamping - input 7		
		TruthTable1Input1	UInt32	Truth table 1 - input 1		
		TruthTable1Input2	UInt32	Truth table 1 - input 2		
		TruthTable1Input3	UInt32	Truth table 1 - input 3		
		TruthTable1Bit7	Boolean	0 0 0		
		TruthTable1Bit6	Boolean	0 0 1		
		TruthTable1Bit5	UInt32	0 1 0		
		TruthTable1Bit4	Boolean	0 1 1		
		TruthTable1Bit3	Boolean	1 0 0		
		TruthTable1Bit2	Boolean	1 0 1		
		TruthTable1Bit1	Boolean	1 1 0		
		TruthTable1Bit0	Boolean	1 1 1		
		TruthTable2Input1	UInt32	Truth table 2 - input 1		
		TruthTable2Input2	UInt32	Truth table 2 - input 2		
		TruthTable2Input3	UInt32	Truth table 2 - input 3		
		TruthTable2Bit7	Boolean	0 0 0		
		TruthTable2Bit6	Boolean	0 0 1		
		TruthTable2Bit5	Boolean	0 1 0		
		TruthTable2Bit4	Boolean	0 1 1		
		TruthTable2Bit3	Boolean	1 0 0		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		TruthTable2Bit2	Boolean	1 0 1		
		TruthTable2Bit1	Boolean	1 1 0		
		TruthTable2Bit0	Boolean	1 1 1		
		TruthTable3Input1	UInt32	Truth table 3 - input 1		
		TruthTable3Input2	UInt32	Truth table 3 - input 2		
		TruthTable3Input3	UInt32	Truth table 3 - input 3		
		TruthTable3Bit7	Boolean	0 0 0		
		TruthTable3Bit6	Boolean	0 0 1		
		TruthTable3Bit5	Boolean	0 1 0		
		TruthTable3Bit4	Boolean	0 1 1		
		TruthTable3Bit3	Boolean	1 0 0		
		TruthTable3Bit2	Boolean	1 0 1		
		TruthTable3Bit1	Boolean	1 1 0		
		TruthTable3Bit0	Boolean	1 1 1		
		TruthTable4Input1	UInt32	Truth table 4 - input 1		
		TruthTable4Input2	UInt32	Truth table 4 - input 2		
		TruthTable4Input3	UInt32	Truth table 4 - input 3		
		TruthTable4Bit7	Boolean	0 0 0		
		TruthTable4Bit6	Boolean	0 0 1		
		TruthTable4Bit5	Boolean	0 1 0		
		TruthTable4Bit4	Boolean	0 1 1		
		TruthTable4Bit3	Boolean	1 0 0		
		TruthTable4Bit2	Boolean	1 0 1		
		TruthTable4Bit1	Boolean	1 1 0		
		TruthTable4Bit0	Boolean	1 1 1		
		TruthTable5Input1	UInt32	Truth table 5 - input 1		
		TruthTable5Input2	UInt32	Truth table 5 - input 2		
		TruthTable5Input3	UInt32	Truth table 5 - input 3		
		TruthTable5Bit7	Boolean	0 0 0		
		TruthTable5Bit6	Boolean	0 0 1		
		TruthTable5Bit5	Boolean	0 1 0		
		TruthTable5Bit4	Boolean	0 1 1		
		TruthTable5Bit3	Boolean	1 0 0		
		TruthTable5Bit2	Boolean	1 0 1		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		TruthTable5Bit1	Boolean	1 1 0		
		TruthTable5Bit0	Boolean	1 1 1		
		TruthTable6Input1	UInt32	Truth table 6 - input 1		
		TruthTable6Input2	UInt32	Truth table 6 - input 2		
		TruthTable6Input3	UInt32	Truth table 6 - input 3		
		TruthTable6Bit7	Boolean	0 0 0		
		TruthTable6Bit6	Boolean	0 0 1		
		TruthTable6Bit5	Boolean	0 1 0		
		TruthTable6Bit4	Boolean	0 1 1		
		TruthTable6Bit3	Boolean	1 0 0		
		TruthTable6Bit2	Boolean	1 0 1		
		TruthTable6Bit1	Boolean	1 1 0		
		TruthTable6Bit0	Boolean	1 1 1		
		TruthTable10Input1	UInt32	Truth table 10 - input 1		
		TruthTable10Input2	UInt32	Truth table 10 - input 2		
		TruthTable10Input3	UInt32	Truth table 10 - input 3		
		TruthTable10Bit7	Boolean	0 0 0		
		TruthTable10Bit6	Boolean	0 0 1		
		TruthTable10Bit5	Boolean	0 1 0		
		TruthTable10Bit4	Boolean	0 1 1		
		TruthTable10Bit3	Boolean	1 0 0		
		TruthTable10Bit2	Boolean	1 0 1		
		TruthTable10Bit1	Boolean	1 1 0		
		TruthTable10Bit0	Boolean	1 1 1		
		TruthTable11Input1	UInt32	Truth table 11 - input 1		
		TruthTable11Input2	UInt32	Truth table 11 - input 2		
		TruthTable11Input3	UInt32	Truth table 11 - input 3		
		TruthTable11Bit7	Boolean	0 0 0		
		TruthTable11Bit6	Boolean	0 0 1		
		TruthTable11Bit5	Boolean	0 1 0		
		TruthTable11Bit4	Boolean	0 1 1		
		TruthTable11Bit3	Boolean	1 0 0		
		TruthTable11Bit2	Boolean	1 0 1		
		TruthTable11Bit1	Boolean	1 1 0		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		TruthTable11Bit0	Boolean	1 1 1		
		TruthTable7Input1	UInt32	Truth table 7 - input 1		
		TruthTable7Input2	UInt32	Truth table 7 - input 2		
		TruthTable7Bit3	Boolean	0 0		
		TruthTable7Bit2	Boolean	0 1		
		TruthTable7Bit1	Boolean	1 0		
		TruthTable7Bit0	Boolean	1 1		
		TruthTable8Input1	UInt32	Truth table 8 - input 1		
		TruthTable8Input2	UInt32	Truth table 8 - input 2		
		TruthTable8Bit3	Boolean	0 0		
		TruthTable8Bit2	Boolean	0 1		
		TruthTable8Bit1	Boolean	1 0		
		TruthTable8Bit0	Boolean	1 1		
		TruthTable9Input1	UInt32	Truth table 9 - input 1		
		TruthTable9Input2	UInt32	Truth table 9 - input 2		
		TruthTable9Input3	UInt32	Truth table 9 - input 3		
		TruthTable9Input4	UInt32	Truth table 9 - input 4		
		TruthTable9Input5	UInt32	Truth table 9 - input 5		
		TruthTable9Output1Bit31	Boolean	0 0 0 0 0 [1]		
		TruthTable9Output1Bit30	Boolean	0 0 0 0 1 [2]		
		TruthTable9Output1Bit29	Boolean	0 0 0 1 0 [3]		
		TruthTable9Output1Bit28	Boolean	0 0 0 1 1 [4]		
		TruthTable9Output1Bit27	Boolean	0 0 1 0 0 [5]		
		TruthTable9Output1Bit26	Boolean	0 0 1 0 1 [6]		
		TruthTable9Output1Bit25	Boolean	0 0 1 1 0 [7]		
		TruthTable9Output1Bit24	Boolean	0 0 1 1 1 [8]		
		TruthTable9Output1Bit23	Boolean	0 1 0 0 0 [9]		
		TruthTable9Output1Bit22	Boolean	0 1 0 0 1 [10]		
		TruthTable9Output1Bit21	Boolean	0 1 0 1 0 [11]		
		TruthTable9Output1Bit20	Boolean	0 1 0 1 1 [12]		
		TruthTable9Output1Bit19	Boolean	0 1 1 0 0 [13]		
		TruthTable9Output1Bit18	Boolean	0 1 1 0 1 [14]		
		TruthTable9Output1Bit17	Boolean	0 1 1 1 0 [15]		
		TruthTable9Output1Bit16	Boolean	0 1 1 1 1 [16]		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		TruthTable9Output1Bit15	Boolean	1 0 0 0 0 [17]		
		TruthTable9Output1Bit14	Boolean	1 0 0 0 1 [18]		
		TruthTable9Output1Bit13	Boolean	1 0 0 1 0 [19]		
		TruthTable9Output1Bit12	Boolean	1 0 0 1 1 [20]		
		TruthTable9Output1Bit11	Boolean	1 0 1 0 0 [21]		
		TruthTable9Output1Bit10	Boolean	1 0 1 0 1 [22]		
		TruthTable9Output1Bit9	Boolean	1 0 1 1 0 [23]		
		TruthTable9Output1Bit8	Boolean	1 0 1 1 1 [24]		
		TruthTable9Output1Bit7	Boolean	1 1 0 0 0 [25]		
		TruthTable9Output1Bit6	Boolean	1 1 0 0 1 [26]		
		TruthTable9Output1Bit5	Boolean	1 1 0 1 0 [27]		
		TruthTable9Output1Bit4	Boolean	1 1 0 1 1 [28]		
		TruthTable9Output1Bit3	Boolean	1 1 1 0 0 [29]		
		TruthTable9Output1Bit2	Boolean	1 1 1 0 1 [30]		
		TruthTable9Output1Bit1	Boolean	1 1 1 1 0 [31]		
		TruthTable9Output1Bit0	Boolean	1 1 1 1 1 [32]		
		TruthTable9Output2Bit31	Boolean	0 0 0 0 0 [1]		
		TruthTable9Output2Bit30	Boolean	0 0 0 0 1 [2]		
		TruthTable9Output2Bit29	Boolean	0 0 0 1 0 [3]		
		TruthTable9Output2Bit28	Boolean	0 0 0 1 1 [4]		
		TruthTable9Output2Bit27	Boolean	0 0 1 0 0 [5]		
		TruthTable9Output2Bit26	Boolean	0 0 1 0 1 [6]		
		TruthTable9Output2Bit25	Boolean	0 0 1 1 0 [7]		
		TruthTable9Output2Bit24	Boolean	0 0 1 1 1 [8]		
		TruthTable9Output2Bit23	Boolean	0 1 0 0 0 [9]		
		TruthTable9Output2Bit22	Boolean	0 1 0 0 1 [10]		
		TruthTable9Output2Bit21	Boolean	0 1 0 1 0 [11]		
		TruthTable9Output2Bit20	Boolean	0 1 0 1 1 [12]		
		TruthTable9Output2Bit19	Boolean	0 1 1 0 0 [13]		
		TruthTable9Output2Bit18	Boolean	0 1 1 0 1 [14]		
		TruthTable9Output2Bit17	Boolean	0 1 1 1 0 [15]		
		TruthTable9Output2Bit16	Boolean	0 1 1 1 1 [16]		
		TruthTable9Output2Bit15	Boolean	1 0 0 0 0 [17]		
		TruthTable9Output2Bit14	Boolean	1 0 0 0 1 [18]		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		TruthTable9Output2Bit13	Boolean	1 0 0 1 0 [19]		
		TruthTable9Output2Bit12	Boolean	1 0 0 1 1 [20]		
		TruthTable9Output2Bit11	Boolean	1 0 1 0 0 [21]		
		TruthTable9Output2Bit10	Boolean	1 0 1 0 1 [22]		
		TruthTable9Output2Bit9	Boolean	1 0 1 1 0 [23]		
		TruthTable9Output2Bit8	Boolean	1 0 1 1 1 [24]		
		TruthTable9Output2Bit7	Boolean	1 1 0 0 0 [25]		
		TruthTable9Output2Bit6	Boolean	1 1 0 0 1 [26]		
		TruthTable9Output2Bit5	Boolean	1 1 0 1 0 [27]		
		TruthTable9Output2Bit4	Boolean	1 1 0 1 1 [28]		
		TruthTable9Output2Bit3	Boolean	1 1 1 0 0 [29]		
		TruthTable9Output2Bit2	Boolean	1 1 1 0 1 [30]		
		TruthTable9Output2Bit1	Boolean	1 1 1 1 0 [31]		
		TruthTable9Output2Bit0	Boolean	1 1 1 1 1 [32]		
		Counter1LimitValue	UInt32	Counter 1 - limit value		
		Counter1InputIncrement	UInt32	Counter 1 - input +		
		Counter1InputDecrement	UInt32	Counter 1 - input -		
		Counter1Reset	UInt32	Counter 1 - reset		
		Counter2LimitValue	UInt32	Counter 2 - limit value		
		Counter2InputIncrement	UInt32	Counter 2 - input +		
		Counter2InputDecrement	UInt32	Counter 2 - input -		
		Counter2Reset	UInt32	Counter 2 - reset		
		Counter3LimitValue	UInt32	Counter 3 - limit value		
		Counter3InputIncrement	UInt32	Counter 3 - input +		
		Counter3InputDecrement	UInt32	Counter 3 - input -		
		Counter3Reset	UInt32	Counter 3 - reset		
		Counter4LimitValue	UInt32	Counter 4 - limit value		
		Counter4InputIncrement	UInt32	Counter 4 - input +		
		Counter4InputDecrement	UInt32	Counter 4 - input -		
		Counter4Reset	UInt32	Counter 4 - reset		
		Counter5LimitValue	UInt32	Counter 5 - limit value		
		Counter5InputIncrement	UInt32	Counter 5 - input +		
		Counter5InputDecrement	UInt32	Counter 5 - input -		
		Counter5Reset	UInt32	Counter 5 - reset		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		Counter6LimitValue	UInt32	Counter 6 - limit value		
		Counter6InputIncrement	UInt32	Counter 6 - input +		
		Counter6InputDecrement	UInt32	Counter 6 - input -		
		Counter6Reset	UInt32	Counter 6 - reset		
		Timer1Type	UInt32	Timer 1 - type		
					3	WithFleetingClosing
					2	WithOpeningDelay
					1	ClosingDelayWithMemory
					0	WithClosingDelay
		Timer1LimitValue	Double	Timer 1 - limit value		
		Timer1Input	UInt32	Timer 1 - input		
		Timer1Reset	UInt32	Timer 1 - reset		
		Timer2Type	UInt32	Timer 2 - type		
					0	WithClosingDelay
					1	ClosingDelayWithMemory
					2	WithOpeningDelay
					3	WithFleetingClosing
		Timer2LimitValue	Double	Timer 2 - limit value		
		Timer2Input	UInt32	Timer 2 - input		
		Timer2Reset	UInt32	Timer 2 - reset		
		Timer3Type	UInt32	Timer 3 - type		
					0	WithClosingDelay
					1	ClosingDelayWithMemory
					2	WithOpeningDelay
					3	WithFleetingClosing
		Timer3LimitValue	Double	Timer 3 - limit value		
		Timer3Input	UInt32	Timer 3 - input		
		Timer3Reset	UInt32	Timer 3 - reset		
		Timer4Type	UInt32	Timer 4 - type		
					0	WithClosingDelay
					1	ClosingDelayWithMemory
					2	WithOpeningDelay
					3	WithFleetingClosing
		Timer4LimitValue	Double	Timer 4 - limit value		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		Timer4Input	UInt32	Timer 4 - input		
		Timer4Reset	UInt32	Timer 4 - reset		
		Timer5Type	UInt32	Timer 5 - type		
					0	WithClosingDelay
					1	ClosingDelayWithMemory
					2	WithOpeningDelay
					3	WithFleetingClosing
		Timer5LimitValue	Double	Timer 5 - limit value		
		Timer5Input	UInt32	Timer 5 - input		
		Timer5Reset	UInt32	Timer 5 - reset		
		Timer6Type	UInt32	Timer 6 - type		
					0	WithClosingDelay
					1	ClosingDelayWithMemory
					2	WithOpeningDelay
					3	WithFleetingClosing
		Timer6LimitValue	Double	Timer 6 - limit value		
		Timer6Input	UInt32	Timer 6 - input		
		Timer6Reset	UInt32	Timer 6 - reset		
		SignalConditioning1Type	UInt32	Signal conditioning 1 - type		
					0	NonInverting
					1	Inverting
					2	EdgeRisingWithMemory
					3	EdgeFallingWithMemory
		SignalConditioning1Input	UInt32	Signal conditioning 1 - input		
		SignalConditioning1Reset	UInt32	Signal conditioning 1 - reset		
		SignalConditioning2Type	UInt32	Signal conditioning 2 - type		
					0	NonInverting
					1	Inverting
					2	EdgeRisingWithMemory
					3	EdgeFallingWithMemory
		SignalConditioning2Input	UInt32	Signal conditioning 2 - input		
		SignalConditioning2Reset	UInt32	Signal conditioning 2 - reset		
		SignalConditioning3Type	UInt32	Signal conditioning 3 - type		
					0	NonInverting

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					1	Inverting
					2	EdgeRisingWithMemory
					3	EdgeFallingWithMemory
		SignalConditioning3Input	UInt32	Signal conditioning 3 - input		
		SignalConditioning3Reset	UInt32	Signal conditioning 3 - reset		
		SignalConditioning4Type	UInt32	Signal conditioning 4 - type		
					0	NonInverting
					1	Inverting
					2	EdgeRisingWithMemory
					3	EdgeFallingWithMemory
		SignalConditioning4Input	UInt32	Signal conditioning 4 - input		
		SignalConditioning4Reset	UInt32	Signal conditioning 4 - reset		
		SignalConditioning5Type	UInt32	Signal conditioning 5 - type		
					0	NonInverting
					1	Inverting
					2	EdgeRisingWithMemory
					3	EdgeFallingWithMemory
		SignalConditioning5Input	UInt32	Signal conditioning 5 - input		
		SignalConditioning5Reset	UInt32	Signal conditioning 5 - reset		
		SignalConditioning6Type	UInt32	Signal conditioning 6 - type		
					3	EdgeFallingWithMemory
					2	EdgeRisingWithMemory
					1	Inverting
					0	NonInverting
		SignalConditioning6Input	UInt32	Signal conditioning 6 - input		
		SignalConditioning6Reset	UInt32	Signal conditioning 6 - reset		
		NonVolatileElement1Type	UInt32	Non-volatile element 1 - type		
					0	NonInverting
					1	Inverting
					2	EdgeRisingWithMemory
					3	EdgeFallingWithMemory
		NonVolatileElement1Input	UInt32	Non-volatile element 1 - input		
		NonVolatileElement1Reset	UInt32	Non-volatile element 1 - reset		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		NonVolatileElement2Type	UInt32	Non-volatile element 2 - type		
					0	NonInverting
					1	Inverting
					2	EdgeRisingWithMemory
					3	EdgeFallingWithMemory
		NonVolatileElement2Input	UInt32	Non-volatile element 2 - input		
		NonVolatileElement2Reset	UInt32	Non-volatile element 2 - reset		
		NonVolatileElement3Type	UInt32	Non-volatile element 3 - type		
					0	NonInverting
					1	Inverting
					2	EdgeRisingWithMemory
					3	EdgeFallingWithMemory
		NonVolatileElement3Input	UInt32	Non-volatile element 3 - input		
		NonVolatileElement3Reset	UInt32	Non-volatile element 3 - reset		
		NonVolatileElement4Type	UInt32	Non-volatile element 4 - type		
					0	NonInverting
					1	Inverting
					2	EdgeRisingWithMemory
					3	EdgeFallingWithMemory
		NonVolatileElement4Input	UInt32	Non-volatile element 4 - input		
		NonVolatileElement4Reset	UInt32	Non-volatile element 4 - reset		
		Flashing1Input	UInt32	Flashing 1 - input		
		Flashing2Input	UInt32	Flashing 2 - input		
		Flashing3Input	UInt32	Flashing 3 - input		
		Flicker1Input	UInt32	Flicker 1 - input		
		Flicker2Input	UInt32	Flicker 2 - input		
		Flicker3Input	UInt32	Flicker 3 - input		
		LimitMonitorsHysteresis	UInt32	Hysteresis for limit monitor		
		LimitMonitor1Type	UInt32	Type		
					0	Overshoot
					1	Undershoot
		LimitMonitor1ActiveStatus	UInt32	Active status		
					0	AlwaysOn
					1	AlwaysExceptWithTpf

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					2	IfMotorIsRunningExceptTpf
					3	IfMotorIsRunningExceptTpfWithStartupOverride
		LimitMonitor1Limit	UInt32	Limit		
		LimitMonitor1Delay	Double	Delay		
		LimitMonitor1Marking	String	Marking		
		LimitMonitor1Input	UInt32	Limit monitor 1 - input		
		LimitMonitor2Type	UInt32	Type		
					1	Undershoot
					0	Overshoot
		LimitMonitor2ActiveStatus	UInt32	Active status		
					0	AlwaysOn
					1	AlwaysExceptWithTpf
					2	IfMotorIsRunningExceptTpf
					3	IfMotorIsRunningExceptTpfWithStartupOverride
		LimitMonitor2Limit	UInt32	Limit		
		LimitMonitor2Delay	Double	Delay		
		LimitMonitor2Marking	String	Marking		
		LimitMonitor2Input	UInt32	Limit monitor 2 - input		
		LimitMonitor3Type	UInt32	Type		
					0	Overshoot
					1	Undershoot
		LimitMonitor3ActiveStatus	UInt32	Active status		
					3	IfMotorIsRunningExceptTpfWithStartupOverride
					2	IfMotorIsRunningExceptTpf
					1	AlwaysExceptWithTpf
					0	AlwaysOn
		LimitMonitor3Limit	UInt32	Limit		
		LimitMonitor3Delay	Double	Delay		
		LimitMonitor3Marking	String	Marking		
		LimitMonitor3Input	UInt32	Limit monitor 3 - input		
		LimitMonitor4Type	UInt32	Type		
					0	Overshoot
					1	Undershoot

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		LimitMonitor4ActiveStatus	UInt32	Active status		
					0	AlwaysOn
					1	AlwaysExceptWithTpf
					2	IfMotorIsRunningExceptTpf
					3	IfMotorIsRunningExceptTpfWithStartupOverride
		LimitMonitor4Limit	UInt32	Limit		
		LimitMonitor4Delay	Double	Delay		
		LimitMonitor4Marking	String	Marking		
		LimitMonitor4Input	UInt32	Limit monitor 4 - input		
		LimitMonitor5Type	UInt32	Type		
					0	Overshoot
					1	Undershoot
		LimitMonitor5ActiveStatus	UInt32	Active status		
					0	AlwaysOn
					1	AlwaysExceptWithTpf
					2	IfMotorIsRunningExceptTpf
					3	IfMotorIsRunningExceptTpfWithStartupOverride
		LimitMonitor5Limit	UInt32	Limit		
		LimitMonitor5Delay	Double	Delay		
		LimitMonitor5Marking	String	Marking		
		LimitMonitor5Input	UInt32	Limit monitor 5 - input		
		LimitMonitor6Type	UInt32	Type		
					1	Undershoot
					0	Overshoot
		LimitMonitor6ActiveStatus	UInt32	Active status		
					0	AlwaysOn
					1	AlwaysExceptWithTpf
					2	IfMotorIsRunningExceptTpf
					3	IfMotorIsRunningExceptTpfWithStartupOverride
		LimitMonitor6Limit	UInt32	Limit		
		LimitMonitor6Delay	Double	Delay		
		LimitMonitor6Marking	String	Marking		
		LimitMonitor6Input	UInt32	Limit monitor 6 - input		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		Calculator2OperatingMode	UInt32	Operation mode		
					0	BothInputsOfTheTypeWord
					1	Inputs1And2AsDWordInput
		Calculator1Numerator	Int32	Calculator 1 - numerator		
		Calculator1Denominator	UInt32	Calculator 1 - denominator		
		Calculator1Offset	Int32	Calculator 1 - offset		
		Calculator1Input	UInt32	Calculator 1 - input		
		Calculator2Numerator1	Int32	Numerator 1		
		Calculator2Denominator1	UInt32	Denominator 1		
		Calculator2Operator	UInt32	Calculator 2 - operator		
					0	Addition
					1	Subtraction
					2	Multiplication
					3	Division
		Calculator2Numerator2	UInt32	Numerator 2		
		Calculator2Denominator2	Int32	Denominator 2		
		Calculator2Offset	Int32	Offset		
		Calculator2Input1	UInt32	Calculator 2 - input 1		
		Calculator2Input2	UInt32	Calculator 2 - input 2		
		Calculator3Constant1	UInt32	Calculator - constant 1		
		Calculator3Constant2	UInt32	Calculator - constant 2		
		Calculator3Constant3	UInt32	Calculator - constant 3		
		Calculator3Constant4	UInt32	Calculator - constant 4		
		Calculator3Operator1	UInt32	Calculator - operator 1		
					0	Addition
					1	Subtraction
					2	Multiplication
					3	Division
		Calculator3Operator2	UInt32	Calculator - operator 2		
					0	Addition
					1	Subtraction
					2	Multiplication
					3	Division

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		Calculator3Operator3	UInt32	Calculator - operator 3		
					0	Addition
					1	Subtraction
					2	Multiplication
					3	Division
		Calculator3Priority1	UInt32	Calculator - priority 1		
					2	High
					1	Medium
					0	Low
		Calculator3Priority2	UInt32	Calculator - priority 2		
					2	High
					1	Medium
					0	Low
		Calculator3Priority3	UInt32	Calculator - priority 3		
					0	Low
					1	Medium
					2	High
		Calculator3Input1	UInt32	Calculator 3 - input 1		
		Calculator3Input2	UInt32	Calculator 3 - input 2		
		Calculator3Input3	UInt32	Calculator 3 - input 3		
		Calculator3Input4	UInt32	Calculator 3 - input 4		
		Calculator4Constant1	UInt32	Calculator - constant 1		
		Calculator4Constant2	UInt32	Calculator - constant 2		
		Calculator4Constant3	UInt32	Calculator - constant 3		
		Calculator4Constant4	UInt32	Calculator - constant 4		
		Calculator4Operator1	UInt32	Calculator - operator 1		
					0	Addition
					1	Subtraction
					2	Multiplication
					3	Division
		Calculator4Operator2	UInt32	Calculator - operator 2		
					0	Addition
					1	Subtraction
					2	Multiplication

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					3	Division
		Calculator4Operator3	UInt32	Calculator - operator 3		
					0	Addition
					1	Subtraction
					2	Multiplication
					3	Division
		Calculator4Priority1	UInt32	Calculator - priority 1		
					0	Low
					1	Medium
					2	High
		Calculator4Priority2	UInt32	Calculator - priority 2		
					0	Low
					1	Medium
					2	High
		Calculator4Priority3	UInt32	Calculator - priority 3		
					0	Low
					1	Medium
					2	High
		Calculator4Input1	UInt32	Calculator 4 - input 1		
		Calculator4Input2	UInt32	Calculator 4 - input 2		
		Calculator4Input3	UInt32	Calculator 4 - input 3		
		Calculator4Input4	UInt32	Calculator 4 - input 4		
		MuxConstant1	UInt32	MUX - constant 1		
		MuxConstant2	UInt32	MUX - constant 2		
		MuxConstant3	UInt32	MUX - constant 3		
		MuxConstant4	UInt32	MUX - constant 4		
		MuxControlSignalS1	UInt32	MUX - control signal S1		
		MuxControlSignalS2	UInt32	MUX - control signal S2		
		MuxInput1	UInt32	MUX - input 1		
		MuxInput2	UInt32	MUX - input 2		
		MuxInput3	UInt32	MUX - input 3		
		MuxInput4	UInt32	MUX - input 4		
		PwmConstantInput	UInt32	PWM - constant input		
		PWMInputMinimum	UInt32	PWM - input minimum		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		PWMInputMaximum	UInt32	PWM - input maximum		
		PwmDuration	Double	PWM - duration		
		PwmInputAnalog	UInt32	PWM - Input		
		CompatibilityMode3UF50Active	Boolean	3UF50 - compatibility mode		
		CompatibilityMode3UF50Mode	UInt32	3UF50 - mode		
					0	Dpv0
					1	Dpv1
		CompatibilityMode3UF50BasicType	UInt32	3UF50 - basic type		
					0	Value1
					1	Value2
					2	Value3
		ProfiEnergyMinPauseTime	Double	Minimum pause time		
		OPDReturnToOperationsDisplayAfter	UInt32	Return to operations display after		
					0	Manually
					1	Value3Seconds
					2	Value10Seconds
					3	Value1Minute
					4	Value5Minutes
		OPDLanguage	UInt32	Language		
					0	English
					1	German
					2	French
					3	Polish
					4	Spanish
					5	Portuguese
					6	Italian
					7	Suomi
					8	Chinese
					9	Russian
					10	Language4Placeholder
					11	Language5Placeholder
					12	Language6Placeholder
					13	Language7Placeholder
					14	Language8Placeholder

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					15	Language9Placeholder
		OPDContrast	UInt32	Contrast		
		OPDProfiles	UInt32	Profiles		
					0	IL1IL2IL3A
					1	IL1IL2IL3Percent
					2	IMaxA
					3	IMaxPercent
					4	IMaxCos
					5	IMaxUL1NCosS
					6	IMaxUL1L2CosS
					7	IMaxUL1NCosP
					8	IMaxUL1L2CosP
					9	In1AndOutAm1
					10	In2AndOutAm1
					11	InputsAm1
					12	In1AndOutAm2
					13	In2AndOutAm2
					14	InputsAm2
					15	MaxTempTm1C
					16	TempTm1C
					17	MaxTempTm1F
					18	TempTm1F
					19	MaxTempTm2C
					20	TempTm2C
					21	MaxTempTm2F
					22	TempTm2F
					23	UL1NUL2NUL3N
					24	UL1L2UL2L3UL3L1
					25	IMaxUL1NCos
					26	IMaxUL1L2Cos
					27	IMaxUL1NC
					28	IMaxUL1L2C
					29	IMaxUL1nNF
					30	IMaxUL1L2F

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
					31	CalculatorModule1
					32	CalculatorModule2
					33	EnergyUsedKwh
		OPDKeepIlluminationOnFor	UInt32	Keep illumination on for		
					0	Off
					1	Value3Seconds
					2	Value10Seconds
					3	Value1Minute
					4	Value5Minutes
		OPDWarnings	UInt32	Warnings		
					0	DoNotDisplay
					1	Display
		OPDFaults	UInt32	Faults		
					0	DoNotDisplay
					1	Display
		TraceTriggerEdge	UInt32	Trigger edge		
					1	Negative
					0	Positive
		TraceSamplingRateV2	Double	Sampling rate		
		TracePreTrigger	UInt32	Pre-trigger		
		TraceTriggerInput	UInt32	Trigger input		
		TraceAssignedAnalogValue	UInt32	Assigned analog value		
		UseBootpOrDhcp	Boolean	Use BOOTP/DHCP		
		Name	String	Name		
		ShortDesignation	String	Short designation		
		OrderNumber	String	Article number		
		FirmwareVersion	String	Firmware version		
		BasicType	UInt32	Basic type		
					1	Value1
					2	Value2
					3	Value3
		TM1TripLevelResponse	UInt32	Response to trip level T>		
					1	Signal
					3	Trip

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Head modules 3UF7 0** - any Version						
		TM1WarningLevelResponse	UInt32	Response to warning level T>		
					2	Warn
					1	Signal
					0	Deactivated

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Simocode Pro Rack						
		Author	String	Author		
		Comment	String	Comment		
		OrderNumber	String	Article number		
		ShortDesignation	String	Short designation		
		Name	String	Name		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Global Enums - Digital Connetions					
				0	NotConnected
				1	FixedLevel0
				2	FixedLevel1
				4	EventAm2WarningLevelUpperLimit
				5	EventAm2WarningLevelLowerLimit
				6	EventAm2TripLevelUpperLimit
				7	EventAm2TripLevelLowerLimit
				8	BuTestOrResetButton
				9	BuInput1
				10	BuInput2
				11	BuInput3
				12	BuInput4
				16	Dm1InputDMFL
				17	Dm1Input2
				18	Dm1FeedbackCircuitDmfl
				19	Dm1CascadingInput
				20	Dm2Input1
				21	Dm2Input2
				22	Dm2Input3
				23	Dm2Input4
				24	Dm1SensorChannel1
				25	Dm1SensorChannel2
				28	EventTm2SensorFault
				29	EventTm2OutOfRange
				30	EventTm2WarningLevelUpperLimit
				31	EventTm2TripLevelUpperLimit
				32	OpTestOrResetButton
				33	OpButton1
				34	OpButton2
				35	OpButton3
				36	OpButton4
				38	EventLimitMonitor5
				39	EventLimitMonitor6
				40	AcyclicReceiveByte0Bit0

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Global Enums - Digital Connetions						
					41	AcyclicReceiveByte0Bit1
					42	AcyclicReceiveByte0Bit2
					43	AcyclicReceiveByte0Bit3
					44	AcyclicReceiveByte0Bit4
					45	AcyclicReceiveByte0Bit5
					46	AcyclicReceiveByte0Bit6
					47	AcyclicReceiveByte0Bit7
					48	AcyclicReceiveByte1Bit0
					49	AcyclicReceiveByte1Bit1
					50	AcyclicReceiveByte1Bit2
					51	AcyclicReceiveByte1Bit3
					52	AcyclicReceiveByte1Bit4
					53	AcyclicReceiveByte1Bit5
					54	AcyclicReceiveByte1Bit6
					55	AcyclicReceiveByte1Bit7
					56	CyclicReceiveByte0Bit0
					57	CyclicReceiveByte0Bit1
					58	CyclicReceiveByte0Bit2
					59	CyclicReceiveByte0Bit3
					60	CyclicReceiveByte0Bit4
					61	CyclicReceiveByte0Bit5
					62	CyclicReceiveByte0Bit6
					63	CyclicReceiveByte0Bit7
					64	CyclicReceiveByte1Bit0
					65	CyclicReceiveByte1Bit1
					66	CyclicReceiveByte1Bit2
					67	CyclicReceiveByte1Bit3
					68	CyclicReceiveByte1Bit4
					69	CyclicReceiveByte1Bit5
					70	CyclicReceiveByte1Bit6
					71	CyclicReceiveByte1Bit7
					72	OnReverseFastEnabledControlCommand
					73	OnReverseEnabledControlCommand
					74	OffEnabledControlCommand

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Global Enums - Digital Connetions						
					75	OnForwardEnabledControlCommand
					76	OnForwardFastEnabledControlCommand
					80	ContactorControl1Qe1
					81	ContactorControl2Qe2
					82	ContactorControl3Qe3
					83	ContactorControl4Qe4
					84	ContactorControl5Qe5
					88	DisplayQleReversefast
					89	DisplayQleReverse
					90	DisplayQlaOff
					91	DisplayQleForward
					92	DisplayQleForwardFast
					93	DisplayQlsFault
					96	StatusGroupFault
					97	StatusGroupWarning
					98	StatusDeviceOK
					99	StatusBusOK
					100	StatusPlcDcsInRun
					101	StatusCurrentFlowing
					102	StatusProfienergyCommandStartPausePending
					104	StatusOnReverseFast
					105	StatusOnReverse
					106	StatusOff
					107	StatusOnForward
					108	StatusOnForwardFast
					109	StatusStartActive
					110	StatusInterlockingTimeActive
					111	StatusChangeOverPauseActive
					112	StatusPositionerRunsInOpenDirection
					113	StatusPositionerRunsInClosedDirection
					114	StatusFeedbackClosedFc
					115	StatusFeedbackOpenFo
					116	StatusTorqueClosedTc
					117	StatusTorqueOpenTo

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Global Enums - Digital Connetions						
					118	StatusTestPositionFeedback
					119	StatusOperationalProtectionOff
					120	StatusRemoteMode
					121	StatusEmergencyStartExecuted
					122	StatusCoolingDownPeriodActive
					123	StatusPauseTimeActive
					124	StatusDeviceTestActive
					125	StatusPhaseSequence123
					126	StatusPhaseSequence321
					127	StatusEnablingCircuitClosed
					128	EventPrewarningOverload
					129	EventUnbalance
					130	EventOverload
					131	EventOverloadAndPhaseFailure
					132	EventInternalGroundFault
					133	EventExternalGroundFault
					134	EventExternalGroundFaultWarning
					135	EventThermistorTripLevel
					136	EventThermistorShortCircuit
					137	EventThermistorOpenCircuit
					138	EventTm1WarningLevelUpperLimit
					139	EventTm1TripLevelUpperLimit
					140	EventTm1SensorFault
					141	EventTm1OutOfRange
					142	EventEmOpenCircuit
					143	EventEmShortCircuit
					144	EventWarningLevelIUpperLimit
					145	EventWarningLevelILowerLimit
					146	EventWarningLevelPUpperLimit
					147	EventWarningLevelPLowerLimit
					148	EventWarningLevelCosPhi
					149	EventWarningLevelULowerLimit
					150	EventAm1WarningLevelUpperLimit
					151	EventAm1WarningLeveLowerLimit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Global Enums - Digital Connetions						
					152	EventTripLevelIUpperLimit
					153	EventTripLevelILowerLimit
					154	EventTripLevelPUpperLimit
					155	EventTripLevelPLowerLimit
					156	EventTripLevelCosPhi
					157	EventTripLevelULowerLimit
					158	EventAm1TripLevelUpperLimit
					159	EventAm1TripLevelLowerLimit
					160	EventStalledRotor
					161	EventInternalGroundFaultWarning
					163	EventNoStartPermitted
					164	EventNumberOfStarts
					165	EventJustOneStartPossible
					166	EventMotorOperatingHours
					167	EventStopTime
					168	EventLimitMonitor1
					169	EventLimitMonitor2
					170	EventLimitMonitor3
					171	EventLimitMonitor4
					172	EventExternalFault1
					173	EventExternalFault2
					174	EventExternalFault3
					175	EventExternalFault4
					176	EventExternalFault5
					177	EventExternalFault6
					179	EventAm2OpenCircuit
					180	EventAm1OpenCircuit
					181	EventSafetyRelatedTripping
					182	EventMonitoringPeriodForMandatoryTestingTestRequirement
					186	EventDmFLocalOK
					187	EventProfisafeActive
					188	EventConfiguredOperatorPanelMissing
					190	WarningFeedbackCircuit

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					191	WarningSimultaneity

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Global Enums - Digital Connetions						
					192	FaultHardwareFaultBasicUnit
					193	FaultModuleFault
					194	FaultTemporaryComponents
					195	FaultConfigurationError
					196	FaultParameterization
					197	FaultBus
					198	FaultPlcDcs
					199	DryRunningProtectionTripLevel
					200	FaultExecutionOnCommand
					201	FaultExecutionStopCommand
					202	FaultFeedbackOn
					203	FaultFeedbackOff
					204	FaultStalledPositioner
					205	FaultDouble0
					206	FaultDouble1
					207	FaultEndPosition
					208	FaultAntivalence
					209	FaultTestPositionFeedback
					210	FaultPowerFailure
					211	FaultOperationalProtectionOff
					214	SignalConditioning5Output
					215	SignalConditioning6Output
					216	TruthTable1Output
					217	TruthTable2Output
					218	TruthTable3Output
					219	TruthTable4Output
					220	TruthTable5Output
					221	TruthTable6Output
					222	TruthTable7Output
					223	TruthTable8Output
					224	TruthTable9Output1
					225	TruthTable9Output2
					228	Counter5Output
					229	Counter6Output

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Global Enums - Digital Connetions						
					230	Timer5Output
					231	Timer6Output
					232	Timer1Output
					233	Timer2Output
					234	Timer3Output
					235	Timer4Output
					236	Counter1Output
					237	Counter2Output
					238	Counter3Output
					239	Counter4Output
					240	Dm1FeedbackCircuitDmfp
					241	Dm1Input1
					242	Dm1Input3
					243	Dm1Input4
					244	Dm1Start
					245	NonVolatileElement2Output
					246	NonVolatileElement3Output
					247	NonVolatileElement4Output
					248	Flashing1Output
					249	Flashing2Output
					250	Flashing3Output
					251	Flicker1Output
					252	Flicker2Output
					253	Flicker3Output
					254	NonVolatileElement1Output
					255	CloseSolenoidValve
					256	ClosePositioner
					257	OpcUaReceiveByte0Bit0
					258	OpcUaReceiveByte0Bit1
					259	OpcUaReceiveByte0Bit2
					260	OpcUaReceiveByte0Bit3
					261	OpcUaReceiveByte0Bit4
					262	OpcUaReceiveByte0Bit5
					263	OpcUaReceiveByte0Bit6

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Global Enums - Digital Connetions						
					264	OpcUaReceiveByte0Bit7
					265	OpcUaReceiveByte1Bit0
					266	OpcUaReceiveByte1Bit1
					267	OpcUaReceiveByte1Bit2
					268	OpcUaReceiveByte1Bit3
					269	OpcUaReceiveByte1Bit4
					270	OpcUaReceiveByte1Bit5
					271	OpcUaReceiveByte1Bit6
					272	OpcUaReceiveByte1Bit7
					273	Open
					274	PwmOutput
					275	SignalConditioning1Output
					276	SignalConditioning2Output
					277	SignalConditioning3Output
					278	SignalConditioning4Output
					279	Stop

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Global Enums - Analog Connetions						
					0	NotConnected
					1	FixedLevel
					4	Timer1ActualValue
					5	Timer2ActualValue
					6	Timer3ActualValue
					7	Timer4ActualValue
					8	Counter1ActualValue
					9	Counter2ActualValue
					10	Counter3ActualValue
					11	Counter4ActualValue
					12	Counter5ActualValue
					13	Counter6ActualValue
					14	Timer5ActualValue
					15	Timer6ActualValue
					16	MaxCurrentIMaxPercentageOfIs
					17	CurrentIL1PercentageOfIs
					18	CurrentIL2PercentageOfIs
					19	CurrentIL3PercentageOfIs
					20	PhaseUnbalance
					21	InternalGroundFaultGroundFaultCurrent
					22	InternalGroundFaultLastTrippingCurrent
					23	VoltageUMin
					24	LineToLineVoltageUl1L2
					25	LineToLineVoltageUl2L3
					26	LineToLineVoltageUl3L1
					27	CosPhi
					28	Frequency
					30	NumberOfOverloadTrips
					31	IntNumberOfOverloadTrips
					32	ThermalMotorModel
					33	TimeToTrip
					34	RemainingCoolingDownPeriod
					35	LastTripCurrentPercentageOfIs
					36	TemperatureModule1MaxTemperature

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Global Enums - Analog Connetions						
					37	TemperatureModule1Temperature1
					38	TemperatureModule1Temperature2
					39	TemperatureModule1Temperature3
					40	PermissibleStartsActualValue
					41	StopTime
					42	MonitoringIntervalForMandatoryTestingTimeUntilTest
					43	EmLastTrippingCurrent
					44	AnalogModule1Input1
					45	AnalogModule1Input2
					47	EmGroundFaultCurrent
					48	AcyclicReceiveAnalogValue
					49	CyclicReceiveAnalogValue
					50	CyclicReceiveAnalogValue2
					51	NumberOfParameterizations
					52	MotorOperatingHoursHWord
					53	MotorOperatingHoursLWord
					54	IntMotorOperatingHoursHWord
					55	IntMotorOperatingHoursLWord
					56	DeviceOperatingHoursHWord
					57	DeviceOperatingHoursLWord
					58	NumberOfStartsHWord
					59	NumberOfStartsLWord
					60	IntNumberOfStartsCwHWord
					61	IntNumberOfStartsCwLWord
					62	IntNumberOfStartsCcwHWord
					63	IntNumberOfStartsCcwLWord
					64	ConsumedEnergyHWord
					65	ConsumedEnergyLWord
					70	ActivePowerHWord
					71	ActivePowerLWord
					72	ApparentPowerHWord
					73	ApparentPowerLWord
					86	Calculator1Output

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
					90	Calculator2Output

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - Global Enums - Analog Connetions						
					91	Calculator3Output
					92	Calculator4Output
					93	AnalogMultiplexerOutput
					104	MaxCurrentIMax10Ma
					105	CurrentIL110Ma
					106	CurrentIL210Ma
					107	CurrentIL310Ma
					108	MaxCurrentIMax100Ma
					109	CurrentIL1100Ma
					110	CurrentIL2100Ma
					111	CurrentIL3100Ma
					116	TemperatureModule2MaxTemperature
					117	TemperatureModule2Temperature1
					118	TemperatureModule2Temperature2
					119	TemperatureModule2Temperature3
					120	AnalogModule2Input1
					121	AnalogModule2Input2
					122	CyclicReceiveAnalogValue1
					123	OpcUaReceiveAnalogValue
					124	PhaseVoltageUL1N
					125	PhaseVoltageUL2N
					126	PhaseVoltageUL3N

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA9977-0TA10 - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA9977-0TA20 - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA9987-0TA10 - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA9987-0TA10 - V4.4						
		Comment	String	Comment		
Module - 3VA9987-0TA20 - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		OrderNumber	String	Article number		
		Name	String	Name		
		ShortDesignation	String	Short designation		
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		OrderNumber	String	Article number		
		Name	String	Name		
		ShortDesignation	String	Short designation		
Module - 3VA2 0xx-xJP3x-xxxx - V4.4						
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 0xx-xJP3x-xxxx - V4.4						
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 0xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 0xx-xJQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 0xx-xJQ3x-xxxx - V4.4						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 0xx-xJQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 0xx-xKP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 0xx-xKP3x-xxxx - V4.4						
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 0xx-xKP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 0xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 0xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 0xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 1xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 1xx-xJP3x-xxxx - V4.4						
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 1xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 1xx-xJQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 1xx-xJQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 1xx-xJQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 1xx-xKP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 1xx-xKP3x-xxxx - V4.4						
		Comment	String	Comment		
Module - 3VA2 1xx-xKP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 1xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 1xx-xKQ4x-xxxx - V4.4					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 1xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 1xx-xMP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 1xx-xMQ3x-xxxx - V4.4						
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 1xx-xMQ3x-xxxx - V4.4						
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 2xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 2xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 2xx-xJP4x-xxxx - V4.4						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 2xx-xJQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 2xx-xJQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 2xx-xJQ4x-xxxx - V4.4						
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 2xx-xKP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 2xx-xKP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 2xx-xKP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 2xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 2xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 2xx-xKQ4x-xxxx - V4.4						
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 2xx-xMP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 2xx-xMQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 2xx-xMQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 3xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 3xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 3xx-xJP4x-xxxx - V4.4						
		Comment	String	Comment		
Module - 3VA2 3xx-xJQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 3xx-xJQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 3xx-xKP3x-xxxx - V4.4					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 3xx-xKP3x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA2 3xx-xKP4x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA2 3xx-xKQ3x-xxxx - V4.4					
	Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 3xx-xKQ3x-xxxx - V4.4						
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 3xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 3xx-xMP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 3xx-xMP3x-xxxx - V4.4						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 3xx-xMQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 4xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 4xx-xJP3x-xxxx - V4.4						
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 4xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 4xx-xJQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
	Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 4xx-xJQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 4xx-xJQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 4xx-xKP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 4xx-xKP3x-xxxx - V4.4						
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 4xx-xKP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 4xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
	Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 4xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 4xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 4xx-xMP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 4xx-xMP3x-xxxx - V4.4						
		Comment	String	Comment		
Module - 3VA2 4xx-xMQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 5xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 5xx-xJP4x-xxxx - V4.4					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 5xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 5xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 5xx-xKQ4x-xxxx - V4.4						
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 5xx-xKQ4x-xxxx - V4.4						
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 5xx-xMP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 5xx-xMQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 5xx-xMQ3x-xxxx - V4.4						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 6xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 6xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 6xx-xJP4x-xxxx - V4.4						
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 6xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 6xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 6xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 6xx-xMQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 xxx-xJPxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 xxx-xJPxx-xxxx - V4.4						
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 xxx-xJQxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 xxx-xKPxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
	Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 xxx-xKPxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 xxx-xKQxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA2 xxx-xMPxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA2 xxx-xMPxx-xxxx - V4.4						
		Comment	String	Comment		
Module - 3VA2 xxx-xMQxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 1xx-xJP4x-xxxx - V4.4					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 1xx-xJP4x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 1xx-xJQ3x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 1xx-xJQ4x-xxxx - V4.4					
	Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 1xx-xJQ4x-xxxx - V4.4						
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xJT3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xJT4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 1xx-xJT4x-xxxx - V4.4						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xKL3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xKL4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 1xx-xKL4x-xxxx - V4.4						
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xKM3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xKM4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 1xx-xKM4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xKP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xKP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 1xx-xKP4x-xxxx - V4.4						
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 1xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xKT3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 1xx-xKT4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 1xx-xKT4x-xxxx - V4.4						
		Comment	String	Comment		
Module - 3VA6 2xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 2xx-xJQ3x-xxxx - V4.4					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 2xx-xJQ3x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 2xx-xJQ4x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 2xx-xJT3x-xxxx - V4.4					
	Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 2xx-xJT3x-xxxx - V4.4						
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xJT4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xKL3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 2xx-xKL3x-xxxx - V4.4						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xKL4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xKM3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 2xx-xKM3x-xxxx - V4.4						
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xKM4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xKP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 2xx-xKP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xKP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 2xx-xKQ3x-xxxx - V4.4						
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xKT3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
	Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 2xx-xKT3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 2xx-xKT4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 3xx-xJP3x-xxxx - V4.4						
		Comment	String	Comment		
Module - 3VA6 3xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xJQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 3xx-xJQ4x-xxxx - V4.4					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 3xx-xJQ4x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 3xx-xJT3x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 3xx-xJT4x-xxxx - V4.4					
	Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 3xx-xJT4x-xxxx - V4.4						
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xKL3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xKL4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 3xx-xKL4x-xxxx - V4.4						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xKM3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xKM4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 3xx-xKM4x-xxxx - V4.4						
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xKP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xKP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
	Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 3xx-xKP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 3xx-xKQ4x-xxxx - V4.4						
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xKT3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 3xx-xKT4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 3xx-xKT4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 4xx-xJP4x-xxxx - V4.4						
		Comment	String	Comment		
Module - 3VA6 4xx-xJQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xJQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 4xx-xJT3x-xxxx - V4.4					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 4xx-xJT3x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 4xx-xJT4x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 4xx-xKL3x-xxxx - V4.4					
	Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 4xx-xKL3x-xxxx - V4.4						
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xKL4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xKM3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 4xx-xKM3x-xxxx - V4.4						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xKM4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xKP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 4xx-xKP3x-xxxx - V4.4						
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xKP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 4xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xKT3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 4xx-xKT3x-xxxx - V4.4						
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 4xx-xKT4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 5xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 5xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 5xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 5xx-xJQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 5xx-xJQ3x-xxxx - V4.4						
		Comment	String	Comment		
Module - 3VA6 5xx-xJQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 5xx-xJT3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 5xx-xJT4x-xxxx - V4.4					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 5xx-xJT4x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 5xx-xKL3x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 5xx-xKL4x-xxxx - V4.4					
	Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 5xx-xKL4x-xxxx - V4.4						
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 5xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 5xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 5xx-xKQ4x-xxxx - V4.4						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 5xx-xKT3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 5xx-xKT4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 5xx-xKT4x-xxxx - V4.4						
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 6xx-xJP3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 6xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 6xx-xJP4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 6xx-xJQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 6xx-xJQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 6xx-xJQ4x-xxxx - V4.4						
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 6xx-xJT3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 6xx-xJT4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Submodules					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 6xx-xJT4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 6xx-xKL3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 6xx-xKL4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 6xx-xKL4x-xxxx - V4.4						
		Comment	String	Comment		
Module - 3VA6 6xx-xKQ3x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 6xx-xKQ4x-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 6xx-xKT3x-xxxx - V4.4					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 6xx-xKT3x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 6xx-xKT4x-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 xxx-xJPxx-xxxx - V4.4					
	Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 xxx-xJPxx-xxxx - V4.4						
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 xxx-xJQxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 xxx-xJTxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		InstallationDate	DateTime	Installation date		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 xxx-xJTxx-xxxx - V4.4						
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 xxx-xKLxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 xxx-xKMxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		LocationIdentifier	String	Location identifier		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 xxx-xKMxx-xxxx - V4.4						
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 xxx-xKPxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
	Submodules					
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 3VA6 xxx-xKQxx-xxxx - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
	Submodules					

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA6 xxx-xKQxx-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA6 xxx-xKTxx-xxxx - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	InstallationDate	DateTime	Installation date		
	PlantDesignation	String	Plant designation		
	LocationIdentifier	String	Location identifier		
	AdditionalInformation	String	Additional information		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Submodules					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA9 177_0TB10 - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA9 187_0TB10 - V4.4					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
Module - 3VA9 377_0TB10 - V4.4					
	Name	String			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
		Author	String	Author		

Channel Range		Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 3VA9 377_0TB10 - V4.4						
		Comment	String	Comment		
Module - 3VA9 387_0TB10 - V4.4						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
Module - 7KM9300-0AB01-0AA0 - V4.0						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostics interrupt (OB82)		
		Comment	String	Comment		
		Author	String	Author		
		HardwareInterrupt	Boolean	Hardware interrupts (OB40 to OB 47)		
		DpWatchdog	Boolean	Watchdog		
Module - 7KM9300-0AB01-0AA0 - V4.1						
		InterfaceType	Int32			
		InterfaceOperatingModes	Int32			
		Label	String			
		Name	String			
		DiagnosticsInterrupt	Boolean	Diagnostics interrupt (OB82)		
		Comment	String	Comment		
		Author	String	Author		
		HardwareInterrupt	Boolean	Hardware interrupts (OB40 to OB 47)		
		DpWatchdog	Boolean	Watchdog		
Module - 7KM9300-0AE01-0AA0 - V2.1						
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		MediaRedundancyRole	UInt64			
		MrpDiagnosticInterrupts	Boolean			
		AlternativeRedundancy	Boolean			

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 7KM9300-0AE01-0AA0 - V2.1						
		Label	String			
		InterfaceOperatingModes	Int32			
		InterfaceType	Int32			
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		OperatingMode	UInt64	IO device		
	Port					
		EndOfDetectionOfAccessibleDevices	Boolean			
		EndOfTopologyDiscovery	Boolean			
		PortActivation	Boolean			
		TransmissionRateAutoNegotiation	Boolean			
		PortMonitoring	Boolean			
		TransmissionRateAndDuplex	Int32			
		EndOfSyncDomain	Boolean			
		RingPort	Boolean			
		SignalDelaySelection	Byte[]			
		CableLength	Int32			
		SignalDelayTime	Double			
		CableName	UInt64			
		Label	String			
		MediumAttachmentType	Byte[]			
		AlternativePartnerPorts	Boolean			
		Name	String			
		Comment	String	Comment		
		PositionNumber	Int32	Slot		
		Name	String	Name		
Module - 7KM9300-0AE02-0AA0 - V3.0						
		IECV22LLDPMode	Boolean			
		DiagnosticsCommunicationError	Boolean			
		KeepAlivesInterval	UInt32			
		LoadLimitation	Boolean			
		KeepAlivesInterval	UInt32			
		MediaRedundancyRole	UInt64			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 7KM9300-0AE02-0AA0 - V3.0					
	MrpDiagnosticInterrupts	Boolean			
	AlternativeRedundancy	Boolean			
	Label	String			
	InterfaceOperatingModes	Int32			
	InterfaceType	Int32			
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	OperatingMode	UInt64	IO device		
Port					
	EndOfDetectionOfAccessibleDevices	Boolean			
	EndOfTopologyDiscovery	Boolean			
	PortActivation	Boolean			
	TransmissionRateAutoNegotiation	Boolean			
	PortMonitoring	Boolean			
	TransmissionRateAndDuplex	Int32			
	EndOfSyncDomain	Boolean			
	RingPort	Boolean			
	SignalDelaySelection	Byte[]			
	CableLength	Int32			
	SignalDelayTime	Double			
	CableName	UInt64			
	Label	String			
	MediumAttachmentType	Byte[]			
	AlternativePartnerPorts	Boolean			
	Name	String			
	Comment	String	Comment		
	PositionNumber	Int32	Slot		
	Name	String	Name		
Module - 7KM9200-0AD00-0AA0 - V1.0					
	Name	String			
	Author	String	Author		
	Comment	String	Comment		
	PlantDesignation	String	Plant designation		

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module - 7KM9200-0AD00-0AA0 - V1.0						
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
Module - 7KM3220-xBA01-1xA0 - V3.1						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
Module - 7KM3220-xBA01-1xA0 - V3.2						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			
Module - 7KM421x-xBx00-xAA0 - V2.3						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		InstallationDate	DateTime	Installation date		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		AdditionalInformation	String	Additional information		
	Submodules					
		Name	String			

Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module					

	Channel Range	Property	DataType	Label	EomAtom Value	EomAtom Description
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		PlantDesignation	String	Plant designation		
		LocationIdentifier	String	Location identifier		
		InstallationDate	DateTime	Installation date		
		AdditionalInformation	String	Additional information		
Module						
		Author	String	Author		
		Comment	String	Comment		
		Name	String	Name		
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		OrderNumber	String	Article number		
Module						
		Name	String			
		Author	String	Author		
		Comment	String	Comment		
		OrderNumber	String	Article number		