

User Manual

Piera-1 Evaluation Kit (PEK)

(SenseiPM Software Guide)

Version 1.1

Piera Systems Inc.
Copyright © 2020 Piera Systems Inc.



User Manual for Piera-1 Evaluation Kit (PEK)

SenseiPM Software Guide

Version 1.1

Table of Contents

1. Introduction	2
2. Piera-1 Evaluation Kit (PEK).....	2
3. Getting Started with SenseiPM.....	3
3.1. System Requirements	3
3.2. Installation	3
4. How to Use SenseiPM.....	7
4.1. SenseiPM.....	7
4.2. Connecting Piera-1.....	8
4.3. SenseiPM Functions	8
5. Appendix – Brief Application Note	14
5.1. Requirements	14
5.2. Configuration	14
5.3. Commands	15
5.4. Remarks	15

Piera Systems Inc. reserves the right to make corrections, modifications enhancements, improvements and other changes to its products, documents and services at any time and to discontinue any product or service without notice. Please contact Piera Systems anytime to obtain the latest relevant information.



1. Introduction

Piera System's Intelligent Particulate Sensor (IPS), **Piera-1** uses a breakthrough approach for detecting and measuring the quantity and size of particles suspended in air with precision. Piera-1 has unparalleled accuracy, and can detect ultrafine submicron particles (PM0.1-PM10) in real-time, with low power consumption. Piera-1 uses a patented, photon-counting custom ASIC to deliver a highly sensitive optoelectronic particulate sensor. It can be programmed to detect a wide range of particle sizes allowing for a single sensor to be used in many applications.

Piera Systems also offer a software called **SenseiPM**, a dedicated software for viewing and logging data from Piera-1. The software allows users to obtain an intuitive real-time information of different sized airborne particles via plots of particle count and mass concentration data. SenseiPM features a data-logging capabilities and data can be exported to .csv file format with time stamp.

SenseiPM offers a function to let users to adjust some key electrical settings (threshold voltage and AFE gain) for Piera-1. This feature is protected by an access code, and not available for all customers. Please contact Piera Systems info@pierasystems.com for more information.

2. Piera-1 Evaluation Kit (PEK)

A PEK includes one Piera-1 unit, a USB cable, SenseiPM software along with this manual. The kit box contains Piera-1 and cable while SenseiPM and soft copies of other documentations can be found in the downloadable SenseiPM.zip file provided electronically.

Please refer to the ReadMe.txt in the SenseiPM.zip file to check the software version.



Piera-1 Evaluation Kit (PEK) box and its contents

Piera Systems Inc. reserves the right to make corrections, modifications enhancements, improvements and other changes to its products, documents and services at any time and to discontinue any product or service without notice. Please contact Piera Systems anytime to obtain the latest relevant information.


3. Getting Started with SenseiPM

3.1. System Requirements

Windows 10, at least 4.1MB disk space is needed. SenseiPM version 1.0.0 runs only on PC, and does not support MacOS. Requires USB port (standard USB-A).


3.2. Installation

- 3.2.1. Download the SenseiPM.zip and unzip the file under a desired directory. In this example, the file is under “This PC > Downloads > SenseiPM” folder.




Step 1

- 3.2.2. Navigate to the directory where the file is saved. Run “SenseiPM.exe” it as administrator by right clicking the SenseiPM icon.




Step 2

- 3.2.3. Read through the software license agreement on the dialogue box, and select “I accept the agreement” checkbox to continue with the installation. Click “Next” to proceed. Click “Cancel” to quit the installation process any time.



Step 3

- 3.2.4. Next, a disclaimer will be presented. Read it carefully and click “Next” once ready.




Step 4

Piera Systems Inc. reserves the right to make corrections, modifications enhancements, improvements and other changes to its products, documents and services at any time and to discontinue any product or service without notice. Please contact Piera Systems anytime to obtain the latest relevant information.




- 3.2.5. SenseiPM will be installed under C:\Program Files (x86) by default. Choose a desired destination location by clicking “Browse.” A folder named “SenseiPM” will be created at the target location, which will contain the application files. Click “Next.”



Step 5

- 3.2.6. Select “Create a desktop shortcut” checkbox (optional).




Step 6

Piera Systems Inc. reserves the right to make corrections, modifications enhancements, improvements and other changes to its products, documents and services at any time and to discontinue any product or service without notice. Please contact Piera Systems anytime to obtain the latest relevant information.




- 3.2.7. Confirm the current installation information, and click “Install.” Click “Back” to change or review your installation settings.



Step 7

- 3.2.8. Click “Finish” to exit setup and launch the application once the installation is completed. Uncheck the “Launch SenseiPM” and click “Finish” to exit setup without launching.



Step 8

Piera Systems Inc. reserves the right to make corrections, modifications enhancements, improvements and other changes to its products, documents and services at any time and to discontinue any product or service without notice. Please contact Piera Systems anytime to obtain the latest relevant information.

4. How to Use SenseiPM

Run SenseiPM application as administrator from your desktop shortcut. If the “Launch SenseiPM” box was unchecked, the application would need to be launched from your installation directory.

Click “Yes” on the Windows User Account Control dialogue box to allow Windows to run the application.

Home Screen as shown in Fig. 1 will appear.

4.1. SenseiPM

Fig. 1. illustrates the home screen of SenseiPM. The number labeled windows are explained below.

- Section 1: The local system’s date and time display window.
- Section 2: Main control window.
- Sections 3-9: Real-time plotting windows for PM0.1, PM0.3, PM0.5, PM1.0, PM2.5, PM5.0, and PM10 respectively, either in particle counts or mass concentration.

Clicking the Piera Systems logo will take you to Piera Systems’ website.




Fig. 1. Home screen of SenseiPM

4.2. Connecting Piera-1

Connect Piera-1 to the PC where SenseiPM is installed with a provided USB cable and sync the sensor with SenseiPM by clicking “Search” button on the section 2. A “Failure” window will pop up if no sensor is connected or there is a problem with the connection. Please contact Piera Systems support team for trouble shooting.

Once a Piera-1 is detected and synced, the “Start” button will become active, and the systems is ready for data gathering.




Fig. 2. Main control window before connecting Piera-1

4.3. SenseiPM Functions

4.3.1. Main Control Window:

The window on section 2 shows the list of sensors connected. More than 1 Piera-1 units can be connected simultaneously using a multi USB port. The user can choose to enable or disable data transfer from any connected sensor with the checkbox under “Select.”

Click the “Start” button to start reading data from Piera-1. The button will change to “Stop,” if “Start” button is clicked. Click the “Stop” button to halt data gathering, and “Stop” button will change back to “Start.”

If the box under “Select” is unchecked, plots will not be displayed. Checking the “Log” checkbox will record the data in .csv format, which will be saved under “data” folder in the installation directory. Refer to Fig. 3.




Fig. 3. Main control window after connecting Piera-1

The blue gear icon under “Config” is for modifying various parameters for each sensor. This parameter configuration feature is not available for all customers. User is not permitted to reconfigure the default system settings of each sensor without a Piera Systems’ consent and the password.

Clicking on the icon will open a pop-up login window asking for an access password.




Fig. 4. Login window

If you have the password, enter it and press “Ok” to change the sensor parameters that allow Piera-1 to be more versatile by changing its sensitivity and detection range depending on applications.

Fig. 6 below is an example of SenseiPM in action with one Piera-1 unit connected.




Fig. 6. Home screen of SenseiPM plotting data

4.3.2. Changing Output Units:

Navigate to the top left of the home screen and select either “Number” or “Mass.” By default “Number” tab is selected, which plots data in number of particles per cubic feet (displays as N/CF). If “Mass” tab is chosen, the plots will display the results in micrograms per cubic feet (ug/CF). Refer to Fig. 7, reference number 1.

Note that the mass concentration values should only be considered as indicative values. It should also be noted that PM0.1 data is not fully calibrated yet. Please contact Piera Systems for more details.

Always evaluate Piera-1 based on particle count readings for PM0.3 and above.




Fig. 7. Settings

4.3.3. Display Settings:

Click on the blue gear icon next to each of the plot windows (Section 3-9) to change axis settings for respective bins. Refer to Fig. 7, reference number 2.

- X-axis interval: Set to “0” by default, which is for continuous plotting.
- X-axis X range: Set the range of X-axis in seconds (default time span is 50s).
- Y-axis AutoScale: Selected by default. Turn this feature off by unchecking the box.
- Y-axis Y min: Set the minimum value of the Y-axis (in N/CF or ug/CF).
- Y-axis Y max: Set the maximum value of the Y-axis (in N/CF or ug/CF).
- Chart Line color: Change color of the plot by selecting different colors on the dropdown menu. Red is selected by default.

4.3.4. Accessing Data Log File:

Click on the “File” menu on the top left corner, and select “Open Logging Folder.” The folder containing the log file will open, where .csv data log file can be found. Data will be stored with time stamp. Log file will only be generated if the checkbox under “Log” on the main control window is selected.




Fig. 7. Accessing data log folder

	A	B	C	D	E	F	G	H	I	J	K	L	M	N	O
1	2020-06-05 12-22-51-result.csv														
2	PM0.1 (N/ PM0.3 (N/ PM0.5 (N/ PM1.0 (N/ PM2.5 (N/ PM5.0 (N/ PM10.0 (N/ PM0.1 (ug PM0.3 (ug PM0.5 (ug PM1.0 (ug PM2.5 (ug PM5.0 (ug PM10.0 (u														
3	2020-06-0	4752	3960	330	23	4	0	0	3.99E-06	8.93E-05	3.45E-05	1.92E-05	5.22E-05	0	0
4	2020-06-0	4708	3924	327	23	4	0	0	3.95E-06	8.85E-05	3.42E-05	1.92E-05	5.22E-05	0	0
5	2020-06-0	4665	3888	324	23	4	0	0	3.92E-06	8.77E-05	3.38E-05	1.92E-05	5.22E-05	0	0
6	2020-06-0	4708	3924	327	23	4	1386	154	3.95E-06	8.85E-05	3.42E-05	1.92E-05	5.22E-05	0.144698	0.128676
7	2020-06-0	4752	3960	330	23	4	0	0	3.99E-06	8.93E-05	3.45E-05	1.92E-05	5.22E-05	0	0
8	2020-06-0	4795	3996	333	23	4	0	0	4.03E-06	9.01E-05	3.48E-05	1.92E-05	5.22E-05	0	0
9	2020-06-0	4838	4032	336	24	4	0	0	4.06E-06	9.10E-05	3.51E-05	2.01E-05	5.22E-05	0	0
10	2020-06-0	4886	4072	339	24	4	0	0	4.10E-06	9.19E-05	3.54E-05	2.01E-05	5.22E-05	0	0
11	2020-06-0	4934	4112	342	24	4	0	0	4.14E-06	9.28E-05	3.57E-05	2.01E-05	5.22E-05	0	0
12	2020-06-0	4886	4072	339	24	4	0	0	4.10E-06	9.19E-05	3.54E-05	2.01E-05	5.22E-05	0	0
13	2020-06-0	4838	4032	336	24	4	0	0	4.06E-06	9.10E-05	3.51E-05	2.01E-05	5.22E-05	0	0
14	2020-06-0	4790	3992	332	23	4	0	0	4.02E-06	9.01E-05	3.47E-05	1.92E-05	5.22E-05	0	0
15	2020-06-0	4747	3956	329	23	4	0	0	3.99E-06	8.92E-05	3.44E-05	1.92E-05	5.22E-05	0	0
16	2020-06-0	4704	3920	326	23	4	0	0	3.95E-06	8.84E-05	3.40E-05	1.92E-05	5.22E-05	0	0
17	2020-06-0	4660	3884	323	23	4	0	0	3.91E-06	8.76E-05	3.37E-05	1.92E-05	5.22E-05	0	0
18	2020-06-0	4617	3848	320	22	4	0	0	3.88E-06	8.68E-05	3.34E-05	1.84E-05	5.22E-05	0	0
19	2020-06-0	4574	3812	317	22	4	0	0	3.84E-06	8.60E-05	3.31E-05	1.84E-05	5.22E-05	0	0
20	2020-06-0	4531	3776	314	22	4	0	0	3.81E-06	8.52E-05	3.28E-05	1.84E-05	5.22E-05	0	0
21	2020-06-0	4488	3740	311	22	4	0	0	3.77E-06	8.44E-05	3.25E-05	1.84E-05	5.22E-05	0	0
22	2020-06-0	4444	3704	308	22	4	0	0	3.73E-06	8.36E-05	3.22E-05	1.84E-05	5.22E-05	0	0
23	2020-06-0	4401	3668	305	21	4	0	0	3.70E-06	8.28E-05	3.19E-05	1.75E-05	5.22E-05	0	0

Fig. 8. Example data log file

4.3.5. Version Information:

Click on the “Help” menu and select “About” to find out the current version of SenseiPM. A dialogue box with the current version information will appear.




Fig. 9. Version information

4.3.6. Notes:

The module cleaning feature will be implemented in the upcoming versions of SenseiPM.

Fully functional programmable bin size adjusting feature will be available on the next versions of Piera Systems' IPS products.

4.3.7. Troubleshooting:

Please send your inquiries to info@pierasystems.com.

5. Appendix – Brief Application Note

It is possible to test or integrate Piera-1 sensor module without SenseiPM or a provided USB cable. The user is required to build a custom cable to connect Piera-1 to a PC, and will have to get a serial data monitoring software such as PuTTY.

5.1. Requirements

- 5.1.1. A USB to RS232 TTL UART PL2303HX auto converter cable adapter module (5V). 5-pin female connector head (1.5mm pitch) is recommended for secure connection.



- 5.1.2. A serial data monitoring software.



5.2. Configuration

- 5.2.1. Connect Piera-1 sensor module and PC using a custom USB cable.
- 5.2.2. Run serial data monitoring software.
- 5.2.3. Select the right COM port and set the speed or baud rate to 115,200 with standard configuration – 1 stop, no parity and 8-bit to establish connection.
- 5.2.4. The system is ready once device is connected to the PC successfully.



5.3. Commands

A table of command lines will be provided with the configuration access code for a qualified customer. Please contact Piera Systems for more information.

5.4. Remarks

Piera-1 is primarily designed for indoor use. User is advised to operate Piera-1 under the standard room environment.

It is not recommended to use a custom cable that exceeds 6ft in length. Piera Systems will not be responsible for any inaccurate data nor interpretation of such data obtained with longer than 6ft cable.



Version Control

Version	Date	Description
0.1	06/01/2020	Document created
0.2	06/05/2020	Edited for formatting
0.3	06/06/2020	Updated contents and changed design
0.4	06/06/2020	Added contents and font changed
1.0	06/07/2020	Official document release
1.1	06/07/2020	Minor content edited

Piera Systems Inc. reserves the right to make corrections, modifications enhancements, improvements and other changes to its products, documents and services at any time and to discontinue any product or service without notice. Please contact Piera Systems anytime to obtain the latest relevant information.



Piera Systems

Innovation Complex L1240, 3359 Mississauga Rd., Mississauga, ON L5L 1C6 Canada

info@pierasystems.com

Piera Systems Inc. reserves the right to make corrections, modifications enhancements, improvements and other changes to its products, documents and services at any time and to discontinue any product or service without notice. Please contact Piera Systems anytime to obtain the latest relevant information.