

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Camera
Manufacturer: Atlona
Firmware Version: N/A
Model(s): AT-HDVS-CAM

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.15.0000-b004	2.14.0

Version History

Module Version	Date	Notes
1_0_1_0	6/23/2022	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- DeviceID variable must be set accordingly. Default value is '1'. DeviceID ranges from '1' to '7'.
Example: `InterfaceName.DeviceID = '1'`

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='AT-HDVS-CAM')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='AT-HDVS-CAM')</code>
EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 52381, Model='AT-HDVS-CAM')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	Value	
Backlight	'On'	'Off'	
# Backlight example InterfaceName.Set('Backlight', 'On')			
Command	Value	Value	Value
Focus	'Near'	'Far'	'Stop'
# Focus example InterfaceName.Set('Focus', 'Near')			
Command	Value	Value	
FocusMode	'Auto'	'Manual'	
# FocusMode example InterfaceName.Set('FocusMode', 'Auto')			
Command	Value	Value	Value
Iris	'Reset'	'Up'	'Down'
# Iris example InterfaceName.Set('Iris', 'Reset')			
Command	Value	Value	Value
PanTilt	'Up'	'Down'	'Left'
	'Right'	'Up Left'	'Up Right'
	'Down Left'	'Down Right'	'Stop'
Qualifier Key	Qualifier Value		
'Pan Speed'	'1' – '24'		
Qualifier Key	Qualifier Value		
'Tilt Speed'	'1' – '20'		
# PanTilt example InterfaceName.Set('PanTilt', 'Up', {'Pan Speed': '1', 'Tilt Speed': '1'})			
Command	Value	Value	
Power	'On'	'Off'	
# Power example InterfaceName.Set('Power', 'On')			
Command	Value		
PresetRecall	'0' – '9'		
# PresetRecall example InterfaceName.Set('PresetRecall', '0')			
Command	Value		
PresetSave	'0' – '9'		
# PresetSave example InterfaceName.Set('PresetSave', '0')			

Global Scripter Module Communication Sheet

Command VideoSystem	Value	Value	Value
	'1080P60'	'1080P50'	'1080i60'
	'1080i50'	'720P60'	'720P50'
	'1080P30'	'1080P25'	'720P30'
	'720P25'	'1080P59.94'	'1080i59.94'
	'720P59.94'	'1080P29.97'	'720P29.97'
# VideoSystem example InterfaceName.Set('VideoSystem', '1080P60')			
Command WhiteBalance	Value	Value	Value
	'Auto'	'3000K'	'4000K'
	'One Push Mode'	'5000K'	'Manual'
	'6500K'		
# WhiteBalance example InterfaceName.Set('WhiteBalance', 'Auto')			
Command Zoom	Value	Value	Value
	'Tele'	'Wide'	'Stop'
Qualifier Key 'Speed'	Qualifier Value '0' – '7'		
# Zoom example InterfaceName.Set('Zoom', 'Tele', {'Speed': '0'})			

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})  
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})  
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},  
FeedbackHandler)
```

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)  
Value = InterfaceName.ReadStatus(Command)  
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)  
FeedbackHandler will be called when any qualifier gets a new status.
```

Command	Value	Value	
Backlight	'On'	'Off'	
# Backlight example InterfaceName.Update('Backlight') Value = InterfaceName.ReadStatus('Backlight') InterfaceName.SubscribeStatus('Backlight', None, FeedbackHandler)			
Command	Value	Value	
ConnectionStatus	'Connected'	'Disconnected'	
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command	Value	Value	
FocusMode	'Auto'	'Manual'	
# FocusMode example InterfaceName.Update('FocusMode') Value = InterfaceName.ReadStatus('FocusMode') InterfaceName.SubscribeStatus('FocusMode', None, FeedbackHandler)			
Command	Value	Value	
Power	'On'	'Off'	
# Power example InterfaceName.Update('Power') Value = InterfaceName.ReadStatus('Power') InterfaceName.SubscribeStatus('Power', None, FeedbackHandler)			
Command	Value	Value	Value
VideoSystem	'1080P60'	'1080P50'	'1080i60'
	'1080i50'	'720P60'	'720P50'
	'1080P30'	'1080P25'	'720P30'
	'720P25'	'1080P59.94'	'1080i59.94'
	'720P59.94'	'1080P29.97'	'720P29.97'
# VideoSystem example InterfaceName.Update('VideoSystem') Value = InterfaceName.ReadStatus('VideoSystem') InterfaceName.SubscribeStatus('VideoSystem', None, FeedbackHandler)			

Global Scripter Module Communication Sheet

Command	Value	Value	Value
WhiteBalance	'Auto'	'3000K'	'4000K'
	'One Push Mode'	'5000K'	'Manual'
	'6500K'		
<pre># WhiteBalance example InterfaceName.Update('WhiteBalance') Value = InterfaceName.ReadStatus('WhiteBalance') InterfaceName.SubscribeStatus('WhiteBalance', None, FeedbackHandler)</pre>			

Cable and Adapter Requirements

Captive Screw to DIN-8 VISCA Serial Cable

Notes for the Device

Serial communication

Port Type: RS-232

Baud Rate: 9600


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	5	RxD
RxD	←	3	TxD
GND	→	4	GND



Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type: Ethernet (UDP)

Device Listen Port: 52381

Device Reply Port: 0

Logon Credentials No

Supported:

Multi-Connection Undetermined

Capabilities:

Port Changeability: Yes

Ethernet Module Configuration Description

- Please refer to user manual for settings and changes to the network communication
- When using multiple UDP drivers within the same configuration each driver should have a unique 'Reply on Port' number due to the nature of UDP communication. If you have a driver with a fixed 'Reply on Port' number, only one instance of the driver can be used within the configuration.

Notes for the Device

Appendix A. Set Commands (Serial, Device ID: 1)

Backlight Off	\x81\x01\x043\x03\xff
Backlight On	\x81\x01\x043\x02\xff
Focus Far	\x81\x01\x04\x08\x03\xff
Focus Mode Auto	\x81\x01\x048\x02\xff
Focus Mode Manual	\x81\x01\x048\x03\xff
Focus Near	\x81\x01\x04\x08\x02\xff
Focus Stop	\x81\x01\x04\x08\x00\xff
Iris Down	\x81\x01\x04\x0B\x03\xff
Iris Reset	\x81\x01\x04\x0B\x00\xff
Iris Up	\x81\x01\x04\x0B\x02\xff
Pan Tilt Down Left Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\xff
Pan Tilt Down Left Pan Speed 1 Tilt Speed 20	\x81\x01\x06\x01\x01\x14\x01\x02\xff
Pan Tilt Down Left Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\xff
Pan Tilt Down Left Pan Speed 24 Tilt Speed 20	\x81\x01\x06\x01\x18\x14\x01\x02\xff
Pan Tilt Down Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x03\x02\xff
Pan Tilt Down Pan Speed 1 Tilt Speed 20	\x81\x01\x06\x01\x01\x14\x03\x02\xff
Pan Tilt Down Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x02\xff
Pan Tilt Down Pan Speed 24 Tilt Speed 20	\x81\x01\x06\x01\x18\x14\x03\x02\xff
Pan Tilt Down Right Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x02\x02\xff
Pan Tilt Down Right Pan Speed 1 Tilt Speed 20	\x81\x01\x06\x01\x01\x14\x02\x02\xff
Pan Tilt Down Right Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x02\xff
Pan Tilt Down Right Pan Speed 24 Tilt Speed 20	\x81\x01\x06\x01\x18\x14\x02\x02\xff
Pan Tilt Left Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\xff
Pan Tilt Left Pan Speed 1 Tilt Speed 20	\x81\x01\x06\x01\x01\x14\x01\x03\xff
Pan Tilt Left Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\x03\xff
Pan Tilt Left Pan Speed 24 Tilt Speed 20	\x81\x01\x06\x01\x18\x14\x01\x03\xff
Pan Tilt Right Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x02\x03\xff
Pan Tilt Right Pan Speed 1 Tilt Speed 20	\x81\x01\x06\x01\x01\x14\x02\x03\xff
Pan Tilt Right Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x03\xff
Pan Tilt Right Pan Speed 24 Tilt Speed 20	\x81\x01\x06\x01\x18\x14\x02\x03\xff
Pan Tilt Stop Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x03\x03\xff
Pan Tilt Stop Pan Speed 1 Tilt Speed 20	\x81\x01\x06\x01\x01\x14\x03\x03\xff
Pan Tilt Stop Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x03\xff
Pan Tilt Stop Pan Speed 24 Tilt Speed 20	\x81\x01\x06\x01\x18\x14\x03\x03\xff
Pan Tilt Up Left Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x01\xff
Pan Tilt Up Left Pan Speed 1 Tilt Speed 20	\x81\x01\x06\x01\x01\x14\x01\x01\xff
Pan Tilt Up Left Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\x01\xff
Pan Tilt Up Left Pan Speed 24 Tilt Speed 20	\x81\x01\x06\x01\x18\x14\x01\x01\xff
Pan Tilt Up Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x03\x01\xff
Pan Tilt Up Pan Speed 1 Tilt Speed 20	\x81\x01\x06\x01\x01\x14\x03\x01\xff
Pan Tilt Up Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x01\xff
Pan Tilt Up Pan Speed 24 Tilt Speed 20	\x81\x01\x06\x01\x18\x14\x03\x01\xff

Global Scriptor Module Communication Sheet

Pan Tilt Up Right Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x02\x01\xff
Pan Tilt Up Right Pan Speed 1 Tilt Speed 20	\x81\x01\x06\x01\x01\x14\x02\x01\xff
Pan Tilt Up Right Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x01\xff
Pan Tilt Up Right Pan Speed 24 Tilt Speed 20	\x81\x01\x06\x01\x18\x14\x02\x01\xff
Power Off	\x81\x01\x04\x00\x03\xff
Power On	\x81\x01\x04\x00\x02\xff
Preset Recall 0	\x81\x01\x04?\x02\x00\xff
Preset Recall 9	\x81\x01\x04?\x02\x09\xff
Preset Save 0	\x81\x01\x04?\x01\x00\xff
Preset Save 9	\x81\x01\x04?\x01\x09\xff
Video System 1080i50	\x81\x01\x065\x00\x03\xff
Video System 1080i59.94	\x81\x01\x065\x00\x0B\xff
Video System 1080i60	\x81\x01\x065\x00\x02\xff
Video System 1080P25	\x81\x01\x065\x00\x07\xff
Video System 1080P29.97	\x81\x01\x065\x00\x0D\xff
Video System 1080P30	\x81\x01\x065\x00\x06\xff
Video System 1080P50	\x81\x01\x065\x00\x01\xff
Video System 1080P59.94	\x81\x01\x065\x00\x0A\xff
Video System 1080P60	\x81\x01\x065\x00\x00\xff
Video System 720P25	\x81\x01\x065\x00\x09\xff
Video System 720P29.97	\x81\x01\x065\x00\x0E\xff
Video System 720P30	\x81\x01\x065\x00\x08\xff
Video System 720P50	\x81\x01\x065\x00\x05\xff
Video System 720P59.94	\x81\x01\x065\x00\x0C\xff
Video System 720P60	\x81\x01\x065\x00\x04\xff
White Balance 3000K	\x81\x01\x045\x01\xff
White Balance 4000K	\x81\x01\x045\x02\xff
White Balance 5000K	\x81\x01\x045\x04\xff
White Balance 6500K	\x81\x01\x045\x06\xff
White Balance Auto	\x81\x01\x045\x00\xff
White Balance Manual	\x81\x01\x045\x05\xff
White Balance One Push Mode	\x81\x01\x045\x03\xff
Zoom Stop Speed 0	\x81\x01\x04\x07\x00\xff
Zoom Stop Speed 7	\x81\x01\x04\x07\x00\xff
Zoom Tele Speed 0	\x81\x01\x04\x07 \xff
Zoom Tele Speed 7	\x81\x01\x04\x07' \xff
Zoom Wide Speed 0	\x81\x01\x04\x070\xff
Zoom Wide Speed 7	\x81\x01\x04\x077\xff

Appendix B. Update Commands (Serial, Device ID: 1)

Backlight	\x81\x09\x043\xff
Focus Mode	\x81\x09\x048\xff
Power	\x81\x09\x04\x00\xff
Video System	\x81\x09\x06#\xff
White Balance	\x81\x09\x045\xff

Appendix C. Set Commands (Ethernet, Device ID: 1)

Backlight Off	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x043\x03\xFF
Backlight On	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x043\x02\xFF
Focus Far	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x08\x03\xFF
Focus Mode Auto	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x048\x02\xFF
Focus Mode Manual	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x048\x03\xFF
Focus Near	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x08\x02\xFF
Focus Stop	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x08\x00\xFF
Iris Down	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0B\x03\xFF
Iris Reset	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0B\x00\xFF
Iris Up	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0B\x02\xFF
Pan Tilt Down Left Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x02\xFF
Pan Tilt Down Left Pan Speed 1 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x14\x02\xFF
Pan Tilt Down Left Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x02\xFF
Pan Tilt Down Left Pan Speed 24 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x14\x02\xFF
Pan Tilt Down Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x03\x02\xFF
Pan Tilt Down Pan Speed 1 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x14\x03\x02\xFF
Pan Tilt Down Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x03\x02\xFF
Pan Tilt Down Pan Speed 24 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x14\x03\x02\xFF
Pan Tilt Down Right Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x02\x02\xFF
Pan Tilt Down Right Pan Speed 1 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x14\x02\x02\xFF
Pan Tilt Down Right Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x02\x02\xFF
Pan Tilt Down Right Pan Speed 24 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x14\x02\x02\xFF
Pan Tilt Left Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x03\xFF
Pan Tilt Left Pan Speed 1 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x14\x01\x03\xFF
Pan Tilt Left Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x01\x03\xFF
Pan Tilt Left Pan Speed 24 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x14\x01\x03\xFF
Pan Tilt Right Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x02\x03\xFF

Global Scriptor Module Communication Sheet

Revision: 6/23/2022

Pan Tilt Right Pan Speed 1 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x14\x02\x03\xFF
Pan Tilt Right Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x02\x03\xFF
Pan Tilt Right Pan Speed 24 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x14\x02\x03\xFF
Pan Tilt Stop Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x03\x03\xFF
Pan Tilt Stop Pan Speed 1 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x14\x03\x03\xFF
Pan Tilt Stop Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x03\x03\xFF
Pan Tilt Stop Pan Speed 24 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x14\x03\x03\xFF
Pan Tilt Up Left Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x01\x01\xFF
Pan Tilt Up Left Pan Speed 1 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x14\x01\x01\xFF
Pan Tilt Up Left Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x01\x01\xFF
Pan Tilt Up Left Pan Speed 24 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x14\x01\x01\xFF
Pan Tilt Up Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x03\x01\xFF
Pan Tilt Up Pan Speed 1 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x14\x03\x01\xFF
Pan Tilt Up Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x03\x01\xFF
Pan Tilt Up Pan Speed 24 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x14\x03\x01\xFF
Pan Tilt Up Right Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x02\x01\xFF
Pan Tilt Up Right Pan Speed 1 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x14\x02\x01\xFF
Pan Tilt Up Right Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x02\x01\xFF
Pan Tilt Up Right Pan Speed 24 Tilt Speed 20	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x14\x02\x01\xFF
Power Off	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x00\x03\xFF
Power On	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x00\x02\xFF
Preset Recall 0	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x04?\x02\x00\xFF
Preset Recall 9	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x04?\x02\x09\xFF
Preset Save 0	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x04?\x01\x00\xFF
Preset Save 9	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x04?\x01\x09\xFF
Video System 1080i50	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x03\xFF
Video System 1080i59.94	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x0B\xFF

Global Scripter Module Communication Sheet

Revision: 6/23/2022

Video System 1080i60	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x02\xFF
Video System 1080P25	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x07\xFF
Video System 1080P29.97	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x0D\xFF
Video System 1080P30	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x06\xFF
Video System 1080P50	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x01\xFF
Video System 1080P59.94	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x0A\xFF
Video System 1080P60	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x00\xFF
Video System 720P25	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x09\xFF
Video System 720P29.97	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x0E\xFF
Video System 720P30	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x08\xFF
Video System 720P50	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x05\xFF
Video System 720P59.94	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x0C\xFF
Video System 720P60	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x065\x00\x04\xFF
White Balance 3000K	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x01\xFF
White Balance 4000K	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x02\xFF
White Balance 5000K	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x04\xFF
White Balance 6500K	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x06\xFF
White Balance Auto	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x00\xFF
White Balance Manual	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x05\xFF
White Balance One Push Mode	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x03\xFF
Zoom Stop Speed 0	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x07\x00\xFF
Zoom Stop Speed 7	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x07\x00\xFF
Zoom Tele Speed 0	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x07 \xFF
Zoom Tele Speed 7	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x07' \xFF
Zoom Wide Speed 0	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x070\xFF
Zoom Wide Speed 7	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x077\xFF

Appendix D. Update Commands (Ethernet, Device ID: 1)

Backlight	\x01\x10\x00\x05\x00\x00\x00\x01\x81\x09\x043\xff
Focus Mode	\x01\x10\x00\x05\x00\x00\x00\x01\x81\x09\x048\xff
Power	\x01\x10\x00\x05\x00\x00\x00\x01\x81\x09\x04\xff
Video System	\x01\x10\x00\x05\x00\x00\x00\x01\x81\x09\x06#\xff
White Balance	\x01\x10\x00\x05\x00\x00\x00\x01\x81\x09\x045\xff