

1. U4 (STM32G474RET6) ピン → ネット

pin	port	ネット	pin	port	ネット	pin	port	ネット	pin	port	ネット
1	VBAT_1	3.3V	17	PA3_17	DBG_RX	33	PB11_33	LED_ERR	49	PA13_49	SWDIO
2	PC13_2	未接続(NC)	18	PA4_18	未接続(NC)	34	PB12_34	CAN Interface1/CAN_RX	50	PA14_50	SWCLK
3	PC14_3	未接続(NC)	19	PA5_19	LED_RUN	35	PB13_35	CAN Interface1/CAN_TX	51	PA15_51	I2C_SCL
4	PC15_4	未接続(NC)	20	PA6_20	未接続(NC)	36	PB14_36	未接続(NC)	52	PC10_52	SPI3_SCK
5	PF0_5	HSE_IN	21	PA7_21	未接続(NC)	37	PB15_37	未接続(NC)	53	PC11_53	SPI3_MISO
6	PF1_6	HSE_OUT	22	PC4_22	未接続(NC)	38	PC6_38	UNIT_ID0	54	PC12_54	SPI3_MOSI
7	PG10_7	NRST	23	PC5_23	未接続(NC)	39	PC7_39	UNIT_ID1	55	PD2_55	AMT22_CS_N
8	PC0_8	未接続(NC)	24	PB0_24	未接続(NC)	40	PC8_40	UNIT_ID2	56	PB3_56	SWO
9	PC1_9	未接続(NC)	25	PB1_25	未接続(NC)	41	PC9_41	未接続(NC)	57	PB4_57	未接続(NC)
10	PC2_10	未接続(NC)	26	PB2_26	未接続(NC)	42	PA8_42	未接続(NC)	58	PB5_58	未接続(NC)
11	PC3_11	未接続(NC)	27	VSSA_27	GND	43	PA9_43	未接続(NC)	59	PB6_59	未接続(NC)
12	PA0_12	ADC_5V_MON	28	VREF+…	VREF_PLUS	44	PA10_44	未接続(NC)	60	PB7_60	I2C_SDA
13	PA1_13	未接続(NC)	29	VDDA_29	VDDA_A	45	PA11_45	CAN Interface/CAN_RX	61	PB8_61	BOOT0
14	PA2_14	DBG_TX	30	PB10_30	LED_COMM	46	PA12_46	CAN Interface/CAN_TX	62	PB9_62	未接続(NC)
15	VSS_15	GND	31	VSS_31	GND	47	VSS_47	GND	63	VSS_63	GND
16	VDD_16	3.3V	32	VDD_32	3.3V	48	VDD_48	3.3V	64	VDD_64	3.3V

※ port 列は KiCad シンボルのピン名。「未接続(NC)」は設計上の未使用ピン。

2. ネット → 接続ピン (電源系を先頭、以降アルファベット順)

ネット	数	接続ピン RefDes.pad(ピン名)	ネット	数	接続ピン RefDes.pad(ピン名)
GND	55	C1.2, C2.2, C3.2, C4.2, C5.2, C6.2, C7.2, C8.2, C9.2, C10.1, C11.2, C12.2, C13.2, C14.2, C15.2, C16.2, C17.2, C18.2, C101.2, C201.2, C202.2, C203.2, C204.2, D1.3(GND_3), D2.3(GND_3), D6.1(K_1), D7.1(A_1), D8.1(K_1), D9.1(K_1), D10.1(K_1), J1.2(Pin_2_2), J2.3(Pin_3_3), J3.3(Pin_3_3), J4.3(Pin_3_3), J5.3(Pin_3_3), J6.4(Pin_4_4), J7.1(Pin_1_1), R4.2, R14.2, SW3.4, SW3.5, SW3.6, U1.2(GND_2), U2.1(GND_1), U3.2(GND_2), U3.8(S_8), U4.15(VSS_15), U4.27(VSSA_27), U4.31(VSS_31), U1.6(VOUT_6), U2.3(VI_3), U3.3(VCC_3), U5.3(VCC_3)	LED_ERR	2	R22.1, U4.33(PB11_33)
PWR_5V	11	C1.1, C17.1, C201.1, C202.1, J6.1(Pin_1_1), R13.1, U1.3(~{CE}_3), U1.6(VOUT_6), U2.3(VI_3), U3.3(VCC_3), U5.3(VCC_3)	LED_RUN	2	R20.1, U4.19(PA5_19)
3.3V	22	C2.1, C5.1, C6.1, C7.1, C8.1, C9.1, C10.2, C18.1, C203.1, C204.1, D7.2(K_2), FB1.2, R19.1, U2.2(VO_2), U2.2(VO_2), U3.5(VIO_5), U4.1(VBAT_1), U4.16(VDD_16), U4.32(VDD_32), U4.48(VDD_48), U4.64(VDD_64), U5.5(VIO_5)	NRST	3	C15.1, J7.4(Pin_4_4), U4.7(PG10_7)
ADC_5V_MON	5	C16.1, D7.3(COM_3), R13.2, R14.1, U4.12(PA0_12)	Net-(C4-Pad1)	3	C4.1, R3.2, Y1.1(1_1)
AMT22_CS_N	2	R18.2, U4.55(PD2_55)	Net-(D10-A)	2	D10.2(A_2), R22.2
BOOT0	2	R4.1, U4.61(PB8_61)	Net-(D6-A)	2	D6.2(A_2), R19.2
C620_CAN_H	4	D2.1(IO_1_1), J4.1(Pin_1_1), J5.1(Pin_1_1), U5.7(CANH_7)	Net-(D8-A)	2	D8.2(A_2), R20.2
C620_CAN_L	4	D2.2(IO_2_2), J4.2(Pin_2_2), J5.2(Pin_2_2), U5.6(CANL_6)	Net-(D9-A)	2	D9.2(A_2), R21.2
CAN Interface/CAN_RX	2	U3.4(RXD_4), U4.45(PA11_45)	Net-(J6-Pin_2)	2	J6.2(Pin_2_2), R15.1
CAN Interface/CAN_TX	2	U3.1(TXD_1), U4.46(PA12_46)	Net-(J6-Pin_3)	2	J6.3(Pin_3_3), R16.1
CAN Interface1/CAN_RX	2	U4.34(PB12_34), U5.4(RXD_4)	Net-(J6-Pin_5)	2	J6.5(Pin_5_5), R17.1
CAN Interface1/CAN_TX	2	U4.35(PB13_35), U5.1(TXD_1)	Net-(J6-Pin_6)	2	J6.6(Pin_6_6), R18.1
COMM_A	5	D1.1(IO_1_1), J2.1(Pin_1_1), J3.1(Pin_1_1), R1.1, U3.7(CANH_7)	Net-(SW1-COM)	2	R1.2, SW1.2(COM_2)
COMM_B	5	D1.2(IO_2_2), J2.2(Pin_2_2), J3.2(Pin_2_2), SW1.3(N.O._3), U3.6(CANL_6)	PWR_5V_IN	3	C101.1, J1.1(Pin_1_1), U1.1(VIN_1)
DBG_RX	2	J7.6(Pin_6_6), U4.17(PA3_17)	SPI3_MISO	2	R17.2, U4.53(PC11_53)
DBG_TX	2	J7.5(Pin_5_5), U4.14(PA2_14)	SPI3_MOSI	2	R16.2, U4.54(PC12_54)
HSE_IN	3	C3.1, U4.5(PF0_5), Y1.3(3_3)	SPI3_SCK	2	R15.2, U4.52(PC10_52)
HSE_OUT	2	R3.1, U4.6(PF1_6)	SWCLK	2	J7.2(Pin_2_2), U4.50(PA14_50)
I2C_SCL	1	U4.51(PA15_51)	SWDIO	2	J7.3(Pin_3_3), U4.49(PA13_49)
I2C_SDA	1	U4.60(PB7_60)	SWO	1	U4.56(PB3_56)
LED_COMM	2	R21.1, U4.30(PB10_30)	UNIT_ID0	2	SW3.1, U4.38(PC6_38)
			UNIT_ID1	2	SW3.2, U4.39(PC7_39)
			UNIT_ID2	2	SW3.3, U4.40(PC8_40)
			VDDA_A	5	C11.1, C13.1, FB1.1, R2.1, U4.29(VDDA_29)
			VREF_PLUS	4	C12.1, C14.1, R2.2, U4.28(VREF+_28)

3. 実装部品（.kicad_pcb の RefDes / Value / Footprint）

Ref	Value	Footprint	Ref	Value	Footprint	Ref	Value	Footprint
C1	100nF	C_0603_1608Metric	C204	10uF	C_0805_2012Metric	R14	RC0603FR-0710KL 10k	R_0603_1608Metric
C2	100nF	C_0603_1608Metric	D1	ESD2CAN24DBZRQ1	SOT-23	R15	0R	R_0603_1608Metric
C3	10pF	C_0603_1608Metric	D2	ESD2CAN24DBZRQ1	SOT-23	R16	0R	R_0603_1608Metric
C4	10pF	C_0603_1608Metric	D6	LTST-C190KGKT	LED_0603_1608Metric	R17	0R	R_0603_1608Metric
C5	100nF	C_0603_1608Metric	D7	BAT54S-HF	SOT-23	R18	0R	R_0603_1608Metric
C6	100nF	C_0603_1608Metric	D8	LTST-C190KGKT	LED_0603_1608Metric	R19	1k	R_0603_1608Metric
C7	100nF	C_0603_1608Metric	D9	LTST-C190KSKT	LED_0603_1608Metric	R20	1k	R_0603_1608Metric
C8	100nF	C_0603_1608Metric	D10	LTST-C190KRKT	LED_0603_1608Metric	R21	1k	R_0603_1608Metric
C9	100nF	C_0603_1608Metric	FB1	BLM18AG601SN1D	L_0603_1608Metric	R22	1k	R_0603_1608Metric
C10	4.7uF	C_0805_2012Metric	G***	LOGO	DifferentialSwerve_Logo	REF**	MountingHole_2.7mm_M2.5	MountingHole_2.7mm_M2.5
C11	1uF	C_0603_1608Metric	J1	SM02B-GHS-TB	JST_GH_SM02B-GHS-TB_1x0...	REF**	MountingHole_2.7mm_M2.5	MountingHole_2.7mm_M2.5
C12	10nF	C_0603_1608Metric	J2	SM03B-GHS-TB	JST_GH_SM03B-GHS-TB_1x0...	REF**	MountingHole_2.7mm_M2.5	MountingHole_2.7mm_M2.5
C13	100nF	C_0603_1608Metric	J3	SM03B-GHS-TB	JST_GH_SM03B-GHS-TB_1x0...	REF**	MountingHole_2.7mm_M2.5	MountingHole_2.7mm_M2.5
C14	1uF	C_0603_1608Metric	J4	SM03B-GHS-TB	JST_GH_SM03B-GHS-TB_1x0...	SW1	JS102011SAQN	JS102011SAQN
C15	100nF	C_0603_1608Metric	J5	SM03B-GHS-TB	JST_GH_SM03B-GHS-TB_1x0...	SW3	DS04-254-1-03BK-SMT	SW_DIP_SPSTx03_Slide_Omro...
C16	GRM188R71H103KA01D 10nF	C_0603_1608Metric	J6	SM06B-GHS-TB	JST_GH_SM06B-GHS-TB_1x0...	U1	LM66100DCKR	SOT-363_SC-70-6
C17	100nF	C_0603_1608Metric	J7	BM06B-GHS-TBT	JST_GH_BM06B-GHS-TBT_1x...	U2	TLV76133DCYR	SOT-223-3_TabPin2
C18	100nF	C_0603_1608Metric	R1	120R	R_0603_1608Metric	U3	TCAN1051VDRQ1	SOIC-8_3.9x4.9mm_P1.27mm
C101	2.2uF	C_0805_2012Metric	R2	0R	R_0603_1608Metric	U4	STM32G474RET6	LQFP-64_10x10mm_P0.5mm
C201	100nF	C_0603_1608Metric	R3	RC0603JR-070RL 0R	R_0603_1608Metric	U5	TCAN1051VDRQ1	SOIC-8_3.9x4.9mm_P1.27mm
C202	10uF	C_0805_2012Metric	R4	RC0603FR-0710KL 10k	R_0603_1608Metric	Y1	FC3BAEBDI8.0-T1	Crystal_SMD_3225-4Pin_3.2x2...
C203	100nF	C_0603_1608Metric	R13	RC0603FR-0722KL 22k	R_0603_1608Metric			

✓ 基板上でネット未割当のパッドは無し（コネクタの取付脚 MP を除く）

1. U1 (STM32F405RGTx) ピン → ネット

pin	port	ネット	pin	port	ネット	pin	port	ネット	pin	port	ネット
1	VBAT_1	PWR_3.3V	17	PA3_17	USART2_RX	33	PB12_33	未接続(NC)	49	PA14_49	SWCLK
2	PC13_2	未接続(NC)	18	VSS_18	GND	34	PB13_34	未接続(NC)	50	PA15_50	未接続(NC)
3	PC14_3	未接続(NC)	19	VDD_19	PWR_3.3V	35	PB14_35	未接続(NC)	51	PC10_51	Net-(J7-Pin_5)
4	PC15_4	未接続(NC)	20	PA4_20	未接続(NC)	36	PB15_36	未接続(NC)	52	PC11_52	Net-(J7-Pin_3)
5	PH0_5	Net-(U1-PH0)	21	PA5_21	RUN	37	PC6_37	Net-(U1-PC6)	53	PC12_53	Net-(J7-Pin_4)
6	PH1_6	Net-(U1-PH1)	22	PA6_22	AMT102_input1/W1_A	38	PC7_38	Net-(U1-PC7)	54	PD2_54	IMU_CS_N
7	NRST_7	NRST	23	PA7_23	AMT102_input1/W1_B	39	PC8_39	Net-(U1-PC8)	55	PB3_55	未接続(NC)
8	PC0_8	未接続(NC)	24	PC4_24	IMU_INT1	40	PC9_40	未接続(NC)	56	PB4_56	未接続(NC)
9	PC1_9	未接続(NC)	25	PC5_25	IMU_INT2	41	PA8_41	未接続(NC)	57	PB5_57	未接続(NC)
10	PC2_10	未接続(NC)	26	PB0_26	未接続(NC)	42	PA9_42	未接続(NC)	58	PB6_58	AMT102_input2/W1_A
11	PC3_11	未接続(NC)	27	PB1_27	未接続(NC)	43	PA10_43	未接続(NC)	59	PB7_59	AMT102_input2/W1_B
12	VSSA_12	GND	28	PB2_28	未接続(NC)	44	PA11_44	COMM_RX	60	BOOT0...	BOOT0
13	VDDA_13	Net-(U1-VDDA)	29	PB10_29	COMM	45	PA12_45	COMM_TX	61	PB8_61	未接続(NC)
14	PA0_14	AMT102_input/W1_A	30	PB11_30	ERR	46	PA13_46	SWDIO	62	PB9_62	未接続(NC)
15	PA1_15	AMT102_input/W1_B	31	VCAP_...	Net-(U1-VCAP_1)	47	VCAP_...	Net-(U1-VCAP_2)	63	VSS_63	GND
16	PA2_16	USART2_TX	32	VDD_32	PWR_3.3V	48	VDD_48	PWR_3.3V	64	VDD_64	PWR_3.3V

※ port 列は KiCad シンボルのピン名。「未接続(NC)」は設計上の未使用ピン。

2. ネット → 接続ピン (電源系を先頭、以降アルファベット順)

ネット	数	接続ピン RefDes.pad(ピン名)	ネット	数	接続ピン RefDes.pad(ピン名)
GND	56	C1.2, C2.2, C3.2, C4.2, C5.2, C6.2, C7.2, C8.2, C9.2, C10.1, C11.2, C12.2, C13.2, C14.2, C15.2, C16.2, C17.2, C18.2, C19.2, C20.2, C21.2, C22.2, C23.2, C24.2, C25.2, C26.2, C27.2, C28.1, D1.3(GND_3), D2.3(common_3), D3.3(common_3), D4.3(common_3), D6.1(K_1), D8.1(K_1), D9.1(K_1), D10.1(K_1), J1.2(Pin_2_2), J2.3(Pin_3_3), J4.2(Pin_2_2), J5.2(Pin_2_2), J6.2(Pin_2_2), J7.2(Pin_2_2), J8.1(Pin_1_1), R4.1, SW3.4, SW3.5, SW3.6, U1.12(VSSA_12), U1.18(VSS_18), U1.63(VSS_63), U2.1(GND_1), U4.3(VCC_3), U5.3(~[CE]_3), U5.6(VOUT_6)	Net-(C24-Pad1)	3	C24.1, R7.2, U7.3
PWR_5V	10	C2.1, C3.1, C18.1, J4.1(Pin_1_1), J5.1(Pin_1_1), J6.1(Pin_1_1), U2.3(VI_3), U4.3(VCC_3), U5.3(~[CE]_3), U5.6(VOUT_6)	Net-(C25-Pad1)	3	C25.1, R8.2, U9.1
PWR_3.3V	22	C4.1, C5.1, C8.1, C9.1, C10.2, C11.1, C12.1, C13.1, C19.1, C27.1, C28.2, FB1.2, J7.1(Pin_1_1), R19.1, U1.1(VBAT_1), U1.19(VDD_19), U1.32(VDD_32), U1.48(VDD_48), U1.64(VDD_64), U2.2(VO_2), U2.2(VO_2), U4.5(VIO_5)	Net-(C26-Pad1)	3	C26.1, R9.2, U9.3
AMT102_input/W1_A	2	U1.14(PA0_14), U3.6	Net-(C6-Pad1)	3	C6.1, R3.2, Y1.1(1_1)
AMT102_input/W1_B	2	U1.15(PA1_15), U3.4	Net-(D1-IO_1)	4	D1.1(IO_1_1), J2.1(Pin_1_1), R1.1, U4.7(CANH_7)
AMT102_input1/W1_A	2	U1.22(PA6_22), U7.6	Net-(D1-IO_2)	4	D1.2(IO_2_2), J2.2(Pin_2_2), SW1.3(N.O._3), U4.6(CANL_6)
AMT102_input1/W1_B	2	U1.23(PA7_23), U7.4	Net-(D10-A)	2	D10.2(A_2), R22.2
AMT102_input2/W1_A	2	U1.58(PB6_58), U9.6	Net-(D2-A1)	3	D2.1(A1_1), J4.4(Pin_4_4), R5.1
AMT102_input2/W1_B	2	U1.59(PB7_59), U9.4	Net-(D2-A2)	3	D2.2(A2_2), J4.3(Pin_3_3), R2.1
BOOT0	2	R4.2, U1.60(BOOT0_60)	Net-(D3-A1)	3	D3.1(A1_1), J5.4(Pin_4_4), R7.1
COMM	2	R21.1, U1.29(PB10_29)	Net-(D3-A2)	3	D3.2(A2_2), J5.3(Pin_3_3), R6.1
COMM_RX	2	U1.44(PA11_44), U4.4(RXD_4)	Net-(D4-A1)	3	D4.1(A1_1), J6.4(Pin_4_4), R9.1
COMM_TX	2	U1.45(PA12_45), U4.1(TXD_1)	Net-(D4-A2)	3	D4.2(A2_2), J6.3(Pin_3_3), R8.1
ERR	2	R22.1, U1.30(PB11_30)	Net-(D6-A)	2	D6.2(A_2), R19.2
IMU_CS_N	2	J7.6(Pin_6_6), U1.54(PD2_54)	Net-(D8-A)	2	D8.2(A_2), R20.2
IMU_INT1	2	J7.7(Pin_7_7), U1.24(PC4_24)	Net-(D9-A)	2	D9.2(A_2), R21.2
IMU_INT2	2	J7.8(Pin_8_8), U1.25(PC5_25)	Net-(J1-Pin_1)	3	C1.1, J1.1(Pin_1_1), U5.1(VIN_1)
NRST	3	C22.1, J8.4(Pin_4_4), U1.7(NRST_7)	Net-(J7-Pin_3)	2	J7.3(Pin_3_3), U1.52(PC11_52)
Net-(C15-Pad1)	3	C15.1, R2.2, U3.1	Net-(J7-Pin_4)	2	J7.4(Pin_4_4), U1.53(PC12_53)
Net-(C17-Pad1)	3	C17.1, R5.2, U3.3	Net-(J7-Pin_5)	2	J7.5(Pin_5_5), U1.51(PC10_51)
Net-(C23-Pad1)	3	C23.1, R6.2, U7.1	Net-(SW1-COM)	2	R1.2, SW1.2(COM_2)
			Net-(U1-PC6)	2	SW3.1, U1.37(PC6_37)
			Net-(U1-PC7)	2	SW3.2, U1.38(PC7_38)
			Net-(U1-PC8)	2	SW3.3, U1.39(PC8_39)
			Net-(U1-PH0)	3	C7.1, U1.5(PH0_5), Y1.3(3_3)
			Net-(U1-PH1)	2	R3.1, U1.6(PH1_6)
			Net-(U1-VCAP_1)	2	C20.1, U1.31(VCAP_1_31)
			Net-(U1-VCAP_2)	2	C21.1, U1.47(VCAP_2_47)
			Net-(U1-VDDA)	4	C14.1, C16.1, FB1.1, U1.13(VDDA_13)

ネット	数	接続ピン RefDes.pad(ピン名)
RUN	2	R20.1, U1.21(PA5_21)
SWCLK	2	J8.2(Pin_2_2), U1.49(PA14_49)
SWDIO	2	J8.3(Pin_3_3), U1.46(PA13_46)
USART2_RX	2	J8.6(Pin_6_6), U1.17(PA3_17)
USART2_TX	2	J8.5(Pin_5_5), U1.16(PA2_16)

3. 実装部品（.kicad_pcb の RefDes / Value / Footprint）

Ref	Value	Footprint	Ref	Value	Footprint	Ref	Value	Footprint
C1	2.2uF	C_0805_2012Metric	C25	DNP	C_0603_1608Metric	R4	RC0603FR-0710KL 10k	R_0603_1608Metric
C2	100nF	C_0603_1608Metric	C26	DNP	C_0603_1608Metric	R5	100R	R_0603_1608Metric
C3	10uF	C_0805_2012Metric	C27	2.2 μF	C_0805_2012Metric	R6	100R	R_0603_1608Metric
C4	100nF	C_0603_1608Metric	C28	100nF	C_0603_1608Metric	R7	100R	R_0603_1608Metric
C5	10uF	C_0805_2012Metric	D1	ESD2CAN24DBZRQ1	SOT-23	R8	100R	R_0603_1608Metric
C6	10pF	C_0603_1608Metric	D2	D_TVS_Dual_AACESDS452DBZ	SOT-23	R9	100R	R_0603_1608Metric
C7	10pF	C_0603_1608Metric	D3	D_TVS_Dual_AACESDS452DBZ	SOT-23	R19	1k	R_0603_1608Metric
C8	100nF	C_0603_1608Metric	D4	D_TVS_Dual_AACESDS452DBZ	SOT-23	R20	1k	R_0603_1608Metric
C9	100nF	C_0603_1608Metric	D6	LTST-C190KGKT	LED_0603_1608Metric	R21	1k	R_0603_1608Metric
C10	4.7uF	C_0805_2012Metric	D8	LTST-C190KGKT	LED_0603_1608Metric	R22	1k	R_0603_1608Metric
C11	100nF	C_0603_1608Metric	D9	LTST-C190KSKT	LED_0603_1608Metric	REF**	MountingHole_2.7mm_M2.5	MountingHole_2.7mm_M2.5
C12	100nF	C_0603_1608Metric	D10	LTST-C190KRKT	LED_0603_1608Metric	REF**	MountingHole_2.7mm_M2.5	MountingHole_2.7mm_M2.5
C13	100nF	C_0603_1608Metric	FB1	BLM18AG601SN1D	L_0603_1608Metric	SW1	JS102011SAQN	JS102011SAQN
C14	100nF	C_0603_1608Metric	G***	LOGO	DifferentialSwerve_Logo	SW3	DS04-254-1-03BK-SMT	SW_DIP_SPSTx03_Slide_Omro…
C15	DNP	C_0603_1608Metric	J1	SM02B-GHS-TB	JST_GH_SM02B-GHS-TB_1x0…	U1	STM32F405RGTx	LQFP-64_10x10mm_P0.5mm
C16	1uF	C_0603_1608Metric	J2	SM03B-GHS-TB	JST_GH_SM03B-GHS-TB_1x0…	U2	TLV76133DCYR	SOT-223-3_TabPin2
C17	DNP	C_0603_1608Metric	J4	Conn_01x04	JST_XH_B4B-XH-AM_1x04_P2…	U3	74LVC2G17	SOT-23-6
C18	100nF	C_0603_1608Metric	J5	Conn_01x04	JST_XH_B4B-XH-AM_1x04_P2…	U4	TCAN1051VDRQ1	SOIC-8_3.9x4.9mm_P1.27mm
C19	100nF	C_0603_1608Metric	J6	Conn_01x04	JST_XH_B4B-XH-AM_1x04_P2…	U5	LM66100DCKR	SOT-363_SC-70-6
C20	2.2 μF	C_0805_2012Metric	J7	Conn_01x08	JST_XH_B8B-XH-AM_1x08_P2…	U7	74LVC2G17	SOT-23-6
C21	2.2 μF	C_0805_2012Metric	J8	BM06B-GHS-TBT	JST_GH_BM06B-GHS-TBT_1x…	U9	74LVC2G17	SOT-23-6
C22	100nF	C_0603_1608Metric	R1	120R	R_0603_1608Metric	Y1	FC3BAEBDI8.0-T1	Crystal_SMD_3225-4Pin_3.2x2…
C23	DNP	C_0603_1608Metric	R2	100R	R_0603_1608Metric			
C24	DNP	C_0603_1608Metric	R3	RC0603JR-070RL 0R	R_0603_1608Metric			

△ 基板上でどこにも繋がっていないパッド: U3.2, U3.5, U7.2, U7.5, U9.2, U9.5
→ 74LVC2G17 の pad2=GND / pad5=VCC。実装手順書 p.5 のジャンパで接続すること。（コネクタの取付脚 MP は元から非電気パッドなので除外）