ETSI TR 138 903 V19.3.0 (2026-07)



TECHNICAL REPORT

5G;
NR;
Derivation of test tolerances and measurement uncertainty for User Equipment (UE) conformance test cases
(3GPP TR 38.903 version 19.3.0 Release 19)



Reference
RTR/TSGR-0538903vj30

Keywords
5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from the
ETSI Search & Browse Standards application.

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on ETSI deliver repository.

Users should be aware that the present document may be revised or have its status changed, this information is available in the Milestones listing.

If you find errors in the present document, please send your comments to the relevant service listed under Committee Support Staff.

If you find a security vulnerability in the present document, please report it through our Coordinated Vulnerability Disclosure (CVD) program.

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.
No recommendation as to products and services or vendors is made or should be implied.
No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.
In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.
The content of the PDF version shall not be modified without the written authorization of ETSI.
The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2026.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI IPR online database.

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™**, **LTE™** and **5G™** logo are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM**® and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Report (TR) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found at 3GPP to ETSI numbering cross-referencing.

Modal verbs terminology

In the present document "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the ETSI Drafting Rules (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights 2
Legal Notice 2
Modal verbs terminology 2
Foreword 10
Introduction 10
1 Scope 11
2 References 11
3 Definitions, symbols and abbreviations 12
3.1 Definitions 12
3.2 Symbols 12
3.3 Abbreviations 13
4 General Principles 14
4.1 Principle of Superposition 14
4.2 Sensitivity analysis 14
4.3 Statistical combination of uncertainties 14
4.4 Correlation between uncertainties 15
4.4.1 Uncorrelated uncertainties 15
4.4.2 Positively correlated uncertainties 16
4.4.3 Negatively correlated uncertainties 17
4.4.4 Treatment of uncorrelated uncertainties 17
4.4.5 Treatment of positively correlated uncertainties with adverse effect 17
4.4.6 Treatment of positively correlated uncertainties with beneficial effect 17
4.4.7 Treatment of negatively correlated uncertainties 18
5 Determination of Test System Uncertainties 18
5.1 General 18
5.2 Uncertainty figures 18
6 Determination of Test Tolerances 18
6.1 General 18
7 Grouping of test cases defined in TS 38.521-4 19
8 Grouping of test cases defined in TS 38.533 20
9 Grouping of test cases defined in TS 37.571-1 62
Annex A: Derivation documents for test tolerance 69
A.1 Void 69
A.2 Handling of common Test Tolerance topics for radiated test cases defined in TS 38.533 69
A.2.1 Angles of Arrival 69
A.2.1.1 Relevant core requirements 69
A.2.1.2 Modelling of variation within spherical coverage directions 70
A.2.1.3 Principles for Test Tolerance analysis 70
A.2.2 UE Fine beams and Rough beams 70
A.2.2.1 Relevant core requirements 70
A.2.2.2 Modelling of Fine beams and Rough beams 72
A.2.2.3 Principles for Test Tolerance analysis 72
A.2.3 UE internal noise 72
A.2.3.1 Relevant core requirements 72
A.2.3.2 Calculation method 72
A.2.3.3 Principles for Test Tolerance analysis 73
A.2.4 Calculation of Es/Iot at UE baseband 73
A.2.4.1 Relevant core requirements 73

A.2.4.2 Calculation method 73
A.2.4.3 Principles for Test Tolerance analysis 74
A.2.5 Calculation of Applied Io 74
A.2.5.1 Relevant core requirements 74
A.2.5.2 Calculation method 75
A.2.5.3 Principles for Test Tolerance analysis 75
A.2.6 UE Reported RSRP and UE gain 75
A.2.6.1 Relevant core requirements 75
A.2.6.2 Absolute RSRP 76
A.2.6.3 Relative RSRP, 2 levels on same cell, same Angle of Arrival 77
A.2.6.4 Relative RSRP, 2 intra-frequency cells, same Angle of Arrival 78
A.2.6.5 Relative RSRP, 2 inter-frequency cells, same Angle of Arrival 78
A.2.6.6 Relative RSRP, 2 cells, different Angles of Arrival 78
A.2.6.7 Principles for Test Tolerance analysis 79
A.2.7 Intra-frequency cells without AWGN, same Angle of Arrival 79
A.2.7.1 Test system 79
A.2.7.2 Calculation method for Es/Iot at UE baseband 79
A.2.7.3 Calculation method for Applied Io 80
A.2.7.4 Principles for Test Tolerance analysis 81

A.3 Test Tolerance analysis templates for radiated test cases awaiting completion 81

A.4 Design of radiated test cases defined in TS 38.533 82
A.4.1 Downlink considerations 82
A.4.1.1 Side conditions for Rx Beam Peak angle of arrival 82
A.4.1.2 Side conditions for Spherical Coverage angle of arrival 82
A.4.1.3 Test case design options to increase downlink dB range 83

Annex B: Acceptable uncertainty of test system for test cases defined in TS 38.521-2 for radiative testing 85

B.1 Uncertainty budget calculation principle 85
B.1.1 Uncertainty budget calculation principle for DFF 85
B.1.2 Uncertainty budget calculation principle for IFF 86
B.1.3 Uncertainty budget calculation principle for NFTF 86

B.2 Measurement error contribution descriptions 86
B.2.1 Measurement error contribution descriptions for DFF 86
B.2.1.1 Positioning misalignment 86
B.2.1.2 Measure distance uncertainty 86
B.2.1.3 Quality of quiet zone 86
B.2.1.4 Mismatch 86
B.2.1.5 Standing Wave Between the DUT and measurement antenna 88
B.2.1.6 Uncertainty of the RF power measurement equipment 88
B.2.1.7 Phase curvature 89
B.2.1.8 Amplifier uncertainties 89
B.2.1.9 Random uncertainty 89
B.2.1.10 Influence of the XPD 90
B.2.1.11 Insertion loss Variation 94
B.2.1.12 RF leakage (from measurement antenna to receiver/transmitter) 94
B.2.1.13 Misalignment of positioning System 94
B.2.1.14 Uncertainty of the Network Analyzer 94
B.2.1.15 Uncertainty of the absolute gain of the calibration antenna 94
B.2.1.16 Positioning and pointing misalignment between the reference antenna and the measurement antenna 94
B.2.1.17 gNB emulator uncertainty 94
B.2.1.18 Phase centre offset of calibration 95
B.2.1.19 Quality of quiet zone for calibration process 95
B.2.1.20 Standing wave between reference calibration antenna and measurement antenna 95
B.2.1.21 Influence of the calibration antenna feed cable (Flexing cables, adapters, attenuators, connector repeatability) 96
B.2.1.22 Influence of TRP measurement grid 96
B.2.1.23 Influence of beam peak search grid 96
B.2.1.24 Systematic error due to TRP calculation/quadrature 96

B.2.1.25 Multiple measurement antenna uncertainty 96
B.2.1.26 DUT repositioning 96
B.2.1.27 Influence of noise 96
B.2.1.28 Systematic error related to beam peak search 97
B.2.1.29 Influence of spherical coverage grid 97
B.2.1.30 Systematic error related to EIS spherical coverage 97
B.2.1.31 Misalignment of DUT due to change of DUT orientation 97
B.2.1.32 Additional Impact of Interferer ACLR 97
B.2.1.33 Modulated Interferer uncertainty 97
B.2.1.34 Void 97
B.2.1.35 Influence of offset antenna for blocker signal 97
B.2.1.36 Uncertainty of the RF relative power measurement equipment 98
B.2.2 Measurement error contribution descriptions for IFF 98
B.2.2.1 Positioning misalignment 98
B.2.2.2 Measure distance uncertainty 98
B.2.2.3 Quality of Quiet Zone 99
B.2.2.4 Mismatch 102
B.2.2.5 Standing wave between DUT and measurement antenna 105
B.2.2.6 Uncertainty of the RF power measurement equipment 105
B.2.2.7 Phase Curvature 105
B.2.2.8 Amplifier Uncertainties 106
B.2.2.9 Random uncertainty 106
B.2.2.10 Influence of XPD 107
B.2.2.11 Insertion Loss Variation 107
B.2.2.12 RF leakage (from measurement antenna to receiver/transmitter) 108
B.2.2.13 Misalignment of positioning system 108
B.2.2.14 Uncertainty of the Network Analyzer 108
B.2.2.15 Uncertainty of the absolute gain of the calibration antenna 109
B.2.2.16 Positioning and pointing misalignment between the reference antenna and the measurement antenna 109
B.2.2.17 gNB emulator uncertainty 109
B.2.2.18 Phase centre offset of calibration 110
B.2.2.19 Quality of the Quiet Zone for Calibration Process 110
B.2.2.20 Standing wave between reference calibration antenna and measurement antenna 111
B.2.2.21 Influence of the calibration antenna feed cable (Flexing cables, adapters, attenuators, connector repeatability) 112
B.2.2.22 Influence of TRP measurement grid 112
B.2.2.23 Influence of beam peak search grid 113
B.2.2.24 Systematic error due to TRP calculation/quadrature 113
B.2.2.25 Multiple measurement antenna uncertainty 113
B.2.2.26 DUT repositioning 113
B.2.2.27 Influence of noise 114
B.2.2.28 Systematic error related to beam peak search 126
B.2.2.29 Influence of spherical coverage grid 126
B.2.2.30 Systematic error related to EIS spherical coverage 126
B.2.2.31 Misalignment of DUT due to change of DUT orientation 127
B.2.2.32 Additional Impact of Interferer ACLR 127
B.2.2.33 Modulated Interferer uncertainty 127
B.2.2.34 Void 128
B.2.2.35 Influence of offset antenna for blocker signal 128
B.2.2.36 Uncertainty of the RF relative power measurement equipment 128
B.2.3 Measurement error contribution descriptions for NFTF 128
B.2.3.1 Axes Alignment 128
B.2.3.2 Measurement Distance uncertainty 128
B.2.3.3 Quality of the Quiet Zone 128
B.2.3.4 Mismatch 128
B.2.3.5 Multiple Reflections: Coupling Measurement Antenna and DUT 128
B.2.3.6 Uncertainty of the RF power measurement equipment 129
B.2.3.7 Phase curvature 129
B.2.3.8 Amplifier uncertainties 129
B.2.3.9 Random uncertainty 129
B.2.3.10 Influence of the XPD 129
B.2.3.11 NF to FF truncation 129

B.2.3.12 Probe Polarization Amplitude and Phase 129
B.2.3.13 Probe Array Uniformity (for multi-probe systems only) 129
B.2.3.14 Uncertainty of the Network Analyzer 129
B.2.3.15 Uncertainty of the absolute gain of the calibration antenna 129
B.2.3.16 Phase Recovery Non-Linearity over signal bandwidth 130
B.2.3.17 Probe Pattern Effect 130
B.2.3.18 Phase centre offset of calibration 130
B.2.3.19 Quality of the Quiet Zone for Calibration Process 130
B.2.3.20 Phase Drift and Noise 130
B.2.3.21 Mismatch in the connection of the calibration antenna 130
B.2.3.22 Influence of TRP measurement grid 130
B.2.3.23 130
B.2.3.24 130
B.2.3.25 Leakage and Crosstalk 130
B.2.3.26 Systematic error due to TRP calculation/quadrature 130
B.2.3.27 Multiple measurement antenna uncertainty 130
B.2.3.28 DUT repositioning 131
B.2.3.29 Influence of noise 131
B.2.3.30 Uncertainty of the RF relative power measurement equipment 131

B.3 UE maximum output power 131
B.3.1 Uncertainty budget format and assessment for DFF 133
B.3.2 Uncertainty budget format and assessment for IFF 137
B.3.3 Uncertainty budget format and assessment for NFTF 155

B.4 UE maximum output power for modulation / channel bandwidth 157
B.4.1 Uncertainty budget format and assessment for DFF 159
B.4.2 Uncertainty budget format and assessment for IFF 159
B.4.3 Uncertainty budget format and assessment for NFTF 163

B.5 UE maximum output power with additional requirements 163

B.6 Configured transmitted power with Power Boost 163
B.6.1 Uncertainty budget format and assessment for DFF 164
B.6.2 Uncertainty budget format and assessment for IFF 166
B.6.3 Uncertainty budget format and assessment for NFTF 175

B.6a UE Maximum Output Power – EIRP with UL Gaps 176
B.6a.1 Uncertainty budget format and assessment for DFF 176
B.6a.2 Uncertainty budget format and assessment for IFF 177
B.6a.3 Uncertainty budget format and assessment for NFTF 180

B.7 Minimum Output power 181
B.7.1 Uncertainty budget format and assessment for DFF 181
B.7.2 Uncertainty budget format and assessment for IFF 185

B.8 Transmit OFF power 197
B.8.1 Uncertainty budget format and assessment for DFF 197
B.8.2 Uncertainty budget format and assessment for IFF 200

B.9 ON/OFF time mask 206
B.9.1 ON power subtest 206
B.9.1.1 Uncertainty budget format and assessment for DFF 206
B.9.1.2 Uncertainty budget format and assessment for IFF 206
B.9.2 OFF power subtest 206
B.9.2.1 Uncertainty budget format and assessment for DFF 207
B.9.2.2 Uncertainty budget format and assessment for IFF 207

B.9a Power control 213
B.9a.1 Absolute power tolerance 213
B.9a.2 Relative power control tolerance 213
B.9a.2.1 Uncertainty budget format and assessment for DFF 213
B.9a.2.2 Uncertainty budget format and assessment for IFF 214
B.9a.2.3 Uncertainty budget format and assessment for NFTF 215
B.9a.3 Aggregate Power control tolerance 216

B.9a.3.1 Uncertainty budget format and assessment for DFF 216
B.9a.3.2 Uncertainty budget format and assessment for IFF 217
B.9a.3.3 Uncertainty budget format and assessment for NFTF 218
B.10 Frequency error 219
B.10.1 Uncertainty budget format and assessment for DFF 219
B.10.2 Uncertainty budget format and assessment for IFF 220
B.11 Carrier leakage 220
B.11.1 Uncertainty budget format and assessment for DFF 220
B.11.2 Uncertainty budget format and assessment for IFF 224
B.12 Error Vector Magnitude 231
B.12.1 Uncertainty budget format and assessment for DFF 232
B.12.2 Uncertainty budget format and assessment for IFF 232
B.13 to B.14 235
B.15 Occupied bandwidth 235
B.15.1 Uncertainty budget format and assessment for DFF 236
B.15.2 Uncertainty budget format and assessment for IFF 236
B.16 Spectrum emission mask 236
B.16.1 Uncertainty budget format and assessment for DFF 236
B.16.2 Uncertainty budget format and assessment for IFF 239
B.17 Adjacent Channel Leakage Ratio 245
B.17.1 Uncertainty budget format and assessment for DFF 246
B.17.2 Uncertainty budget format and assessment for IFF 250
B.18 Spurious emissions 255
B.18.1 Uncertainty budget format and assessment for DFF 258
B.18.2 Uncertainty budget format and assessment for IFF 262
B.18.3 Uncertainty budget format and assessment for NFTF 295
B.18a Beam correspondence - EIRP 296
B.18a.1 Uncertainty budget format and assessment for DFF 296
B.18a.2 Uncertainty budget format and assessment for IFF 296
B.18a.3 Uncertainty budget format and assessment for NFTF 297
B.19 Reference Sensitivity 298
B.19.1 Uncertainty budget format and assessment for DFF 300
B.19.2 Uncertainty budget format and assessment for IFF 300
B.20 316
B.21 Adjacent Channel Selectivity 316
B.21.1 Uncertainty budget format and assessment for DFF 316
B.21.2 Uncertainty budget format and assessment for IFF 316
B.22 In-Band Blocking 326
B.22.1 Uncertainty budget format and assessment for DFF 327
B.22.2 Uncertainty budget format and assessment for IFF 327
B.23 327
B.24 327
B.25 Receiver spurious emissions 327
B.25.1 Uncertainty budget format and assessment for DFF 329
B.25.2 Uncertainty budget format and assessment for IFF 331
B.26 FR2 RF test cases with testability issues related to MU 361
Annex C: Acceptable uncertainty of test system for test cases defined in TS 38.521-3 for radiative testing 363

Annex D: Acceptable uncertainty of test system for test cases defined in TS 38.521-4 for radiative testing 364

D.1 Uncertainty budget calculation principle 370
D.1.1 Uncertainty budget calculation principle for DNF 370
D.1.2 Uncertainty budget calculation principle for DFF 370
D.1.3 Uncertainty budget calculation principle for IFF 370

D.2 Measurement error contribution descriptions 370
D.2.1 Measurement error contribution descriptions for DNF 370
D.2.1.1 gNB emulator SNR uncertainty 370
D.2.1.2 gNB emulator Downlink EVM 370
D.2.1.3 gNB emulator fading model impairments 371
D.2.2 Measurement error contribution descriptions for DFF 371
D.2.2.1 gNB emulator SNR uncertainty 371
D.2.2.2 gNB emulator Downlink EVM 371
D.2.2.3 gNB emulator fading model impairments 371
D.2.3 Measurement error contribution descriptions for IFF 371
D.2.3.1 gNB emulator SNR uncertainty 371
D.2.3.2 gNB emulator Downlink EVM 371
D.2.3.3 gNB emulator fading model impairments 371
D.3 Assessment of testable DL SNR range and accuracy 371
D.3.1 Method and Parameters 371
D.3.2.1 SNR range for SNR_{RP} - $SNR_{BB} \leq$ 1dB for DFF 372
D.3.2.2 SNR range for SNR_{RP} - $SNR_{BB} \leq$ 1dB for IFF 372
D.4 Simulation results 376

Annex E: Acceptable uncertainty of test system for test cases defined in TS 38.533 for radiative testing 380

E.1 Uncertainty budget calculation principle 380
E.1.1 Uncertainty budget calculation principle for DFF 380
E.1.2 Uncertainty budget calculation principle for IFF 380

E.2 Measurement error contribution descriptions 380
E.2.1 Measurement error contribution descriptions for DFF 380
E.2.1.1 gNB emulator SNR uncertainty 380
E.2.1.2 gNB emulator Downlink EVM 380
E.2.1.3 gNB emulator fading model impairments 380
E.2.1.4 Uncertainty of the Network Analyzer 381
E.2.2 Measurement error contribution descriptions for IFF 381
E.2.2.1 gNB emulator SNR uncertainty 381
E.2.2.2 gNB emulator Downlink EVM 381
E.2.2.3 gNB emulator fading model impairments 381
E.2.2.4 Uncertainty of the Network Analyzer 381

E.3 Uncertainty assessment for RRM MU quantities. 381
E.3.1 Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power 381
E.3.1.1 Uncertainty budget format and assessment for DFF test setup 382
E.3.1.2 Uncertainty budget format and assessment for Simplified DFF test setup 385
E.3.1.3 Uncertainty budget format and assessment for IFF test setup 385
E.3.1.4 Uncertainty budget format and assessment for Enhanced IFF test setup 389
E.3.1.5 Uncertainty budget format and assessment for IFF+DFF Hybrid test setup 393
E.3.1A Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power for 3AoA and 2AoA 393
E.3.1A.1 Uncertainty budget format and assessment for DFF test setup 393
E.3.1A.2 Uncertainty budget format and assessment for Simplified DFF test setup 396
E.3.1A.3 Uncertainty budget format and assessment for IFF test setup 396
E.3.1A.4 Uncertainty budget format and assessment for Enhanced IFF test setup 396
E.3.1A.5 Uncertainty budget format and assessment for IFF+DFF Hybrid test setup 399
E.3.2 Uncertainty assessment for DL applied SNR 399
E.3.3 Uncertainty assessment for DL Fading profile uncertainty 399
E.3.4 Uncertainty assessment for DL AWGN and signal flatness 399

E.3.5 Uncertainty assessment for UL absolute power measurement 399
E.3.5.1 Uncertainty budget format and assessment for DFF 399
E.3.5.2 TBD 402
E.3.5.3 Uncertainty budget format and assessment for IFF 402
E.3.5.4 Uncertainty budget format and assessment for Enhanced IFF test setup 404
E.3.5.5 Uncertainty budget format and assessment for IFF+DFF Hybrid test setup 406
E.3.6 Uncertainty assessment for UL relative power measurement 406
E.3.7 Uncertainty assessment for UL signal transmit timing relative to DL 406
E.3.8 Uncertainty assessment for Relative transmit timing accuracy during UE timing adjustment 406

Annex F: Applicable MTSU for Different QZ/Device Sizes 407

Annex G: Acceptable uncertainty of test system for test cases defined in TS 37.571-1 for radiative testing 409

Annex H: Change history 410

History 431

Foreword

This Technical Report has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

Introduction

FFS

1 Scope

The present document specifies a general method used to derive Measurement Uncertainties and Test Tolerances for UE conformance tests. The acceptable uncertainties for each test case are documented and establish a system for relating the Test Tolerances to the measurement uncertainties of the Test System.

For UE radio transmitting and reception tests, only FR2 is considered in this document. For UE RRM and Demodulation tests, both FR1 and FR2 are considered in this document.

The test cases which have been analysed to determine Test Tolerances are included as .zip files.

The present document is applicable from Release 15 up to the release indicated on the front page of the present Terminal conformance specifications.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

[1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".

[2] 3GPP TR 36.903: "Evolved Universal Terrestrial Radio Access (E-UTRA) and Evolved Universal Terrestrial Radio Access Network (E-UTRAN); Derivation of test tolerances for Radio Resource Management (RRM) conformance tests".

[3] 3GPP TS 36.904: "Evolved Universal Terrestrial Radio Access (E-UTRA) and Evolved Universal Terrestrial Radio Access Network (E-UTRAN); Derivation of test tolerances for User Equipment (UE) radio reception conformance tests".

[4] ETSI ETR 273-1-2: "Improvement of radiated methods of measurement (using test sites) and evaluation of the corresponding measurement uncertainties; Part 1: Uncertainties in the measurement of mobile radio equipment characteristics; Sub-part 2: Examples and annexes".

[5] 3GPP TS 36.521-1: "User Equipment (UE) conformance specification, Radio transmission and reception Part 1: conformance testing".

[6] 3GPP TS 38.521-1: "NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 1: Range 1 Standalone".

[7] 3GPP TS 38.521-2: "NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 2: Range 2 Standalone".

[8] 3GPP TS 38.521-3: "NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 3: NR interworking between NR range1 + NR range2; and between NR and LTE".

[9] 3GPP TS 38.521-4: "NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 4: Performance requirements".

[10] 3GPP TS 38.533: "NR; User Equipment (UE) conformance specification; Radio Resource Management (RRM)".

[11] ETSI TR 102 273-1-1 V1.2.1 (2001-12): "Electromagnetic compatibility and Radio spectrum Matters (ERM); Improvement on Radiated Methods of Measurement (using test site) and evaluation of the corresponding measurement uncertainties; Part 1: Uncertainties in the measurement of mobile radio equipment characteristics; Sub-part 1: Introduction".

[12] 3GPP TR 25.914: "Measurement of Radio Performances for UMTS terminals in speech mode".

[13] 3GPP TR 38.810: "Study on test methods for New Radio ".

[14] CTIA OTA Test Plan version 3.7, https://www.ctia.org/.

[15] 3GPP TS 36.521-3: "User Equipment (UE) conformance specification, Radio transmission and reception Part 3: Radio Resource Management (RRM) conformance testing."

[16] 3GPP TS 38.101-2: "User Equipment (UE) radio transmission and reception Part 2: Range 2 Standalone"

[17] 3GPP TS 38.133: "Requirements for support of radio resource management"

[18] 3GPP TS 38.508-1: "5GS; User Equipment (UE) conformance specification; Part 1: Common test environment"

[19] 3GPP TS 38.101-4: "NR; User Equipment (UE) radio transmission and reception; Part 4: Performance requirements"

[20] 3GPP TS 37.571-1: User Equipment (UE) conformance specification for UE positioning; Part 1: Conformance test specification.

[21] 3GPP TS 38.215: "NR; Physical layer measurements"

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] apply.

3.2 Symbols

For the purposes of the present document, the following symbols apply:

ϕ	phi
θ	theta
σ	Standard uncertainty
$\Delta\phi$	Measurement grid spacing in ϕ for constant-step size grids
$\Delta\theta$	Measurement grid spacing in θ for constant-step size grids
ΔMB_S	Allowed relaxation to each, EIRP spherical coverage and EIS spherical coverage due to support for multi-band operation, per band in a combination of supported bands
D	DUT radiating aperture
Es	Received energy per RE (power normalized to the subcarrier spacing) during the useful part of the symbol, i.e. excluding the cyclic prefix, at the UE antenna connector or at the gNB reference point as defined in TS 38.215 [21], subclause 5.2 for the respective measurement type
G	UE Gain
gNB	node providing NR user plane and control plane protocol terminations towards the UE
Io	The total received power density, including signal and interference, as measured at the UE antenna connector
IoT	The received power spectral density of the total noise and interference for a certain RE (power integrated over the RE and normalized to the subcarrier spacing) as measured at the UE antenna connector or at the gNB reference point as defined in TS 38.215 [21], subclause 5.2 for the respective measurement type
lambda	wavelength

Noc The power spectral density of a white noise source (average power per RE normalised to the subcarrier spacing), simulating interference from cells that are not defined in a test procedure, as measured at the UE antenna connector

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

ACLR Adjacent Channel Leakage Ratio
ACS Adjacent Channel Selectivity
AoA Angle of Arrival
AWGN Additive White Gaussian Noise
BPSK Binary Phase-Shift Keying
BW Bandwidth
CA Carrier Aggregation
CCDF Complementary Cumulative Distribution Function
ChBW Channel Bandwidth
CP-OFDM Cyclic Prefix-OFDM
CSI Channel-State Information
DFF Direct Far Field
DFT-s-OFDM Discrete Fourier Transform-spread-OFDM
DL Downlink
DUT Device Under Test
EIS Effective Isotropic Sensitivity
EIRP Effective (or equivalent) isotropic radiated power
ETC Extreme Temperature Condition
EVM Error Vector Magnitude
FF Far Field
FFS For Further Study
FR1 Frequency Range 1
FR2 Frequency Range 2
FWA Fixed Wireless Access
IBB In-band Blocking
IFF Indirect Far Field
MBW Maximum Bandwidth
MCS Modulation and Coding Scheme
MIMO Multiple Input Multiple Output
MOP Maximum Output Power
MPR Maximum Power Reduction
MTSU Maximum Test System Uncertainty
MU Measurement Uncertainty
NC Normal Condition
NFTF Near Field To Far-field
NR New Radio
NTC Normal Temperature Condition
OFDM Orthogonal Frequency Division Multiplexing
OTA Over The Air
PAPR Peak-to-Average Power Ratio
PDCCH Physical Downlink Control Channel
PDSCH Physical Downlink Shared Channel
PRACH Physical RACH
PRB Physical Resource Block
PUCCH Physical Uplink Control Channel
PUSCH Physical Uplink Shared ChannelQAM Quadrature Amplitude Modulation
QZ Quiet Zone
QoQZ Quality of Quiet Zone
QPSK Quadrature Phase Shift Keying
RACH Random Access Channel
RB Resource Blocks
Refsens Reference Sensitivity

RRM	Radio Resource Management
RSS	Root Sum Squared
RSRP	Reference Signal Received Power
Rx	Receiver
SE	Spurious Emissions
SEM	Spectrum Emission Mask
SISO	Single Input Single Output
SCS	Subcarrier spacing
SSB	Synchronization Signal Block
SS-RSRP	Synchronization Signal based Reference Signal Received Power
SNR	Signal-to-Noise Ratio
STxMP	Simultaneous Transmission with Multi-Panel
TBD	To Be Determined
TC	Testcase
TCI	Transmission Configuration Indicator
TDL	Tapped Delay Line
TRP	Total Radiated Power
TT	Test Tolerance
UE	User Equipment
UL	Uplink
VNA	Vector Network Analyser
XPD	Cross Polar Discrimination

4 General Principles

4.1 Principle of Superposition

For multi-cell tests there are several cells each generating various Physical channels. In general cells are combined along with AWGN, so the signal and noise seen by the UE may be determined by more than one cell.

Since several cells may contribute towards the overall power applied to the UE, a number of test system uncertainties affect the signal and noise seen by the UE. The aim of the superposition method is to vary each controllable parameter of the test system separately, and to establish its effect on the critical parameters as seen by the UE receiver. The superposition principle then allows the effect of each test system uncertainty to be added, to calculate the overall effect.

The contributing test system uncertainties shall form a minimum set for the superposition principle to be applicable.

4.2 Sensitivity analysis

A change in any one channel level or channel ratio generated at source does not necessarily have a 1:1 effect at the UE. The effect of each controllable parameter of the test system on the critical parameters as seen by the UE receiver shall therefore be established. As a consequence of the sensitivity scaling factors not necessarily being unity, the test system uncertainties cannot be directly applied as test tolerances to the critical parameters as seen by the UE.

EXAMPLE: In many of the tests described, the $\hat{E}s / I_{ot}$ is one of the critical parameters at the UE. Scaling factors are used to model the sensitivity of the $\hat{E}s / I_{ot}$ to each test system uncertainty. When the scaling factors have been determined, the superposition principle then allows the effect of each test system uncertainty to be added, to give the overall variability in the critical parameters as seen at the UE.

There are often constraints on several parameters at the UE. The aim of the sensitivity analysis, together with the acceptable test system uncertainties, is to ensure that the variability in each of these parameters is controlled within the limits necessary for the specification to apply. The test has then been conducted under valid conditions.

4.3 Statistical combination of uncertainties

The acceptable uncertainties of the test system are specified as the measurement uncertainty tolerance interval for a specific measurement that contains 95 % of the performance of a population of test equipment. In the RRM and UE

radio transmission and reception conformance tests covered by the present document, the Test System shall enable the stimulus signals in the test case to be adjusted to within the specified range, with an uncertainty not exceeding the specified values.

The method given in the present document combines the acceptable uncertainties of the test system, to give the overall variability in the critical parameters as seen at the UE. Since the process does not add any new uncertainties, the method of combination should be chosen to maintain the same tolerance interval for the combined uncertainty as is already specified for the contributing test system uncertainties.

The basic principle for combining uncertainties is in accordance with ETR 273-1-2 [4]. In summary, the process requires 3 steps:

a) Express the value of each contributing uncertainty as a one standard deviation figure, from knowledge of its numeric value and its distribution.

b) Combine all the one standard deviation figures as root-sum-squares, to give the one standard deviation value for the combined uncertainty.

c) Expand the combined uncertainty by a coverage factor, according to the tolerance interval required.

Provided that the contributing uncertainties have already been obtained using this method, using a coverage factor of 2, further stages of combination can be achieved by performing step b) alone, since steps a) and c) simply divide by 2 and multiply by 2 respectively.

The root-sum-squares method is therefore used to maintain the same tolerance interval for the combined uncertainty as is already specified for the contributing test system uncertainties. In some cases where correlation between contributing uncertainties has an adverse effect, the method is modified in accordance with clause 4.4.5 of the present document.

In each analysis, the uncertainties are assumed to be uncorrelated, and are added result root-sum-square unless otherwise stated.

The combination of uncertainties is performed using dB values for simplicity. It has been shown that using dB uncertainty values gives a slightly worse combined uncertainty result than using linear values for the uncertainties. The analysis method therefore errs on the safe side.

4.4 Correlation between uncertainties

The statistical (root-sum-square) addition of uncertainties is based on the assumption that the uncertainties are independent of each other. For realisable test systems, the uncertainties may not be fully independent. The validity of the method used to add uncertainties depends on both the type of correlation and on the way in which the uncertainties affect the test requirements.

Clauses 4.4.1 to 4.4.3 give examples to illustrate different types of correlation.

Clauses 4.4.4 to 4.4.7 show how the scenarios applicable to multi-cell RRM tests are treated.

4.4.1 Uncorrelated uncertainties

The graph shows an example of two test system uncertainties, A and B, which affect a test requirement. Each sample from a population of test systems has a specific value of error in parameter A, and a specific value of error in parameter B. Each dot on the graph represents a sample from a population of test systems, and is plotted according to its error values for parameters A and B.




Figure 4.4.1-1: Example of two test system uncertainties affecting a test requirement

It can be seen that a positive value of error in parameter A, for example, is equally likely to occur with either a positive or a negative value of error in parameter B. This is expected when two parameters are uncorrelated, such as two uncertainties which arise from different and unrelated parts of the test system.

4.4.2 Positively correlated uncertainties

The graph shows an example of two test system uncertainties, A and B, which affect a test requirement. Each sample from a population of test systems has a specific value of error in parameter A, and a specific value of error in parameter B. Each dot on the graph represents a sample from a population of test systems, and is plotted according to its error values for parameters A and B.




Figure 4.4.2-1: Example of two test system uncertainties affecting a test requirement

It can be seen that a positive value of error in parameter A, for example, is more likely to occur with a positive value of error in parameter B and less likely to occur with a negative value of error in parameter B. This can occur when the two uncertainties arise from similar parts of the test system, or when one component of the uncertainty affects both parameters in a similar way.

In an extreme case, if the error in parameter A and the error in parameter B came from the same sources of uncertainty, and no others, the dots would lie on a straight line of slope +1.

4.4.3 Negatively correlated uncertainties

The graph shows an example of two test system uncertainties, A and B, which affect a test condition. Each sample from a population of test systems has a specific value of error in parameter A, and a specific value of error in parameter B. Each dot on the graph represents a sample from a population of test systems, and is plotted according to its error values for parameters A and B.




Figure 4.4.3-1: Example of two test system uncertainties affecting a test condition

It can be seen that a positive value of error in parameter A, for example, is more likely to occur with a negative value of error in parameter B and less likely to occur with a positive value of error in parameter B. This effect can theoretically occur, and is included for completeness, but is unlikely in a practical test system.

4.4.4 Treatment of uncorrelated uncertainties

If two uncertainties are uncorrelated, they are added statistically in the analysis. Provided that each uncertainty is already expressed as an expanded uncertainty with coverage factor 2, the contributing uncertainties are added root-sum-squares to give a combined uncertainty which also has coverage factor 2, and the 95% tolerance interval is maintained.

This is the default assumption.

4.4.5 Treatment of positively correlated uncertainties with adverse effect

If two test system uncertainties are positively correlated, and if they affect the value of a critical parameter in the same direction, the combined effect may be greater than predicted by adding the contributing uncertainties root-sum-squares.

In this scenario the two uncertainties are added worst-case in the analysis. Provided that each uncertainty is already expressed as an expanded uncertainty with coverage factor 2, the combined uncertainty will cover a 95% tolerance interval even when the two contributing uncertainties are fully correlated. If the two contributing uncertainties are less than fully correlated, the combined uncertainty will cover a tolerance interval greater than 95%.

4.4.6 Treatment of positively correlated uncertainties with beneficial effect

If two test system uncertainties are positively correlated, and if they affect the value of a critical parameter in opposite directions, the combined effect will be less than predicted by adding the contributing uncertainties root-sum-squares.

In this scenario the two uncertainties are added statistically in the analysis. Provided that each uncertainty is already expressed as an expanded uncertainty with coverage factor 2, the combined uncertainty will cover a 95% tolerance interval when the two contributing uncertainties are uncorrelated. If the two contributing uncertainties are positively correlated, the combined uncertainty will cover a tolerance interval greater than 95%.

4.4.7 Treatment of negatively correlated uncertainties

Negatively correlated uncertainties are excluded by the assumptions. This has been agreed as an acceptable restriction on practical test systems, as the mechanisms which produce correlation generally arise from similarities between two parts of the test system, and therefore produce positive correlation.

5 Determination of Test System Uncertainties

5.1 General

The uncertainty of a test system when making measurements reduces the ability of the test system to distinguish between conformant and non-conformant test subjects. The aim is therefore to minimise uncertainty, subject to a number of practical constraints:

a) A vendor's test system should be reproducible in the required quantities.

b) A choice of test systems should be available from different vendors.

c) The uncertainties should allow reasonable freedom of test system implementation

d) The test system can be run automatically

e) The test system may include several radio access technologies

f) It should be possible to maintain calibration of deployed test systems over reasonable spans of time and environmental conditions

In practice therefore within 3GPP the acceptable uncertainty of the test system is the smallest value that can be agreed between the test system vendors represented, consistent with the above constraints. The uncertainty will not therefore be as low as could be achieved, for example, by a national standards laboratory.

5.2 Uncertainty figures

The actual figures for the acceptable uncertainty of a test system are defined in Annex F of 38.521-1, Annex F of 38.521-2, Annex F of 38.521-3, Annex F of TS 38.521-4, Annex F of TS 38.533 and Annex C of 37.571-1. To avoid maintenance issues with figures in separate specifications, the uncertainties are not formally defined within the present document, but informative guidelines are provided in Annex B to Annex E of the present document.

6 Determination of Test Tolerances

6.1 General

The general principles given in the present document are applied to each test case, according to the applicable uncertainties and requirements to obtain a correct verdict.

The test cases which have been analysed to determine Test Tolerances are included the present document as .zip files. The name of the zip file indicates the specification and the test cases covered.

Annex A gives the rationale for their inclusion.

7 Grouping of test cases defined in TS 38.521-4

Editor's note: intended to capture grouping of demodulation test cases.

Table 7-1: Grouping of FR1 test cases defined in Clause 5 of TS 38.521-4

Group	Test Case Numbers	.zip file name	Comments
PDSCH_Intercell_interference	5.2.2.1.15 5.2.2.2.16 5.2.3.1.15 5.2.3.2.16	"38.521-4 5.2.2.1.15 TT.zip"	"2 Interfering NR Cells, 2 sub-tests, Fading"
PDSCH_Intercell_CRS_interference	5.2.2.1.19 5.2.2.2.20 5.2.3.1.18 5.2.3.2.19	"38.521-4 5.2.2.1.19 TT.zip"	"2 Interfering LTE Cells, 2 sub-tests for FDD, 4 sub-tests for TDD, Fading"
PDSCH_CRS_interference_mitigation_under_NR-LTE_coexistence	5.2.2.1.18 5.2.2.2.19 5.2.3.1.17 5.2.3.2.18	"38.521-4 5.2.2.1.18 TT.zip"	"2 Interfering LTE Cells, 1 sub-test, Fading"

Table 7-2: Grouping of FR1 test cases defined in Clause 6 of TS 38.521-4

Group	Test Case Numbers	.zip file name	Comments
CQI_Intercell_interference	6.2.2.1.2.3 6.2.2.2.2.3 6.2.3.1.2.3 6.2.3.2.2.3	"38.521-4 6.2.2.1.2.3 TT.zip"	"1 Interfering NR Cell, 1 sub-test, Fading"

8 Grouping of test cases defined in TS 38.533

Table 8-1: Grouping of FR1 test cases defined in Clauses 4, 4A, 6, 8, 16, 18 and 19 of TS 38.533

Group	Test Case Numbers	.zip file name	Comments
SCell_Activation_01	4.5.3.1 4.5.3.2 4.5.3.3 6.5.3.1 6.5.3.2 6.5.3.3	“38.533 4.5.3.1+4.5.3.2+6.5.3.1+6.5.3.2 TT v7.zip”	“2 Inter Frequency NR Cells, 3 time periods, Various number of sub-tests, No fading”
SCell_Activation_05	4.5.3.4	“38.533 4.5.3.4 TT.zip”	“3 Cells with 2 Intra frequency and 3rd cell with Inter Frequency NR FR1 Cells, Various number of sub-tests, No fading” multiple unknown SCells in FR1 with single activation/deactivation command
SCell_Activation_06	6.5.3.17	“38.533 6.5.3.17 TT.zip”	“2 Inter Frequency NR Cells, 3 time periods, Various number of sub-tests, No fading” Scell is having 12 PRB configuration
SCell_Activation_02	4.5.3.5 6.5.3.4	“38.533 4.5.3.5 +6.5.3.4 TT.zip”	“2 Inter Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading” Direct Scell activation configurations
DCI_Based_BWP_Switch_02	4.5.6.3.1 6.5.6.3.1	“38.533 4.5.6.3.1 TT.zip”	“2 NR cells, 3 time periods, No fading” DCI-based and Timer-based
ATG_pathloss_RS_switch	19.4.5.1	“38.533 19.4.5.1 TT.zip”	“1 NR Cell, 1 sub-test, no fading, 3 Time Periods”
RRC_Based_BWP_Switch_02	4.5.6.4.1 6.5.6.5.1	“38.533 4.5.6.4.1 TT.zip”	“3 NR cells, 3 time periods, No fading” RRC-based
PSCell_Activation	4.5.10.1	“38.533 4.5.10.1 TT.zip”	1 NR Cell, no fading
PSCell_Activation	5.5.12.1	“38.533 5.5.12.1 TT.zip”	1 NR Cell, no fading
SCell_Activation_03	6.5.3.5	“38.533 6.5.3.5 TT.zip”	“3 Cells with 2 Intra frequency and 3rd cell with Inter Frequency NR FR1 Cells, Various number of sub-tests, No fading” direct Scell activation configurations
SCell_Activation_04	4.5.3.6 4.5.3.7 6.5.3.10 6.5.3.11	“38.533 4.5.3.6+4.5.3.7 +6.5.3.10+6.5.3.11 TT.zip”	“2 Inter Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading” Fast Scell activation configurations

Intra_Freq_Meas_01	4.6.1.1 4.6.1.2 4.6.1.3 4.6.1.4 4.6.1.5 4.6.1.6 4.6.1.7 6.6.1.1 6.6.1.2 6.6.1.3 6.6.1.4 6.6.1.5 6.6.1.6 6.6.1.7 6.6.1.9 6.6.1.13 6.6.19.1 6.6.24.1 6.6.24.5 16.6.1.2 16.6.1.4 16.6.1.6 16.6.1.8 16.6.1.10 16.6.1.12 16.6.5.2 19.5.1.1 19.5.1.2 19.5.1.3 19.5.1.4	“38.533 4.6.1.1+4.6.1.2+4.6.1.3+4.6.1.4 TT v6.zip”	“2 Intra Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading” Note: The spreadsheet “16.6.1.4-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
Intra_Freq_Meas_02	6.6.1.12	“38.533 6.6.1.12 TT.zip”	“2 Intra Frequency NR Cells, 2 time periods, No fading”
Intra_Freq_Meas_03	6.6.1.14	“38.533 6.6.1.14 TT.zip”	“2 Intra Frequency NR Cells, 2 time periods, No fading”
Intra_Freq_Meas_04	6.6.1.15	“38.533 6.6.1.15 TT.zip”	“2 Intra Frequency NR Cells, 2 time periods, No fading”

Intra_Freq_CGI_identification	4.6.6.1 6.6.7.1 19.5.5.1	“38.533 4.6.6.1 TT.zip”	“2 Intra Frequency NR Cells, 3 time periods, Various number of sub-tests, No fading”
Inter_RAT_E-UTRA_CGI_Identification	16.6.5.4 6.6.7.2	“38.533 16.6.5.4 TT_v2.zip”	“1 NR cell and 1 E-UTRA cell, 3 time periods, Various number of sub-tests, No fading”
Intra_Freq_MG_Enh	6.6.17.1 6.6.17.2	“38.533 6.6.17.1+6.6.17.2 TT.zip”	“2 Intra Frequency NR Cells, 3 time periods, Various number of sub-tests, No fading”
Intra_Freq_Meas_RedCap_1Rx_01	16.6.1.1 16.6.1.3 16.6.1.5 16.6.1.7 16.6.1.9 16.6.1.11 16.6.5.1	“38.533 16.6.1.1+16.6.1.3+16.6.1.5+16.6.1.7 TT.zip”	“2 Intra Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading”
Intra_Freq_HST_Meas_01	4.6.1.8 6.6.1.8 6.6.19.4	“38.533 4.6.1.8+6.6.1.8 TT”	“3 NR cells on 2 channels (2 Intra Frequency NR Cells), 2 time periods, Various number of sub-tests, No fading”
Inter_Freq_Meas_01	4.6.2.1 4.6.2.2 4.6.2.5 4.6.2.6 4.6.2.9 6.6.2.1 6.6.2.2 6.6.2.5 6.6.2.6 6.6.2.9 6.6.2.10 6.6.2.11 6.6.2.12 6.6.2.13 6.6.2.14 6.6.19.2 6.6.23.1 6.6.23.2 6.6.24.2 6.6.24.3 6.6.24.4 16.6.2.2 16.6.2.4 16.6.2.6 16.6.2.8 16.6.2.10 16.6.2.12 19.5.2.1 19.5.2.2 19.5.2.3	“4.6.2.1+4.6.2.2+4.6.2.5+4.6.2.6 TT v7.zip"	“2 Inter Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading” Note: The spreadsheet “16.6.2.2-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations

Inter_Freq_Meas_02	6.6.2.15	“38.533 6.6.2.15 TT.zip"	“2 Inter Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading”
Inter_Freq_MG_Enh	6.6.18.1 6.6.18.2	“6.6.18.1+6.6.18.2 TT.zip"	“3 Inter Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading”
Inter_Freq_MG_Enh_01	6.6.18.4	“38.533 6.6.18.4 TT.zip"	“2 Inter Frequency NR Cells, 1 Intra Frequency NR Cell with PRS 2 time periods, Various number of sub-tests, No fading”
Intra_inter_Freq_MG_Enh2_01	6.6.22.1	“38.533 6.6.22.1 TT.zip"	“2 intra-frequency cells and 1 inter-frequency cell”
Intra_inter_Freq_MG_Enh2_02	6.6.22.2	“38.533 6.6.22.2 TT.zip"	“2 intra-frequency cells and 1 inter-frequency cell”
intra_Freq_MG_Enh2_SCell	6.6.23.3	“38.533 6.6.23.3 TT.zip"	“3 intra-frequency cells, including a PCell, 1 SCell and 1 intra-frequency cell on SCC”
Intra_Reselection_01	6.1.1.1 16.1.1.2 19.1.1	“38.533 6.1.1.1 +16.1.1.2_v2.zip”	“2 Intra Frequency NR Cells, 3 time periods, No fading” The spreadsheet “16.1.1.2-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
Intra_Reselection_02	6.1.1.9	“38.533 6.1.1.9 TT v2.zip”	“2 Intra Frequency NR Cells, 3 time periods, No fading”
Inter_Reselection_01	6.1.1.2 6.1.1.8 16.1.1.4	38.533 6.1.1.2 + 16.1.1.4 TT	“2 Inter Frequency NR Cells, 3 time periods, No fading” The spreadsheet “16.1.1.4-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
Inter_Reselection_02	19.1.2	“38.533 19.1.2.zip"	“2 Inter Frequency NR Cells, 3 time periods, No fading”
Inter_Reselection_03	19.1.3	“38.533 19.1.3.zip"	“2 Inter Frequency NR Cells, 2 time periods, No fading”

InterRAT_Higher_Reselection_01	6.1.2.1 16.1.2.2	38.533 6.1.2.1+16.1.2.2	“1 E-UTRAN Cell, 1 NR Cells, 3 time periods, No fading” The spreadsheet “16.1.2.2-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
InterRAT_Lower_Reselection_01	6.1.2.2 6.1.2.3 6.1.2.5 16.1.2.4 16.1.2.6	38.533 6.1.2.2+6.1.2.3+6.1.2.5+16.1.2.4	“1 E-UTRAN Cell, 1 NR Cells, 2 time periods, No fading” The spreadsheet “16.1.2.4-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
InterRAT_Lower_Reselection_02	6.1.2.4	“38.533 6.1.2.4 TT.zip”	“1 E-UTRAN Cell, 1 NR Cells, 2 time periods, No fading”
InterRAT_Known_Handover_01_1Rx	16.3.1.7	”38.533 16.3.1.7 TT.zip”	“1 E-UTRAN Cell, 1 NR Cells, 3 time periods, No fading”
InterRAT_Known_Handover_01	6.3.1.4 16.3.1.8	”38.533 6.3.1.4+16.3.1.8 TT v2.zip”	“1 E-UTRAN Cell, 1 NR Cells, 3 time periods, No fading” Note: The spreadsheet “16.3.1.8-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
InterRAT_Unknown_Handover_01_1Rx	16.3.1.9	”38.533 16.3.1.9 TT.zip”	“1 E-UTRAN Cell, 1 NR Cells, 2 time periods, No fading”
InterRAT_Unknown_Handover_01	6.3.1.5 16.3.1.10	“38.533 6.3.1.5+16.3.1.10 TT.zip”	“1 E-UTRAN Cell, 1 NR Cells, 2 time periods, No fading” Note: The spreadsheet “16.3.1.10-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
Intra_RRC_re-establishment_01	6.3.2.1.1 16.3.2.1.1 16.3.2.1.2 19.2.3.1.1	“38.533 6.3.2.1.1+16.3.2.1.1+16.3.2.1.2 TT.zip”	“2 Intra Frequency NR Cells, 3 time periods, No fading” Note: The spreadsheet “16.3.2.1.2-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.

Intra_SS-RSRP_Abs_Acc_01	4.7.1.1.1 6.7.1.1.1 16.7.1.2.1 19.6.1.1.1	“38.533 4.7.1.1.1+6.7.1.1.1+16.7.1.2.1+19.6.1.1.1 TT_v2.zip”	“2 Intra-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
Intra_SS-RSRP_Rel_Acc_01	4.7.1.1.2 6.7.1.1.2 16.7.1.2.2 19.6.1.1.2	“38.533 4.7.1.1.2+6.7.1.1.2+16.7.1.2.2+19.6.1.1.2 TT.zip"	“2 Intra-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
Intra_CSI-RSRP_Abs_Acc_01	4.7.8.1	“38.533 4.7.8.1 TT.zip”	“2 Intra-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
Intra_SS-RSRP_Abs_Acc_01_RedCap_1Rx	16.7.1.1.1	“38.533 16.7.1.1.1 TT.zip”	2 Intra-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
Intra_SS-RSRP_Rel_Acc_01_RedCap_1Rx	16.7.1.1.2	38.533 16.7.1.1.2 TT.zip	“2 Intra-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
Inter_RRC_re-establishment_01	6.3.2.1.2 16.3.2.1.3 16.3.2.1.4	“38.533 6.3.2.1.2+16.3.2.1.3+16.3.2.1.4+19.2.3.1.2 TT.zip”	“2 Inter Frequency NR Cells, 3 time periods, No fading” Note: The spreadsheet “16.3.2.1.4-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
Inter_RRC_redirection_01	6.3.2.3.1 16.3.2.3.1 16.3.2.3.2 18.2.2.1 19.2.3.3.1	“38.533 6.3.2.3.1+16.3.2.3.1+16.3.2.3.2+18.2.2.1 TT.v2zip”	“2 Inter Frequency NR Cells, 2 time periods, No fading” Note: The spreadsheet “16.3.2.3.2-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
InterRAT_RRC_redirection_01	6.3.2.3.2 16.3.2.3.3 16.3.2.3.4	“38.533 6.3.2.3.2+16.3.2.3.3+16.3.2.3.4 TT.zip”	“1 E-UTRAN Cell, 1 NR Cells, 2 time periods, No fading” Note: The spreadsheet “16.3.2.3.4-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
MTRP_uTCI_Switch	6.5.13.1	“38.533 6.5.13.1 TT.zip”	“1 NR Cell, 2 time periods, No fading”

RLM_InSync_01	4.5.1.2 4.5.1.4 6.5.1.2 6.5.1.4 4.5.1.6 4.5.1.8 6.5.1.6 6.5.1.8 16.5.1.3 16.5.1.4 16.5.1.7 16.5.1.8 16.5.1.11 16.5.1.12 16.5.1.15 16.5.1.16	"38.533 4.5.1.2+4.5.1.4+6.5.1.2+6.5.1.4 TT v4.zip"	"1 NR Cell (1 E-UTRA Cell for NSA case), 1 sub-test, Fading, 5 Time Periods" Note: The spreadsheet "16.5.1.4-3" only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
RLM_Out_of_Sync_01	4.5.1.1 4.5.1.3 6.5.1.1 6.5.1.3 4.5.1.5 4.5.1.7 6.5.1.5 6.5.1.7 16.5.1.1 16.5.1.2 16.5.1.5 16.5.1.6 16.5.1.9 16.5.1.10 16.5.1.13 16.5.1.14	"38.533 4.5.1.1+4.5.1.3+6.5.1.1+6.5.1.3 TT v5.zip"	"1 NR Cell (1 E-UTRA Cell for NSA case), 1 sub-test, Fading, 3 Time Periods" Note: The spreadsheet "16.5.1.2-3" only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
RLM_InSync_02	6.5.1.16	"38.533 6.5.1.16 TT v2.zip"	"1 NR Cell, Fading, 5 Time Periods"
RLM_InSync_03	6.5.1.15	"38.533 6.5.1.15 TT v2.zip"	"1 NR Cell, Fading, 5 Time Periods"
RLM_Out_of_Sync_02	6.5.1.13	"38.533 6.5.1.13 TT v2.zip"	"1 NR Cell, Fading, 3 Time Periods"
RLM_Out_of_Sync_03	6.5.1.14	"38.533 6.5.1.14 TT v2.zip"	"1 NR Cell, Fading, 3 Time Periods"
UE_Timing_Advance_01	4.4.3.1 6.4.3.1 10.2.2.1 11.3.2.1 16.4.3.1 16.4.3.2 19.3.3.1	"38.533 4.4.3.1+6.4.3.1+16.4.3.1+16.4.3.2 TT_v3.zip"	"1 NR Cell (1 E-UTRA Cell for NSA case), No Fading"
UE Transmit_Timing_01	4.4.1.1 6.4.1.1 10.2.1.1 11.3.1.1 16.4.1.1 16.4.1.2	"38.533 4.4.1.1+6.4.1.1+16.4.1.1+16.4.1.2 TT_v2.zip"	"1 NR Cell (1 E-UTRA Cell for NSA case), 2 sub-tests, No Fading"
UE Transmit_Timing_02	19.3.1.1	"38.533 19.3.1.1 TT.zip"	"1 NR Cell, No Fading"
RRC_reconfiguration_delay_01	4.5.4.1 6.5.4.1	"38.533 4.5.4.1+6.5.4.1 TT_v2.zip"	"1 E-UTRA Cell, 2 NR Cells", 3 Time Periods, No Fading"

Intra_Freq_HO_Known_Target	6.3.1.1 16.3.1.2 19.2.1.1	“38.533 6.3.1.1+16.3.1.2 TT.zip”	“2 Intra-Freq NR Cells, 3 Time Periods, No Fading” Note: The spreadsheet “16.3.1.2-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
Intra_Freq_HO_Known_Target_1 Rx_RedCap	16.3.1.1	“38.533 16.3.1.1 TT_v2.zip”	“2 Intra-Freq NR Cells, 3 Time Periods, No Fading”
Intra_Freq_HO_Unknown_Target	6.3.1.2 16.3.1.3 16.3.1.4	“38.533 6.3.1.2+16.3.1.4 TT.zip”	“2 Intra-Freq NR Cells, 2 Time Periods, No Fading” Note: The spreadsheet “16.3.1.4-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
Intra_Freq_HO_Unknown_Target _01	6.3.1.18	“38.533 6.3.1.18 TT.v2zip”	“2 Intra-Freq NR Cells, 2 Time Periods, No Fading”
Inter_Freq_HO	6.3.1.3 16.3.1.5 16.3.1.6 19.2.1.2	“38.533 6.3.1.3+16.3.1.6 TT.zip”	“2 Inter-Freq NR Cells, 2 Time Periods, No Fading” Note: The spreadsheet “16.3.1.6-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
InterRAT_Meas_01	6.6.3.1 6.6.3.2 6.6.19.3 6.6.25.1 6.6.25.2 6.6.25.3	“38.533 6.6.3.1+6.6.3.2 TT v3.zip”	“1 E-UTRAN Cell, 1 NR Cell, 2 time periods
InterRAT_Meas_MG_Enh	6.6.18.3	“38.533 6.6.18.3 TT.zip”	“1 E-UTRAN Cell, 2 Inter-Frequency NR Cells, 2 time periods
Interruption_Transition_01	4.5.2.1 4.5.2.2	“38.533 4.5.2.1+4.5.2.2 TT.zip”	“1 E-UTRAN Cell, 1 NR Cells, 1 time period, No fading”
Interruption_meas_NR_SCC_01	4.5.2.3 4.5.2.4 6.5.2.1	“38.533 4.5.2.3+4.5.2.4+6.5.2.1 TT.zip”	“1 E-UTRAN Cell, 2 NR Cells (2 NR Cells for SA case), 1 time period, No fading”
Interruption_meas_NR_SCC_01	4.5.2.5 4.5.2.6	“38.533 4.5.2.5+4.5.2.6 TT.zip”	“2 E-UTRAN Cell, 1 NR Cells, 1 time period, No fading”
Interruption_SRS_01	4.5.2.8 4.5.2.9 6.5.2.2	“38.533 4.5.2.8+4.5.2.9+6.5.2.2 TT.zip”	“1 NR Cell, (1 E-UTRA) 1 time period, No fading”
Interruption_meas_NR_PSCell	4.5.2.10	“38.533 4.5.2.10 TT.zip”	“1 E-UTRAN Cell, 1 NR Cells, 1 time period, No fading”

Inter_SS-RSRP_Abs_Acc_01	4.7.1.2.1 6.7.1.2.1 16.7.1.4.1 19.6.1.2.1	”38.533 4.7.1.2.1+6.7.1.2.1+16.7.1.4.1+19.6.1 .2.1 TT_v2.zip”	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
Inter_SS-RSRP_Rel_Acc_01	4.7.1.2.2 6.7.1.2.2 16.7.1.4.2 19.6.1.2.2	"38.533 4.7.1.2.2+6.7.1.2.2+16.7.1.4.2+19.6.1 .2.2 TT.zip”	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
Inter_SS-RSRP_Abs_Acc_01_RedCap_1Rx	16.7.1.3.1	38.533 16.7.1.3.1 TT.zip	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
Inter_SS-RSRP_Rel_Acc_01_RedCap_1Rx	16.7.1.3.2	38.533 16.7.1.3.2 TT.zip	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
Intra_SS-SINR_Acc_01	4.7.3.1 6.7.3.1 16.7.3.1 16.7.3.2 19.6.3.1	“38.533 4.7.3.1+6.7.3.1+16.7.3.1+16.7.3.2 TT_v2.zip”	“2 Intra-Frequency NR Cells, periodic reporting, No fading”
Inter_CSI-RSRP_Abs_Acc_01	4.7.8.2	“38.533 4.7.8.2 TT.zip”	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
SSB_Based_L1-RSRP-Meas	4.6.4.1 4.6.4.2 4.6.4.5 6.6.4.1 6.6.4.2 6.6.4.5 6.6.4.6 16.6.4.2 16.6.4.4 19.5.3.1	"38.533 4.6.4.1+4.6.4.2+6.6.4.1+6.6.4.2 TT v4.zip"	“1 NR Cell (1 E-UTRA Cell for NSA case), 2 time periods, No fading” Note: The spreadsheet “16.6.4.2-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
SSB_Based_L1-RSRP-Meas_RedCap_1Rx	16.6.4.1 16.6.4.3	“38.533 16.6.4.1+16.6.4.3 TT.zip”	“1 NR Cell, 2 time periods, No fading”
Intra-frequency_SSB_Based_L1-RSRP-Meas	6.6.26.1	“38.533 6.6.26.1 TT.zip”	“1 NR serving cell and 1 NR intra frequency cell, various number of sub-tests, 2 time periods, periodic reporting, no fading”
Inter-frequency_SSB_Based_L1-RSRP-Meas_01	6.6.27.1	“38.533 6.6.27.1 TT.zip”	“1 NR serving cell and 1 NR inter frequency cell, 2 time periods, periodic reporting, no fading”
Inter-frequency_SSB_Based_L1-RSRP-Meas_02	6.6.28.1	“38.533 6.6.28.1 TT.zip”	“1 NR serving cell and 1 NR inter frequency cell, various number of sub-tests, 2 time periods, periodic reporting, no fading”
CSI-RS_Based_L1-RSRP-Meas	4.6.4.3 4.6.4.4 6.6.4.3 6.6.4.4 16.6.4.6 16.6.4.8 19.5.3.2	“38.533 4.6.4.3+4.6.4.4+6.6.4.3+6.6.4.4 TT v6.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), one time period, No fading” Note: The spreadsheet “16.6.4.6-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.

CSI-RS_Based_L1-RSRP-Meas_RedCap_1Rx	16.6.4.5 16.6.4.7	“38.533 16.6.4.5+16.6.4.7 TT.zip”	“1 NR Cell, one time period, No fading”
CSI-RS_WithoutIMR_L1-SINR-Meas	4.6.7.1 6.6.8.1 19.5.4.1	“38.533 4.6.7.1+6.6.8.1 TT.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), one time period, No fading”
SSB_WithCSI-IM_L1-SINR-Meas	4.6.7.2	“38.533 4.6.7.2 TT.zip”	“1 E-UTRA Cell, 1 NR Cell, 2 time periods, No fading”
CSI-RS_WithCSI-IM_L1-SINR-Meas_abs_acc	4.7.7.3.1 6.7.9.3.1 19.6.5.3.1	“38.533 4.7.7.3.1+6.7.9.3.1+19.6.5.3.1 TT.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), one time period, No fading”
CSI-RS_WithCSI-IM_L1-SINR-Meas_rel_acc	4.7.7.3.2 6.7.9.3.2 19.6.5.3.2	“38.533 4.7.7.3.2+6.7.9.3.2+19.6.5.3.2 TT.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), one time period, No fading”
CSI-RS_Based_L1-SINR-Meas_abs_acc	4.7.7.1.1 6.7.9.1.1 19.6.5.1.1	“38.533 4.7.7.1.1+6.7.9.1.1+19.6.5.1.1 TT.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), one time period, No fading”
CSI-RS_Based_L1-SINR-Meas_rel_acc	4.7.7.1.2 6.7.9.1.2 19.6.5.1.2	“38.533 4.7.7.1.2+6.7.9.1.2+19.6.5.1.2 TT.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), one time period, No fading”
SSB_WithCSI-IM_L1-SINR-Meas	4.7.7.2 6.7.9.2 19.6.5.2	“38.533 4.7.7.2+6.7.9.2+19.6.5.2 TT.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), one time period, No fading”
CSI-RS_WithNZP_L1-SINR-Meas	4.6.7.3	“38.533 4.6.7.3 TT.zip”	“1 E-UTRA Cell, 1 NR Cell, one time period, No fading”
Intra_SS-RSRQ_Acc_01	4.7.2.1 6.7.2.1 16.7.2.2 19.6.2.1	“38.533 4.7.2.1+6.7.2.1+16.7.2.2+19.6.2.1 TT.zip”	“2 Intra-Frequency NR Cells, periodic reporting, No fading”
Intra_SS-RSRQ_Acc_01_RedCap_1Rx	16.7.2.1	“38.533 16.7.2.1 TT.zip”	“2 Intra-Frequency NR Cells, periodic reporting, No fading”
Inter_SS-RSRQ_Abs_Acc_01	4.7.2.2.1 6.7.2.2.1 19.6.2.2.1	“38.533 4.7.2.2.1+6.7.2.2.1+16.7.2.4.1+19.6.2.2.1 TT.zip”	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
Inter_SS-RSRQ_Rel_Acc_01	4.7.2.2.2 6.7.2.2.2 19.6.2.2.2	“38.533 4.7.2.2.2+6.7.2.2.2+16.7.2.4.2+19.6.2.2.2 TT.zip”	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
Inter_SS-SINR_Abs_Acc_01	4.7.3.2.1 6.7.3.2.1 16.7.3.4.1 19.6.3.2.1	“38.533 4.7.3.2.1+6.7.3.2.1+16.7.3.4.1+19.6.3.2.1 TT.zip”	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
Inter_SS-SINR_Rel_Acc_01	4.7.3.2.2 6.7.3.2.2 16.7.3.4.2 19.6.3.2.2	“38.533 4.7.3.2.2+6.7.3.2.2+16.7.3.4.2+19.6.3.2.2 TT.zip”	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
Inter_RAT_SS-RSRP_LTE_Serving_01	8.5.2.1.1.1	“38.533 8.5.2.1.1.1 TT.zip”	1 NR Cell, 1 LTE serving cell, periodic SS-RSRP reporting, No fading
Inter_RAT_SS-RSRQ_LTE_Serving_01	8.5.2.2.1	“38.533 8.5.2.2.1 TT.zip”	1 NR Cell, 1 LTE serving cell, periodic SS-RSRQ reporting, No fading
Inter_RAT_SS-SINR_LTE_Serving_01	8.5.2.3.1	“38.533 8.5.2.3.1 TT.zip”	1 NR Cell, 1 LTE serving cell, periodic SS-SINR reporting, No fading

L1-RSRP_Abs_Acc_01	4.7.4.1.1 6.7.4.1.1 4.7.4.2.1 6.7.4.2.1 16.7.4.2.1 16.7.4.4.1 19.6.4.1.1 19.6.4.2.1	"38.533 4.7.4.1.1+4.7.4.2.1+6.7.4.1.1+6.7.4.2.1 TT v4.zip"	1 NR Cell, periodic L1-RSRP reporting, No fading
L1-RSRP_Abs_Acc_01_RedCap_1Rx	16.7.4.1.1 16.7.4.3.1	"38.533 16.7.4.1.1 TT.zip"	1 NR Cell, periodic L1-RSRP reporting, No fading
Inter-frequency_L1-RSRP_Abs_Acc	6.7.17.1.1	"38.533 6.7.17.1.1 TT.zip"	"1 NR serving cell and 1 NR inter frequency cell, periodic L1-RSRP reporting, no fading"
L1-RSRP_Rel_Acc_01	4.7.4.1.2 6.7.4.1.2 4.7.4.2.2 6.7.4.2.2 16.7.4.4.2 19.6.4.1.2 19.6.4.2.2	"38.533 4.7.4.1.2+4.7.4.2.2+6.7.4.1.2+6.7.4.2.2 TT v5.zip"	1 NR Cell with 2 Beams, periodic L1-RSRP reporting, No fading
L1-RSRP_Rel_Acc_01_RedCap_1Rx	16.7.4.1.2 16.7.4.3.2	"38.533 16.7.4.1.2 TT.zip"	1 NR Cell with 2 Beams, periodic L1-RSRP reporting, No fading
SSB_Based_BFR	4.5.5.1 4.5.5.2 6.5.5.1 6.5.5.2 16.5.2.2 16.5.2.4	"38.533 4.5.5.1+4.5.5.2+6.5.5.1+6.5.5.2 TT v4.zip"	"1 NR Cell (1 E-UTRA Cell for NSA case), 5 time periods, Fading" Note: The spreadsheet "16.5.2.2-3" only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
SSB_Based_BFR_01	6.5.5.8	"38.533 6.5.5.8 TT.zip"	"1 NR Cell, 5 time periods, Fading"
SSB_Based_BFR_02	19.4.2.1	"38.533 19.4.2.1 TT.zip"	"1 NR Cell, 5 time periods, No fading"
TRP specific SSB_Based_BFR	4.5.5.7	38.533 4.5.5.7 TT.zip	1 NR Cell 1 E-UTRA Cell PCell, 5 time periods, Fading"
SSB_Based_BFR_RedCap_1Rx_01	16.5.2.1 16.5.2.3	"38.533 16.5.2.3 TT.zip"	"1 NR Cell (1 E-UTRA Cell for NSA case), 5 time periods, Fading"
CSI-RS_Based_BFR	4.5.5.3 4.5.5.4 6.5.5.3 6.5.5.4 16.5.2.6 16.5.2.8	"38.533 4.5.5.3+4.5.5.4+6.5.5.3+6.5.5.4 TT v3.zip"	"1 NR Cell (1 E-UTRA Cell for NSA case), 5 time periods, Fading" Note: The spreadsheet "16.5.2.6-3" only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
CSI-RS_Based_BFR_01	19.4.2.2	"38.533 19.4.2.2 TT.zip"	"1 NR Cell, 5 time periods, No fading"

CSI-RS_Based_BFR_RedCap_1Rx	16.5.2.5 16.5.2.7	“38.533 16.5.2.5+16.5.2.7 TT.zip”	“1 NR Cell, 5 time periods, Fading”
TRP specific CSI-RS_Based_BFR	6.5.5.7	“38.533 6.5.5.7 TT.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), 5 time periods, Fading”
CSI-RS_Based_BFD_SSB_Based_FR	4.5.5.5 4.5.5.6 6.5.5.5 6.5.5.6	For SSB refer to “38.533 4.5.5.1+4.5.5.2+6.5.5.1+6.5.5.2 TT v2.zip” For CSI-RS refer to “38.533 4.5.5.3+4.5.5.4+6.5.5.3+6.5.5.4 TT v2.zip”	“2 NR Cell (1 E-UTRA Cell for NSA case), 5 time periods, Fading”
TRP specific CSI-RS_Based_BFD_SSB_Based_FR	4.5.5.8	38.533 4.5.5.8 TT.zip	“2 NR Cell (1 E-UTRA Cell for NSA case), 5 time periods, Fading”
DCI_Based_BWP_Switch	4.5.6.1.1 4.5.6.1.2 6.5.6.1.1 6.5.6.1.2 16.5.3.1.1 16.5.3.1.2 19.4.3.1.1	“38.533 4.5.6.1.1+4.5.6.1.2+6.5.6.1.1+6.5.6.1.2 TT v3.zip“	“1 NR Cell (2NR Cells for Scell case, 1 E-UTRA Cell for NSA case), 3 time periods, No fading”
RRC_Based_BWP_Switch_01	4.5.6.2.1 6.5.6.2.1 16.5.3.2.1 16.5.3.2.2 19.4.3.2.1	“38.533 4.5.6.2.1+6.5.6.2.1+16.5.3.2.1+16.5.3.2.2 T v2T.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), 3 time periods, No fading”
Intra_RRC_re-establishment_without_timing	6.3.2.1.3 16.3.2.1.5 16.3.2.1.6	“38.533 6.3.2.1.3+16.3.2.1.5+16.3.2.1.6 TT.zip”	“2 Intra Frequency NR Cells, 3 time periods, No fading” Note: The spreadsheet “16.3.2.1.6-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
InterRAT_re-selection_LTE_Serving	8.2.1.1	“38.533 8.2.1.1 TT.zip”	“1 NR Cell, 1 LTE serving cell, 3 time periods No fading”
InterRAT_HO_LTE_Serving	8.3.1.1 18.2.1.1	“38.533 8.3.1.1+18.2.1.1 TT.zip”	“1 NR Cell, 1 LTE serving cell, 3 time periods No fading” Note: The spreadsheet “18.2.1.1-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
InterRAT_SFTD_Meas_LTE_Serving	8.4.1.1 8.4.1.2	“38.533 8.4.1.1+8.4.1.2 TT.zip”	“1 NR Cell, 1 LTE serving cell, 1 time period No fading”

InterRAT_Meas_LTE_Serving	8.4.2.1 8.4.2.2 8.4.2.3 8.4.2.4 18.3.1.1 18.3.1.2 18.3.1.3 18.3.1.4	“38.533 8.4.2.1+8.4.2.2+8.4.2.3+8.4.2.4 TT v3.zip”	“1 NR Cell, 1 LTE serving cell, 2 time periods, No Fading”
InterRAT_Meas_LTE_Serving_gap-less	8.4.3.2	“38.533 8.4.3.2.zip”	“1 NR Cell, 1 LTE serving cell, 2 time periods, No Fading”
PSCell_Addition	4.5.7.1	“38.533 4.5.7.1 TT v2.zip”	1 NR Cell, no fading
PSCell_Addition_01	4.5.11.1	“38.533 4.5.11.1 TT.zip”	1 NR Cell, no fading
SFTD_Accuracy	4.7.5.1	“38.533 4.7.5.1 TT.zip”	1 E-UTRA Cell, 1 NR Cell, no fading
SSB_WithNZP-IMR_L1-SINR-Meas	6.6.8.2 19.5.4.2	“38.533 6.6.8.2 TT.zip”	“1 NR Cell, 2 time periods, No fading”
CSI-RS_WithCSI-IM_L1-SINR-Meas	6.6.8.3 19.5.4.3	“38.533 6.6.8.3 TT.zip”	“1 NR Cell, one time period, No fading”
RLM_Out_of_Sync_PowerSaving Enh	4.5.1.9 6.5.1.9	38.533 4.5.1.9+6.5.1.9 TT.zip	1 NR Cell (1 E-UTRA Cell for NSA case), 1 sub-test, Fading, 3 Time Periods
iRAT_E-UTRA_RSRP_Accuracy	6.7.5.1	“38.533 6.7.5.1 TT.zip”	1 E-UTRA Cell, 1 NR Cell, no fading
iRAT_E-UTRA_RSRQ_Accuracy	6.7.6.1	“38.533 6.7.6.1 TT.zip”	1 E-UTRA Cell, 1 NR Cell, no fading
iRAT_E-UTRA_RS-SINR_Accuracy	6.7.7.1	“38.533 6.7.7.1 TT.zip”	1 E-UTRA Cell, 1 NR Cell, no fading
InterRAT_SFTD_Meas_Accuracy_LTE_Serving	8.5.1.1	“38.533 8.5.1.1 TT.zip”	1 E-UTRA Cell, 1 NR Cell, no fading
Inter_Freq_HO_DAPS	6.3.1.9 6.3.1.10	“38.533 6.3.1.9+6.3.1.10 TT.zip”	“2 Inter-Freq NR Cells, 5 Time Periods, No Fading”
Intra_Reselection_Low_Mobility	6.1.1.3 16.1.1.6	38.533 6.1.1.3+16.1.1.6 TT	“2 Intra Frequency NR Cells, 2 time periods, No fading” The spreadsheet “16.1.1.6-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
Intra_Reselection_Not_cell_edge	6.1.1.4	“38.533 6.1.1.4 TT.zip”	“2 Intra Frequency NR Cells, 2 time periods, No fading”
Inter_Reselection_Low_mobility	6.1.1.5 16.1.1.8	38.533 6.1.1.5+16.1.1.8 TT	“2 Inter Frequency NR Cells, 2 time periods, No fading” The spreadsheet “16.1.1.8-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
Inter_Reselection_Not_cell_edge	6.1.1.6	“38.533 6.1.1.6 TT.zip”	“2 Inter Frequency NR Cells, 2 time periods, No fading”
Intra_Reselection_HST	6.1.1.7	“38.533 6.1.1.7 TT.zip”	“2 Intra Frequency NR Cells, 3 time periods, No fading”

InterRAT_HO_UTRA_FDD	6.3.1.6	“38.533 6.3.1.6 TT.zip”	“1 UTRA Cell, 1 NR Cell, 3 time periods, No fading”
InterRAT_Meas_UTRA_FDD	6.6.5.1	“38.533 6.6.5.1 TT.zip”	“1 UTRA Cell, 1 NR Cell, 2 time periods, No fading”
InterRAT_Meas_HST	6.6.3.3	“38.533 6.6.3.3 TT.zip”	1 E-UTRA Cell, 1 NR Cell, no fading
InterRAT_re-selection_LTE_Serving_HST	8.2.1.2	“38.533 8.2.1.2 TT.zip”	1 E-UTRA Cell, 1 NR Cell, no fading
InterRAT_Meas_LTE_Serving_HST	8.4.2.9	“38.533 8.4.2.9 TT.zip”	1 E-UTRA Cell, 1 NR Cell, no fading
Intra_Freq_HO_DAPS	6.3.1.7 6.3.1.8	“38.533 6.3.1.7+6.3.1.8 TT.zip”	“2 Intra-Freq NR Cells, 5 Time Periods, No Fading”
Inter_Freq_HO_DAPS	6.3.1.9 6.3.1.10	“38.533 6.3.1.9+6.3.1.10 TT.zip”	“2 Inter-Freq NR Cells, 5 Time Periods, No Fading”
Inter_Freq_HO_DAPS	6.3.1.11 6.3.1.12	“38.533 6.3.1.11+6.3.1.12 TT.zip”	“2 Inter-band Inter-Freq NR Cells, 5 Time Periods, No Fading”
Intra_Freq_CHO	6.3.3.1 6.3.3.6 19.2.2.1	“38.533 6.3.3.1+19.2.2.1 TT.zip”	“2 Intra-Freq NR Cells, 2 Time Periods, No Fading”
Intra_Freq_CHO_01	6.3.3.3	“38.533 6.3.3.3 TT.zip”	“4 Intra-Freq NR Cells, 2 Time Periods, No Fading”
Intra_Freq_CHO_02	6.3.3.4	“38.533 6.3.3.4 TT v2.zip”	“4 Intra-Freq NR Cells, 3 Time Periods, No Fading”
Intra_Freq_CHO_03	6.3.3.5	“38.533 6.3.3.5 TT.zip”	“2 Inter-Freq NR Cells, 2 intra-freq NR Cells, 2 Time Periods, No Fading”
Inter_Freq_CHO	6.3.3.2 19.2.2.2	“38.533 6.3.3.2+19.2.2.2 TT.zip”	“2 Inter-Freq NR Cells, 2 Time Periods, No Fading”
Inter_Freq_NES_CHO	6.3.3.7	“38.533 6.3.3.7 TT.zip”	“2 Inter-Freq NR Cells, 2 Time Periods, No Fading”
Intra_Freq_LTM_cell_switch_RACHbased	6.3.4.1	“38.533 6.3.4.1 TT.zip”	“2 Intra-Freq NR Cells, 4 time periods, No Fading”
Inter_Freq_LTM_cell_switch_RACHbased	6.3.4.2	“38.533 6.3.4.2 TT.zip”	“2 Inter-Freq NR Cells,
Intra_Freq_LTM_cell_switch_RACHless	6.3.4.3 6.3.4.4	“38.533 6.3.4.3 TT_v2.zip”	“2 Intra-Freq NR Cells, 5 Time Periods, No Fading”
Intra_Freq_CLI_SRS-RSRP	4.6.5.1 6.6.6.1	“38.533 4.6.5.1+6.6.6.1 TT.zip”	“1 E-UTRA Cell (clause 4 test only), 1 NR Cell, 1 Virtual UE, 2 Time Periods, no fading”

Intra_Freq_LTM_PSCell_switch_RACHbased	6.3.5.1	“38.533 6.3.5.1 TT.zip”	“2 Intra-Freq NR Cells, 4 time periods, No Fading”
Intra_Freq_CLI_RSSI	4.6.5.2	“38.533 4.6.5.2 TT.zip”	“1 E-UTRA Cell, 1 NR Cell, 2 Time Periods, no fading”
Intra_Freq_CLI_SRS-RSRP_Accuracy	4.7.6.1 6.7.8.1	“38.533 4.7.6.1+6.7.8.1 TT.zip”	“1 E-UTRA Cell (clause 4 test only), 1 NR Cell, 1 Virtual UE, 1 Time Period, no fading”
DL_Interruption_UL_Switching_SA_01	6.5.7.1 6.5.7.2 6.5.7A.1 6.5.7A.2 6.5.7B.1 6.5.7B.2 6.5.7C.1 6.5.7C.2 6.5.7D.1 6.5.7D.2 6.5.7D.3 6.5.7D.4 4.5.8.1	“38.533 6.5.7.1+6.5.7.2+6.5.7A.1+6.5.7A.2 TT_v2.zip”	“2 NR Cells, 1 time period, no fading”
PRACH_01_1RX	16.3.2.2.1 16.3.2.2.3 16.3.2.2.5 16.3.2.2.7	“38.533 16.3.2.2.1+16.3.2.2.3+16.3.2.2.5+16.3.2.2.7 TT v2”	“1 NR Cell, PRACH measurements, no fading”
PRACH_01	4.3.2.2.1 4.3.2.2.2 6.3.2.2.1 6.3.2.2.2 16.3.2.2.2 16.3.2.2.4 19.2.3.2.1 19.2.3.2.2	“38.533 4.3.2.2.1+4.3.2.2.2+6.3.2.2.1+6.3.2.2.2 TT v4.zip”	“1 NR Cell, PRACH measurements, no fading” Note: The spreadsheet “16.3.2.2.2-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
PRACH_02	4.3.2.2.3 4.3.2.2.4 6.3.2.2.3 6.3.2.2.4 16.3.2.2.6 16.3.2.2.8 19.2.3.2.3 19.2.3.2.4	“38.533 4.3.2.2.3+4.3.2.2.4+6.3.2.2.3+6.3.2.2.4 TT v5.zip”	“1 NR Cell, PRACH measurements, no fading” Note: The spreadsheet “16.3.2.2.6-3” only applies to 30kHz SCS + 20MHz CBW RedCap test configurations.
Idle_CADC_meas	6.6.9.1	“38.533 6.6.9.1 TT.zip”	“2 NR Cells, 5 time periods, no fading”
Idle_CADC_fast_meas_01	6.6.9.2 6.6.9.3	“38.533 6.6.9.2+6.6.9.3 TT”	“2 NR Cells, 4 time periods, no fading”
Idle_CADC_meas_01	6.6.9.5	“38.533 6.6.6.9.5 TT.zip”	“2 NR Cells, 5 time periods, no fading”
CBW_change	6.5.8.1 16.5.4.1 16.5.4.2	“38.533 6.5.8.1+16.5.4.1+16.5.4.2 TT.zip”	“1 NR Cell, 1 time period, no fading”
NE-DC PSCell addition	4A.1.1.1	“38.533 4A.1.1.1 TT.zip”	“1 E-UTRA Cell, no fading”

NE-DC SFTD accuracy	4A.2.1.1	“38.533 4A.2.1.1 TT.zip”	“1 NR Cell, 1 E-UTRA Cell, no fading”
InterRAT_Idle_CADC_meas	6.6.15.1	“38.533 6.6.15.1 TT.zip”	“1 NR Cell, 1 E-UTRA Cell, 3 time periods, no fading”
InterRAT_LTE_Idle_CADC_meas	8.2.2.1	“38.533 8.2.2.1 TT.zip”	“1 E-UTRA Cell, 1 NR Cell, 3 time periods, no fading”
Inter_Freq_Idle_CADC_meas_no_report	7.6.23.1 7.6.23.2	“38.533 7.6.23.1+7.6.23.2 TT.zip”	“1 NR FR1 Cell, 1 NR FR2 Cell, 4 time periods, no fading”
UE_Rx_Tx_difference_PDC_01	6.6.20.1 6.6.21.1	“38.533 6.6.20+6.6.21 TT.zip”	“1 NR Cell, 2 time periods, no fading”
Inter_Reselection_RedCap_1Rx	16.1.1.1	“38.533 16.1.1.1 TT_v2.zip”	“2 Intra Frequency NR Cells, 3 time periods, No fading, 1Rx RedCap UE”
Inter_Reselection_RedCap_1Rx	16.1.1.3	38.533 16.1.1.3 TT	“2 Inter Frequency NR Cells, 3 time periods, No fading, 1Rx RedCap UE”
Intra_Reselection_Low_Mobility_RedCap_1Rx	16.1.1.5	“38.533 16.1.1.5 TT_v2.zip”	“2 Intra Frequency NR Cells, 2 time periods, No fading, 1Rx RedCap UE”
Inter_Reselection_Low_mobility_RedCap_1Rx	16.1.1.7	38.533 16.1.1.7 TT	“2 Inter Frequency NR Cells, 2 time periods, No fading, 1Rx RedCap UE”
InterRAT_Higher_Reselection_RedCap_1Rx	16.1.2.1	38.533 16.1.2.1 TT	“1 E-UTRAN Cell, 1 NR Cells, 3 time periods, No fading, 1Rx RedCap UE”
InterRAT_Lower_Reselection_RedCap_1Rx	16.1.2.3	38.533 16.1.2.3 TT	“1 E-UTRAN Cell, 1 NR Cells, 2 time periods, No fading, 1Rx RedCap UE”
InterRAT_Lower_Reselection_RedCap_Relaxed_1Rx	16.1.2.5	38.533 16.1.2.5 TT	“1 E-UTRAN Cell, 1 NR Cells, 2 time periods, No fading, 1Rx RedCap UE”
Inter_Freq_Meas_01	16.6.2.1 16.6.2.3 16.6.2.5 16.6.2.7 16.6.2.9 16.6.2.11	38.533 16.6.2.1+16.6.2.3+16.6.2.5+16.6.2.7 TT	“2 Inter Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading, 1Rx RedCap UE”
CG-SDT	6.2.1	38.533 6.2.1+16.6.1.2 TT	“1 NR Cell, 6 time periods, no fading” Note: the spreadsheet "16.2.1.2-3" only applies to RedCap 30kHz+20MHz test configuration
CG-SDT_1Rx	16.2.1.1	“38.533 16.2.1.1 TT.zip”	“1 NR Cell, 6 time periods, no fading”

Inter-RAT_Meas_RedCap_1Rx_01	16.6.3.1 16.6.3.3	“38.533 16.6.3.1+16.6.3.3 TT_v2.zip”	1 E-UTRA Cell, 1 NR Cell, no fading, 1Rx RedCap UE
Inter-RAT_Meas_RedCap_1Rx_02	16.6.3.2 16.6.3.4	“38.533 16.6.3.2+16.6.3.4 TT_v2.zip”	1 E-UTRA Cell, 1 NR Cell, no fading, 2Rx RedCap UE
UE_Specific_CBW_Change	4.5.9.1 19.4.4.1	“38.533 4.5.9.1+19.4.4.1 TT.zip”	“1 E-UTRA Cell and 1 NR Cell, 1 time period, no fading”
Intra-LTM_PDCCH_Order	6.3.2.4.1 6.3.2.4.3	“38.533 6.3.2.4.1+6.3.2.4.3 TT.zip”	“2 Intra Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading”
Inter-LTM_PDCCH_Order	6.3.2.4.2	“38.533 6.3.2.4.2 TT.zip”	“2 Inter Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading”
InterRAT_re-selection_LTE_Serving_RedCap	18.1.1.1	“38.533 18.1.1.1 TT.zip”	“1 NR Cell, 1 LTE serving cell, 3 time periods, no fading, 2Rx RedCap UE”
SSBless_SCell_Activation	4.5.3.12 6.5.3.16	“38.533 4.5.3.12+6.5.3.16 TTv2.zip”	“2 Inter Frequency NR Cells, 2 time periods, No fading”
SSBless_SCell_Activation_01	4.5.3.11 6.5.3.15	“38.533 4.5.3.11 TT.zip”	“2 Inter Frequency NR Cells, 2 time periods, No fading”
Intra_CSI-RSRP_Abs_Acc	19.6.6.1.1	“38.533 19.6.6.1.1 TT.zip”	“2 Intra-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
Intra_CSI-RSRP_Rel_Acc	19.6.6.1.2	“38.533 19.6.6.1.2 TT.zip”	“2 Intra-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
Inter_CSI-RSRP_Abs_Acc	19.6.6.2.1	“38.533 19.6.6.2.1 TT.zip”	“2 Inter-Frequency NR Cells, 2 Sub-tests, periodic reporting, No fading”
Inter_CSI-RSRP_Rel_Acc	19.6.6.2.2	“38.533 19.6.6.2.2 TT.zip”	“2 Inter-Frequency NR Cells, 2 Sub-tests, periodic reporting, No fading”
Intra_CSI-RSRQ_Abs_Acc	19.6.7.1	“38.533 19.6.7.1 TT.zip”	“2 Intra-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
Inter_CSI-RSRQ_Abs_Acc	19.6.7.2.1	“38.533 19.6.7.2.1 TT.zip”	“2 Inter-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”

Inter_CSI-RSRQ_Rel_Acc	19.6.7.2.2	“38.533 19.6.7.2.2 TT.zip”	“2 Inter-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
Intra_CSI-SINR_Abs_Acc	19.6.8.1	“38.533 19.6.8.1 TT.zip”	“2 Intra-Frequency NR Cells, 2 Sub-tests, periodic reporting, No fading”
Inter_CSI-SINR_Abs_Acc	19.6.8.2.1	“38.533 19.6.8.2.1 TT.zip”	“2 Inter-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
Inter_CSI-SINR_Rel_Acc	19.6.8.2.2	“38.533 19.6.8.2.2 TT.zip”	“2 Inter-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
RLM_Out_of_Sync_ATG_01	19.4.1.1 19.4.1.3	“38.533 19.4.1.1+19.4.1.3 TT.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), 1 sub-test, No Fading, 3 Time Periods”
RLM_In_Sync_ATG_01	19.4.1.2 19.4.1.4	“38.533 19.4.1.2+19.4.1.4 TT.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), 1 sub-test, No Fading, 5 Time Periods”

Table 8-2: Grouping of FR2 test cases defined in Clauses 5, 7, 8 and 17 of TS 38.533

Group	Test Case Numbers	.zip file name	Comments
Transmit_Timing_01	5.4.1.1 7.4.1.1 17.4.1.1 7.4.1.3 5.4.1.2	“38.533 5.4.1.1+7.4.1.1 TT v3.zip”	1 NR FR2 cell, no fading
Timing_Advance_01	5.4.3.1 7.4.3.1 17.4.3.1	“38.533 5.4.3.1+7.4.3.1 TT v2.zip"	1 NR FR2 cell, no fading
iRAT_meas_LTE_Serving	8.4.2.5 18.3.1.5	“38.533 8.4.2.5+18.3.1.5 TT.zip"	“1 NR FR2 cell, 1 E-UTRA serving cell, 2 time periods, No fading”
iRAT_meas_LTE_Serving_01	8.4.2.6 8.4.2.7 8.4.2.8 18.3.1.6 18.3.1.7 18.3.1.8	“38.533 8.4.2.6+8.4.2.7+8.4.2.8+18.3.1.6 TT.zip”	“1 NR FR2 cell, 1 E-UTRA serving cell, 2 time periods, No fading”
iRAT_SS-RSRP_01	8.5.2.1.2	“38.533 8.5.2.1.2 TT.zip”	“1 NR FR2 cell, 1 E-UTRA serving cell, 2 sub-tests, No fading”
iRAT_SS-RSRQ_01	8.5.2.2.2	“38.533 8.5.2.2.2 TT.zip”	“1 NR FR2 cell, 1 E-UTRA serving cell, 2 sub-tests, No fading”
iRAT_SS-SINR_01	8.5.2.3.2	“38.533 8.5.2.3.2 TT.zip”	“1 NR FR2 cell, 1 E-UTRA serving cell, 2 sub-tests, No fading”
Interruption_Transition_01	5.5.2.1 5.5.2.2	“38.533 5.5.2.1+5.5.2.2 TT.zip”	”1 E-UTRAN Cell, 1 NR FR2 Cell, 1 time period, No fading”
Interruption_meas_NR_SCC_01	5.5.2.3 5.5.2.4 7.5.2.1	“38.533 5.5.2.3+5.5.2.4+7.5.2.1 TT.zip”	1 E-UTRAN Cell, 2 NR Cells (2 NR Cells for SA case), 1 time period, No fading
Interruption_E-UTRA_SRS_switching	5.5.2.7	“38.533 5.5.2.7 TT.zip”	“2 E-UTRA cells, 1 NR cell, 2 time periods, No fading”
Interruption_NR_SRS_switching	5.5.2.8	“38.533 5.5.2.8 TT.zip”	“1 E-UTRA cell, 2 NR cells, 2 time periods, No fading”
SCell_Activation_01	5.5.3.1 5.5.3.7	“38.533 5.5.3.1 TT.zip”	“2 Inter Frequency NR FR2 Cells, 3 time periods, Various number of sub-tests, No fading”
RRC_Based_Activation_Deactivation_Multiple_CCs	5.5.3.6	“38.533 5.5.3.6 TT.zip”	“1 FR1 NR cell, 2 FR2 NR cells, 3 time periods, No fading”
SCell_Activation_02	7.5.3.3	“38.533 7.5.3.3 TT.zip”	“2 Inter Frequency NR FR2 Cells, 3 time periods, Various number of sub-tests, No fading”

SCell_Activation_02	7.5.3.4	“38.533 7.5.3.4 TT.zip”	“2 Inter Frequency NR FR2 Cells, 3 time periods, Various number of sub-tests, No fading” direct Scell activation configurations
SCell_Activation_03	7.5.3.5	“38.533 7.5.3.5 TT.zip”	“3 Cells with 2 Intra frequency and 3rd cell with Inter Frequency NR FR2 Cells, 3 time periods, Various number of sub-tests, No fading” direct Scell activation with handover test case
SCell_Activation_04	5.5.3.8 7.5.3.13	“38.533 5.5.3.8+7.5.3.13 TT.zip”	“2 Inter Frequency NR FR2 Cells, 2 time periods, Various number of sub-tests, No fading” fast Scell activation configurations
FastSCell_Activation	7.5.3.14	“38.533 7.5.3.14 TT.zip”	“2 Inter Frequency NR FR2 Cells, 2 time periods, No fading”
UE_Specific_CBW_Change_NR_FR2	5.5.10.1 7.5.10.1	“38.533 5.5.10.1+7.5.10.1 TT.zip”	“1 NR FR2 cell (1 E-UTRA cell for NSA case), 1 time period, No fading”
Intra_Freq_Meas_01	5.6.1.1 5.6.1.3 7.6.1.1 7.6.1.3 7.6.16.1 17.6.1.1 17.6.1.3 7.6.19.1 7.6.19.2	"38.533 5.6.1.1+5.6.1.3+7.6.1.1+7.6.1.3 v4 TT.zip"	2 NR FR2 Cells (1 E-UTRA Cell for NSA case), 2 SSBs, 2 time periods, no fading, 2 AoAs, both are in EIS spherical coverage and rough beams
Intra_Freq_Meas_02	5.6.1.2 5.6.1.4 7.6.1.2 7.6.1.4 17.6.1.2 17.6.1.4	“38.533 5.6.1.2+5.6.1.4+7.6.1.2+7.6.1.4 TT v2.zip”	2 NR FR2 Cells (1 E-UTRA Cell for NSA case), 2 SSBs, 2 time periods, no fading, 1 AoA in Rx peak and rough beam
CSI-RS based_Inter_Freq_Meas	5.6.8.1	"38.533 5.6.8.1 TT.zip"	2 NR FR2 Cells (1 E-UTRA Cell for NSA case), 2 SSBs/CSI-RSs, 2 time periods, no fading, 1 AoA in Rx peak and rough beam
Inter_Freq_Meas_01	5.6.2.1 5.6.2.3 7.6.2.1 7.6.2.3 7.6.2.20 7.6.2.21 17.6.2.1 17.6.2.3	“38.533 5.6.2.1+5.6.2.3+7.6.2.1+7.6.2.3 TTv4.zip”	“2 Inter Frequency NR FR2 Cells, 2 time periods, Various number of sub-tests, No fading”

Inter_Freq_Meas_02	5.6.2.5 5.6.2.7 7.6.2.5 7.6.2.7	"38.533 5.6.2.5+5.6.2.7+7.6.2.5+7.6.2.7 TT.zip"	"2 Inter Frequency NR Cells (Cell 1 on FR1 and Cell 2 on FR2), 2 time periods, Various number of sub-tests, No fading"
Inter_Freq_Meas_03	5.6.2.6 5.6.2.8 7.6.2.6 7.6.2.8	"38.533 5.6.2.6+5.6.2.8+7.6.2.6+7.6.2.8 TT.zip"	"2 Inter Frequency NR Cells (Cell 1 on FR1 and Cell 2 on FR2), 2 time periods, Various number of sub-tests, No fading"
Inter_Freq_Meas_04	5.6.2.2 5.6.2.4 7.6.2.2 7.6.2.4 17.6.2.2 17.6.2.4	"38.533 5.6.2.2+5.6.2.4+7.6.2.2+7.6.2.4 TT.zip"	"2 Inter Frequency NR Cells (both on FR2), 2 time periods, Various number of sub-tests, No fading"
Event_Triggered_Reporting_Test	7.6.2.9	"38.533 7.6.2.9 TT.zip"	"2 NR FR2 Cells, 2 time periods, No fading"
SSB_Based_L1-RSRP-Meas	5.6.3.1 5.6.3.2 7.6.3.1 7.6.3.2 17.6.3.1 17.6.3.2	"38.533 5.6.3.1+5.6.3.2+7.6.3.1+7.6.3.2 TT.zip"	"1 NR FR2 Cell (1 E-UTRA Cell for NSA case), 2 time periods, No fading"
SSB_Based_L1-RSRP-Meas_01	7.6.3.5	"38.533 7.6.3.5 TT.zip"	"1 NR FR2 Cell, 2 time periods, No fading"
Inter_Freq_CGI_NR_Neighbor	5.6.5.1	"38.533 5.6.5.1 TT.zip"	"2 NR Cells (1 E-UTRA Cell for NSA case), 3 time periods, No fading"
Inter_Freq_CGI_NR_Neighbor_02	7.6.5.1	"38.533 7.6.5.1 TT.zip"	"2 NR Cells, 2 time periods, No fading"
Intra_Freq_SSB_Based_L1-RSRP-Meas	7.6.20.1	"38.533 7.6.20.1 TT.zip"	"1 NR serving cell and 1 NR intra-frequency cell, various number of sub-tests, 2 time periods, periodic reporting, no fading"
Inter_Freq_SSB_Based_L1-RSRP-Meas 01	7.6.21.1	"38.533 7.6.21.1 TT.zip"	"1 NR serving cell and 1 NR inter-frequency cell, 2 time periods, periodic reporting, no fading"
Inter_Freq_SSB_Based_L1-RSRP-Meas_02	7.6.22.1	"38.533 7.6.22.1 TT.zip"	"1 NR serving cell and 1 NR inter-frequency cell, 2 time periods, periodic reporting, no fading"
SS-RSRP_01	5.7.1.1 7.7.1.1 17.7.1.1	"38.533 5.7.1.1+7.7.1.1 TT v4.zip"	"2 Intra-Frequency NR FR2 Cells, 2 sub-tests, No fading"
CSI-RSRP_01	5.7.7.1	"38.533 5.7.7.1 TT.zip"	"2 Intra-Frequency NR FR2 Cells, 2 sub-tests, No fading"
SS-RSRP_02	5.7.1.2 7.7.1.2 17.7.1.2	"38.533 5.7.1.2+7.7.1.2 TT v4.zip"	"2 Inter-Frequency NR FR2 Cells, 2 sub-tests, No fading"

CSI-RSRP_02	5.7.7.2	“38.533 5.7.7.2 TT.zip”	“2 Inter-Frequency NR FR2 Cells, 2 sub-tests, No fading”
SS-RSRP_03	5.7.1.3 7.7.1.3	“38.533 5.7.1.3+7.7.1.3 TT.zip”	“1 NR FR1 Cell, 1 NR FR2 Cell, 2 sub-tests, No fading”
SS-RSRQ_01	5.7.2.1 7.7.2.1 17.7.2.1	“38.533 5.7.2.1+7.7.2.1 TT.zip”	“2 Intra-Frequency NR FR2 Cells, 2 sub-tests, No fading”
SS-RSRQ_02	5.7.2.2 7.7.2.2 17.7.2.2	“38.533 5.7.2.2+7.7.2.2 TT.zip”	“2 Inter-Frequency NR FR2 Cells, 2 sub-tests, No fading”
SS-SINR_01	5.7.3.1 7.7.3.1 17.7.4.1	“38.533 5.7.3.1+7.7.3.1 TT.zip”	“2 Intra-Frequency NR FR2 Cells, 2 sub-tests, No fading”
SS-SINR_02	5.7.3.2 7.7.3.2 17.7.4.2	“38.533 5.7.3.2+7.7.3.2 TT v2.zip”	“2 Inter-Frequency NR FR2 Cells, 3 sub-tests, No fading”
CSI-RS_Based_L1-RSRP-Meas	5.6.3.3 5.6.3.4 7.6.3.3 7.6.3.4 17.6.3.3 17.6.3.4	“38.533 5.6.3.3+6.6.3.4+7.6.3.3+7.6.3.4 TT.zip”	“1 NR FR2 Cell (1 E-UTRA Cell for NSA case), 1 time period, No fading”
SSB_Based_BFD	5.5.5.1 5.5.5.2 5.5.5.5 7.5.5.1 7.5.5.2 7.5.5.5 17.5.2.1 17.5.2.2 17.5.2.5	"38.533 5.5.5.1+5.5.5.2+7.5.5.1+7.5.5.2 TT.zip"	"1 NR FR2 Cell (1 E-UTRA Cell for NSA case), 2 SSBs, 5 time periods, fading, 1AoA Rx peak, Rough beam"
CSI-RS Based BFD and BFR	5.5.5.3 5.5.5.4 7.5.5.3 7.5.5.4 17.5.2.3 17.5.2.4	“38.533 5.5.5.3+5.5.5.4+7.5.5.3+7.5.5.4 TT v2.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), 5 time periods, Fading”
CSI-RS Based SCell BFD and BFR	5.5.5.6 5.5.5.7 7.5.5.6 7.5.5.7	“38.533 5.5.5.3+5.5.5.4+7.5.5.3+7.5.5.4 TT v2.zip”	“2 NR Cell (1 E-UTRA Cell for NSA case), 5 time periods, Fading”
TRP specific CSI-RS Based BFD and BFR	5.5.5.8 7.5.5.9	“38.533 5.5.5.8+7.5.5.9 TT.zip”	“2 NR Cell (1 E-UTRA Cell for NSA case), 5 time periods, Fading”
SSB_Based_BFD_Relaxed_Meas	5.5.5.9	"38.533 5.5.5.9 TT.zip"	"1 NR FR2 Cell (1 E-UTRA Cell for NSA case), 2 SSBs, 5 time periods, fading, 1AoA Rx peak, Rough beam"
TRP specific SSB_Based_BFD	7.5.5.10	“38.533 7.5.5.10 TT.zip”	"2 NR FR2 Cell, 2 SSBs, 5 time periods, fading"
TRP specific CSI-RS_Based_BFD_multi-Rx	7.5.5.14	“38.533 7.5.5.14 TT.zip”	"1 NR FR2 Cell, 3AoA, spherical coverage, 3 CSI-RS sets, 5 time periods, fading"
CSI-RS_Based_L1-RSRP_Meas_multi-Rx	7.5.16	“38.533 7.5.16 TT.zip”	"1 NR FR2 Cell, 2 AoA, 2 SSBs, 2 CSI-RS, 2 time periods, no fading, no noise"

CSI-RS_WithoutIMR_L1-SINR-Meas	5.6.6.1 7.6.6.1	“38.533 5.6.6.1+7.6.6.1 TT.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), one time period, No fading”
CSI-RS_WithCSI-IM_L1-SINR-Meas	5.6.6.3	“38.533 5.6.6.3 TT.zip”	“1 E-UTRA Cell, 1 NR Cell, one time period, No fading”
Inter_Reselection_low_mobility	7.1.1.5 17.1.1.4	“38.533 7.1.1.5 TT.zip”	“2 NR FR2 Cells, 2 SSBs, 2 time periods, 1 AoA in Rx peak and rough beam”
CSI-RS_RLM_Out_of_Sync_02	5.5.1.7 7.5.1.7 17.5.1.7	“38.533 5.5.1.7+7.5.1.7 TT.zip”	1 NR FR2 Cell (1 E-UTRA cell), 2 CSI-RSs, 3 time periods, 1AoA beam peak directions and rough beam, fading.
CSI-RS_RLM_InSync_02	5.5.1.8 7.5.1.8 17.5.1.8	“38.533 5.5.1.8+7.5.1.8 TT.zip”	1 NR FR2 Cell (1 E-UTRA cell), 2 CSI-RSs, 5 time periods, 1AoA in beam peak directions and rough beam, fading.
SSB_WithNZP-IMR_L1-SINR-Meas	5.6.6.2	“38.533 5.6.6.2 TT.zip”	“1 E-UTRA Cell, 1 NR Cell, 2 time periods, No fading”
Inter_band_DAPS_HO	7.3.1.4 7.3.1.5	"38.533 7.3.1.4+7.3.1.5 TT.zip	"1 NR FR2 Cell, 1 SSB, 5 time periods, 1 AoA in Rx peak and rough beam"
Intra_Freq_RRC_re-establishment_01	7.3.2.1.1 17.3.2.1.1	“38.533 7.3.2.1.1+17.3.2.1.1 TT”	“2 Intra Frequency NR Cells, 3 time periods, No fading”
Intra_Freq_RRC_re-establishment_02	7.3.2.1.3 17.3.2.1.3	“38.533 7.3.2.1.3+17.3.2.1.3 TT”	“2 Intra Frequency NR Cells, 3 time periods, No fading”
Inter_Freq_RRC_re-establishment_01	7.3.2.1.2 17.3.2.1.2	“38.533 7.3.2.1.2+17.3.2.1.2 TT”	“2 Inter Frequency NR Cells, 3 time periods, No fading”
Intra_freq_HO	7.3.1.2 17.3.1.1	“38.533 7.3.1.2 TT.zip”	2 NR FR2 intra-frequency Cells, 2 time periods, no fading
Inter_freq_HO	7.3.1.3 17.3.1.2	“38.533 7.3.1.3+7.3.2.3.1 TT.zip”	2 NR FR2 inter-frequency Cells, 2 time periods, no fading
Inter_freq_redirection	7.3.2.3.1 17.3.2.3.1	“38.533 7.3.1.3+7.3.2.3.1 TT.zip”	2 NR FR2 inter-frequency Cells, 2 time periods, no fading
Intra_freq_CHO	7.3.3.1 7.3.3.3	"38.533 7.3.3.1 TT.zip	2 NR FR2 Cells, 2 SSBs, 2 time periods, 1 AoA in Rx peak and rough beam
Intra_Inter_Freq_CHO_02	7.3.3.5	“38.533 7.3.3.5 TT.zip”	“2 Intra-Freq NR Cells, 2 Inter-Freq NR Cells, 2 Time Periods, No Fading”
Intra_Inter_Freq_CHO_03	7.3.3.6	“38.533 7.3.3.6 TT.zip”	“2 Intra-Freq NR Cells, 2 Inter-Freq NR Cells, 3 Time Periods, No Fading”

Intra_Freq_LTM_cell_switch_RACHbased	7.3.4.1	“38.533 7.3.4.1 TT.zip”	2 NR FR2 Intra-Freq Cells, 4 time periods, No Fading, 1 AoA in Rx peak and rough beam
Intra_Freq_LTM_PSCell_switch_RACHbased	7.3.5.1	“38.533 7.3.5.1 TT.zip”	“2 Intra-Freq NR Cells, 4 time periods, No Fading”
Intra_Freq_LTM_cell_switch_RACHless	7.3.4.2	“38.533 7.3.4.2 TT.zip”	2 NR FR2 Intra-Freq Cells, 5 time periods, No Fading, 1 AoA in Rx peak and rough beam
Inter_Freq_LTM_cell_switch_RACHbased	7.3.4.3	“38.533 7.3.4.3 TT.zip”	2 NR FR2 Intra-Freq Cells, 4 time periods, No Fading, 1 AoA in Rx peak and rough beam
CSI-RS_RLM_Out_of_Sync_01	5.5.1.5 7.5.1.5 17.5.1.5	“38.533 5.5.1.5+7.5.1.5 TT.zip”	1 NR FR2 Cell (1 E-UTRA cell), 2 CSI-RSs, 3 time periods, 2AoA spherical coverage directions and rough beam, fading.
CSI-RS_RLM_InSync_01	5.5.1.6 7.5.1.6 17.5.1.6	“38.533 5.5.1.6+7.5.1.6 TT.zip”	1 NR FR2 Cell (1 E-UTRA cell), 2 CSI-RSs, 5 time periods, 2AoA in spherical coverage directions and rough beam, fading.
SSB_RLM_Out_of_Sync_02	5.5.1.10	“38.533 5.5.1.10 TT.zip”	1 NR FR2 Cell (1 E-UTRA cell), 3 time periods, 1AoA in Rx peak and rough beam, fading.
SSB_RLM_Out_of_Sync_03_multi-Rx	5.5.1.11 7.5.1.10	“38.533 5.5.1.11+7.5.1.10 TT.zip”	1 NR FR2 Cell (1 E-UTRA cell), 3 time periods, 2AoA in spherical coverage, fading.
Interruption_NR_SRS_Carrier-based_Switching	7.5.2.2	“38.533 7.5.2.2 TT.zip”	“2 NR cells, 2 time periods, No fading”
CSI-RS_WithNZP_L1-SINR-Meas	7.6.6.3	“38.533 7.6.6.3 TT.zip”	“1 NR Cell, one time period, No fading”
L1-RSRP_Accuracy_1	5.7.4.1 7.7.4.1 17.7.3.1	“38.533 5.7.4.1+7.7.4.1 TT.zip”	1 NR FR2 Cell, 2 SSBs, 2 subtests, 1 AoA in Rx peak and rough beam
L1-RSRP_Accuracy_2	5.7.4.2 7.7.4.2 17.7.3.2	“38.533 5.7.4.2+7.7.4.2 TT.zip”	1 NR FR2 Cell, 2 CSI-RS, 2 subtests, 1 AoA in Rx peak and rough beam
Inter_Freq_SSB-based_L1-RSRP_Accuracy	7.7.15.1	“38.533 7.7.15.1 TT.zip”	“1 NR serving cell and 1 NR inter-frequency cell, 2 subtests, 1 AoA in Rx peak and rough beam, no fading”
SSB_WithCSI-IM_L1-SINR-Meas	7.6.6.2 7.6.3.6	“38.533 7.6.6.2 TT.zip”	“1 NR Cell, 2 time periods, No fading”

L1-SINR_Accuracy_1	5.7.6.1 7.7.6.1	“38.533 5.7.6.1+7.7.6.1 TT.zip”	1 NR FR2 Cell, 2 CSI-RSs, 1 subtest, 1 AoA in Rx peak and rough beam
L1-SINR_Accuracy_2	5.7.6.2	“38.533 5.7.6.2 TT.zip”	1 NR FR2 Cell, 2 SSB and 2 CSI-RS, 1 subtests, 1 AoA in Rx peak and rough beam
L1-SINR_Accuracy_3	5.7.6.3	“38.533 5.7.6.3 TT.zip”	1 NR FR2 Cell, 2 CSI-RS and 2 CSI-IM, 1 subtests, 1 AoA in Rx peak and rough beam
L1-SINR_Accuracy_4	7.7.6.2	“38.533 7.7.6.2 TT.zip”	1 NR FR2 Cell, 2 SSB and 2 CSI-RS, 1 subtests, 1 AoA in Rx peak and rough beam
L1-SINR_Accuracy_5	7.7.6.3	“38.533 7.7.6.3 TT.zip”	1 NR FR2 Cell, 2 CSI-RS and 2 CSI-IM, 1 subtest, 1 AoA in Rx peak and rough beam
Inter_Reselection_not_at_cell_edge	7.1.1.6	“38.533 7.1.1.6 TT.zip”	“2 NR FR2 Cells, 2 SSBs, 2 time periods, 1 AoA in Rx peak and rough beam”
Intra_Reselection	7.1.1.1 17.1.1.1	“38.533 7.1.1.1 v2 TT.zip”	“2 NR FR2 Cells, 2 SSBs, 3 time periods, 1 AoA in Rx peak and rough beam”
Intra_Freq_Reselection_HST	7.1.1.7	“38.533 7.1.1.7 TT.zip”	“2 NR FR2 Cells, 2 SSBs, 3 time periods, 1 AoA in Rx peak and rough beam”
Inter_Reselection	7.1.1.2 17.1.1.2	“38.533 7.1.1.2 TT.zip”	“2 NR FR2 Cells, 2 SSBs, 3 time periods, 1 AoA in Rx peak and rough beam”
Inter_Reselection_HST	7.1.1.8	“38.533 7.1.1.8 TT.zip”	“2 NR FR2 Cells, 2 SSBs, 3 time periods, 1 AoA in Rx peak and rough beam”
RRC_Based_BWP_Switch	5.5.6.2.1 7.5.6.2.1 5.5.6.4.1	“38.533 5.5.6.2.1+7.5.6.2.1 TT.zip”	“1 NR Cell (1 E-UTRA Cell for NSA case), one time period, No fading”
RRC_Based_BWP_Switch_Multiple_CCs	5.5.6.5.1 7.5.6.5.1	“38.533 5.5.6.5.1+7.5.6.5.1 TT.zip”	“2 NR cells (1 E-UTRA cell for NSA case), one time period, No fading”
DCI_Based_BWP_Switch_on_Multiple_CCs	7.5.6.3.1 5.5.6.3.1	“38.533 5.5.6.3.1+7.5.6.3.1 TT.zip”	“2 NR Cells (1 E-UTRA Cell for NSA case), one time period, No fading”
TCI_State_Switch	7.5.8.1.1 7.5.8.2.1 17.5.4.1.1 17.5.4.2.1	“38.533 7.5.8.1.1+7.5.8.2.1 TT.zip”	1 NR FR2 Cell, 2 SSBs, 2 time periods, no fading, 2AoA in spherical coverage directions and rough beam
Intra_Freq_CLI_SRS-RSRP_Meas	5.6.4.1 7.6.4.1	“38.533 5.6.4.1+7.6.4.1 TT.zip”	Cell 1 and Neighbor Cell UE on f1, T1 and T2.
Intra_Freq_CLI_SRS-RSRP_Meas_Accu	5.7.5.1 7.7.5.1	“38.533 5.7.5.1+7.7.5.1 TT.zip”	Cell 1 and Neighbor Cell UE on f1, T1 and T2.

Inter_Freq_Idle_CADC_meas	7.6.23.3	“38.533 7.6.23.3 TT.zip”	“1 NR FR1 Cell, 1 NR FR2 Cell, 4 time periods, no fading”
InterRAT_LTE_Idle_CADC_meas	8.2.2.2	“38.533 8.2.2.2 TT.zip”	“1 E-UTRA Cell, 1 NR Cell, 3 time periods, no fading”
UE_Rx_Tx_difference_PDC_02	7.6.13.1 7.6.13.2	“38.533 7.6.13.1 TT.zip”	“1 NR FR2 Cell, 2 time periods, no fading”
Intra_Reselection_not_at_cell_edge	7.1.1.4	“38.533 7.1.1.4 TT.zip”	“2 NR FR2 Cells, 2 SSBs, 2 time periods, 1 AoA in Rx peak and rough beam”
Intra_Reselection_low_mobility	7.1.1.3 17.1.1.3	“38.533 7.1.1.3 TT.zip”	“2 NR FR2 Cells, 2 SSBs, 2 time periods, 1 AoA in Rx peak and rough beam”
RLM_Out_of_Sync_01	5.5.1.1 5.5.1.9 7.5.1.1 7.5.1.9 17.5.1.1 17.5.1.3 17.5.1.9	“38.533 5.5.1.1+5.5.1.9+7.5.1.1+7.5.1.9 TT.zip”	1 NR FR2 Cell (1 E-UTRA cell), 2 SSBs, 3 time periods, 2AoA spherical coverage directions and rough beam, fading.
RLM_Out_of_Sync_02	5.5.1.3 7.5.1.3	38.533 5.5.1.3+7.5.1.3 TT.zip	1 NR FR2 Cell (1 E-UTRA cell), 2 SSBs, 3 time periods, 1AoA in Rx beam peak and rough beam, fading.
RLM_InSync_01	5.5.1.2 7.5.1.2 17.5.1.2	38.533 5.5.1.2+7.5.1.2+17.5.1.2 TT_v2.zip	1 NR FR2 Cell (1 E-UTRA cell), 2 SSBs, 5 time periods, 2AoA in spherical coverage directions and rough beam, fading.
RLM_InSync_02	5.5.1.4 7.5.1.4 17.5.1.4	38.533 5.5.1.4+7.5.1.4+17.5.1.4 TT.zip	1 NR FR2 Cell (1 E-UTRA cell), 2 SSBs, 5 time periods, 1AoA in Rx beam peak direction and rough beam, fading.
RRC_reconfiguration_delay_01	7.5.11.1	“38.533 7.5.11.1 TT.zip”	“2 NR Cells, 3 Time Periods, No Fading”
MAC-CE_Based_Uplink_Spatial_Switch	5.5.9.1.1 7.5.9.1.1 17.5.5.1.1	“38.533 5.5.9.1.1+7.5.9.1.1 TT.zip”	“1 NR Cell, 2 time periods, no fading”
RRC_Based_Uplink_Spatial_Switch	5.5.9.2.1 7.5.9.2.1 17.5.5.2.1	“38.533 5.5.9.2.1+7.5.9.2.1 TT.zip”	“1 NR Cell, 2 time periods, no fading”
Unified_TCI_Switch_01	5.5.11.1 5.5.11.2 7.5.13.2	38.533 5.5.11.1 + 5.5.11.2 + 7.5.13.2 TT.zip	“1 NR Cell, 2 time periods, no fading”
Unified_TCI_Switch_02	5.5.11.3 7.5.13.1 7.5.13.3 7.5.13.4.1 7.5.13.5.1	38.533 5.5.11.3 + 7.5.13.1 + 7.5.13.3 TT.zip	“1 NR Cell, 2 time periods, no fading”
Unified_TCI_Switch_03	7.5.13.6.1	38.533 7.5.13.6.1 TT.zip	“1 NR Cell, 2 time periods, no fading”
Conditional_PSCell_Add	5.5.13.1 7.5.12.1	“38.533 5.5.13.1+7.5.12.1 TT.zip”	“1 NR FR2 Cell (1 E-UTRA Cell for NSA case), 4 time periods, No fading”
Conditional_PSCell_Add_02	6.5.12.1	“38.533 6.5.12.1 TT.zip”	“3 NR Cells for SA”, 3 time periods, no fading

Conditional_PSCell_Add_03	6.5.12.2	“38.533 6.5.12.2 TT.zip”	“3 NR Cells for SA”, 4 time periods, no fading
Conditional_PSCell_Add_04	7.5.18.1	“38.533 7.5.18.1 TT.zip”	“1 NR FR1 Cell, 2 intra-frequency NR FR2 Cells, 3 time periods, no fading”
Conditional_PSCell_Add_05	6.5.12.3	“38.533 6.5.12.3 TT.zip”	“2 Intra-Freq NR Cells, 3 time periods, No Fading”
Conditional_PSCell_Add_05	7.5.18.2	“38.533 7.5.18.2 TT.zip”	“1 NR FR1 Cell, 2 inter-frequency NR FR2 Cells, 4 time periods, no fading”
PSCell_activate	7.5.14	“38.533 7.5.14 TT.zip”	“1 NR FR1 Cell, 1 NR FR2 Cell, 4 time periods, no fading”
Intra_Freq_Meas_03	7.6.14.1	"38.533 7.6.14.1 TT.zip	2 NR FR2 Cells, 2 SSBs, 3 time periods, no fading, 2 AoAs, both are in EIS spherical coverage and rough beams
Intra_Freq_Meas_04	7.6.14.2	"38.533 7.6.14.2 TT.zip	2 NR FR2 Cells, 2 SSBs, 3 time periods, no fading, 2 AoAs, both are in EIS spherical coverage and rough beams
Inter_Freq_Meas_05	7.6.15.1 7.6.15.2 7.6.18.1	“38.533 7.6.15.1+7.6.15.2 TT.zip”	“3 Inter Frequency NR FR2 Cells, 2 time periods, No fading, 2 AoAs, both are in EIS spherical coverage and rough beams”
Inter_Freq_Meas_06	7.6.15.3	“38.533 7.6.15.3 TT.zip”	“3 Inter Frequency NR FR2 Cells with 2 carrier frequencies, 2 time periods, No fading, 1 AoA in Rx beam peak direction and rough beam”
Inter_Freq_Meas_07	7.6.16.2	“38.533 7.6.16.2 TT.zip”	“2 Inter Frequency NR Cells (both on FR2), 2 time periods, No fading”
Inter_Freq_Meas_08	7.6.16.3	“38.533 7.6.16.3 TT.zip”	“3 Inter Frequency NR Cells (2 frequencies in FR2), 2 time periods, No fading”
Inter_Freq_Meas_09	7.6.2.10 7.6.19.3	“38.533 7.6.2.10 TT.zip”	“2 Inter Frequency NR Cells (both on FR2), 2 time periods, Various number of sub-tests, No fading”

Inter_Freq_Meas_10	7.6.2.11	“38.533 7.6.2.11 TT.zip”	“2 Inter Frequency NR Cells (both on FR2), 2 time periods, Various number of sub-tests, No fading”
Inter_Freq_Meas_11	7.6.17.1	38.533 7.6.17.1 TT.zip	“2 Inter Frequency NR Cells (both on FR2), 2 time periods, Various number of sub-tests, No fading”
Inter_Freq_Meas_12	7.6.17.2	38.533 7.6.17.2 TT.zip	“2 Inter Frequency NR Cells (both on FR2), 2 time periods, Various number of sub-tests, No fading”
BWP_Switching_01	17.5.3.1.1 17.5.3.2.1	“38.533 17.5.3.1.1+17.5.3.2.1 TT.zip”	“1 NR Cell 3 time period, No fading”
CSI-RSRQ_01	5.7.8.1 7.7.8.1	“38.533 5.7.8.1+7.7.8.1 TT.zip”	“2 Intra-Frequency NR FR2 Cells, 2 sub-tests, No fading”
CSI-RSRQ_02	5.7.8.2 7.7.8.2	“38.533 5.7.8.2+7.7.8.2 TT.zip”	“2 Inter-Frequency NR FR2 Cells, 2 sub-tests, No fading”
CSI-SINR_01	5.7.9.1 7.7.9.1	“38.533 5.7.9.1+7.7.9.1 TT.zip”	“2 Intra-Frequency NR FR2 Cells, 2 sub-tests, No fading”
CSI-SINR_02	5.7.9.2 7.7.9.2	“38.533 5.7.9.2+7.7.9.2 TT.zip”	“2 Inter-Frequency NR FR2 Cells, 2 sub-tests, No fading”
PSCell_addition_removal_delay	5.5.7.1	“38.533 5.5.7.1 TT.zip”	“1NR FR2 Cell (1 E-UTRA Cell), No Fading”

Table 8-3: Grouping of FR1 NR sidelinl test cases defined in Clauses 9 of TS 38.533

Group	Test Case Numbers	.zip file name	Comments
SL_Timing_Accuracy_01	9.1.1.1	"38.533 9.1.1.1 TT.zip"	1 time period , no fading
SL_Timing_Accuracy_02	9.1.1.2	"38.533 9.1.1.2 TT.zip"	1 sidelink UE, 1 time period, no fading
SL_Timing_Accuracy_03	9.1.1.3	"38.533 9.1.1.3 TT.zip"	1 Cell, 1 time period, no fading
SL_SSB_Tx_01	9.1.2.1	“38.533 9.1.2.1 TT.zip”	1 Cell, 3 time periods, no fading”
SL_SSB_Tx_02	9.1.2.2	“38.533 9.1.2.2 TT.zip”	1 sidelink UE, 3 time periods, no fading”
SyncREF_Reselect_01	9.1.3.1	"38.533 9.1.3.1 TT.zip"	3 sidelink UEs, 3 time periods, no fading
SyncREF_Reselect_02	9.1.3.2	"38.533 9.1.3.2 TT.zip"	2 sidelink UEs, 3 time periods, no fading
SL-RSRP_01	9.1.4.1	"38.533 9.1.4.1 TT.zip"	50 sidelink UEs, 2 time periods, no fading
SL-RSRP_02	9.1.4.2	"38.533 9.1.4.2 TT.zip"	1 sidelink UE, 2 time periods, no fading”
SL-RSRP_03	9.1.4.3	"38.533 9.1.4.3 TT.zip"	130 sidelink UEs, 2 time periods, no fading”
SL-RSSI	9.1.5.1 9.1.5.2	“38.533 9.1.5.1+9.1.5.2 TT.zip”	4 sidelink UEs, 2 time periods, no fading”
WAN_Interruption	9.1.6.1	“38.533 9.1.6.1 TT.zip”	8 sidelink UEs, 3 time periods, no fading”
SL_Discovery_Interruption	9.1.6.3	“38.533 9.1.6.3 TT.zip”	8 sidelink UEs, 3 time periods, no fading”
SL_Relay_Selection/Reselection	9.1.7.1	“38.533 9.1.7.1 TT.zip”	3 sidelink UEs, 5 time periods, no fading”

Table 8-4: Grouping of FR1 NR shared spectrum test cases defined in Clauses 10, 11, 12 and 13 of TS 38.533

Group	Test Case Numbers	.zip file name	Comments
NR-U_EN-DC_HO_01	10.1.2	“38.533 10.1.2 TT.zip”	“2 intra-frequency E-UTRAN Cells, 2 intra-frequency NR Cells under CCA, 1 sub-test, no fading, 3 Time Periods,”
NR-U_RLM_Out_of_Sync_01	10.3.1.2 11.4.1.2	“38.533 10.3.1.2+11.4.1.2 TT.zip”	“1 NR Cell under CCA (1 E-UTRA Cell for NSA case), 1 sub-test, Fading, 3 Time Periods,”
NR-U_RLM_In_Sync_01	10.3.1.3 11.4.1.3	“38.533 10.3.1.3+11.4.1.3 TT.zip”	“1 NR Cell under CCA (1 E-UTRA Cell for NSA case), 1 sub-test, Fading, 5 Time Periods,”
NR-U_SCell_Activation_01	10.3.3.1 10.3.3.2 10.3.3.3 11.4.3.1 11.4.3.2 11.4.3.3 13.2.2.1 13.2.2.2 13.2.2.3	“38.533 10.3.3.1+10.3.3.2+10.3.3.3+11.4.3.1 TT.zip”	“2 Inter Frequency NR Cells under CCA, 3 time periods, Various number of sub-tests, No fading”
NR-U_SSB_Based_BFR_01	10.3.4.1 10.3.4.2 11.4.4.1 11.4.4.2	“38.533 10.3.4.1+10.3.4.2+11.4.4.1+11.4.4.2 TT.zip”	“1 NR Cell under CCA (1 E-UTRA Cell for NSA case), 1 sub-test, 5 time periods, Fading”
NR-U_BWP_Switch_01	10.3.5.1 11.4.5.1	"38.533 10.3.5.1+11.4.5.1 TT.zip"	"1 NR PCell (1 E-UTRAN Cell for NSA case), 2 time periods, no fading”
NR-U_BWP_Switch_02	10.3.5.2.1 10.3.5.2.2 11.4.5.2.1 11.4.5.2.2	“38.533 10.3.5.2.1+10.3.5.2.2+11.4.5.2.1+11.4.5.2.2 TT.zip"	"1 E-UTRAN Cell, 1 NR PCell, (1 NR SCell), 3 time periods, no fading”
NR-U_BWP_Switch_03	10.3.5.3.1 11.4.5.3.1	"38.533 10.3.5.3.1+11.4.5.3.1 TT.zip"	"1 NR PCell (1 E-UTRAN Cell for NSA case), 1 time period, no fading”
NR-U_Intra_SS-RSRQ_Acc_01	10.5.2.1 11.6.2.1 11.6.2.3 13.4.2.1	“38.533 10.5.2.1+11.6.2.1+11.6.2.3+13.4.2.1 TT.zip”	“2 Intra-Frequency NR Cells, periodic reporting, No fading”

NR-U_Inter_SS-SINR_Abs_Acc_01	10.5.3.2 11.6.3.2	“38.533 10.5.3.2+11.6.3.2 TT.zip”	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
NR-U_L1-RSRP_Abs_Acc_01	10.5.4.1 11.6.4.1 13.4.4.1	“38.533 10.5.4.1+11.6.4.1+13.4.4.1 TT.zip”	1 NR Cell, periodic L1-RSRP reporting, No fading
NR-U_RRC_Redirection_01	11.2.2.3.1 11.2.2.3.2	"38.533 11.2.2.3.1 + 11.2.2.3.2 TT.zip"	“2 Inter Frequency NR Cells, 2 time periods, No fading”
NR-U_PSCell_addition_01	10.3.6.1	"38.533 10.3.6.1 TT.zip"	"1 NR PCell, 1 E-UTRAN Cell, 5 time periods, no fading”
NR-U_Inter_Freq_Meas_01	10.4.2.3 10.4.2.4 10.4.2.5 10.4.2.6 11.5.2.3 11.5.2.4 11.5.2.5 11.5.2.6	“38.533 10.4.2.3+10.4.2.4+10.4.2.5+10.4.2.6 TT.zip"	“2 Inter Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading”
NR-U_Inter_Freq_Meas_02	10.4.2.7 10.4.2.8 10.4.2.9 10.4.2.10 11.5.2.7 11.5.2.8 11.5.2.9 11.5.2.10	“38.533 10.4.2.7+10.4.2.8+10.4.2.9+10.4.2.10 TT.zip"	“2 Inter Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading”
NR-U_Inter_Freq_Meas_03	13.3.2.3 13.3.2.4 13.3.2.5 13.3.2.6	“38.533 13.3.2.3+13.3.2.4+13.3.2.5+13.3.2.6 TT.zip"	“2 Inter Frequency NR Cells, 2 time periods, Various number of sub-tests, No fading”
NR-U_meas_intra-freq_01	10.4.1.1 10.4.1.4	"38.533 10.4.1.1+10.4.1.4 TT.zip"	"1 NR PCell (1 E-UTRAN Cell for NSA case), 2 time period, no fading”
NR-U_meas_intra-freq_02	11.5.1.1 11.5.1.2	38.533 11.5.1.1+11.5.1.2 TT.zip	"1 NR PCell, 2 time period, no fading”
NR-U_InterRAT_Meas_01	11.5.3.1 11.5.3.2	38.533 11.5.3.1+11.5.3.2 TT.zip	“1 E-UTRAN Cell, 1 NR Cell, 2 time periods
NR-U_meas_intra-freq_02	13.3.1.1 13.3.1.2 13.3.1.3 13.3.1.4	"38.533 13.3.1.1+13.3.1.2+13.3.1.3+13.3.1.4 TT.zip"	"1 licensed carrier NR Cell, 2 unlicensed carrier NR Cells, 2 time periods, no fading”

NR-U_Inter-RAT_Meas_01	10.4.4.1 10.4.4.2 10.4.4.3 10.4.4.4 12.4.2.1 12.4.2.2 12.4.2.3 12.4.2.4	“38.533 10.4.4.1+10.4.4.2+12.4.2.1+12.4.2.2 TT.zip"	“1 E-UTRA PCell, 1-2 NR Cell(s), 2 time periods, Various number of sub-tests, No fading”
NR-U_L1-RSRP_meas_01	10.4.3.1 10.4.3.2 10.4.3.3 10.4.3.4 11.5.4.1 11.5.4.2 11.5.4.3 11.5.4.4 13.3.3.1 13.3.3.2	"38.533 10.4.3.1+10.4.3.2+11.5.4.1+11.5.4.2 TT.zip"	"1 NR PCell (1 E-UTRAN Cell for NSA case), 2 time periods, no fading”
NR-U_Intra_SS-RSRP_Abs_Acc_01	10.5.1.1 11.6.1.1 13.4.1.1	“38.533 10.5.1.1+11.6.1.1+13.4.1.1 TT.zip”	“2 Intra-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading”
NR-U_Inter_SS-RSRP_Abs_Acc_01	10.5.1.2	“38.533 10.5.1.2 TT.zip”	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
NR-U_Inter_SS-RSRQ_Abs_Acc_01	10.5.2.2 11.6.2.2	“38.533 10.5.2.2+11.6.2.2 TT.zip”	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
NR-U_Inter_SS-RSRQ_Abs_Rel_Acc_01	11.6.2.4	“38.533 11.6.2.4 TT.zip”	2 Inter-Frequency NR Cells, periodic reporting, No fading”
NR-U_Inter_SS-SINR_Abs_Rel_Acc_01	11.6.3.4	“38.533 11.6.3.4 TT.zip”	“2 Inter-Frequency NR Cells, periodic reporting, No fading”
NR-U_Intra_SS-SINR_Acc_01	10.5.3.1 10.5.3.3 11.6.3.1 11.6.3.3 13.4.3.1	“38.533 10.5.3.1+10.5.3.3+11.6.3.1+11.6.3.3 TT.zip”	“2 Intra-Frequency NR Cells, periodic reporting, No fading”
NR-U_PRACH_01	10.1.1.1.1 10.1.1.1.2 11.2.2.2.1 11.2.2.2.2	“38.533 10.1.1.1.1+10.1.1.1.2+11.2.2.2.1+11.2.2.2.2 TT.zip”	“1 NR Cell under CCA (1 E-UTRA Cell for NSA case), PRACH measurements, no fading”

NR-U_PRACH_02	10.1.1.1.3 10.1.1.1.4 11.2.2.2.3 11.2.2.2.4	"38.533 10.1.1.1.3+10.1.1.1.4+11.2.2.2.3+11.2.2.2.4 TT.zip"	"1 NR Cell under CCA (1 E-UTRA Cell for NSA case), PRACH measurements, no fading"
NR-U_Intra_RSSI_Abs_Acc_01	10.5.5.1 10.5.5.2 11.6.5.1 11.6.5.2 13.4.5.1	"38.533 10.5.5.1+10.5.5.2+11.6.5.1+11.6.5.2 TT_v2.zip"	"1 NR Cell under CCA (1 E-UTRA Cell for NSA case), periodic reporting, no fading"
NR-U_Inter_RSSI _Abs_Acc_01	10.5.5.3 11.6.5.3 13.4.5.2	"38.533 10.5.5.3+11.6.5.3+13.4.5.2 TT.zip"	"2 Inter-Frequency NR Cell under CCA (1 E-UTRA Cell for NSA case), periodic reporting, no fading"
NR-U_Intra_SS-RSRP_Abs_Acc_02	11.6.1.2	"38.533 11.6.1.2 TT.zip"	"3 Intra-Frequency NR Cells, 3 Sub-tests, periodic reporting, No fading"
NR-U_Intra_channel_occupancy _Abs_Acc_01	10.5.6.1 10.5.6.2 11.6.6.1 11.6.6.2 13.4.6.1	"38.533 10.5.6.1+10.5.6.2+11.6.6.1+11.6.6.2 TT_v2.zip"	"1 NR Cell under CCA (1 E-UTRA Cell for NSA case), periodic reporting, no fading"
NR-U_Inter_channel_occupancy _Abs_Acc_01	10.5.6.3 11.6.6.3 13.4.6.2	"38.533 10.5.6.3+11.6.6.3+13.4.6.2 TT.zip"	"2 NR Cell under CCA (1 E-UTRA Cell for NSA case), periodic reporting, no fading"
NR-U_Intra_Reselection_01	11.1.1.1	"38.533 11.1.1.1 TT.zip"	"2 Intra Frequency NR Cells under CCA, 3 time periods, No fading"
NR-U_Inter_Reselection_01	11.1.1.2	"38.533 11.1.1.2 TT.zip"	"2 Inter Frequency NR Cells under CCA, 3 time periods, No fading"
NR-U_Inter_Reselection_02	11.1.2.1	"38.533 11.1.2.1 TT.zip"	"2 Inter Frequency NR Cells with source cell under CCA, 3 time periods, No fading"

NR-U_Inter_Reselection_03	11.1.3.1	“38.533 11.1.3.1 TT.zip”	“2 Inter Frequency NR Cells with target cell under CCA, 3 time periods, No fading”
NR-U_InterRAT_Higher_Reselection_01	11.1.4.1	“38.533 11.1.4.1 TT.zip”	“1 E-UTRAN Cell, 1 NR Cell under CCA, 3 time periods, No fading”
NR-U_InterRAT_lower_Reselection_01	11.1.4.2	“38.533 11.1.4.2 TT.zip”	“1 E-UTRAN Cell, 1 NR Cell under CCA, 3 time periods, No fading”
NR-U_Intra_Freq_HO_Known_Target_01	11.2.1.1	“38.533 11.2.1.1 TT.zip”	“2 Intra-Freq NR Cells under CCA, 3 Time Periods, No Fading”
NR-U_Intra_Freq_HO_Unknown_Target_01	11.2.1.2	“38.533 11.2.1.2 TT.zip”	“2 Intra-Freq NR Cells under CCA, 2 Time Periods, No Fading”
NR-U_Inter_Freq_HO_01	11.2.1.3	“38.533 11.2.1.3 TT.zip”	“2 Inter-Freq NR Cells under CCA, 2 Time Periods, No Fading”
NR-U_Inter_Freq_HO_known_01	11.2.1.4	“38.533 11.2.1.4 TT.zip”	“2 Inter-Freq NR Cells with source under CCA, 3 Time Periods, No Fading”
NR-U_Inter_Freq_HO_02	11.2.1.5	“38.533 11.2.1.5 TT.zip”	“2 Inter-Freq NR Cells with source cell under CCA, 2 Time Periods, No Fading”
NR-U_Inter_Freq_HO_03	11.2.1.6	“38.533 11.2.1.6 TT.zip”	“2 Inter-Freq NR Cells with target cell under CCA, 2 Time Periods, No Fading”
NR-U_InterRAT_Known _Handover_01	11.2.1.7	“38.533 11.2.1.7 TT.zip”	“1 E-UTRAN Cell, 1 NR Cell under CCA, 3 time periods, No fading”
NR-U_InterRAT_Unknown _Handover_01	11.2.1.8	“38.533 11.2.1.8 TT.zip”	“1 E-UTRAN Cell, 1 NR Cell under CCA, 3 time periods, No fading”

NR-U_Intra_RRC_re-establishment_01	11.2.2.1.1	“38.533 11.2.2.1.1 TT.zip”	“2 Intra Frequency NR Cells under CCA, 3 time periods, No fading”
NR-U_Inter_RRC_re-establishment_01	11.2.2.1.2	“38.533 11.2.2.1.2 TT.zip”	“2 Inter Frequency NR Cells under CCA, 3 time periods, No fading”
NR-U_Intra_RRC_re-establishment_without_timing_01	11.2.2.1.3	“38.533 11.2.2.1.3 TT.zip”	“2 Intra Frequency NR Cells under CCA, 3 time periods, No fading”
NR-U_Inter_RRC_re-establishment_02	11.2.2.1.4	“38.533 11.2.2.1.4 TT.zip”	“2 Inter Frequency NR Cells with target cell under CCA, 3 time periods, No fading”
NR-U_InterRAT_re-selection_LTE_Serving	12.1.1.1	“38.533 12.1.1.1 TT.zip”	“1 NR Cell under CCA, 1 LTE serving cell, 3 time periods No fading”
NR-U_InterRAT_HO_LTE_Serving	12.2.1.1	“38.533 12.2.1.1 TT.zip”	“1 NR Cell under CCA, 1 LTE serving cell, 3 time periods No fading”
NR-U_InterRAT_SFTD_meas	12.4.1.1	“38.533 12.4.1.1 TT.zip”	“1 NR Cell under CCA, 1 LTE serving cell, 1 time period No fading”
NR-U_InterRAT_SFTD_meas_accuracy	12.5.1.1	“38.533 12.5.1.1 TT.zip”	“1 NR Cell under CCA, 1 LTE serving cell, 1 time period No fading”

Table 8-5: Grouping of FR1 NR Satellite Access test cases defined in clause 14 of TS 38.533

Group	Test Case Numbers	.zip file name	Comments
NTN_Handover_intra	14.2.1.1 14.2.1.3 14.2.1.5 14.2.3	“38.533 14.2.1.1+14.2.1.3+14.2.1.5 TT.zip”	“2 intra-frequency NR-NTN Cells, 1 sub-test, no fading, 2-3 Time Periods”
NTN_Handover_inter	14.2.1.2 14.2.1.4 14.2.1.6 14.2.4	“38.533 14.2.1.2+14.2.1.4+14.2.1.6 TT.zip”	“2 inter-frequency NR-NTN Cells, 1 sub-test, no fading, 2-3 Time Periods”
NTN_re-establishment_01	14.2.2.1.1	“38.533 14.2.2.1.1 TT.zip”	“2 intra-frequency NR-NTN Cells, 1 sub-test, no fading, 3 Time Periods”
NTN_re-establishment_02	14.2.2.1.2	“38.533 14.2.2.1.2 TT.zip”	“2 inter-frequency NR-NTN Cells, 1 sub-test, no fading, 3 Time Periods”
NTN_redirection	14.2.2.3.1	“38.533 14.2.2.3.1 TT.zip”	“2 Inter Frequency NR Cells, 2 time periods, No fading”
NTN_transmit_timing	14.3.1.1	“38.533 14.3.1.1 TT.zip”	“1 NR-NTN Cell, 2 sub-tests, no fading, 1 Time Period”
NTN_timing_advance	14.3.2.1	“38.533 14.3.2.1 TT.zip”	“1 NR-NTN Cell, 1 sub-test, no fading, 1 Time Period”
NTN_RLM_OOS	14.4.1.1 14.4.1.3 14.4.1.5 14.4.1.7	“38.533 14.4.1.1+14.4.1.3+14.4.1.5+14.4.1.7 TT.zip”	“1 NR-NTN Cell, 1 sub-test, fading, 3 Time Periods”
NTN_RLM_IS	14.4.1.2 14.4.1.4 14.4.1.6 14.4.1.8	“38.533 14.4.1.2+14.4.1.4+14.4.1.6+14.4.1.8 TT.zip”	“1 NR-NTN Cell, 1 sub-test, fading, 5 Time Periods”
NTN_BWP_Switch_01	14.4.3.1.1	“38.533 14.4.3.1.1 TT.zip”	“1 NR-NTN Cell, 1 sub-test, no fading, 3 Time Periods”
NTN_BWP_Switch_02	14.4.3.2.1	“38.533 14.4.3.2.1 TT.zip”	“1 NR-NTN Cell, 1 sub-test, no fading, 1 Time Period”
NTN_CBW_change	14.4.4.1	“38.533 14.4.4.1 TT.zip”	“1 NR-NTN Cell, 1 sub-test, no fading, 1 Time Period”
NTN_pathloss_RS_switch	14.4.5.1	“38.533 14.4.5.1 TT.zip”	“1 NR-NTN Cell, 1 sub-test, no fading, 3 Time Periods”
NTN_meas_intra	14.5.1.1 14.5.1.2 14.5.1.3 14.5.1.4 14.5.1.5 14.5.1.6	“38.533 14.5.1.1+14.5.1.2+14.5.1.3+14.5.1.4 TT.zip”	“2 intra-frequency NR-NTN Cells, 1 sub-test, no fading, 2 Time Periods”
NTN_meas_inter_01	14.5.2.1 14.5.2.2 14.5.2.3	“38.533 14.5.2.1+14.5.2.2+14.5.2.3 TT.zip”	“2 inter-frequency NR-NTN Cells, 1 sub-test, no fading, 2 Time Periods”
NTN_meas_inter_02	14.5.2.4 14.5.2.6	“38.533 14.5.2.4+14.5.2.6 TT.zip”	“2 inter-frequency NR-NTN Cells, 1 sub-test, no fading, 2 Time Periods”
NTN_meas_inter_03	14.5.2.7 14.5.2.8	“38.533 14.5.2.7+14.5.2.8 TT.zip”	“2 inter-frequency NR-NTN Cells, 1 sub-test, no fading, 2 Time Periods”

NTN_SSB_Based_BFR	14.4.2.1 14.4.2.2	“38.533 14.4.2.1+14.4.2.2 TT.zip”	“1 NR-NTN Cells, no fading, 5 Time Periods”
NTN_CSI-RS_Based_BFR	14.4.2.3 14.4.2.4	“38.533 14.4.2.3+14.4.2.4 TT.zip”	“1 NR-NTN Cells, no fading, 5 Time Periods”
NTN_Intra_SS-RSRP_Acc	14.6.1.1	“38.533 14.6.1.1 TT v2.zip”	“2 Intra-Frequency NR-NTN Cells, 3 Sub-tests, periodic reporting, No fading”
NTN_Inter_SS-RSRP_Acc	14.6.1.2	“38.533 14.6.1.2 TT v2.zip”	“2 Inter-Frequency NR-NTN Cells, 2 Sub-tests, periodic reporting, No fading”
NTN_Intra_SS-RSRQ_Acc	14.6.2.1	“38.533 14.6.2.1 TT v2.zip”	“2 Intra-Frequency NR-NTN Cells, 3 Sub-tests, periodic reporting, No fading”
NTN_Inter_SS-RSRQ_Acc	14.6.2.2	“38.533 14.6.2.2 TT v2.zip”	“2 Inter-Frequency NR-NTN Cells, 3 Sub-tests, periodic reporting, No fading”
NTN_Intra_SS-SINR_Acc	14.6.3.1	“38.533 14.6.3.1 TT_v2.zip”	“2 Intra-Frequency NR-NTN Cells, periodic reporting, No fading”
NTN_Inter_SS-SINR_Abs_Rel_Acc	14.6.3.2	“38.533 14.6.3.2 TT_v2.zip”	“2 Inter-Frequency NR-NTN Cells, periodic reporting, No fading”
NTN_Inter_Reselection_Low_mobility	14.1.9	38.533 14.1.9 TT	“2 Inter Frequency NR-NTN Cells, 2 time periods, No fading”
NTN_Inter_Reselection_Not_cell_edge	14.1.10	“38.533 14.1.10 TT.zip”	“2 Inter Frequency NR-NTN Cells, 2 time periods, No fading”
NTN_Intra_Reselection_01	14.1.1 14.1.2	38.533 14.1.1+14.1.2 TT	“2 Intra Frequency NR NTN Cells, 3 time periods, No fading”
NTN_Intra_Reselection_02	14.1.3 14.1.4	38.533 14.1.3+14.1.4 TT	“2 Intra Frequency NR NTN Cells, 2 time periods, No fading”
NTN_Inter_Reselection_01	14.1.5	38.533 14.1.5 TT	“2 Inter Frequency NR NTN Cells, 3 time periods, No fading”
NTN_Inter_Reselection_02	14.1.6	38.533 14.1.6 TT	“2 Inter Frequency NR NTN Cells, 3 time periods, No fading”
NTN_Inter_Reselection_03	14.1.7 14.1.8	38.533 14.1.7+14.1.8 TT	“2 Inter Frequency NR NTN Cells, 2 time periods, No fading”
NTN_TN_InterRAT_Higher_Reselection	14.1.11	38.533 14.1.11 TT	“1 E-UTRAN TN Cell, 1 NR NTN Cell, 2 time periods, No fading”

NTN_TN_Inter_Higher_Reselection	14.1.12	38.533 14.1.12 TT	“1 NR TN Cell, 1 NR NTN Cell, 2 time periods, No fading”
PRACH	14.2.2.2.1 14.2.2.2.2	38.533 14.2.2.2.1+14.2.2.2.2 TT	“1 NR-NTN Cell, PRACH measurements, no fading”
NTN_SSB_Based_L1-RSRP-Meas	14.5.3.1 14.5.3.2	“38.533 14.5.3.1+14.5.3.2 TT.zip”	“1 NR NTN Cell, 2 time periods, No fading”
NTN_RACH-less_Handover_intra	14.2.1.8	“38.533 14.2.1.8 TT.zip”	“2 intra-frequency NR-NTN Cells, 1 sub-test, no fading, 3 Time Periods”
NTN_Hard_Satellite_switch_intra	14.2.2.4	“38.533 14.2.2.4 TT.zip”	“2 intra-frequency NR-NTN Cells, 1 sub-test, no fading, 2 Time Periods”
NTN_Soft_Satellite_switch_intra	14.2.2.5	“38.533 14.2.2.5 TT.zip”	“2 intra-frequency NR-NTN Cells, 1 sub-test, no fading, 3 Time Periods”
NTN_CSI-RS_Based_L1-RSRP-Meas	14.5.3.3 14.5.3.4	“38.533 14.5.3.3+14.5.3.4 TT.zip”	“1 NR NTN Cell, 1 time periods, No fading”
NTN_L1-RSRP_Abs_Rel_Acc	14.6.4.1 14.6.4.2	“38.533 14.6.4.1_14.6.4.2 TT.zip”	1 NR-NTN Cell, periodic L1-RSRP reporting, No fading

9 Grouping of test cases defined in TS 37.571-1

Table 9-1: Grouping of positioning test cases defined in TS 37.571-1

Group	Test Case Numbers	.zip file name	Comments
RSTD_reporting_1	14.2.1	“37.571-1 14.2.1 TT v3.zip”	3cells, RSTD reporting delay Single positioning frequency layer FR1
RSTD_Accuracy_1	14.3.1	“37.571-1 14.3.1 TT v2”	RSTD accuracy Single positioning frequency layer FR1
RSTD_reporting_2	14.2.2	“37.571-1 14.2.2 TT v3.zip”	3 cells, 2 PFLs, reporting delay, FR1
RSTD_accuracy_2	14.3.2	“37.571-1 14.3.2 TT v3.zip”	3 cells, 2 PFLs, RSTD accuracy, FR1
RSTD_accuracy_3	14.3.3 14.3.8 14.5.3	“37.571-1 14.3.3+14.3.8+14.5.3 TT.zip”	RSTD accuracy Single positioning frequency layer FR2
RSTD_accuracy_4	14.3.4	“37.571-1 14.3.4 TT v2.zip”	RSTD accuracy Dual positioning frequency layer FR2
RSTD_reporting_3	14.2.3 14.2.10 14.4.3	“37.571-1 14.2.3+14.2.10+14.4.3 TT.zip”	3 cells, RSTD reporting delay Single positioning frequency layer FR2
RSTD_reporting_4	14.2.4	“37.571-1 14.2.4 TT v2.zip”	3 cells, RSTD reporting delay Dual positioning frequency layer FR2
PRP_reporting_1	16.2.3 16.2.7 16.2.8 16.4.3 16.4.4	“37.571-1 16.2.3+16.2.7+16.2.8+16.4.3+16.4.4 TT.zip”	PRP reporting delay, Single positioning frequency layer FR2
PRP_reporting_2	16.2.4	“37.571-1 16.2.4 TT v2.zip”	PRP reporting delay, Dual positioning frequency layer FR2
PRP_reporting_3	16.2.1	“37.571-1 16.2.1 TT v2.zip”	PRP reporting delay, Single positioning frequency layer FR1
PRP_reporting_4	16.2.2	“37.571-1 16.2.2 TT v2.zip”	PRP reporting delay,
PRP_reporting_5	16.2.5	“37.571-1 16.2.5 TT.zip”	PRP reporting delay, Single positioning frequency layer, reduced number of samples FR1
PRP_reporting_6	16.2.6	“37.571-1 16.2.6 TT.zip”	PRP reporting delay, Single positioning frequency layer FR1
PRP_reporting_7	16.4.1	“37.571-1 16.4.1 TT.zip”	PRP reporting delay, Single positioning frequency layer FR1
PRP_reporting_8	16.4.2	“37.571-1 16.4.2 TT.zip”	PRP reporting delay, reduced number of samples, Single positioning frequency layer FR1

PRP_accuracy_1	16.3.1	“37.571-1 16.3.1 TT v3.zip”	PRP reporting accuracy, Single positioning frequency layer FR1
PRP_accuracy_2	16.3.2 16.5.3	“37.571-1 16.3.2+16.5.3 TT.zip”	PRP accuracy, Single positioning frequency layer FR2
PRP_accuracy_3	16.3.4	“37.571-1 16.3.4 TT v2.zip”	PRP accuracy, reduce number of samples Single positioning frequency layer FR2
PRP_accuracy_4	16.5.4	“37.571-1 16.5.4 TT.zip”	PRP accuracy, reduce number of samples Single positioning frequency layer FR2
PRP_accuracy_5	16.3.3	“37.571-1 16.3.3 TT.zip”	PRP accuracy, reduce number of samples FR1
PRP_accuracy_6	16.5.1	“37.571-1 16.5.1 TT.zip”	PRP accuracy Single positioning frequency layer FR1
PRP_accuracy_7	16.5.2	“37.571-1 16.5.2 TT.zip”	PRP accuracy, reduce number of samples Single positioning frequency layer FR1
UE_RxTxTimeDiff_reporting_1	15.2.1 15.4.1	“37.571-1 15.2.1+15.4.1 TT v2.zip”	UE Rx-Tx time difference reporting delay, Single positioning frequency layer FR1
UE_RxTxTimeDiff_reporting_2	15.2.2	“37.571-1 15.2.2 TT v3.zip”	UE Rx-Tx time difference reporting delay, Dual positioning frequency layer FR1
UE_RxTxTimeDiff_reporting_3	15.2.3 15.4.3	“37.571-1 15.2.3+15.4.3 TT.zip”	UE Rx-Tx time difference reporting delay, Single positioning frequency layer FR2
UE_RxTxTimeDiff_reporting_4	15.2.4	“37.571-1 15.2.4 TT v2.zip”	UE Rx-Tx time difference reporting delay, Dual positioning frequency layer FR2
UE_RxTxTimeDiff_reporting_5	15.2.5	“37.571-1 15.2.5 TT.zip”	UE Rx-Tx time difference reporting delay, reduce number of samples, Single positioning frequency layer FR1

UE_RxTxTimeDiff_reporting_6	15.2.8,15.2.9, 15.2.10, 15.4.4	“37.571-1 15.2.8+15.2.9+15.2.10+15.4.4 TT.zip”	UE Rx-Tx time difference reporting delay, reduce number of samples, Single positioning frequency layer FR2
UE_RxTxTimeDiff_reporting_7	15.4.2	“37.571-1 15.4.2 TT.zip”	UE Rx-Tx time difference reporting delay, reduce number of samples, Single positioning frequency layer FR1
UE_RxTxTimeDiff_reporting_8	15.2.6	“37.571-1 15.2.6 TT.zip”	UE Rx-Tx time difference reporting delay, Single positioning frequency layer FR1
UE_RxTxTimeDiff_reporting_9	15.2.7	“37.571-1 15.2.7 TT.zip”	UE Rx-Tx time difference reporting delay, Single positioning frequency layer with Rx TEG FR1
UE_RxTxTimeDiff_reporting_10	15.2.11 15.4.5	“37.571-1 15.2.11+15.4.5 TT.zip”	UE Rx-Tx time difference reporting delay, Dual positioning frequency layer with PRS aggregation, FR1
UE_RxTxTimeDiff_reporting_11	15.2.12 15.4.6	“37.571-1 15.2.12+15.4.6 TT.zip”	UE Rx-Tx time difference reporting delay, Dual positioning frequency layer with PRS aggregation, FR2
UE_RxTxTimeDiff_reporting_12	15.2.14 15.2.16 15.4.8	“37.571-1 15.2.14+15.2.16+15.4.8 TT.zip”	UE Rx-Tx time difference reporting delay, Singlel positioning frequency layer Redcap UE In FR2
UE_RxTxTimeDiff_reporting_13	15.2.13 15.4.7	“37.571-1 15.2.3+15.4.7 TT.zip”	UE Rx-Tx time difference reporting delay, Single positioning frequency layer Redcap UE without Rx FH
UE_RxTxTimeDiff_accuracy_1	15.3.1	“37.571-1 15.3.1 TT v2.zip”	UE Rx-Tx time difference accuracy, Single positioning frequency layer FR1
UE_RxTxTimeDiff_accuracy_2	15.3.2 15.5.3	“37.571-1 15.3.2 TT v2.zip”	UE Rx-Tx time difference accuracy, Single positioning frequency layer FR2

UE_RxTxTimeDiff_accuracy_3	15.3.5 15.5.4	“37.571-1 15.3.5 TT v2.zip”	UE Rx-Tx time difference accuracy, reduce number of samples Single positioning frequency layer FR2
UE_RxTxTimeDiff_accuracy_4	15.3.6	“37.571-1 15.3.6 TT v2.zip”	UE Rx-Tx time difference accuracy, Same RxTx TEG Single positioning frequency layer FR2
UE_RxTxTimeDiff_accuracy_5	15.3.3	“37.571-1 15.3.3 TT.zip”	UE Rx-Tx time difference accuracy, reduce number of samples Single positioning frequency layer FR1
UE_RxTxTimeDiff_accuracy_6	15.3.4	“37.571-1 15.3.4 TT.zip”	UE Rx-Tx time difference accuracy, Single positioning frequency layer with Rx TEG FR1
UE_RxTxTimeDiff_accuracy_7	15.5.1	“37.571-1 15.5.1 TT.zip”	UE Rx-Tx time difference accuracy, reduce number of samples Single positioning frequency layer FR1
UE_RxTxTimeDiff_accuracy_8	15.5.2	“37.571-1 15.5.2 TT.zip”	UE Rx-Tx time difference accuracy, reduce number of samples Single positioning frequency layer FR1
UE_RxTxTimeDiff_accuracy_9	15.3.7	“37.571-1 15.3.7 TT.zip”	UE Rx-Tx time difference accuracy, Dual positioning frequency layer with PRS aggregation, FR1
UE_RxTxTimeDiff_accuracy_10	15.3.8	“37.571-1 15.3.8 TT.zip”	UE Rx-Tx time difference accuracy, Dual positioning frequency layer with PRS aggregation, FR2
UE_RxTxTimeDiff_accuracy_11	15.3.9 15.5.7	“37.571-1 15.3.9+15.5.7 TT.zip”	UE Rx-Tx time difference accuracy, Single PFL, Redcap UE in FR1
UE_RxTxTimeDiff_accuracy_12	15.3.10 15.3.12 15.5.8 15.5.10	“37.571-1 15.3.10+15.3.12+15.5.8+15.5.10 TT.zip”	UE Rx-Tx time difference accuracy, Single PFL, Redcap UE in FR2
RSTD_reporting_5	14.2.8 14.2.9 14.4.4	“37.571-1 14.2.8+14.2.9+14.4.4 TT.zip”	3 cells, RSTD reporting delay, reduce number of samples, Single positioning frequency layer FR2

RSTD_reporting_6	14.2.5	“37.571-1 14.2.5 TT.zip”	3 cells, RSTD reporting delay, reduce number of samples, Single positioning frequency layer FR1
RSTD_reporting_7	14.2.6	“37.571-1 14.2.6 TT.zip”	3cells, RSTD reporting delay Single positioning frequency layer FR1
RSTD_reporting_8	14.2.7	“37.571-1 14.2.7 TT v2.zip.zip”	3 cells, RSTD reporting delay Single positioning frequency layer with Rx TEG FR1
RSTD_reporting_9	14.4.1	“37.571-1 14.4.1 TT.zip	3 cells, RSTD reporting delay Single positioning frequency layer FR1
RSTD_reporting_10	14.4.2	“37.571-1 14.4.2 TT.zip	3 cells, RSTD reporting delay, reduce number of samples, Single positioning frequency layer FR1
RSTD_reporting_11	14.2.11	“37.571-1 14.2.11 TT.zip	3 cells, RSTD reporting delay, dual positioning frequency layers, PRS aggregation, FR1
RSTD_accuracy_5	14.3.7 14.5.4	“37.571-1 14.3.7+14.5.4 TT.zip”	2 cells, RSTD accuracy, reduce number of samples, Single positioning frequency layer FR2
RSTD_accuracy_6	14.3.5	“37.571-1 14.3.5 TT.zip”	2 cells, RSTD accuracy, reduced number of samples, Single positioning frequency layer FR1
RSTD_accuracy_7	14.3.6	“37.571-1 14.3.6 TT.zip”	2 cells, RSTD accuracy, Single positioning frequency layer with Rx TEG FR1
RSTD_accuracy_8	14.5.1	“37.571-1 14.5.1 TT.zip”	2 cells, RSTD accuracy, Single positioning frequency layer FR1
RSTD_accuracy_9	14.5.2	“37.571-1 14.5.2 TT.zip”	2 cells, RSTD accuracy, reduced number of samples, Single positioning frequency layer FR1

RSTD_accuracy_10	14.3.9	“37.571-1 14.3.9 TT.zip	3 cells, RSTD accuracy, dual positioning frequency layers, PRS aggregation, FR1
PRS_RSRPP_reporting_1	17.2.1 17.2.2 17.2.3 17.4.1 17.4.2	“37.571-1 17.2.1+17.2.2+17.2.3+17.4.1+17.4.2 TT.zip”	2 cells, PRS-RSRPP reporting delay, Single positioning frequency layer FR1
PRS_RSRPP_reporting_2	17.2.4 17.2.5 17.2.6 17.4.3 17.4.4	“37.571-1 17.2.4+17.2.5+17.2.6+17.4.3+17.4.4 TT.zip”	2 cells, PRS-RSRPP reporting delay, Single positioning frequency layer FR2
PRS_RSRPP_accuracy_1	17.3.1 17.5.1	“37.571-1 17.3.1+17.5.1 TT.zip”	2 cells, PRS-RSRPP accuracy test cases, Single positioning frequency layer FR1
PRS_RSRPP_accuracy_2	17.3.2 17.5.2	“37.571-1 17.3.2+17.5.2 TT.zip”	2 cells, PRS-RSRPP accuracy test cases with reduce number of samples, Single positioning frequency layer FR1
PRS_RSRPP_accuracy_3	17.3.3 17.5.3	“37.571-1 17.3.3+17.5.3 TT.zip”	2 cells, PRS-RSRPP accuracy test cases, Single positioning frequency layer FR2
PRS_RSRPP_accuracy_4	17.3.4 17.5.4	“37.571-1 17.3.4+17.5.4 TT.zip”	2 cells, PRS-RSRPP accuracy test cases, reduce number of samples, Single positioning frequency layer FR2

Annex A: Derivation documents for test tolerance

The documents (and spreadsheets where applicable) used to derive the test tolerances for each test case are included in the present document as zip files.

The aim is to provide a reference to completed test cases, so that test tolerances for similar test cases can be derived on a common basis. The information on test case grouping in clauses 7 and 8 can be used to identify similarities.

A.1 Void

A.2 Handling of common Test Tolerance topics for radiated test cases defined in TS 38.533

The basic principles of Test Tolerance analysis are the same for conducted testing and radiated testing, but for radiated testing additional topics are taken into account. This annex contains methods to handle common additional topics, to allow re-use and to avoid the need for each test case analysis to repeat the same detail.

Individual test case analyses are expected to follow the methods contained here where applicable, and to refer to relevant clauses in this Annex.

A.2.1 Angles of Arrival

A.2.1.1 Relevant core requirements

In FR2, the performance of the UE depends on the downlink signal angle of arrival, and is characterised by two parameters:

- Refsens: lowest signal level for a given demodulation performance in the UE Rx beam peak direction, specified in TS 38.101-2 [16] clause 7.3.2 according to UE Power class, Channel bandwidth and operating band
- EIS spherical coverage: lowest signal level for a given demodulation performance in a specified percentile of other directions, specified in TS 38.101-2 [16] clause 7.3.4 according to UE Power class, Channel bandwidth and operating band

As both of these requirements are defined in the context of a throughput requirement, the UE is assumed to be using fine beams. Note that for directions outside the specified percentile of spherical coverage directions, there are no requirements. Testing must therefore be carried out within the spherical coverage directions. For testing, direction is 3-dimensional, but the principle can be illustrated in a 2-dimensional diagram:




Figure A.2.1.1-1: UE Rx Beam-peak and spherical coverage directions, Fine beams

A.2.1.2 Modelling of variation within spherical coverage directions

Within the spherical coverage directions, a signal may be anywhere from near Rx Beam Peak (high gain direction, close to Refsens) to the worst of the allowed percentile (low gain direction, close to EIS spherical coverage requirement value). This is modelled by taking the midpoint of the Spherical coverage range as the nominal value, and then adding a variation of ±(half the difference between Refsens and Spherical coverage).

UE Spherical coverage gain midpoint in dB is derived as (UE Refsens - UE Spherical coverage)/2

Figure A.2.1.2-1 shows an example for UE Power class 3, Channel bandwidth 100MHz and operating band n257. In this example the UE Spherical coverage gain midpoint would be -5.45dB, as the gain is lower than in the Rx Beam peak direction. Variation about the midpoint is handled as a UE uncertainty.




Figure A.2.1.2-1: Example modelling of variation within spherical coverage directions, Fine beams

A.2.1.3 Principles for Test Tolerance analysis

The following principles shall be followed in the test case analysis:

- The Angle of Arrival for each downlink signal shall be defined: either from UE Rx beam peak direction or from a direction within the EIS spherical coverage
- Variations over the EIS spherical coverage directions shall be included, using the method shown in A.2.1.2.

Variations over the EIS spherical coverage directions do not directly affect signals applied to the UE, but they do affect the SS-RSRP level measured by the UE, and the Es/Iot at UE baseband. Where the test case has requirements on UE baseband Es/Iot_{BB}, UE internal noise calculation is given in clause A.2.3, and calculation of Es/Iot at UE baseband is given in clauses A.2.4 and A.2.7.

A.2.2 UE Fine beams and Rough beams

A.2.2.1 Relevant core requirements

UE requirements such as Refsens in TS 38.101-2 [16], assume that the UE is using a fine beam which has higher antenna gain to give good demodulation performance. However, in some RRM scenarios where the UE is for example searching for or measuring other cells, the UE uses rough beams which have lower antenna gain. The difference in gain is specified depending on the Angle of Arrival:

- The Gain difference Y between fine and rough beams in the UE Rx beam peak direction is specified in TS 38.133 [17] Table B.2.1.3.1-1 according to UE Power class

- The Gain difference Z between fine and rough beams in the UE Spherical coverage directions is specified in TS 38.133 [17] Table B.2.1.3.2-1 according to UE Power class

The Gain differences Y and Z are not dependent on Channel bandwidth or operating band. The concept is illustrated in Figures A.2.2.1-1 and A.2.2.1-2.




Figure A.2.2.1-1: Fine and rough beams, Rx Beam peak direction




Figure A.2.2.1-2: Fine and rough beams, spherical coverage directions

When the Rx Beam Peak is selected and defined based on Fine Beams, the rough beam gain in that direction may be lower than the largest rough beam gain in another direction within Spherical Coverage. The term “D” is the maximum allowed rough beam gain reduction and is specified in TS 38.133 [17] Table B.2.1.5.3-1 for each power class. D parameter is applicable only to RSRP relative accuracy test cases.




Figure A.2.2.1-3: Fine and rough beams alignment, Rx Beam peak direction

A.2.2.2 Modelling of Fine beams and Rough beams

Where the UE is assumed to use fine beams, the scenario is already covered in the Refsens and EIS spherical coverage requirements, and no further modifications are needed.

Where the UE is assumed to use rough beams, the effect is modelled as a reduction in gain of YdB or ZdB, according to the Angle of Arrival of each downlink signal. The reduction in gain translates to a higher UE internal noise seen at the Reference point where the downlink signals are applied. UE noise calculated from Refsens or from EIS spherical coverage requirements is increased by YdB or ZdB respectively. UE internal noise calculation is given in clause A.2.3.

A.2.2.3 Principles for Test Tolerance analysis

The following principles shall be followed in the test case analysis:

- The Type of beam assumed to be used by the UE for each downlink signal shall be defined: either Fine Beam or Rough Beam
- Where UE internal noise is relevant, and the UE is assumed to be using Rough Beams, it is increased by the value of Y or Z, selected according to UE Power class and Angle of Arrival.

UE internal noise calculation is given in clause A.2.3.

A.2.3 UE internal noise

A.2.3.1 Relevant core requirements

The relevant Core requirements are:

- Refsens or EIS spherical coverage, specified in TS 38.101-2 [16] clauses 7.3.2 and 7.3.4 respectively
- UE baseband SNR at which Refsens or EIS spherical coverage is specified, in TS 38.133 [17] clause B.2.1.3
- N_{RB} in channel BW at which Refsens or EIS spherical coverage is specified, in TS 38.101-2 [16] Table 5.3.2-1
- Gain difference between fine and rough beams, in TS 38.133 [17] clause B.2.1.3
- UE multi-band relaxation factors, in TS 38.101-2 [16] Table 6.2.1.3-4

A.2.3.2 Calculation method

For signals arriving from Rx Beam Peak direction:

$$\text{Noise in dBm/SCS} = \text{Refsens}_{\text{PC, band, Ch BW}} - \text{SNR}_{\text{Refsens}} - 10\text{Log}_{10}(N_{\text{RB_Ch BW, SCS}} \times 12) + Y_{\text{PC}} + \Sigma MB_P$$

where:

$\text{Refsens}_{\text{PC, band, Ch BW}}$ is the reference sensitivity value in dBm specified in TS 38.101-2 [16] clause 7.3.2 according to Power Class, Operating band and Channel bandwidth

$\text{SNR}_{\text{Refsens}}$ is the SNR used for simulation of Refsens and EIS spherical coverage, and is -1 dB

$N_{\text{RB_Ch BW, SCS}}$ is the number of PRBs specified in TS 38.101-2 [16] Table 5.3.2-1 according to Channel bandwidth and subcarrier spacing (not necessarily equal to the number of PRBs used in the test case)

12 is the number of subcarriers in a PRB

Y_{PC} is the gain difference in dB specified in TS 38.133 [17] Table B.2.1.3.1-1, according to Power Class, and is only applied when the UE is assumed to be using rough beams. Otherwise, use 0dB.

ΣMB_P is the UE multi-band relaxation factor value in dB specified in TS 38.101-2 [16] clause 6.2.1

For signals arriving from Spherical coverage directions:

$$\text{Noise in dBm/SCS} = \text{EIS spherical coverage}_{\text{PC, band, Ch BW}} - \text{SNR}_{\text{Refsens}} - 10\text{Log}_{10}(N_{\text{RB_Ch BW, SCS}} \times 12) + Z_{\text{PC}} + \Sigma MB_S$$

where:

EIS spherical coverage $_{\text{PC, band, Ch BW}}$ is the EIS spherical coverage value in dBm specified in TS 38.101-2 [16] clause 7.3.4 according to Power Class, Operating band and Channel bandwidth

$\text{SNR}_{\text{Refsens}}$ is the SNR used for simulation of Refsens and EIS spherical coverage, and is -1 dB

$N_{\text{RB_Ch BW, SCS}}$ is the number of PRBs specified in TS 38.101-2 [16] Table 5.3.2-1 according to Channel bandwidth and subcarrier spacing (not necessarily equal to the number of PRBs used in the test case)

12 is the number of subcarriers in a PRB

Z_{PC} is the gain difference in dB specified in TS 38.133 [17] Table B.2.1.3.2-1, according to Power Class, and is only applied when the UE is assumed to be using rough beams. Otherwise, use 0dB.

ΣMB_S is the UE multi-band relaxation factor value in dB specified in TS 38.101-2 [16] clause 6.2.1

The analysis spreadsheet converts dBm/SCS to linear power in pW/SCS for ease of further calculations.

A.2.3.3 Principles for Test Tolerance analysis

The following principles shall be followed in the test case analysis:

- Where the test case has requirements on UE baseband $\text{Es/Iot}_{\text{BB}}$, the Test Tolerance analysis should include UE internal noise in the calculation
- UE internal noise is calculated using the method in A.2.3.2

A.2.4 Calculation of Es/Iot at UE baseband

A.2.4.1 Relevant core requirements

Core requirements applicable to RRM test cases depend on the test purpose, and should be selected for each test case. For test cases where the UE makes a measurement, the following are relevant:

- Measurement Performance requirements are specified in TS 38.133 [17] clause 10, and side conditions such as Es/Iot are included in the core requirements for each measurement. For FR2, notes in tables clarify that Es/Iot is at UE baseband.
- Operating band specific conditions for RRM requirements are specified in TS 38.133 [17] Annex B, and side conditions such as Es/Iot are included for each measurement. For FR2, notes in tables clarify that Es/Iot is at UE baseband.

Other UE core requirements may also have conditions on Es/Iot.

A.2.4.2 Calculation method

An example is provided here for a scenario with applied AWGN and two intra-frequency cells. SSB Es/Iot at UE baseband is calculated for Cell 1. Interference to Cell 1 comes from the applied AWGN, from the UE internal noise, and from Cell 2. The values are chosen for illustration, and not taken from any specific test case.

$$\text{Cell 1 SSB Es/Iot}_{\text{BB}} = 10\text{Log}_{10}((\text{Cell 1 SSB power}) / (\text{Applied AWGN power} + \text{UE internal noise} + \text{Cell 2 SSB power}))$$

Where Applied AWGN power, UE internal noise, Cell 1 power and Cell 2 power are linear powers in W, per subcarrier.




Figure A.2.4.2-1: Example Es/Iot$_{BB}$ scenario, applied AWGN and two intra-frequency cells

In this case, the calculation gives Cell 1 SSB Es/Iot$_{BB}$ = 10Log$_{10}$ (0.139 / (0.055 + 0.037 + 0.070)) = **-0.67dB**

The main point is that the Es/Iot at UE baseband is lower than the applied Es/Iot, because the UE internal noise adds to the interference, and can be a significant contribution for the parameters used in some test cases.

The presence of UE internal noise also affects the calculation of Es/Iot sensitivity factors in the Test Tolerance analysis. The UE internal noise is a fixed (worst) value, being based on the UE minimum requirement, and is taken into account in the scaling which uses linear powers:

- Cell 1 SSB Es/Iot$_{BB}$ sensitivity to applied AWGN absolute power = UE internal noise /(Applied AWGN power + UE internal noise + Cell 2 SSB power). In this example, (0.037 / (0.055 + 0.037 + 0.070)) = **+0.230**
- Cell 1 SSB Es/Iot$_{BB}$ sensitivity to Cell 1 Es/Noc = **+1.000**
- Cell 1 SSB Es/Iot$_{BB}$ sensitivity to Cell 2 Es/Noc = -Cell 2 SSB power /(Applied AWGN power + UE internal noise + Cell 2 SSB power). In this example, (0.070 / (0.055 + 0.037 + 0.070)) = **-0.429**

A positive sensitivity factor is used where an increase in the quantity produces an increase in Cell 1 SSB Es/Iot$_{BB}$, for example increasing Cell 1 Es/Noc. A negative sensitivity factor is used where an increase in the quantity produces a decrease in Cell 1 SSB Es/Iot$_{BB}$, for example increasing Cell 2 Es/Noc. The sensitivity factors are used to scale the uncertainties.

Where the uncertainties are uncorrelated, as here, they are added root-sum-square so the sign of the sensitivity factor does not have any effect. In special cases where the uncertainties are correlated, they may be added arithmetically and the sign affects the result, as in clause A.2.7.

A.2.4.3 Principles for Test Tolerance analysis

The following principles shall be followed in the test case analysis:

- UE internal noise is included in the interference when calculating Es/Iot$_{BB}$
- Es/Iot$_{BB}$ sensitivity factors are calculated using the method in A.2.4.2

A.2.5 Calculation of Applied Io

A.2.5.1 Relevant core requirements

Core requirements applicable to RRM test cases depend on the test purpose, and should be selected for each test case. For test cases where the UE makes a measurement, the following are relevant:

- Measurement Performance requirements are specified in TS 38.133 [17] clause 10, and side conditions such as Io are included in the core requirements for each measurement. Normally the maximum Io condition is specified in the channel bandwidth, whereas the minimum Io condition is specified as a power density per subcarrier.

A.2.5.2 Calculation method

An example is provided here for a scenario with applied AWGN and two intra-frequency cells. Io applied to the UE is the arithmetic sum of linear powers in the channel bandwidth. UE internal noise is not counted, as it is not applied to the UE. The values are chosen for illustration, and not taken from any specific test case.

Channel Io = $10Log_{10}$ (Applied AWGN power + Cell 1 power + Cell 2 power) + $10Log_{10}$ (N_{RB_TC} x 12)

where:

AWGN, Cell 1 power and Cell 2 power are linear powers in W, per subcarrier

N_{RB_TC} is the number of PRBs allocated in the test case (not necessarily equal to the number of PRBs in the channel bandwidth)

12 is the number of subcarriers in a PRB




Figure A.2.5.2-1: Example Io scenario, applied AWGN and two intra-frequency cells

With 24 PRBs allocated, the example gives Io = $10Log_{10}$ ((0.055 +0.139 +0.070) x10^{-9})+$10Log_{10}$ (24 x 12) = **-71.2dBm**

Io sensitivity factors in the Test Tolerance analysis are based on linear powers:

- Io sensitivity to applied AWGN absolute power = **+1.000**
- Io sensitivity to Cell 1 Es/Noc = Cell 1 power / (Applied AWGN power + Cell 1 power + Cell 2 power). In this example, (0.139 / (0.055 + 0.139 + 0.070)) = **+0.527**
- Io sensitivity to Cell 2 Es/Noc = Cell 2 power / (Applied AWGN power + Cell 1 power + Cell 2 power). In this example, (0.070 / (0.055 + 0.139 + 0.070)) = +**0.264**

All the sensitivity factors are positive, as an increase in the quantity produces an increase in Io. The sensitivity factors are used to scale the uncertainties.

A.2.5.3 Principles for Test Tolerance analysis

The following principles shall be followed in the test case analysis:

- Io is calculated using the method in A.2.5.2
- Io sensitivity factors are calculated using the method in A.2.5.2

A.2.6 UE Reported RSRP and UE gain

A.2.6.1 Relevant core requirements

SS-RSRP is defined to be measured based on the combined signal from antenna elements corresponding to a given receiver branch. The reference point for requirement parameters from the UE perspective is the input of the UE antenna array. The UE gain “G” relates the combined signal from antenna elements corresponding to a given receiver branch to the reference point for requirement parameters.

For test cases where the UE reports a measured value, or compares a measured value to a signalled threshold, the UE Gain "G" affects the SS-RSRP level measured by the UE

- The UE Gain from the reference point (where test case parameters are specified) to the SS-RSRP measurement point is specified in TS 38.133 [17] clause B.2.1.5. As the UE gain "G" is specified for Rx Beam Peak angle of arrival, it does not include effects related to spherical coverage.

- Measurement Performance requirements are specified in TS 38.133 [17] clause 10, and include accuracy requirements as +/-dB values. For FR2, the accuracy is considered to apply at the combined signal from antenna elements corresponding to a given receiver branch, and does not include the UE gain "G".

The specified range of UE Gain "G" allows the UE to use either Rough beams or Fine beams, so no further allowance is required for the parameters Y or Z in A.2.2.

In any specific direction, the UE gain G may be different depending on frequencies. The UE gain difference between inter-frequencies "Ginter" affects relative signal level values reported by the UE when measuring between different frequencies and is specified in TS 38.133 [17] Table B.2.1.5.2-1 for each power class. Ginter parameter is applicable only to RSRP relative accuracy test cases.

A.2.6.2 Absolute RSRP

An example is provided here for a scenario where the UE reports SS-RSRP for a signal arriving from a direction within the UE spherical coverage, to illustrate variation from both UE spherical coverage and variation from UE gain "G".

UE-measured SS-RSRP$_{nom}$ = Applied SSB_RP + UE Spherical coverage gain midpoint + UE gain G midpoint

where:

Applied SSB_RP is specified in the test case, either directly as Es or derived from Noc and Es/Noc, and is in dBm per subcarrier

UE Spherical coverage gain midpoint in dB is derived as (UE Refsens - UE Spherical coverage)/2

UE gain G midpoint in dB is derived as (Min value of G + Max value of G)/2

As an example for a UE power class 3 in band n257, measuring SS_RSRP from a spherical coverage direction, UE-measured SS-RSRP$_{nom}$ = Applied SSB_RP -5.45dB +5.0dB.

Figure A.2.1.2-1 shows the derivation of UE Spherical coverage gain midpoint. Variation about the midpoint is handled as a UE uncertainty. For signals arriving from Rx Beam Peak direction, this gain is 0dB and does not vary.

Figure A.2.6.2-1 shows the derivation of UE gain G midpoint. Variation about the midpoint is handled as a UE uncertainty.




Figure A.2.6.2-1: Example modelling of UE Gain "G" variation

To calculate the range of valid SS-RSRP values that can be reported by the UE, contributions from Spherical coverage gain variation, UE gain variation and UE reporting accuracy are considered:




Figure A.2.6.2-2: modelling of contributions affecting SS-RSRP reported values

Reported SS-RSRP = UE measured SS-RSRP$_{nom}$ ±Spherical coverage gain variation ±UE gain variation ±UE accuracy

where:

UE measured SS-RSRP$_{nom}$ is the nominal value derived from Applied SSB_RP, UE Spherical coverage gain midpoint and UE gain G midpoint

Spherical coverage gain variation is derived from Refsens and Spherical coverage, as shown in Figure A.2.1.2-1

UE gain variation is derived from Minimum and maximum values of G, as shown in Figure A.2.6.2-1

UE accuracy is the absolute accuracy from the core requirement referred to in A.2.6.1

As an example for a UE power class 3 in band n257, measuring SS_RSRP from a spherical coverage direction with applied Io > -70dBm, the variation would be (±5.45dB ±15dB ±8dB) = **±28.45dB**

These variations are added arithmetically in the test case analysis, as each could be systematic and not random. For signals arriving from Rx Beam Peak direction, spherical coverage gain variation is 0dB.

A.2.6.3 Relative RSRP, 2 levels on same cell, same Angle of Arrival

An example is provided here for a scenario where the test case require the UE to report SS-RSRP for the same cell at two different levels, with the signal arriving from the same direction. The Angle of Arrival may be within the UE spherical coverage, or from Rx Beam peak direction.

UE-measured SS-RSRP1$_{nom}$ = Applied SSB_RP1 + UE Spherical coverage gain midpoint + UE gain G midpoint

UE-measured SS-RSRP2$_{nom}$ = Applied SSB_RP2 + UE Spherical coverage gain midpoint + UE gain G midpoint

UE-measured SS-RSRP2$_{nom}$ - UE-measured SS-RSRP1$_{nom}$ = Applied SSB_RP2 - Applied SSB_RP1

where:

Applied SSB_RP1 and Applied SSB_RP2 are specified in the test case, either directly as Es or derived from Noc and Es/Noc, and are in dBm per subcarrier

It can be seen that UE Spherical coverage gain midpoint and UE gain G midpoint cancel out for this relative measurement, as they remain the same for a signal from the same Angle of Arrival.

Reported SS-RSRP2 - Reported SS-RSRP1 = UE-measured SS-RSRP2$_{nom}$ - UE-measured SS-RSRP1$_{nom}$ ±UE accuracy

where:

UE accuracy is the relative accuracy from the core requirement referred to in A.2.6.1

A.2.6.4 Relative RSRP, 2 intra-frequency cells, same Angle of Arrival

An example is provided here for a scenario where the test case require the UE to report SS-RSRP for two different cells, with the signals arriving from the same direction. The Angle of Arrival may be within the UE spherical coverage, or from Rx Beam peak direction.

UE-measured SS-RSRP1$_{nom}$ = Applied SSB_RP1 + UE Spherical coverage gain midpoint + UE gain G midpoint

UE-measured SS-RSRP2$_{nom}$ = Applied SSB_RP2 + UE Spherical coverage gain midpoint + UE gain G midpoint

UE-measured SS-RSRP2$_{nom}$ - UE-measured SS-RSRP1$_{nom}$ = Applied SSB_RP2 - Applied SSB_RP1

where:

Applied SSB_RP1 and Applied SSB_RP2 are specified in the test case, either directly as Es or derived from Noc and Es/Noc, and are in dBm per subcarrier

It can be seen that UE Spherical coverage gain midpoint and UE gain G midpoint cancel out for this relative measurement, as they are the same for signals from the same Angle of Arrival.

Reported SS-RSRP2 - Reported SS-RSRP1 = UE-measured SS-RSRP2$_{nom}$ - UE-measured SS-RSRP1$_{nom}$ ±UE accuracy

where:

UE accuracy is the relative accuracy from the core requirement referred to in A.2.6.1

A.2.6.5 Relative RSRP, 2 inter-frequency cells, same Angle of Arrival

[FFS]

A.2.6.6 Relative RSRP, 2 cells, different Angles of Arrival

Examples are provided here for scenarios where the test case requires the UE to report SS-RSRP for two different cells, with the signals arriving from different directions.

For both Angles of Arrival from UE spherical coverage directions:

UE-measured SS-RSRP1$_{nom}$ = Applied SSB_RP1 + UE Spherical coverage gain midpoint + UE gain G midpoint

UE-measured SS-RSRP2$_{nom}$ = Applied SSB_RP2 + UE Spherical coverage gain midpoint + UE gain G midpoint

UE-measured SS-RSRP2$_{nom}$ - UE-measured SS-RSRP1$_{nom}$ = Applied SSB_RP2 - Applied SSB_RP1

where:

Applied SSB_RP1 and Applied SSB_RP2 are specified in the test case, either directly as Es or derived from Noc and Es/Noc, and are in dBm per subcarrier

For the nominal values, UE Spherical coverage gain midpoint and UE gain G midpoint cancel out for this relative measurement. For the variations, UE gain variation cancels out as the same value affects both cells, but Spherical coverage gain variation applies separately to each Angle of Arrival.

Reported SS-RSRP2 - Reported SS-RSRP1 = UE-measured SS-RSRP2$_{nom}$ - UE-measured SS-RSRP1$_{nom}$ ±Spherical coverage gain variation$_{AoA1}$ ±Spherical coverage gain variation$_{AoA2}$ ±UE accuracy

where:

Spherical coverage gain variation$_{AoA1}$ is derived from Refsens and Spherical coverage, as in Figure A.2.1.2-1

Spherical coverage gain variation$_{AoA2}$ is derived from Refsens and Spherical coverage, as in Figure A.2.1.2-1

UE accuracy is the relative accuracy from the core requirement referred to in A.2.6.1

For one Angle of Arrival from UE spherical coverage directions, and one from Rx Beam peak direction:

UE-measured SS-RSRP1$_{nom}$ = Applied SSB_RP1 + UE Spherical coverage gain midpoint + UE gain G midpoint

UE-measured SS-RSRP2$_{nom}$ = Applied SSB_RP2 + UE gain G midpoint

UE-measured SS-RSRP2$_{nom}$ - UE-measured SS-RSRP1$_{nom}$ = Applied SSB_RP2 - Applied SSB_RP1 - UE Spherical coverage gain midpoint

where:

Applied SSB_RP1 and Applied SSB_RP2 are specified in the test case, either directly as Es or derived from Noc and Es/Noc, and are in dBm per subcarrier

UE Spherical coverage gain midpoint in dB is derived as (UE Refsens - UE Spherical coverage)/2

For the nominal values, UE gain G midpoint cancels out for this relative measurement, but UE Spherical coverage gain midpoint applies to one Angle of Arrival. For the variations, UE gain variation cancels out as the same value affects both cells, but Spherical coverage gain variation applies to one Angle of Arrival.

Reported SS-RSRP2 - Reported SS-RSRP1 = UE-measured SS-RSRP2$_{nom}$ - UE-measured SS-RSRP1$_{nom}$ ±Spherical coverage gain variation$_{AoA1}$ ±UE accuracy

where:

Spherical coverage gain variation$_{AoA1}$ is derived from Refsens and Spherical coverage, as in Figure A.2.1.2-1

UE accuracy is the relative accuracy from the core requirement referred to in A.2.6.1

A.2.6.7 Principles for Test Tolerance analysis

The following principles shall be followed in the test case analysis:

- UE-measured SS-RSRP$_{nom}$ is calculated using the relevant method in A.2.6.2 to A.2.6.6
- The range of SS-RSRP reported values is calculated using the relevant methods in A.2.6.2 to A.2.6.6

A.2.7 Intra-frequency cells without AWGN, same Angle of Arrival

A.2.7.1 Test system

In a practical test system running a test case where Intra-frequency cells come from the same Angle of Arrival, the level uncertainties for all cells will be highly correlated. If the test case has applied AWGN, it will specify Noc and Es/Noc, and the absolute uncertainty for applied AWGN will be the dominant contribution to the overall Es uncertainty for each cell. As AWGN is common to all cells on that frequency, the correlation is already included.

If the test case does not have applied AWGN, it will specify Es for each cell, with an absolute Es uncertainty for each cell. The method of handling the effect of correlation in the Test Tolerance analysis is given in A.2.7.2 and A.2.7.3.

A.2.7.2 Calculation method for Es/Iot at UE baseband

An example is provided here for a scenario with two intra-frequency cells, without applied AWGN. SSB Es/Iot at UE baseband is calculated for Cell 1. Interference to Cell 1 comes from the UE internal noise and from Cell 2. The values are chosen for illustration, and not taken from any specific test case.

Cell 1 SSB Es/Iot$_{BB}$ = 10Log$_{10}$ ((Cell 1 SSB power) / (UE internal noise + Cell 2 SSB power))

Where UE internal noise, Cell 1 power and Cell 2 power are linear powers in W, per subcarrier.




Figure A.2.7.2-1: Example Es/Iot$_{BB}$ scenario, two intra-frequency cells

In this case, the calculation gives Cell 1 SSB Es/Iot$_{BB}$ = 10Log$_{10}$ (0.139 / (0.037 + 0.070)) = **1.14dB**

The presence of UE internal noise also affects the calculation of Es/Iot sensitivity factors in the Test Tolerance analysis. The UE internal noise is a fixed (worst) value, being based on the UE minimum requirement, and is taken into account in the scaling which uses linear powers:

- Cell 1 SSB Es/Iot$_{BB}$ sensitivity to Cell 1 Es = **+1.000**
- Cell 1 SSB Es/Iot$_{BB}$ sensitivity to Cell 2 Es = -Cell 2 SSB power /(UE internal noise + Cell 2 SSB power). In this example, (0.070 / (0.037 + 0.070)) = **-0.651**

A positive sensitivity factor is used where an increase in the quantity produces an increase in Cell 1 SSB Es/Iot$_{BB}$, for example increasing Cell 1 Es. A negative sensitivity factor is used where an increase in the quantity produces a decrease in Cell 1 SSB Es/Iot$_{BB}$, for example increasing Cell 2 Es. The sensitivity factors are used to scale the uncertainties.

Where the uncertainties are correlated, as here, they are added arithmetically and the sign affects the result. In this example, increasing Cell 1 Es increases the Cell 1 SSB Es/Iot$_{BB}$, but the correlated increase in Cell 2 Es decreases the Cell 1 SSB Es/Iot$_{BB}$. The overall effect is smaller, and depends on the ratios of linear powers.

A.2.7.3 Calculation method for Applied Io

An example is provided here for a scenario with two intra-frequency cells, without applied AWGN. Io applied to the UE is the arithmetic sum of linear powers in the channel bandwidth. UE internal noise is not counted, as it is not applied to the UE. The values are chosen for illustration, and not taken from any specific test case.

$$\text{Channel Io} = 10\text{Log}_{10}(\text{Cell 1 power} + \text{Cell 2 power}) + 10\text{Log}_{10}(N_{RB_TC} \times 12)$$

where:

Cell 1 power and Cell 2 power are linear powers in W, per subcarrier

N_{RB_TC} is the number of PRBs allocated in the test case (not necessarily equal to the number of PRBs in the channel bandwidth)

12 is the number of subcarriers in a PRB




Figure A.2.7.3-1: Example Io scenario, two intra-frequency cells

With 24 PRBs allocated, the example gives Io = $10Log_{10}$ ((0.139 +0.070) $x10^{-9}$) +$10Log_{10}$ (24 x 12) = **-72.2dBm**

Io sensitivity factors in the Test Tolerance analysis are based on linear powers:

- Io sensitivity to Cell 1 Es = Cell 1 power / (Cell 1 power + Cell 2 power). In this example, (0.139 / (0.139 + 0.070)) = **+0.667**
- Io sensitivity to Cell 2 Es = Cell 2 power / (Cell 1 power + Cell 2 power). In this example, (0.070 / (0.139 + 0.070)) = +**0.333**

All the sensitivity factors are positive, as an increase in the quantity produces an increase in Io. The sensitivity factors are used to scale the uncertainties.

Where the uncertainties are correlated, as here, they are added arithmetically, and the sign affects the result. In this example increasing Cell 1 Es increases Io, and the correlated increase in Cell 2 Es also increases Io. The overall effect of scaling adds up to 1, as expected.

A.2.7.4 Principles for Test Tolerance analysis

The following principles shall be followed in the test case analysis:

- For Intra-frequency cells from the same Angle of Arrival without AWGN, Es/Iot_{BB} is calculated using the method in A.2.7.2.
- For Intra-frequency cells from the same Angle of Arrival without AWGN, Es/Iot_{BB} sensitivity factors are calculated using the method in A.2.7.2.
- For Intra-frequency cells from the same Angle of Arrival without AWGN, Io is calculated using the method in A.2.7.3.
- For Intra-frequency cells from the same Angle of Arrival without AWGN, Io sensitivity factors are calculated using the method in A.2.7.3.

A.3 Test Tolerance analysis templates for radiated test cases awaiting completion

Test Tolerance analyses for Radiated testing listed below are not yet complete, but contain the main features for the test cases covered and can be used as templates. For each analysis, the missing aspects are listed.

The analysis documents (and spreadsheets where applicable) are included in the present document as zip files with “draft” at the end of the filename. When the test case analyses are complete, the draft versions and listing in this clause should be removed.

38.533 5.3.2.2.1+5.3.2.2.2+7.3.2.2.1+7.3.2.2.2 TT draft v2

Editor’s note: This test tolerance analysis is incomplete. The following aspects are missing:

- Settable window for first preamble uplink power and the uplink calibration process

- Derivation of test requirement for absolute uplink power after uplink calibration process

- Derivation of test requirement for relative uplink power

- The uncertainty value and test requirement for PRACH timing are in [ ] and not yet finalised

- The results of the TT analysis are provisional until the corresponding MU values are agreed

A.4 Design of radiated test cases defined in TS 38.533

The design of radiated test cases defined in TS 38.533 is more challenging than for conducted test cases, because the over-the-air path loss reduces the downlink power seen by the UE, and reduces the uplink power received by the test system.

The achievable downlink power in a practical test system is restricted, and there is less dB range between the lowest and highest power that can be applied within the UE Core requirement side conditions.

The range of uplink power that can be measured by a practical test system is also restricted, by signal-to-noise ratio considerations at the low end, and by the UE output power at the high end.

For both downlink and uplink, the achievable dB range is most restricted when the signal arrives from the UE Spherical coverage direction. In a test case it is further restricted by downlink power level uncertainty or uplink power measurement uncertainty, which are both larger for radiated signals than for conducted signals. This Annex considers the effect of restricted dB range on radiated RRM test case design.

A.4.1 Downlink considerations

A.4.1.1 Side conditions for Rx Beam Peak angle of arrival

Side conditions for Rx Beam Peak angle of arrival are less stringent than for Spherical Coverage angle of arrival. They are not directly analysed here, but the same principles apply as for Spherical Coverage in clause A.4.1.2.

A.4.1.2 Side conditions for Spherical Coverage angle of arrival

As an example, consider a test case where the UE makes measurements on the downlink signal, for example in Event-triggered reporting. Some side condition values are band-dependent, and also depend on whether the cell being measured is intra-frequency or inter-frequency. An adverse case is chosen for illustration:

- Spherical Coverage angle of arrival
- Inter-frequency
- UE Power Class 3
- Band n259
- Maximum multi-band relaxation
- Full RB allocation
- UE is required to make measurements, so side conditions apply

The scenario is however best case on two points:

- Applied Es only, without Noc (only UE internal noise)
- Only one cell on the frequency (no other intra-frequency cells)




Figure A.4.1.2-1: Example side conditions when UE is making measurements

It can be seen that when uncertainties are taken into account (an indicative value of ±6dB is used), the applied level range can be from -87dBm/SCS to -85dBm/SCS, a range of only 2dB. This is very restrictive for the test case design.

A.4.1.3 Test case design options to increase downlink dB range

A number of options are available to increase the dB range of the applied downlink signal, if necessary. For a specific test case, only some may be available, for example in a test case such as Radio Link Monitoring, it would not be possible to use applied Es only, because the test case relies on a well-defined SNR at the UE baseband.

Table A.4.1.3-1: Options to increase downlink dB range

Option	Applicability	Comments
Reduce number of allocated RBs	All Test cases	120kHz SSB SCS, use 24RBs 240kHz SSB SCS, use 48RBs Allocated RBs must include CORESET
Use applied Es only, without applied Noc	Test cases where Es/Iot_{BB} requirement is to be ≥ defined value	Maximises Es contribution to Io. Not suitable for test cases where Es/Iot_{BB} is intended as well-defined SNR.
If applied Noc is used, reduce margin above UE internal noise	Test cases where Es/Iot_{BB} requirement is to be ≥ defined value	Not suitable for test cases where Es/Iot_{BB} is intended as well-defined SNR.
Use time-division multiplexing with SSB#0, SSB#1	Test cases using SSB#0, SSB#1	Avoids intra-frequency interference and degradation of Es/Iot_{BB}
Use Rx Beam Peak AoA instead of Spherical Coverage	Test cases where using Rx Beam Peak for one or both AoA, instead of Spherical Coverage, would provide adequate test coverage	Adequate test coverage may be achievable across several Test cases
Allow Io > -50dBm	Test cases where measurement side conditions are not applicable	Test system may not be able to deliver >-50dBm
Restrict to 120kHz SSB SCS	Test cases with a 240kHz SSB SCS Configuration	Adequate test coverage of 120kHz and 240kHz SSB SCS may be achievable across several Test cases




Figure A.4.1.3-1: Example illustration of selected options to increase downlink dB range

Annex B: Acceptable uncertainty of test system for test cases defined in TS 38.521-2 for radiative testing

This annex contains suggested uncertainties for each test case in TS 38.521-2.

B.1 Uncertainty budget calculation principle

Three permitted test methodologies, DFF, IFF and NFTF, have been identified for UE RF FR2 test cases defined in TS 38.521-2.

This Annex is deriving Total expanded Measurement Uncertainties per test case for each test methodology.

Threshold MU is equivalent to Total expanded uncertainty of the reference methodology which has been defined as IFF.

If the Total expanded Measurement Uncertainty per test case of a permitted test method is lower than or equal to the threshold MU, then that test method is applicable to the respective test cases defined in TS 38.521-2.

B.1.1 Uncertainty budget calculation principle for DFF

The uncertainty tables should be presented with two stages:

- Stage 1: the calibration of the absolute level of the DUT measurement results is performed by means of using a calibration antenna whose absolute gain is known at the frequencies of measurement
- Stage 2: the actual measurement with the DUT as either the transmitter or receiver is performed.

The MU budget should comprise the following headings:

1) The uncertainty source. Compile a complete list of the individual measurement uncertainty elements that contribute to a measurement
2) Determine the maximum value of each uncertainty
3) Determine the distribution of each uncertainty (rectangular, U-shaped, etc.),
4) Calculate (if necessary) the standard deviation of each uncertainty, u_i, (NOTE 1) for each uncertainty element,
5) Convert the units (if necessary) of each uncertainty element into the chosen unit, i.e., dB,
6) Combine ALL the standard uncertainties by the root-sum-squares method to derive the 'combined standard uncertainty',
7) Multiply the resulting combined standard uncertainty by an expansion factor 'k' to derive the 'expanded uncertainty' for a given confidence level. All expanded uncertainties are quoted to 95% confidence level, so k is taken as 1.96. This gives 95% confidence that the true value is within 1.96 times the combined standard uncertainty of the measured value to derive the 'expanded uncertainty'.
8) Any systematic errors are added to the expanded uncertainty to derive the ‘total expanded uncertainty’, i.e.,

$$u_{c,\text{total expanded}} = u_{c,\text{expanded}} + u_{c,\text{systematic}} = 1.96\sqrt{\sum u_i^2} + \sum u_{i,\text{systematic}}$$

NOTE 1: The standard deviation from a data set of N samples is defined as

$$u_i = \sqrt{\frac{1}{N-1}\sum_{k=1}^{N}\left|s_k - \overline{s}\right|^2}$$

where s_k are the respective sample results and $\overline{S}$ the mean of all N samples. For an uncertainty u_i in dB, the dB values (instead of the linear powers) of s_k and $\overline{S}$ are used.

B.1.2 Uncertainty budget calculation principle for IFF

The same as defined in B.1.1.

B.1.3 Uncertainty budget calculation principle for NFTF

The same as defined in B.1.1 with the exception of Stage 2, only the measurement of the DUT transmitter is performed.

B.2 Measurement error contribution descriptions

B.2.1 Measurement error contribution descriptions for DFF

B.2.1.1 Positioning misalignment

This contribution originates from the misalignment of the testing direction and the beam peak direction of the measurement antenna due to imperfect rotation operation. The pointing misalignment may happen in both azimuth and vertical directions and the effect of the misalignment depends highly on the beam width of the beam under test. The same level of misalignment results in a larger measurement error for a narrower beam.

B.2.1.2 Measure distance uncertainty

The cause of this uncertainty contributor is due to the reduction of distance between the measurement antenna and the DUT. If the distance of separation is $2D^2$/lambda based on D being the entire device size, then the phase variation is 22.5deg. Whether this is the minimum acceptable criteria of phase taper over the entire DUT is FFS and shall be assessed during final MU definition for the test method. Any reduction in the distance of separation increases the phase variation and creates an error which is DUT dependant. Determination of limit of the error shall be done during final MU definition for the test method.

B.2.1.3 Quality of quiet zone

The quality of the quiet zone procedure characterizes the quiet zone performance of the anechoic chamber, specifically the effect of reflections within the anechoic chamber including any positioners and support structures. The MU term additionally includes the amplitude variations effect of offsetting the directive antenna array inside a DUT from the centre of the quiet zone as well as the directivity MU, i.e., the variation of antenna gains in the different direct line-of-sight links. An additional MU term related to phase variation and phase ripple effects which depends on measurement distance is FFS, and shall be assessed during final MU definition for the test method. This might require an augmentation of the quality of the quiet zone validation procedure.

For test cases requiring 1 (UE RF, Demodulation, RRM) or 2 AoAs (RRM), the re-positioning concept is assumed to define the reference MU for QoQZ for MTSU purposes. For 3 AoA RRM test cases, the re-positioning concept is also assumed as a working assumption which can be confirmed pending the availability of commercial devices supporting those test cases.

B.2.1.4 Mismatch

Mismatch uncertainty occurs when;

- Changing the signal path between the measurement and calibration procedure
- Evaluating the insertion loss of a signal path

The mismatch uncertainty for a system consisting of a generator, a load and a component in between is defined as

$$\text{Mismatch contribution (standard deviation)} = \frac{|\Gamma_{generator}|\cdot|\Gamma_{load}|\cdot|S_{21}|\cdot|S_{12}|\cdot 100}{\sqrt{2}\cdot 11.5}\ \text{dB},$$

Where Γ denotes the reflection coefficient and S_{21} is the transmission coefficient, both in linear voltage ratios.

For a cascade of several components, the interactions between all components have to be evaluated. For example, for four devices in a row (shown in Figure B.2.1.4-1) the following contributions have to be accounted for: AB, BC, CD, ABC, BCD, ABCD. The term ABCD represents the interaction between A and D (generator and load) with the components B and C in between.




Figure B.2.1.4-1: Cascade of components

The combined mismatch uncertainty is given by the root sum square of the individual contributions:

$$combined\ mismatch\ uncertainty = \sqrt{(AB)^2 + (BC)^2 + (CD)^2 + (ABC)^2 + (BCD)^2 + (ABCD)^2}$$

In an optimized test procedure, the overall mismatch uncertainty is smaller when matching pairs of mismatches exist in the calibration and measurement stage since these pairs cancel each other out. Figure B.2.1.4-2 displays a calibration setup, where device D is replaced by device F. The mismatch contributions for this path are AB, BC, CE, ABC, BCE and ABCE. For a result based on the measurement and calibration stage, the mismatch contributions AB, BC, and ABC are matching pairs as they occur both in the measurement and calibration stage. Thus, they can be eliminated [11], and the system mismatch uncertainty is obtained as $\sqrt{(CD)^2 + (CE)^2 + (BCD)^2 + (BCE)^2 + (ABCD)^2 + (ABCE)^2}$




Figure B.2.1.4-2: Sketch of a calibration path

In the following, an example mismatch uncertainty calculation for a TX/RX patch from the measurement equipment to the measurement antenna is performed for a frequency of 43.5GHz. The example path under investigation consists of four SPDT switches, one SP6T switch and one DPDT switch and microwave cable interconnects with PC2.4 mm connectors. The attenuation and reflectance of typical components suitable for frequencies ranging up to 43.5 GHz have been considered in the calculation of the mismatch uncertainty.

Figure B1.1.4.4-3 shows a sample system setup for an EIRP/EIS test case with rather simple complexity of the switch box similar to a current sub 6GHz test setup. It should be noted that the switch unit is significantly less complex than a state-of-the-art switch unit currently used for conformance tests.




Figure B.2.1.4-3: Block Diagram of an EIRP/EIS test case with components from the gNB to the antenna (only portion of switch unit shown)

Table B.2.1.4-1: comprises the reflection and transmission properties of the components of the example path at a frequency of 43.5 GHz

Device / Component	VSWR	Transmission (dB)	Identifier in Figure B.2.1.4-3	Additional Comment/ Assumption
System Simulator	3.5		gNB	
Cable	1.5	-5.38	C1	Length: 1.5m Loss: 3.59dB/m
Cable	1.5	-0.61	C2, C3, C4, C5, C6, C7, C8	Length: 0.17m Loss: 3.59dB/m
Cable	1.5	-7.18	C9, C10	Length: 2.0m Loss: 3.59dB/m
Feedthrough	1.3	-0.66	F1, F2, F3	
SPDT switch	1.9	-1.10	K1, K3, K5, K7	
SP6T switch	2.2	-1.20	K9	
Transfer switch	2.0	-1.10	K10	
Antenna	2.0		Meas. Ant.	

The calculation of the overall mismatch uncertainty for a frequency of 43.5 GHz results in a value of 2.7 dB for the standard deviation, i.e., the expanded uncertainty is 5.3 dB.

Figure B.2.1.4-4 depicts a possible calibration for a part of the setup.




Figure B.2.1.4-4: Block Diagram of the calibration stage

For the VNA a return loss of 30 dB is assumed after a full two-port calibration. The calculation of the system mismatch uncertainty applying the elimination of matching pairs results in a value of 1.0 dB (standard deviation) with an expanded value of 1.9 dB.

Since the overall mismatch uncertainty value is already a standard deviation, which is RSS of values divided by the divisor ($\sqrt{2}$), the overall mismatch uncertainty value should be divided by actual divisor 1 when calculating total mismatch.

B.2.1.5 Standing Wave Between the DUT and measurement antenna

This uncertainty term is related to the amplitude ripple coming from the standing waves between the DUT and measurement antenna. If this term is not considered to be negligible one method to obtain this value is to slide the DUT lambda/4 towards the measurement antenna while measuring the amplitude. The uncertainty term can be derived by performing the standard deviation on the results.

B.2.1.6 Uncertainty of the RF power measurement equipment

The receiving device is used to measure the received signal level in the EIRP tests as an absolute level. These receiving devices are spectrum analysers, communication analysers, or power meters. The uncertainty value will be indicated in the manufacturer's data sheet. It needs to be ensured that appropriate manufacturer's uncertainty contributions are

specified for the settings used such as bandwidth and absolute level. If a power meter is used zero offset, zero drift and measurement noise need to be included.

B.2.1.7 Phase curvature

This contribution originates from the finite far field measurement distance, which causes phase curvature across the antenna of UE/reference antenna. At a measurement distance of $2D^2$/lambda the phase curvature is 22.5 degrees. The impact of this factor shall be assessed during final MU definition for the test method.

B.2.1.8 Amplifier uncertainties

Any components in the setup can potentially introduce measurement uncertainty. It is then needed to determine the uncertainty contributors associated with the use of such components. For the case of external amplifiers, the following uncertainties should be considered but the applicability is contingent to the measurement implementation and calibration procedure.

- Stability
  - An uncertainty contribution comes from the output level stability of the amplifier. Even if the amplifier is part of the system for both measurement and calibration, the uncertainty due to the stability shall be considered. This uncertainty can be either measured or determined by the manufacturers' data sheet for the operating conditions in which the system will be required to operate.
- Linearity
  - An uncertainty contribution comes from the linearity of the amplifier since in most cases calibration and measurements are performed at two different input/output power levels. This uncertainty can be either measured or determined by the manufacturers' data sheet.
- Noise Figure
  - When the signal goes into an amplifier, noise is added so that the SNR at the output is reduced with regard to the SNR of the signal at the input. This added noise introduces error on the signal which affects the Error Rate of the receiver thus the EVM (Error Vector Magnitude). An uncertainty can be calculated through the following formula:

$$\varepsilon_{EVM} = 20\log_{10}\left(1 + 10^{\frac{-SNR}{20}}\right)$$

  - Where SNR is the signal to noise ratio in dB at the signal level used during the sensitivity measurement.
- Mismatch
  - If the external amplifier is used for both stages, measurement and calibration the uncertainty contribution associated with it can be considered systematic and constant -> 0dB. If it is not the case, the mismatch uncertainty at its input and output shall be either measured or determined by the method described in [12].
- Gain
  - If the external amplifier is used for both stages, measurement and calibration the uncertainty contribution associated with it can be considered systematic and constant -> 0dB. If it is not the case, this uncertainty shall be considered.

B.2.1.9 Random uncertainty

This contribution is used to account for all the unknown, unquantifiable, etc. uncertainties associated with the measurements.

Random uncertainty MU contributions are normally distributed.

The random uncertainty term, by definition, cannot be measured, or even isolated completely. However, past system definitions provide an empirical basis for a value. Current LTE SISO OTA measurements have random uncertainty

contributions of ~0.2dB. A value of 0.5dB is suggested due to increased sensitivity to random effects in more complex, higher frequency NR test systems.

B.2.1.10 Influence of the XPD

This factor takes into account the uncertainty caused due to the finite cross polar discrimination (XPD) between the two polarization ports of the measurement probe. The XPD of the probe antenna shall be take into account during final MU definition for the test method.

A typical probe antenna can have XPD of 30dB.

A transmission matrix and calibration setup as shown in Figure B.2.1.10-1 is considered here. Typically, a single-polarized reference antenna with known gain is placed at the centre of the quiet zone and the total attenuation, L, between the reference antenna terminal and the feed antenna terminals is determined as part of the range reference calibration procedure.




Figure B.2.1.10-1: Calibration Setup

Since the reference antenna is considered a single-polarized antenna, the XPD effect is negligible. Since the measurement probe is assumed to be a dual-linearly polarized antenna, leakage from one terminal/polarization to the other, i.e., XPD, needs to be considered.

The dual-linearly polarized measurement probe has two terminals corresponding to a set of orthogonal polarizations, θ and ϕ which match the orientations of the reference antenna. The most thorough calibration procedure would determine the path losses between the four different combinations of signal paths: θθ, θϕ, ϕθ, and ϕϕ, e.g., the power received by the measurement probe at the θ polarization/terminal, $P_{Feed,\theta}$, is attenuated by $L_{\phi\theta}$ with respect to the power delivered to the reference antenna oriented in the ϕ polarization and placed in the centre of quiet zone, $P_{QZ,\phi}$.

The most common calibration approach, however, is based on calibrating the polarization matched paths in Figure B.2.1.10-1 (thick solid lines), i.e., θθ and ϕϕ. In this case, as illustrated in Figure B.2.1.10-2, the normalized pathlosses $L_{\theta\theta}$ and $L_{\phi\phi}$ are 1 and the pathlosses of the crossed components become the XPD terms of the measurement probe:

$$\alpha_{\theta\phi} = 10^{\frac{XPD_{\theta\phi}}{10}} \quad (1.1)$$

and

$$\alpha_{\phi\theta} = 10^{\frac{XPD_{\phi\theta}}{10}} \quad (1.2)$$




Figure B.2.1.10-2: Common calibration approach based on calibrating the polarization matched signal paths

In the remainder of this analysis, it is assumed that the leakage between the two polarization ports of the measurement probe is assumed to be the same, i.e., XPD = $XPD_{\theta\phi}$ = $XPD_{\phi\theta}$ and $\alpha = \alpha_{\theta\phi} = \alpha_{\phi\theta}$.

The normalized powers at the measurement probe terminals can then be written as

$$P_{\text{Probe},\theta} = P_{\text{QZ},\theta} + \alpha P_{\text{QZ},\phi} \quad (1.3)$$

$$P_{\text{Probe},\phi} = P_{\text{QZ},\phi} + \alpha P_{\text{QZ},\theta} \quad (1.4)$$

The normalized ratio of total powers at measurement probe and the centre of the quiet zone is therefore

$$\frac{\mathrm{P}_{\text{Probe}}}{\mathrm{P}_{\text{QZ}}} = \frac{\mathrm{P}_{\text{Probe},\theta} + \mathrm{P}_{\text{Probe},\phi}}{\mathrm{P}_{\text{QZ},\theta} + \mathrm{P}_{\text{QZ},\phi}} = \frac{\left(\mathrm{P}_{\text{QZ},\theta} + \mathrm{P}_{\text{QZ},\phi}\right)(1+\alpha)}{\mathrm{P}_{\text{QZ},\theta} + \mathrm{P}_{\text{QZ},\phi}} = 1+\alpha \quad (1.5)$$

This simple analysis shows that the XPD of the measurement probe introduces a small error of the total power measured by the measurement probe and that the conservation of measured powers is not guaranteed, i.e., the MU based on the XPD can be expressed as

$$\mathrm{MU}_{XPD}\left[\mathrm{dB}\right] = 10\log_{10}\left(1+\alpha\right) = 10\log_{10}\left(1+10^{\frac{XPD}{10}}\right) \quad (1.6)$$

This XPD MU is tabulated for different levels of XPD in Table B.2.1.10-1.

Table B.2.1.10-1: XPD MU for different XPD values

XPD [dB]	MU_{XPD} [dB]
-20	0.043
-25	0.014
-30	0.004
-35	0.001
-40	0.000

When the range reference calibration is based on a full matrix-based approach, i.e., all signal paths are calibrated, the conservation of measured powers is guaranteed. As shown in Figure B.2.1.10-3, the polarization-matched signal paths take into account the leakage of power into the cross paths.




Figure B.2.1.10-3: Calibration approach based on calibrating all signal paths

The powers at the measurement probe can now be written as

$$P_{\text{Probe},\theta} = (1-\alpha)P_{\text{QZ},\theta} + \alpha P_{\text{QZ},\phi} \quad (1.7)$$

$$P_{\text{Probe},\phi} = (1-\alpha)P_{\text{QZ},\phi} + \alpha P_{\text{QZ},\theta} \quad (1.8)$$

The normalized ratio of total powers at measurement probe and the centre of the quiet zone is then

$$\frac{\mathrm{P}_{\text{Probe}}}{\mathrm{P}_{\text{QZ}}} = \frac{\mathrm{P}_{\text{Probe},\theta} + \mathrm{P}_{\text{Probe},\phi}}{\mathrm{P}_{\text{QZ},\theta} + \mathrm{P}_{\text{QZ},\phi}} = \frac{\mathrm{P}_{\text{QZ},\theta} + \mathrm{P}_{\text{QZ},\phi}}{\mathrm{P}_{\text{QZ},\theta} + \mathrm{P}_{\text{QZ},\phi}} = 1 \quad (1.9)$$

This simple analysis now shows that for a matrix-based calibration of all signal paths the XPD of the measurement probe no longer introduces any error and that the conservation of measured powers is guaranteed, i.e., the MU based on the XPD is 0dB.

The derivation of the XPD MU based on powers is a more straightforward and less complex approach than with electric fields as attempted in [2]. This annex shows that the same XPU MU result as derived in (1.5) can be derived using electric fields.

The corresponding signal paths are illustrated in Figure B.2.1.10-4.




Figure B.2.1.10-4: Signal paths for electric fields (based on calibrating the polarization matched signal paths)

The normalized fields at the measurement probe terminals can then be written as

$$E_{\text{Probe},\theta} = E_{\text{QZ},\theta} + ce^{jd}E_{\text{QZ},\phi} \quad (1.10)$$

$$E_{\text{Probe},\phi} = E_{\text{QZ},\phi} + ae^{jb}E_{\text{QZ},\theta} \quad (1.11)$$

The transmission matrix can be defined as H

$$\begin{bmatrix} E_{\text{Probe},\theta} \\ E_{\text{Probe},\phi} \end{bmatrix} = H \begin{bmatrix} E_{\text{QZ},\theta} \\ E_{\text{QZ},\phi} \end{bmatrix} \quad (1.12)$$

$$H = \begin{bmatrix} 1 & ae^{jb} \\ ce^{jd} & 1 \end{bmatrix} \quad (1.13)$$

The total magnitude component of the electric field including coherence/interference terms at the probe is

$$\begin{aligned} E_{\text{Probe},T} &= \sqrt{\left|E_{\text{Probe},\theta}\right|^2 + \left|E_{\text{Probe},\phi}\right|^2} = \sqrt{\left|E_{\text{QZ},\theta} + ce^{jd}E_{\text{QZ},\phi}\right|^2 + \left|E_{\text{QZ},\phi} + ae^{jb}E_{\text{QZ},\theta}\right|^2} \\ &= \sqrt{\left[\left(E_{\text{QZ},\theta} + cE_{\text{QZ},\phi}\cos(d)\right)^2 + \left(cE_{\text{QZ},\phi}\sin(d)\right)^2\right] + \left[\left(E_{\text{QZ},\phi} + aE_{\text{QZ},\theta}\cos(b)\right)^2 + \left(aE_{\text{QZ},\theta}\sin(b)\right)^2\right]} \\ &= \sqrt{\begin{aligned}&\left[{E_{\text{QZ},\theta}}^2 + 2cE_{\text{QZ},\theta}E_{\text{QZ},\phi}\cos(d) + c^2{E_{\text{QZ},\phi}}^2\cos^2(d) + c^2{E_{\text{QZ},\phi}}^2\sin^2(d)\right] + \\ &\left[{E_{\text{QZ},\phi}}^2 + 2aE_{\text{QZ},\theta}E_{\text{QZ},\phi}\cos(b) + a^2{E_{\text{QZ},\theta}}^2\cos^2(b) + a^2{E_{\text{QZ},\theta}}^2\sin^2(b)\right]\end{aligned}} \\ &= \sqrt{{E_{\text{QZ},\theta}}^2\left(1+a^2\right) + {E_{\text{QZ},\phi}}^2\left(1+c^2\right) + 2E_{\text{QZ},\theta}E_{\text{QZ},\phi}\left(c\cos(d) + a\cos(b)\right)} \end{aligned} \quad (1.14)$$

When it is assumed that leakage between the two polarization ports of the measurement probe is assumed to be the same, then $a=c=10^{\text{XPD}/20}$ in (1.14). Additionally, it has to be assumed that $d=b+\pi$ which guarantees the orthogonality between the two field vectors, i.e., the dot product between the vectors has to be zero. With these assumptions, Equation (1.14) will become

$$E_{\text{Probe},T} = \sqrt{\left({E_{\text{QZ},\theta}}^2 + {E_{\text{QZ},\phi}}^2\right)\left(1+a^2\right)} \quad (1.15)$$

The normalized ratio of total powers at measurement probe and the centre of the quiet zone is therefore

$$\frac{\text{P}_{\text{Probe}}}{\text{P}_{\text{QZ}}} \propto \frac{{E_{\text{Probe},T}}^2}{{E_{\text{QZ},T}}^2} = 1 + a^2 = 1 + 10^{\frac{2\,XPD}{20}} = 1 + 10^{\frac{XPD}{10}} \quad (1.16)$$

The derived XPD MU based on electric fields which included the coherence/interference terms in (1.16) is the same as in (1.6).

The XPD of the measurement system shall be determined from the quality of quiet zone measurements, see clause O.2 of [7], at the 7 reference points, P1 through P7, specifically with reference AUT orientations $\gamma=\beta=0^{\text{o}}$ for distributed axes systems, Section O.2.6.1 [7], or reference AUT orientations $\beta=\alpha=0^{\text{o}}$ for combined-axes systems, Section O.2.6.2 [7]. Alternatively, it can be determined using a reference antenna optimized for XPD measurements and with the corresponding alignment to achieve optimal polarization matching between the reference and the measurement antenna.

The XPD for each reference point shall be calculated as the ratio of cross-polarized to co-polarized measured powers and the largest XPD from the 7 different reference points shall be used to determine the XPD MU, i.e.,

$$\text{MU}_{XPD}\left[\text{dB}\right] = 10\log_{10}\left(1+\alpha_{\max}\right) = 10\log_{10}\left(1 + 10^{\frac{XPD_{\max}}{10}}\right) \quad (1\text{-}17)$$

where

$$XPD_{\max}[\text{dB}] = 10\log_{10}\left[\max\left(\left.\frac{P_{cross-pol}}{P_{co-pol}}\right|_{\text{P1},\gamma_{rot}=0^{\text{o}}}, \left.\frac{P_{cross-pol}}{P_{co-pol}}\right|_{\text{P1},\gamma_{rot}=90^{\text{o}}}, \ldots, \left.\frac{P_{cross-pol}}{P_{co-pol}}\right|_{\text{P7},\gamma_{rot}=0^{\text{o}}}, \left.\frac{P_{cross-pol}}{P_{co-pol}}\right|_{\text{P7},\gamma_{rot}=90^{\text{o}}}\right)\right] \quad (1\text{-}18)$$

B.2.1.11 Insertion loss Variation

This uncertainty contribution comes from introducing an additional cable which is not present for both the calibration and DUT measurement. If the cables remain the same for the calibration and DUT measurement, then the contribution should be set to zero.

If an additional cable is added for one part of the test, the insertion loss must be accounted for in the measurement results. If the insertion loss is measured the uncertainty contribution will be the combined uncertainty related to the insertion loss measurement. The insertion loss can also be taken from the datasheet and assumed to have a rectangular distribution.

B.2.1.12 RF leakage (from measurement antenna to receiver/transmitter)

This contribution denotes noise leaking in to connector and cable(s) between measurement antenna and receiving/transmitting equipment. The contribution also includes the noise leakage between the connector and cable(s) between reference antenna and transmitting equipment for the calibration phase. This uncertainty contributor is contained in the contributor quality of quiet zone described in clause B.2.1.3 and its value therefore is set to zero.

B.2.1.13 Misalignment of positioning System

This contribution originates from uncertainty in sliding position and turn table angle/tilt accuracy. If the calibration antenna is aligned to the beam peak this contribution can be considered negligible and therefore set to zero.

B.2.1.14 Uncertainty of the Network Analyzer

This contribution originates from all uncertainties involved transmission magnitude measurement with a network analyser, for example: drift, frequency flatness, temperature variation from kit calibration to path losses measurement as well as interpolation of calibration data if test frequencies were not calibrated during path loss characterization. The uncertainty value will be indicated in the manufacturer's data sheet. It needs to be ensured that appropriate manufacturer's uncertainty contribution is specified for the absolute levels measured.

When an end-to-end system calibration approach is used, the absolute levels are related to the total system losses of the measurement path. When a split calibration approach is used, separate MU contributions need to be determined

- u_cond: transmission magnitude uncertainty for the conducted portion of the calibration; the absolute levels are related to the total system losses for the portion of the system calibrated
- u_rad: transmission magnitude uncertainty for the radiated portion of the calibration; the absolute levels are related to the total system losses for the portion of the system calibrated

The total MU of the network analyser for the split calibration is the RSS’ed value of u_cond and u_rad.

B.2.1.15 Uncertainty of the absolute gain of the calibration antenna

The calibration antenna only appears in Stage 2. Therefore, the gain uncertainty has to be taken into account. This uncertainty will come from a calibration report with traceability to a National Metrology Institute with measurement uncertainty budgets generated following the guidelines outlined in internationally accepted standards.

B.2.1.16 Positioning and pointing misalignment between the reference antenna and the measurement antenna

This contribution originates from reference antenna alignment and pointing error. In this measurement if the maximum gain direction of the reference antenna and the transmitting antenna are aligned to each other, this contribution can be considered negligible and therefore set to zero.

B.2.1.17 gNB emulator uncertainty

gNB emulator is used to drive a signal to the horn antenna (via multiple external components such as a switch box, an amplifier and a circulator, etc.) in sensitivity tests either as an absolute level or as a relative level. Receiving device used

is typically a UE/phablet/tablet/FWA. Generally there occurs uncertainty contribution from absolute level accuracy, non-linearity and frequency characteristic of the gNB emulator.

For practical reasons, in a case that a VNA is used as calibration equipment, gNB emulator is connected to the system after the calibration measurement (Stage 2) is performed by the VNA. Hence, the uncertainty on the absolute level of gNB emulator (transmitter device) cannot be assumed as systematic. This uncertainty should be calculated from the manufacturer's data in logs with a rectangular distribution, unless otherwise informed. Furthermore, the uncertainty of the non-linearity is included in the absolute level uncertainty.

B.2.1.18 Phase centre offset of calibration

Gain is defined at the phase centre of the antenna. If the phase centre of the calibration antenna is not aligned at the centre of the set up during the calibration, then there will be uncertainty related to the measurement distance.

The phase centre of a horn antenna moves with frequency along the taper length of the antenna therefore during the calibration the phase centre of all frequencies will not be aligned with the setup centre. The associated uncertainty term can be estimated using the following formula [14]:

$$\pm 20 \log_{10} \left(\frac{d_m - d_p}{d_m} \right)$$

+/-20log((measurement distance – d)/measurement distance) [14]

Where d_m is the measurement distance and d_p is the maximum positional uncertainty. For a Horn antenna this is equal to 0.5 the length of the taper. This uncertainty is considered to have a rectangular distribution so the standard uncertainty is calculated by dividing the uncertainty by √3.

The same equation applies to log periodic antennas with d_m being 0.5 the length of the boom.

For a dipole antenna, given that the phase centre of the antenna is easily aligned with the centre of the set up the measurement uncertainty is zero.

If the calibration antenna (i.e. horn) is adjusted during the calibration to align the phase centre to the setup centre then this uncertainty term can be considered to be zero.

As an example a horn with a taper length of 50 mm, at 43.5 GHz and a measurement distance of 72.55 cm the uncertainty term is 0.62, with a rectangular distribution the standard uncertainty is 0.358 dB.

For DFF systems this uncertainty contribution must be included.

B.2.1.19 Quality of quiet zone for calibration process

During the calibration process the calibration antenna will be placed at the centre of the quiet zone. Therefore, only point P1 from the procedure outlined in B.2.1.3 needs to be considered for the quality of the quiet zone validation measurement.

For gain calibrations, the standard uncertainty of the EIRP results obtained following the method outlined in clause O.2.8 of [7] shall be used.

B.2.1.20 Standing wave between reference calibration antenna and measurement antenna

This term comes from the amplitude ripple caused by the standing waves between the reference antenna and measurement antenna. This value can be captured by sliding (lambda/4) the reference antenna towards the measurement antenna as the standing waves go in and out of phase causing a ripple in amplitude. The uncertainty term can be derived by performing the standard deviation on the results.

B.2.1.21 Influence of the calibration antenna feed cable (Flexing cables, adapters, attenuators, connector repeatability)

During the calibration measurement a cable (adapters, attenuators) is used to feed the calibration antenna. This uncertainty captures any influence the cable may have on the measurements result. This term can be assessed by repeating measurements while flexing the cables and rotary joints and using the largest difference between the results as the uncertainty. For some calibration test configurations this uncertainty can be considered to be zero.

B.2.1.22 Influence of TRP measurement grid

This contributor describes the uncertainty of the measured TRP value due to the finite number of measurement grid points.

B.2.1.23 Influence of beam peak search grid

This contributor describes the uncertainty of absolute TX power beam peak measurements, e.g., EIRP in beam peak direction, due to the finite number of measurement points in the beam peak search grid.

B.2.1.24 Systematic error due to TRP calculation/quadrature

When calculating TRP using different quadrature of constant step size data, a mean error shall be taken into account. The value of this contributor depends on the number of measurement grid points and the quadrature technique used.

No mean error has to be taken into account for constant density approach (using the charged particle or the golden spiral implementation) for non-sparse antenna arrays.

This measurement uncertainty contributor represents a systematic uncertainty and must not be root sum squared with contributors described by standard deviation.

B.2.1.25 Multiple measurement antenna uncertainty

This contributor describes the uncertainty caused by switching multiple measurement antennas either by mechanically or electrically to measure TRx spurious emission.

A frequency range of spurious tests (e.g. general spurious emission) is defined from 6 GHz to second harmonic of FR2 bands such as 80 GHz. Since that frequency range is quite wide, it is impossible to cover the whole range only by one measurement antenna. Therefore to provide a feature of the spurious emission measurement by FR2 test system, the system has to equip a capability to switch corresponding measurement antennas in an anechoic chamber. One of the mechanical antenna switching methods can be a structure of a slider. Then a repeatability of a bending loss of a feeder cable which is connected to the measurement antennas shall be taken into account. On the other hand for electrical antenna switching, since multiple antennas need to be aligned in a chamber with a different position, the quiet zone characteristics might receive an influence by a displacement from the ideal focal point. In a case of electrical switching system, if the measurement antenna configuration is the same for the quality of the quiet zone measurement and the DUT measurement, then this uncertainty term is encompassed in the quality of the quiet zone results.

B.2.1.26 DUT repositioning

This contributor describes the uncertainty due to a displacement of a DUT. The DUT may need to be re-positioned between measurements, for instance when the battery runs low in charge.

B.2.1.27 Influence of noise

This contributor describes an offset uncertainty factor caused by a noise floor especially in a case of low SNR. This contributor works as a bias to measured results only to a direction to increase values and thus this shall be included in the uncertainty budget table as a systematic uncertainty. The uncertainty value can be derived by the following equation.

$$\text{Influence of noise} = 10 * \log(1 + 10^{\left(\frac{SNR}{10}\right)})$$

B.2.1.28 Systematic error related to beam peak search

When calculating beam peak search a systematic error shall be taken into account. The value of this contributor depends on the number of measurement grid points.

This measurement uncertainty contributor represents a systematic uncertainty and must not be root sum squared with contributors described by standard deviation.

B.2.1.29 Influence of spherical coverage grid

This contributor describes the uncertainty of spherical measurements, due to the finite number of measurement points in the spherical coverage grid.

B.2.1.30 Systematic error related to EIS spherical coverage

When calculating EIS spherical coverage, a mean error shall be taken into account. The value of this contributor depends on the DL power step size used for the EIS search and then number of measurement grid points.

This measurement uncertainty contributor represents a systematic uncertainty and must not be root sum squared with contributors described by standard deviation.

B.2.1.31 Misalignment of DUT due to change of DUT orientation

This contributor describes the uncertainty due to a mis-alignment of a DUT after a change of DUT orientations described in Tables J.2-1 through J.2-3 in [3] during spurious emission and spherical coverage measurements. This contribution is negligible with spherical coverage TC as far as the misalignment is within the accuracy of DUT re-positioning.

B.2.1.32 Additional Impact of Interferer ACLR

This contribution describes the effect of the interferer ACLR over the wanted signal channel when testing ACS and in-band blocking. Even if power is set perfectly in the configured transmission bandwidth, interferer power will leak in the wanted signal channel due to its ACLR.

B.2.1.33 Modulated Interferer uncertainty

Modulated Interferer is used to drive a signal to the horn antenna (via multiple external components such as a switch box, an amplifier and a circulator, etc.) in ACS and In-band Blocking tests either as an absolute level or as a relative level. Receiving device used is typically a UE/phablet/tablet/FWA. Generally, there occurs uncertainty contribution from absolute level accuracy, non-linearity and frequency characteristic of the interferer generator.

For practical reasons, in a case that a VNA is used as calibration equipment, Modulated Interferer is connected to the system after the calibration measurement (Stage 2) is performed by the VNA. Hence, the uncertainty on the absolute level of Modulated Interferer (transmitter device) cannot be assumed as systematic. This uncertainty should be calculated from the manufacturer's data in logs with a rectangular distribution, unless otherwise informed. Furthermore, the uncertainty of the non-linearity is included in the absolute level uncertainty.

B.2.1.34 Void

B.2.1.35 Influence of offset antenna for blocker signal

This MU term describes the additional uncertainty caused by using offset antenna for blocker signal for FR2 blocking test cases. The cause of additional MU using offset antenna is the difference of UE antenna's gain between beam peak direction and offset beam peak direction, which will cause the error for the ACS or IBB performance requirement which

is given by the power ratio of the wanted signal power and blocker signal power. Such difference of the UE antenna gain can be compensated by increasing the blocker signal power by the measured EIS difference at beam peak direction and at offset beam peak. Despite this compensation, there still is a residual error corresponding to the antenna gain difference due to different frequency of wanted and blocker signal. Table B.2.1.35-1 summarizes the residual error after compensation for various offset angle assumption.

Table B.2.1.35-1: Residual error when offset antenna is used for FR2 blocking test

offset angle[deg]	Mean error[dB]	Std.dev[dB]	Mean error[dB]	Std.dev[dB]
	2x8 Assumption		1x4 Assumption	
0	0.000	0.000	0.000	0.000
0.5	0.001	0.001	0.000	0.000
1	0.004	0.003	0.001	0.001
1.5	0.010	0.006	0.002	0.002
2	0.018	0.011	0.004	0.003
2.5	0.028	0.018	0.006	0.004
3	0.041	0.026	0.009	0.006
3.5	0.057	0.036	0.013	0.009
4	0.075	0.048	0.016	0.011
4.5	0.096	0.062	0.021	0.015
5	0.120	0.078	0.026	0.018
5.5	0.147	0.096	0.031	0.022
6	0.178	0.117	0.038	0.026
6.5	0.213	0.142	0.044	0.031
7	0.252	0.170	0.051	0.036
NOTE 1: For MU assessment of the test system, the MU values should be taken from the row corresponding to the test system's offset antenna angle. NOTE 2: Mean error should be counted as systematic offset and Std.dev should be counted as a random uncertainty in the MU budget table. NOTE 3: For PC3 UE testing, the values for 2x8 Assumption should be used. NOTE 4: EIS step size used for compensation should be added as mean error.				

B.2.1.36 Uncertainty of the RF relative power measurement equipment

The receiving device is used to measure the received signal level in the EIRP tests as a relative level. These receiving devices are spectrum analysers, communication analysers, or power meters. The uncertainty value will be indicated in the manufacturer's data sheet. Basically, the linearity and impact of the averaging time needs to be considered in this MU term.

B.2.2 Measurement error contribution descriptions for IFF

B.2.2.1 Positioning misalignment

See B.2.1.1.

The uncertainty value of positioning misalignment is estimated as below table and used across clause B.

Table B.2.2.1-1: Uncertainty value for positioning misalignment for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC5	0.02	Normal	2.00	0.01
PC3, PC6, PC7	0.00	Normal	2.00	0.00

B.2.2.2 Measure distance uncertainty

See B.2.1.2. For IFF, this can be considered to be zero.

The uncertainty value of measure distance uncertainty is estimated as below table and used across clause B.

Table B.2.2.2-1: Uncertainty value for measure distance uncertainty for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	0.00	Rectangular	1.73	0.00

B.2.2.3 Quality of Quiet Zone

See B.2.1.3.

The uncertainty value of quality of quiet zone is estimated as below table and used across clause B.

Table B.2.2.3-1: Uncertainty value for quality of quiet zone for IFF

QZ size	Power class	Condition	Test case	Frequency range	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
All	All	All	ACLR (relative measurement)	FR2a, FR2b, FR2c	0.52	Actual	1.00	0.52
≤30cm	PC1, PC3, PC5, PC6, PC7	NC	NOTE1	FR2a, FR2b	0.6	Actual	1.00	0.6
				FR2c, FR2d	0.7 (NOTE 2)	Actual	1.00	0.7
			NOTE5	FR2a, FR2b	0.7	Actual	1.00	0.7
			NOTE5	FR2c	0.8	Actual	1.00	0.8
			SE	6GHz to 12.75GHz	0.7	Actual	1.00	0.7
				12.75GHz to 23.45GHz	0.6	Actual	1.00	0.6
				23.45GHz to 40.8GHz	0.6	Actual	1.00	0.6
				40.8GHz to 66GHz	0.6	Actual	1.00	0.6
				66GHz to 80GHz	0.6	Actual	1.00	0.6
				80GHz to 87GHz	0.6	Actual	1.00	0.6
		ETC	NOTE1	FR2a, FR2b, FR2c, FR2d	0.9	Actual	1.00	0.9
40cm	PC1, PC3, PC5, PC6, PC7	NC	NOTE1	FR2a, FR2b	0.7 (NOTE 2)	Actual	1.00	0.7
				FR2c, FR2d	0.8 (NOTE 2)	Actual	1.00	0.8
			NOTE6	FR2a, FR2b	0.8 (NOTE 2)	Actual	1.00	0.8
			SE	6GHz to 12.75GHz	1.0 (NOTE 4)	Actual	1.00	1.0
				12.75GHz to 23.45GHz	0.6	Actual	1.00	0.6
				23.45GHz to 40.8GHz	0.6	Actual	1.00	0.6
				40.8GHz to 66GHz	0.6	Actual	1.00	0.6
				66GHz to 80GHz	0.6	Actual	1.00	0.6
				80GHz to 87GHz	0.6	Actual	1.00	0.6
		ETC	NOTE1	FR2a, FR2b	0.9	Actual	1.00	0.9
			NOTE6	FR2a, FR2b	FFS	Actual	1.00	FFS

NOTE 1: The uncertainty in current row applies to maximum output power with EIRP and TRP, EIRP spherical coverage, MPR, configured output power with power boost, minimum output power, transmit OFF power, spectrum emission mask, reference sensitivity, adjacent selectivity, in-band blocking.
NOTE 2: For Uncertainty assessment in tables across clause B and MTSU calculation, QoQZ uncertainty value for QZ ≤ 30cm is used also for 40cm for FR2a through FR2c. For uncertainty assessment in tables across clause B and MTSU calculation for FR2d, QoQZ uncertainty value for QZ size of 40cm is used also for QZ size ≤ 30cm.
NOTE 3: Void
NOTE 4: For Uncertainty assessment in tables across clause B and MTSU calculation, QoQZ uncertainty value for QZ ≤ 30cm is used also for 40cm.
NOTE 5: The uncertainty in current row applies to 2AoA Multi-Rx Spherical coverage measurement for Reference Sensitivity.
NOTE 6: The uncertainty in current row applies to to 2AoA STxMP (Simultaneous Transmission with Multi-Panel) testing with two-layer transmission (i.e., one layer per TCI).

B.2.2.4 Mismatch

See B.2.1.4.

The uncertainty value of mismatch is estimated as below table and used across clause B.

Table B.2.2.4-2: Uncertainty value for mismatch for IFF

QZ size	Power class	Condition	Test case	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement							
<= 30cm	PC1, PC3, PC5, PC6, PC7	NC	Default (FR2a, FR2b)	1.30	Actual	1.00	1.30
			NOTE 1 (FR2a, FR2b)	1.70	Actual	1.00	1.70
			Default (FR2c)	1.70	Actual	1.00	1.70
			NOTE 1 (FR2c)	[1.75]	Actual	1.00	[1.75]
			ACLR (relative measurement) (FR2a, FR2b)	1.84	Actual	1.00	1.84
			ACLR (relative measurement) (FR2c)	2.4	Actual	1.00	2.4
			Tx SE (6GHz to 12.75GHz)	1.5	Actual	1.00	1.5
			Tx SE (12.75GHz to 23.45GHz)	1.5	Actual	1.00	1.5
			Tx SE (23.45GHz to 40.8GHz)	1.4	Actual	1.00	1.4
			Tx SE (40.8GHz to 66GHz)	2.3	Actual	1.00	2.3
			Tx SE (66GHz to 87GHz)	2.3	Actual	1.00	2.3
			Rx SE (6GHz to 12.75GHz)	1.6	Actual	1.00	1.6
			Rx SE (12.75GHz to 23.45GHz)	1.6	Actual	1.00	1.6
			Rx SE (23.45GHz to 40.8GHz)	1.5	Actual	1.00	1.5
			Rx SE (40.8GHz to 66GHz)	2.3	Actual	1.00	2.3
			Rx SE (66GHz to 87GHz)	2.3	Actual	1.00	2.3
		ETC	Default (FR2a, FR2b)	1.30	Actual	1.00	1.30
			NOTE 1 (FR2a, FR2b)	1.70	Actual	1.00	1.70
			Default (FR2c)	1.70	Actual	1.00	1.70
			ACLR (relative measurement) (FR2a, FR2b)	1.84	Actual	1.00	1.84
			ACLR (relative measurement) (FR2c)	2.4	Actual	1.00	2.4
Stage 1: Calibration measurement							
<= 30cm	PC1, PC3, PC5, PC6, PC7	NC	All	0.00	U-shaped	1.41	0.00
		ETC	All	0.00	U-shaped	1.41	0.00

NOTE 1: The uncertainty in current row applies to 2AoA Multi-Rx Spherical coverage measurement for Reference Sensitivity and to 2AoA STxMP (Simultaneous Transmission with Multi-Panel) testing with two-layer transmission (i.e., one layer per TCI).

B.2.2.5 Standing wave between DUT and measurement antenna

See B.2.1.5.

The uncertainty value of standing wave between the DUT and measurement antenna is estimated as below table and used across clause B.

Table B.2.2.5-1: Uncertainty value for standing wave between the DUT and measurement antenna for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	0.00	U-shaped	1.41	0.00

B.2.2.6 Uncertainty of the RF power measurement equipment

See B.2.1.6.

The uncertainty value of RF power measurement equipment is estimated as below table and used across clause B.

Table B.2.2.6-1: Uncertainty value for RF power measurement equipment for IFF

Power class	Test case	Frequency range	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	MOP, MPR, Configured output power with power boost,SEM, ACLR	FR2a, FR2b	2.16	Normal	2.00	1.08
		FR2c	3.60	Normal	2.00	1.80
	Minimum output power, OFF power	FR2a, FR2b	2.50	Normal	2.00	1.25
		FR2c	3.60	Normal	2.00	1.80
	SE	6GHz to 12.75GHz	2.00	Normal	2.00	1.00
		12.75GHz to 23.45GHz	2.16	Normal	2.00	1.08
		23.45GHz to 40.8GHz	2.73	Normal	2.00	1.37
		40.8GHz to 66GHz	4.00	Normal	2.00	2.00
		66GHz to 87GHz	4.00	Normal	2.00	2.00
PC1, PC5	MOP, MPR	FR2a, FR2b (NOTE 1)	2.5	Normal	2.00	1.25
NOTE 1: The uncertainty in current row applies to 2AoA STxMP (Simultaneous Transmission with Multi-Panel) testing with two-layer transmission (i.e., one layer per TCI).						

B.2.2.7 Phase Curvature

See B.2.1.7. For IFF this can be considered to be zero.

The uncertainty value of phase curvature is estimated as below table and used across clause B.

Table B.2.2.7-1: Uncertainty value for phase curvature for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	0.00	U-shaped	1.41	0.00

B.2.2.8 Amplifier Uncertainties

See B.2.1.8.

The uncertainty value of amplifier uncertainties is estimated as below table and used across clause B.

Table B.2.2.8-1: Uncertainty value for amplifier uncertainties for IFF

Power class	Test case	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
PC1, PC5	Default	2.10	Normal	2.00	1.05
	Relative power tolerance	TBD	Rectangular	1.73	TBD
	SE (66GHz to 80GHz)	3.0	Normal	2.00	1.50
PC3, PC7	Default	2.10	Normal	2.00	1.05
	Relative power tolerance	0.5	Rectangular	1.73	0.29
	SE (66GHz to 87GHz)	3.0	Normal	2.00	1.50
PC6	Default	2.10	Normal	2.00	1.05
	Relative power tolerance	TBD	Rectangular	1.73	TBD
	SE (66GHz to 80GHz)	3.0	Normal	2.00	1.50
Stage 1: Calibration measurement					
PC1, PC3, PC5, PC6, PC7	Default	0.00	Normal	2.00	0.00

B.2.2.9 Random uncertainty

See B.2.1.9.

The uncertainty value of random uncertainty is estimated as below table and used across clause B.

Table B.2.2.9-1: Uncertainty value for random uncertainty for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	0.5	Normal	2.00	0.25

B.2.2.10 Influence of XPD

See B.2.1.10.

The uncertainty value of influence of the XPD is estimated as below table and used across clause B.

Table B.2.2.10-2: Uncertainty value for influence of the XPD for IFF

QZ size	Power class	Test case	Frequency range	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
All	All	ACLR	FR2a, FR2b, FR2c	0.00	U-shaped	1.41	0.00
≤30cm	PC1, PC3, PC5, PC6, PC7	Default	FR2a, FR2b, FR2c	0.01	U-shaped	1.41	0.00
		SE	6GHz to 12.75GHz	0.09	U-shaped	1.41	0.064
			12.75GHz to 23.45GHz	0.09	U-shaped	1.41	0.064
			23.45GHz to 40.8GHz	0.01	U-shaped	1.41	0.00
			40.8GHz to 66GHz	0.09	U-shaped	1.41	0.064
			66GHz to 87GHz	0.09	U-shaped	1.41	0.064
40cm	PC1, PC3, PC5, PC6, PC7	Default	FR2a, FR2b, FR2c	0.07 (NOTE 1)	U-shaped	1.41	0.02
		SE	6GHz to 12.75GHz	TBD	U-shaped	1.41	TBD
			12.75GHz to 23.45GHz)	TBD	U-shaped	1.41	TBD
			23.45GHz to 40.8GHz	TBD	U-shaped	1.41	TBD
			40.8GHz to 66GHz	TBD	U-shaped	1.41	TBD
			66GHz to 87GHz	TBD	U-shaped	1.41	TBD
NOTE 1: For Uncertainty assessment in tables across clause B and MTSU calculation, influence of the XPD uncertainty value for QZ ≤ 30cm is used also for 40cm.							

B.2.2.11 Insertion Loss Variation

See B.2.1.11.

The uncertainty value of insertion loss variation is estimated as below table and used across clause B.

Table B.2.2.11-1: Uncertainty value for insertion loss variaion for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement				
PC1, PC3, PC5, PC6, PC7	0.00	Rectangular	1.73	0.00
Stage 1: Calibration measurement				
PC1, PC3, PC5, PC6, PC7	0.00	Rectangular	1.73	0.00

B.2.2.12 RF leakage (from measurement antenna to receiver/transmitter)

See B.2.1.12.

The uncertainty value of RF leakage is estimated as below table and used across clause B.

Table B.2.2.12-1: Uncertainty value for RF leakage for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	0.00	Actual	1.00	0.00

B.2.2.13 Misalignment of positioning system

See B.2.1.13.

The uncertainty value of misalignment of positioning system is estimated as below table and used across clause B.

Table B.2.2.13-1: Uncertainty value for misalignment of positioning system for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	0.00	Normal	2.00	0.00

B.2.2.14 Uncertainty of the Network Analyzer

See B.2.1.14.

The uncertainty value of uncertainty of the network analyzer is estimated as below table and used across clause B.

Table B.2.2.14-1: Uncertainty value for uncertainty of the network analyser for IFF

Power class	Test case	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
All	Default (6GHz to 40.8GHz)	1.50	Normal	2.00	0.75
	SE (40.8GHz to 87GHz)	1.70	Normal	2.00	0.85

B.2.2.15 Uncertainty of the absolute gain of the calibration antenna

See B.2.1.15.

The uncertainty value of uncertainty of the absolute gain of the calibration antenna is estimated as below table and used across clause B.

Table B.2.2.15-1: Uncertainty value for uncertainty of the absolute gain of the calibration antenna for IFF

Power class	Test case	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	Default	0.60	Normal	2.00	0.30
	SE (40.8GHz to 66GHz)	1.70	Normal	2.00	0.85
	SE (66GHz to 87GHz)	1.70	Normal	2.00	0.85

B.2.2.16 Positioning and pointing misalignment between the reference antenna and the measurement antenna

See B.2.1.16.

The uncertainty value of positioning and pointing misalignment between the reference antenna and the measurement antenna is estimated as below table and used across clause B.

Table B.2.2.16-1: Uncertainty value for positioning and pointing misalignment between the reference antenna and the measurement antenna for IFF

Power class	Test case	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	Default	0.01	Rectangular	1.73	0.00
	ACLR	0.00	Rectangular	1.73	0.00
	SE	0.05	Rectangular	1.73	0.03

B.2.2.17 gNB emulator uncertainty

See B.2.1.17.

The uncertainty value of gNB emulator uncertainty is estimated as below table and used across clause B.

Table B.2.2.17-1: Uncertainty value for gNB emulator uncertainty for IFF

Power class	Uncertainty value	Frequency range	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	2.9	FR2a, FR2b	Normal	2.00	1.45
	3.2	FR2a, FR2b (NOTE 1)	Normal	2.00	1.6
	3.6	FR2c	Normal	2.00	1.8
	[3.7]	FR2c (NOTE 1)	Normal	2.00	[1.85]
NOTE 1: The uncertainty in current row applies to 2AoA Multi-Rx Spherical coverage measurement for Reference Sensitivity.					

B.2.2.18 Phase centre offset of calibration

See B.2.1.18. For IFF this can be considered to be zero.

The uncertainty value of phase centre offset of calibration is estimated as below table and used across clause B.

Table B.2.2.18-1: Uncertainty value for phase centre offset of calibration for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	0.00	Rectangular	1.73	0.00

B.2.2.19 Quality of the Quiet Zone for Calibration Process

See B.2.1.19.

The uncertainty value of quality of quiet zone for calibration process is estimated as below table and used across clause B.

Table B.2.2.19-1: Uncertainty value for quiet zone for calibration process for IFF

QZ size	Power class	Condition	Test case	Frequency range	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
All	All	All	ACLR (relative measurement)	FR2a, FR2b, FR2c	0.32	Actual	1.00	0.32
≤ 30cm	PC1, PC3, PC5, PC6, PC7	NC	NOTE1	FR2a, FR2b	0.4	Actual	1.00	0.4
				FR2c, FR2d	0.5	Actual	1.00	0.5
			SE	6GHz to 12.75GHz	0.7	Actual	1.00	0.7
				12.75GHz to 23.45GHz	0.6	Actual	1.00	0.6
				23.45GHz to 40.8GHz	0.6	Actual	1.00	0.6
				40.8GHz to 66GHz	0.6	Actual	1.00	0.6
				66GHz to 80GHz	0.6	Actual	1.00	0.6
				80GHz to 87GHz	0.6	Actual	1.00	0.6
		ETC	NOTE1	FR2a, FR2b, FR2c, FR2d	0.6	Actual	1.00	0.6
40cm	PC1, PC3, PC5, PC6, PC7	NC	NOTE1	FR2a, FR2b	0.4	Actual	1.00	0.4
				FR2c, FR2d	0.5	Actual	1.00	0.5
			SE	6GHz to 12.75GHz	1.0 (Note 3)	Actual	1.00	1.0
				12.75GHz to 23.45GHz	0.6	Actual	1.00	0.6
				23.45GHz to 40.8GHz	0.6	Actual	1.00	0.6
				40.8GHz to 66GHz	0.6	Actual	1.00	0.6
				66GHz to 80GHz	0.6	Actual	1.00	0.6
				80GHz to 87GHz	0.6	Actual	1.00	0.6
		ETC	NOTE 1	FR2a, FR2b, FR2c, FR2d	0.6	Actual	1.00	0.6

NOTE 1: The uncertainty in current row applies to maximum output power with EIRP and TRP, EIRP spherical coverage, MPR, configured output power with power boost, minimum output power, transmit OFF power, spectrum emission mask, reference sensitivity, adjacent selectivity, in-band blocking.
NOTE 2: Void
NOTE 3: For Uncertainty assessment in tables across clause B and MTSU calculation, QoQZ uncertainty value for QZ ≤ 30cm is used also for 40cm.

B.2.2.20 Standing wave between reference calibration antenna and measurement antenna

See B.2.1.20.

The uncertainty value of standing wave between reference calibration antenna and measurement antenna is estimated as below table and used across clause B.

Table B.2.2.20-1: Uncertainty value for standing wave between reference calibration antenna and measurement antenna for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	0.00	U-shaped	1.41	0.00

B.2.2.21 Influence of the calibration antenna feed cable (Flexing cables, adapters, attenuators, connector repeatability)

See B.2.1.21.

The uncertainty value of influence of the calibration antenna feed cable is estimated as below table and used across clause B.

Table B.2.2.21-1: Uncertainty value for influence of the calibration antenna feed cable for IFF

Power class	Test case	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	Default (FR2a,FR2b,FR2c)	0.14	Normal	2.00	0.07
	ACLR (FR2a,FR2b,FR2c)	0.00	Normal	2.00	0.00
	SE (40.8GHz to 66GHz)	0.28	Normal	2.00	0.14
	SE (66GHz to 87GHz)	0.28	Normal	2.00	0.14

B.2.2.22 Influence of TRP measurement grid

See B.2.1.22.

The uncertainty value of influence of TRP measurement grid is estimated as below table and used across clause B.

Table B.2.2.22-1: Uncertainty value for influence of TRP measurement grid for IFF

Power class	Test case	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC5 (Note 1)	Default	0.25	Actual	1.00	0.25
	SE	0.25	Actual	1.00	0.25
PC3, PC7	Default	0.25	Actual	1.00	0.25
	SE	0.32	Actual	1.00	0.32
PC6	Default	0.25	Actual	1.00	0.25
	SE	0.25	Actual	1.00	0.25
Note 1: A finer measurement grid for SE (when compared to default) is required near the harmonic region, i.e., a constant-step size grid with 2522 unique grid points ($\Delta\theta=\Delta\phi=5°$) or a constant-density grid with 1600 grid points.					

B.2.2.23 Influence of beam peak search grid

See B.2.1.23.

The uncertainty value of influence of beam peak search grid is estimated as below table and used across clause B.

Table B.2.2.23-1: Uncertainty value for influence of beam peak search grid for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6, PC7	0.00	Actual	1.00	0.00

B.2.2.24 Systematic error due to TRP calculation/quadrature

See B.2.1.24.

The uncertainty value of systematic error due to TRP calculation/quadrature is estimated as below table and used across clause B.

Table B.2.2.24-1: Uncertainty value for systematic error due to TRP calculation/quadrature for IFF

Power class	Uncertainty value
PC1, PC3, PC5, PC6, PC7	0.00

B.2.2.25 Multiple measurement antenna uncertainty

See B.2.1.25.

The uncertainty value of multiple measurement antenna uncertainty is estimated as below table and used across clause B.

Table B.2.2.25-1: Uncertainty value for multiple measurement antenna uncertainty for IFF

Power class	Test case	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC3, PC5, PC6	Default	0.15	Actual	1.00	0.15
	ACLR	0.00	Actual	1.00	0.00

B.2.2.26 DUT repositioning

See B.2.1.26.

The uncertainty value of DUT repositioning is estimated as below table and used across clause B.

Table B.2.2.26-1: Uncertainty value for DUT repositioning for IFF

Power class	Test case	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC5	TRP, spherical coverage	0.00	Rectangular	1.73	0.00
	EIRP, EIS	0.35	Rectangular	1.73	0.20
PC3, PC6, PC7	TRP, spherical coverage	0.00	Rectangular	1.73	0.00
	EIRP, EIS	0.08	Rectangular	1.73	0.05
PC3	2AoA Multi-Rx Spherical coverage	[0.00]	Rectangular	1.73	[0.00]

B.2.2.27 Influence of noise

See B.2.1.27.

The uncertainty value of influence of noise is estimated as below table and used across clause B.

Editor's Note: For ACLR, all applicable configurations need to be added.

Table B.2.2.27-1: Uncertainty value for influence of noise for PC3, SISO for IFF

Test case	Frequency range	Noise floor	Minimum requirement	Estimated SNR_{total} [dB/400MHz]	Relaxation	Influence of noise
MOP-EIRP	FR2a	N/A	20.7dBm/ChBW (22.4-1.7)	16.33 (NOTE 1)	0	0.1
	FR2b	N/A	18.9dBm/ChBW (20.6-1.7)	11.45 (NOTE 1)	0	0.3
	FR2c	N/A	18.2dBm/ChBW (18.7-0.5)	11.45 (NOTE 1)	0	0.3
MOP-TRP	FR2a	N/A	23dBm/ChBW	16.33 (NOTE 1)	0	0.1
	FR2b, FR2c	N/A	23dBm/ChBW	11.45 (NOTE 1)	0	0.3
MOP-Spherical	FR2a	N/A	9.75dBm/ChBW (Spherical – MBR= 11.5-1.75)	11.45 (NOTE 1)	0	0.3
	FR2b	N/A	7.6dBm/ChBW (Spherical – MBR=8-0.4)	6.37 (NOTE 1)	0	0.9
	FR2c	N/A	5.4dBm/ChBW (Spherical – MBR=5.8-0.4)	5.86 (NOTE 1)	0	1.0
MPR	FR2a	-7.6dBm/400MHz	7.65dBm/ChBW (EIRP-MPB-MPR-T(MPR)=22.4-0.75-9-5)	15.17 (NOTE 1)	0	0.13
	FR2b	-5.5dBm/400MHz	5.85dBm/ChBW (EIRP-MPB-MPR-T(MPR)=20.6-0.75-9-5)	11.30 (NOTE 1)	0	0.31
	FR2c	-4.5dBm/400MHz	4.2dBm/ChBW (EIRP-MPB-MPR-T(MPR)=18.7-0.5-9-5)	8.70 (NOTE 1)	0	0.55
Configured output power with power boost	FR2a	N/A	21.7dBm/ChBW (22.4-1.7+1)	16.33 (NOTE 1)	0	0.1
	FR2b	N/A	19.9dBm/ChBW (20.6-1.7+1)	11.45 (NOTE 1)	0	0.3
Minimum output power	FR2a	-10.6dBm/400MHz	-13dBm	-2.54 (NOTE 1)	8.4	1.0 (with relaxation)
	FR2b	-5.5dBm/400MHz	-13dBm	-7.64 (NOTE 1)	13.5	1.0 (with relaxation)
	FR2c	-4.5dBm/400MHz	-13dBm	-8.64 (NOTE 1)	14.5	1.0 (with relaxation)
OFF power – TRP	FR2a	-10.6dBm/400MHz	-35dBm/ChBW	-24.54 (NOTE 2)	30.4	1.0 (with relaxation)
	FR2b	-5.5dBm/400MHz		-29.64 (NOTE 2)	35.5	1.0 (with relaxation)
	FR2c	-4.5dBm/400MHz		-30.64 (NOTE 2)	36.5	1.0 (with relaxation)
OFF power – EIRP	FR2a	-7.6dBm/400MHz	-30dBm/ChBW	-22.54 (NOTE 2)	EIRP + 8dB	1.0 (with relaxation)
	FR2b	-5.5dBm/400MHz		-24.64 (NOTE 2)	EIRP + 11dB	1.0 (with relaxation)
	FR2c	[-4.5]dBm/400MHz		[-25.64] (NOTE 2)	TBD	[1.0] (with relaxation)
Absolute power tolerance	Same as Minimum output power					
	FR2a	-13.6dBm/100MHz	-7.6dBm/100MHz	5.86 (NOTE 1)	0	1.0

Relative power tolerance	FR2b	-11.5dBm/100MHz	-5.5dBm/100MHz	5.86 (NOTE 1)	0	1.0
Aggregate power tolerance	Same as Relative power tolerance					
Aggregate power tolerance	FR2a	-13.6dBm/100MHz	-7.6dBm/100MHz	5.86 (NOTE 1)	0	1.0
	FR2b	-11.5dBm/100MHz	-5.5dBm/100MHz	5.86 (NOTE 1)	0	1.0
Carrier Leakage	FR2a	-7.6dBm/400MHz	-18.5dBm (Preq + MU – RelativeLimit = 0 + 6.15 – 25)	13.3 (NOTE 1)	0	0.2
	FR2b	-5.5dBm/400MHz		11.1 (NOTE 1)	0	0.33
SEM	FR2a	N/A	-13dBm/1MHz	8.14 (NOTE 1)	0	0.62
	FR2b, FR2c	N/A		5.86 (NOTE 1)	0	1.0
ACLR (CP)	FR2a	-7.6dBm/400MHz	Highest testable MPR for 400MHz: 3dB 16.65dBm/ChBW (EIRP-MPB-MPR-T(MPR) =22.4-0.75-3-2) Actual lowest: 7.65dBm/ChBW (EIRP-MPB-MPR-T(MPR)=22.4-0.75-9-5)	22.86 (with 3dB MPR) (NOTE 1)	0	N/A
	FR2b	-5.5dBm/400MHz	Highest testable MPR for 400MHz: 2dB 16.35dBm/ChBW (EIRP-MPB-MPR-T(MPR) =20.6-0.75-2-1.5) Actual lowest: 5.85dBm/ChBW (EIRP-MPB-MPR-T(MPR)=20.6-0.75-9-5)	21.86 (with 2dB MPR) (NOTE 1)	0	N/A
	FR2c	-4.5dBm/400MHz	Highest testable MPR for 400MHz: 0dB 18.2dBm/ChBW (EIRP-MPB-MPR-T(MPR) =18.7-0.5-0-0) Actual lowest: 4.2dBm/ChBW (EIRP-MPB-MPR-T(MPR)=18.7-0.5-9-5)	22.71 (with 0dB MPR) (NOTE 1)	0	N/A

ACLR (ACP)	FR2a	-7.6dBm/400MHz	Highest testable MPR for 400MHz: 3dB -0.35dBm/ChBW (EIRP-MPB-MPR-T(MPR)-ACLR=22.4-0.75-3-2-17) Actual lowest: -9.35 dBm/ChBW (EIRP-MPB-MPR-T(MPR)-ACLR=22.4-0.75-9-5-17)	5.86 (NOTE 1)	0	1.0
	FR2b	-5.5dBm/400MHz	Highest testable MPR for 400MHz: 2dB 0.35dBm/ChBW (EIRP-MPB-MPR-T(MPR)-ACLR=20.6-0.75-2-1.5-16) Actual lowest: -10.15 dBm/ChBW (EIRP-MPB-MPR-T(MPR)-ACLR=20.6-0.75-9-5-16)	5.86 (with 2dB MPR) (NOTE 1)	0	1.0
	FR2c	-4.5dBm/400MHz	Highest testable MPR for 400MHz: 0dB 2.2dBm/ChBW (EIRP-MPB-MPR-T(MPR)-ACLR=18.7-0.5-0-0-16) Actual lowest: -11.8dBm/ChBW (EIRP-MPB-MPR-T(MPR)-ACLR=18.7-0.5-9-5-16)	6.71 (with 0dB MPR) (NOTE 1)	0	1.14
General Tx spurious	6GHz <=f<=23.45GHz	N/A	-13dBm/1MHz	10.0 (NOTE 1)	0	0.41
	23.45GHz<=f<=40GHz	N/A	-13dBm/1MHz	10.0 (NOTE 1)	0	
	40GHz<=f<=80GHz	N/A	-13dBm/1MHz	10.0 (NOTE 1)	0	
	80GHz<f<=87GHz	N/A	-13dBm/1MHz	6.8 (NOTE 1)	0	0.83
Tx spurious Co-existence	n260 (Aggressor band : n257, n261)	-23	-2dBm/100MHz (-22dBm/MHz)	0.86 (NOTE 2)	5	1.0 (with relaxation)
	n257, n261 (Aggressor band : n260)	-27.7	-5dBm/100MHz (-25dBm/MHz)	2.56 (NOTE 2)	3.3	1.0 (with relaxation)
	23.6 GHz ≤ f ≤ 24.0GHz	-27.7	1dBm/200MHz (-22 dBm/MHz)	5.56 (NOTE 2)	0.3	1.0 (with relaxation)
	36 GHz ≤ f ≤ 37GHz	-23dBm/MHz	7dBm/1000MHz (-23dBm/MHz)	-0.14 (NOTE 2)	6	1.0 (with relaxation)
	57 GHz ≤ f ≤ 66GHz	N/A	2dBm/100MHz (-18dBm/MHz)	5.86 (NOTE 1)	0	1.0

Additional spurious emission	NS_202 (7.25GHz <=f <=12.75GHz)	-40 dBm/MHz	-10dBm/100MHz (-30 dBm/MHz)	10 (NOTE 1)	0	0.41
	NS_202 (12.75GHz <=f <=23.45GHz)	-23 dBm/MHz	-10dBm/100MHz (-30 dBm/MHz)	-7.14 (NOTE 2)	13	1.0 (with relaxation)
	NS_202, NS_205 (23.6GHz <=f <=24.0GHz)	-27.7 dBm/MHz	-5dBm/200MHz (-28 dBm/MHz)	-0.44 (NOTE 2)	6.3	1.0 (with relaxation)
	NS_202 (23.45GHz <=f <=40.8GHz)	-23 dBm/MHz	-10dBm/100MHz (-30 dBm/MHz)	-7.14 (NOTE 2)	13	1.0 (with relaxation)
	NS_202 (40.8GHz <=f <=66GHz)	-23 dBm/MHz	-10dBm/100MHz (-30 dBm/MHz)	-7.14 (NOTE 2)	13	1.0 (with relaxation)
	NS_203 (23.6GHz <=f <=24.0GHz)	-27.7 dBm/MHz	+1dBm/200MHz (-22dBm/MHz)	5.56 (NOTE 2)	0.3	1.0 (with relaxation)
Rx spurious	6GHz <=f<=20GHz		-47dBm/1MHz	-2.2 (NOTE 3)	10.2	1.0 dB for 23.45~40.8GHz and 80~87 GHz, 0.64dB for 6~23.45 and 40.8~80 GHz.
	20GHz<=f<=40GHz		-47dBm/1MHz	-11.34 (NOTE 2)	17.2	
	40GHz<=f<=80GHz		-47dBm/1MHz	-25.1 (NOTE 3)	33.1	
	80GHz<f<=87GHz		-47dBm/1MHz	-27.1 (NOTE 2)	33.1	

NOTE 1: Estimated SNR is calculated based on agreed influence of noise.
NOTE 2: Estimated SNR is calculated based on agreed relaxation value: Estimated SNR = 6dB - relaxation.
NOTE 3: Estimated SNR is calculated based on agreed relaxation value: Estimated SNR = 8dB - relaxation.

Table B.2.2.27-1a: Uncertainty value for influence of noise for PC3, MIMO for IFF

Test case	Frequency range	Noise floor	Minimum requirement	Estimated SNR_{total} [dB/400MHz]	Relaxation	Influence of noise
MOP-EIRP	FR2a	N/A	22.4 dBm/ChBW	16.33 (NOTE 1)	0	0.1
	FR2b	N/A	20.6 dBm/ChBW	11.45 (NOTE 1)	0	0.3
	FR2c	N/A	18.7 dBm/ChBW	11.45 (NOTE 1)	0	0.3
MPR	FR2a	-7.6dBm/400MHz	7.65dBm/ChBW (EIRP-MPB-MPR-T(MPR)=22.4-0.75-9-5)	15.17 (NOTE 1)	0	0.13
	FR2b	-5.5dBm/400MHz	5.85dBm/ChBW (EIRP-MPB-MPR-T(MPR)=20.6-0.75-9-5)	11.30 (NOTE 1)	0	0.31
	FR2c	-4.5dBm/400MHz	4.2dBm/ChBW (EIRP-MPB-MPR-T(MPR)=18.7-0.5-9-5)	8.70 (NOTE 1)	0	0.55
MOP-TRP	FR2a	N/A	23 dBm/ChBW	16.33 (NOTE 1)	0	0.1
	FR2b, FR2c	N/A	23 dBm/ChBW	11.45 (NOTE 1)	0	0.3
MOP-Spherical	FR2a	N/A	11.5 dBm/ChBW	11.45 (NOTE 1)	0	0.3
	FR2b	N/A	8 dBm/ChBW	6.37 (NOTE 1)	0	0.9
Minimum output power	FR2a	-10.6dBm/400MHz	-10 dBm	-0.46 (NOTE 1)	5.4	1.0 (with relaxation)
	FR2b	-5.5dBm/400MHz	-10 dBm	-4.64 (NOTE 1)	10.5	1.0 (with relaxation)
OFF power – TRP	FR2a	-10.6dBm/400MHz	-35dBm/ChBW	-24.54 (NOTE 2)	30.4	1.0 (with relaxation)
	FR2b	-5.5dBm/400MHz		-29.64 (NOTE 2)	35.5	1.0 (with relaxation)
SEM	FR2a	N/A	-13dBm/1MHz	8.14 (NOTE 1)	0	0.62
	FR2b, FR2c	N/A		5.86 (NOTE 1)	0	1.0
ACLR (CP)	FR2a	-7.6dBm/400MHz	Highest testable MPR for 400MHz: 3dB 16.65dBm/ChBW (EIRP-MPB-MPR-T(MPR) =22.4-0.75-3-2) Actual lowest: 7.65dBm/ChBW (EIRP-MPB-MPR-T(MPR)=22.4-0.75-9-5)	22.86 (with 3dB MPR) (NOTE 1)	0	N/A

	FR2b	-5.5dBm/400MHz	Highest testable MPR for 400MHz: 2dB 16.35dBm/ChBW (EIRP-MPB-MPR-T(MPR) =20.6-0.75-2-1.5) Actual lowest: 5.85dBm/ChBW (EIRP-MPB-MPR-T(MPR)=20.6-0.75-9-5)	21.86 (with 2dB MPR) (NOTE 1)	0	N/A
ACLR (ACP)	FR2a	-7.6dBm/400MHz	Highest testable MPR for 400MHz: 3dB -0.35dBm/ChBW (EIRP-MPB-MPR-T(MPR)-ACLR=22.4-0.75-3-2-17) Actual lowest: -9.35 dBm/ChBW (EIRP-MPB-MPR-T(MPR)-ACLR=22.4-0.75-9-5-17)	5.86 (NOTE 1)	0	1.0
	FR2b	-5.5dBm/400MHz	Highest testable MPR for 400MHz: 2dB 0.35dBm/ChBW (EIRP-MPB-MPR-T(MPR)-ACLR=20.6-0.75-2-1.5-16) Actual lowest: -10.15 dBm/ChBW (EIRP-MPB-MPR-T(MPR)-ACLR=20.6-0.75-9-5-16)	5.86 (with 2dB MPR) (NOTE 1)	0	1.0
General Tx spurious	Same as SISO in Table B.2.2.27-1					
Tx spurious Co-existence	Same as SISO in Table B.2.2.27-1					
Additional spurious emission	Same as SISO in Table B.2.2.27-1					
NOTE 1: Estimated SNR is calculated based on agreed influence of noise.						

Table B.2.2.27-2: Uncertainty value for influence of noise for PC1, SISO for IFF

Test case	Frequency range	Relaxation [dB]	Influence of noise [dB]
MOP-EIRP	FR2a	0	0.13
	FR2b	0	0.2
MOP-TRP	FR2a	0	0.13
	FR2b	0	0.27
MOP-Spherical	FR2a	0	0.2
	FR2b	0	0.35
MPR	FR2a	0	0.13
	FR2b	0	0.3
Minimum output power	FR2a	0	0.3
	FR2b	0	0.6
OFF power – TRP	FR2a	Same as defined for PC3 in Table B.2.2.27-1	
	FR2b	Same as defined for PC3 in Table B.2.2.27-1	
SEM	FR2a	0	1.81 (NOTE 1, 2)
	FR2b	0	TBD
ACLR (ACP)	FR2a	0	0.95
	FR2b	0	0.95
General Tx spurious	6GHz <=f<12.75GHz	Same as defined for PC3 in Table B.2.2.27-1	
	12.75GHz<=f<66GHz	0	1.08 (NOTE 1, 3)
	66GHz<=f<=80GHz	Same as defined for PC3 in Table B.2.2.27-1	
Tx spurious Co-existence	n260 (Aggressor band : n257, n261)	5 (Same as PC3)	2.34 (NOTE 1, 4)
	n257, n261 (Aggressor band : n260)	3.3 (Same as PC3)	2.34 (NOTE 1, 4)
	23.6 GHz ≤ f ≤ 24.0GHz	0.3 (Same as PC3)	2.34 (NOTE 1, 4)
	57 GHz ≤ f ≤ 66GHz	Same as defined for PC3 in Table B.2.2.27-1	
Additional spurious emission	NS_202 (7.25GHz <=f <=12.75GHz)	Same as defined for PC3 in Table B.2.2.27-1	
	NS_202 (12.75GHz <=f <=23.45GHz)	13 (Same as PC3)	2.34 (NOTE 1, 4)
	NS_202, NS_205 (23.6 GHz ≤ f ≤ 24.0GHz)	6.3 (Same as PC3)	2.34 (NOTE 1, 4)
	NS_203 (23.6 GHz ≤ f ≤ 24.0GHz)	0.3 (Same as PC3)	2.34 (NOTE 1, 4)
	NS_202 (23.45GHz <=f <=40.8GHz)	13 (Same as PC3)	2.34 (NOTE 1, 4)
	NS_202 (40.8GHz <=f <=66GHz)	13 (Same as PC3)	2.34 (NOTE 1, 4)
Rx spurious	6GHz <=f<=20GHz	Same as defined for PC3 in Table B.2.2.27-1	
	20GHz<=f<=40GHz	Same as defined for PC3 in Table B.2.2.27-1	
	40GHz<=f<=80GHz	Same as defined for PC3 in Table B.2.2.27-1	

NOTE 1: values assuming up to 6% of grid points with EIRP > 43dBm.
NOTE 2: values assuming SNR = -7.9dB for points with EIRP > 43dBm / SNR = 8.14dB otherwise.
NOTE 3: values assuming SNR = -5dB for points with EIRP > 43dBm / SNR = 10dB otherwise.
NOTE 4: values assuming SNR = -9dB for points with EIRP > 43dBm / SNR = 6dB otherwise and considering the proposed relaxation.

Table B.2.2.27-2a: Uncertainty value for influence of noise for PC1, MIMO for IFF

Test case	Frequency range	Relaxation [dB]	Influence of noise [dB]
MOP-EIRP	FR2a	0	0.13
	FR2b	0	0.2
MOP-TRP	FR2a	0	0.13
	FR2b	0	0.27
MOP-Spherical	FR2a	0	0.2
	FR2b	0	0.35
MPR	FR2a	0	0.13
	FR2b	0	0.3
Minimum output power	FR2a	0	0.15
	FR2b	0	0.3
SEM	FR2a	0	1.81 (NOTE 1, 2)
	FR2b	0	TBD
ACLR (ACP)	FR2a	0	0.95
	FR2b	0	0.95
General Tx spurious	Same as SISO in Table B.2.2.27-2		
Tx spurious Co-existence	Same as SISO in Table B.2.2.27-2		
Additional spurious emission	Same as SISO in Table B.2.2.27-2		

Table B.2.2.27-2b: Uncertainty value for influence of noise for PC1, 2AoA STxMP for IFF

Test case	Frequency range	Relaxation [dB]	Influence of noise [dB]
MOP-EIRP	FR2a	0	0.26
	FR2b	0	0.39
MOP-TRP	FR2a	0	0.26
	FR2b	0	0.52
MPR	FR2a	0	0.26
	FR2b	0	0.58

Table B.2.2.27-3: Uncertainty value for influence of noise for PC5 and PC6, SISO for IFF

Test case	Frequency range	Relaxation [dB]	Influence of noise [dB]
MOP-EIRP	FR2a	0	0.13
MOP-TRP	FR2a	0	0.13
MOP-Spherical	FR2a	0	0.2
MPR	FR2a	0	0.13
Minimum output power	FR2a	1.4dB for 400MHz 0dB otherwise	1
OFF power – TRP	FR2a	Same as defined for PC3 in Table B.2.2.27-1	
SEM	FR2a	Same as defined for PC3 in Table B.2.2.27-1	
ACLR (ACP)	FR2a	0	0.95
General Tx spurious	6GHz <=f<12.75GHz	Same as defined for PC3 in Table B.2.2.27-1	
	12.75GHz<=f<66GHz	Same as defined for PC3 in Table B.2.2.27-1	
	66GHz<=f<=80GHz	Same as defined for PC3 in Table B.2.2.27-1	
Tx spurious Co-existence	n260 (Aggressor band : n257, n258)	Same as defined for PC3 in Table B.2.2.27-1	
	23.6 GHz ≤ f ≤ 24.0GHz	Same as defined for PC3 in Table B.2.2.27-1	
	57 GHz ≤ f ≤ 66GHz	Same as defined for PC3 in Table B.2.2.27-1	
Additional spurious emission	NS_202 (7.25GHz <=f <=12.75GHz)	Same as defined for PC3 in Table B.2.2.27-1	
	NS_202 (12.75GHz <=f <=23.45GHz)	Same as defined for PC3 in Table B.2.2.27-1	
	NS_202, NS_205 (23.6 GHz ≤ f ≤ 24.0GHz)	Same as defined for PC3 in Table B.2.2.27-1	
	NS_203 (23.6 GHz ≤ f ≤ 24.0GHz)	Same as defined for PC3 in Table B.2.2.27-1	
	NS_202 (23.45GHz <=f <=40.8GHz)	Same as defined for PC3 in Table B.2.2.27-1	
	NS_202 (40.8GHz <=f <=66GHz)	Same as defined for PC3 in Table B.2.2.27-1	
Rx spurious	6GHz <=f<12.75GHz	Same as defined for PC3 in Table B.2.2.27-1	
	12.75GHz<=f<66GHz	Same as defined for PC3 in Table B.2.2.27-1	
	66GHz<=f<=80GHz	Same as defined for PC3 in Table B.2.2.27-1	

Table B.2.2.27-3a: Uncertainty value for influence of noise for PC5 and PC6, MIMO for IFF

Test case	Frequency range	Relaxation [dB]	Influence of noise [dB]
MOP-EIRP	FR2a	0	0.13
MOP-TRP	FR2a	0	0.13
MOP-Spherical	FR2a	0	0.2
MPR	FR2a	0	0.13
Minimum output power	FR2a	1.4dB for 400MHz 0dB otherwise	1
ACLR (ACP)	FR2a	0	0.95

Table B.2.2.27-3b: Uncertainty value for influence of noise for PC5, 2AoA STxMP for IFF

Test case	Frequency range	Relaxation [dB]	Influence of noise [dB]
MOP-EIRP	FR2a	0	0.26
MOP-TRP	FR2a	0	0.26
MPR	FR2a	0	0.26

Table B.2.2.27-4: Void

Table B.2.2.27-5: Uncertainty value for influence of noise for PC7, SISO for IFF

Test case	Frequency range	Relaxation [dB]	Influence of noise [dB]
MOP-EIRP	FR2a	Same as defined for PC3 in Table B.2.2.27-1	
MOP-TRP	FR2a	Same as defined for PC3 in Table B.2.2.27-1	
MOP-Spherical	FR2a	Same as defined for PC3 in Table B.2.2.27-1	
MPR	FR2a	Same as defined for PC3 in Table B.2.2.27-1	
Minimum output power	FR2a	Same as defined for PC3 in Table B.2.2.27-1	
Carrier Leakage	FR2a	Same as defined for PC3 in Table B.2.2.27-1	

B.2.2.28 Systematic error related to beam peak search

See B.2.1.28.

The uncertainty value of systematic error related to beam peak search is estimated as below table and used across clause B.

Table B.2.2.28-1: Uncertainty value for systematic error related to beam peak search for IFF

Power class	Test case	Uncertainty value
PC1, PC5, PC6	Default	0.7
PC1, PC5	NOTE 1	0.0
PC3, PC7	Default	0.5
NOTE 1: The uncertainty in current row applies to 2AoA STxMP (Simultaneous Transmission with Multi-Panel) testing with two-layer transmission (i.e., one layer per TCI). In this case, the error due to finite testing directions can be handled in test tolerance.		

B.2.2.29 Influence of spherical coverage grid

See B.2.1.29.

The uncertainty value of influence of spherical coverage grid is estimated as below table and used across clause B.

Table B.2.2.29-1: Uncertainty value for influence of spherical coverage grid for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC5	0.13	Actual	1.00	0.13
PC3, PC7	0.12	Actual	1.00	0.12
PC3 (NOTE 1)	[0.12]	Actual	1.00	[0.12]
PC6	N/A	Actual	1.00	N/A
NOTE 1: The uncertainty in current row applies to 2AoA Multi-Rx Spherical coverage measurement for Reference Sensitivity.				

B.2.2.30 Systematic error related to EIS spherical coverage

See B.2.1.30.

The uncertainty value of systematic error related to EIS spherical coverage is estimated as below table and used across clause B.

Table B.2.2.30-1: Uncertainty value for systematic error related to EIS spherical coverage for IFF

Power class	Uncertainty value
PC1, PC5	DL power step size, 0.2
PC3, PC7	DL power step size, 0.2
PC6	DL power step size, 0.2

B.2.2.31 Misalignment of DUT due to change of DUT orientation

See B.2.1.31.

The uncertainty value of misalignment of DUT due to change of DUT orientation is estimated as below table and used across clause B.

Table B.2.2.31-1: Uncertainty value for misalignment of DUT due to change of DUT orientation for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC5	0.10	Actual	1.00	0.10
PC3, PC7	0.10	Actual	1.00	0.10
PC6	0.10	Actual	1.00	0.10

B.2.2.32 Additional Impact of Interferer ACLR

See B.2.1.32.

The uncertainty value of additional Impact of Interferer ACLR is estimated as below table and used across clause B.

Table B.2.2.32-1: Uncertainty value for additional Impact of Interferer ACLR for IFF

Power class	Uncertainty value
PC1, PC3, PC5, PC6, PC7	0.7

B.2.2.33 Modulated Interferer uncertainty

See B.2.1.33.

The uncertainty value of modulated Interferer uncertainty is estimated as below table and used across clause B.

Table B.2.2.33-1: Uncertainty value for modulated Interferer uncertainty for IFF

Power class	Uncertainty value	Frequency range	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1, PC5	2.9	FR2a, FR2b	Normal	2.00	1.45
PC3, PC7	2.9	FR2a, FR2b	Normal	2.00	1.45
	3.6	FR2c	Normal	2.00	1.8
PC6	2.9	FR2a, FR2b	Normal	2.00	1.45

B.2.2.34 Void

B.2.2.35 Influence of offset antenna for blocker signal

See B.2.1.35.

B.2.2.36 Uncertainty of the RF relative power measurement equipment

See B.2.1.36.

The uncertainty value of uncertainty of the RF relative power measurement equipment is estimated as below table and used across clause B.

Table B.2.2.36-1: Uncertainty value for uncertainty of the RF relative power measurement equipment for IFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC1	TBD	Normal	2	TBD
PC3, PC7	[0.4]	Normal	2	[0.2]
PC6	TBD	Normal	2	TBD

B.2.3 Measurement error contribution descriptions for NFTF

B.2.3.1 Axes Alignment

Includes the following mechanical alignment errors:

- The uncertainty related with the lateral displacement between the horizontal and vertical axes of the DUT positioner.
- The differences from 90° of the angle between the horizontal and vertical axes.
- The horizontal mis-pointing of the horizontal axis to the probe reference point for Theta=0°.

These mechanical errors can result in sampling the field on a non-ideal sphere. This uncertainty can be considered to have a normal distribution.

B.2.3.2 Measurement Distance uncertainty

See B.2.1.2.

B.2.3.3 Quality of the Quiet Zone

See B.2.1.3.

B.2.3.4 Mismatch

See B.2.1.4.

B.2.3.5 Multiple Reflections: Coupling Measurement Antenna and DUT

The multiple reflections occur when a portion of the transmitted signal is reflected form the receiving antenna back to the transmitting antenna and re-reflected by the transmitting antenna back to the receiving antenna. This uncertainty can

be determined by multiple measurements of the DUT when at different distance from the probes. This uncertainty is assumed to have a U-shaped distribution.

B.2.3.6 Uncertainty of the RF power measurement equipment

See B.2.1.6.

B.2.3.7 Phase curvature

See B.2.1.7.

B.2.3.8 Amplifier uncertainties

See B.2.1.8.

B.2.3.9 Random uncertainty

See B.2.1.9.

B.2.3.10 Influence of the XPD

Refer to B.2.1.10. If the Probe Polarization Amplitude and Phase is measured and corrected for then this uncertainty term can be considered to be zero.

B.2.3.11 NF to FF truncation

The measured near field is expanded using a finite set of spherical modes. The number of modes is linked to number of samples. The filtering effect generated by the finite number of modes can improve measurement results by removing signals from outside the physical area of the DUT. Care must be taken in order to make sure the removed signals are not from the DUT itself. This term also includes the uncertainty related to the scan area truncation. This uncertainty is usually negligible. This uncertainty is assumed to have a normal distribution.

B.2.3.12 Probe Polarization Amplitude and Phase

The amplitude and phase of the probe polarization coefficients should be measured. This uncertainty is assumed to have a normal distribution.

B.2.3.13 Probe Array Uniformity (for multi-probe systems only)

This is the uncertainty due to the fact that different probes are used for each physical position. Different probes have different radiation patterns. Generally, the probe array is calibrated so that the uniformity of the probes is achieved. This uncertainty term must be considered if the amplitude and phase of each probe is not identical or corrected for. This uncertainty is assumed to have a normal distribution

B.2.3.14 Uncertainty of the Network Analyzer

See B.2.1.14.

B.2.3.15 Uncertainty of the absolute gain of the calibration antenna

See B.2.1.15.

B.2.3.16 Phase Recovery Non-Linearity over signal bandwidth

This uncertainty originates from the non-linearity of the phase recovery for wide band signal. The phase recovery can be due to either phase non-linearity of the receiver and/or the DUT itself. The method to quantify the non-linarites is not defined.

B.2.3.17 Probe Pattern Effect

The probe/s pattern/s is assumed to be known so that the DUT measurement in near field can be corrected when performing the near field to far field transform. If the probe pattern is known, then the uncertainty term is zero. There is no direct dependence between the DUT pattern and the probe pattern in near field measurements. This uncertainty is assumed to have a normal distribution.

B.2.3.18 Phase centre offset of calibration

See B.2.1.18.

B.2.3.19 Quality of the Quiet Zone for Calibration Process

See B.2.1.19.

B.2.3.20 Phase Drift and Noise

This uncertainty is due to the noise level and drift of the test range and should be determined or measured at the DUT location. The noise level is usually measured with a Spectrum Analyzer. This uncertainty is assumed to have a normal distribution.

B.2.3.21 Mismatch in the connection of the calibration antenna

See B.2.1.4.

B.2.3.22 Influence of TRP measurement grid

See B.2.1.22.

B.2.3.23

B.2.3.24

B.2.3.25 Leakage and Crosstalk

This uncertainty can be addressed by measurements on the actual system setup. The leakage and crosstalk cannot be separated from the random amplitude and phase errors so that the relative importance should be determined. This uncertainty is assumed to have a normal distribution.

B.2.3.26 Systematic error due to TRP calculation/quadrature

See B.2.1.24.

B.2.3.27 Multiple measurement antenna uncertainty

See B.2.1.25.

B.2.3.28 DUT repositioning

See B.2.1.26.

B.2.3.29 Influence of noise

See B.2.1.27.

B.2.3.30 Uncertainty of the RF relative power measurement equipment

See B.2.1.36.

B.3 UE maximum output power

Editor's note: The MU for 2AoA STxMP is working assumption. Values will be confirmed once devices supporting 2AoA STxMP test cases are commercially available.

Following tables summarize the MU threshold for EIRP and TRP measurements for UE maximum output power. The origin MU values for different test setups with varies parameters can be found in following clauses.

Table B.3-1: MU threshold for EIRP measurement for UE maximum output power

Power Class	Frequency	MBW	Power (NOTE2)	Threshold MU value for NTC [dB] (NOTE1)	Threshold MU value for ETC [dB] (NOTE1)
PC3, PC7 (NOTE3)	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.08	5.35
	32.125GHz < f <= 40.8GHz			5.28	5.55
	40.8GHz < f <= 44.3GHz			6.64	6.78
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.33	5.60
	32.125GHz < f <= 40.8GHz			5.40	5.67
PC5	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.33	5.60
PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.31	5.58
NOTE 1: Total EIRP Expanded MU for IFF for Quiet Zone size ≤30cm in Table B.3.2-2 for PC3 and PC6 UEs (NTC), in Table B.3.2-8 for PC3 and PC6 UEs (ETC) and B.3.2-6 (NTC) and B.3.2-9 (ETC) for PC1 and PC5 UEs. NOTE 2: Max output power level for device with corresponding power class. NOTE 3: MU thresholds for PC7 limited to FR2a (23.45GHz <= f <= 32.125GHz), SISO and MBW <=100MHz. NOTE 4: The MU values are valid for SISO and MIMO.					

Table B.3-1a: MU threshold for EIRP measurement for UE maximum output power for 2AoA STxMP

Power Class	Frequency	MBW	Power (NOTE2)	Threshold MU value for NTC [dB] (NOTE1)	Threshold MU value for ETC [dB] (NOTE1)
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.50	TBD
	32.125GHz < f <= 40.8GHz			5.63	TBD
PC5	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.50	TBD
NOTE 1: Total EIRP Expanded MU for IFF for Quiet Zone size ≤30cm in Table B.3.2-6a (NTC) and B.3.2-9a (ETC) for PC1 and PC5 UEs. NOTE 2: Max output power level for device with corresponding power class.					

Table B.3-2: MU threshold for TRP measurement for UE maximum output power

Power Class	Frequency	MBW	Power (NOTE2)	Threshold MU value for NTC [dB] (NOTE 1)	Threshold MU value for ETC [dB] (NOTE 1)
PC3, PC7 (NOTE3)	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	4.61	4.87
	32.125GHz < f <= 40.8GHz			4.81	5.07
	40.8GHz < f <= 44.3GHz			6.16	6.30
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	4.64	4.90
	32.125GHz < f <= 40.8GHz			4.78	5.04
PC5	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	4.64	4.90
PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	4.64	4.90
NOTE 1: Total TRP Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.3.2-2 for PC3 and PC6 UEs (NTC), in Table B.3.2-8 for PC3 and PC6 UEs (ETC) and B.3.2-6 (NTC) and B.3.2-9 (ETC) for PC1 and PC5 UEs. NOTE 2: Max output power level for device with corresponding power class. NOTE 3: MU thresholds for PC7 limited to FR2a (23.45GHz <= f <= 32.125GHz), SISO and MBW <=100MHz. NOTE 4: The MU values are valid for SISO and MIMO.					

Table B.3-2a: MU threshold for TRP measurement for UE maximum output power for 2AoA STxMP

Power Class	Frequency	MBW	Power (NOTE2)	Threshold MU value for NTC [dB] (NOTE 1)	Threshold MU value for ETC [dB] (NOTE 1)
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.50	TBD
	32.125GHz < f <= 40.8GHz			5.76	TBD
PC5	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.50	TBD
NOTE 1: Total EIRP Expanded MU for IFF for Quiet Zone size ≤30cm in Table B.3.2-6a (NTC) and B.3.2-9a (ETC) for PC1 and PC5 UEs. NOTE 2: Max output power level for device with corresponding power class.					

Table B.3-3: MU threshold for Spherical coverage measurement for UE maximum output power

Power Class	Frequency	MBW	Power	Threshold MU value (NOTE 1)
PC3, PC7 (NOTE2)	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = TBD	4.78
	32.125GHz < f <= 40.8GHz			5.38
	40.8GHz < f <= 44.3GHz			6.84
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = TBD	4.69
	32.125GHz < f <= 40.8GHz			4.84
PC5	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = TBD	4.69
PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = TBD	5.38
NOTE 1: Total Spherical coverage Expanded MU for IFF for Quiet Zone size ≤ 30cm in Tables B.3.2-4 for PC3 UEs and B.3.2-7 for PC1 and PC5 UEs. NOTE 2: MU thresholds for PC7 limited to FR2a (23.45GHz <= f <= 32.125GHz), SISO and MBW <=100MHz. NOTE 3: The MU values are valid for SISO and MIMO.				

B.3.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.3.1-1.

Table B.3.1-1: Uncertainty contributions for EIRP and TRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of quiet zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing Wave Between the DUT and measurement antenna	B.2.1.5
6	Uncertainty of the RF power measurement equipment	B.2.1.6
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Influence of TRP measurement grid	B.2.1.22
14	Influence of beam peak search grid	B.2.1.23
15	Multiple measurement antenna uncertainty	B.2.1.25
16	DUT repositioning	B.2.1.26
17	Influence of spherical coverage grid	B.2.1.29
Stage 1: Calibration measurement		
18	Mismatch	B.2.1.4
19	Amplifier uncertainties	B.2.1.8
20	Misalignment of positioning System	B.2.1.13
21	Uncertainty of the Network Analyzer	B.2.1.14
22	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
24	Phase centre offset of calibration antenna	B.2.1.18
25	Quality of quiet zone for calibration process	B.2.1.19
26	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
27	Influence of the calibration antenna feed cable	B.2.1.21
28	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
29	Systematic error due to TRP calculation/quadrature	B.2.1.24
30	Influence of noise	B.2.1.27
31	Systematic error related to beam peak search	B.2.1.28

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].
- The uncertainty assessment for EIRP and TRP is provided in Table B.3.1-2.

Table B.3.1-2: Uncertainty assessment for EIRP and TRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment				
2	Measure distance uncertainty				
3	Quality of quiet zone (NOTE 2)				
4	Mismatch (NOTE 3)				
5	Standing Wave Between the DUT and measurement antenna				
6	Uncertainty of the RF power measurement equipment (NOTE 4)				
7	Phase curvature				
8	Amplifier uncertainties				
9	Random uncertainty				
10	Influence of the XPD				
11	Insertion Loss Variation				
12	RF leakage (from measurement antenna to the receiver/transmitter)				
13	Influence of TRP measurement grid (NOTE 5)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 6)	0.0	Actual	1	0.0
15	Multiple measurement antenna uncertainty				
16	DUT repositioning				
17	Influence of spherical coverage grid (NOTE 8)	0.12	Actual	1	0.12
Stage 1: Calibration measurement					
18	Mismatch				
19	Amplifier uncertainties				
20	Misalignment of positioning System				
21	Uncertainty of the Network Analyzer				
22	Uncertainty of the absolute gain of the calibration antenna				
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna				
24	Phase centre offset of calibration antenna				
25	Quality of quiet zone for calibration process (NOTE 2)				
26	Standing wave between reference calibration antenna and measurement antenna				
27	Influence of the calibration antenna feed cable				
28	Insertion Loss Variation				
	Systematic uncertainties (NOTE 7)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 5)				0.00
30	Influence of noise				
31	Systematic error related to beam peak search (NOTE 6)				0.5
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (1.96σ – confidence interval of 95 %) [dB]					TBD
TRP Expanded uncertainty (1.96σ – confidence interval of 95 %) [dB]					TBD

NOTE 1:	The impact of phase variation on EIRP shall be taken into account during final MU definition for the test method.
NOTE 2:	The quality of quiet zone is different for EIRP and TRP in normal temperature conditions. For TRP, the standard uncertainty is FFS; for EIRP, the standard uncertainty of quiet zone is FFS.
NOTE 3:	The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 4:	The assessment assumes maximum DUT output power.
NOTE 5:	This contributor shall only be considered for TRP measurements.
NOTE 6:	This contributor shall only be considered for EIRP measurements.
NOTE 7:	In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 8:	This contributor shall only be considered for spherical EIRP measurements

B.3.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.3.2-1.

Table B.3.2-1: Uncertainty contributions for EIRP and TRP measurement

UID	Description of uncertainty contribution	Details in clause
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	Uncertainty of the RF power measurement equipment	B.2.2.6
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Influence of TRP measurement grid	B.2.2.22
14	Influence of beam peak search grid	B.2.2.23
15	Multiple measurement antenna uncertainty	B.2.2.25
16	DUT repositioning	B.2.2.26
17	Influence of spherical coverage grid	B.2.2.29
Stage 1: Calibration measurement		
18	Mismatch	B.2.2.4
19	Amplifier Uncertainties	B.2.2.8
20	Misalignment of positioning System	B.2.2.13
21	Uncertainty of the Network Analyzer	B.2.2.14
22	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
24	Phase centre offset of calibration antenna	B.2.2.18
25	Quality of quiet zone for calibration process	B.2.2.19
26	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
27	Influence of the calibration antenna feed cable	B.2.2.21
28	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
29	Systematic error due to TRP calculation/quadrature	B.2.2.24
30	Influence of noise	B.2.1.27
31	Systematic error related to beam peak search	B.2.2.28

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D

- The uncertainty assessment has been derived for the case of Quiet Zone size ≤ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz}, [P = maximum output power].

- The uncertainty assessment for EIRP and TRP in normal temperature conditions is provided in Table B.3.2-2 for PC3 UEs and in Table B.3.2-6 for PC1 and PC5 UEs.

- The uncertainty assessment for EIRP and TRP in extreme temperature conditions is provided in Table B.3.2-8 for PC3 UEs and in Table B.3.2-9 for PC1 and PC5 UEs.

- The uncertainty assessment for Spherical coverage is provided in Table B.3.2-4 for PC3 UEs, Table B.3.2-5 for PC6 UEs and Table B.3.2-7 for PC1 and PC5 UEs.

Table B.3.2-2: Uncertainty assessment for EIRP and TRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 and PC6 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 1) (23.45GHz <= f <= 40.8GHz)	0.6	Actual	1.00	0.6
3	Quality of Quiet Zone (NOTE 1) (40.8GHz < f <= 44.3GHz)	0.7	Actual	1.00	0.7
4	Mismatch (23.45GHz <= f <= 40.8GHz)	1.30	Actual	1.00	1.30
4	Mismatch (40.8GHz < f <= 44.3GHz)	1.70	Actual	1.00	1.70
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 3) (23.45GHz <= f <= 40.8GHz)	2.16	Normal	2.00	1.08
6	Uncertainty of the RF power measurement equipment (NOTE 3) (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 4)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 5)	0.00	Actual	1	0.00
15	Multiple measurement antenna uncertainty (NOTE 9)	0.15	Actual	1	0.15
16	DUT repositioning	0.00 (NOTE 4) 0.08 (NOTE 5)	Rectangular	1.73	0.00 (NOTE 4) 0.05 (NOTE 5)
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.50	Normal	2.00	0.75
20	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.70	Normal	2.00	0.85
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 1) (23.45GHz <= f <= 40.8GHz)	0.4	Actual	1.00	0.4
24	Quality of quiet zone for calibration process (NOTE 1) (40.8GHz < f <= 44.3GHz)	0.5	Actual	1.00	0.5
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00

26	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 6)				**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 4)				0.00
29	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC3)				0.1
29	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC6)				0.13
29	Influence of noise (32.125GHz < f <= 40.8GHz) (PC3)				0.3
29	Influence of noise (40.8GHz < f <= 44.3GHz) (PC3)				0.3
30	Systematic error related to beam peak search (NOTE 5) (PC3)				0.5
30	Systematic error related to beam peak search (NOTE 5) (PC6)				0.7
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)					5.08
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC6)					5.31
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)					5.28
EIRP Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)					6.64
TRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)					4.61
TRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC6)					4.64
TRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)					4.81
TRP Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)					6.16

NOTE 1: The quality of quiet zone is the same for EIRP and TRP. Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA and is valid for SISO and MIMO.
NOTE 3: The assessment assumes maximum DUT output power.
NOTE 4: This contributor shall only be considered for TRP measurements.
NOTE 5: This contributor shall only be considered for EIRP measurements.
NOTE 6: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 7: Void.
NOTE 8: Void
NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.3.2-3: Void

Table B.3.2-4: Uncertainty assessment for Spherical coverage measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 1) (23.45GHz <= f <= 40.8GHz)	0.6	Actual	1.00	0.6
3	Quality of Quiet Zone (NOTE 1) (40.8GHz < f <= 44.3GHz)	0.7	Actual	1.00	0.7
4	Mismatch (23.45GHz <= f <= 40.8GHz)	1.30	Actual	1.00	1.30
4	Mismatch (40.8GHz < f <= 44.3GHz)	1.70	Actual	1.00	1.70
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 3) (23.45GHz <= f <= 40.8GHz)	2.16	Normal	2.00	1.08
6	Uncertainty of the RF power measurement equipment (NOTE 3) (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
14	DUT repositioning	0.00	Rectangular	1.73	0.00
15	Influence of spherical coverage grid	0.12	Actual	1	0.12
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.50	Normal	2.00	0.75
19	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.70	Normal	2.00	0.85
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 1) (23.45GHz <= f <= 40.8GHz)	0.4	Actual	1.00	0.4
23	Quality of quiet zone for calibration process (NOTE 1) (40.8GHz < f <= 44.3GHz)	0.5	Actual	1.00	0.5
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 4)				**Value**
27	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.3

27	Influence of noise (32.125GHz < f <= 40.8GHz)	0.9
27	Influence of noise (40.8GHz < f <= 44.3GHz)	1.0
Total measurement uncertainty		**Value**
Spherical coverage Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]		4.78
Spherical coverage Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]		5.38
Spherical coverage Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB]		6.84
NOTE 1: The quality of quiet zone is the same for EIRP and TRP. Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.		
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA and is valid for SISO and MIMO.		
NOTE 3: The assessment assumes maximum DUT output power.		
NOTE 4: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.		
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.		

Table B.3.2-4a: Uncertainty assessment for Spherical coverage measurement (f=23.45GHz, 32.125GHz, Quiet Zone size ≤ 30 cm) for PC6 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1 to 16	Same as defined inTable B.3.2-2 for PC6, EIRP, 23.45GHz <= f <= 32.125GHz				
Stage 1: Calibration measurement					
17 to 27	Same as defined inTable B.3.2-2 for PC6, EIRP, 23.45GHz <= f <= 32.125GHz				
	Systematic uncertainties (NOTE 4)				**Value**
28	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.2
29	Systematic error related to beam peak search				0.7
Total measurement uncertainty					**Value**
Spherical coverage Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					5.38
NOTE 1: The quality of quiet zone is the same for EIRP and TRP. Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.					
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA and is valid for SISO and MIMO.					
NOTE 3: The assessment assumes maximum DUT output power.					
NOTE 4: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.					

Table B.3.2-5: Void

Table B.3.2-6: Uncertainty assessment for EIRP and TRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 1)	0.6	Actual	1.00	0.6
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 3)	2.16	Normal	2.00	1.08
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 4)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 5)	0.00	Actual	1	0.00
15	Multiple measurement antenna uncertainty (NOTE 9)	0.15	Actual	1	0.15
16	DUT repositioning	0.00 (NOTE 4) 0.35 (NOTE 5)	Rectangular	1.73	0.00 (NOTE 4) 0.20 (NOTE 5)
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 1)	0.4	Actual	1.00	0.4
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
26	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 6)				**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 4)				0.00
29	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.13
29	Influence of noise (32.125GHz < f <= 40.8GHz)				0.27 (NOTE 4) 0.20 (NOTE 5)
30	Systematic error related to beam peak search (NOTE 5)				0.7
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					5.33
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					5.40
TRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					4.64

TRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]	4.78
NOTE 1: The quality of quiet zone is the same for EIRP and TRP. Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.	
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA and is valid for SISO and MIMO.	
NOTE 3: The assessment assumes maximum DUT output power.	
NOTE 4: This contributor shall only be considered for TRP measurements.	
NOTE 5: This contributor shall only be considered for EIRP measurements.	
NOTE 6: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.	
NOTE 7: Void.	
NOTE 8: Void	
NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.	

Table B.3.2-6a: Uncertainty assessment for EIRP and TRP measurement for 2AoA STxMP (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1, 2, 5, 7 to 16	Same as Stage 2 of Table B.3.2-6				
3	Quality of Quiet Zone (NOTE 1)	0.8	Actual	1.00	0.8
4	Mismatch	1.70	Actual	1.00	1.70
6	Uncertainty of the RF power measurement equipment (NOTE 3)	2.50	Normal	2.00	1.25
to 16					
Stage 1: Calibration measurement					
17 to 27	Same as Stage 1 of Table B.3.2-6				
	Systematic uncertainties (NOTE 6)				**Value**
28	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.26
28	Influence of noise (32.125GHz < f <= 40.8GHz)				0.52 (NOTE 4) 0.39 (NOTE 5)
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					5.50
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					5.63
TRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					5.50
TRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					5.76
NOTE 1: The quality of quiet zone is the same for EIRP and TRP. Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.					
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA.					
NOTE 3: The assessment assumes maximum DUT output power.					
NOTE 4: This contributor shall only be considered for TRP measurements.					
NOTE 5: This contributor shall only be considered for EIRP measurements.					
NOTE 6: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.					

Table B.3.2-7: Uncertainty assessment for Spherical coverage measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 1)	0.60	Actual	1.00	0.60
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 3)	2.16	Normal	2.00	1.08
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
14	DUT repositioning	0.00	Rectangular	1.73	0.00
15	Influence of spherical coverage grid	0.13	Actual	1	0.13
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 1)	0.40	Actual	1.00	0.40
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 4)				**Value**
27	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.20
27	Influence of noise (32.125GHz < f <= 40.8GHz)				0.35
Total measurement uncertainty					**Value**
Spherical coverage Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					4.69
Spherical coverage Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					4.84

NOTE 1: The quality of quiet zone is the same for EIRP and TRP. Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA and is valid for SISO and MIMO.
NOTE 3: The assessment assumes maximum DUT output power.
NOTE 4: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.3.2-8: Uncertainty assessment for EIRP and TRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 and PC6 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 1)	0.9	Actual	1.00	0.9
4	Mismatch (23.45GHz <= f <= 40.8GHz)	1.30	Actual	1.00	1.30
4	Mismatch (40.8GHz < f <= 44.3GHz)	1.70	Actual	1.00	1.70
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 3) (23.45GHz <= f <= 40.8GHz)	2.16	Normal	2.00	1.08
6	Uncertainty of the RF power measurement equipment (NOTE 3) (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 4)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 5)	0.00	Actual	1	0.00
15	Multiple measurement antenna uncertainty (NOTE 7)	0.15	Actual	1	0.15
16	DUT repositioning	0.00 (NOTE 4) 0.08 (NOTE 5)	Rectangular	1.73	0.00 (NOTE 4) 0.05 (NOTE 5)
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.50	Normal	2.00	0.75
20	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.70	Normal	2.00	0.85
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 1)	0.6	Actual	1.00	0.6
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
26	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 6)				**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 4)				0.00
29	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC3)				0.1
29	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC6)				0.13

29	Influence of noise (32.125GHz < f <= 44.3GHz) (PC3)	0.3
30	Systematic error related to beam peak search (NOTE 5) (PC3)	0.5
30	Systematic error related to beam peak search (NOTE 5) (PC6)	0.7
Total measurement uncertainty		Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		5.35
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC6)		5.58
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		5.55
EIRP Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		6.78
TRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		4.87
TRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC6)		4.90
TRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		5.07
TRP Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		6.30

NOTE 1: The quality of quiet zone is the same for EIRP and TRP. Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm. The ETC QoQZ MU and ETC calibration path losses shall be applied to the NTC test cases if the ETC environment is used for NTC test cases.
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA and is valid for SISO and MIMO.
NOTE 3: The assessment assumes maximum DUT output power.
NOTE 4: This contributor shall only be considered for TRP measurements.
NOTE 5: This contributor shall only be considered for EIRP measurements.
NOTE 6: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 7: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.3.2-9: Uncertainty assessment for EIRP and TRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 1)	0.90	Actual	1.00	0.90
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 3)	2.16	Normal	2.00	1.08
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 4)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 5)	0.00	Actual	1	0.00
15	Multiple measurement antenna uncertainty (NOTE 7)	0.15	Actual	1	0.15
16	DUT repositioning	0.00 (NOTE 4) 0.35 (NOTE 5)	Rectangular	1.73	0.00 (NOTE 4) 0.20 (NOTE 5)
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 1)	0.60	Actual	1.00	0.60
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
26	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 6)				**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 4)				0.00
29	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.13
29	Influence of noise (32.125GHz < f <= 40.8GHz)				0.27 (NOTE 4) 0.20 (NOTE 5)
30	Systematic error related to beam peak search (NOTE 5)				0.7
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					5.60
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					5.67
TRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					4.90

TRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]	5.04
NOTE 1: The quality of quiet zone is the same for EIRP and TRP. Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm. The ETC QoQZ MU and ETC calibration path losses shall be applied to the NTC test cases if the ETC environment is used for NTC test cases. NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA and is valid for SISO and MIMO. NOTE 3: The assessment assumes maximum DUT output power. NOTE 4: This contributor shall only be considered for TRP measurements. NOTE 5: This contributor shall only be considered for EIRP measurements. NOTE 6: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 7: Applies to the system which has a structure of mechanical feed antenna positioning.	

Table B.3.2-9a: Uncertainty assessment for EIRP and TRP measurement for 2AoA STxMP (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1, 2, 5, 7 to 16	Same as Stage 2 of Table B.3.2-9				
3	Quality of Quiet Zone (NOTE 1)	TBD	Actual	1.00	TBD
4	Mismatch	1.70	Actual	1.00	1.70
6	Uncertainty of the RF power measurement equipment (NOTE 3)	2.50	Normal	2.00	1.25
Stage 1: Calibration measurement					
17 to 27	Same as Stage 1 of Table B.3.2-9				
	Systematic uncertainties (NOTE 6)				**Value**
28	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.26
28	Influence of noise (32.125GHz < f <= 40.8GHz)				0.52 (NOTE 4) 0.39 (NOTE 5)
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					TBD
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					TBD
TRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					TBD
TRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					TBD
NOTE 1: The quality of quiet zone is the same for EIRP and TRP. Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm. NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA. NOTE 3: The assessment assumes maximum DUT output power. NOTE 4: This contributor shall only be considered for TRP measurements. NOTE 5: This contributor shall only be considered for EIRP measurements. NOTE 6: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.					

B.3.3 Uncertainty budget format and assessment for NFTF

The uncertainty contributions that may impact the overall MU value are listed in Table B.3.3-1.

Table B.3.3-1: Uncertainty contributions for EIRP and TRP measurement

UID	Description of uncertainty contribution	Details in paragraph
	Stage 2: EIRP Near Field Radiation Pattern Measurement and EIRP Near Field DUT power measurement	
1	Axis Alignment	B.2.3.1
2	Measurement Distance Uncertainty	B.2.3.2
3	Quality of the Quiet Zone	B.2.3.3
4	Mismatch	B.2.3.4
5	Multiple Reflections: Coupling between Measurement Antenna and DUT	B.2.3.5
6	Uncertainty of the RF power measurement equipment	B.2.3.6
7	Phase curvature	B.2.3.7
8	Amplifier uncertainties	B.2.3.8
9	Random uncertainty	B.2.3.9
10	Influence of the XPD	B.2.3.10
11	NF to FF truncation	B.2.3.11
12	Probe Polarization Amplitude and Phase	B.2.3.12
13	Probe Array Uniformity (for multi-probe systems only)	B.2.3.13
14	Phase Recovery Non-Linearity over signal bandwidth	B.2.3.16
15	Probe Pattern Effect	B.2.3.17
16	Phase Drift and Noise	B.2.3.20
17	Leakage and Crosstalk	B.2.3.25
	Stage 1: Calibration measurement	
18	Mismatch	B.2.3.4
19	Amplifier uncertainties	B.2.3.8
20	Uncertainty of the Network Analyzer	B.2.3.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.3.15
22	Phase centre offset of calibration	B.2.3.18
23	Quality of the Quiet Zone for Calibration Process	B.2.3.19
24	Mismatch in the connection of the calibration antenna	B.2.3.21

The uncertainty assessment table is organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].
- The uncertainty assessment for EIRP and TRP is provided in Table B.3.1-2.

Table B.3.3-2: Uncertainty assessment for EIRP and TRP measurement (f=TBD, D=TBD)

UID	Description of uncertainty contribution	Uncertainty Value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
	Stage 2: EIRP Near Field Radiation Pattern Measurement and EIRP Near Field DUT power measurement				
1	Axis Alignment				
2	Measurement Distance Uncertainty				
3	Quality of the Quiet Zone				
4	Mismatch				
5	Multiple Reflections: Coupling between Measurement Antenna and DUT				
6	Uncertainty of the RF power measurement equipment				
7	Phase curvature				
8	Amplifier uncertainties				
9	Random uncertainty				
10	Influence of the XPD				
11	NF to FF truncation				
12	Probe Polarization Amplitude and Phase				
13	Probe Array Uniformity (for multi-probe systems only)				
14	Phase Recovery Non-Linearity over signal bandwidth				
15	Probe Pattern Effect				
16	Phase Drift and Noise				
17	Leakage and Crosstalk				
	Stage 1: Calibration measurement				
18	Mismatch				
19	Amplifier uncertainties				
20	Uncertainty of the Network Analyzer				
21	Uncertainty of the absolute gain of the calibration antenna				
22	Phase centre offset of calibration				
23	Quality of the Quiet Zone for Calibration Process				
24	Mismatch in the connection of the calibration antenna				
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					
TRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					

NOTE 1: The impact of phase variation on EIRP shall be taken into account during final MU definition for the test method.
NOTE 2: The quality of quiet zone is different for EIRP and TRP. For TRP, the standard uncertainty is FFS; for EIRP FFS.
NOTE 3: The analysis was done only for the case of operating at max output power, in-band, non-CA
NOTE 4: The assessment assumes maximum DUT output power.
NOTE 5: The Phase Recovery Non-Linearity over signal bandwidth is shall be taken into account during final MU definition for the test method.

B.4 UE maximum output power for modulation / channel bandwidth

Editor's note: The MU for 2AoA STxMP is working assumption. Values will be confirmed once devices supporting 2AoA STxMP test cases are commercially available.

Following tables summarize the MU threshold for EIRP measurements for UE maximum output power for modulation / channel bandwidth (a.k.a Maximum Power Reduction/MPR). The origin MU values for different test setups with varies parameters can be found in following clauses.

Table B.4-1: MU threshold for EIRP measurement for UE maximum output power for modulation / channel bandwidth

Power Class	Frequency	MBW	Power (NOTE2)	Threshold MU value for NTC [dB] (NOTE1)	Threshold MU value for ETC [dB] (NOTE1)
PC3, PC7 (NOTE4)	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power –MBR - MPR – T(MPR)	5.11	5.38
	32.125GHz < f <= 40.8GHz			5.29	5.56
	40.8GHz < f <= 44.3GHz			6.89	7.03
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power –MPR – T(MPR)	5.33	5.60
	32.125GHz < f <= 40.8GHz			5.50	5.77
PC5	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power –MPR – T(MPR)	5.33	5.60
PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power –MPR – T(MPR)	5.31	5.58
NOTE 1: Total EIRP Expanded MU for IFF for Quiet Zone size ≤30cm in Table B.4.2-2 and Table B.4.2-3 for PC3 and PC6 UEs and Table B.4.2-4 and Table B.4.2-5 for PC1 and PC5 UEs. NOTE 2: Max output power level for device with corresponding power class. NOTE 3: The MU values are valid for SISO and MIMO. NOTE 4: MU thresholds for PC7 limited to FR2a (23.45GHz <= f <= 32.125GHz), SISO and MBW <=100MHz.					

Table B.4-2: MU threshold for EIRP measurement for UE maximum output power for modulation / channel bandwidth for 2AoA STxMP

Power Class	Frequency	MBW	Power (NOTE2)	Threshold MU value for NTC [dB] (NOTE1)	Threshold MU value for ETC [dB] (NOTE1)
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power –MPR – T(MPR)	5.50	TBD
	32.125GHz < f <= 40.8GHz			5.82	TBD

PC5	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power –MPR – T(MPR)	5.50	TBD
NOTE 1: Total EIRP Expanded MU for IFF for Quiet Zone size ≤30cm in Table B.4.2-4a (NTC) and Table B.4.2-5a (ETC) for PC1 and PC5 UEs. NOTE 2: Max output power level for device with corresponding power class. NOTE 3: The MU values are valid for SISO and MIMO. NOTE 4: MU thresholds for PC7 limited to FR2a (23.45GHz <= f <= 32.125GHz), SISO and MBW <=100MHz.					

B.4.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.4.1-1.

Table B.4.1-1: Uncertainty contributions for EIRP measurement

UID	Description of uncertainty contribution	Details in annex
Same as Table 3.1-1 for EIRP		

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = 5 cm, f = {22.65GHz, 31.1GHz, 45.1GHz}, P = maximum output power – MBR - MPR – T(MPR).
- The uncertainty assessment for EIRP is provided in Table B.4.1-2.

Table B.4.1-2: Uncertainty assessment for EIRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1 to 17	Same as Stage 2 of Table 3.1-2 for EIRP				
Stage 1: Calibration measurement					
18 to 28	Same as Stage 1 of Table 3.1-2 for EIRP				
	Systematic uncertainties				**Value**
29	Systematic error due to TRP calculation/quadrature				N/A
30	Influence of noise				
31	Systematic error related to beam peak search				Same as Table 3.1-2
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					TBD
TRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					TBD
NOTE 1: The assessment assumes maximum DUT output power – MBR - MPR – T(MPR)					

B.4.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.4.2-1.

Table B.4.2-1: Uncertainty contributions for EIRP and TRP measurement

UID	Description of uncertainty contribution	Details in annex
Same as Stage 2 of Table 3.2-1 for EIRP		

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size ≤ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz}, P = maximum output power – MPR – T(MPR).
- The uncertainty assessment for EIRP and TRP is provided in Table B.3.2-2 for PC3 UEs and in Table B.4.2-x for PC1 UEs.

Table B.4.2-2: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 and PC6 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1 to 16	Same as Stage 2 of Table B.3.2-2 for EIRP				
Stage 1: Calibration measurement					
17 to 27	Same as Stage 1 of Table B.3.2-2 for EIRP				
	Systematic uncertainties				**Value**
28	Systematic error due to TRP calculation/quadrature				N/A
29	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC3 and PC6)				0.13
29	Influence of noise (32.125GHz < f <= 40.8GHz) (PC3)				0.31
29	Influence of noise (40.8GHz < f <= 44.3GHz) (PC3)				0.55
30	Systematic error related to beam peak search				Same as Table B.3.2-2
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ – confidence interval of 95 %) [dB] (PC3)					5.11
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ – confidence interval of 95 %) [dB] (PC6)					5.31
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ – confidence interval of 95 %) [dB] (PC3)					5.29
EIRP Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ – confidence interval of 95 %) [dB] (PC3)					6.89
NOTE 1: The assessment assumes maximum DUT output power – MBR - MPR – T(MPR) NOTE 2: The analysis is valid for SISO and MIMO.					

Table B.4.2-3: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 and PC6 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1 to 16	Same as Stage 2 of Table B.3.2-8 for EIRP				
Stage 1: Calibration measurement					
17 to 27	Same as Stage 1 of Table B.3.2-8 for EIRP				
	Systematic uncertainties				**Value**
28	Systematic error due to TRP calculation/quadrature				N/A
29	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC3 and PC6)				0.13
29	Influence of noise (32.125GHz < f <= 40.8GHz) (PC3)				0.31
29	Influence of noise (40.8GHz < f <= 44.3GHz)				0.55
30	Systematic error related to beam peak search				Same as Table B.3.2-8
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)					5.38
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC6)					5.58
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)					5.56
EIRP Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ – confidence interval of 95 %) [dB]					7.03
NOTE 1: The assessment assumes maximum DUT output power – MBR - MPR – T(MPR) NOTE 2: The analysis is valid for SISO and MIMO.					

Table B.4.2-4: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1 to 16	Same as Stage 2 of Table B.3.2-6 for EIRP				
Stage 1: Calibration measurement					
17 to 27	Same as Stage 1 of Table B.3.2-6 for EIRP				
	Systematic uncertainties				**Value**
28	Systematic error due to TRP calculation/quadrature				N/A
29	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.13
29	Influence of noise (32.125GHz < f <= 40.8GHz)				0.3
30	Systematic error related to beam peak search				Same as Table B.3.2-6
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					5.33
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					5.50
NOTE 1: The assessment assumes maximum DUT output power – MPR – T(MPR) NOTE 2: The analysis is valid for SISO and MIMO.					

Table B.4.2-4a: Uncertainty assessment for EIRP measurement for 2AoA STxMP (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1 to 16	Same as Stage 2 of Table B.3.2-6a for EIRP				
Stage 1: Calibration measurement					
17 to 27	Same as Stage 1 of Table B.3.2-6a for EIRP				
	Systematic uncertainties				**Value**
28	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.26
28	Influence of noise (32.125GHz < f <= 40.8GHz)				0.58
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					5.50
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					5.82
NOTE 1: The assessment assumes maximum DUT output power – MPR – T(MPR)					

Table B.4.2-5: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1 to 16	Same as Stage 2 of Table B.3.2-9 for EIRP				
Stage 1: Calibration measurement					
17 to 27	Same as Stage 1 of Table B.3.2-9 for EIRP				
	Systematic uncertainties				**Value**
28	Systematic error due to TRP calculation/quadrature				N/A
29	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.13
29	Influence of noise (32.125GHz < f <= 40.8GHz)				0.3
30	Systematic error related to beam peak search				Same as Table B.3.2-9
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					5.60
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					5.77
NOTE 1: The assessment assumes maximum DUT output power – MPR – T(MPR) NOTE 2: The analysis is valid for SISO and MIMO.					

Table B.4.2-5a: Uncertainty assessment for EIRP measurement for 2AoA STxMP (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1 to 16	Same as Stage 2 of Table B.3.2-9a for EIRP				
Stage 1: Calibration measurement					
17 to 27	Same as Stage 1 of Table B.3.2-9a for EIRP				
	Systematic uncertainties				**Value**
28	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.26
28	Influence of noise (32.125GHz < f <= 40.8GHz)				0.58
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					TBD
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					TBD
NOTE 1: The assessment assumes maximum DUT output power – MPR – T(MPR)					

B.4.3 Uncertainty budget format and assessment for NFTF

FFS

B.5 UE maximum output power with additional requirements

FFS

B.6 Configured transmitted power with Power Boost

Following tables summarize the MU threshold for EIRP measurements for UE maximum output power. The origin MU values for different test setups with varies parameters can be found in following clauses.

Table B.6-1: MU threshold for EIRP measurement for Configured transmitted power with Power Boost

Power Class	Frequency	MBW	Power (NOTE2)	Threshold MU value for NTC [dB] (NOTE1)	Threshold MU value for ETC [dB] (NOTE1)
PC3	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.08	5.35
	32.125GHz < f <= 40.8GHz			5.28	5.55
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	FFS	FFS
	32.125GHz < f <= 40.8GHz			FFS	FFS
NOTE 1: Total EIRP Expanded MU for IFF for Quiet Zone size ≤30cm in Table B.6.2-2 for PC3 UEs (NTC), in Table B.6.2-8 for PC3 UEs (ETC) and B.6.2-6 for PC1 UEs. NOTE 2: Max output power level for device with corresponding power class.					

B.6.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.6.1-1.

Table B.6.1-1: Uncertainty contributions for EIRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of quiet zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing Wave Between the DUT and measurement antenna	B.2.1.5
6	Uncertainty of the RF power measurement equipment	B.2.1.6
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Influence of beam peak search grid	B.2.1.23
14	Multiple measurement antenna uncertainty	B.2.1.25
15	DUT repositioning	B.2.1.26
Stage 1: Calibration measurement		
16	Mismatch	B.2.1.4
17	Amplifier uncertainties	B.2.1.8
18	Misalignment of positioning System	B.2.1.13
19	Uncertainty of the Network Analyzer	B.2.1.14
20	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
22	Phase centre offset of calibration antenna	B.2.1.18
23	Quality of quiet zone for calibration process	B.2.1.19
24	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
25	Influence of the calibration antenna feed cable	B.2.1.21
26	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
27	Influence of noise	B.2.1.27
28	Systematic error related to beam peak search	B.2.1.28

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].
- The uncertainty assessment for EIRP is provided in Table B.6.1-2.

Table B.6.1-2: Uncertainty assessment for EIRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment				
2	Measure distance uncertainty				
3	Quality of quiet zone				
4	Mismatch (NOTE 2)				
5	Standing Wave Between the DUT and measurement antenna				
6	Uncertainty of the RF power measurement equipment (NOTE 3)				
7	Phase curvature				
8	Amplifier uncertainties				
9	Random uncertainty				
10	Influence of the XPD				
11	Insertion Loss Variation				
12	RF leakage (from measurement antenna to the receiver/transmitter)				
13	Influence of beam peak search grid	0.0	Actual	1	0.0
14	Multiple measurement antenna uncertainty				
15	DUT repositioning				
Stage 1: Calibration measurement					
16	Mismatch				
17	Amplifier uncertainties				
18	Misalignment of positioning System				
19	Uncertainty of the Network Analyzer				
20	Uncertainty of the absolute gain of the calibration antenna				
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna				
22	Phase centre offset of calibration antenna				
23	Quality of quiet zone for calibration process				
24	Standing wave between reference calibration antenna and measurement antenna				
25	Influence of the calibration antenna feed cable				
26	Insertion Loss Variation				
	Systematic uncertainties (NOTE 4)				**Value**
27	Influence of noise				
28	Systematic error related to beam peak search				0.5
	Total measurement uncertainty				**Value**
	EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]				TBD

NOTE 1: The impact of phase variation on EIRP shall be taken into account during final MU definition for the test method.
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 3: The assessment assumes maximum DUT output power.
NOTE 4: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.

B.6.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.6.2-1.

Table B.6.2-1: Uncertainty contributions for EIRP measurement

UID	Description of uncertainty contribution	Details in clause
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	Uncertainty of the RF power measurement equipment	B.2.2.6
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Influence of beam peak search grid	B.2.2.23
14	Multiple measurement antenna uncertainty	B.2.2.25
15	DUT repositioning	B.2.2.26
Stage 1: Calibration measurement		
16	Mismatch	B.2.2.4
17	Amplifier Uncertainties	B.2.2.8
18	Misalignment of positioning System	B.2.2.13
19	Uncertainty of the Network Analyzer	B.2.2.14
20	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
22	Phase centre offset of calibration antenna	B.2.2.18
23	Quality of quiet zone for calibration process	B.2.2.19
24	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
25	Influence of the calibration antenna feed cable	B.2.2.21
26	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
27	Influence of noise	B.2.1.27
28	Systematic error related to beam peak search	B.2.2.28

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz}, [P = maximum output power].
- The uncertainty assessment for EIRP is provided in Table B.6.2-2 for PC3 UEs and in Table B.6.2-6 for PC1 UEs.

Table B.6.2-2: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 1)	0.6	Actual	1.00	0.6
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 3)	2.16	Normal	2.00	1.08
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of beam peak search grid	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
15	DUT repositioning	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 1)	0.4	Actual	1.00	0.4
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 4)				**Value**
27	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.1
27	Influence of noise (32.125GHz < f <= 40.8GHz)				0.3
28	Systematic error related to beam peak search				0.5
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					5.08
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					5.28

NOTE 1: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 3: The assessment assumes maximum DUT output power.
NOTE 4: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.6.2-3: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	FFS	Rectangular	1.73	FFS
3	Quality of Quiet Zone (NOTE 1)	FFS	Actual	1.00	FFS
4	Mismatch	FFS	Actual	1.00	FFS
5	Standing wave between the DUT and measurement antenna	FFS	U-shaped	1.41	FFS
6	Uncertainty of the RF power measurement equipment (NOTE 3)	FFS	Normal	2.00	FFS
7	Phase curvature	FFS	U-shaped	1.41	FFS
8	Amplifier uncertainties	FFS	Normal	2.00	FFS
9	Random uncertainty	FFS	Normal	2.00	FFS
10	Influence of the XPD	FFS	U-shaped	1.41	FFS
11	Insertion Loss Variation	FFS	Rectangular	1.73	FFS
12	RF leakage (from measurement antenna to the receiver/transmitter)	FFS	Actual	1.00	FFS
13	Influence of beam peak search grid	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 5)	FFS	Actual	1	FFS
15	DUT repositioning	0.35	Rectangular	1.73	0.20
Stage 1: Calibration measurement					
16	Mismatch	FFS	U-shaped	1.41	FFS
17	Amplifier Uncertainties	FFS	Normal	2.00	FFS
18	Misalignment of positioning System	FFS	Normal	2.00	FFS
19	Uncertainty of the Network Analyzer	FFS	Normal	2.00	FFS
20	Uncertainty of the absolute gain of the calibration antenna	FFS	Normal	2.00	FFS
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	FFS	Rectangular	1.73	FFS
22	Phase centre offset of calibration antenna	FFS	Rectangular	1.73	FFS
23	Quality of quiet zone for calibration process (NOTE 1)	FFS	Actual	1.00	FFS
24	Standing wave between reference calibration antenna and measurement antenna	FFS	U-shaped	1.41	FFS
25	Influence of the calibration antenna feed cable	FFS	Normal	2.00	FFS
26	Insertion Loss Variation	FFS	Rectangular	1.73	FFS
	Systematic uncertainties (NOTE 4)				**Value**
27	Influence of noise (23.45GHz <= f <= 32.125GHz)				FFS
27	Influence of noise (32.125GHz < f <= 40.8GHz)				FFS
28	Systematic error related to beam peak search				0.7
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					FFS
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					FFS

NOTE 1: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 3: The assessment assumes maximum DUT output power.
NOTE 4: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.6.2-4: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 1)	0.9	Actual	1.00	0.9
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 3)	2.16	Normal	2.00	1.08
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of beam peak search grid	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
15	DUT repositioning	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 1)	0.6	Actual	1.00	0.6
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 4)				**Value**
27	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.1
27	Influence of noise (32.125GHz < f <= 40.8GHz)				0.3
28	Systematic error related to beam peak search (NOTE 5)				0.5
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					5.35
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					5.55

NOTE 1: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm. The ETC QoQZ MU and ETC calibration path losses shall be applied to the NTC test cases if the ETC environment is used for NTC test cases.
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 3: The assessment assumes maximum DUT output power.
NOTE 4: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.6.2-5: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	FFS	Rectangular	1.73	FFS
3	Quality of Quiet Zone (NOTE 1)	FFS	Actual	1.00	FFS
4	Mismatch	FFS	Actual	1.00	FFS
5	Standing wave between the DUT and measurement antenna	FFS	U-shaped	1.41	FFS
6	Uncertainty of the RF power measurement equipment (NOTE 3)	FFS	Normal	2.00	FFS
7	Phase curvature	FFS	U-shaped	1.41	FFS
8	Amplifier uncertainties	FFS	Normal	2.00	FFS
9	Random uncertainty	FFS	Normal	2.00	FFS
10	Influence of the XPD	FFS	U-shaped	1.41	FFS
11	Insertion Loss Variation	FFS	Rectangular	1.73	FFS
12	RF leakage (from measurement antenna to the receiver/transmitter)	FFS	Actual	1.00	FFS
13	Influence of beam peak search grid	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 5)	FFS	Actual	1	FFS
15	DUT repositioning	0.35	Rectangular	1.73	0.20
Stage 1: Calibration measurement					
16	Mismatch	FFS	U-shaped	1.41	FFS
17	Amplifier Uncertainties	FFS	Normal	2.00	FFS
18	Misalignment of positioning System	FFS	Normal	2.00	FFS
19	Uncertainty of the Network Analyzer	FFS	Normal	2.00	FFS
20	Uncertainty of the absolute gain of the calibration antenna	FFS	Normal	2.00	FFS
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	FFS	Rectangular	1.73	FFS
22	Phase centre offset of calibration antenna	FFS	Rectangular	1.73	FFS
23	Quality of quiet zone for calibration process (NOTE 1)	FFS	Actual	1.00	FFS
24	Standing wave between reference calibration antenna and measurement antenna	FFS	U-shaped	1.41	FFS
25	Influence of the calibration antenna feed cable	FFS	Normal	2.00	FFS
26	Insertion Loss Variation	FFS	Rectangular	1.73	FFS
	Systematic uncertainties (NOTE 4)				**Value**
27	Influence of noise (23.45GHz <= f <= 32.125GHz)				FFS
27	Influence of noise (32.125GHz < f <= 40.8GHz)				FFS
28	Systematic error related to beam peak search				0.7
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					FFS
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					FFS

NOTE 1: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 3: The assessment assumes maximum DUT output power.
NOTE 4: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

B.6.3 Uncertainty budget format and assessment for NFTF

The uncertainty contributions that may impact the overall MU value are listed in Table B.6.3-1.

Table B.6.3-1: Uncertainty contributions for EIRP measurement

UID	Description of uncertainty contribution	Details in paragraph
	Stage 2: EIRP Near Field Radiation Pattern Measurement and EIRP Near Field DUT power measurement	
1	Axis Alignment	B.2.3.1
2	Measurement Distance Uncertainty	B.2.3.2
3	Quality of the Quiet Zone	B.2.3.3
4	Mismatch	B.2.3.4
5	Multiple Reflections: Coupling between Measurement Antenna and DUT	B.2.3.5
6	Uncertainty of the RF power measurement equipment	B.2.3.6
7	Phase curvature	B.2.3.7
8	Amplifier uncertainties	B.2.3.8
9	Random uncertainty	B.2.3.9
10	Influence of the XPD	B.2.3.10
11	NF to FF truncation	B.2.3.11
12	Probe Polarization Amplitude and Phase	B.2.3.12
13	Probe Array Uniformity (for multi-probe systems only)	B.2.3.13
14	Phase Recovery Non-Linearity over signal bandwidth	B.2.3.16
15	Probe Pattern Effect	B.2.3.17
16	Phase Drift and Noise	B.2.3.20
17	Leakage and Crosstalk	B.2.3.25
	Stage 1: Calibration measurement	
18	Mismatch	B.2.3.4
19	Amplifier uncertainties	B.2.3.8
20	Uncertainty of the Network Analyzer	B.2.3.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.3.15
22	Phase centre offset of calibration	B.2.3.18
23	Quality of the Quiet Zone for Calibration Process	B.2.3.19
24	Mismatch in the connection of the calibration antenna	B.2.3.21

The uncertainty assessment table is organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].
- The uncertainty assessment for EIRP is provided in Table B.6.1-2.

Table B.6.3-2: Uncertainty assessment for EIRP measurement (f=TBD, D=TBD)

UID	Description of uncertainty contribution	Uncertainty Value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
	Stage 2: EIRP Near Field Radiation Pattern Measurement and EIRP Near Field DUT power measurement				
1	Axis Alignment				
2	Measurement Distance Uncertainty				
3	Quality of the Quiet Zone				
4	Mismatch				
5	Multiple Reflections: Coupling between Measurement Antenna and DUT				
6	Uncertainty of the RF power measurement equipment				
7	Phase curvature				
8	Amplifier uncertainties				
9	Random uncertainty				
10	Influence of the XPD				
11	NF to FF truncation				
12	Probe Polarization Amplitude and Phase				
13	Probe Array Uniformity (for multi-probe systems only)				
14	Phase Recovery Non-Linearity over signal bandwidth				
15	Probe Pattern Effect				
16	Phase Drift and Noise				
17	Leakage and Crosstalk				
	Stage 1: Calibration measurement				
18	Mismatch				
19	Amplifier uncertainties				
20	Uncertainty of the Network Analyzer				
21	Uncertainty of the absolute gain of the calibration antenna				
22	Phase centre offset of calibration				
23	Quality of the Quiet Zone for Calibration Process				
24	Mismatch in the connection of the calibration antenna				
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					

NOTE 1: The impact of phase variation on EIRP shall be taken into account during final MU definition for the test method.
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA
NOTE 3: The assessment assumes maximum DUT output power.
NOTE 4: The Phase Recovery Non-Linearity over signal bandwidth shall be taken into account during final MU definition for the test method.

B.6a UE Maximum Output Power – EIRP with UL Gaps

B.6a.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.6a.1-1.

Table B.6a.1-1: Uncertainty contributions for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.1.36
2	Amplifier uncertainties	B.2.1.8
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
3	Influence of noise	B.2.1.27

On top of uncertainty factors defined for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement defined in table B.6a.1-1, for $EIRP_{meas_peak}$ measurement, Table B.3.1-1applies (only measurement uncertainty factors applicable to EIRP measurement).

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].
- The uncertainty assessment for UE Maximum Output Power – EIRP with UL Gaps is provided in Table B.6a.1-2.

Table B.6a.1-2: Uncertainty assessment for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	FFS	FFS	FFS	FFS
2	Amplifier uncertainties	FFS	FFS	FFS	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
3	Influence of noise				FFS
Total measurement uncertainty					**Value**
Relative EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					FFS

On top of uncertaintiy calculation defined for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement defined in table B.3.1-2 for $EIRP_{meas_peak}$ measurement, table B.3.1-2 applies respectively (only measurement uncertainty factors applicable to EIRP measurement).

B.6a.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.6a.2-1.

Table B.6a.2-1: Uncertainty contributions for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.2.36
2	Amplifier uncertainties	B.2.2.8
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
3	Influence of noise	B.2.2.27

On top of uncertainty factors defined for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement defined in table B.6a.2-1, for $EIRP_{meas_peak}$ measurement, Table B.3.2-1 applies (only measurement uncertainty calculation applicable to EIRP measurement).

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz}.
- The uncertainty assessment for UE Maximum Output Power – EIRP with UL Gaps is provided in Table B.6a.2-2 for PC3 UEs and in Table B.6a.2-3 for PC1 UEs.

Table B.6a.2-2: Uncertainty assessment for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	0.4	Normal	2.00	0.2
2	Amplifier uncertainties	0.5	Rectangular	1.73	0.29
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
3	Influence of noise (23.45GHz <= f <= 40.8GHz)				1.0
	Total measurement uncertainty				Value
	EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]				1.7
NOTE 1: Measurement uncertainties in this table assume absolute power measurements involved in the same relative power measurement are performed over the same RF path.					

Table B.6a.2-3: Uncertainty assessment for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	0.4	Normal	2.00	0.2
2	Amplifier uncertainties	[0.5]	Rectangular	1.73	[0.29]
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
3	Influence of noise (23.45GHz <= f <= 40.8GHz)				1.0
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					[1.7]
NOTE 1: Measurement uncertainties in this table assume absolute power measurements involved in the same relative power measurement are performed over the same RF path.					

Table B.6a.2-4: Uncertainty assessment for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF power measurement equipment	FFS	Normal	2.0	FFS
2	Amplifier uncertainties	FFS	Rectangular	1.73	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
3	Influence of noise (23.45GHz <= f <= 40.8GHz)				FFS
Total measurement uncertainty					Value
Relative EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					FFS

Table B.6a.2-5: Uncertainty assessment for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF power measurement equipment	FFS	Normal	2.0	FFS
2	Amplifier uncertainties	FFS	Rectangular	1.73	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
3	Influence of noise (23.45GHz <= f <= 40.8GHz)				FFS
Total measurement uncertainty Table B.3.2-2					Value
Relative EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					FFS

On top of uncertaintiy calculation defined for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement defined in tables B.6a.2-2 (PC3-normal temperature conditions), B.6a.2-3 (PC3 extreme temperature conditions), B.6a.2-4 (PC1 normal temperature conditions) and B.6a.2-5 (PC1 extreme conditions), for $EIRP_{meas_peak}$ measurement, Tables B.3.2-2 (PC3 normal temperature conditions), B.3.2-8 (PC3 extreme temperature conditions), B.3.2-6 (PC1 normal temperature conditions) and B.3.2-9 (PC1 extreme temperature conditions) apply respectively (only measurement uncertainty calculation applicable to EIRP measurement).

B.6a.3 Uncertainty budget format and assessment for NFTF

The uncertainty contributions that may impact the overall MU value are listed in Table B.6a.3-1.

Table B.6a.3-1: Uncertainty contributions for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.3.30
2	Amplifier uncertainties	B.2.3.8
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
3	Influence of noise (23.45GHz <= f <= 40.8GHz)	B.2.3.29

On top of uncertainty factors defined for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement defined in table B.6a.3-1, for $EIRP_{meas_peak}$ measurement, Table B.3.3-1 applies (only measurement uncertainty calculation applicable to EIRP measurement).

The uncertainty assessment table is organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].
- The uncertainty assessment for UE Maximum Output Power – EIRP with UL Gaps is provided in Table B.6a.3-2

Table B.6a.3-2: Uncertainty assessment for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	FFS	FFS	FFS	FFS
2	Amplifier uncertainties	FFS	FFS	FFS	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
3	Influence of noise (23.45GHz <= f <= 40.8GHz)				FFS
Total measurement uncertainty					**Value**
Relative EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					FFS

On top of uncertainty calculation defined for P_{UMAX,f,c_GAP_ON} - P_{UMAX,f,c_GAP_OFF} measurement defined in tables B.6a.3-2 for $EIRP_{meas_peak}$ measurement, Tables B.3.3-2 applies(only measurement uncertainty calculation applicable to EIRP measurement).

B.7 Minimum Output power

Following tables summarize the MU threshold for EIRP measurements for Minimum Output Power. The origin MU values for different test setups can be found in following clauses.

Table B.7-1: MU threshold for EIRP measurement for Minimum output power

Power Class	Frequency	MBW	Power	Threshold MU value for NTC [dB] (NOTE1)	Threshold MU value For ETC [dB] (NOTE1)
PC1	23.45GHz ≤ f ≤ 32.125GHz	BW ≤ 400MHz	P = Minimum Output Power for SISO	5.66	5.92
	32.125GHz < f ≤ 40.8GHz			5.96	6.22
	23.45GHz ≤ f ≤ 32.125GHz		P = Minimum Output Power for MIMO	5.51	5.77
	32.125GHz < f ≤ 40.8GHz			5.66	5.92
PC3, PC7 (NOTE2)	23.45GHz ≤ f ≤ 32.125GHz	BW ≤ 400MHz	P = Minimum Output Power	6.15	6.41
	32.125GHz < f ≤ 40.8GHz			6.15	6.41
	40.8GHz < f ≤ 44.3GHz			7.34	7.48
PC5	23.45GHz ≤ f ≤ 32.125GHz	BW ≤ 400MHz	P = Minimum Output Power	6.36	6.62
PC6	23.45GHz ≤ f ≤ 32.125GHz	BW ≤ 400MHz	P = Minimum Output Power	6.35	6.61

NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.7.2-2 and Table B.7.2-5 for PC3 and PC6 UEs and Table B.7.2-3 and Table B.7.2-6 for PC1 and PC5 UEs.
NOTE 2: MU thresholds for PC7 limited to FR2a (23.45GHz <= f <= 32.125GHz), SISO and MBW <=100MHz.
NOTE 3: The MU values are valid for both SISO and MIMO for power classes other than PC1. For PC1, specific MU values for SISO and MIMO are defined separately above.

B.7.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.7.1-1.

Table B.7.1-1: Uncertainty contributions for EIRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of quiet zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing Wave Between the DUT and measurement antenna	B.2.1.5
6	Uncertainty of the RF power measurement equipment	B.2.1.6
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Influence of beam peak search grid	B.2.1.23
14	Multiple measurement antenna uncertainty	B.2.1.25
15	DUT repositioning	B.2.1.26
Stage 1: Calibration measurement		
16	Mismatch	B.2.1.4
17	Amplifier uncertainties	B.2.1.8
18	Misalignment of positioning System	B.2.1.13
19	Uncertainty of the Network Analyzer	B.2.1.14
20	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
22	Phase centre offset of calibration antenna	B.2.1.18
23	Quality of quiet zone for calibration process	B.2.1.19
24	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
25	Influence of the calibration antenna feed cable	B.2.1.21
26	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
27	Systematic error related to beam peak search	B.2.1.28
28	Influence of noise	B.2.1.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {23.45 GHz, 32.125 GHz, 40.8 GHz, 44.3 GHz}, P = [Minimum output power].
- The uncertainty assessment for EIRP is provided in Table B.7.1-2.

Table B.7.1-2: Uncertainty assessment for EIRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment				
2	Measure distance uncertainty				
3	Quality of quiet zone (NOTE 2)				
4	Mismatch (NOTE 3)				
5	Standing Wave Between the DUT and measurement antenna				
6	Uncertainty of the RF power measurement equipment (NOTE 4)				
7	Phase curvature				
8	Amplifier uncertainties				
9	Random uncertainty				
10	Influence of the XPD				
11	Insertion Loss Variation				
12	RF leakage (from measurement antenna to the receiver/transmitter)				
13	Influence of beam peak search grid (NOTE 6)				
14	Multiple measurement antenna uncertainty				
15	DUT repositioning		Actual	1	
Stage 1: Calibration measurement					
16	Mismatch				
17	Amplifier uncertainties				
18	Misalignment of positioning System				
19	Uncertainty of the Network Analyzer				
20	Uncertainty of the absolute gain of the calibration antenna				
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna				
22	Phase centre offset of calibration antenna				
23	Quality of quiet zone for calibration process (NOTE 2)				
24	Standing wave between reference calibration antenna and measurement antenna				
25	Influence of the calibration antenna feed cable				
26	Insertion Loss Variation				
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					
Systematic uncertainties (NOTE 7)					**Value**
27	Systematic error related to beam peak search				
28	Influence of noise				
Total measurement uncertainty					
EIRP total measurement uncertainty [dB]					

NOTE 1: The analysis was done only for the case of operating at Minimum output power, in-band, non-CA.
NOTE 2: The assessment assumes DUT Minimum output power.
NOTE 3: This contributor shall only be considered for EIRP measurements.
NOTE 4: Void
NOTE 5: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 6: Void.
NOTE 7: Void
NOTE 8: Value based on procedure defined in Annex D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.

B.7.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.7.2-1.

Table B.7.2-1: Uncertainty contributions for EIRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	Uncertainty of the RF power measurement equipment	B.2.2.6
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Influence of beam peak search grid	B.2.2.23
14	Multiple measurement antenna uncertainty	B.2.2.25
15	DUT repositioning	B.2.2.26
Stage 1: Calibration measurement		
16	Mismatch	B.2.2.4
17	Amplifier Uncertainties	B.2.2.8
18	Misalignment of positioning System	B.2.2.13
19	Uncertainty of the Network Analyzer	B.2.2.14
20	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
22	Phase centre offset of calibration antenna	B.2.2.18
23	Quality of quiet zone for calibration process	B.2.2.19
24	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
25	Influence of the calibration antenna feed cable	B.2.2.21
26	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
27	Systematic error related to beam peak search	B.2.2.28
28	Influence of noise	B.2.2.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz}, P = Minimum output power.
- The uncertainty assessment for EIRP is provided in Table B.7.2-2 for PC3 UEs and in Table B.7.2-3 for PC1 UEs.

Table B.7.2-2: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 and PC6 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 8) (23.45GHz <= f <= 40.8GHz)	0.6	Actual	1.00	0.6
3	Quality of Quiet Zone (NOTE 8) (40.8GHz < f <= 44.3GHz)	0.7	Actual	1.00	0.7
4	Mismatch (NOTE 1) (23.45GHz <= f <= 40.8GHz)	1.30	Actual	1.00	1.30
4	Mismatch (NOTE 1) (40.8GHz < f <= 44.3GHz)	1.70	Actual	1.00	1.70
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2) (23.45GHz <= f <= 40.8GHz)	2.50	Normal	2.00	1.25
6	Uncertainty of the RF power measurement equipment (NOTE 2) (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of beam peak search grid (NOTE 3)	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 9)	0.15	Actual	1	0.15
15	DUT repositioning (NOTE 3)	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.50	Normal	2.00	0.75
19	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.70	Normal	2.00	0.85
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 8) (23.45GHz <= f <= 40.8GHz)	0.4	Actual	1.00	0.4
23	Quality of quiet zone for calibration process (NOTE 8) (40.8GHz < f <= 44.3GHz)	0.5	Actual	1.00	0.5
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 5)				**Value**

27	Systematic error related to beam peak search (PC3)	0.5
27	Systematic error related to beam peak search (PC6)	0.7
28	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC3 and PC6)	1.0
28	Influence of noise (32.125GHz < f <= 40.8GHz) (PC3)	1.0
28	Influence of noise (40.8GHz < f <= 44.3GHz) (PC3)	1.0
Total measurement uncertainty		**Value**
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		6.15
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC6)		6.35
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		6.15
EIRP Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		7.34

NOTE 1: The analysis was done only for the case of operating at Minimum output power, in-band, non-CA and is valid for SISO and MIMO.
NOTE 2: The assessment assumes DUT Minimum output power.
NOTE 3: This contributor shall only be considered for EIRP measurements.
NOTE 4: Void
NOTE 5: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 6: Void.
NOTE 7: Void
NOTE 8: Value based on procedure defined in Annex D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.7.2-3: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 8)	0.60	Actual	1.00	0.60
4	Mismatch (NOTE 1)	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2)	2.50	Normal	2.00	1.25
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of beam peak search grid (NOTE 3)	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 9)	0.15	Actual	1	0.15
15	DUT repositioning (NOTE 3)	0.35	Rectangular	1.73	0.20
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 8)	0.40	Actual	1.00	0.40
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 5)				**Value**
27	Systematic error related to beam peak search				0.7
28	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC1) (SISO)				0.30
28	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC1) (MIMO)				0.15
28	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC5)				1.00
28	Influence of noise (32.125GHz < f <= 40.8GHz) (PC1) (SISO)				0.60
28	Influence of noise (32.125GHz < f <= 40.8GHz) (PC1) (MIMO)				0.30
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC1) (SISO)					5.66
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC1) (MIMO)					5.51
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC5)					6.36
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC1) (SISO)					5.96
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC1) (MIMO)					5.66

NOTE 1: The analysis was done only for the case of operating at Minimum output power, in-band, non-CA and is valid for SISO and MIMO.
NOTE 2: The assessment assumes DUT Minimum output power.
NOTE 3: This contributor shall only be considered for EIRP measurements.
NOTE 4: Void
NOTE 5: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 6: Void.
NOTE 7: Void
NOTE 8: Value based on procedure defined in Annex D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.

NOTE: MU assessment in Table B.7.2-2 and Table B7.2-3 is based on the following relaxations for 400MHz BW:

Table B.7.2-4: Minimum output power requirement relaxation considered in MU assessment for 400 MHz EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm)

Power Class	Diversity	Frequency Range	Relaxation (dB)
PC1	SISO	FR2a	0
		FR2b	0
PC2	SISO	FR2a	FFS
		FR2b	FFS
PC3	SISO	FR2a	8.4
		FR2b	13.5
		FR2c	14.5
PC3	MIMO	FR2a	5.4
		FR2b	10.5
		FR2c	FFS
PC4	SISO	FR2a	FFS
		FR2b	FFS
PC5, PC6	SISO, MIMO	FR2a	1.4

Table B.7.2-5: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 and PC6 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 8)	0.9	Actual	1.00	0.9
4	Mismatch (NOTE 1) (23.45GHz <= f <= 40.8GHz)	1.30	Actual	1.00	1.30
4	Mismatch (NOTE 1) (40.8GHz < f <= 44.3GHz)	1.70	Actual	1.00	1.70
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2) (23.45GHz <= f <= 40.8GHz)	2.50	Normal	2.00	1.25
6	Uncertainty of the RF power measurement equipment (NOTE 2) (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of beam peak search grid (NOTE 3)	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 9)	0.15	Actual	1	0.15
15	DUT repositioning (NOTE 3)	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.50	Normal	2.00	0.75
19	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.70	Normal	2.00	0.85
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 8)	0.6	Actual	1.00	0.6
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 5)				**Value**
27	Systematic error related to beam peak search (PC3)				0.5
27	Systematic error related to beam peak search (PC6)				0.7
28	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC3 and PC6)				1.0
28	Influence of noise (32.125GHz < f <= 40.8GHz) (PC3)				1.0
28	Influence of noise (40.8GHz < f <= 44.3GHz)				1.0
Total measurement uncertainty					**Value**

EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)	6.41
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC6)	6.61
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)	6.41
EIRP Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB]	7.48
NOTE 1: The analysis was done only for the case of operating at Minimum output power, in-band, non-CA and is valid for SISO and MIMO. NOTE 2: The assessment assumes DUT Minimum output power. NOTE 3: This contributor shall only be considered for EIRP measurements. NOTE 4: Void NOTE 5: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 6: Void. NOTE 7: Void NOTE 8: Value based on procedure defined in Annex D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm. NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.	

NOTE: MU assessment in Table B.7.2-5 is based on the relaxations for 400MHz BW in Table B.7.2-4.

Table B.7.2-6: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 8)	0.90	Actual	1	0.90
4	Mismatch (NOTE 1)	1.30	Actual	1	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2)	2.50	Normal	2	1.25
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2	1.05
9	Random uncertainty	0.50	Normal	2	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1	0.00
13	Influence of beam peak search grid (NOTE 3)	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 9)	0.15	Actual	1	0.15
15	DUT repositioning (NOTE 3)	0.35	Rectangular	1.73	0.20
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2	0.00
18	Misalignment of positioning System	0.00	Normal	2	0.00
19	Uncertainty of the Network Analyzer	1.50	Normal	2	0.75
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 8)	0.60	Actual	1	0.60
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 5)				Value
27	Systematic error related to beam peak search				0.70
28	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC1) (SISO)				0.30
28	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC1) (MIMO)				0.15
28	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC5)				1.00
28	Influence of noise (32.125GHz < f <= 40.8GHz) (PC1) (SISO)				0.60
28	Influence of noise (32.125GHz < f <= 40.8GHz) (PC1) (MIMO)				0.30
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC1) (SISO)					5.92
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC1) (MIMO)					5.75
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC5)					6.62
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC1) (SISO)					6.22
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC1) (MIMO)					5.92

NOTE 1: The analysis was done only for the case of operating at Minimum output power, in-band, non-CA and is valid for SISO and MIMO.
NOTE 2: The assessment assumes DUT Minimum output power.
NOTE 3: This contributor shall only be considered for EIRP measurements.
NOTE 4: Void
NOTE 5: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 6: Void.
NOTE 7: Void
NOTE 8: Value based on procedure defined in Annex D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.

B.8 Transmit OFF power

Following tables summarize the MU threshold for TRP measurements for Transmit OFF power. The origin MU values for different test setups can be found in following clauses.

Table B.8-1: MU threshold for TRP measurement for Transmit OFF power

Power Class	Frequency	MBW	Power	Threshold MU value (NOTE1)
PC3	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Off Power	5.67
	32.125GHz < f <= 40.8GHz			5.67
	40.8GHz < f <= 44.3GHz			6.86
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Off Power	5.67
	32.125GHz < f <= 40.8GHz			5.67
PC5, PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Off Power	5.67
NOTE 1: Total TRP Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.8.2-2 for PC3 UEs and Table B.8.2-6 for PC1, PC5 and PC6 UEs. NOTE 2: The MU values are valid for SISO and MIMO.				

Table B.8-2: Void

B.8.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.8.1-1.

Table B.8.1-1: Uncertainty contributions for TRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of quiet zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing Wave Between the DUT and measurement antenna	B.2.1.5
6	Uncertainty of the RF power measurement equipment	B.2.1.6
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Influence of TRP measurement grid	B.2.1.22
14	Influence of beam peak search grid	B.2.1.23
15	Multiple measurement antenna uncertainty	B.2.1.25
16	DUT repositioning	B.2.1.26
Stage 1: Calibration measurement		
17	Mismatch	B.2.1.4
18	Amplifier uncertainties	B.2.1.8
19	Misalignment of positioning System	B.2.1.13
20	Uncertainty of the Network Analyzer	B.2.1.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
23	Phase centre offset of calibration antenna	B.2.1.18
24	Quality of quiet zone for calibration process	B.2.1.19
25	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
26	Influence of the calibration antenna feed cable	B.2.1.21
27	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
28	Systematic error due to TRP calculation/quadrature	B.2.1.24
29	Influence of noise	B.2.1.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {23.45 GHz, 32.125 GHz, 40.8 GHz, 44.3 GHz}, P = [Off power].
- The uncertainty assessment for TRP is provided in Table B.8.1-2.

Table B.8.1-2: Uncertainty assessment for TRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment				
2	Measure distance uncertainty				
3	Quality of quiet zone (NOTE 2)				
4	Mismatch (NOTE 3)				
5	Standing Wave Between the DUT and measurement antenna				
6	Uncertainty of the RF power measurement equipment (NOTE 4)				
7	Phase curvature				
8	Amplifier uncertainties				
9	Random uncertainty				
10	Influence of the XPD				
11	Insertion Loss Variation				
12	RF leakage (from measurement antenna to the receiver/transmitter)				
13	Influence of TRP measurement grid (NOTE 5)				
14	Influence of beam peak search grid (NOTE 6)				
15	Multiple measurement antenna uncertainty				
16	DUT repositioning		Actual	1	
Stage 1: Calibration measurement					
17	Mismatch				
18	Amplifier uncertainties				
19	Misalignment of positioning System				
20	Uncertainty of the Network Analyzer				
21	Uncertainty of the absolute gain of the calibration antenna				
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna				
23	Phase centre offset of calibration antenna				
24	Quality of quiet zone for calibration process (NOTE 2)				
25	Standing wave between reference calibration antenna and measurement antenna				
26	Influence of the calibration antenna feed cable				
27	Insertion Loss Variation				
TRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					
Systematic uncertainties (NOTE 7)					**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 5)				
29	Influence of noise				
Total measurement uncertainty					
TRP total measurement uncertainty [dB]					

NOTE 1: The impact of phase variation on EIRP is FFS.
NOTE 2: The quality of quiet zone is different for EIRP and TRP. For TRP, the standard uncertainty is FFS; for EIRP, the standard uncertainty of quiet zone is FFS.
NOTE 3: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 4: The assessment assumes maximum DUT output power.
NOTE 5: This contributor shall only be considered for TRP measurements.
NOTE 6: This contributor shall only be considered for EIRP measurements.
NOTE 7: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.

B.8.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.8.2-1.

Table B.8.2-1: Uncertainty contributions for TRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	Uncertainty of the RF power measurement equipment	B.2.2.6
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Influence of TRP measurement grid	B.2.2.22
14	Influence of beam peak search grid	B.2.2.23
15	Multiple measurement antenna uncertainty	B.2.2.25
16	DUT repositioning	B.2.2.26
Stage 1: Calibration measurement		
17	Mismatch	B.2.2.4
18	Amplifier Uncertainties	B.2.2.8
19	Misalignment of positioning System	B.2.2.13
20	Uncertainty of the Network Analyzer	B.2.2.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
23	Phase centre offset of calibration antenna	B.2.2.18
24	Quality of quiet zone for calibration process	B.2.2.19
25	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
26	Influence of the calibration antenna feed cable	B.2.2.21
27	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
28	Systematic error due to TRP calculation/quadrature	B.2.2.24
29	Influence of noise	B.2.2.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz, 44.3 GHz}, P = Off power.
- The uncertainty assessment for TRP is provided in Table B.8.2-2 for PC3 UEs and Table B.8.2-6 for PC1 and PC5 UEs.

Table B.8.2-2: Uncertainty assessment for TRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3 GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 8) (23.45GHz <= f <= 40.8GHz)	0.6	Actual	1.00	0.6
3	Quality of Quiet Zone (NOTE 8) (40.8GHz < f <= 44.3GHz)	0.7	Actual	1.00	0.7
4	Mismatch (NOTE 1) (23.45GHz <= f <= 40.8GHz)	1.30	Actual	1.00	1.30
4	Mismatch (NOTE 1) (40.8GHz < f <= 44.3GHz)	1.70	Actual	1.00	1.70
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2) (23.45GHz <= f <= 40.8GHz)	2.50	Normal	2.00	1.25
6	Uncertainty of the RF power measurement equipment (NOTE 2) (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 3)	0.25	Actual	1	0.25
14	Influence of beam peak search grid	0.00	Actual	1	0.00
15	Multiple measurement antenna uncertainty (NOTE 9)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.5	Normal	2.00	0.75
20	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.7	Normal	2.00	0.85
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 8) (23.45GHz <= f <= 40.8GHz)	0.4	Actual	1.00	0.4
24	Quality of quiet zone for calibration process (NOTE 8) (40.8GHz < f <= 44.3GHz)	0.5	Actual	1.00	0.5
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
26	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 5)				**Value**

28	Systematic error due to TRP calculation/quadrature (NOTE 3)	0.0
29	Influence of noise (23.45GHz <= f <= 32.125GHz)	1.0
29	Influence of noise (32.125GHz < f <= 40.8GHz)	1.0
29	Influence of noise (40.8GHz < f <= 44.3GHz)	1.0
Total measurement uncertainty		**Value**
TRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]		5.67
TRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]		5.67
TRP Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB]		6.86

NOTE 1: The analysis was done only for the case of operating at TX OFF power, in-band, non-CA and is valid for SISO and MIMO.
NOTE 2: The assessment assumes DUT Off power.
NOTE 3: This contributor shall only be considered for TRP measurements.
NOTE 4: Void
NOTE 5: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 6: Void.
NOTE 7: Void
NOTE 8: Value based on procedure defined in Annex D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.8.2-3: Void

Table B.8.2-4: Void

Table B.8.2-5: Void

Table B.8.2-6: Uncertainty assessment for TRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1, PC5 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment (PC1, PC5)	0.02	Normal	2.00	0.01
1	Positioning misalignment (PC6)	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 8)	0.6	Actual	1.00	0.6
4	Mismatch (NOTE 1)	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2)	2.50	Normal	2.00	1.25
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 3)	0.25	Actual	1	0.25
14	Influence of beam peak search grid	0.00	Actual	1	0.00
15	Multiple measurement antenna uncertainty (NOTE 9)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 8)	0.4	Actual	1.00	0.4
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
26	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 5)				**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 3)				0.0
29	Influence of noise (23.45GHz <= f <= 32.125GHz)				1.0
29	Influence of noise (32.125GHz < f <= 40.8GHz) (PC1)				1.0
Total measurement uncertainty					**Value**
TRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					5.67
TRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC1)					5.67

NOTE 1:	The analysis was done only for the case of operating at TX OFF power, in-band, non-CA and is valid for SISO and MIMO.
NOTE 2:	The assessment assumes DUT Off power.
NOTE 3:	This contributor shall only be considered for TRP measurements.
NOTE 4:	Void
NOTE 5:	In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 6:	Void.
NOTE 7:	Void
NOTE 8:	Value based on procedure defined in Annex D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 9:	Applies to the system which has a structure of mechanical feed antenna positioning.

NOTE: MU assessment in Table B.8.2-2 and Table B.8.2-6 is based on the following relaxation for 400MHz BW.

Table B.8.2-7: Transmit OFF power requirement relaxation considered in MU assessment for 400 MHz EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm)

Power Class	Diversity	Frequency Range	Relaxation (dB)
PC1, PC2, PC3, PC4, PC5, PC6	SISO, MIMO	FR2a	30.4
		FR2b	35.5
		FR2c	36.5

B.9 ON/OFF time mask

B.9.1 ON power subtest

MU threshold for EIRP measurements in the ON power subtest in the Transmit ON/OFF time mask test case is specified in Table B.3-1. The origin MU values for different test setups can be found in following subclauses.

B.9.1.1 Uncertainty budget format and assessment for DFF

Uncertainty budget format and assessment for IFF for EIRP measurement is contained in clause B.3.1.

B.9.1.2 Uncertainty budget format and assessment for IFF

Uncertainty budget format and assessment for IFF for EIRP measurement is contained in clause B.3.2.

B.9.2 OFF power subtest

MU threshold for EIRP measurements in the OFF power subtest in the Transmit ON/OFF time mask test case. The origin MU values for different test setups can be found in following subclauses.

Table B.9.2-1: MU threshold for EIRP measurement for Transmit OFF power

Frequency	CBW	Power	Threshold MU value for NTC [dB] (NOTE1)	Threshold MU value for ETC [dB] (NOTE1)
23.45GHz <= f <= 32.125GHz	50MHz	P = Off Power	6.15	6.41
	100MHz			

	200MHz			
	400MHz			
32.125GHz < f <= 40.8GHz	50MHz	P = Off Power	6.15	6.41
	100MHz			
	200MHz			
	400MHz			
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.8.2-4 for PC3 UEs				

B.9.2.1 Uncertainty budget format and assessment for DFF

FFS

B.9.2.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.9.2.2-1.

Table B.9.2.2-1: Uncertainty contributions for EIRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	Uncertainty of the RF power measurement equipment	B.2.2.6
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Influence of TRP measurement grid	B.2.2.22
14	Influence of beam peak search grid	B.2.2.23
15	Multiple measurement antenna uncertainty	B.2.2.25
16	DUT repositioning	B.2.2.26
Stage 1: Calibration measurement		
17	Mismatch	B.2.2.4
18	Amplifier Uncertainties	B.2.2.8
19	Misalignment of positioning System	B.2.2.13
20	Uncertainty of the Network Analyzer	B.2.2.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
23	Phase centre offset of calibration antenna	B.2.2.18
24	Quality of quiet zone for calibration process	B.2.2.19
25	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
26	Influence of the calibration antenna feed cable	B.2.2.21
27	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
28	Systematic error due to TRP calculation/quadrature	B.2.2.24
29	Influence of noise	B.2.2.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz}, P = Off power.

Table B.9.2.2-2: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 8)	0.6	Actual	1.00	0.6
4	Mismatch (NOTE 1)	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2)	2.50	Normal	2.00	1.25
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of beam peak search grid (NOTE 3)	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 9)	0.15	Actual	1	0.15
15	DUT repositioning (NOTE 3)	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 8)	0.4	Actual	1.00	0.4
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 5)				**Value**
27	Systematic error related to beam peak search				0.5
28	Influence of noise (23.45GHz <= f <= 32.125GHz)				1
28	Influence of noise (32.125GHz < f <= 40.8GHz)				1
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					6.15
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					6.15

NOTE 1: The analysis was done only for the case of operating at TX OFF power, in-band, non-CA.
NOTE 2: The assessment assumes DUT Off power.
NOTE 3: This contributor shall only be considered for EIRP measurements.
NOTE 4: Void
NOTE 5: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 6: Void.
NOTE 7: Void
NOTE 8: Value based on procedure defined in Annex D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.9.2.2-3: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 8)	0.9	Actual	1.00	0.9
4	Mismatch (NOTE 1)	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2)	2.50	Normal	2.00	1.25
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of beam peak search grid (NOTE 3)	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 9)	0.15	Actual	1	0.15
15	DUT repositioning (NOTE 3)	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 8)	0.6	Actual	1.00	0.6
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 5)				**Value**
27	Systematic error related to beam peak search				0.5
28	Influence of noise (23.45GHz <= f <= 32.125GHz)				1
28	Influence of noise (32.125GHz < f <= 40.8GHz)				1
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					6.41
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					6.41

NOTE 1: The analysis was done only for the case of operating at TX OFF power, in-band, non-CA.
NOTE 2: The assessment assumes DUT Off power.
NOTE 3: This contributor shall only be considered for EIRP measurements.
NOTE 4: Void
NOTE 5: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 6: Void.
NOTE 7: Void
NOTE 8: Value based on procedure defined in Annex D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.

NOTE: MU assessment in Table B.9.2.2-2 and Table B.9.2.2-3 is based on the relaxation in Table B.9.2.2-4.

Table B.9.2.2-4: Transmit OFF power (EIRP) requirement relaxation considered in MU assessment (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm)

Frequency	Power Class	Relaxation			
		CHBW 50MHz	CHBW 100MHz	CHBW 200MHz	CHBW 400MHz
23.45GHz <= f <= 32.125GHz	PC1	EIRP - 1dB	EIRP + 2dB	EIRP + 5dB	EIRP + 8dB
	PC2	FFS	FFS	FFS	FFS
	PC3	EIRP - 1dB	EIRP + 2dB	EIRP + 5dB	EIRP + 8dB
	PC4	FFS	FFS	FFS	FFS
32.125GHz <= f <= 40.8GHz	PC1	EIRP + 2dB	EIRP + 5dB	EIRP + 8dB	EIRP + 11dB
	PC2	FFS	FFS	FFS	FFS
	PC3	EIRP + 2dB	EIRP + 5dB	EIRP + 8dB	EIRP + 11dB
	PC4	FFS	FFS	FFS	FFS
NOTE: EIRP is the measured UE rms ON power level in ON/OFF time mask testing.					

B.9a Power control

B.9a.1 Absolute power tolerance

B.9a.2 Relative power control tolerance

B.9a.2.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.9a.2.1-1.

Table B.9a.2.1-1: Uncertainty contributions for EIRP relative power control tolerance measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.1.36
2	Amplifier uncertainties	B.2.1.8
3	Impact of frequency response	FFS
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
4	Influence of noise	B.2.1.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D

- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].

- The uncertainty assessment for EIRP relative power control tolerance is provided in Table B.9a.2.1-2.

Table B.9a.2.1-2: Uncertainty assessment for EIRP relative power control tolerance measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	FFS	FFS	FFS	FFS
2	Amplifier uncertainties	FFS	FFS	FFS	FFS
3	Impact of frequency response	FFS	FFS	FFS	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
4	Influence of noise				FFS
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					FFS
NOTE 1: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.					

B.9a.2.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.9a.2.2-1.

Table B.9a.2.2-1: Uncertainty contributions for EIRP relative power control tolerance measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.2.36
2	Amplifier uncertainties	B.2.2.8
3	Impact of frequency response	FFS
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
4	Influence of noise	B.2.2.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D

- The uncertainty assessment has been derived for the case of Quiet Zone size ≤ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz}.

- The uncertainty assessment for EIRP relative power control tolerance is provided in Table B.9a.2.2-2.for PC3 UEs and in Table B.9a.2.2-3 for PC1 UEs.

Table B.9a.2.2-2: Uncertainty assessment for EIRP relative power control tolerance measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	[0.4]	Normal	2.00	[0.2]
2	Amplifier uncertainties	0.5	Rectangular	1.73	0.29
3	Impact of frequency response	FFS	FFS	FFS	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
4	Influence of noise (23.45GHz <= f <= 40.8GHz)				1.0
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					[1.7]
NOTE 1: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 2: Power step size assumed ΔP = 1 dB. NOTE 3: Measurement uncertainties in this table assume absolute power measurements involved in the same relative power measurement are performed over the same RF path.					

Table B.9a.2.2-3: Uncertainty assessment for EIRP relative power control tolerance measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF power measurement equipment	FFS	Normal	2.0	FFS
2	Amplifier uncertainties	FFS	Rectangular	1.73	FFS
3	Impact of frequency response	FFS	FFS	FFS	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
4	Influence of noise (23.45GHz <= f <= 40.8GHz)				FFS
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					FFS
NOTE 1: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.					

B.9a.2.3 Uncertainty budget format and assessment for NFTF

The uncertainty contributions that may impact the overall MU value are listed in Table B.9a.2.3-1.

Table B.9a.2.3-1: Uncertainty contributions for EIRP relative power control tolerance measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.3.30
2	Amplifier uncertainties	B.2.3.8
3	Impact of frequency response	FFS
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
4	Influence of noise	B.2.3.29

The uncertainty assessment table is organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].
- The uncertainty assessment for EIRP relative power control tolerance is provided in Table B.9a.2.3-2

Table B.9a.2.3-2: Uncertainty assessment for EIRP relative power control tolerance measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	FFS	FFS	FFS	FFS
2	Amplifier uncertainties	FFS	FFS	FFS	FFS
3	Impact of frequency response	FFS	FFS	FFS	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
4	Influence of noise				FFS
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					FFS
NOTE 1: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.					

B.9a.3 Aggregate Power control tolerance

B.9a.3.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.9a.3.1-1.

Table B.9a.3.1-1: Uncertainty contributions for EIRP aggregate power control tolerance measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.1.36
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
2	Influence of noise	B.2.1.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D

- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].

- The uncertainty assessment for EIRP aggregate power control tolerance is provided in Table B.9a.3.1-2.

Table B.9a.3.1-2: Uncertainty assessment for EIRP aggregate power control tolerance measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	FFS	FFS	FFS	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
2	Influence of noise				FFS
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					FFS
NOTE 1: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.					

B.9a.3.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.9a.3.2-1.

Table B.9a.3.2-1: Uncertainty contributions for EIRP aggregate power control tolerance measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.2.36
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
2	Influence of noise	B.2.2.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D

- The uncertainty assessment has been derived for the case of Quiet Zone size ≤ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz}.

- The uncertainty assessment for EIRP aggregate power control tolerance is provided in Table B.9a.3.2-2.for PC3 UEs and in Table B.9a.3.2-3 for PC1 UEs.

Table B.9a.3.2-2: Uncertainty assessment for EIRP aggregate power control tolerance measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	0.4	Normal	2.00	0.2
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
2	Influence of noise (23.45GHz <= f <= 40.8GHz)				1.0
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					1.4
NOTE 1: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 2: Power step size assumed ΔP = 1 dB. NOTE 3: Measurement uncertainties in this table assume absolute power measurements involved in the same relative power measurement are performed over the same RF path.					

Table B.9a.3.2-3: Uncertainty assessment for EIRP aggregate power control tolerance measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF power measurement equipment	FFS	Normal	2.0	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
2	Influence of noise (23.45GHz <= f <= 40.8GHz)				FFS
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					FFS
NOTE 1: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.					

B.9a.3.3 Uncertainty budget format and assessment for NFTF

The uncertainty contributions that may impact the overall MU value are listed in Table B.9a.3.3-1.

Table B.9a.3.3-1: Uncertainty contributions for EIRP aggregate power control tolerance measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.3.30
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
2	Influence of noise	B.2.3.29

The uncertainty assessment table is organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D

- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].

- The uncertainty assessment for EIRP aggregate power control tolerance is provided in Table B.9a.3.3-2

Table B.9a.3.3-2: Uncertainty assessment for EIRP aggregate power control tolerance measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	FFS	FFS	FFS	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
2	Influence of noise				FFS
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					FFS
NOTE 1: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.					

B.10 Frequency error

Following tables summarize the MU threshold for EIRP measurements for Frequency error. The origin MU values for different test setups can be found in following subclauses.

Table B.10-1: MU threshold for beam peak measurement for Frequency error

Power Class	Frequency	MBW	Power	Threshold MU value for NTC and ETC (NOTE1)
PC3	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	+/- 0.01 ppm
	32.125GHz < f <= 40.8GHz			+/- 0.01 ppm
	40.8GHz < f <= 44.3GHz			
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	+/- 0.01 ppm
	32.125GHz < f <= 40.8GHz			+/- 0.01 ppm
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in section B.10.2 NOTE 2: The MU values are valid for SISO and MIMO.				

B.10.1 Uncertainty budget format and assessment for DFF

+/- 0.01 ppm

- The uncertainty assessment has been derived for the case of D = [5 cm], f = {23.45 GHz, 32.125 GHz, 40.8 GHz, 44.3GHz}, P = [Maximum output power]. This uncertainty has no dependency with extreme temperature conditions.

B.10.2 Uncertainty budget format and assessment for IFF

+/- 0.01 ppm

- The uncertainty assessment has been derived for the case of Quiet zone size ≤ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz}, P = [Maximum output power].
- The analysis is valid for SISO and MIMO.

B.11 Carrier leakage

Editor's Note: MU value analysis for PC1, 2 and 4 are not complete.

Following tables summarize the MU threshold for EIRP measurements for carrier leakage. The origin MU values for different test setups can be found in following subclauses.

Table B.11-1: MU threshold for EIRP measurement for carrier leakage

Power Class	Frequency	MBW	Power (NOTE2)	Threshold MU value for NTC [dB] (NOTE 1)
PC3, PC7 (NOTE2)	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = 0 + MU to 0 + (MU + Uplink power control window size) dBm	5.44
	32.125GHz < f <= 40.8GHz			5.57
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	FFS	FFS
	32.125GHz < f <= 40.8GHz			FFS
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.11.2-2 for PC3 UEs and FFS for PC1 UEs. NOTE 2: MU thresholds for PC7 limited to FR2a (23.45GHz <= f <= 32.125GHz), SISO and MBW <=100MHz.				

B.11.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.11.1-1.

Table B.11.1-1: Uncertainty contributions for EIRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of quiet zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing Wave Between the DUT and measurement antenna	B.2.1.5
6	Uncertainty of the RF power measurement equipment	B.2.1.6
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Influence of TRP measurement grid	B.2.1.22
14	Influence of beam peak search grid	B.2.1.23
15	Multiple measurement antenna uncertainty	B.2.1.25
16	DUT repositioning	B.2.1.26
Stage 1: Calibration measurement		
17	Mismatch	B.2.1.4
18	Amplifier uncertainties	B.2.1.8
19	Misalignment of positioning System	B.2.1.13
20	Uncertainty of the Network Analyzer	B.2.1.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
23	Phase centre offset of calibration antenna	B.2.1.18
24	Quality of quiet zone for calibration process	B.2.1.19
25	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
26	Influence of the calibration antenna feed cable	B.2.1.21
27	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
28	Systematic error due to TRP calculation/quadrature	B.2.1.24
29	Influence of noise	B.2.1.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {23.45 GHz, 32.125 GHz, 40.8 GHz}, P = [Maximum output power].
- The uncertainty assessment is provided in Table B.11.1-2.

Table B.11.1-2: Uncertainty assessment for EIRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment				
2	Measure distance uncertainty				
3	Quality of quiet zone (NOTE 2)				
4	Mismatch (NOTE 3)				
5	Standing Wave Between the DUT and measurement antenna				
6	Uncertainty of the RF power measurement equipment (NOTE 4)				
7	Phase curvature				
8	Amplifier uncertainties				
9	Random uncertainty				
10	Influence of the XPD				
11	Insertion Loss Variation				
12	RF leakage (from measurement antenna to the receiver/transmitter)				
13	Influence of TRP measurement grid (NOTE 5)				
14	Influence of beam peak search grid (NOTE 6)				
15	Multiple measurement antenna uncertainty				
16	DUT repositioning				
Stage 1: Calibration measurement					
17	Mismatch				
18	Amplifier uncertainties				
19	Misalignment of positioning System				
20	Uncertainty of the Network Analyzer				
21	Uncertainty of the absolute gain of the calibration antenna				
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna				
23	Phase centre offset of calibration antenna				
24	Quality of quiet zone for calibration process (NOTE 2)				
25	Standing wave between reference calibration antenna and measurement antenna				
26	Influence of the calibration antenna feed cable				
27	Insertion Loss Variation				
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					
Systematic uncertainties (NOTE 7)					**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 5)				
29	Influence of noise				
Total measurement uncertainty					
EIRP total measurement uncertainty [dB]					

NOTE 1: The impact of phase variation on EIRP is FFS.
NOTE 2: The quality of quiet zone is different for EIRP and TRP. For TRP, the standard uncertainty is FFS; for EIRP, the standard uncertainty of quiet zone is FFS.
NOTE 3: The analysis was done only for the case of operating at 0dBm output power, in-band, non-CA.
NOTE 4: The assessment assumes 0 dBm UE output power – carrier leakage requirement.
NOTE 5: This contributor shall only be considered for TRP measurements.
NOTE 6: This contributor shall only be considered for EIRP measurements.
NOTE 7: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 8: Void

B.11.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.12.2-1.

Table B.11.2-1: Uncertainty contributions for EIRP measurement

UID	Description of uncertainty contribution	Details in clause
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	Uncertainty of the RF power measurement equipment	B.2.2.6
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Influence of TRP measurement grid	B.2.2.22
14	Influence of beam peak search grid	B.2.2.23
15	Multiple measurement antenna uncertainty	B.2.2.25
16	DUT repositioning	B.2.2.26
Stage 1: Calibration measurement		
17	Mismatch	B.2.2.4
18	Amplifier Uncertainties	B.2.2.8
19	Misalignment of positioning System	B.2.2.13
20	Uncertainty of the Network Analyzer	B.2.2.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
23	Phase centre offset of calibration antenna	B.2.2.18
24	Quality of quiet zone for calibration process	B.2.2.19
25	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
26	Influence of the calibration antenna feed cable	B.2.2.21
27	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
28	Systematic error due to TRP calculation/quadrature	B.2.2.24
29	Influence of noise	B.2.2.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz}, for PC3 with measured UE power in the range 0dBm + MU to 0dBm + MU + uplink power control window size, where

- MU is the test system uplink absolute power measurement uncertainty for minimum output power in Table B.7.2-2.

- Uplink power control window size = 1dB (UE power step size) + 5 dB (UE power step tolerance) + (Test system uplink relative power measurement uncertainty), where, the UE power step tolerance is specified in TS 38.101-1 [2], Table 6.3.4.3-1 and is 5dB for 1dB power step size, and the Test system uplink relative power measurement uncertainty is specified in Table F.1.2-1 in TS 38.521-2 for TC 6.4.2.2 with a value of 1.4 dB.

- The uncertainty assessment for EIRP is provided in Table B.17.2-2 for PC3 UEs and Table B.17.2-3 for PC1 UEs.

Table B.11.2-2: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 10)	0.52	Actual	1.00	0.52
4	Mismatch (NOTE 2)	1.84	Actual	1.00	1.84
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 3, 7)	2.50	Normal	2.00	1.25
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.00	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 4)	0.0	Actual	1	0.0
14	Influence of beam peak search grid (NOTE 5)	0.00	Actual	1	0.00
15	Multiple measurement antenna uncertainty (NOTE 9)	0.0	Actual	1	0.0
16	DUT repositioning (NOTE 4)	0.00	Rectangular	1.73	0.00
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.00	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 10)	0.32	Actual	1.00	0.32
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
26	Influence of the calibration antenna feed cable	0.00	Normal	2.00	0.00
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					5.24
	Systematic uncertainties (NOTE 6)				**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 4)				0.00
29	Influence of noise (23.45GHz ≤ f ≤ 32.125GHz)				0.20
29	Influence of noise (32.125GHz < f ≤ 40.8GHz)				0.33
30	Beam peak search				0.00
Total measurement uncertainty					**Value**
EIRP total measurement uncertainty (23.45GHz ≤ f ≤ 32.125GHz) [dB]					5.44
EIRP total measurement uncertainty (32.125GHz < f ≤ 40.8GHz) [dB]					5.57

NOTE 1: Void
NOTE 2: The analysis was done only for the case of measured UE power in the range from 0dBm + MU to 0dBm + MU + uplink power control window size, in-band, non-CA.
NOTE 3: The assessment assumes measured power in the range from 0dBm + MU – carrier leakage requirement to 0dBm + MU + uplink power control window – carrier leakage requirement.
NOTE 4: This contributor shall only be considered for TRP measurements.
NOTE 5: Void
NOTE 6: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 7: Void
NOTE 8: Void
NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 10: Defined as fixed value MU contributor.

Table B.11.2-3: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	FFS	Rectangular	1.73	FFS
3	Quality of Quiet Zone (NOTE 10)	FFS	Actual	1.00	FFS
4	Mismatch (NOTE 2, NOTE 7)	FFS	Actual	1.00	FFS
5	Standing wave between the DUT and measurement antenna	FFS	U-shaped	1.41	FFS
6	Uncertainty of the RF power measurement equipment (NOTE 3, 7)	FFS	Normal	2.00	FFS
7	Phase curvature	FFS	U-shaped	1.41	FFS
8	Amplifier uncertainties	FFS	Normal	2.00	FFS
9	Random uncertainty	FFS	Normal	2.00	FFS
10	Influence of the XPD	FFS	U-shaped	1.41	FFS
11	Insertion Loss Variation	FFS	Rectangular	1.73	FFS
12	RF leakage (from measurement antenna to the receiver/transmitter)	FFS	Actual	1.00	FFS
13	Influence of TRP measurement grid (NOTE 4)	0.00	Actual	1	0.00
14	Influence of beam peak search grid (NOTE 5)	0.00	Actual	1	0.00
15	Multiple measurement antenna uncertainty (NOTE 9)	FFS	Actual	1	FFS
16	DUT repositioning (NOTE 4)	0.00	Rectangular	1.73	0.00
Stage 1: Calibration measurement					
17	Mismatch	FFS	U-shaped	1.41	FFS
18	Amplifier Uncertainties	FFS	Normal	2.00	FFS
19	Misalignment of positioning System	FFS	Normal	2.00	FFS
20	Uncertainty of the Network Analyzer	FFS	Normal	2.00	FFS
21	Uncertainty of the absolute gain of the calibration antenna	FFS	Normal	2.00	FFS
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	FFS	Rectangular	1.73	FFS
23	Phase centre offset of calibration antenna	FFS	Rectangular	1.73	FFS
24	Quality of quiet zone for calibration process (NOTE 10)	FFS	Actual	1.00	FFS
25	Standing wave between reference calibration antenna and measurement antenna	FFS	U-shaped	1.41	FFS
26	Influence of the calibration antenna feed cable	FFS	Normal	2.00	FFS
27	Insertion Loss Variation	FFS	Rectangular	1.73	FFS
TRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					FFS
	Systematic uncertainties (NOTE 6)				**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 4)				0.00
29	Influence of noise				FFS
30	Beam peak search				FFS
Total measurement uncertainty					**Value**
EIRP total measurement uncertainty [dB]					FFS

NOTE 1: Void
NOTE 2: The analysis was done only for the case of measured UE power in the range from FFS to FFS, in-band, non-CA.
NOTE 3: The assessment assumes measured power in the range from FFS to FFS.
NOTE 4: This contributor shall only be considered for TRP measurements.
NOTE 5: Void
NOTE 6: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 7: Void.
NOTE 8: Void.
NOTE 9: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 10: Defined as fixed value MU contributor.

B.12 Error Vector Magnitude

Following tables summarize the MU threshold for Error Vector Magnitude (EVM) measurements. The origin MU values for different test setups can be found in following subclauses.

Table B.12-1: MU threshold for beam peak measurement for Frequency error

Power Class	Frequency	MBW	Power	Threshold MU value for NTC and ETC (NOTE1)
PC3	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	PUSCH: Table B.12.2-1. PUCCH: Table B.12.2-9 PRACH: FFS
	32.125GHz < f <= 40.8GHz			PUSCH: Table B.12.2-2. PUCCH: Table B.12.2-9 PRACH: FFS
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	PUSCH: Table B.12.2-5 PUCCH: Table B.12.2-9 PRACH: FFS
	32.125GHz < f <= 40.8GHz			FFS
PC5, PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	PUSCH: Table B.12.PUCCH: Table B.12.2-9 PRACH2-7 : FFS
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in section B.10.2				

B.12.1 Uncertainty budget format and assessment for DFF

FFS

B.12.2 Uncertainty budget format and assessment for IFF

Table B.12.2-1: Measurement Uncertainty (MU) for PUSCH, PC3, FR2a (23.45GHz <= f <= 32.125GHz)

Test ID	Modulation	RB alloc.	50MHz	100MHz	200MHz	400MHz
1	DFT-s-OFDM PI/2 BPSK	Inner_Full	2.78%	3.85%	5.44%	7.69%
2	DFT-s-OFDM PI/2 BPSK	Outer_Full	3.10%	4.16%	5.88%	8.99%
3	DFT-s-OFDM QPSK	Inner_Full	2.78%	3.85%	5.44%	7.69%
4	DFT-s-OFDM QPSK	Outer_Full	3.10%	4.16%	5.88%	8.99%
5	DFT-s-OFDM 16 QAM	Inner_Full	3.31%	4.50%	6.36%	11.21%
6	DFT-s-OFDM 16 QAM	Outer_Full	3.60%	4.73%	6.68%	11.21%
7	DFT-s-OFDM 64 QAM	Inner_Full	4.26%	5.96%	8.41%	15.84%
8	DFT-s-OFDM 64 QAM	Outer_Full	5.01%	7.08%	9.99%	15.84%
9	CP-OFDM QPSK	Inner_Full	3.60%	4.73%	6.68%	11.89%
10	CP-OFDM QPSK	Outer_Full	3.71%	4.99%	7.07%	11.89%
11	CP-OFDM 16 QAM	Inner_Full	4.26%	5.96%	8.41%	15.84%
12	CP-OFDM 16 QAM	Outer_Full	4.26%	5.96%	8.41%	15.84%
13	CP-OFDM 64 QAM	Inner_Full	6.31%	8.91%	12.59%	21.13%
14	CP-OFDM 64 QAM	Outer_Full	6.31%	8.91%	12.59%	21.13%

Table B.12.2-2: Measurement Uncertainty (MU) for PUSCH, PC3, FR2b (32.125GHz < f <= 40.8GHz)

Test ID	Modulation	RB alloc.	50MHz	100MHz	200MHz	400MHz
1	DFT-s-OFDM PI/2 BPSK	Inner_Full	3.56%	4.83%	6.91%	9.65%
2	DFT-s-OFDM PI/2 BPSK	Outer_Full	4.15%	5.69%	8.11%	12.50%
3	DFT-s-OFDM QPSK	Inner_Full	3.56%	4.83%	6.91%	9.65%
4	DFT-s-OFDM QPSK	Outer_Full	4.15%	5.69%	8.11%	12.50%
5	DFT-s-OFDM 16 QAM	Inner_Full	4.54%	6.26%	8.91%	18.06%
6	DFT-s-OFDM 16 QAM	Outer_Full	5.09%	7.19%	10.15%	18.06%
7	DFT-s-OFDM 64 QAM	Inner_Full	6.78%	9.58%	13.54%	25.50%
8	DFT-s-OFDM 64 QAM	Outer_Full	8.06%	11.38%	16.09%	25.50%
9	CP-OFDM QPSK	Inner_Full	5.09%	7.19%	10.15%	19.13%
10	CP-OFDM QPSK	Outer_Full	5.39%	7.61%	10.75%	19.13%
11	CP-OFDM 16 QAM	Inner_Full	6.78%	9.58%	13.54%	25.50%
12	CP-OFDM 16 QAM	Outer_Full	6.78%	9.58%	13.54%	25.50%
13	CP-OFDM 64 QAM	Inner_Full	10.14%	14.33%	20.25%	34.01%
14	CP-OFDM 64 QAM	Outer_Full	10.14%	14.33%	20.25%	34.01%

- The uncertainty assessment has been derived for the case of Quiet zone size ≤ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz}, P = [Maximum output power].
- Values above are calculated considering a TE noise floor assumption of -10.6 dBm/400 MHz for FR2a and -8.5 dBm/400 MHz for FR2b and additional TE measurement uncertainty (not related to TE noise floor) as shown in Table B.12-2-3 and Table B.12-2-4 added quadratically.

Table B.12.2-3: Additional TE EVM MU (not related to TE noise floor) for PUSCH and PUCCH, PC3, FR2a (23.45GHz <= f <= 32.125GHz)

Test ID	Modulation	RB alloc.	50MHz	100MHz	200MHz	400MHz
1	DFT-s-OFDM PI/2 BPSK	Inner_Full	2.50%	3.44%	4.86%	6.87%
2	DFT-s-OFDM PI/2 BPSK	Outer_Full	2.50%	3.26%	4.61%	6.58%
3	DFT-s-OFDM QPSK	Inner_Full	2.50%	3.44%	4.86%	6.87%
4	DFT-s-OFDM QPSK	Outer_Full	2.50%	3.26%	4.61%	6.58%
5	DFT-s-OFDM 16 QAM	Inner_Full	2.50%	3.29%	4.65%	6.45%
6	DFT-s-OFDM 16 QAM	Outer_Full	2.50%	3.01%	4.25%	6.45%
7	DFT-s-OFDM 64 QAM	Inner_Full	2.50%	3.43%	4.84%	9.12%
8	DFT-s-OFDM 64 QAM	Outer_Full	2.88%	4.07%	5.75%	9.12%
9	CP-OFDM QPSK	Inner_Full	2.50%	3.01%	4.25%	6.85%
10	CP-OFDM QPSK	Outer_Full	2.50%	3.16%	4.48%	6.85%
11	CP-OFDM 16 QAM	Inner_Full	2.50%	3.43%	4.84%	9.12%
12	CP-OFDM 16 QAM	Outer_Full	2.50%	3.43%	4.84%	9.12%
13	CP-OFDM 64 QAM	Inner_Full	3.63%	5.12%	7.25%	12.16%
14	CP-OFDM 64 QAM	Outer_Full	3.63%	5.12%	7.25%	12.16%
NOTE 1: For PUCCH, only values from Test ID 4 are considered disregarding the PUCCH waveform.						

Table B.12.2-4: Additional TE EVM MU (not related to TE noise floor) for PUSCH and PUCCH, PC3, FR2b (32.125GHz < f <= 40.8GHz)

Test ID	Modulation	RB alloc.	50MHz	100MHz	200MHz	400MHz
1	DFT-s-OFDM PI/2 BPSK	Inner_Full	3.00%	4.00%	5.75%	8.00%
2	DFT-s-OFDM PI/2 BPSK	Outer_Full	3.00%	4.00%	5.75%	8.00%
3	DFT-s-OFDM QPSK	Inner_Full	3.00%	4.00%	5.75%	8.00%
4	DFT-s-OFDM QPSK	Outer_Full	3.00%	4.00%	5.75%	8.00%
5	DFT-s-OFDM 16 QAM	Inner_Full	3.00%	4.00%	5.75%	10.93%
6	DFT-s-OFDM 16 QAM	Outer_Full	3.08%	4.35%	6.14%	10.93%
7	DFT-s-OFDM 64 QAM	Inner_Full	4.10%	5.79%	8.19%	15.44%
8	DFT-s-OFDM 64 QAM	Outer_Full	4.87%	6.88%	9.73%	15.44%
9	CP-OFDM QPSK	Inner_Full	3.08%	4.35%	6.14%	11.58%
10	CP-OFDM QPSK	Outer_Full	3.26%	4.60%	6.50%	11.58%
11	CP-OFDM 16 QAM	Inner_Full	4.10%	5.79%	8.19%	15.44%
12	CP-OFDM 16 QAM	Outer_Full	4.10%	5.79%	8.19%	15.44%
13	CP-OFDM 64 QAM	Inner_Full	6.12%	8.66%	12.25%	20.59%
14	CP-OFDM 64 QAM	Outer_Full	6.12%	8.66%	12.25%	20.59%
NOTE 1: For PUCCH, only values from Test ID 4 are considered disregarding the PUCCH waveform.						

Table B.12.2-5: Measurement Uncertainty (MU) for PUSCH, PC1, FR2a (23.45GHz <= f <= 32.125GHz)

50MHz	100MHz	200MHz	400MHz
2.48%	3.50%	4.95%	7.00%

- The uncertainty assessment has been derived for the case of Quiet zone size ≤ [30 cm], f = {23.45GHz, 32.125GHz}, P = [Maximum output power].

- Values above are calculated considering a TE noise floor assumption of -10.6 dBm/400 MHz for FR2a and additional TE measurement uncertainty (not related to TE noise floor) as shown in Table B.12-2-6 added quadratically.

Table B.12.2-6: Additional TE EVM MU (not related to TE noise floor) for PUSCH and PUCCH, PC1, FR2a (23.45GHz <= f <= 32.125GHz)

50MHz	100MHz	200MHz	400MHz
2.40%	3.39%	4.79%	6.68%

Table B.12.2-7: Measurement Uncertainty (MU) for PUSCH, PC5, PC6, FR2a (23.45GHz <= f <= 32.125GHz)

Test ID	Modulation	RB alloc.	50MHz	100MHz	200MHz	400MHz
1	DFT-s-OFDM PI/2 BPSK	Inner_Full	2.47%	3.50%	4.95%	7.00%
2	DFT-s-OFDM PI/2 BPSK	Outer_Full	2.54%	3.59%	5.08%	7.31%
3	DFT-s-OFDM QPSK	Inner_Full	2.47%	3.50%	4.95%	7.00%
4	DFT-s-OFDM QPSK	Outer_Full	2.54%	3.59%	5.08%	7.31%
5	DFT-s-OFDM 16 QAM	Inner_Full	2.58%	3.65%	5.17%	7.84%
6	DFT-s-OFDM 16 QAM	Outer_Full	2.65%	3.74%	5.30%	7.84%
7	DFT-s-OFDM 64 QAM	Inner_Full	2.81%	3.97%	5.62%	8.71%
8	DFT-s-OFDM 64 QAM	Outer_Full	2.96%	4.18%	5.91%	8.71%
9	CP-OFDM QPSK	Inner_Full	2.65%	3.74%	5.30%	7.95%
10	CP-OFDM QPSK	Outer_Full	2.67%	3.78%	5.35%	7.95%
11	CP-OFDM 16 QAM	Inner_Full	2.81%	3.97%	5.62%	8.71%
12	CP-OFDM 16 QAM	Outer_Full	2.81%	3.97%	5.62%	8.71%
13	CP-OFDM 64 QAM	Inner_Full	3.23%	4.56%	6.45%	9.91%
14	CP-OFDM 64 QAM	Outer_Full	3.23%	4.56%	6.45%	9.91%

- The uncertainty assessment has been derived for the case of Quiet zone size ≤ [30 cm], f = {23.45GHz, 32.125GHz}, P = [Maximum output power].

- Values above are calculated considering a TE noise floor assumption of -10.6 dBm/400 MHz for FR2a and additional TE measurement uncertainty (not related to TE noise floor) as shown in Table B.12-2-8 added quadratically.

Table B.12.2-8: Additional TE EVM MU (not related to TE noise floor) for PUSCH and PUCCH, PC5, PC6, FR2a (23.45GHz <= f <= 32.125GHz)

50MHz	100MHz	200MHz	400MHz
2.42%	3.43%	4.85%	6.85%

Table B.12.2-9: Measurement Uncertainty (MU) for PUCCH, PC3 (23.45GHz <= f <= 40.8GHz), PC1, PC5, PC6 (23.45GHz <= f <= 32.125GHz)

Power Class	Frequency	50MHz	100MHz	200MHz	400MHz
PC3	23.45GHz <= f <= 32.125GHz	3.23%	4.36%	6.17%	9.00%
	32.125GHz < f <= 40.8GHz	4.39%	6.05%	8.62%	12.51%
PC1	23.45GHz <= f <= 32.125GHz	2.96%	4.18%	5.91%	8.29%
PC5, PC6	23.45GHz <= f <= 32.125GHz	2.56%	3.63%	5.14%	7.31%

- The uncertainty assessment has been derived for the case of Quiet zone size ≤ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz}, P = [Maximum output power].
- Values above are calculated considering a TE noise floor assumption of -10.6 dBm/400 MHz for FR2a and -8.5 dBm/400 MHz for FR2b and additional TE measurement uncertainty (not related to TE noise floor) as shown in Test ID 4 of Table B.12.2-3 for PC3, FR2a, Test ID 4 of Table B.12.2-4 for PC3, FR2b, Table B.12.2-6 for PC1, and Table B.12.2-8 for PC5 and PC6 added quadratically.

B.13 to B.14

B.15 Occupied bandwidth

Following tables summarize the MU threshold for EIRP measurements for Occupied bandwidth. The origin MU values for different test setups can be found in following subclauses.

Table B.15-1: MU threshold for beam peak measurement for Occupied bandwidth (SISO)

Power Class	Frequency	Power	BW	MBW/BW	Threshold MU value (NOTE1) [%CBW]
PC3, PC1	23.45 GHz ≤ f ≤ 32.125 GHz	P = Max Output Power	50 MHz	1.5	±0.4
			100 MHz	1.5	±0.4
			200 MHz	1.5	±1.2
			400 MHz	1.5	±1.2
	32.125 GHz < f ≤ 40.8 GHz	P = Max Output Power	50 MHz	1.5	±0.4
			100 MHz	1.5	±0.4
			200 MHz	1.5	±1.3
			400 MHz	1.5	±1.3
PC3	40.8GHz < f <= 44.3GHz	P = Max Output Power	50 MHz	1.5	±0.65
			100 MHz	1.5	±0.65
			200 MHz	1.5	±1.3
			400 MHz	1.3	±1.5
PC5, PC6	23.45 GHz ≤ f ≤ 32.125 GHz	P = Max Output Power	50 MHz	1.5	±0.4
			100 MHz	1.5	±0.4
			200 MHz	1.5	±1.2
			400 MHz	1.5	±1.2
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm.					

Table B.15-2: MU threshold for beam peak measurement for Occupied bandwidth (MIMO)

Power Class	Frequency	Power	BW	MBW/BW	Threshold MU value (NOTE1) [%CBW]
PC3	23.45 GHz ≤ f ≤ 32.125 GHz	P = Max Output Power	50 MHz	1.5	±0.4
			100 MHz	1.5	±0.4
			200 MHz	1.5	±1.2
			400 MHz	1.5	±1.3
	32.125 GHz < f ≤ 40.8 GHz	P = Max Output Power	50 MHz	1.5	±0.4
			100 MHz	1.5	±0.4
			200 MHz	1.5	±1.3
			400 MHz	1.3	±1.7
	40.8GHz < f <= 44.3GHz	P = Max Output Power	50 MHz	1.5	±0.65
			100 MHz	1.5	±0.65
			200 MHz	1.3	±1.3
			400 MHz	1.2	±2.0
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm.					

B.15.1 Uncertainty budget format and assessment for DFF

FFS

- The uncertainty assessment has been derived for the case of D = [5 cm], f = {23.45 GHz, 32.125 GHz, 40.8 GHz, 44.3 GHz }, P = [Maximum output power].

B.15.2 Uncertainty budget format and assessment for IFF

FFS

- The uncertainty assessment has been derived for the case of Quiet Zone size ≤ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz, 44.3 GHz }, P = Maximum output power.

B.16 Spectrum emission mask

Following tables summarize the MU threshold for TRP measurements for Spectrum emission mask. The origin MU values for different test setups can be found in following subclauses.

Table B.16-1: MU threshold for TRP measurement for Spectrum emission mask

Power Class	Frequency	MBW	Power	Threshold MU value (NOTE 1)
PC5, PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.13
PC3	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.13
	32.125GHz < f <= 40.8GHz			5.51
	40.8GHz < f <= 44.3GHz			6.86
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	6.32
	32.125GHz < f <= 40.8GHz			FFS
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.16.2-2 for PC3 UEs and in Table B.16.2-4 for PC1, PC5 and PC6 UEs NOTE 2: The MU values are valid for SISO and MIMO.				

B.16.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.16.1-1.

Table B.16.1-1: Uncertainty contributions for TRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of quiet zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing Wave Between the DUT and measurement antenna	B.2.1.5
6	Uncertainty of the RF power measurement equipment	B.2.1.6
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Influence of TRP measurement grid	B.2.1.22
14	Influence of beam peak search grid	B.2.1.23
15	Multiple measurement antenna uncertainty	B.2.1.25
16	DUT repositioning	B.2.1.26
Stage 1: Calibration measurement		
17	Mismatch	B.2.1.4
18	Amplifier uncertainties	B.2.1.8
19	Misalignment of positioning System	B.2.1.13
20	Uncertainty of the Network Analyzer	B.2.1.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
23	Phase centre offset of calibration antenna	B.2.1.18
24	Quality of quiet zone for calibration process	B.2.1.19
25	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
26	Influence of the calibration antenna feed cable	B.2.1.21
27	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
28	Systematic error due to TRP calculation/quadrature	B.2.1.24
29	Influence of noise	B.2.1.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {23.45 GHz, 32.125 GHz, 40.8 GHz}, P = [Maximum output power].
- The uncertainty assessment for TRP is provided in Table B.16.1-2.

Table B.16.1-2: Uncertainty assessment for TRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment				
2	Measure distance uncertainty				
3	Quality of quiet zone (NOTE 2)				
4	Mismatch (NOTE 3)				
5	Standing Wave Between the DUT and measurement antenna				
6	Uncertainty of the RF power measurement equipment (NOTE 4)				
7	Phase curvature				
8	Amplifier uncertainties				
9	Random uncertainty				
10	Influence of the XPD				
11	Insertion Loss Variation				
12	RF leakage (from measurement antenna to the receiver/transmitter)				
13	Influence of TRP measurement grid (NOTE 5)				
14	Influence of beam peak search grid (NOTE 6)				
15	Multiple measurement antenna uncertainty				
16	DUT repositioning				
Stage 1: Calibration measurement					
17	Mismatch				
18	Amplifier uncertainties				
19	Misalignment of positioning System				
20	Uncertainty of the Network Analyzer				
21	Uncertainty of the absolute gain of the calibration antenna				
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna				
23	Phase centre offset of calibration antenna				
24	Quality of quiet zone for calibration process (NOTE 2)				
25	Standing wave between reference calibration antenna and measurement antenna				
26	Influence of the calibration antenna feed cable				
27	Insertion Loss Variation				
TRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					
Systematic uncertainties (NOTE 7)					**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 5)				
29	Influence of noise				
Total measurement uncertainty					
TRP total measurement uncertainty [dB]					

NOTE 1: The impact of phase variation on EIRP is FFS.
NOTE 2: The quality of quiet zone is different for EIRP and TRP. For TRP, the standard uncertainty is FFS; for EIRP, the standard uncertainty of quiet zone is FFS.
NOTE 3: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 4: The assessment assumes maximum DUT output power.
NOTE 5: This contributor shall only be considered for TRP measurements.
NOTE 6: This contributor shall only be considered for EIRP measurements.
NOTE 7: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.

B.16.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.16.2-1.

Table B.16.2-1: Uncertainty contributions for TRP measurement

UID	Description of uncertainty contribution	Details in clause
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	Uncertainty of the RF power measurement equipment	B.2.2.6
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Influence of TRP measurement grid	B.2.2.22
14	Influence of beam peak search grid	B.2.2.23
15	Multiple measurement antenna uncertainty	B.2.2.25
16	DUT repositioning	B.2.2.26
Stage 1: Calibration measurement		
17	Mismatch	B.2.2.4
18	Amplifier Uncertainties	B.2.2.8
19	Misalignment of positioning System	B.2.2.13
20	Uncertainty of the Network Analyzer	B.2.2.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
23	Phase centre offset of calibration antenna	B.2.2.18
24	Quality of quiet zone for calibration process	B.2.2.19
25	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
26	Influence of the calibration antenna feed cable	B.2.2.21
27	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
28	Systematic error due to TRP calculation/quadrature	B.2.2.24
29	Influence of noise	B.2.2.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz}, P = [Maximum output power].
- The uncertainty assessment for TRP is provided in Table B.16.2-2 for PC3 UEs and in Table B.16.2-4 for PC1 and PC5 UEs.

Table B.16.2-2: Uncertainty assessment for TRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 9) (23.45GHz <= f <= 40.8GHz)	0.6	Actual	1.00	0.6
3	Quality of Quiet Zone (NOTE 1) (40.8GHz < f <= 44.3GHz)	0.7	Actual	1.00	0.7
4	Mismatch (NOTE 1) (23.45GHz <= f <= 40.8GHz)	1.30	Actual	1.00	1.30
4	Mismatch (40.8GHz < f <= 44.3GHz)	1.70	Actual	1.00	1.70
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2) (23.45GHz <= f <= 40.8GHz)	2.16	Normal	2.00	1.08
6	Uncertainty of the RF power measurement equipment (NOTE 3) (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 3)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 4)	0.00	Actual	1	0.00
15	Multiple measurement antenna uncertainty (NOTE 8)	0.15	Actual	1	0.15
16	DUT repositioning (NOTE 3)	0.00	Rectangular	1.73	0.00
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.50	Normal	2.00	0.75
20	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.70	Normal	2.00	0.85
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 9) (23.45GHz <= f <= 40.8GHz)	0.4	Actual	1.00	0.4
24	Quality of quiet zone for calibration process (NOTE 9) (40.8GHz < f <= 44.3GHz)	0.5	Actual	1.00	0.5
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
26	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00

	Systematic uncertainties (NOTE 5)	**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 3)	0.00
29	Influence of noise (23.45GHz <= f <= 32.125GHz)	0.62
29	Influence of noise (32.125GHz < f <= 40.8GHz)	1.00
29	Influence of noise (40.8GHz < f <= 44.3GHz)	1.00
Total measurement uncertainty		**Value**
TRP total measurement uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]		5.13
TRP total measurement uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]		5.51
TRP Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB]		6.86

NOTE 1: The analysis was done only for the case of operating at max output power, in-band, non-CA and is valid for SISO and MIMO.
NOTE 2: The assessment assumes maximum DUT output power.
NOTE 3: This contributor shall only be considered for TRP measurements.
NOTE 4: This contributor shall only be considered for EIRP measurements.
NOTE 5: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 6: Values extracted from TR 38.810 v2.6.1 in square brackets pending for further analysis.
NOTE 7: Void.
NOTE 8: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 9: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.

Table B.16.2-3: Void

Table B.16.2-4: Uncertainty assessment for TRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1, PC5 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment (PC1, PC5)	0.02	Normal	2.00	0.01
1	Positioning misalignment (PC6)	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 9)	0.60	Actual	1.00	0.60
4	Mismatch (NOTE 1)	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2)	2.16	Normal	2.00	1.08
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 3)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 4)	0.00	Actual	1	0.00
15	Multiple measurement antenna uncertainty (NOTE 8)	0.15	Actual	1	0.15
16	DUT repositioning (NOTE 3)	0.00	Rectangular	1.73	0.00
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 9)	0.40	Actual	1.00	0.40
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
26	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 5)				**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 3)				0.00
29	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC1)				1.81
29	Influence of noise (23.45GHz <= f <= 32.125GHz) (PC5 and PC6)				0.62
29	Influence of noise (32.125GHz < f <= 40.8GHz)				FFS
Total measurement uncertainty					**Value**
TRP total measurement uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC1)					6.32
TRP total measurement uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC5 and PC6)					5.13
TRP total measurement uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					FFS

NOTE 1: The analysis was done only for the case of operating at max output power, in-band, non-CA and is valid for SISO and MIMO.
NOTE 2: The assessment assumes maximum DUT output power.
NOTE 3: This contributor shall only be considered for TRP measurements.
NOTE 4: This contributor shall only be considered for EIRP measurements.
NOTE 5: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 6: Values extracted from TR 38.810 v2.6.1 in square brackets pending for further analysis.
NOTE 7: Void.
NOTE 8: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 9: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.

B.17 Adjacent Channel Leakage Ratio

Editor's Note: MU value analysis for PC1, 2 and 4 are not complete.

Following tables summarize the MU threshold for EIRP measurements for Adjacent Channel Leakage Ratio. The origin MU values for different test setups can be found in following subclauses.

Table B.17-1: MU threshold for TRP measurement for Adjacent Channel Leakage Ratio

Power Class	Frequency	MBW	Power	Threshold MU value (NOTE 1)
PC3	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	TBD
	32.125GHz < f <= 40.8GHz			TBD
	40.8GHz < f <= 44.3GHz			TBD
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	TBD
	32.125GHz < f <= 40.8GHz			TBD
PC5	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	TBD
NOTE 1: Total Expanded MU for IFF for a Quiet Zone size ≤ 30 cm in Table B.17.2-2 for PC3 UEs and B.17.2-3 for PC1 UEs.				

Table B.17-1B: MU threshold for EIRP measurement for Adjacent Channel Leakage Ratio

Power Class	Frequency	CBW	Power	Threshold MU value for NTC and ETC (NOTE 1)
PC3	23.45GHz <= f <= 32.125GHz	50MHz	P = Max Output Power	5.63
		100MHz		6.09
		200MHz		6.09 (NOTE5)
		400MHz		6.09 (NOTE2)
	32.125GHz < f <= 40.8GHz	50MHz	P = Max Output Power	6.09 (NOTE7)
		100MHz		6.09 (NOTE6)
		200MHz		6.09 (NOTE3)
		400MHz		6.09 (NOTE4)
	40.8GHz < f <= 44.3GHz	50MHz	P = Max Output Power	7.75 (NOTE 9)
		100MHz		7.75 (NOTE 10)
		200MHz		7.75 (NOTE 11)
		400MHz		7.75 (NOTE 12)
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	6.04
	32.125GHz < f <= 40.8GHz	BW <= 400MHz	P = Max Output Power	6.04
PC5, PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	6.04

NOTE 1: Total Expanded MU for IFF for a Quiet Zone size ≤ 30 cm in Table B.17.2-2 for PC3 UEs and Table B.17.2-3 for PC1, PC5 and PC6 UEs.
NOTE 2: This value is based on the relaxation of (MPR + T(MPR) – 6.0) dB for MPR > 3.0dB.
NOTE 3: Not applicable for MPR > 3.5dB
NOTE 4: Not applicable for MPR > 2.0dB
NOTE 5: This value is based on the relaxation of (MPR + T(MPR) – 9.0) dB for MPR > 5.0dB.
NOTE 6: Not applicable for MPR > 5.0dB
NOTE 7: Not applicable for MPR > 7.5dB
NOTE 8: The MU values are valid for SISO and MIMO.
NOTE 9: Not applicable for MPR > 5.5dB
NOTE 10: Not applicable for MPR > 4.0dB
NOTE 11: Not applicable for MPR > 2.5dB
NOTE 12: Not applicable for MPR > 0.0dB

B.17.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.17.1-1.

Table B.17.1-1: Uncertainty contributions for EIRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of quiet zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing Wave Between the DUT and measurement antenna	B.2.1.5
6	Uncertainty of the RF power measurement equipment	B.2.1.6
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Influence of TRP measurement grid	B.2.1.22
14	Influence of beam peak search grid	B.2.1.23
15	Multiple measurement antenna uncertainty	B.2.1.25
16	DUT repositioning	B.2.1.26
Stage 1: Calibration measurement		
17	Mismatch	B.2.1.4
18	Amplifier uncertainties	B.2.1.8
19	Misalignment of positioning System	B.2.1.13
20	Uncertainty of the Network Analyzer	B.2.1.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
23	Phase centre offset of calibration antenna	B.2.1.18
24	Quality of quiet zone for calibration process	B.2.1.19
25	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
26	Influence of the calibration antenna feed cable	B.2.1.21
27	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
28	Systematic error due to TRP calculation/quadrature	B.2.1.24
29	Influence of noise	B.2.1.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {23.45 GHz, 32.125 GHz, 40.8 GHz, 44.3 GHz}, P = [Maximum output power].
- The uncertainty assessment for TRP is provided in Table B.17.1-2.

Table B.17.1-2: Uncertainty assessment for EIRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment				
2	Measure distance uncertainty				
3	Quality of quiet zone (NOTE 2)				
4	Mismatch (NOTE 3)				
5	Standing Wave Between the DUT and measurement antenna				
6	Uncertainty of the RF power measurement equipment (NOTE 4)				
7	Phase curvature				
8	Amplifier uncertainties				
9	Random uncertainty				
10	Influence of the XPD				
11	Insertion Loss Variation				
12	RF leakage (from measurement antenna to the receiver/transmitter)				
13	Influence of TRP measurement grid (NOTE 5)				
14	Influence of beam peak search grid (NOTE 6)				
15	Multiple measurement antenna uncertainty				
16	DUT repositioning				
Stage 1: Calibration measurement					
17	Mismatch				
18	Amplifier uncertainties				
19	Misalignment of positioning System				
20	Uncertainty of the Network Analyzer				
21	Uncertainty of the absolute gain of the calibration antenna				
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna				
23	Phase centre offset of calibration antenna				
24	Quality of quiet zone for calibration process (NOTE 2)				
25	Standing wave between reference calibration antenna and measurement antenna				
26	Influence of the calibration antenna feed cable				
27	Insertion Loss Variation				
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					
Systematic uncertainties (NOTE 7)					**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 5)				
29	Influence of noise				
Total measurement uncertainty					
TRP total measurement uncertainty [dB]					

NOTE 1: The impact of phase variation on EIRP is FFS.
NOTE 2: The quality of quiet zone is different for EIRP and TRP. For TRP, the standard uncertainty is FFS; for EIRP, the standard uncertainty of quiet zone is FFS.
NOTE 3: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 4: The assessment assumes maximum DUT output power.
NOTE 5: This contributor shall only be considered for TRP measurements.
NOTE 6: This contributor shall only be considered for EIRP measurements.
NOTE 7: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 8: Void

B.17.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.17.2-1.

Table B.17.2-1: Uncertainty contributions for EIRP measurement

UID	Description of uncertainty contribution	Details in clause
Stage 2: DUT measurement		
1	Quality of Quiet Zone	B.2.2.3
2	Mismatch	B.2.2.4
3	Standing wave between the DUT and measurement antenna	B.2.2.5
4	Uncertainty of the RF power measurement equipment	B.2.2.6
5	Phase curvature	B.2.2.7
6	Amplifier uncertainties	B.2.2.8
7	Random uncertainty	B.2.2.9
8	Influence of the XPD	B.2.2.10
9	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
10	Multiple measurement antenna uncertainty	B.2.2.25
Stage 1: Calibration measurement		
11	Mismatch	B.2.2.4
12	Amplifier Uncertainties	B.2.2.8
13	Misalignment of positioning System	B.2.2.13
14	Uncertainty of the Network Analyzer	B.2.2.14
15	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
16	Phase centre offset of calibration antenna	B.2.2.18
17	Quality of quiet zone for calibration process	B.2.2.19
18	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
19	Influence of the calibration antenna feed cable	B.2.2.21
20	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
21	Influence of noise	B.2.2.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz}, P = Maximum output power - MPR – MBR(Multi-band relaxation).
- The uncertainty assessment for EIRP is provided in Table B.17.2-2 for PC3 UEs and Table B.17.2-3 for PC1 UEs.

Table B.17.2-2: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Quality of Quiet Zone (NOTE 10)	0.52	Actual	1.00	0.52
2	Mismatch (NOTE 2) (23.45GHz <= f <= 40.8GHz)	1.84	Actual	1.00	1.84
2	Mismatch (NOTE 2) (40.8GHz < f <= 44.3GHz)	2.40	Actual	1.00	2.40
3	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
4	Uncertainty of the RF power measurement equipment (NOTE 3, 7) (23.45GHz <= f <= 40.8GHz)	2.16	Normal	2.00	1.08
4	Uncertainty of the RF power measurement equipment (NOTE 3, 7) (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
5	Phase curvature	0.00	U-shaped	1.41	0.00
6	Amplifier uncertainties	2.1	Normal	2.00	1.05
7	Random uncertainty	0.50	Normal	2.00	0.25
8	Influence of the XPD	0.00	U-shaped	1.41	0.00
9	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
10	Multiple measurement antenna uncertainty (NOTE 9)	0.0	Actual	1	0.0
Stage 1: Calibration measurement					
11	Mismatch	0.00	U-shaped	1.41	0.00
12	Amplifier Uncertainties	0.00	Normal	2.00	0.00
13	Misalignment of positioning System	0.00	Normal	2.00	0.00
14	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.5	Normal	2.00	0.75
14	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.7	Normal	2.00	0.85
15	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
16	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
17	Quality of quiet zone for calibration process (NOTE 10)	0.32	Actual	1.00	0.32
18	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
19	Influence of the calibration antenna feed cable	0.00	Normal	2.00	0.00
20	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB] (23.45GHz <= f <= 40.8GHz)					5.09
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB] (40.8GHz < f <= 44.3GHz)					6.61
	Systematic uncertainties (NOTE 6)				**Value**
21	Influence of noise				Table B.17.2-4
Total measurement uncertainty					**Value**
EIRP total measurement uncertainty [dB] (23.45GHz <= f <= 40.8GHz)					5.09 + Influence of Noise
EIRP total measurement uncertainty [dB] (40.8GHz < f <= 44.3GHz)					6.61 + Influence of Noise

NOTE 1: Void
NOTE 2: The analysis was done only for the case of operating at max output power – MPR – MBR(Multi-band relaxation)., in-band, non-CA and is valid for SISO and MIMO.
NOTE 3: The assessment assumes maximum DUT output power – MPR – MBR(Multi-band relaxation).
NOTE 4: Void
NOTE 5: Void
NOTE 6: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 7: Void
NOTE 8: Void
NOTE 9: Void
NOTE 10: Defined as fixed value MU contributor.

Table B.17.2-3: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1, PC5 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Quality of Quiet Zone (NOTE 10)	0.52	Actual	1.00	0.52
2	Mismatch (NOTE 2, NOTE 7)	1.84	Actual	1.00	1.84
3	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
4	Uncertainty of the RF power measurement equipment (NOTE 3, 7)	2.16	Normal	2.00	1.08
5	Phase curvature	0.00	U-shaped	1.41	0.00
6	Amplifier uncertainties	2.1	Normal	2.00	1.05
7	Random uncertainty	0.50	Normal	2.00	0.25
8	Influence of the XPD	0.00	U-shaped	1.41	0.00
9	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
10	Multiple measurement antenna uncertainty (NOTE 9)	0.00	Actual	1	0.00
Stage 1: Calibration measurement					
11	Mismatch	0.00	U-shaped	1.41	0.00
12	Amplifier Uncertainties	0.00	Normal	2.00	0.00
13	Misalignment of positioning System	0.00	Normal	2.00	0.00
14	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
15	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
16	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
17	Quality of quiet zone for calibration process (NOTE 10)	0.32	Actual	1.00	0.32
18	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
19	Influence of the calibration antenna feed cable	0.00	Normal	2.00	0.00
20	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					5.09
	Systematic uncertainties (NOTE 6)				**Value**
21	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.95
21	Influence of noise (32.125GHz < f <= 40.8GHz) (PC1)				0.95
Total measurement uncertainty					**Value**
EIRP total measurement uncertainty (23.45GHz <= f <= 32.125GHz) [dB]					6.04
EIRP total measurement uncertainty (32.125GHz < f <= 40.8GHz) [dB] (PC1)					6.04

NOTE 1: Void
NOTE 2: The analysis was done only for the case of operating at max output power, in-band, non-CA and is valid for SISO and MIMO.
NOTE 3: The assessment assumes maximum DUT output power.
NOTE 4: Void
NOTE 5: Void
NOTE 6: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 7: Values extracted from TR 38.810 v2.6.1 in square brackets pending for further analysis.
NOTE 8: Void.
NOTE 9: Void
NOTE 10: Defined as fixed value MU contributor.

Table B.17.2-4: Influence of noise measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

	FR2a	FR2b	FR2c
ChBW (50MHz)	0.54	1.0 (NOTE 6)	1.14 (NOTE 8)
ChBW (100MHz)	1.0	1.0 (NOTE 5)	1.14 (NOTE 9)
ChBW (200MHz)	1.0 (NOTE 4)	1.0 (NOTE 2)	1.14 (NOTE 10)
ChBW (400MHz)	1.0 (NOTE 1)	1.0 (NOTE 3)	1.14 (NOTE 11)
NOTE 1: This value is based on the relaxation of (MPR + T(MPR) – 6.0) dB for MPR > 3.0dB. NOTE 2: Not applicable for MPR > 3.5dB NOTE 3: Not applicable for MPR > 2.0dB NOTE 4: This value is based on the relaxation of (MPR + T(MPR) – 9.0) dB for MPR > 5.0dB. NOTE 5: Not applicable for MPR > 5.0dB NOTE 6: Not applicable for MPR > 7.5dB NOTE 7: Values are valid for SISO and MIMO. NOTE 8: Not applicable for MPR > 5.5dB NOTE 9: Not applicable for MPR > 4.0dB NOTE 10: Not applicable for MPR > 2.5dB NOTE 11: Not applicable for MPR > 0.0dB			

B.18 Spurious emissions

Editor's Note:

- MU value analysis and offset value analysis for PC 2 and 4 are not complete.
- MU offset value analysis for PC2 and 4 are not complete.
- MU value analysis for various test setups in clause B.18.x is not complete for above 87 GHz.

Test procedure of general spurious emission comprises 2 stages: coarse TRP measurement and fine TRP measurement BW. Coarse TRP measurement is introduced to reduce the measurement time by applying sparser grids and/or wider measurement BW than fine TRP measurement while having offset dB more stringent test requirement in order not to cause additional misjudgement risk. For the frequency ranges for which coarse TRP measurement does not PASS, the measurement is continued with fine TRP measurement procedure.

Tables B.18-1, B.18-1a, B.18-1b summarizes the MU threshold for fine TRP measurements for General spurious emissions, spurious emission band UE co-existence and additional spurious emission, respectively. The origin MU values for fine TRP measurement for different test setups can be found in following subclauses.

Table B.18-1: MU threshold for TRP measurement for general spurious emission

Power Class	Frequency	In-band BW	In-band Power (NOTE2)	Threshold MU value [dB] (NOTE1)
PC3	6 GHz <= f <=12.75 GHz	BW <= 400MHz	P = Max Output Power	5.29
	12.75 GHz <= f <= 23.45 GHz			5.25
	23.45 GHz <= f <= 40.8 GHz			5.41
	40.8 GHz <= f <= 66 GHz			7.42
	66 GHz <= f <= 80 GHz			7.72
	80 GHz < f <= 87 GHz			8.14
PC1	6 GHz <= f <=12.75 GHz	BW <= 400MHz	P = Max Output Power	5.28
	12.75 GHz <= f <= 23.45 GHz			5.91
	23.45 GHz <= f <= 40.8 GHz			6.07
	40.8 GHz <= f <= 66 GHz			8.09
	66 GHz <= f <= 80 GHz			7.71
PC5, PC6	6 GHz <= f <=12.75 GHz	BW <= 400MHz	P = Max Output Power	5.28
	12.75 GHz <= f <= 23.45 GHz			5.24
	23.45 GHz <= f <= 40.8 GHz			5.40
	40.8 GHz <= f <= 66 GHz			7.42
	66 GHz <= f <= 80 GHz			7.71
	80 GHz < f <= 87 GHz			8.13
NOTE 1: Total EIRP Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.18.2-3 to Table B.18.2-11 for PC3 UEs and in Table B.18.2-12 to Table B.18.2-16 for PC1, PC5 and PC6 UEs. NOTE 2: Max output power level for device with corresponding power class. NOTE 3: The MU values are valid for SISO and MIMO.				

Table B.18-1a: MU threshold for TRP measurement for spurious emission band UE co-existence

Power Class	Frequency	In-band BW	In-band Power (NOTE2)	Threshold MU value [dB] (NOTE1)
PC3	n257, n260, n261	BW <= 400MHz	P = Max Output Power	6.00
	23.6 GHz < f <= 24.0 GHz			6.00
	36 GHz <= f <= 37 GHz			6.00
	57 GHz <= f <= 66 GHz			8.01
PC1	n257, n261	BW <= 400MHz	P = Max Output Power	7.32
	n260			7.32
	23.6 GHz < f <= 24.0 GHz			7.32
	57 GHz <= f <= 66 GHz			8.00
PC5, PC6	n260	BW <= 400MHz	P = Max Output Power	5.98
	23.6 GHz < f <= 24.0 GHz			5.98
	57 GHz <= f <= 66 GHz			8.00
NOTE 1: Total EIRP Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.18.2-3 to Table B.18.2-11 for PC3 UEs and in Table B.18.2-12 to Table B.18.2-16 for PC1, PC5 and PC6 UEs. NOTE 2: Max output power level for device with corresponding power class. NOTE 3: The MU values are valid for SISO and MIMO.				

Table B.18-1b: MU threshold for TRP measurement for additional spurious emission

Power Class	Frequency	In-band BW	In-band Power (NOTE2)	Threshold MU value [dB] (NOTE1)
PC3	6 GHz <= f <=12.75 GHz NS_202	BW <= 400MHz	P = Max Output Power	5.29
	12.75 GHz <= f <= 23.45 GHz NS_202			5.84
	23.45 GHz <= f <= 40.8 GHz NS_202, NS_203, NS_205			6.00
	40.8 GHz <= f <= 2nd harmonic of the upper frequency edge of the UL operating band NS_202			8.01
PC1	6 GHz <= f <=12.75 GHz NS_202	BW <= 400MHz	P = Max Output Power	5.28
	12.75 GHz <= f <= 23.45 GHz NS_202			7.16
	23.45 GHz <= f <= 40.8 GHz NS_202, NS_203, NS_205			7.32
	40.8 GHz <= f <= 2nd harmonic of the upper frequency edge of the UL operating band NS_202			9.34
PC5, PC6	6 GHz <= f <=12.75 GHz NS_202	BW <= 400MHz	P = Max Output Power	5.28
	12.75 GHz <= f <= 23.45 GHz NS_202			5.82
	23.45 GHz <= f <= 40.8 GHz NS_202, NS_203, NS_205			5.98
	40.8 GHz <= f <= 2nd harmonic of the upper frequency edge of the UL operating band NS_202			8.00
NOTE 1: Total EIRP Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.18.2-3 to Table B.18.2-11 for PC3 UEs and in Table B.18.2-12 to Table B.18-2.16 for PC1, PC5 and PC6 UEs. NOTE 2: Max output power level for device with corresponding power class. NOTE 3: The MU values are valid for SISO and MIMO.				

B.18.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.18.1-1.

Table B.18.1-1: Uncertainty contributions for TRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of quiet zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing Wave Between the DUT and measurement antenna	B.2.1.5
6	Uncertainty of the RF power measurement equipment	B.2.1.6
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Influence of TRP measurement grid	B.2.1.22
14	Influence of beam peak search grid	B.2.1.23
15	Multiple measurement antenna uncertainty	B.2.1.25
16	DUT repositioning	B.2.1.26
Stage 1: Calibration measurement		
17	Mismatch	B.2.1.4
18	Amplifier uncertainties	B.2.1.8
19	Misalignment of positioning System	B.2.1.13
20	Uncertainty of the Network Analyzer	B.2.1.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
23	Phase centre offset of calibration antenna	B.2.1.18
24	Quality of quiet zone for calibration process	B.2.1.19
25	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
26	Influence of the calibration antenna feed cable	B.2.1.21
27	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
28	Systematic error due to TRP calculation/quadrature	B.2.1.24
29	Influence of noise	B.2.1.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {6 GHz to 87 GHz}, P = [Maximum output power].
- The uncertainty assessment for TRP is provided in Table B.18.1-2 to B.18.1-xx

Table B.18.1-2: Uncertainty assessment for TRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment				
2	Measure distance uncertainty				
3	Quality of quiet zone (NOTE 2)				
4	Mismatch (NOTE 3)				
5	Standing Wave Between the DUT and measurement antenna				
6	Uncertainty of the RF power measurement equipment (NOTE 4)				
7	Phase curvature				
8	Amplifier uncertainties				
9	Random uncertainty				
10	Influence of the XPD				
11	Insertion Loss Variation				
12	RF leakage (from measurement antenna to the receiver/transmitter)				
13	Influence of TRP measurement grid (NOTE 5)				
14	Influence of beam peak search grid (NOTE 6)				
15	Multiple measurement antenna uncertainty				
16	DUT repositioning				
Stage 1: Calibration measurement					
17	Mismatch				
18	Amplifier uncertainties				
19	Misalignment of positioning System				
20	Uncertainty of the Network Analyzer				
21	Uncertainty of the absolute gain of the calibration antenna				
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna				
23	Phase centre offset of calibration antenna				
24	Quality of quiet zone for calibration process (NOTE 2)				
25	Standing wave between reference calibration antenna and measurement antenna				
26	Influence of the calibration antenna feed cable				
27	Insertion Loss Variation				
TRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					
Systematic uncertainties (NOTE 7)					**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 5)				
29	Influence of noise				
Total measurement uncertainty					
TRP total measurement uncertainty [dB]					

NOTE 1: The impact of phase variation on EIRP is FFS.
NOTE 2: The quality of quiet zone is different for EIRP and TRP. For TRP, the standard uncertainty is FFS; for EIRP, the standard uncertainty of quiet zone is FFS.
NOTE 3: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 4: The assessment assumes maximum DUT output power.
NOTE 5: This contributor shall only be considered for TRP measurements.
NOTE 6: This contributor shall only be considered for EIRP measurements.
NOTE 7: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 8: Void

B.18.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.18.2-1.

Table B.18.2-1: Uncertainty contributions for TRP measurement

UID	Description of uncertainty contribution	Details in clause
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	Uncertainty of the RF power measurement equipment	B.2.2.6
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Influence of TRP measurement grid	B.2.2.22
14	Influence of beam peak search grid	B.2.2.23
15	Multiple measurement antenna uncertainty	B.2.2.25
16	DUT repositioning	B.2.2.26
17	Misalignment of DUT due to change of DUT orientation	B.2.2.31
Stage 1: Calibration measurement		
18	Mismatch	B.2.2.4
19	Amplifier Uncertainties	B.2.2.8
20	Misalignment of positioning System	B.2.2.13
21	Uncertainty of the Network Analyzer	B.2.2.14
22	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
24	Phase centre offset of calibration antenna	B.2.2.18
25	Quality of quiet zone for calibration process	B.2.2.19
26	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
27	Influence of the calibration antenna feed cable	B.2.2.21
28	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
29	Systematic error due to TRP calculation/quadrature	B.2.2.24
30	Influence of noise	B.2.2.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet zone size $\leq$ 30 cm, f = {6 GHz to 87 GHz}, P = Maximum output power.
- The uncertainty assessment for TRP is provided from Table B.18.2-2 to Table B.18.2-11 for PC3 UEs and from Table B.18.2-12 to Table B.18.2-16 for PC1, PC5 and PC6 UEs.

Table B.18.2-2: Void

Table B.18.2-3: Uncertainty assessment for TRP measurement (f=6 GHz to 12.75GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.70	Actual	1.00	0.70
4	Mismatch	1.50	Actual	1.00	1.50
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.00	Normal	2.00	1.00
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.32	Actual	1	0.32
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.70	Actual	1.00	0.70
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (6 GHz < f <= 12.75 GHz) [dB] (a)				4.88
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.0

30	General spurious emissions Influence of noise (c_1) (6 GHz < f <= 12.75 GHz)	0.41
30	Additional spurious emissions Influence of noise (c_2) NS_202 (6 GHz < f <= 12.75 GHz)	0.41
	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (6 GHz < f <= 12.75 GHz)		5.29
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_2) [dB] NS_202 (6 GHz < f <= 12.75 GHz)		5.29

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 6: The analysis is valid for SISO and MIMO.

Table B.18.2-4: Void

Table B.18.2-5: Uncertainty assessment for TRP measurement (f=12.75 GHz to 23.45 GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.60	Actual	1.00	0.60
4	Mismatch	1.50	Actual	1.00	1.50
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.16	Normal	2.00	1.08
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.32	Actual	1	0.32
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.60	Actual	1.00	0.60
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (12.75 GHz < f <= 23.45 GHz) [dB] (a)				4.84
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.0

30	General spurious emissions Influence of noise (c_1) (12.75 GHz < f <= 23.45 GHz)	0.41
30	Additional spurious emissions Influence of noise (c_2) NS_202 (12.75 GHz < f <= 23.45 GHz)	1.0
31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (12.75 GHz < f <= 23.45 GHz)		5.25
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_2) [dB] NS_202 (12.75 GHz < f <= 23.45 GHz)		5.84
NOTE 1: This contributor shall only be considered for TRP measurements. NOTE 2: This contributor shall only be considered for EIRP measurements. NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm. NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning. NOTE 6: The analysis is valid for SISO and MIMO.		

Table B.18.2-6: Void

Table B.18.2-7: Uncertainty assessment for TRP measurement (f=23.45 GHz to 40.8 GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	1.40	Actual	1.00	1.40
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.73	Normal	2.00	1.37
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.32	Actual	1	0.32
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.6	Normal	2.00	0.3
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.6	Actual	1.00	0.6
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (23.45 GHz < f <= 40.8 GHz) [dB] (a)				5.00
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.0

30	General spurious emissions Influence of noise (c_1) (23.45 GHz < f <= 40.8 GHz)	0.41
30	Spurious emission band UE co-existence Influence of noise (c_2) (f within NR Bands n257, n260 or n261)	1.0
30	Spurious emission band UE co-existence Influence of noise (c_3) (36 GHz <= f <= 37 GHz)	1.0
30	Additional spurious emissions Influence of noise (c_4) NS_202, NS_205 (23.6 GHz < f <= 24.0 GHz)	1.0
30	Additional spurious emissions Influence of noise (c_5) NS_202 (23.45 GHz < f <= 40.8 GHz)	1.0
30	Additional spurious emissions Influence of noise (c_6) NS_203 (23.6 GHz < f <= 24.0 GHz)	1.0
30	Spurious emission band UE co-existence Influence of noise (c_7) (23.6 GHz < f <= 24.0 GHz)	1.0
31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (23.45 GHz < f <= 40.8 GHz)		5.41
Spurious emission band UE co-existence Total measurement uncertainty (a)+(b)+(c_2) [dB] (f within NR Bands n257, n260 or n261)		6.00
Spurious emission band UE co-existence Total measurement uncertainty (a)+(b)+(c_3) [dB] (36 GHz <= f <= 37 GHz)		6.00
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_4) [dB] NS_202, NS_205 (23.6 GHz < f <= 24.0 GHz)		6.00
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_5) [dB] NS_202 (23.45 GHz < f <= 40.8 GHz)		6.00
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_6) [dB] NS_203 (23.6 GHz < f <= 24.0 GHz)		6.00
Spurious emission band UE co-existence Total measurement uncertainty (a)+(b)+(c_7) [dB] (23.6 GHz < f <= 24.0 GHz)		6.00

NOTE 1:	This contributor shall only be considered for TRP measurements.
NOTE 2:	This contributor shall only be considered for EIRP measurements.
NOTE 3:	In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4:	Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5:	Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 6:	The analysis is valid for SISO and MIMO.

Table B.18.2-8: Void

Table B.18.2-9: Uncertainty assessment for TRP measurement (f= 40.8 GHz to 66 GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.0	Normal	2.00	0.0
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	2.30	Actual	1.00	2.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	4.0	Normal	2.00	2.00
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.32	Actual	1	0.32
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.7	Normal	2.00	0.85
22	Uncertainty of the absolute gain of the calibration antenna	1.70	Normal	2.00	0.85
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.6	Actual	1.00	0.6
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.28	Normal	2.00	0.14
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (40.8 GHz < f <= 66 GHz) [dB] (a)				7.01
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.00

30	General spurious emissions Influence of noise (c_1) (40.8 GHz < f <= 66 GHz)	0.41
30	Spurious emission band UE co-existence Influence of noise (c_2) (57 GHz <= f <= 66 GHz)	1.0
30	Additional spurious emissions Influence of noise (c_3) NS_202 (40.8 GHz < f <= 2nd harmonic of the upper frequency edge of the UL operating band)	1.0
31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (40.8 GHz < f <= 66 GHz)		7.42
Spurious emission band UE co-existence Total measurement uncertainty (a)+(b)+(c_2) [dB] (57 GHz <= f <= 66 GHz)		8.01
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_3) [dB] NS_202 (40.8 GHz < f <= 2nd harmonic of the upper frequency edge of the UL operating band)		8.01

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 6: Void
NOTE 7: The analysis is valid for SISO and MIMO.

Table B.18.2-10: Void

Table B.18.2-11: Uncertainty assessment for TRP measurement (f= 66 GHz to 87 GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	2.30	Actual	1.00	2.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	4.00	Normal	2.00	2.00
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	3.0	Normal	2.00	1.50
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.32	Actual	1	0.32
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.70	Normal	2.00	0.85
22	Uncertainty of the absolute gain of the calibration antenna	1.70	Normal	2.00	0.85
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.60	Actual	1.00	0.60
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.28	Normal	2.00	0.14
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (66 GHz < f <= 87 GHz) [dB] (a)				7.31
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.00

30	General spurious emissions Influence of noise (c_1) (66 GHz < f <= 80 GHz)	0.41
30	General spurious emissions Influence of noise (c_1) (80 GHz < f <= 87 GHz)	0.83
31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (66 GHz < f <= 80 GHz)		7.72
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (80 GHz < f <= 87 GHz)		8.14

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 6: The analysis is valid for SISO and MIMO.

Table B.18.2-12: Uncertainty assessment for TRP measurement (f=6 GHz to 12.75GHz, Quiet Zone size ≤ 30 cm) for PC1, PC5 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.70	Actual	1.00	0.70
4	Mismatch	1.50	Actual	1.00	1.50
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.00	Normal	2.00	1.00
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.70	Actual	1.00	0.70
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (6 GHz < f <= 12.75 GHz) [dB] (a)				4.87
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.00

30	General spurious emissions Influence of noise (c_1) (6 GHz < f <= 12.75 GHz)	0.41
30	Additional spurious emissions Influence of noise (c_2) NS_202 (6 GHz < f <= 12.75 GHz)	0.41
31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (6 GHz < f <= 12.75 GHz)		5.28
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_2) [dB] NS_202 (6 GHz < f <= 12.75 GHz)		5.28

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 6: The analysis is valid for SISO and MIMO.

Table B.18.2-13: Uncertainty assessment for TRP measurement (f=12.75 GHz to 23.45 GHz, Quiet Zone size ≤ 30 cm) for PC1, PC5 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.60	Actual	1.00	0.60
4	Mismatch	1.50	Actual	1.00	1.50
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.16	Normal	2.00	1.08
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.60	Actual	1.00	0.60
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (12.75 GHz < f <= 23.45 GHz) [dB] (a)				4.83
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.00

30	General spurious emissions Influence of noise (c_1) (12.75 GHz < f <= 23.45 GHz) (PC1)	1.08
30	Additional spurious emissions Influence of noise (c_2) NS_202 (12.75 GHz < f <= 23.45 GHz) (PC1)	2.34
30	General spurious emissions Influence of noise (c_3) (12.75 GHz < f <= 23.45 GHz) (PC5, PC6)	0.41
30	Additional spurious emissions Influence of noise (c_4) NS_202 (12.75 GHz < f <= 23.45 GHz) (PC5, PC6)	1.0
31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (12.75 GHz < f <= 23.45 GHz) (PC1)		5.91
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_2) [dB] NS_202 (12.75 GHz < f <= 23.45 GHz) (PC1)		7.16
General spurious emissions Total measurement uncertainty (a)+(b)+(c_3) [dB] (12.75 GHz < f <= 23.45 GHz) (PC5, PC6)		5.24
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_4) [dB] NS_202 (12.75 GHz < f <= 23.45 GHz) (PC5, PC6)		5.82

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 6: The analysis is valid for SISO and MIMO.

Table B.18.2-14: Uncertainty assessment for TRP measurement (f=23.45 GHz to 40.8 GHz, Quiet Zone size ≤ 30 cm) for PC1, PC5 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	1.40	Actual	1.00	1.40
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.73	Normal	2.00	1.37
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.6	Normal	2.00	0.3
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.6	Actual	1.00	0.6
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (23.45 GHz < f <= 40.8 GHz) [dB] (a)				4.99
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.00

30	General spurious emissions Influence of noise (c_1) (23.45 GHz < f <= 40.8 GHz) (PC1)	1.08
30	Spurious emission band UE co-existence Influence of noise (c_2) (f within NR Bands n257, n260 or n261) (PC1)	2.34
30	Additional spurious emissions Influence of noise (c_4) NS_202, NS_205 (23.6 GHz < f <= 24.0 GHz) (PC1)	2.34
30	Additional spurious emissions Influence of noise (c_5) NS_202 (23.45 GHz < f <= 40.8 GHz) (PC1)	2.34
30	Additional spurious emissions Influence of noise (c_6) NS_203 (23.6 GHz < f <= 24.0 GHz) (PC1)	2.34
30	Spurious emission band UE co-existence Influence of noise (c_7) (23.6 GHz < f <= 24.0 GHz) (PC1)	2.34
30	General spurious emissions Influence of noise (c_8) (23.45 GHz < f <= 40.8 GHz) (PC5, PC6)	0.41
30	Spurious emission band UE co-existence Influence of noise (c_9) (f within NR Bands n260) (PC5, PC6)	1.0
30	Additional spurious emissions Influence of noise (c_{10}) NS_202, NS_205 (23.6 GHz < f <= 24.0 GHz) (PC5, PC6)	1.0
30	Additional spurious emissions Influence of noise (c_{11}) NS_202 (23.45 GHz < f <= 40.8 GHz) (PC5, PC6)	1.0
30	Additional spurious emissions Influence of noise (c_{12}) NS_203 (23.6 GHz < f <= 24.0 GHz) (PC5, PC6)	1.0
30	Spurious emission band UE co-existence Influence of noise (c_{13}) (23.6 GHz < f <= 24.0 GHz) (PC5, PC6)	1.0
31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (23.45 GHz < f <= 40.8 GHz) (PC1)		6.07
Spurious emission band UE co-existence Total measurement uncertainty (a)+(b)+(c_2) [dB] (f within NR Bands n257, n260 or n261) (PC1)		7.32

Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_4) [dB] NS_202, NS_205 (23.6 GHz < f <= 24.0 GHz) (PC1)	7.32
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_5) [dB] NS_202 (23.45 GHz < f <= 40.8 GHz) (PC1)	7.32
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_6) [dB] NS_203 (23.6 GHz < f <= 24.0 GHz) (PC1)	7.32
Spurious emission band UE co-existence Total measurement uncertainty (a)+(b)+(c_7) [dB] (23.6 GHz < f <= 24.0 GHz) (PC1)	7.32
General spurious emissions Total measurement uncertainty (a)+(b)+(c_8) [dB] (23.45 GHz < f <= 40.8 GHz) (PC5, PC6)	5.40
Spurious emission band UE co-existence Total measurement uncertainty (a)+(b)+(c_9) [dB] (f within NR Bands n257, n260 or n261) (PC5, PC6)	5.98
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_{10}) [dB] NS_202, NS_205 (23.6 GHz < f <= 24.0 GHz) (PC5, PC6)	5.98
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_{11}) [dB] NS_202 (23.45 GHz < f <= 40.8 GHz) (PC5, PC6)	5.98
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_{12}) [dB] NS_203 (23.6 GHz < f <= 24.0 GHz) (PC5, PC6)	5.98
Spurious emission band UE co-existence Total measurement uncertainty (a)+(b)+(c_{13}) [dB] (23.6 GHz < f <= 24.0 GHz) (PC5, PC6)	5.98
NOTE 1: This contributor shall only be considered for TRP measurements. NOTE 2: This contributor shall only be considered for EIRP measurements. NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm. NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning. NOTE 6: The analysis is valid for SISO and MIMO.	

Table B.18.2-15: Uncertainty assessment for TRP measurement (f= 40.8 GHz to 66 GHz, Quiet Zone size ≤ 30 cm) for PC1, PC5 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	2.30	Actual	1.00	2.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	4.0	Normal	2.00	2.00
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.7	Normal	2.00	0.85
22	Uncertainty of the absolute gain of the calibration antenna	1.70	Normal	2.00	0.85
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.6	Actual	1.00	0.6
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.28	Normal	2.00	0.14
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (40.8 GHz < f <= 66 GHz) [dB] (a)				7.00
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.00

30	General spurious emissions Influence of noise (c_1) (40.8 GHz < f <= 66 GHz) (PC1)	1.08
30	Spurious emission band UE co-existence Influence of noise (c_2) (57 GHz <= f <= 66 GHz) (PC1, PC5, PC6)	1
30	Additional spurious emissions Influence of noise (c_3) NS_202 (40.8 GHz < f <= 2nd harmonic of the upper frequency edge of the UL operating band) (PC1)	2.34
30	General spurious emissions Influence of noise (c_4) (40.8 GHz < f <= 66 GHz) (PC5, PC6)	0.41
30	Additional spurious emissions Influence of noise (c_5) NS_202 (40.8 GHz < f <= 2nd harmonic of the upper frequency edge of the UL operating band) (PC5, PC6)	1.0
31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (40.8 GHz < f <= 66 GHz) (PC1)		8.09
Spurious emission band UE co-existence Total measurement uncertainty (a)+(b)+(c_2) [dB] (57 GHz <= f <= 66 GHz) (PC1, PC5, PC6)		8.00
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_3) [dB] NS_202 (40.8 GHz < f <= 2nd harmonic of the upper frequency edge of the UL operating band) (PC1)		9.34
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (40.8 GHz < f <= 66 GHz) (PC5, PC6)		7.42
Additional spurious emissions Total measurement uncertainty (a)+(b)+(c_3) [dB] NS_202 (40.8 GHz < f <= 2nd harmonic of the upper frequency edge of the UL operating band) (PC5, PC6)		8.00

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 6: Void
NOTE 7: The analysis is valid for SISO and MIMO.

Table B.18.2-16: Uncertainty assessment for TRP measurement (f= 66 GHz to 87 GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.60	Actual	1.00	0.60
4	Mismatch	2.30	Actual	1.00	2.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	4.00	Normal	2.00	2.00
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	3.00	Normal	2.00	1.50
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.06
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.70	Normal	2.00	0.85
22	Uncertainty of the absolute gain of the calibration antenna	1.70	Normal	2.00	0.85
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.60	Actual	1.00	0.60
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.28	Normal	2.00	0.14
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (66 GHz < f <= 87 GHz) [dB] (a)				7.30
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0

30	General spurious emissions Influence of noise (c_1) (66 GHz < f <= 80 GHz)	0.41
30	General spurious emissions Influence of noise (c_2) (80 GHz < f <= 87 GHz) (PC5)	0.83
31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (66 GHz < f <= 80 GHz)		7.71
General spurious emissions Total measurement uncertainty (a)+(b)+(c_1) [dB] (80 GHz < f <= 87 GHz) (PC5)		8.13
NOTE 1: This contributor shall only be considered for TRP measurements. NOTE 2: This contributor shall only be considered for EIRP measurements. NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm. NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning. NOTE 6: The analysis is valid for SISO and MIMO.		

NOTE: MU assessment for additional spurious in Table B.18.2-3 to Table B.18.2-16 is based on the following relaxations:

Table B.18.2-17: Transmitter Spurious emissions relaxation considered in MU assessment (Quiet Zone size ≤ 30 cm)

Power Class	Frequency	Relaxation
PC1	6 GHz < f <= 12.75 GHz	0 dB
	12.75 GHz < f <= 23.45 GHz	0 dB
	23.45GHz <= f <= 40.8GHz	0 dB
	40.8 GHz < f <= 66 GHz	0 dB
	66 GHz < f <= 80 GHz	0 dB
PC2	6 GHz < f <= 12.75 GHz	FFS
	12.75 GHz < f <= 23.45 GHz	FFS
	23.45GHz <= f <= 40.8GHz	FFS
	40.8 GHz < f <= 66 GHz	FFS
	66 GHz < f <= 87 GHz	FFS
PC3	6 GHz < f <= 12.75 GHz	0 dB
	12.75 GHz < f <= 23.45 GHz	0 dB
	23.45GHz <= f <= 40.8GHz	0 dB
	40.8 GHz < f <= 66 GHz	0 dB
	66 GHz < f <= 87 GHz	0 dB
PC4	6 GHz < f <= 12.75 GHz	FFS
	12.75 GHz < f <= 23.45 GHz	FFS
	23.45GHz <= f <= 40.8GHz	FFS
	40.8 GHz < f <= 66 GHz	FFS
	66 GHz < f <= 80 GHz	FFS
PC5, PC6	6 GHz < f <= 12.75 GHz	0 dB
	12.75 GHz < f <= 23.45 GHz	0 dB
	23.45GHz <= f <= 40.8GHz	0 dB
	40.8 GHz < f <= 66 GHz	0 dB
	66 GHz < f <= 87 GHz (NOTE 1)	0 dB
NOTE 1: Only applicable for PC5 in band n259.		

Table B.18.2-18: Spurious emissions band UE co-existence relaxation considered in MU assessment (Quiet Zone size ≤ 30 cm)

Power Class	Frequency	Relaxation
PC1	23.45GHz <= f <= 40.8GHz	3.3 dB (for protected bands n257, n261) 5 dB (for protected band n260) 0.3 dB (for 23.6 GHz ≤ f ≤ 24.0 GHz)
	40.8 GHz < f <= 66 GHz	0 dB (for 57.0 GHz ≤ f ≤ 66.0 GHz)
PC2	23.45GHz <= f <= 40.8GHz	FFS
	40.8 GHz < f <= 66 GHz	FFS
PC3	23.45GHz <= f <= 40.8GHz	3.3 dB (for protected bands n257, n261) 5 dB (for protected band n260) 0.3 dB (for 23.6 GHz ≤ f ≤ 24.0 GHz)
	40.8 GHz < f <= 66 GHz	6 dB (for 36.0 GHz ≤ f ≤ 37.0 GHz) 0 dB (for 57.0 GHz ≤ f ≤ 66.0 GHz)
PC4	23.45GHz <= f <= 40.8GHz	FFS
	40.8 GHz < f <= 66 GHz	FFS
PC5, PC6	23.45GHz <= f <= 40.8GHz	3.3 dB (for protected bands n257, n261) 5 dB (for protected band n260) 0.3 dB (for 23.6 GHz ≤ f ≤ 24.0 GHz)
	40.8 GHz < f <= 66 GHz	0 dB (for 57.0 GHz ≤ f ≤ 66.0 GHz)

Table B.18.2-19: Additional Spurious emissions relaxation considered in MU assessment (Quiet Zone size ≤ 30 cm)

Power Class	Frequency	Relaxation
PC1	6 GHz < f <= 12.75 GHz	0 dB (NS_202)
	12.75 GHz < f <= 23.45 GHz	13 dB (NS_202)
	23.45GHz <= f <= 40.8GHz	13 dB (whole frequency range for NS_202) 0.3 dB (for 23.6 GHz ≤ f ≤ 24.0 GHz for NS_203) 6.3 dB (for 23.6 GHz ≤ f ≤ 24.0 GHz for NS_202 & NS_205)
	40.8 GHz < f <= 66 GHz	13 dB (NS_202)
	66 GHz < f <= 80 GHz	FFS
PC2	6 GHz < f <= 12.75 GHz	FFS
	12.75 GHz < f <= 23.45 GHz	FFS
	23.45GHz <= f <= 40.8GHz	FFS
	40.8 GHz < f <= 66 GHz	FFS
	66 GHz < f <= 80 GHz	FFS
PC3	6 GHz < f <= 12.75 GHz	0 dB (NS_202)
	12.75 GHz < f <= 23.45 GHz	13 dB (NS_202)
	23.45GHz <= f <= 40.8GHz	13 dB (whole frequency range for NS_202) 0.3 dB (for 23.6 GHz ≤ f ≤ 24.0 GHz for NS_203) 6.3 dB (for 23.6 GHz ≤ f ≤ 24.0 GHz for NS_202 & NS_205)
	40.8 GHz < f <= 66 GHz	13 dB (NS_202)
PC4	6 GHz < f <= 12.75 GHz	FFS
	12.75 GHz < f <= 23.45 GHz	FFS
	23.45GHz <= f <= 40.8GHz	FFS
	40.8 GHz < f <= 66 GHz	FFS
	66 GHz < f <= 80 GHz	FFS
PC5, PC6	6 GHz < f <= 12.75 GHz	0 dB (NS_202)
	12.75 GHz < f <= 23.45 GHz	13 dB (NS_202)
	23.45GHz <= f <= 40.8GHz	13 dB (whole frequency range for NS_202) 0.3 dB (for 23.6 GHz ≤ f ≤ 24.0 GHz for NS_203) 6.3 dB (for 23.6 GHz ≤ f ≤ 24.0 GHz for NS_202 & NS_205)
	40.8 GHz < f <= 66 GHz	13 dB (NS_202)

B.18.3 Uncertainty budget format and assessment for NFTF

FFS

B.18a Beam correspondence - EIRP

B.18a.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.18a.1-1.

Table B.18a.1-1: Uncertainty contributions for Beam correspondence - EIRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.1.36
2	Amplifier uncertainties	B.2.1.8
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
3	Influence of noise	B.2.1.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].
- The uncertainty assessment for Beam correspondence - EIRP is provided in Table B.18a.1-2.

Table B.18a.1-2: Uncertainty assessment for Beam correspondence - EIRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	FFS	FFS	FFS	FFS
2	Amplifier uncertainties	FFS	FFS	FFS	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
3	Influence of noise				FFS
	Total measurement uncertainty				**Value**
	EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]				FFS
NOTE 1: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.					

B.18a.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.18a.2.-1.

Table B.18a.2-1: Uncertainty contributions for Beam correspondence - EIRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.2.36
2	Amplifier uncertainties	B.2.2.8
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
3	Influence of noise	B.2.2.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size ≤ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz}.
- The uncertainty assessment for Beam Correspondence - EIRP is provided in Table B.18a.2-2.for PC3.

Table B.18a.2-2: Uncertainty assessment for Beam correspondence - EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	0.4	Normal	2.00	[0.2]
2	Amplifier uncertainties	2.1	Rectangular	1.73	1.05
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
3	Influence of noise (23.45GHz <= f <= 32.125GHz)				0.58
3	Influence of noise (32.125GHz < f <= 40.8GHz)				1.71
Total measurement uncertainty					Value
EIRP Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB]					2.67
EIRP Expanded uncertainty (32.125GHz < f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB]					3.80
NOTE 1: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 2: Power step size assumed to be no higher than 3.2 dB in 85% of the measurement grid points. NOTE 3: Measurement uncertainties in this table assume absolute power measurements involved in the same relative power measurement are performed over the same RF path.					

B.18a.3 Uncertainty budget format and assessment for NFTF

The uncertainty contributions that may impact the overall MU value are listed in Table B.18a.3-1.

Table B.18a.3-1: Uncertainty contributions for Beam correspondence - EIRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Uncertainty of the RF relative power measurement equipment	B.2.3.30
2	Amplifier uncertainties	B.2.3.8
Stage 1: Calibration measurement		
	N/A	
Systematic uncertainties		
3	Influence of noise	B.2.3.29

The uncertainty assessment table is organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {22.65GHz, 31.1GHz, 45.1GHz}, P = [maximum output power].
- The uncertainty assessment for Beam correspondence - EIRP is provided in Table B.18a.3-2

Table B.18a.3-2: Uncertainty assessment for Beam correspondence - EIRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Uncertainty of the RF relative power measurement equipment	FFS	FFS	FFS	FFS
2	Amplifier uncertainties	FFS	FFS	FFS	FFS
Stage 1: Calibration measurement					
	N/A				
	Systematic uncertainties (NOTE 1)				**Value**
3	Influence of noise				FFS
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					FFS
NOTE 1: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.					

B.19 Reference Sensitivity

Editor's note: The MU for Multi-Rx is working assumption. Values will be confirmed once devices supporting Multi-Rx test cases are commercially available.

Following tables summarize the MU threshold for EIS measurements for Reference Sensitivity. The origin MU values for different test setups with varies parameters can be found in following subclauses.

Table B.19-1: MU threshold for EIS for Reference Sensitivity

Power Class	Frequency	MBW	Power	Threshold MU value for NTC (NOTE 1)	Threshold MU value for ETC (NOTE 1)
PC3, PC7 (NOTE2)	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.36	5.61
	32.125GHz < f <= 40.8GHz			5.36	5.61
	40.8GHz < f <= 44.3GHz			6.34	6.48
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.58	5.83
	32.125GHz < f <= 40.8GHz			5.58	5.83
PC5	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.58	5.83
PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.56	5.81
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.19.2-2 for PC3 and PC6 UEs (NTC), in Table B.19.2-4 for PC3 and PC6 UEs (ETC), and Table B.19.2-5 for PC1 and PC5 UEs. NOTE 2: MU thresholds for PC7 limited to FR2a (23.45GHz <= f <= 32.125GHz) and MBW <=100MHz.					

Table B.19-2: MU threshold for Spherical coverage measurement for Reference Sensitivity

Power Class	Frequency	MBW	Power	Threshold MU value (NOTE 1)
PC3, PC7 (NOTE2)	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.07
	32.125GHz < f <= 40.8GHz			5.07
	40.8GHz < f <= 44.3GHz			6.04
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.07
	32.125GHz < f <= 40.8GHz			5.07
PC5	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.07
PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	5.56
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.19.2-2 for PC3 UEs and Table B.19.2-3 for PC1 and PC5 UEs. NOTE 2: MU thresholds for PC7 limited to FR2a (23.45GHz <= f <= 32.125GHz) and MBW <=100MHz.				

Table B.19-3: MU threshold for 2AoA Multi-Rx Spherical coverage measurement for Reference Sensitivity

Power Class	Frequency	MBW	Power	Threshold MU value (NOTE 1)
PC3	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	[5.53]
	32.125GHz < f <= 40.8GHz			[5.53]
	40.8GHz < f <= 44.3GHz			[6.01]
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.19.2-2a for PC3 UEs.				

B.19.1 Uncertainty budget format and assessment for DFF

FFS

B.19.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.19.2-1.

Table B.19.2-1: Uncertainty contributions for EIS measurement

UID	Description of uncertainty contribution	Details in clause
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	gNB emulator uncertainty	B.2.2.17
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Multiple measurement antenna uncertainty	B.2.2.25
14	DUT repositioning	B.2.2.26
15	Influence of spherical coverage grid	B.2.2.29
Stage 1: Calibration measurement		
16	Mismatch	B.2.2.4
17	Amplifier Uncertainties	B.2.2.8
18	Misalignment of positioning System	B.2.2.13
19	Uncertainty of the Network Analyzer	B.2.2.14
20	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
22	Phase centre offset of calibration antenna	B.2.2.18
23	Quality of quiet zone for calibration process	B.2.2.19
24	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
25	Influence of the calibration antenna feed cable	B.2.2.21
26	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
27	Systematic error related to beam peak search	B.2.2.28
28	Systematic error related to EIS spherical coverage	B.2.2.30

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size ≤ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz}, [P = maximum output power].
- The uncertainty assessment for EIS is provided in Table B.19.2-2 for PC3 and PC6 UEs and Table B.19.2-3 for PC1 UEs.

Table B.19.2-2: Uncertainty assessment for EIS measurement for PC3 (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) and PC6 (f=23.45GHz, 32.125GHz, Quiet Zone size ≤ 30 cm) UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 7) (23.45GHz <= f <= 40.8GHz)	0.6	Actual	1.00	0.6
3	Quality of Quiet Zone (NOTE 7) (40.8GHz < f <= 44.3GHz)	0.7	Actual	1.00	0.7
4	Mismatch (23.45GHz <= f <= 40.8GHz)	1.30	Actual	1.00	1.30
4	Mismatch (40.8GHz < f <= 44.3GHz)	1.70	Actual	1.00	1.70
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level (23.45GHz <= f <= 40.8GHz)	2.9	Normal	2.00	1.45
6	gNB uncertainty on absolute level (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 6)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.00 (NOTE 4) 0.08 (NOTE 5)	Rectangular	1.73	0.00 (NOTE 4) 0.05 (NOTE 5)
15	Influence of spherical coverage grid (NOTE 4)	0.12	Actual	1	0.12
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.50	Normal	2.00	0.75
19	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.70	Normal	2.00	0.85
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 7) (23.45GHz <= f <= 40.8GHz)	0.4	Actual	1.00	0.4
23	Quality of quiet zone for calibration process (NOTE 7) (40.8GHz < f <= 44.3GHz)	0.5	Actual	1.00	0.5
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00

	Systematic uncertainties (NOTE 3)	Value
27	Systematic error related to beam peak search (NOTE 5) (PC3)	0.5
27	Systematic error related to beam peak search (NOTE 5) (PC6)	0.7
28	Systematic error related to EIS spherical coverage (NOTE 4) (PC3)	DL power step size, 0.2
Total measurement uncertainty		**Value**
EIS Expanded uncertainty (23.45GHz <= f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		5.36
EIS Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		6.34
EIS / Spherical coverage Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC6)		5.56
EIS Spherical coverage Expanded uncertainty (23.45GHz <= f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		5.07
EIS Spherical coverage Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)		6.04

NOTE 1: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 2: Void.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: This contributor shall only be considered for spherical EIS measurements.
NOTE 5: This contributor shall only be considered for EIS measurements.
NOTE 6: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 7: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.

Table B.19.2-2a: Uncertainty assessment for 2AoA Multi-Rx EIS Spherical coverage measurement for PC3 (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 3) (23.45GHz < f <= 40.8GHz)	0.70	Actual	1.00	0.70
3	Quality of Quiet Zone (NOTE 3) (40.8GHz < f <= 44.3GHz)	0.80	Actual	1.00	0.80
4	Mismatch (23.45GHz <= f <= 40.8GHz)	1.70	Actual	1.00	1.70
4	Mismatch (40.8GHz < f <= 44.3GHz)	[1.75]	Actual	1.00	[1.75]
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level (23.45GHz <= f <= 40.8GHz)	3.20	Normal	2.00	1.60
6	gNB uncertainty on absolute level (40.8GHz < f <= 44.3GHz)	[3.70]	Normal	2.00	[1.85]
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 2)	0.15	Actual	1.00	0.15
14	DUT repositioning (NOTE 4)	0.00	Rectangular	1.73	[0.00]
15	Influence of spherical coverage grid (NOTE 4)	0.12	Actual	1	[0.12]
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.50	Normal	2.00	0.75
19	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.70	Normal	2.00	0.85
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 3) (23.45GHz <= f <= 40.8GHz)	0.4	Actual	1.00	0.4
23	Quality of quiet zone for calibration process (NOTE 3) (40.8GHz < f <= 44.3GHz)	0.5	Actual	1.00	0.5
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
Total measurement uncertainty					**Value**
EIS Spherical coverage Expanded uncertainty (23.45GHz <= f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)					[5.53]

EIS Spherical coverage Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)	[6.01]
NOTE 1: The analysis was done only for the case of operating at max output power, in-band, non-CA. NOTE 2: Applies to the system which has a structure of mechanical feed antenna positioning. NOTE 3: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm. NOTE 4: Confirmation of MU value is pending on further analysis from OEM/chipset vendors.	

Table B.19.2-3: Uncertainty assessment for EIS measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 7)	0.6	Actual	1.00	0.6
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level	2.9	Normal	2.00	1.45
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 6)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.00 (NOTE 4) 0.35 (NOTE 5)	Rectangular	1.73	0.00 (NOTE 4) 0.20 (NOTE 5)
15	Influence of spherical coverage grid (NOTE 4)	0.13	Actual	1	0.13
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 7)	0.4	Actual	1.00	0.4
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 3)				**Value**
27	Systematic error related to beam peak search (NOTE 5)				0.7
28	Systematic error related to EIS spherical coverage (NOTE 4)				DL power step size, 0.2
	Total measurement uncertainty				**Value**
	EIS Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]				5.58
	EIS Spherical coverage Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]				5.07

NOTE 1: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 2: Void.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: This contributor shall only be considered for spherical EIS measurements.
NOTE 5: This contributor shall only be considered for EIS measurements.
NOTE 6: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 7: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.

Table B.19.2-4: Uncertainty assessment for EIS measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 and PC6 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 7)	0.9	Actual	1.00	0.9
4	Mismatch (23.45GHz <= f <= 40.8GHz)	1.30	Actual	1.00	1.30
4	Mismatch (40.8GHz < f <= 44.3GHz)	1.70	Actual	1.00	1.70
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level (23.45GHz <= f <= 40.8GHz)	2.9	Normal	2.00	1.45
6	gNB uncertainty on absolute level (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 6)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.00 (NOTE 4) 0.08 (NOTE 5)	Rectangular	1.73	0.00 (NOTE 4) 0.05 (NOTE 5)
15	Influence of spherical coverage grid (NOTE 4)	0.12	Actual	1	0.12
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.50	Normal	2.00	0.75
19	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.70	Normal	2.00	0.85
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 7)	0.6	Actual	1.00	0.6
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 3)				**Value**
27	Systematic error related to beam peak search (NOTE 5) (PC3)				0.5
27	Systematic error related to beam peak search (NOTE 5) (PC6)				0.7
28	Systematic error related to EIS spherical coverage (NOTE 4)				DL power step size, 0.2
Total measurement uncertainty					**Value**

EIS Expanded uncertainty (23.45GHz <= f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)	5.61
EIS Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)	6.48
EIS Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC6)	5.81
NOTE 1: The analysis was done only for the case of operating at max output power, in-band, non-CA. NOTE 2: Void. NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 4: This contributor shall only be considered for spherical EIS measurements. NOTE 5: This contributor shall only be considered for EIS measurements. NOTE 6: Applies to the system which has a structure of mechanical feed antenna positioning. NOTE 7: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm. The ETC QoQZ MU and ETC calibration path losses shall be applied to the NTC test cases if the ETC environment is used for NTC test cases.	

Table B.19.2-5: Uncertainty assessment for EIS measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs and extreme temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 7)	0.90	Actual	1.00	0.90
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level	2.90	Normal	2.00	1.45
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 6)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.00 (NOTE 4) 0.35(NOTE 5)	Rectangular	1.73	0.00 (NOTE 4) 0.20 (NOTE 5)
15	Influence of spherical coverage grid (NOTE 4)	0.13	Actual	1	0.13
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 7)	0.60	Actual	1.00	0.60
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 3)				**Value**
27	Systematic error related to beam peak search (NOTE 5)				0.7
28	Systematic error related to EIS spherical coverage (NOTE 4)				DL power step size, 0.2
Total measurement uncertainty					**Value**
EIS Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					5.83

NOTE 1: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 2: Void.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: This contributor shall only be considered for spherical EIS measurements.
NOTE 5: This contributor shall only be considered for EIS measurements.
NOTE 6: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 7: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm. The ETC QoQZ MU and ETC calibration path losses shall be applied to the NTC test cases if the ETC environment is used for NTC test cases.

B.20

B.21 Adjacent Channel Selectivity

Following tables summarize the MU threshold for Adjacent Channel Selectivity measurement. The origin MU values for different test setups with varies parameters can be found in following subclauses.

Table B.21-1: MU threshold for Adjacent Channel Selectivity

Power Class	Frequency	MBW	Power	Threshold MU value (NOTE 1)
PC3, PC7 (NOTE2)	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	8.08
	32.125GHz < f <= 40.8GHz			8.08
	40.8GHz < f <= 44.3GHz			9.46
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	8.31
	32.125GHz < f <= 40.8GHz			8.31
PC5	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	8.31
PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	P = Max Output Power	8.28
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.21.2-2 for PC3 and PC6 UEs and Table B.21.2-3 for PC1 and PC5 UEs. NOTE 2: MU thresholds for PC7 limited to FR2a (23.45GHz <= f <= 32.125GHz) and MBW <=100MHz.				

B.21.1 Uncertainty budget format and assessment for DFF

FFS

B.21.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.21.2-1.

Table B.21.2-1: Total Uncertainty contributions for Adjacent Channel Selectivity measurement

UID	Description of uncertainty contribution	Details in clause
Stage 2: DUT measurement (Wanted Signal contributions)		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	gNB emulator uncertainty	B.2.2.17
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Multiple measurement antenna uncertainty	B.2.2.25
14	DUT repositioning	B.2.2.26
Stage 2: DUT measurement (Modulated Interferer Signal specific contributions)		
15	Positioning misalignment	B.2.2.1
16	Measure distance uncertainty	B.2.2.2
17	Quality of Quiet Zone	B.2.2.3
18	Mismatch	B.2.2.4
19	Standing wave between the DUT and measurement antenna	B.2.2.5
20	Modulated Interferer uncertainty	B.2.2.33
21	Phase curvature	B.2.2.7
22	Amplifier uncertainties	B.2.2.8
23	Random uncertainty	B.2.2.9
24	Influence of the XPD	B.2.2.10
25	Insertion Loss Variation	B.2.2.11
26	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
27	Multiple measurement antenna uncertainty	B.2.2.25
28	DUT repositioning	B.2.2.26
29	Influence of offset antenna (Std.Dev)	B.2.2.35
Stage 1: Calibration measurement (Wanted Signal contributions)		
30	Mismatch	B.2.2.4
31	Amplifier Uncertainties	B.2.2.8
32	Misalignment of positioning System	B.2.2.13
33	Uncertainty of the Network Analyzer	B.2.2.14
34	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
35	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
36	Phase centre offset of calibration antenna	B.2.2.18
37	Quality of quiet zone for calibration process	B.2.2.19
38	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
39	Influence of the calibration antenna feed cable	B.2.2.21
40	Insertion Loss Variation	B.2.2.11
Stage 1: Calibration measurement (Modulated Interferer Signal contributions)		
41	Mismatch	B.2.2.4
42	Amplifier Uncertainties	B.2.2.8
43	Misalignment of positioning System	B.2.2.13
44	Uncertainty of the Network Analyzer	B.2.2.14
45	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
46	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
47	Phase centre offset of calibration antenna	B.2.2.18
48	Quality of quiet zone for calibration process	B.2.2.19
48	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
50	Influence of the calibration antenna feed cable	B.2.2.21
51	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
52	Systematic error related to beam peak search	B.2.2.28
53	Additional impact of interferer ACLR	B.2.2.32

54	Influence of offset antenna (mean error)	B.2.2.35

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz}
- The uncertainty assessment for ACS is provided in Table B.21.2-2 for PC3 UEs and Table B.21.2-3 for PC1 and PC5 UEs.

Table B.21.2-2: Uncertainty assessment for Adjacent Channel Selectivity measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm) for PC3 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement (Wanted Signal contributions)					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4) (23.45GHz <= f <= 40.8GHz)	0.6	Actual	1.00	0.6
3	Quality of Quiet Zone (NOTE 4) (40.8GHz < f <= 44.3GHz)	0.7	Actual	1.00	0.7
4	Mismatch (23.45GHz <= f <= 40.8GHz)	1.30	Actual	1.00	1.30
4	Mismatch (40.8GHz < f <= 44.3GHz)	1.70	Actual	1.00	1.70
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level (23.45GHz <= f <= 40.8GHz)	2.9	Normal	2.00	1.45
6	gNB uncertainty on absolute level (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.08	Rectangular	1.73	0.05
Stage 2: DUT measurement (Modulated Interferer Signal specific contributions)					
15	Positioning misalignment	0.00	Normal	2.00	0.00
16	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
17	Quality of Quiet Zone (NOTE 4) (23.45GHz <= f <= 40.8GHz)	0.6	Actual	1.00	0.6
17	Quality of Quiet Zone (NOTE 4) (40.8GHz < f <= 44.3GHz)	0.7	Actual	1.00	0.7
18	Mismatch (23.45GHz <= f <= 40.8GHz)	1.30	Actual	1.00	1.30
18	Mismatch (40.8GHz < f <= 44.3GHz)	1.70	Actual	1.00	1.70
19	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
20	Modulated Interferer uncertainty on absolute level (23.45GHz <= f <= 40.8GHz)	2.9	Normal	2.00	1.45
20	Modulated Interferer uncertainty on absolute level (40.8GHz < f <= 44.3GHz)	3.6	Normal	2.00	1.8
21	Phase curvature	0.00	U-shaped	1.41	0.00
22	Amplifier uncertainties	2.1	Normal	2.00	1.05
23	Random uncertainty	0.50	Normal	2.00	0.25
24	Influence of the XPD	0.01	U-shaped	1.41	0.00
25	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
26	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
27	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
28	DUT repositioning	0.08	Rectangular	1.73	0.05
29	Influence of offset antenna (Std.Dev) (NOTE 5)	0.00	Normal	2.00	0.00
Stage 1: Calibration measurement (Wanted Signal contributions)					
30	Mismatch	0.00	U-shaped	1.41	0.00
31	Amplifier Uncertainties	0.00	Normal	2.00	0.00

32	Misalignment of positioning System	0.00	Normal	2.00	0.00
33	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.50	Normal	2.00	0.75
33	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.70	Normal	2.00	0.85
34	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
35	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
36	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
37	Quality of quiet zone for calibration process (NOTE 4) (23.45GHz <= f <= 40.8GHz)	0.4	Actual	1.00	0.4
37	Quality of quiet zone for calibration process (NOTE 4) (40.8GHz < f <= 44.3GHz)	0.5	Actual	1.00	0.5
38	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
39	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
40	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
Stage 1: Calibration measurement (Modulated Interferer Signal contributions)					
41	Mismatch	0.00	U-shaped	1.41	0.00
42	Amplifier Uncertainties	0.00	Normal	2.00	0.00
43	Misalignment of positioning System	0.00	Normal	2.00	0.00
44	Uncertainty of the Network Analyzer (23.45GHz <= f <= 40.8GHz)	1.50	Normal	2.00	0.75
44	Uncertainty of the Network Analyzer (40.8GHz < f <= 44.3GHz)	1.70	Normal	2.00	0.85
45	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
46	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
47	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
48	Quality of quiet zone for calibration process (NOTE 4) (23.45GHz <= f <= 40.8GHz)	0.4	Actual	1.00	0.4
48	Quality of quiet zone for calibration process (NOTE 4) (40.8GHz < f <= 44.3GHz)	0.5	Actual	1.00	0.5
48	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
50	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
51	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 2)				**Value**
52	Systematic error related to beam peak search (PC3)				0.5
52	Systematic error related to beam peak search (PC6)				0.7
53	Additional impact of interferer ACLR				0.7
54	Influence of offset antenna (mean error) (NOTE 5)				0.00
Total measurement uncertainty					**Value**

ACS Expanded uncertainty (23.45GHz <= f <= 40.8GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)	8.08
ACS Expanded uncertainty (23.45GHz <= f <= 32.125GHz) (1.96σ - confidence interval of 95 %) [dB] (PC6)	8.28
ACS Expanded uncertainty (40.8GHz < f <= 44.3GHz) (1.96σ - confidence interval of 95 %) [dB] (PC3)	9.46
NOTE 1: The analysis was done only for the case of operating at max output power, in-band, non-CA. NOTE 2: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 3: Applies to the system which has a structure of mechanical feed antenna positioning. NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm. NOTE 5: For MTSU derivation purpose, this value is set to 0.0 (no offset antenna case).	

Table B.21.2-3: Uncertainty assessment for Adjacent Channel Selectivity measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement (Wanted Signal contributions)					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level	2.9	Normal	2.00	1.45
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.35	Rectangular	1.73	0.20
Stage 2: DUT measurement (Modulated Interferer Signal specific contributions)					
15	Positioning misalignment	0.02	Normal	2.00	0.01
16	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
17	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
18	Mismatch	1.30	Actual	1.00	1.30
19	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
20	Modulated Interferer uncertainty on absolute level	2.9	Normal	2.00	1.45
21	Phase curvature	0.00	U-shaped	1.41	0.00
22	Amplifier uncertainties	2.1	Normal	2.00	1.05
23	Random uncertainty	0.50	Normal	2.00	0.25
24	Influence of the XPD	0.01	U-shaped	1.41	0.00
25	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
26	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
27	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
28	DUT repositioning	0.35	Rectangular	1.73	0.20
29	Influence of offset antenna (Std.Dev) (NOTE 5)	0.00	Normal	2.00	0.00
Stage 1: Calibration measurement (Wanted Signal contributions)					
30	Mismatch	0.00	U-shaped	1.41	0.00
31	Amplifier Uncertainties	0.00	Normal	2.00	0.00
32	Misalignment of positioning System	0.00	Normal	2.00	0.00
33	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
34	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
35	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
36	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
37	Quality of quiet zone for calibration process (NOTE 4)	0.4	Actual	1.00	0.4
38	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
39	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
40	Insertion Loss Variation	0.00	Rectangular	1.73	0.00

Stage 1: Calibration measurement (Modulated Interferer Signal contributions)					
41	Mismatch	0.00	U-shaped	1.41	0.00
42	Amplifier Uncertainties	0.00	Normal	2.00	0.00
43	Misalignment of positioning System	0.00	Normal	2.00	0.00
44	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
45	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
46	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
47	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
48	Quality of quiet zone for calibration process (NOTE 4)	0.4	Actual	1.00	0.4
48	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
50	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
51	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 2)				**Value**
52	Systematic error related to beam peak search				0.7
53	Additional impact of interferer ACLR				0.7
54	Influence of offset antenna (mean error) (NOTE 5)				0.00
Total measurement uncertainty					**Value**
ACS Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB] (23.45GHz <= f <= 32.125GHz)					8.31
ACS Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB] (32.125GHz < f <= 40.8GHz)					8.31
NOTE 1: The analysis was done only for the case of operating at max output power, in-band, non-CA. NOTE 2: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 3: Applies to the system which has a structure of mechanical feed antenna positioning. NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm. NOTE 5: For MTSU derivation purpose, this value is set to 0.0 (no offset antenna case).					

NOTE: MU assessment in Table B.21.2-2 and Table B.21.2-3 is based on the following relaxation for 200MHz BW.

Table B.21.2-4: Adjacent channel selectivity requirement relaxation considered in MU assessment for 100 MHz EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, 44.3GHz, Quiet Zone size ≤ 30 cm)

Power Class	Frequency Range	Relaxation (dB)
PC3	FR2a	0
	FR2b	4.8
	FR2c	6.8
PC1	FR2a	0
	FR2b	0
PC5, PC6	FR2a	0
PC7	FR2a	3

B.22 In-Band Blocking

See B.21.

B.22.1 Uncertainty budget format and assessment for DFF

See B.21.1.

B.22.2 Uncertainty budget format and assessment for IFF

See B.21.2.

B.23

B.24

B.25 Receiver spurious emissions

Editor's Note:

- MU value analysis and offset value analysis for PC 2 and 4 are not complete.
- MU value analysis for various test setups in subsection B.25.x is not complete for above 87 GHz.
- Offset value analysis is not complete as it is derived from MU value analysis for above 87 GHz.

Test procedure of general spurious emission comprises 2 stages: coarse TRP measurement and fine TRP measurement BW. Coarse TRP measurement is introduced to reduce the measurement time by applying sparser grids and/or wider measurement BW than fine TRP measurement while having offset dB more stringent test requirement in order not to cause additional misjudgement risk. For the frequency ranges for which coarse TRP measurement does not PASS, the measurement is continued with fine TRP measurement procedure.

Table B.25-1 summarizes the MU threshold for fine TRP measurements for General spurious emissions. The origin MU values for fine TRP measurement for different test setups can be found in following subclauses.

Table B.25-1: MU threshold for TRP measurement for Rx spurious emission

Power Class	Frequency	In-band BW	In-band Power (NOTE2)	Threshold MU value [dB] (NOTE1)
PC3	6 GHz <= f <=12.75 GHz	BW <= 400MHz	P = Max Output Power	5.64
	12.75 GHz <= f <= 23.45 GHz			5.60
	23.45 GHz <= f <= 40.8 GHz			6.11
	40.8 GHz <= f <= 66 GHz			7.65
	66 GHz <= f <= 80 GHz			7.95
	80 GHz < f <= 87 GHz			8.31
PC1,PC5, PC6	6 GHz <= f <=12.75 GHz	BW <= 400MHz	P = Max Output Power	5.63
	12.75 GHz <= f <= 23.45 GHz			5.59
	23.45 GHz <= f <= 40.8 GHz			6.10
	40.8 GHz <= f <= 66 GHz			7.64
	66 GHz <= f <= 80 GHz			7.95

PC5	80 GHz < f <= 87 GHz	BW <= 400MHz	P = Max Output Power	8.31
NOTE 1: Total EIRP Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.25.2-3 to Table B.25.2-11 for PC3 UEs and in Table B.25.2-12 to Table B.25.2-16 for PC1, PC5 and PC6 UEs.				

Table B.25-2 provides valid coarse TRP measurement grids and corresponding offset dB value that may be used for UE general spurious emission test case. The offset value is derived as 95%-tile TRP measurement uncertainty including the effect from uncertainty due to Coarse TRP measurement grid, excluding influence of noise.

Table B.25-2: Coarse TRP measurement grids and offset values for UE Rx spurious emission

Power Class	Coarse TRP measurement grid	Frequency	Min Number of measurement points on the grid	Influence of coarse TRP measurement grid (dB)	Systematic error due to coarse TRP calculation/quadrature (dB)	Offset value (dB)
PC3	Constant density grid (charged particle based)	6 GHz <= f <=12.75 GHz	35	0.94	0.09	5.38
		12.75 GHz <= f <= 23.45 GHz				5.35
		23.45 GHz <= f <= 40.8 GHz				5.49
		40.8 GHz <= f <= 66 GHz				7.31
		66 GHz <= f <= 87 GHz				7.61
	Constant step size grid	6 GHz <= f <=12.75 GHz	62	0.97	0.2	5.51
		12.75 GHz <= f <= 23.45 GHz				5.48
		23.45 GHz <= f <= 40.8 GHz				5.62
		40.8 GHz <= f <= 66 GHz				7.43
		66 GHz <= f <= 87 GHz				7.73
PC1, PC5, PC6	Constant density grid (charged particle based)	6 GHz <= f <=12.75 GHz	FFS	FFS	FFS	FFS
		12.75 GHz <= f <= 23.45 GHz				FFS
		23.45 GHz <= f <= 40.8 GHz				FFS
		40.8 GHz <= f <= 66 GHz				FFS
		66 GHz <= f <= 80 GHz				FFS
	Constant step size grid	6 GHz <= f <=12.75 GHz	FFS	FFS	FFS	FFS
		12.75 GHz <= f <= 23.45 GHz				FFS
		23.45 GHz <= f <= 40.8 GHz				FFS
		40.8 GHz <= f <= 66 GHz				FFS
		66 GHz <= f <= 80 GHz				FFS
NOTE 1: Based on Total TRP Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table B.25.2-3 to Table B.25.2-11, replacing “Influence of TRP measurement grid” and “Systematic error due to TRP calculation/quadrature” by the values for coarse TRP grid, and excluding “Influence of noise”.						

B.25.1 Uncertainty budget format and assessment for DFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.25.1-1.

Table B.25.1-1: Uncertainty contributions for TRP measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of quiet zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing Wave Between the DUT and measurement antenna	B.2.1.5
6	Uncertainty of the RF power measurement equipment	B.2.1.6
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Influence of TRP measurement grid	B.2.1.22
14	Influence of beam peak search grid	B.2.1.23
15	Multiple measurement antenna uncertainty	B.2.1.25
16	DUT repositioning	B.2.1.26
Stage 1: Calibration measurement		
17	Mismatch	B.2.1.4
18	Amplifier uncertainties	B.2.1.8
19	Misalignment of positioning System	B.2.1.13
20	Uncertainty of the Network Analyzer	B.2.1.14
21	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
23	Phase centre offset of calibration antenna	B.2.1.18
24	Quality of quiet zone for calibration process	B.2.1.19
25	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
26	Influence of the calibration antenna feed cable	B.2.1.21
27	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
28	Systematic error due to TRP calculation/quadrature	B.2.1.24
29	Influence of noise	B.2.1.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of D = [5 cm], f = {6 GHz to 87 GHz}, P = [Off power].
- The uncertainty assessment for TRP is provided in Table B.25.1-2 to B.25.1-xx

Table B.25.1-2: Uncertainty assessment for TRP measurement (f=TBD, D=TBD)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment				
2	Measure distance uncertainty				
3	Quality of quiet zone				
4	Mismatch (NOTE 1)				
5	Standing Wave Between the DUT and measurement antenna				
6	Uncertainty of the RF power measurement equipment (NOTE 2)				
7	Phase curvature				
8	Amplifier uncertainties				
9	Random uncertainty				
10	Influence of the XPD				
11	Insertion Loss Variation				
12	RF leakage (from measurement antenna to the receiver/transmitter)				
13	Influence of TRP measurement grid (NOTE 3)				
14	Influence of beam peak search grid (NOTE 4)				
15	Multiple measurement antenna uncertainty				
16	DUT repositioning				
Stage 1: Calibration measurement					
17	Mismatch				
18	Amplifier uncertainties				
19	Misalignment of positioning System				
20	Uncertainty of the Network Analyzer				
21	Uncertainty of the absolute gain of the calibration antenna				
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna				
23	Phase centre offset of calibration antenna				
24	Quality of quiet zone for calibration process				
25	Standing wave between reference calibration antenna and measurement antenna				
26	Influence of the calibration antenna feed cable				
27	Insertion Loss Variation				
TRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					
Systematic uncertainties (NOTE 5)					**Value**
28	Systematic error due to TRP calculation/quadrature (NOTE 3)				
29	Influence of noise				
Total measurement uncertainty					
TRP total measurement uncertainty [dB]					

NOTE 1: The analysis was done only for the case of operating at max output power, in-band, non-CA.
NOTE 2: The assessment assumes maximum DUT output power.
NOTE 3: This contributor shall only be considered for TRP measurements.
NOTE 4: This contributor shall only be considered for EIRP measurements.
NOTE 5: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 6: Void

B.25.2 Uncertainty budget format and assessment for IFF

The uncertainty contributions that may impact the overall MU value are listed in Table B.25.2-1.

Table B.25.2-1: Uncertainty contributions for TRP measurement

UID	Description of uncertainty contribution	Details in clause
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	Uncertainty of the RF power measurement equipment	B.2.2.6
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Influence of TRP measurement grid	B.2.2.22
14	Influence of beam peak search grid	B.2.2.23
15	Multiple measurement antenna uncertainty	B.2.2.25
16	DUT repositioning	B.2.2.26
17	Misalignment of DUT due to change of DUT orientation	B.2.2.31
Stage 1: Calibration measurement		
18	Mismatch	B.2.2.4
19	Amplifier Uncertainties	B.2.2.8
20	Misalignment of positioning System	B.2.2.13
21	Uncertainty of the Network Analyzer	B.2.2.14
22	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
24	Phase centre offset of calibration antenna	B.2.2.18
25	Quality of quiet zone for calibration process	B.2.2.19
26	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
27	Influence of the calibration antenna feed cable	B.2.2.21
28	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
29	Systematic error due to TRP calculation/quadrature	B.2.2.24
30	Influence of noise	B.2.2.27

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ 30 cm, f = {6 GHz to 87 GHz}, P =Receiver Spurious Core Requirement Level + Relaxation(For n257, 10.2dB for 6GHz $\leq$ f < 20GHz, 17.2 dB for 20GHz$\leq$ f < 40GHz, 33.1dB for 40GHz $\leq$ f $\leq$ 2nd harmonic)
- The uncertainty assessment for TRP is provided from Table B.25.2-2 to Table B.25.2-11 for PC3 UEs and from Table B.25.2-12 to Table B.25.2-16 for PC1, PC5 and PC6 UEs.

Table B.25.2-2: Void

Table B.25.2-3: Uncertainty assessment for TRP measurement (f=6 GHz to 12.75 GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.70	Actual	1.00	0.70
4	Mismatch	1.60	Actual	1.00	1.60
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.00	Normal	2.00	1.00
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.32	Actual	1	0.32
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.70	Actual	1.00	0.70
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (6 GHz < f <= 12.75 GHz) [dB] (a)				5.00
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.0
30	Influence of noise (6 GHz < f <= 12.75 GHz) (c)				0.64

31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
Total measurement uncertainty (a)+(b)+(c) [dB]		5.64

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.25.2-4: void

Table B.25.2-5: Uncertainty assessment for TRP measurement (f=12.75 GHz to 23.45 GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.60	Actual	1.00	0.60
4	Mismatch	1.60	Actual	1.00	1.60
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.16	Normal	2.00	1.08
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.32	Actual	1	0.32
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.60	Actual	1.00	0.60
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (12.75 GHz < f <= 23.45 GHz) [dB] (a)				4.96
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.0
30	Influence of noise (12.75 GHz < f <= 23.45 GHz) (c)				0.64

31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
Total measurement uncertainty (a)+(b)+(c) [dB]		5.60

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.25.2-6: Void

Table B.25.2-7: Uncertainty assessment for TRP measurement (f=23.45 GHz to 40.8 GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	1.50	Actual	1.00	1.50
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.73	Normal	2.00	1.37
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.32	Actual	1	0.32
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.6	Normal	2.00	0.3
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.6	Actual	1.00	0.6
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (23.45 GHz < f <= 40.8 GHz) [dB] (a)				5.11
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.0
30	Influence of noise (23.45 GHz < f <= 40.8 GHz) (c)				1.0

31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
Total measurement uncertainty (a)+(b)+(c) [dB]		6.11

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.25.2-8: Void

Table B.25.2-9: Uncertainty assessment for TRP measurement (f= 40.8 GHz to 66 GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.0	Normal	2.00	0.0
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	2.30	Actual	1.00	2.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	4.0	Normal	2.00	2.00
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.32	Actual	1	0.32
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.7	Normal	2.00	0.85
22	Uncertainty of the absolute gain of the calibration antenna	1.70	Normal	2.00	0.85
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.6	Actual	1.00	0.6
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.28	Normal	2.00	0.14
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (40.8 GHz < f <= 66 GHz) [dB] (a)				7.01
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.0
30	Influence of noise (40.8 GHz < f <= 66 GHz) (c)				0.64

31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
Total measurement uncertainty (a)+(b)+(c) [dB]		7.65

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.25.2-10: Void

Table B.25.2-11: Uncertainty assessment for TRP measurement (f= 66 GHz to 87 GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	2.30	Actual	1.00	2.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	4.0	Normal	2.00	2.0
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	3.0	Normal	2.00	1.50
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.32	Actual	1	0.32
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.7	Normal	2.00	0.85
22	Uncertainty of the absolute gain of the calibration antenna	1.70	Normal	2.00	0.85
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.60	Actual	1.00	0.60
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.28	Normal	2.00	0.14
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (66 GHz < f <= 87 GHz) [dB] (a)				7.31
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.0
30	Influence of noise (66 GHz < f <= 80 GHz) (c)				0.64

30	Influence of noise (80 GHz < f <= 87 GHz) (c)	1.00
31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
Total measurement uncertainty (a)+(b)+(c) [dB] (66 GHz < f <= 80 GHz)		7.95
Total measurement uncertainty (a)+(b)+(c) [dB] (80 GHz < f <= 87 GHz)		8.31

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.25.2-12: Uncertainty assessment for TRP measurement (f=6 GHz to 12.75 GHz, Quiet Zone size ≤ 30 cm) for PC1, PC5 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.70	Actual	1.00	0.70
4	Mismatch	1.60	Actual	1.00	1.60
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.00	Normal	2.00	1.00
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.70	Actual	1.00	0.70
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty ([6] GHz < f <= [12.75] GHz) [dB] (a)				4.99
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.00
30	Influence of noise (6 GHz < f <= 12.75 GHz) (c)				0.64

31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
Total measurement uncertainty (a)+(b)+(c) [dB]		5.63

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.25.2-13: Uncertainty assessment for TRP measurement (f=12.75 GHz to 23.45 GHz, Quiet Zone size ≤ 30 cm) for PC1, PC5 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.60	Actual	1.00	0.60
4	Mismatch	1.60	Actual	1.00	1.60
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.16	Normal	2.00	1.08
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.60	Actual	1.00	0.60
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (12.75 GHz < f <= 23.45 GHz) [dB] (a)				4.95
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.00
30	Influence of noise (12.75 GHz < f <= 23.45 GHz) (c)				0.64

31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
Total measurement uncertainty (a)+(b)+(c) [dB]		5.59

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.25.2-14: Uncertainty assessment for TRP measurement (f=23.45 GHz to 40.8 GHz, Quiet Zone size ≤ 30 cm) for PC1, PC5 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	1.50	Actual	1.00	1.50
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	2.73	Normal	2.00	1.37
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
22	Uncertainty of the absolute gain of the calibration antenna	0.6	Normal	2.00	0.3
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.6	Actual	1.00	0.6
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (23.45 GHz < f <= 40.8 GHz) [dB] (a)				5.10
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.00
30	Influence of noise (23.45 GHz < f <= 40.8 GHz) (c)				1.0

31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
Total measurement uncertainty (a)+(b)+(c) [dB]		6.10

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.25.2-15: Uncertainty assessment for TRP measurement (f= 40.8 GHz to 66 GHz, Quiet Zone size ≤ 30 cm) for PC1, PC5 and PC6 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	2.30	Actual	1.00	2.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	4.0	Normal	2.00	2.00
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.25	Actual	1	0.25
14	Influence of beam peak search grid (NOTE 2)	N/AN/A	Actual	1	N/AN/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.7	Normal	2.00	0.85
22	Uncertainty of the absolute gain of the calibration antenna	1.70	Normal	2.00	0.85
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.6	Actual	1.00	0.6
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.28	Normal	2.00	0.14
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (40.8 GHz < f <= 66 GHz) [dB] (a)				7.00
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.00
30	Influence of noise (40.8 GHz < f <= 66 GHz) (c)				0.64

31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
Total measurement uncertainty (a)+(b)+(c) [dB]		7.64

NOTE 1: This contributor shall only be considered for TRP measurements.
NOTE 2: This contributor shall only be considered for EIRP measurements.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm.
NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.

Table B.25.2-16: Uncertainty assessment for TRP measurement (f= 66 GHz to 87 GHz, Quiet Zone size ≤ 30 cm) for PC1 and PC5 UEs

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	2.30	Actual	1.00	2.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment	4.0	Normal	2.00	2.0
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	3.0	Normal	2.00	1.50
9	Random uncertainty	0.5	Normal	2.00	0.25
10	Influence of the XPD	0.09	U-shaped	1.41	0.064
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of TRP measurement grid (NOTE 1)	0.25	Actual	1	0.32
14	Influence of beam peak search grid (NOTE 2)	N/A	Actual	1	N/A
15	Multiple measurement antenna uncertainty (NOTE 5)	0.15	Actual	1	0.15
16	DUT repositioning	0.00	Rectangular	1.73	0.00
17	Misalignment of DUT due to change of DUT orientation	0.10	Actual	1	0.10
Stage 1: Calibration measurement					
18	Mismatch	0.00	U-shaped	1.41	0.00
19	Amplifier Uncertainties	0.00	Normal	2.00	0.00
20	Misalignment of positioning System	0.00	Normal	2.00	0.00
21	Uncertainty of the Network Analyzer	1.7	Normal	2.00	0.85
22	Uncertainty of the absolute gain of the calibration antenna	1.70	Normal	2.00	0.85
23	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.05	Rectangular	1.73	0.03
24	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
25	Quality of quiet zone for calibration process (NOTE 4)	0.60	Actual	1.00	0.60
26	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
27	Influence of the calibration antenna feed cable	0.28	Normal	2.00	0.14
28	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Expanded uncertainty (1.96σ - confidence interval of 95 %)				**Value**
	TRP Expanded uncertainty (66 GHz < f <= 80 GHz) [dB] (a)				7.31
	Systematic uncertainties (NOTE 3)				**Value**
29	Systematic error due to TRP calculation/quadrature (NOTE 1) (b)				0.00
30	Influence of noise (66 GHz < f <= 80 GHz) (c_1)				0.64

30	Influence of noise (80 GHz < f <= 87 GHz) (c_2) (PC5)	1.00
31	Systematic error related to beam peak search (NOTE 2)	N/A
Total measurement uncertainty		**Value**
Total measurement uncertainty (a)+(b)+(c_1) [dB] (66 GHz < f <= 80 GHz)		7.95
Total measurement uncertainty (a)+(b)+(c_2) [dB] (80 GHz < f <= 87 GHz) (PC5)		8.31
NOTE 1: This contributor shall only be considered for TRP measurements. NOTE 2: This contributor shall only be considered for EIRP measurements. NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors. NOTE 4: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size of less or equal to 30 cm. NOTE 5: Applies to the system which has a structure of mechanical feed antenna positioning.		

B.26 FR2 RF test cases with testability issues related to MU

Editor's note: This informational list of FR2 RF testability issues related to MU is incomplete and ongoing updates.

Table B.26-1: FR2 RF test cases with known testability issues related to MU

Clause	Requirement	FR2 RF Testability issues related to MU	Notes
6.3.1	Minimum output power	Low UL power	For several test points (details in sub-clause 6.3.1.5), Core requirement cannot be tested due to testability issue and test requirement includes relaxation to achieve impact from test system noise to measurement result = 1.0 dB (Minimum requirement + relaxation).
6.3.2	Transmit OFF power	Low UL power	For all FR2 bands and channel bandwidths, Core requirement cannot be tested due to testability issue and test requirement includes relaxation to achieve impact from test system noise to measurement result = 1.0 dB (Minimum requirement + relaxation).
6.3.4.3	Relative Power Tolerance	Starting power at ramp up/ramp down/alternating sub-test is TBD (6.3.4.3 MU dependent)	Testability issue due to narrow range for 1 dB TPC step core requirement and therefore testing is not recommended.
6.3D.2	Transmit OFF power for UL MIMO	The testability of this test case is pending further analysis on relaxation of the requirement for other than Band n257.	For several test points (see 6.3D.2.5 for details), Core requirement cannot be tested due to testability issue and test requirement includes relaxation to achieve impact from test system noise to measurement result = 1.0 dB (Minimum requirement + relaxation).
6.5.1	Occupied bandwidth	High SNR required for measurement	To avoid testability issues, MBW has been reduced from 2*CBW (typical used value in FR1) down to 1.5*CBW in general and even down to 1.3*CBW for PC3 400MHz in FR2c.
6.5.2.1	Spectrum Emission Mask	Low Spurious Emission power	Testability in FR2b for PC1 is FFS. For PC1 in FR2a, to avoid defining relaxations, accepted to use influence of noise remarkable higher than 1dB in the MTSU calculation.
6.5.2.3	Adjacent channel leakage ratio	Low adjacent channel power	Relaxation due to testability limits applied for several TC IDs and MPR values as defined in subclause 6.5.2.3.5
6.5.3.2	Additional spurious emissions	Low Spurious Emission power	Relaxation due to testability limit applied to test requirements as per subclause 6.5.3.2.5
6.5D.2.1	Occupied bandwidth for UL MIMO	High SNR required for measurement	Testability is FFS for PC3 FR2c 400 MHz and other power classes.
7.4	Maximum input power	High DL power	The test requirements deviate from minimum requirements by 26dB relaxation for 24.25 ~ 29.5 GHz and 34 dB relaxation for 37 ~ 40 GHz.
7.5	Adjacent channel selectivity (case 1)	High DL power	For several test points, Core requirement cannot be tested due to testability issue and test requirement for wanted signal and interferer includes relaxation to achieve feasible interferer power level. See details in subclause 7.5.5
7.6.2	In-band blocking	High DL power	For several test points, Core requirement cannot be tested due to testability issue and test requirement for wanted signal and interferer includes relaxation to achieve feasible interferer power level. See details in subclause 7.6.2.5
7.9	Receiver spurious emissions	Low Spurious Emission power	The testability of this test case is pending further analysis on relaxation of the requirement for band other than n257, n258, n259, n260 and n261

Annex C: Acceptable uncertainty of test system for test cases defined in TS 38.521-3 for radiative testing

FFS

Annex D: Acceptable uncertainty of test system for test cases defined in TS 38.521-4 for radiative testing

Editor's note: The MU tables in D-1, D-2, and D-3 serve as sample, consolidated baseline tables for demodulation test cases and can be removed once the MU tables customized for each TS 38.521-4 test case have been finalized.

This annex contains suggested uncertainties for each test case in TS 38.521-4.

The baseline MU table for Mode 1 (conditions with external noise) is shown in Table D-1 for baseband-combining implementation and in Table D-2 for external-combining implementation.

Table D-1: Uncertainty Contributions for Mode 1 Demodulation Test Cases for PC1 and PC3 (Baseband-Combining Implementation)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Signal-to-noise ratio uncertainty					
Stage 2: DUT measurement					
1	Positioning misalignment		N/A	N/A	
2	Measure distance uncertainty		N/A	N/A	
3	Quality of Quiet Zone		N/A	N/A	
4	Mismatch		N/A	N/A	
5	Standing wave between the DUT and measurement antenna		N/A	N/A	
6	gNB emulator SNR uncertainty	0.3	Note 3	1.96	0.153
7	Phase curvature		N/A	N/A	
8	Amplifier uncertainties		N/A	N/A	
9	Random uncertainty		N/A	N/A	
10	Influence of the XPD		N/A	N/A	
11	Insertion Loss Variation		N/A	N/A	
12	RF leakage (from measurement antenna to the receiver/transmitter)		N/A	N/A	
13	Multiple measurement antenna uncertainty		N/A	N/A	
14	DUT repositioning		N/A	N/A	
Stage 1: Calibration measurement					
15	Mismatch		N/A	N/A	
16	Amplifier Uncertainties		N/A	N/A	
17	Misalignment of positioning System		N/A	N/A	
18	Uncertainty of the Network Analyzer		N/A	N/A	
19	Uncertainty of the absolute gain of the calibration antenna		N/A	N/A	
20	Positioning and pointing misalignment between the reference antenna and the measurement antenna		N/A	N/A	
21	Phase centre offset of calibration antenna		N/A	N/A	
22	Quality of quiet zone for calibration process		N/A	N/A	
23	Standing wave between reference calibration antenna and measurement antenna		N/A	N/A	
24	Influence of the calibration antenna feed cable		N/A	N/A	
25	Insertion Loss Variation		N/A	N/A	
Total Signal-to-Noise ratio uncertainty					
					0.153
Other contributors affecting test result					
27	gNB emulator fading model impairments	0.5 for 1Tx 0.7 for 2Tx	Note 3	1.96	0.255 for 1Tx 0.357 for 2Tx
28	AWGN flatness and signal flatness, max deviation for any Resource Block, relative to average over BW_{Config} (Note 4)	3.6	Note 3	1.96	1.837
29	SNR uncertainty due to finite test time	0.3 for PDSCH and Doppler < 100 Hz 0.0 for PDSCH and Doppler ≥ 100 Hz 0.4 for PDCCH	Note 3	1.96	0.153 for PDSCH and Doppler < 100 Hz 0.0 for PDSCH and Doppler ≥ 100 Hz 0.204 for PDCCH
	Systematic uncertainties				**Value**
26	Impact on non-ideal isolation between branches for the wireless cable mode				0.45 (Note 1) 0.60 (Note 2)
Overall system uncertainty					**Value**

	Note 5
Note 1: applies to Rank 2 test cases for FR2a, FR2b, and FR2c Note 2: applies to Rank 1 test cases for FR2a, FR2b, and FR2c Note 3: Divisor of 1.96 is applied as the uncertainty value is based on 95% confidence level k=1.96. Note 4: AWGN flatness and signal flatness has x 0.25 effect on the required SNR. This sensitivity factor shall be considered in the calculation of the test case specific uncertainty. Note 5: Example calculation for fading conditions: Overall system uncertainty for fading conditions comprises five quantities: 1. Total Signal-to-noise ratio uncertainty 2. gNB emulator fading model impairments 3. Effect of AWGN flatness and signal flatness 4. SNR uncertainty due to finite test time 5. Impact on non-ideal isolation between branches for the wireless cable mode Items 1, 2, 3 and 4 are assumed to be uncorrelated so can be root sum squared. Item 5 is systematic and is added: AWGN flatness and signal flatness has x 0.25 effect on the required SNR, so use sensitivity factor of x 0.25 for the uncertainty contribution. Overall system uncertainty = 1.96 x SQRT (Total Signal-to-noise ratio uncertainty ^{2} + gNB emulator fading model impairments^2 + (0.25 x AWGN flatness and signal flatness) ^{2} + SNR uncertainty due to finite test time^2) + Impact on non-ideal isolation between branches for the wireless cable model	

Table D-1a: Overall system uncertainty for Mode 1 Demodulation Test Cases for PC1 and PC3 (Baseband-Combining Implementation)

Overall system uncertainty	Value
PDSCH 1Tx with Doppler < 100 Hz	1.71
PDSCH 2Tx with Doppler < 100 Hz, rank 1	1.82
PDSCH 2Tx with Doppler < 100 Hz, rank 2	1.67
PDSCH 1Tx with Doppler ≥ 100 Hz	1.67
PDSCH 2Tx with Doppler ≥ 100 Hz, rank 1	1.78
PDSCH 2Tx with Doppler ≥ 100 Hz, rank 2	1.63
PDCCH 1Tx, rank 1	1.74
PDCCH 2Tx, rank 1	1.84

Table D-2: Uncertainty Contributions for Mode 1 Demodulation Test Cases (External-Combining Implementation)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Signal-to-noise ratio uncertainty					
Stage 2: DUT measurement					
1	Positioning misalignment		[Normal]	[2.00]	
2	Measure distance uncertainty		[Rectangular]	[1.73]	
3	Quality of Quiet Zone		[Actual]	[1.00]	
4	Mismatch		[Actual]	[1.00]	
5	Standing wave between the DUT and measurement antenna		[U-shaped]	[1.41]	
6	gNB emulator SNR uncertainty		[Normal]	[2.00]	
7	Phase curvature		[U-shaped]	[1.41]	
8	Amplifier uncertainties		[Normal]	[2.00]	
9	Random uncertainty		[Normal]	[2.00]	
10	Influence of the XPD		[U-shaped]	[1.41]	
11	Insertion Loss Variation		[Rectangular]	[1.73]	
12	RF leakage (from measurement antenna to the receiver/transmitter)		[Actual]	[1.00]	
13	Multiple measurement antenna uncertainty		[Actual]	[1.00]	
14	DUT repositioning		[Rectangular]	[1.73]	
Stage 1: Calibration measurement					
15	Mismatch		[U-shaped]	[1.41]	
16	Amplifier Uncertainties		[Normal]	[2.00]	
17	Misalignment of positioning System		[Normal]	[2.00]	
18	Uncertainty of the Network Analyzer		[Normal]	[2.00]	
19	Uncertainty of the absolute gain of the calibration antenna		[Normal]	[2.00]	
20	Positioning and pointing misalignment between the reference antenna and the measurement antenna		[Rectangular]	[1.73]	
21	Phase centre offset of calibration antenna		[Rectangular]	[1.73]	
22	Quality of quiet zone for calibration process		[Actual]	[1.00]	
23	Standing wave between reference calibration antenna and measurement antenna		[U-shaped]	[1.41]	
24	Influence of the calibration antenna feed cable		[Normal]	[2.00]	
25	Insertion Loss Variation		[Rectangular]	[1.73]	
	Systematic uncertainties				**Value**
26	Impact on non-ideal isolation between branches for the wireless cable mode				0.45 (Note 1) 0.60 (Note 2)
Total Signal-to-Noise ratio uncertainty					
Other contributors affecting test result					
27	gNB emulator fading model impairments		[Normal]	[2.00]	
28	AWGN flatness and signal flatness, max deviation for any Resource Block, relative to average over BW_{Config} (Note 3)		[Actual]	1.00	
29	Result variation due to finite test time		[Actual]	[1.00]	

Note 1: applies to Rank 2 test cases for FR2a, FR2b, and FR2c
Note 2: applies to Rank 1 test cases for FR2a, FR2b, and FR2c
Note 3: AWGN flatness and signal flatness has x 0.25 effect on the required SNR. This sensitivity factor shall be considered in the calculation of the test case specific uncertainty.

The baseline MU table for Mode 2 (noise free conditions) is shown in Table D-3.

Table D-3: Uncertainty Contributions for Mode 2 Demodulation Test Cases

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment		[Normal]	[2.00]	
2	Measure distance uncertainty		[Rectangular]	[1.73]	
3	Quality of Quiet Zone		[Actual]	[1.00]	
4	Mismatch		[Actual]	[1.00]	
5	Standing wave between the DUT and measurement antenna		[U-shaped]	[1.41]	
6	gNB uncertainty on absolute level		[Normal]	[2.00]	
7	Phase curvature		[U-shaped]	[1.41]	
8	Amplifier uncertainties		[Normal]	[2.00]	
9	Random uncertainty		[Normal]	[2.00]	
10	Influence of the XPD		[U-shaped]	[1.41]	
11	Insertion Loss Variation		[Rectangular]	[1.73]	
12	RF leakage (from measurement antenna to the receiver/transmitter)		[Actual]	[1.00]	
13	Multiple measurement antenna uncertainty		[Actual]	[1.00]	
14	DUT repositioning		[Rectangular]	[1.73]	
Stage 1: Calibration measurement					
15	Mismatch		[U-shaped]	[1.41]	
16	Amplifier Uncertainties		[Normal]	[2.00]	
17	Misalignment of positioning System		[Normal]	[2.00]	
18	Uncertainty of the Network Analyzer		[Normal]	[2.00]	
19	Uncertainty of the absolute gain of the calibration antenna		[Normal]	[2.00]	
20	Positioning and pointing misalignment between the reference antenna and the measurement antenna		[Rectangular]	[1.73]	
21	Phase centre offset of calibration antenna		[Rectangular]	[1.73]	
22	Quality of quiet zone for calibration process		[Actual]	[1.00]	
23	Standing wave between reference calibration antenna and measurement antenna		[U-shaped]	[1.41]	
24	Influence of the calibration antenna feed cable		[Normal]	[2.00]	
25	Insertion Loss Variation		[Rectangular]	[1.73]	
	Systematic uncertainties				**Value**
26	Systematic error related to beam peak search				
27	Impact on non-ideal isolation between branches for the wireless cable mode				0.45 (Note 1) 0.60 (Note 2)
Other contributors affecting test result					
28	Result variation due to finite test time		[Actual]	[1.00]	
Note 1: applies to Rank 2 test cases for FR2a, FR2b, and FR2c Note 2: applies to Rank 1 test cases for FR2a, FR2b, and FR2c					

D.1 Uncertainty budget calculation principle

D.1.1 Uncertainty budget calculation principle for DNF

The uncertainty tables cover the actual measurement using the DUT receiver. If applicable, any uncertainty arising from a calibration or alignment process before the measurements should also be included.

The MU budget should comprise of a minimum 5 headings:

1) The uncertainty source,
2) Uncertainty value,
3) Distribution of the probability,
4) Divisor based on distribution shape,
5) Calculated standard uncertainty (based on uncertainty value and divisor).

D.1.2 Uncertainty budget calculation principle for DFF

The same as defined in D.1.1.

D.1.3 Uncertainty budget calculation principle for IFF

The same as defined in D.1.1.

D.2 Measurement error contribution descriptions

D.2.1 Measurement error contribution descriptions for DNF

D.2.1.1 gNB emulator SNR uncertainty

This contribution originates from setting the ratio of signal and noise in the conducted part of the test system. It is estimated to be the same as for LTE conducted testing in TS 36.521-1 Annex F, which is ±0.3dB. The default for values in 36.521-1 Annex F is 95% confidence interval, normal distribution.

D.2.1.2 gNB emulator Downlink EVM

When simulations of demodulation performance are run, the downlink signal is modelled with a defined EVM, representing imperfections in the signal transmitted by the gNB. This EVM value is agreed across companies to align simulations, and is normally lower than the gNB EVM requirement, to represent “typical” conditions. The EVM used for simulations is therefore built in to the requirement points, normally specified as the SNR required to meet a specified throughput, with a defined modulation and Reference channel, under defined propagation conditions.

For a conformance test, the EVM defined for the simulations is taken as a maximum allowed value for the test system, as a worse gNB emulator EVM would make the signal harder to demodulate, and disadvantage the UE. In a test system the EVM cannot normally be set to a specific value, but is specified to be no higher than a defined value.

Following this approach, the uncertainty from gNB emulator Downlink EVM is a one-sided distribution, with beneficial effect. Without treating the positive and negative uncertainties separately, and as it would not make the SNR worse, the effective uncertainty is 0dB.

D.2.1.3 gNB emulator fading model impairments

This contribution originates from imperfections in the gNB emulator fading model, compared to the applied fading model. It is estimated to be the same as for LTE conducted testing in TS 36.521-1 Annex F, which is ±0.5dB. The default for values in 36.521-1 Annex F is 95% confidence interval, normal distribution.

D.2.2 Measurement error contribution descriptions for DFF

D.2.2.1 gNB emulator SNR uncertainty

See D.2.1.1.

D.2.2.2 gNB emulator Downlink EVM

See D.2.1.2.

D.2.2.3 gNB emulator fading model impairments

See D.2.1.3.

D.2.3 Measurement error contribution descriptions for IFF

The Measurement uncertainty contributions and uncertainty assessment are expected to be the same as for the Direct near field (DNF) setup in D.2.1.

D.2.3.1 gNB emulator SNR uncertainty

See D.2.1.1.

D.2.3.2 gNB emulator Downlink EVM

See D.2.1.2.

D.2.3.3 gNB emulator fading model impairments

See D.2.1.3.

D.3 Assessment of testable DL SNR range and accuracy

The signal and the noise provided by the test system are both attenuated by the over-the-air link loss. The UE noise then adds to the noise provided by the test system, hence degrading the SNR seen by the UE and potentially limiting the testable SNR range. The calculations and graphs in this clause allow this SNR degradation to be assessed over a range of scenarios.

For conducted tests, the noise provided by the test system can be set much higher than the UE noise and the SNR degradation is negligible. However for over-the-air test systems, the power that can realistically be delivered into the test system probe antenna is limited, so the test point is likely to be closer to the UE noise and a small SNR degradation is allowable.

D.3.1 Method and Parameters

The method is the same as in clause B.2.1.5.1 of TR 38.810 [13], but some values related to the test system are different. The calculation of noise level is described in clause 7.2.1.3 of TR 38.810 [13]. Under fading conditions the backoff is [17.71] dB instead of 13 dB when no fading applies.

D.3.2.1 SNR range for SNR_{RP} - SNR_{BB} ≤ 1dB for DFF

FFS

D.3.2.2 SNR range for SNR_{RP} - SNR_{BB} ≤ 1dB for IFF

Based on the method of setting the noise from the Test system to give a maximum of 1dB degradation in overall SNR between reference point and baseband, we can then work back through the signal chain to determine how high the SNR can be set. As the noise is set to a fixed level, the maximum SNR is set by the test system power amplifier and the channel bandwidth to be tested.

The SNR upper bound depends on the type of test system. For the Indirect Far field (IFF) setup the diagram below illustrates the principle, and is based on the “IFF 100MHz (n257, n258, n261)” tab of the accompanying spreadsheet.

The process works back through the signal chain, from left to right in the diagram.




Figure D.3.2.2-1: Estimation of single band UE SNR range for Indirect far field (IFF) when no fading applies

The test equipment must supply at least the wanted noise level at the reference point. If the noise was lower, the degradation in SNR would be greater than 1dB, and may cause a conformant UE to fail.

For mode2 (noise free) scenarios, the expected SNR at the UE reference point is determined by the level of wanted signal power set by the TE above the UE REFSENS point.

The accuracy of setting the signal and noise levels has been taken as ±5.19 dB.

Inclusion of this contribution directly reduces the maximum SNR that can be measured by a test system for a given channel bandwidth.

To find the maximum SNR that can be measured by a test system with a specific Channel BW, the baseband SNR in the spreadsheet is increased until the value "Wanted signal + headroom, dBm/Ch BW" is just below the "Available DL power at CW 1dB compression at QZ, dBm" value. For fading conditions, the "Backoff from P1dB" with a value of -11.08 dB valid for modulations up to 64 QAM has been applied. In the case without fading with added noise, the "Backoff from P1dB" is [-13] dB valid for modulations up to 64 QAM. The resulting values for SNR_{BB} are given in Table D.3.2.2-1 for tests cases making use of fading, D.3.2.2-2 for test cases without fading with added Noise.

Single band UE values are obtained by setting the UE multi-band relaxation factor to 0 dB.

Table D.3.2.2-1: Predicted SNR_{BB} upper bound values for Indirect far field (IFF) with 30cm QZ, PC3, 100MHz CHBW, modulation up to 64 QAM under fading conditions

	Operating Band	Maximum SNR_{BB} (dB)		
		CHBW 50 MHz	CHBW 100 MHz	CHBW 200 MHz
Multi-band UE (Note)	n257	30.6	27.5	24.4
	n258	30.6	27.5	24.4
	n259	20.4	17.2	14.1
	n260	24.4	21.2	18.2
	n261	30.6	27.5	24.4
Note: For ∑MBp from TS 38.101-2 [16] Table 6.2.1.3-4 allow up to 0.75 dB in Rel-15.				

Table D.3.2.2-2: Predicted SNR_{BB} upper bound values for Indirect far field (IFF) with 30cm QZ, PC3, 100MHz CHBW, modulation up to 64 QAM when no fading conditions apply

	Operating Band	Maximum SNR_{BB} (dB)		
		CHBW 50 MHz	CHBW 100 MHz	CHBW 200 MHz
Multi-band UE (Note)	n257	[28.7]	[25.5]	[22.5]
	n258	[28.7]	[25.5]	[22.5]
	n259	[18.4]	[15.2]	[12.1]
	n260	[22.5]	[19.3]	[16.3]
	n261	[28.7]	[25.5]	[22.5]
Note: For ∑MBp from TS 38.101-2 [16] Table 6.2.1.3-4 allow up to 0.75 dB in Rel-15.				

For mode2 (noise free) scenarios, the maximum baseband SNR that can be achieved by a test system is calculated in the spreadsheet "Mode2 100MHz". For other channel bandwidths the respective N_{RB} and $EIS_{PC3,\,band}$ are to be used.

For the "Backoff from P1dB" a value of -13dB has been applied which is valid for modulations up to 64QAM. The resulting values for SNR_{BB} are given in D.3.2.2-3 for test cases without fading and without added noise.

Table D.3.2.2-3: Predicted SNR_{BB} upper bound values for Indirect far field (IFF) with 30cm QZ, PC3, 100MHz CHBW, modulation up to 64 QAM when no fading conditions and no added noise apply

	Operating Band	Maximum SNR_{BB} (dB)		
		CHBW 50 MHz	CHBW 100 MHz	CHBW 200 MHz
Multi-band UE (Note)	n257	[35.56]	[32.56]	[29.56]
	n258	[35.56]	[32.56]	[29.56]

	n259	[25.36]	[22.36]	[19.36]
	n260	[29.36]	[26.36]	[23.36]
	n261	[35.56]	[32.56]	[29.56]
Note1: For ∑MBp from TS 38.101-2 [16] Table 6.2.1.3-4 allow up to 0.75 dB in Rel-15.				

Note that these are UE baseband SNR values (SNR_{BB}), so the Reference point figures used in TS 38.101-4 [19] will be 1 dB higher.

Table D.3.2.2-4: Predicted SNR_{BB} upper bound values for Indirect far field (IFF) with 30cm QZ, PC3, 100MHz CHBW, modulation up to 256 QAM under fading conditions for DEMOD scenarios

Operating Band / Frequency	Maximum testable SNR_{BB} (dB)		
	CHBW 50 MHz	CHBW 100 MHz	CHBW 200 MHz
n257 mid	29.1	25.9	22.9
n258 mid	29.1	25.9	22.9
n259 mid	18.8	15.6	12.5
n260 mid	22.9	19.7	16.6
n261 mid	29.1	25.9	22.9

Table D.3.2.2-5: Predicted SNR_{BB} upper bound values for Indirect far field (IFF) with 30cm QZ, PC1, 100MHz CHBW, modulation up to 256 QAM under fading conditions for DEMOD scenarios

Operating Band / Frequency	Maximum testable SNR_{BB} (dB)		
	CHBW 50 MHz	CHBW 100 MHz	CHBW 200 MHz
n257 mid	39.0	35.9	32.9
n258 mid	39.0	35.9	32.9
n259 mid	TBD	TBD	TBD
n260 mid	32.4	29.3	26.3
n261 mid	39.0	35.9	32.9

Table D.3.2.2-6: Predicted SNR_{BB} upper bound values for Indirect far field (IFF) with 30cm QZ, PC3, 100MHz CHBW, modulation up to 256 QAM under fading conditions for CSI scenarios

Operating Band / Frequency	Maximum testable SNR_{BB} (dB)		
	CHBW 50 MHz	CHBW 100 MHz	CHBW 200 MHz
n257 mid	26.3	23.2	20.1
n258 mid	26.3	23.2	20.1
n259 mid	16.0	12.8	9.6
n260 mid	20.1	16.9	13.8
n261 mid	26.3	23.2	20.1

Table D.3.2.2-7: Predicted SNR_{BB} upper bound values for Indirect far field (IFF) with 30cm QZ, PC3, 100MHz CHBW, modulation up to 256 QAM with no fading conditions for CSI scenarios

Operating Band / Frequency	Maximum testable SNR_{BB} (dB)		
	CHBW 50 MHz	CHBW 100 MHz	CHBW 200 MHz
n257 mid	28.7	25.5	22.5
n258 mid	28.7	25.5	22.5
n259 mid	18.4	15.2	12.1
n260 mid	22.5	19.3	16.3
n261 mid	28.7	25.5	22.5

An example of SNR calculation for IFF method is provided in “38.521-4 Spreadsheet - Demod SNR range calculator.zip” file attached to the TR.

D.4 Simulation results

During the MU discussions to determine the maximum testable SNR for IFF setup with PC3 30cm QZ, it was found that using a conservative “backoff from P1 dB” value (where signal backoff and fading crest factor were considerably independently), caused most of the RAN4 defined test points to be untestable.

By simulating the CCDF of RAN4 defined signal waveform and faded signal waveform, it was concluded to consider the faded signal crest factor instead of independently adding signal crest factor and fading crest factor.

Figure D.4-1 below captures the CCDF of test 2-6 from table 7.2.2.2.1_1.4-2 of TS 38.521-4 which was considered as the scenario with highest faded signal crest factor for 64QAM.

For the simulation, actual signal corresponding to the RAN4 defined scenarios was generated and the appropriate fading profile as specified in the requirement was applied. Simulations were run for 4*10^8 samples.

In figure D.4-1, Hx denotes the actual RAN4 signal per Rx after fading is applied. The value in dB against each legend correspond to the computed PAPR for that signal and faded signal




Figure D.4-1: CCDF of Test2-6 signal power and signal power after fading

Considering the max PAPR value of the faded signal allowed some more test points to be testable. In order to make more test points testable, higher probability of saturation of faded signal needed to be considered.

In order to determine how much faded signal clipping probability did not adversely impact the UE’s capability to successfully decode the PDSCH signal, simulations were run for most of the 64QAM and 256QAM test points defined in TS 38.521-4.

Two companies participated in providing the simulation results. Below tables and figures capture the simulation results from the 2 companies that was used to determine the faded signal clipping probability to be used for the “backoff from P1 dB” term.

Table D.4-1: Faded signal PAPR at different clipping probability for all test points defined in TS 38.521-4 (Company 1)

	Test#	Fading	MCS	Test SNR	numSamples	Mean Signal Pwr (Rx0/Rx1)	Mean Faded signal Pwr (Rx0/Rx1)	Signal PAPR (Rx0/Rx1)	Faded Signal PAPR (Rx0/Rx1)	Faded Signal PAPR at 1e-6 clipping prob	Faded Signal PAPR at 1e-4 clipping prob	Faded Signal PAPR at 1e-3 clipping prob
1	1-1	TDLC60-300 Low	QPSK	1.4	1.23E+08	-4.44|-4.45	-1.39|-1.37	12.89|13.08	16.87|17.40			
2	1-2	TDLA30-300 Low	16QAM	3.6					leverage from 2-2			
3	1-3	TDLA30-300 XPL Med	64QAM	14.2	1.23E+08	-4.44|-4.45	-1.52|-1.39	13.04|13.15	17.78|18.20	15.72|16.21		8.24|8.4
4	1-4	TDLD30-75 Low	256QAM	21.9	9.22E+07	-4.58|-4.59	-1.72|-1.60	13.31|13.29	17.0|16.24	15.08|14.82	12.62|12.5	10.96|10.84
5	2-1	TDLA30-75 Low	QPSK	5.8					leverage from 2-6			
6	2-2	TDLA30-300 Low	16QAM	16	1.23E+08	-4.44|-4.45	-1.5|-1.43	12.95|12.96	16.37|16.52			
7	2-6	TDLA30-75 Low	64QAM	20.3	3.98E+08	-4.44	-1.54	13.77|13.23	17.77|17.01	14.73|14.54		
8	3-1	TDLA30-75 ULA Medium	16QAM	20.7	1.23E+08	-4.44|-4.45	-1.71|-1.78	12.95|12.96	16.03|16.48	14.19|14.55		
9	8.2.2.2.2	TDLA30-35 ULA High	256QAM	6/7, 12/13, 7/8, 20/21	9.22E+07	-4.59|-4.59	-1.70|-1.90	12.86|12.82	19.24|20.72	17.69|19.05	14.74|15.36	12.64|12.96
10	8.3.2.2.1	TDLA30-35 Low	16QAM		1.23E+08	-4.45|-4.45	-1.86|-1.96	12.76|12.85	17.80|17.19	15.35|15.45		
11	8.4.2.2 Test1/2	TDLA30-35 Low	64QAM	0,16	1.23E+08	-4.45|-4.45	-1.86|-2.0	13.46|12.90	15.98|15.86			
12	8.4.2.2 Test3	TDLA30-35 XP High	64QAM	16	1.23E+08	-4.45|-4.45	-1.80|-2.07	13.25|13.27	16.99|18.05	15.57|15.54		
13	8.4.2.2 Test3	TDLA30-35 XP High	64QAM	16	1.23E+08	-4.45|-4.45	-1.86|-2.08	13.46|12.90	15.42|15.77			
14	8.2.2.2.1.1	AWGN only	64QAM	8/9, 14/15		Signal PAPR already available as part of other cases						

Table D.4-2: Throughput values for key test points at different faded signal clipping probabilities (Company 1)

Test#	Test SNR	Scenario	1E-06	1E-04	1E-03	1E-02
1-3	14.2	64QAM Demod	100%	100%	100%	100%
2-6	20.3	64QAM Demod	100%	100%	100%	100%
1-4	22	256QAM Demod	100%	100%	100%	83%
8.2.2.2.2	13	64QAM CSI	100%	100%	100%	98%
8.2.2.2.2	21	256QAM CSI	100%	100%	97%	85%
Note: All throughput values normalized to the no faded signal clipping case						

Table D.4-3: Faded signal PAPR at different clipping probability for 256QAM test 1-4 (Company 2)

Clipping probability	PAPR (dB)
1e-6	15.43
1e-5	14.43
1e-4	13.18
1e-3	11.69
1e-2	9.79
1e-1	7.11




Figure D.4-2: Throughput vs SNR for 64QAM test 2-6 at different faded signal clipping probabilities (Company 2)




Figure D.4-3: Throughput vs SNR for 256QAM test at different faded signal clipping probabilities (Company 2)

Based on the above simulation results,

For 64QAM scenarios (both Demod and CSI), fading backoff margin of 11.08 dB corresponding to the 1e-3 faded signal clipping probability was considered.

For 256QAM Demod, fading backoff margin of 12.62 dB corresponding to 1e-3 fading signal clipping probability was considered.

For 256QAM CSI scenarios, fading backoff margin of 15.36 dB corresponding to 1e-4 fading signal clipping probability was considered.

Annex E: Acceptable uncertainty of test system for test cases defined in TS 38.533 for radiative testing

This annex contains suggested uncertainties for each test case or MU quantity in TS 38.533 [10].

E.1 Uncertainty budget calculation principle

E.1.1 Uncertainty budget calculation principle for DFF

The uncertainty tables cover the actual measurement using the DUT. In some cases, uncertainty may also arise from a calibration or alignment process before the measurements.

When a calibration process is used before the measurements, the uncertainty tables should be presented with two stages:

- Stage 1: the calibration of the absolute level of the DUT measurement results is performed by means of using a calibration antenna whose absolute gain is known at the frequencies of measurement
- Stage 2: the actual measurement with the DUT as either the transmitter or receiver is performed.

The MU budget should comprise of a minimum 5 headings:

1) The uncertainty source,
2) Uncertainty value,
3) Distribution of the probability,
4) Divisor based on distribution shape,
5) Calculated standard uncertainty (based on uncertainty value and divisor).

E.1.2 Uncertainty budget calculation principle for IFF

The same as defined in E.1.1.

E.2 Measurement error contribution descriptions

E.2.1 Measurement error contribution descriptions for DFF

All the measurement error contributions defined in Section B.2.1, with the following additions and exceptions.

E.2.1.1 gNB emulator SNR uncertainty

See D.2.1.1.

E.2.1.2 gNB emulator Downlink EVM

See D.2.1.2.

E.2.1.3 gNB emulator fading model impairments

See D.2.1.3.

E.2.1.4 Uncertainty of the Network Analyzer

See B.2.2.14.

The uncertainty value of uncertainty of the network analyzer is estimated as below table and used across clause E.

Table E.2.1. 4-1: Uncertainty value for uncertainty of the network analyser for DFF

Power class	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
PC3	0.73	Normal	2.00	0.37

E.2.2 Measurement error contribution descriptions for IFF

All the measurement error contributions defined in Section B.2.2, with the following additions and exceptions.

E.2.2.1 gNB emulator SNR uncertainty

See D.2.1.1.

E.2.2.2 gNB emulator Downlink EVM

See D.2.1.2.

E.2.2.3 gNB emulator fading model impairments

See D.2.1.3.

E.2.2.4 Uncertainty of the Network Analyzer

See E.2.1. 4.

E.3 Uncertainty assessment for RRM MU quantities.

RRM measurement uncertainty analysis shall define the values for the following MU quantities:

- DL AWGN absolute power or wanted DL signal absolute power
- DL applied SNR
- DL Fading profile uncertainty
- DL AWGN and signal flatness
- UL absolute power measurement
- UL relative power measurement
- UL signal transmit timing relative to DL
- Relative transmit timing accuracy during UE timing adjustment

E.3.1 Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power

Table E.3.1-1 summarizes the MU threshold for DL AWGN absolute power for RRM FR2 test cases. The origin MU values for different test setups with varies parameters can be found in following subclauses.

Table E.3.1-1: MU threshold for DL AWGN absolute power for RRM FR2

Power Class	Frequency	MBW	Power	Threshold MU value (NOTE 1)
PC3	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	As configured in the test case	5.65 dB[2]
	32.125GHz < f <= 40.8GHz			5.65 dB[2]
PC1	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	As configured in the test case	5.65 dB[3]
	32.125GHz < f <= 40.8GHz			5.65 dB[3]
PC6	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	As configured in the test case	5.65 dB[4]

NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table E.3.1.3-2 for PC3 UEs , Table E.3.1.3-3 for PC1 UEs and E.3.1.3-4 for PC6 UEs.

NOTE 2: If the TT analysis for a specific test case based on this MU value results in an unsolvable conflict, making the test case untestable, even after the alternative solutions listed in clause A.4 have been considered for the test case in TS 38.133 [6] Annex A, the TT analysis shall be repeated using a lower MU value, taking into account the lower values defined in this clause. The test case will be applicable for the subset of the test systems meeting this reduced MU Threshold.

NOTE 3: For simpler MU definition in TS 38.533 the PC3 Threshold MU value is reused for PC1. As the difference of PC1 MU of 5.63 dB compared to PC3 Threshold MU of 5.65 dB is insignificant.

NOTE 4: For simpler MU definition in TS 38.533 the PC3 Threshold MU value is reused for PC6. The difference between PC6 MU of 5.62 dB and PC3 Threshold MU of 5.65 dB is insignificant. The MU value shall be considered only for 1 AoA test cases. For the 2 AoA test cases, further analysis is needed.

The types of test setup are defined in clause 7.1.3.2 of TS 38.508-1 [18]

E.3.1.1 Uncertainty budget format and assessment for DFF test setup

The uncertainty contributions that may impact the overall MU value are listed in Table E.3.1.1-1.

Table E.3.1.1-1: Uncertainty contributions for DL AWGN absolute power or wanted DL signal absolute power

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of Quiet Zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing wave between the DUT and measurement antenna	B.2.1.5
6	gNB emulator uncertainty	B.2.1.17
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Multiple measurement antenna uncertainty	B.2.1.25
14	DUT repositioning	B.2.1.26
Stage 1: Calibration measurement		
15	Mismatch	B.2.1.4
16	Amplifier Uncertainties	B.2.1.8
17	Misalignment of positioning System	B.2.1.13
18	Uncertainty of the Network Analyzer	E.2.1.4
19	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
20	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
21	Phase centre offset of calibration antenna	B.2.1.18
22	Quality of quiet zone for calibration process	B.2.1.19
23	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
24	Influence of the calibration antenna feed cable	B.2.1.21
25	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
26	Systematic error related to beam peak search	B.2.1.28

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz}.
- The uncertainty assessment is applicable for 1AoA and 2AoA test cases
- The uncertainty assessment is provided in Table E.3.1.1-2.

Table E.3.1.1-2: Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.15	Rectangular	1.73	0.08
3	Quality of Quiet Zone (NOTE 4)	1.2	Actual	1.00	1.2
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level	2.9	Normal	2.00	1.45
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.06	U-shaped	1.41	0.043
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
15	Mismatch	0.00	U-shaped	1.41	0.00
16	Amplifier Uncertainties	0.00	Normal	2.00	0.00
17	Misalignment of positioning System	0.00	Normal	2.00	0.00
18	Uncertainty of the Network Analyzer	0.73	Normal	2.00	0.37
19	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
20	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
21	Phase centre offset of calibration antenna	0.47	Rectangular	1.73	0.27
22	Quality of quiet zone for calibration process (NOTE 4)	0.4	Actual	1.00	0.4
23	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
24	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
25	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 2)				**Value**
26	Systematic error related to beam peak search				0.5
Total measurement uncertainty					**Value**
DL AWGN absolute power or wanted DL signal absolute power expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					5.65

NOTE 1: The analysis was done only for the case of operating in-band, non-CA.
NOTE 2: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 3: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 4: Value based on procedure defined in Annex D.2 of TR 38.810 [13] for Quiet Zone size less or equal to 30 cm.
NOTE 5: The values in this table have been derived for DL powers above and equal to REFSENS. The values might need to be revisited for power levels below REFSENS

E.3.1.2 Uncertainty budget format and assessment for Simplified DFF test setup

[FFS]

E.3.1.3 Uncertainty budget format and assessment for IFF test setup

The uncertainty contributions that may impact the overall MU value are listed in Table E.3.1.3-1.

Table E.3.1.3-1: Uncertainty contributions for DL AWGN absolute power or wanted DL signal absolute power

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	gNB emulator uncertainty	B.2.2.17
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Multiple measurement antenna uncertainty	B.2.2.25
14	DUT repositioning	B.2.2.26
Stage 1: Calibration measurement		
15	Mismatch	B.2.2.4
16	Amplifier Uncertainties	B.2.2.8
17	Misalignment of positioning System	B.2.2.13
18	Uncertainty of the Network Analyzer	E.2.2.4
19	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
20	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
21	Phase centre offset of calibration antenna	B.2.2.18
22	Quality of quiet zone for calibration process	B.2.2.19
23	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
24	Influence of the calibration antenna feed cable	B.2.2.21
25	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
26	Systematic error related to beam peak search	B.2.2.28

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz}.
- The uncertainty assessment is applicable for 1AoA test cases- The uncertainty assessment is provided in Table E.3.1.3-2.

Table E.3.1.3-2: Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level	2.9	Normal	2.00	1.45
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
15	Mismatch	0.00	U-shaped	1.41	0.00
16	Amplifier Uncertainties	0.00	Normal	2.00	0.00
17	Misalignment of positioning System	0.00	Normal	2.00	0.00
18	Uncertainty of the Network Analyzer	0.73	Normal	2.00	0.37
19	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
20	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
21	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
22	Quality of quiet zone for calibration process (NOTE 4)	0.4	Actual	1.00	0.4
23	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
24	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
25	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 2)				**Value**
26	Systematic error related to beam peak search				0.5
Total measurement uncertainty					**Value**
DL AWGN absolute power expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					5.19

NOTE 1: The analysis was done only for the case of operating in-band, non-CA.
NOTE 2: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 3: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 4: Value based on procedure defined in Annex D.2 of TR 38.810 [13] for Quiet Zone size less or equal to 30 cm.
NOTE 5: The values in this table have been derived for DL powers above and equal to REFSENS. The values might need to be revisited for power levels below REFSENS

Table E.3.1.3-3: Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level	2.9	Normal	2.00	1.45
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.35	Rectangular	1.73	0.20
Stage 1: Calibration measurement					
15	Mismatch	0.00	U-shaped	1.41	0.00
16	Amplifier Uncertainties	0.00	Normal	2.00	0.00
17	Misalignment of positioning System	0.00	Normal	2.00	0.00
18	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
19	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
20	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
21	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
22	Quality of quiet zone for calibration process (NOTE 4)	0.4	Actual	1.00	0.4
23	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
24	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
25	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 2)				**Value**
26	Systematic error related to beam peak search				0.7
Total measurement uncertainty					**Value**
DL AWGN absolute power expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					5.58

NOTE 1: The analysis was done only for the case of operating in-band, non-CA.
NOTE 2: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 3: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 4: Value based on procedure defined in Annex D.2 of TR 38.810 [13] for Quiet Zone size less or equal to 30 cm.
NOTE 5: The values in this table have been derived for DL powers above and equal to REFSENS. The values might need to be revisited for power levels below REFSENS

Table E.3.1.3-4: Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power (f=23.45GHz, 32.125GHz, Quiet Zone size ≤ 30 cm) for PC6

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.6	Actual	1.00	0.6
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level	2.9	Normal	2.00	1.45
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
15	Mismatch	0.00	U-shaped	1.41	0.00
16	Amplifier Uncertainties	0.00	Normal	2.00	0.00
17	Misalignment of positioning System	0.00	Normal	2.00	0.00
18	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
19	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
20	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
21	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
22	Quality of quiet zone for calibration process (NOTE 4)	0.4	Actual	1.00	0.4
23	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
24	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
25	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 2)				**Value**
26	Systematic error related to beam peak search				0.7
Total measurement uncertainty					**Value**
DL AWGN absolute power expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					5.56

NOTE 1: The analysis was done only for the case of operating in-band, non-CA.
NOTE 2: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 3: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 4: Value based on procedure defined in Annex D.2 of TR 38.810 [13] for Quiet Zone size less or equal to 30 cm.
NOTE 5: The values in this table have been derived for DL powers above and equal to REFSENS. The values might need to be revisited for power levels below REFSENS

E.3.1.4 Uncertainty budget format and assessment for Enhanced IFF test setup

The uncertainty contributions that may impact the overall MU value are listed in Table E.3.1.4-1.

Table E.3.1.4-1: Uncertainty contributions for DL AWGN absolute power or wanted DL signal absolute power

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1 to 14	See 1-14 of Table E.3.1.3-1	N/A
Stage 1: Calibration measurement		
15 to 25	See 15-25 of Table E.3.1.3-1	N/A
Systematic uncertainties		
26	See 26 of Table E.3.1.3-1	N/A

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz}.
- The uncertainty assessment is applicable for 1AoA and 2AoA test cases
- The uncertainty assessment is provided in Table E.3.1.4-2.

Table E.3.1.4-2: Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.7	Actual	1.00	0.7
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level	2.9	Normal	2.00	1.45
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer	0.73	Normal	2.00	0.37
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 4)	0.4	Actual	1.00	0.4
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
26	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 2)				**Value**
28	Systematic error related to beam peak search				0.5
Total measurement uncertainty					**Value**
DL AWGN absolute power expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					5.25

NOTE 1: The analysis was done only for the case of operating in-band, non-CA.
NOTE 2: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 3: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 4: Value based on procedure defined in Annex M of TR 38.521-2 [7] for Quiet Zone size less or equal to 30 cm.
NOTE 5: The values in this table have been derived for DL powers above and equal to REFSENS. The values might need to be revisited for power levels below REFSENS

Table E.3.1.4-3: Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC1

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.7	Actual	1.00	0.7
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level	2.9	Normal	2.00	1.45
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.35	Rectangular	1.73	0.20
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 4)	0.4	Actual	1.00	0.4
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
26	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 2)				**Value**
28	Systematic error related to beam peak search				0.7
Total measurement uncertainty					**Value**
DL AWGN absolute power expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					5.63

NOTE 1: The analysis was done only for the case of operating in-band, non-CA.
NOTE 2: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 3: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 4: Value based on procedure defined in Annex M of TR 38.521-2 [7] for Quiet Zone size less or equal to 30 cm.
NOTE 5: The values in this table have been derived for DL powers above and equal to REFSENS. The values might need to be revisited for power levels below REFSENS

Table E.3.1.4-4: Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power (f=23.45GHz, 32.125GHz, Quiet Zone size ≤ 30 cm) for PC6

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.02	Normal	2.00	0.01
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.7	Actual	1.00	0.7
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level	2.9	Normal	2.00	1.45
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
14	DUT repositioning	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
17	Mismatch	0.00	U-shaped	1.41	0.00
18	Amplifier Uncertainties	0.00	Normal	2.00	0.00
19	Misalignment of positioning System	0.00	Normal	2.00	0.00
20	Uncertainty of the Network Analyzer	1.50	Normal	2.00	0.75
21	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
22	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
23	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
24	Quality of quiet zone for calibration process (NOTE 4)	0.4	Actual	1.00	0.4
25	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
26	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
27	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 2)				**Value**
28	Systematic error related to beam peak search				0.7
Total measurement uncertainty					**Value**
DL AWGN absolute power expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					5.62

NOTE 1: The analysis was done only for the case of operating in-band, non-CA.
NOTE 2: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 3: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 4: Value based on procedure defined in Annex M of TR 38.521-2 [7] for Quiet Zone size less or equal to 30 cm.
NOTE 5: The values in this table have been derived for DL powers above and equal to REFSENS. The values might need to be revisited for power levels below REFSENS

E.3.1.5 Uncertainty budget format and assessment for IFF+DFF Hybrid test setup

For DFF probe, Uncertainty shall be evaluated using the Uncertainty budget format as specified in E.3.1.1.

For IFF probe, Uncertainty shall be evaluated using the Uncertainty budget format as specified in E.3.1.3.

The overall uncertainty of the IFF+DFF Hybrid test set up shall be calculated with the max(Total DFF probe MU, Total IFF probe MU).

E.3.1A Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power for 3AoA and 2AoA

Table E.3.1A-1 summarizes the MU threshold for DL AWGN absolute power for 3AoA and 2AoA multi-Rx RRM FR2 test cases. The origin MU values for different test setups with varies parameters can be found in following subclauses.

Table E.3.1A-1: MU threshold for DL AWGN absolute power for RRM FR2

Power Class	Frequency	MBW	Power	Threshold MU value (NOTE 1)
PC3	23.45GHz <= f <= 32.125GHz	BW <= 400MHz	As configured in the test case	[5.73] dB
	32.125GHz < f <= 40.8GHz			[5.73] dB
	40.8GHz < f <= 44.3GHz			TBD dB
NOTE 1: Total Expanded MU for IFF for Quiet Zone size ≤ 30cm in Table E.3.1A.4-2 for PC3 UEs.				

The types of test setup are defined in clause 7.1.3.2 of TS 38.508-1 [18]

E.3.1A.1 Uncertainty budget format and assessment for DFF test setup

The uncertainty contributions that may impact the overall MU value are listed in Table E.3.1A.1-1.

Table E.3.1A.1-1: Uncertainty contributions for DL AWGN absolute power or wanted DL signal absolute power

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of Quiet Zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing wave between the DUT and measurement antenna	B.2.1.5
6	gNB emulator uncertainty	B.2.1.17
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Multiple measurement antenna uncertainty	B.2.1.25
14	DUT repositioning	B.2.1.26
15	Influence of spherical coverage grid	B.2.1.29
Stage 1: Calibration measurement		
16	Mismatch	B.2.1.4
17	Amplifier Uncertainties	B.2.1.8
18	Misalignment of positioning System	B.2.1.13
19	Uncertainty of the Network Analyzer	E.2.1.4
20	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
22	Phase centre offset of calibration antenna	B.2.1.18
23	Quality of quiet zone for calibration process	B.2.1.19
24	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
25	Influence of the calibration antenna feed cable	B.2.1.21
26	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
27	Systematic error related to EIS spherical coverage	B.2.1.30

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ [30 cm], f = {23.45GHz, 32.125GHz, 40.8GHz}.
- The uncertainty assessment is applicable for 2AoA and 3AoA multi-Rx RRM test cases
- The uncertainty assessment is provided in Table E.3.1A.1-2.

Table E.3.1A.1-2: Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm)

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment		Normal	2.00	
2	Measure distance uncertainty		Rectangular	1.73	
3	Quality of Quiet Zone (NOTE 4)		Actual	1.00	
4	Mismatch		Actual	1.00	
5	Standing wave between the DUT and measurement antenna		U-shaped	1.41	
6	gNB uncertainty on absolute level		Normal	2.00	
7	Phase curvature		U-shaped	1.41	
8	Amplifier uncertainties		Normal	2.00	
9	Random uncertainty		Normal	2.00	
10	Influence of the XPD		U-shaped	1.41	
11	Insertion Loss Variation		Rectangular	1.73	
12	RF leakage (from measurement antenna to the receiver/transmitter)		Actual	1.00	
13	Multiple measurement antenna uncertainty (NOTE 3)		Actual	1.00	
14	DUT repositioning		Rectangular	1.73	
15	Influence of spherical coverage grid		Actual	1	
Stage 1: Calibration measurement					
16	Mismatch		U-shaped	1.41	
17	Amplifier Uncertainties		Normal	2.00	
18	Misalignment of positioning System		Normal	2.00	
19	Uncertainty of the Network Analyzer		Normal	2.00	
20	Uncertainty of the absolute gain of the calibration antenna		Normal	2.00	
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna		Rectangular	1.73	
22	Phase centre offset of calibration antenna		Rectangular	1.73	
23	Quality of quiet zone for calibration process (NOTE 4)		Actual	1.00	
24	Standing wave between reference calibration antenna and measurement antenna		U-shaped	1.41	
25	Influence of the calibration antenna feed cable		Normal	2.00	
26	Insertion Loss Variation		Rectangular	1.73	
	Systematic uncertainties (NOTE 2)				**Value**
27	Systematic error related to EIS spherical coverage				
	Total measurement uncertainty				**Value**
DL AWGN absolute power or wanted DL signal absolute power expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					

NOTE 1: The analysis was done only for the case of operating in-band, non-CA.
NOTE 2: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 3: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 4: Value based on procedure defined in Annex D.2 of TR 38.810 [13] for Quiet Zone size less or equal to 30 cm.
NOTE 5: The values in this table have been derived for DL powers above and equal to REFSENS. The values might need to be revisited for power levels below REFSENS

E.3.1A.2 Uncertainty budget format and assessment for Simplified DFF test setup

[FFS]

E.3.1A.3 Uncertainty budget format and assessment for IFF test setup

IFF test setup is not applicable to 2AoA and 3AoA RRM multi-Rx test cases due to the lack of multiple AoAs.

E.3.1A.4 Uncertainty budget format and assessment for Enhanced IFF test setup

Editor's note: The MU for Multi-Rx is working assumption. Values will be confirmed once devices supporting Multi-Rx test cases are commercially available.

The uncertainty contributions that may impact the overall MU value are listed in Table E.3.1A.4-1.

Table E.3.1A.4-1: Uncertainty contributions for DL AWGN absolute power or wanted DL signal absolute power

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	gNB emulator uncertainty	B.2.2.17
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Multiple measurement antenna uncertainty	B.2.2.25
14	DUT repositioning	B.2.2.26
15	Influence of spherical coverage grid	B.2.2.29
Stage 1: Calibration measurement		
16	Mismatch	B.2.2.4
17	Amplifier Uncertainties	B.2.2.8
18	Misalignment of positioning System	B.2.2.13
19	Uncertainty of the Network Analyzer	E.2.2.4
20	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
22	Phase centre offset of calibration antenna	B.2.2.18
23	Quality of quiet zone for calibration process	B.2.2.19
24	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
25	Influence of the calibration antenna feed cable	B.2.2.21
26	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
27	Systematic error related to EIS spherical coverage	B.2.2.28

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz}.

- The uncertainty assessment is applicable for 2AoA and 3AoA multi-Rx RRM test cases
- The uncertainty assessment is provided in Table E.3.1A.4-2.

Table E.3.1A.4-2: Uncertainty assessment for DL AWGN absolute power or wanted DL signal absolute power (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 4)	0.7	Actual	1.00	0.7
4	Mismatch	1.7	Actual	1.00	1.7
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	gNB uncertainty on absolute level	3.2	Normal	2.00	1.6
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.1	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Multiple measurement antenna uncertainty (NOTE 3)	0.15	Actual	1.00	0.15
14	DUT repositioning (NOTE 6)	[0.00]	Rectangular	1.73	[0.00]
15	Influence of spherical coverage grid (NOTE 6)	[0.12]	Actual	1.00	[0.12]
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	1.5	Normal	2.00	0.75
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 4)	0.4	Actual	1.00	0.4
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 2)				**Value**
28	Systematic error related to EIS spherical coverage				DL power step size, 0.2
Total measurement uncertainty					**Value**
DL AWGN absolute power expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					[5.73]

NOTE 1: The analysis was done only for the case of operating in-band, non-CA.
NOTE 2: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 3: Applies to the system which has a structure of mechanical feed antenna positioning.
NOTE 4: Value based on procedure defined in Annex M of TS 38.521-2 [7] for Quiet Zone size less or equal to 30 cm.
NOTE 5: The values in this table have been derived for DL powers above and equal to REFSENS. The values might need to be revisited for power levels below REFSENS
NOTE 6: Confirmation of MU value is pending the conclusion of the MU for Clause 7.3K TCs being finalized

E.3.1A.5 Uncertainty budget format and assessment for IFF+DFF Hybrid test setup

For DFF probe, Uncertainty shall be evaluated using the Uncertainty budget format as specified in E.3.1A.1.

For IFF probe, Uncertainty shall be evaluated using the Uncertainty budget format as specified in E.3.1A.4.

The overall uncertainty of the IFF+DFF Hybrid test set up shall be calculated with the max(Total DFF probe MU, Total IFF probe MU).

E.3.2 Uncertainty assessment for DL applied SNR

E.3.3 Uncertainty assessment for DL Fading profile uncertainty

E.3.4 Uncertainty assessment for DL AWGN and signal flatness

E.3.5 Uncertainty assessment for UL absolute power measurement

Editor's Note : Applicability of MU in this section for 2AoA Test Cases needs to be reassessed once 2AoA Test Cases requiring UL power measurement is defined.

Following tables summarize the MU threshold for EIRP UL absolute power measurement in FR2 RRM test cases. The origin MU values for different test setups with varies parameters can be found in following clauses.

Table E.3.5-1: MU threshold for EIRP UL absolute power measurement

TBD

E.3.5.1 Uncertainty budget format and assessment for DFF

Editor's Note : Applicability of MU in this section for 2AoA Test Cases needs to be reassessed once 2AoA Test Cases requiring UL power measurement is defined.

The uncertainty contributions that may impact the overall MU value are listed in Table E.3.5.1-1.

Table E.3.5.1-1: Uncertainty contributions for EIRP UL absolute power measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.1.1
2	Measure distance uncertainty	B.2.1.2
3	Quality of quiet zone	B.2.1.3
4	Mismatch	B.2.1.4
5	Standing Wave Between the DUT and measurement antenna	B.2.1.5
6	Uncertainty of the RF power measurement equipment	B.2.1.6
7	Phase curvature	B.2.1.7
8	Amplifier uncertainties	B.2.1.8
9	Random uncertainty	B.2.1.9
10	Influence of the XPD	B.2.1.10
11	Insertion Loss Variation	B.2.1.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.1.12
13	Influence of beam peak search grid	B.2.1.23
14	Multiple measurement antenna uncertainty	B.2.1.25
15	DUT repositioning	B.2.1.26
Stage 1: Calibration measurement		
16	Mismatch	B.2.1.4
17	Amplifier uncertainties	B.2.1.8
18	Misalignment of positioning System	B.2.1.13
19	Uncertainty of the Network Analyzer	E.2.1.4
20	Uncertainty of the absolute gain of the calibration antenna	B.2.1.15
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.1.16
22	Phase centre offset of calibration antenna	B.2.1.18
23	Quality of quiet zone for calibration process	B.2.1.19
24	Standing wave between reference calibration antenna and measurement antenna	B.2.1.20
25	Influence of the calibration antenna feed cable	B.2.1.21
26	Insertion Loss Variation	B.2.1.11
Systematic uncertainties		
27	Influence of noise	B.2.1.27
28	Systematic error related to beam peak search	B.2.1.28

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz}.
- The uncertainty assessment is applicable for 1AoA and 2AoA test cases
- The uncertainty assessment is provided in Table E.3.5.1-2.

Table E.3.5.1-2: Uncertainty assessment for EIRP measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.15	Rectangular	1.73	0.08
3	Quality of quiet zone (NOTE 1)	1.2	Actual	1.00	1.2
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing Wave Between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2)	2.50	Normal	2.00	1.25
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.06	U-shaped	1.41	0.043
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of beam peak search grid	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty(NOTE 4)	0.15	Actual	1	0.15
15	DUT repositioning	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	0.73	Normal	2.00	0.37
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.47	Rectangular	1.73	0.27
23	Quality of quiet zone for calibration process (NOTE 1)	0.4	Actual	1.00	0.4
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 3)				**Value**
27	Influence of noise				TBD
28	Systematic error related to beam peak search				0.5
Total measurement uncertainty					**Value**
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					TBD

NOTE 1: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 2: The assessment assumes minimum output power level.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Applies to the system which has a structure of mechanical feed antenna positioning.

E.3.5.2 TBD

E.3.5.3 Uncertainty budget format and assessment for IFF

Editor's Note : Applicability of MU in this section for 2AoA Test Cases needs to be reassessed once 2AoA Test Cases requiring UL power measurement is defined.

The uncertainty contributions that may impact the overall MU value are listed in Table E.3.5.3-1.

Table E.3.5.3-1: Uncertainty contributions for EIRP UL absolute power measurement

UID	Description of uncertainty contribution	Details in clause
Stage 2: DUT measurement		
1	Positioning misalignment	B.2.2.1
2	Measure distance uncertainty	B.2.2.2
3	Quality of Quiet Zone	B.2.2.3
4	Mismatch	B.2.2.4
5	Standing wave between the DUT and measurement antenna	B.2.2.5
6	Uncertainty of the RF power measurement equipment	B.2.2.6
7	Phase curvature	B.2.2.7
8	Amplifier uncertainties	B.2.2.8
9	Random uncertainty	B.2.2.9
10	Influence of the XPD	B.2.2.10
11	Insertion Loss Variation	B.2.2.11
12	RF leakage (from measurement antenna to the receiver/transmitter)	B.2.2.12
13	Influence of beam peak search grid	B.2.2.23
14	Multiple measurement antenna uncertainty	B.2.2.25
15	DUT repositioning	B.2.2.26
Stage 1: Calibration measurement		
16	Mismatch	B.2.2.4
17	Amplifier Uncertainties	B.2.2.8
18	Misalignment of positioning System	B.2.2.13
19	Uncertainty of the Network Analyzer	E.2.2.4
20	Uncertainty of the absolute gain of the calibration antenna	B.2.2.15
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	B.2.2.16
22	Phase centre offset of calibration antenna	B.2.2.18
23	Quality of quiet zone for calibration process	B.2.2.19
24	Standing wave between reference calibration antenna and measurement antenna	B.2.2.20
25	Influence of the calibration antenna feed cable	B.2.2.21
26	Insertion Loss Variation	B.2.2.11
Systematic uncertainties		
27	Influence of noise	B.2.2.27
28	Systematic error related to beam peak search	B.2.2.28

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz}.
- The uncertainty assessment is applicable for 1AoA test cases
  - The uncertainty assessment for EIRP is provided in Table E.3.5.3-2 for PC3 UEs

Table E.3.5.3-2: Uncertainty assessment for EIRP UL absolute power measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 1)	0.6	Actual	1.00	0.6
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2)	2.50	Normal	2.00	1.25
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of beam peak search grid	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 4)	0.15	Actual	1	0.15
15	DUT repositioning	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	0.73	Normal	2.00	0.37
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 1)	0.4	Actual	1.00	0.4
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 3)				**Value**
27	Influence of noise (23.45GHz <= f <= 32.125GHz)				TBD
28	Systematic error related to beam peak search				0.5
Total measurement uncertainty					Value
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					TBD

NOTE 1: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 2: The assessment assumes minimum output power level.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Applies to the system which has a structure of mechanical feed antenna positioning.

E.3.5.4 Uncertainty budget format and assessment for Enhanced IFF test setup

Editor's Note : Applicability of MU in this section for 2AoA Test Cases needs to be reassessed once 2AoA Test Cases requiring UL power measurement is defined.

The uncertainty contributions that may impact the overall MU value are listed in Table E.3.5.4-1.

Table E.3.5.4-1: Uncertainty contributions for EIRP UL absolute power measurement

UID	Description of uncertainty contribution	Details in annex
Stage 2: DUT measurement		
1 to 15	See 1-15 of Table E.3.5.3-1	N/A
Stage 1: Calibration measurement		
16 to 26	See 16-26 of Table E.3.5.3-1	N/A
Systematic uncertainties		
27 to 28	See 27-28 of Table E.3.5.3-1	N/A

The uncertainty assessment tables are organized as follows:

- For the purpose of uncertainty assessment, the radiating antenna aperture of the DUT is denoted as D
- The uncertainty assessment has been derived for the case of Quiet Zone size $\leq$ 30 cm, f = {23.45GHz, 32.125GHz, 40.8GHz}.
- The uncertainty assessment is applicable for 1AoA and 2AoA test cases
- The uncertainty assessment is provided in Table E.3.5.4-2.

Table E.3.5.4-2: Uncertainty assessment for EIRP UL absolute power measurement (f=23.45GHz, 32.125GHz, 40.8GHz, Quiet Zone size ≤ 30 cm) for PC3 UEs and normal temperature condition

UID	Uncertainty source	Uncertainty value	Distribution of the probability	Divisor	Standard uncertainty (σ) [dB]
Stage 2: DUT measurement					
1	Positioning misalignment	0.00	Normal	2.00	0.00
2	Measure distance uncertainty	0.00	Rectangular	1.73	0.00
3	Quality of Quiet Zone (NOTE 1)	0.7	Actual	1.00	0.7
4	Mismatch	1.30	Actual	1.00	1.30
5	Standing wave between the DUT and measurement antenna	0.00	U-shaped	1.41	0.00
6	Uncertainty of the RF power measurement equipment (NOTE 2)	2.50	Normal	2.00	1.25
7	Phase curvature	0.00	U-shaped	1.41	0.00
8	Amplifier uncertainties	2.10	Normal	2.00	1.05
9	Random uncertainty	0.50	Normal	2.00	0.25
10	Influence of the XPD	0.01	U-shaped	1.41	0.00
11	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
12	RF leakage (from measurement antenna to the receiver/transmitter)	0.00	Actual	1.00	0.00
13	Influence of beam peak search grid	0.00	Actual	1	0.00
14	Multiple measurement antenna uncertainty (NOTE 4)	0.15	Actual	1	0.15
15	DUT repositioning	0.08	Rectangular	1.73	0.05
Stage 1: Calibration measurement					
16	Mismatch	0.00	U-shaped	1.41	0.00
17	Amplifier Uncertainties	0.00	Normal	2.00	0.00
18	Misalignment of positioning System	0.00	Normal	2.00	0.00
19	Uncertainty of the Network Analyzer	0.73	Normal	2.00	0.37
20	Uncertainty of the absolute gain of the calibration antenna	0.60	Normal	2.00	0.30
21	Positioning and pointing misalignment between the reference antenna and the measurement antenna	0.01	Rectangular	1.73	0.00
22	Phase centre offset of calibration antenna	0.00	Rectangular	1.73	0.00
23	Quality of quiet zone for calibration process (NOTE 1)	0.4	Actual	1.00	0.4
24	Standing wave between reference calibration antenna and measurement antenna	0.00	U-shaped	1.41	0.00
25	Influence of the calibration antenna feed cable	0.14	Normal	2.00	0.07
26	Insertion Loss Variation	0.00	Rectangular	1.73	0.00
	Systematic uncertainties (NOTE 3)				**Value**
27	Influence of noise (23.45GHz <= f <= 32.125GHz)				TBD
28	Systematic error related to beam peak search				0.5
Total measurement uncertainty					Value
EIRP Expanded uncertainty (1.96σ - confidence interval of 95 %) [dB]					TBD

NOTE 1: Value based on procedure defined in clause D.2 of TR 38.810 for Quiet Zone size less or equal to 30 cm.
NOTE 2: The assessment assumes minimum output power level.
NOTE 3: In order to obtain the total measurement uncertainty, systematic uncertainties have to be added to the expanded root sum square of the standard deviations of the Stage 1 and Stage 2 contributors.
NOTE 4: Applies to the system which has a structure of mechanical feed antenna positioning.

E.3.5.5 Uncertainty budget format and assessment for IFF+DFF Hybrid test setup

For DFF probe, Uncertainty shall be evaluated using the Uncertainty budget format as specified in E.3.5.1.

For IFF probe, Uncertainty shall be evaluated using the Uncertainty budget format as specified in E.3.5.3.

The overall uncertainty of the IFF+DFF Hybrid test set up shall be calculated with the max(Total DFF probe MU, Total IFF probe MU).

E.3.6 Uncertainty assessment for UL relative power measurement

E.3.7 Uncertainty assessment for UL signal transmit timing relative to DL

E.3.8 Uncertainty assessment for Relative transmit timing accuracy during UE timing adjustment

Annex F: Applicable MTSU for Different QZ/Device Sizes

The applicability mapping between minimum QZ size, maximum device size and MTSU is outlined in Table F-1. The underlying assumptions for the mapping are as follows:

- The maximum device size ranges/limits follow the currently defined quiet zone sizes, i.e., 20cm, 30cm, 40cm, and 55cm [7], [18]

- The applicable MTSU follows the max device size, e.g., a max device size of 30cm to 40cm yields an MTSU of $MTSU_{40cm}$

- The applicable MTSU is the same regardless of whether a grey-box or black-box approach [7], [18] is selected to simplify the mapping and to prevent different test requirements for the same device depending on whether black or grey box is applied

- A maximum device size exceeding 55cm but with antenna separations of ≤55cm does not have an applicable MTSU given the lack of a larger QZ

- Devices with >55cm maximum device size do not have an applicable MTSU given the lack of a larger QZ

Table F-1: Mapping between minimum QZ size, maximum device size, and applicable MTSU

Minimum QZ required to contain all active antennas within the quiet zone (optional vendor declaration)	Max Device Size	Applicable MTSU	Note
20cm	<20cm	$MTSU_{30cm}$	A system supporting a {20cm, 30cm, 40cm, 55cm} QZ can be used as long as the assessed MU with a {20cm, 30cm, 40cm, 55cm} QoQZ validation is ≤ $MTSU_{30cm}$
20cm	20cm to 30cm	$MTSU_{30cm}$	A system supporting a {20cm, 30cm, 40cm, 55cm} QZ can be used as long as the assessed MU with a {20cm, 30cm, 40cm, 55cm} QoQZ validation is ≤ $MTSU_{30cm}$
20cm	30cm to 40cm	$MTSU_{40cm}$	A system supporting a {20cm, 30cm, 40cm, 55cm} QZ can be used as long as the assessed MU with a {20cm, 30cm, 40cm, 55cm} QoQZ validation is ≤ $MTSU_{40cm}$
20cm	40cm to 55cm	$MTSU_{55cm}$	A system supporting a {20cm, 30cm, 40cm, 55cm} QZ can be used as long as the assessed MU with a {20cm, 30cm, 40cm, 55cm} QoQZ validation is ≤ $MTSU_{55cm}$
20cm	>55cm	Not applicable until larger QZ is defined	Pending larger QZ (exceeding 55cm) definition
30cm	≤30cm	$MTSU_{30cm}$	A system supporting a {30cm, 40cm, 55cm} QZ can be used as long as the assessed MU with a {30cm, 40cm, 55cm} QoQZ validation is ≤ $MTSU_{30cm}$
30cm	30cm to 40cm	$MTSU_{40cm}$	A system supporting a {30cm, 40cm, 55cm} QZ can be used as long as the assessed MU with a {30cm, 40cm, 55cm} QoQZ validation is ≤ $MTSU_{40cm}$
30cm	40cm to 55cm	$MTSU_{55cm}$	A system supporting a {30cm, 40cm, 55cm} QZ can be used as long as the assessed MU with a {30cm, 40cm, 55cm} QoQZ validation is ≤ $MTSU_{55cm}$
30cm	>55cm	Not applicable until larger QZ is defined	Pending larger QZ (exceeding 55cm) definition
40cm	≤40cm	$MTSU_{40cm}$	A system supporting a {40cm, 55cm} QZ can be used as long as the assessed MU with a {40cm, 55cm} QoQZ validation is ≤ $MTSU_{40cm}$
40cm	40cm to 55cm	$MTSU_{55cm}$	A system supporting a {40cm, 55cm} QZ can be used as long as the assessed MU with a {40cm, 55cm} QoQZ validation is ≤ $MTSU_{55cm}$
40cm	>55cm	Not applicable until larger QZ is defined	Pending larger QZ (exceeding 55cm) definition
55cm	40cm to 55cm	$MTSU_{55cm}$	
55cm	>55cm	Not applicable until larger QZ is defined	Pending larger QZ (exceeding 55cm) definition
>55cm	>55cm	Not applicable until larger QZ is defined	Note: QZs exceeding 55cm cannot be declared due to lack of larger QZ definition

Annex G: Acceptable uncertainty of test system for test cases defined in TS 37.571-1 for radiative testing

This Annex is informative only, as the acceptable uncertainties of a test system are defined in Annex C of 37.571-1 [20].

Annex H: Change history

Change history							
Date	**Meeting**	**TDoc**	**CR**	**Rev**	**Cat**	**Subject/Comment**	**New version**
2017-09	RAN5 #76	R5-174706				Initial skeleton	0.0.1
2018-04	RAN5 #2-5G-NR-Adhoc	R5-182093				Implementation of pCRs to TS 38.903 V0.0.1	0.1.0
2018-05	RAN5#79	R5-182670				Editorial update of TR 38.903.	0.2.0
2018-09	RAN5#80	R5-185213				Making Measurement Uncertainty Terms Common between methods in TR 38.90	1.0.0
2018-09	RAN5#80	R5-185214				TP on Measurement Uncertainty Contributions in FR2	1.0.0
2018-09	RAN5#80	R5-185212				Adding MU values for EIRPTRP measurements with Near Field test range (NFTF) at mmWave	1.0.0
2018-09	RAN#81	-	-	-	-	raised to v15.0.0 with editorial changes only	15.0.0
2018-12	RAN#82	R5-187023	0010	-	F	Editorial update of Annex B	15.1.0
2018-12	RAN#82	R5-187024	0011	-	F	Addition of MU contribution for demodulation test cases	15.1.0
2018-12	RAN#82	R5-187025	0012	-	F	Addition of MU contribution for RRM test cases	15.1.0
2018-12	RAN#82	R5-187148	0013	-	F	General clauses updated for TR38.903	15.1.0
2018-12	RAN#82	R5-187848	0008	1	F	FR2 Spurious Emission measurement grids and offset values	15.1.0
2018-12	RAN#82	R5-188060	0019	1	F	Update of MU budget and contributor description to TR 38.903	15.1.0
2018-12	RAN#82	R5-188224	0009	1	F	Update MU budget in TR 38.903	15.1.0
2018-12	RAN#82	R5-188225	0016	1	F	Update of MU budget tables in TR 38.903	15.1.0
2018-12	RAN#82	R5-188226	0017	2	F	Addition of descriptions on new MU contributions	15.1.0
2019-03	RAN#83	R5-192476	0030	1	F	Addition of Test Tolerance analysis for FR1 PRACH Test cases	15.2.0
2019-03	RAN#83	R5-192504	0038	1	F	Addition of TT analysis for Transmit timing accuracy Tests	15.2.0
2019-03	RAN#83	R5-192505	0031	1	F	Addition common text for RRM	15.2.0
2019-03	RAN#83	R5-192534	0039	-	F	Addition of TT Analysis for Timing Advance Adjustment Accuracy 4.4.3.1	15.2.0
2019-03	RAN#83	R5-192671	0033	1	F	Addition of TT analysis for event triggered test cases	15.2.0
2019-03	RAN#83	R5-192679	0036	1	F	Addition of TT analysis for handover with known cell	15.2.0
2019-03	RAN#83	R5-192845	0029	1	F	CR to update TR 38.903	15.2.0
2019-06	RAN#84	R5-193799	0048	-	F	FR1 Test tolerance analysis for intra re-selection 6.1.1.1	15.3.0
2019-06	RAN#84	R5-193800	0049	-	F	FR1 Test tolerance analysis for inter re-selection 6.1.1.2	15.3.0
2019-06	RAN#84	R5-193801	0050	-	F	FR1 Test tolerance analysis for interRAT higher priority re-selection 6.1.2.1	15.3.0
2019-06	RAN#84	R5-193802	0051	-	F	FR1 Test tolerance analysis for interRAT lower priority re-selection 6.1.2.2	15.3.0
2019-06	RAN#84	R5-193803	0052	-	F	FR1 Test tolerance analysis for interRAT known handover 6.3.1.4	15.3.0
2019-06	RAN#84	R5-194027	0057	-	F	CR on spurious emission MU in FR2	15.3.0
2019-06	RAN#84	R5-194123	0058	-	F	Definition of MU terminologies in TR 38.903	15.3.0
2019-06	RAN#84	R5-195014	0054	1	F	FR1 Test tolerance analysis for EN-DC SCell activation 4.5.3.1-4.5.3.3	15.3.0
2019-06	RAN#84	R5-195015	0060	1	F	Test Tolerance analysis for Inter-Freq measurement Test Cases	15.3.0
2019-06	RAN#84	R5-195159	0059	1	F	CR to update TR 38.903 after RAN5#5-5GNR Adhoc	15.3.0
2019-06	RAN#84	R5-195181	0055	1	F	FR1 Test tolerance analysis for EN-DC measurement reporting 4.6.1.1-4.6.1.4	15.3.0
2019-06	RAN#84	-	-	-	-	Administrative release upgrade to match the release of 3GPP TS 38.521-1 which was upgraded at RAN#84 to Rel-16 due to Rel-16 relevant CR(s)	16.0.0
2019-09	RAN#85	R5-195583	0061	-	F	Update FR1 Test tolerance of 4.5.3.1-4.5.3.3 Scell activation	16.1.0
2019-09	RAN#85	R5-195584	0062	-	F	Update FR1 Test tolerance of 6.1.1.1 FR1 cell re-selection	16.1.0
2019-09	RAN#85	R5-195585	0063	-	F	Update FR1 Test tolerance of 6.1.1.2 FR1-FR1 cell re-selection	16.1.0
2019-09	RAN#85	R5-195586	0064	-	F	Update FR1 Test tolerance of 6.1.2.1 inter-RAT cell re-selection to higher priority	16.1.0
2019-09	RAN#85	R5-195587	0065	-	F	Update FR1 Test tolerance of 6.1.2.2 inter-RAT cell re-selection to lower priority	16.1.0
2019-09	RAN#85	R5-195588	0066	-	F	Update FR1 Test tolerance of 6.3.1.4 inter-RAT handover to known cell	16.1.0
2019-09	RAN#85	R5-195589	0067	-	F	Addition FR1 Test tolerance of 6.3.1.5 inter-RAT handover to unknown cell	16.1.0
2019-09	RAN#85	R5-195590	0068	-	F	Addition FR1 Test tolerance of 6.3.2.1.1 intra-freq RRC re-establishment	16.1.0
2019-09	RAN#85	R5-195591	0069	-	F	Addition FR1 Test tolerance of 6.3.2.1.2 inter-freq RRC re-establishment	16.1.0
2019-09	RAN#85	R5-195592	0070	-	F	Addition FR1 Test tolerance of 6.3.2.3.1 NR RRC redirection	16.1.0
2019-09	RAN#85	R5-195593	0071	-	F	Addition FR1 Test tolerance of 6.3.2.3.2 inter-RAT RRC redirection	16.1.0
2019-09	RAN#85	R5-197362	0072	1	F	FR1 Test Tolerance Analysis for SSB-based RLM IS Tests	16.1.0
2019-09	RAN#85	R5-197363	0073	1	F	FR1 Test Tolerance Analysis for SA Tx Timing Accuracy 6.4.1.1	16.1.0
2019-09	RAN#85	R5-197365	0083	1	F	TT_Analysis_ENDC_FR1_RLM_OOS	16.1.0
2019-09	RAN#85	R5-197369	0087	1	F	TT_Analysis_SA_FR1_TAAA	16.1.0
2019-09	RAN#85	R5-197494	0077	1	F	CR on DUT turnover and relations with QoQZ MU	16.1.0
2019-09	RAN#85	R5-197505	0081	1	F	Update of FR2 MUs in TR 38.903	16.1.0

2019-09	RAN#85	R5-197571	0078	1	F	TT Analysis for SS-RSRP FR1 tests	16.1.0
2019-09	RAN#85	R5-197625	0080	1	F	CR on FR2 OFF Power MU	16.1.0
2019-09	RAN#85	R5-197659	0076	2	F	CR on spurious emission MU in FR2	16.1.0
2019-12	RAN#86	R5-198260	0099	-	F	CR to 38.903 to define Reference Methodology for SE	16.2.0
2019-12	RAN#86	R5-198285	0100	-	F	FR1 Test tolerance analysis for interRAT measurement	16.2.0
2019-12	RAN#86	R5-198427	0101	-	F	Correction to uncertainty budget calculation principles	16.2.0
2019-12	RAN#86	R5-199070	0098	1	F	Editorial corrections to FR1 Test Tolerance files	16.2.0
2019-12	RAN#86	R5-199082	0104	2	F	FR1 Test Tolerance : Addition of TT Analysis for 6.3.1.1 NR SA FR1 Intra-Freq Handover	16.2.0
2019-12	RAN#86	R5-199083	0105	2	F	FR1 Test Tolerance : Addition of TT Analysis for 6.3.1.2 NR SA FR1 Intra-Freq Handover	16.2.0
2019-12	RAN#86	R5-199084	0106	2	F	FR1 Test Tolerance : Addition of TT Analysis for 6.3.1.3 NR SA FR1 Inter-Freq Handover	16.2.0
2019-12	RAN#86	R5-199091	0102	1	F	Update on FR2 MUs in 38.903	16.2.0
2019-12	RAN#86	R5-199092	0103	1	F	Update on FR2 Spurious MUs in 38.903	16.2.0
2019-12	RAN#86	R5-199362	0091	1	F	FR1 Test tolerance analysis for interruptions active and non-active	16.2.0
2019-12	RAN#86	R5-199363	0094	1	F	FR1 Test tolerance analysis for CSI-RS based RLM	16.2.0
2020-03	RAN#87	R5-200163	0107	-	F	Add Annex A.2 handling of common Test Tolerance Topics for FR2	16.3.0
2020-03	RAN#87	R5-200329	0112	-	F	CR to 38.903 on XPD Verification	16.3.0
2020-03	RAN#87	R5-200470	0114	-	F	FR1 Test tolerance analysis for interruptions deactivated NR SCC	16.3.0
2020-03	RAN#87	R5-200918	0116	1	F	Update to FR2 TRx Measurement Uncertainties	16.3.0
2020-03	RAN#87	R5-201037	0108	1	F	Test tolerance analysis inter-frequency SS-RSRP and intra-frequency SS-SINR	16.3.0
2020-03	RAN#87	R5-201038	0109	1	F	Test tolerance analysis SS-RSRQ and inter-frequency SS-SINR	16.3.0
2020-03	RAN#87	R5-201042	0110	1	F	Test Tolerance analysis for CSI-RS-Based L1-RSRP measurement test cases	16.3.0
2020-03	RAN#87	R5-201043	0111	1	F	Test Tolerance analysis for SSB-Based L1-RSRP measurement test cases	16.3.0
2020-06	RAN#88	R5-201662	0118	-	F	FR1 Test tolerance analysis for interruptions deactivated E-UTRAN SCC	16.4.0
2020-06	RAN#88	R5-203094	0119	1	F	FR1 Test tolerance analysis for SCell activation	16.4.0
2020-06	RAN#88	R5-202104	0124	-	F	Test tolerance correction for event triggered measurement test cases	16.4.0
2020-06	RAN#88	R5-202105	0125	-	F	Test tolerance correction for CSI-RS-based L1-RSRP measurement test cases	16.4.0
2020-06	RAN#88	R5-202702	0130	1	F	Test Tolerance analysis TC 4.5.4 and 6.5.4 RRC reconfiguration delay	16.4.0
2020-06	RAN#88	R5-202769	0127	1	F	CR to 38.903 to introduce baseline Demod MU tables	16.4.0
2020-06	RAN#88	R5-202915	0117	1	F	MU contributors for RRM FR2 TC 7.7.1.1	16.4.0
2020-06	RAN#88	R5-202916	0126	1	F	CR to 38.903 to introduce PC1 MU Tables	16.4.0
2020-06	RAN#88	R5-202917	0128	1	F	Update to FR2 Measurement Uncertainties	16.4.0
2020-06	RAN#88	R5-202938	0129	1	F	Addition of EIRP to Transmit OFF power MU analysis	16.4.0
2020-09	RAN#89	R5-203231	0131	-	F	TT analysis for RRM TC 8.5.2.1.1.1	16.5.0
2020-09	RAN#89	R5-203232	0132	-	F	TT analysis for RRM TC 8.5.2.2.1	16.5.0
2020-09	RAN#89	R5-203233	0133	-	F	TT analysis for RRM TC 8.5.2.3.1	16.5.0
2020-09	RAN#89	R5-203237	0134	-	F	TT analysis for RRM TC 4.7.4.1.1	16.5.0
2020-09	RAN#89	R5-203238	0135	-	F	TT analysis for RRM TC 4.7.4.1.2	16.5.0
2020-09	RAN#89	R5-203323	0140	-	F	Add Draft Test Tolerance analysis for FR2 Tx Timing Test cases	16.5.0
2020-09	RAN#89	R5-203324	0141	-	F	Add Draft Test Tolerance analysis for FR2 Inter-freq Event-trig Test cases	16.5.0
2020-09	RAN#89	R5-203325	0142	-	F	Add Draft Test Tolerance analysis for FR2 Intra-freq SS-RSRP Test case	16.5.0
2020-09	RAN#89	R5-203825	0149	-	F	Addition of FR1 Test tolerance analysis for 6.3.2.1.3 RRC Re-establishment	16.5.0
2020-09	RAN#89	R5-203826	0150	-	F	Update of grouping of test cases in clause 8	16.5.0
2020-09	RAN#89	R5-204190	0154	-	F	On Standard Deviation Definition in 38.903	16.5.0
2020-09	RAN#89	R5-204788	0138	1	F	Correction to the extreme conditions in TT analysis of 4.7.1.2.1	16.5.0
2020-09	RAN#89	R5-204887	0139	1	F	CR to update the DL AWGN absolute power for RRM test cases	16.5.0
2020-09	RAN#89	R5-204888	0143	1	F	Adjacent Channel Selectivity FR2 MU definition in 38.903	16.5.0
2020-09	RAN#89	R5-204889	0144	1	F	In-band Blocking FR2 MU definition in 38.903	16.5.0
2020-09	RAN#89	R5-204890	0153	1	F	CR to update MU in 38.903	16.5.0
2020-09	RAN#89	R5-204891	0155	1	F	FR2 Minimum output power measurement uncertainty	16.5.0
2020-09	RAN#89	R5-204945	0152	1	F	CR to 38.903 on some of the Transmit OFF power MU parameters	16.5.0
2020-09	RAN#89	R5-204946	0156	1	F	Update of AWGN flatness in TR 38.903	16.5.0
2020-09	RAN#89	R5-204947	0157	1	F	FR2 EIRP OFF power measurement uncertainty	16.5.0
2020-09	RAN#89	R5-205001	0145	1	F	Addition of FR1 Test tolerance analysis for DCI based BWP switch	16.5.0
2020-09	RAN#89	R5-205002	0146	1	F	Addition of FR1 Test tolerance analysis for RRC based BWP switch	16.5.0
2020-09	RAN#89	R5-205003	0147	1	F	Addition of FR1 Test tolerance analysis for SSB based BFR	16.5.0
2020-09	RAN#89	R5-205004	0148	1	F	Addition of FR1 Test tolerance analysis for CSI-RS based BFR	16.5.0
2020-12	RAN#90	R5-205628	0174	-	F	RRM FR2 DL AWGN absolute power MU	16.6.0
2020-12	RAN#90	R5-205704	0176	-	F	Update of demod MU	16.6.0
2020-12	RAN#90	R5-205831	0177	-	F	Editorial correction of clause 5.2	16.6.0

2020-12	RAN#90	R5-205949	0183	-	F	Update of grouping of test cases in clause 8	16.6.0
2020-12	RAN#90	R5-206809	0158	1	F	TT analysis for RRM 6.7.5.1	16.6.0
2020-12	RAN#90	R5-206810	0159	1	F	TT analysis for RRM 6.7.6.1	16.6.0
2020-12	RAN#90	R5-206811	0160	1	F	TT analysis for RRM 6.7.7.1	16.6.0
2020-12	RAN#90	R5-206812	0161	1	F	TT analysis for RRM 4.7.5.1	16.6.0
2020-12	RAN#90	R5-206813	0163	1	F	TT analysis for RRM 8.5.2.1.2	16.6.0
2020-12	RAN#90	R5-206814	0166	1	F	Add Draft Test Tolerance analysis for FR2 PRACH Test cases	16.6.0
2020-12	RAN#90	R5-206815	0178	1	F	Addition of FR1 TT analysis for inter-RAT cell reselection	16.6.0
2020-12	RAN#90	R5-206816	0179	1	F	Addition of FR1 TT analysis for inter-RAT handover	16.6.0
2020-12	RAN#90	R5-206817	0180	1	F	Addition of FR1 TT analysis for inter-RAT SFTD measurement	16.6.0
2020-12	RAN#90	R5-206818	0181	1	F	Addition of FR1 TT analysis for inter-RAT event-triggered reporting	16.6.0
2020-12	RAN#90	R5-206835	0184	1	F	CR to 38.903 on ETC Testing	16.6.0
2020-12	RAN#90	R5-206836	0185	1	F	CR to add DFF MU Tables in 38.903	16.6.0
2020-12	RAN#90	R5-206837	0187	1	F	Update FR2 TRx MU in 38.903	16.6.0
2020-12	RAN#90	R5-206838	0189	1	F	FR2 Time masks updates	16.6.0
2020-12	RAN#90	R5-206845	0164	1	F	TT analysis for RRM 8.5.2.2.2	16.6.0
2020-12	RAN#90	R5-206846	0167	1	F	Update Draft Test Tolerance analysis for FR2 Tx Timing Test cases	16.6.0
2020-12	RAN#90	R5-206847	0169	1	F	Add Draft Test Tolerance analysis FR2 RLM Peak Test cases	16.6.0
2020-12	RAN#90	R5-206848	0170	1	F	Add Draft Test Tolerance analysis for FR2 Intra-freq Event-trig Test cases	16.6.0
2020-12	RAN#90	R5-206849	0171	1	F	Update Draft Test Tolerance analysis for FR2 Inter-freq Event-trig Test cases	16.6.0
2020-12	RAN#90	R5-206850	0172	1	F	Update Draft Test Tolerance analysis for FR2 Intra-freq SS-RSRP Test case	16.6.0
2020-12	RAN#90	R5-206851	0173	1	F	Add Draft Test Tolerance analysis for FR2 Inter-freq SS-RSRP Test case	16.6.0
2020-12	RAN#90	R5-206852	0182	1	F	Update of FR1 TT analysis for 6.1.1.1 intra-freq cell re-selection	16.6.0
2020-12	RAN#90	R5-206911	0165	1	F	TT analysis for RRM 8.5.2.3.2	16.6.0
2021-03	RAN#91	R5-210431	0193	-	F	Test tolerance analysis for 7.4.3.1 and 5.4.3.1	16.7.0
2021-03	RAN#91	R5-210438	0195	-	F	Update TT analyses for FR2 iRAT measurement accuracy test cases	16.7.0
2021-03	RAN#91	R5-210445	0197	-	F	Update SS-RSRQ measurement accuracy TT analyses for SNR uncertainty change	16.7.0
2021-03	RAN#91	R5-210815	0203	-	F	Update Test Tolerance analyses for FR2 Tx Timing Test cases	16.7.0
2021-03	RAN#91	R5-210817	0204	-	F	Update Test Tolerance analyses for FR2 RLM Test cases	16.7.0
2021-03	RAN#91	R5-210818	0205	-	F	Update Test Tolerance analyses for FR2 Event-Trig Test cases	16.7.0
2021-03	RAN#91	R5-210819	0206	-	F	Update Test Tolerance analyses for FR2 SS-RSRP Test cases	16.7.0
2021-03	RAN#91	R5-210820	0207	-	F	Update Test Tolerance analyses for FR1 RLM Test cases	16.7.0
2021-03	RAN#91	R5-210846	0210	-	F	Update of grouping of test cases in clause 8	16.7.0
2021-03	RAN#91	R5-211175	0216	-	F	FR2 Minimum output power measurement uncertainty update	16.7.0
2021-03	RAN#91	R5-211191	0218	-	F	CR to 38.903 on PC1 Measurement Grid MUs	16.7.0
2021-03	RAN#91	R5-211642	0194	1	F	Test tolerance analysis for 4.5.7.1	16.7.0
2021-03	RAN#91	R5-211643	0196	1	F	Update SS-RSRP measurement accuracy TT analyses for SNR uncertainty change	16.7.0
2021-03	RAN#91	R5-211644	0199	1	F	Update RRM MU values for FR2	16.7.0
2021-03	RAN#91	R5-211645	0211	1	F	Update of FR1 TT for SCell activation	16.7.0
2021-03	RAN#91	R5-211646	0212	1	F	Update of FR1 TT for SSB based link recovery	16.7.0
2021-03	RAN#91	R5-211647	0213	1	F	Update of FR1 TT for CSI-RS based link recovery	16.7.0
2021-03	RAN#91	R5-211648	0214	1	F	Update of FR1 TT for RRC re-establishment	16.7.0
2021-03	RAN#91	R5-211649	0219	1	F	Update of Test Tolerance analysis for FR1 event triggered reporting test cases	16.7.0
2021-03	RAN#91	R5-211650	0220	1	F	Update of Test Tolerance analysis for FR1 SSB-based L1-RSRP test cases	16.7.0
2021-03	RAN#91	R5-211651	0221	1	F	Update of Test Tolerance analysis for FR1 CSI-RS based L1-RSRP test cases	16.7.0
2021-03	RAN#91	R5-211652	0224	1	F	Test Tolerance analysis for FR2 event triggered reporting test cases	16.7.0
2021-03	RAN#91	R5-211732	0202	1	F	Editorial correction to several MU factors	16.7.0
2021-03	RAN#91	R5-211892	0198	1	F	Correct 6.3.1.1 TT analysis	16.7.0
2021-03	RAN#91	R5-211930	0191	1	F	Adjacent Channel Selectivity FR2 MU definition in 38.903	16.7.0
2021-03	RAN#91	R5-211931	0192	1	F	In-band Blocking FR2 MU definition in 38.903	16.7.0
2021-03	RAN#91	R5-211932	0208	1	F	Update on FR2 Blocking Test MU	16.7.0
2021-03	RAN#91	R5-211933	0209	1	F	Update MU for FR2 RRM	16.7.0
2021-03	RAN#91	R5-211934	0215	1	F	Update FR2 MU and TT in 38.903	16.7.0
2021-03	RAN#91	R5-211935	0217	1	F	CR to 38.903 on ETC Testing	16.7.0
2021-03	RAN#91	R5-211936	0222	1	F	Update of demod SNR testability	16.7.0
2021-06	RAN#92	R5-212352	0230	-	F	ACS and IBB - FR2 MU definition in 38.903	16.8.0
2021-06	RAN#92	R5-213851	0228	1	F	Update of demod SNR testability	16.8.0
2021-06	RAN#92	R5-213852	0237	1	F	Measurement uncertainties for FR2 Relative and aggregate power tolerance	16.8.0
2021-06	RAN#92	R5-213940	0225	1	F	Update TT analysis for 5.7.1.1	16.8.0
2021-06	RAN#92	R5-213941	0226	1	F	New TT analysis for 5.7.2.1	16.8.0
2021-06	RAN#92	R5-213942	0227	1	F	New TT analysis for 5.7.3.1	16.8.0
2021-06	RAN#92	R5-213943	0235	1	F	Test Tolerance analysis for FR2 event triggered reporting test cases	16.8.0

2021-06	RAN#92	R5-213944	0236	1	F	Test Tolerance analysis for FR2 event triggered reporting test cases	16.8.0
2021-06	RAN#92	R5-213945	0239	1	F	Update of ACLR testability	16.8.0
2021-06	RAN#92	R5-214069	0234	1	F	Measurement Uncertainties updates for FR2 Extreme Testing Conditions	16.8.0
2021-06	RAN#92	R5-214114	0231	1	F	Add Test Tolerance analyses for FR2 RLM Test cases	16.8.0
2021-06	RAN#92	R5-214115	0232	1	F	Update and add Test Tolerance analysis for FR2 Intra-freq Event-trig Test cases	16.8.0
2021-06	RAN#92	R5-214116	0233	1	F	Update Test Tolerance analysis for FR2 Inter-freq SS-RSRP Test case	16.8.0
2021-09	RAN#93	R5-214189	0240	-	F	TT analysis for RRM test cases 5.7.2.2 and 7.7.2.2	16.9.0
2021-09	RAN#93	R5-214190	0241	-	F	TT analysis for RRM test cases 5.7.3.2 and 7.7.3.2	16.9.0
2021-09	RAN#93	R5-214919	0247	-	F	Update TT analysis for RRM test cases 5.7.1.2 and 7.7.1.2	16.9.0
2021-09	RAN#93	R5-215002	0248	-	F	TT analysis for LTE SA TC 8.5.1.1-SFTD accuracy	16.9.0
2021-09	RAN#93	R5-215330	0250	-	F	Correction to MU for spurious emission band UE co-existence	16.9.0
2021-09	RAN#93	R5-215433	0252	-	F	Correction of Test Tolerance analysis for FR2 event triggered reporting in DRX test cases	16.9.0
2021-09	RAN#93	R5-215834	0255	1	F	Introduction of MTSU mapping related to Max Device Size	16.9.0
2021-09	RAN#93	R5-216102	0242	1	F	Update of demod SNR testability	16.9.0
2021-09	RAN#93	R5-216103	0243	1	F	Add Test Tolerance analyses for EN-DC FR2 interruptions at transitions between active and non-active during DRX Test cases	16.9.0
2021-09	RAN#93	R5-216104	0244	1	F	Introducing EIRP UL Absolute Power MU for FR2 RRM	16.9.0
2021-09	RAN#93	R5-216105	0249	1	F	Correction of power control in 38.903	16.9.0
2021-09	RAN#93	R5-216117	0256	1	F	38.903 CR FR2 ETC MU updates for new ETC test cases	16.9.0
2021-09	RAN#93	R5-216362	0251	1	F	Correction of Test Tolerance analysis for FR2 event triggered reporting in non-DRX test cases	16.9.0
2021-09	RAN#93	R5-216363	0253	1	F	Test Tolerance analysis for FR2 SSB-based L1-RSRP measurement for beam reporting test cases	16.9.0
2021-12	RAN#94	R5-218208	0280	-	F	Correct TT analysis for TC 5.7.3.2 and 7.7.3.2	16.10.0
2021-12	RAN#94	R5-218242	0270	1	F	TT analysis for Mob_enh RRM TC 6.3.1.9+6.3.1.10	16.10.0
2021-12	RAN#94	R5-218262	0275	1	F	Test Tolerance analysis for FR2 CSI-RS based L1-RSRP measurement for beam reporting test cases	16.10.0
2021-12	RAN#94	R5-218295	0272	1	F	Addition of test tolerance analysis for test cases of EN-DC FR1 DL Interruptions at switching between two uplink carriers	16.10.0
2021-12	RAN#94	R5-218330	0261	1	F	TT analysis for PS RRM TC 6.1.1.3	16.10.0
2021-12	RAN#94	R5-218331	0262	1	F	TT analysis for PS RRM TC 6.1.1.4	16.10.0
2021-12	RAN#94	R5-218332	0263	1	F	TT analysis for PS RRM TC 6.1.1.5	16.10.0
2021-12	RAN#94	R5-218333	0264	1	F	TT analysis for PS RRM TC 6.1.1.6	16.10.0
2021-12	RAN#94	R5-218334	0273	1	F	Addition of test tolerance analysis for test cases of inter-RAT cell re-selection with relaxed measurement criterion	16.10.0
2021-12	RAN#94	R5-218337	0265	1	F	TT analysis for SRVCC RRM TC 6.3.1.6	16.10.0
2021-12	RAN#94	R5-218338	0266	1	F	TT analysis for SRVCC RRM TC 6.6.5.1	16.10.0
2021-12	RAN#94	R5-218353	0269	1	F	TT analysis for HST RRM TC 6.1.2.5	16.10.0
2021-12	RAN#94	R5-218354	0276	1	F	Test Tolerance analysis for SA FR1 - E-UTRAN event-triggered reporting in DRX for HST	16.10.0
2021-12	RAN#94	R5-218355	0277	1	F	Test Tolerance analysis for E-UTRA - NR FR1 Cell reselection tests for HST	16.10.0
2021-12	RAN#94	R5-218356	0278	1	F	Test Tolerance analysis for SA FR1 - E-UTRAN event-triggered reporting in DRX for HST	16.10.0
2021-12	RAN#94	R5-218394	0257	1	F	TT analysis for Mob_enh RRM TC 6.3.1.7+6.3.1.8	16.10.0
2021-12	RAN#94	R5-218395	0258	1	F	TT analysis for Mob_enh RRM TC 6.3.3.1	16.10.0
2021-12	RAN#94	R5-218396	0259	1	F	TT analysis for Mob_enh RRM TC 6.3.3.2	16.10.0
2021-12	RAN#94	R5-218397	0267	1	F	TT analysis for HST RRM TC 4.6.1.7+6.6.1.7	16.10.0
2021-12	RAN#94	R5-218398	0268	1	F	TT analysis for HST RRM TC 4.6.4.5+6.6.4.5	16.10.0
2021-12	RAN#94	R5-218402	0274	1	F	MU for Tx modulation quality test cases	16.10.0
2021-12	RAN#94	R5-218408	0279	1	F	38.903 Beam correspondence Measurement Uncertainties	16.10.0
2021-12	RAN#94	-	-	-	-	missing attachment file added	16.10.1
2022-03	RAN#95	R5-220281	0285	-	F	Test Tolerance analysis for FR1 CLI-RSSI measurement with non-DRX	16.11.0
2022-03	RAN#95	R5-220718	0289	-	F	TT analysis for FR2 SSB intra-freq measurement with DRX TCs	16.11.0
2022-03	RAN#95	R5-220994	0295	-	F	Addition of test tolerance analysis for 4.6.7.1 and 6.6.8.1 EN-DC and NR SA CSI-RS based L1-SINR measurement	16.11.0
2022-03	RAN#95	R5-220995	0296	-	F	Addition of test tolerance analysis for 4.6.7.2 EN-DC SSB based L1-SINR measurement	16.11.0
2022-03	RAN#95	R5-220996	0297	-	F	Addition of test tolerance analysis for 4.6.7.3 EN-DC CSI-RS based L1-SINR measurement	16.11.0
2022-03	RAN#95	R5-220997	0298	-	F	Addition of test tolerance analysis for 6.6.8.2 NR SA SSB based L1-SINR measurement	16.11.0
2022-03	RAN#95	R5-220998	0299	-	F	Addition of test tolerance analysis for 6.6.8.3 NR SA CSI-RS based L1-SINR measurement	16.11.0
2022-03	RAN#95	R5-221286	0302	-	F	Test Tolerance analysis for E-UTRA - NR FR1 Cell reselection tests for HST	16.11.0
2022-03	RAN#95	R5-221287	0303	-	F	Test Tolerance analysis for inter-frequency RRC re-establishment test case	16.11.0

2022-03	RAN#95	R5-221304	0305	-	F	Correction of clause 3	16.11.0
2022-03	RAN#95	R5-221629	0301	1	F	38.903 Beam correspondence Measurement Uncertainties	16.11.0
2022-03	RAN#95	R5-221644	0304	1	F	Test Tolerance analysis for inter-frequency RRC re-establishment test case	16.11.0
2022-03	RAN#95	R5-221647	0281	1	F	TT analysis for Mob_enh RRM TC 6.3.1.9+6.3.1.10	16.11.0
2022-03	RAN#95	R5-221648	0284	1	F	TT analysis for Mob_enh RRM TC 6.3.1.11+6.3.1.12	16.11.0
2022-03	RAN#95	R5-221649	0290	1	F	TT analysis for Mob_enh RRM TCs 7.3.1.4 and 7.3.1.5	16.11.0
2022-03	RAN#95	R5-221656	0294	1	F	Add Test Tolerance analyses for NR SA FR1 cell re-selection for UE configured with highSpeedMeasFlag-r16 Test cases	16.11.0
2022-03	RAN#95	R5-221743	0286	1	F	FR2 EVM MU definition in 38.903	16.11.0
2022-03	RAN#95	R5-221744	0287	1	F	TT analysis for FR2 SSB based BFD TCs	16.11.0
2022-03	RAN#95	R5-221745	0288	1	F	TT analysis for FR2 SSB intra-freq measurement without DRX TCs	16.11.0
2022-03	RAN#95	R5-221746	0292	1	F	Addition of summary table for MU factors	16.11.0
2022-03	RAN#95	R5-221747	0300	1	F	Update of predicted SNR upper bound for noise free SDR scenarios	16.11.0
2022-03	RAN#95	R5-221814	0291	1	F	TT analysis for Mob_enh RRM TCs 7.3.3.1	16.11.0
2022-03	RAN#95	R5-221840	0293	1	F	Addition of TT analysis for FR2 BFR test cases	16.11.0
2022-06	RAN#96	R5-223608	0306	1	F	Add Test Tolerance analyses for EN-DC FR2 RLM tests for PSCell configured with CSI-RS-based RLM RS in non-DRX	16.12.0
2022-06	RAN#96	R5-223609	0320	1	F	Test Tolerance analysis for FR2 CSI-RS based L1-RSRP measurement for beam reporting test cases	16.12.0
2022-06	RAN#96	R5-223708	0315	1	F	Addition of test tolerance analysis for 5.6.6.3	16.12.0
2022-06	RAN#96	R5-223709	0317	1	F	Addition of test tolerance analysis for 7.6.6.3	16.12.0
2022-06	RAN#96	R5-223865	0308	1	F	TT analysis for RRM test case 5.7.4.1 and 5.7.4.2	16.12.0
2022-06	RAN#96	R5-223866	0318	1	F	Test Tolerances for Intra-frequency SS-RSRP measurement accuracy tests in FR2	16.12.0
2022-06	RAN#96	R5-223883	0313	1	F	Addition of test tolerance analysis for 5.6.6.1 and 7.6.6.1	16.12.0
2022-06	RAN#96	R5-223884	0314	1	F	Addition of test tolerance analysis for 5.6.6.2	16.12.0
2022-06	RAN#96	R5-223885	0316	1	F	Addition of test tolerance analysis for 7.6.6.2	16.12.0
2022-09	RAN#97	R5-223964	0322	-	F	TT analysis for 5.7.1.3 and 7.7.1.3	16.13.0
2022-09	RAN#97	R5-223975	0324	-	F	TT analysis for 4.3.2.2.3	16.13.0
2022-09	RAN#97	R5-224412	0338	-	F	Introduction of NR positioning test cases information	16.13.0
2022-09	RAN#97	R5-224521	0341	-	F	TT analysis for NR SL RRM TC 9.1.1.1 - GNSS	16.13.0
2022-09	RAN#97	R5-224522	0342	-	F	TT analysis for NR SL RRM TC 9.1.1.2 - SyncRef UE	16.13.0
2022-09	RAN#97	R5-224523	0343	-	F	TT analysis for NR SL RRM TC 9.1.1.3 - gNB	16.13.0
2022-09	RAN#97	R5-224524	0344	-	F	TT analysis for NR SL RRM TC 9.1.2.1 - S-SSB Tx gNB	16.13.0
2022-09	RAN#97	R5-224525	0345	-	F	TT analysis for NR SL RRM TC 9.1.2.2 - S-SSB Tx SyncRef UE	16.13.0
2022-09	RAN#97	R5-224526	0346	-	F	TT analysis for NR SL RRM TC 9.1.3.1 - GNSS highest priority	16.13.0
2022-09	RAN#97	R5-224527	0347	-	F	TT analysis for NR SL RRM TC 9.1.3.2 - Cell highest priority	16.13.0
2022-09	RAN#97	R5-224528	0348	-	F	TT analysis for NR SL RRM TC 9.1.4.1 - resource selection	16.13.0
2022-09	RAN#97	R5-224529	0349	-	F	TT analysis for NR SL RRM TC 9.1.4.2 - resource pre-emption	16.13.0
2022-09	RAN#97	R5-224531	0351	-	F	TT analysis for NR SL RRM TC 9.1.5.x - CBR	16.13.0
2022-09	RAN#97	R5-224532	0352	-	F	TT analysis for NR SL RRM TC 9.1.6.1 - WAN interruption	16.13.0
2022-09	RAN#97	R5-224777	0365	-	F	Addition of TT information for 6.5.5.5 and 6.5.5.6	16.13.0
2022-09	RAN#97	R5-225137	0367	-	F	Test Tolerances for Intra-frequency SS-RSRP measurement accuracy tests in FR2	16.13.0
2022-09	RAN#97	R5-225612	0370	1	F	Test Tolerances for DL Interruptions at switching between two uplink carriers test cases	16.13.0
2022-09	RAN#97	R5-225616	0326	1	F	TT analysis for positioning test case 15.2.1 and 15.2.2	16.13.0
2022-09	RAN#97	R5-225618	0321	1	F	Add Test Tolerance analyses for EN-DC FR2 RLM tests for PSCell configured with CSI-RS-based RLM RS in DRX	16.13.0
2022-09	RAN#97	R5-225625	0329	1	F	Addition of test tolerance analysis for 4.7.7.1.2 and 6.7.9.1.2 FR1 L1-SINR relative measurement accuracy	16.13.0
2022-09	RAN#97	R5-225626	0333	1	F	Addition of test tolerance analysis for 7.7.6.2 NR FR2 L1-SINR measurement accuracy test	16.13.0
2022-09	RAN#97	R5-225627	0334	1	F	Addition of test tolerance analysis for 7.7.6.3 NR FR2 L1-SINR measurement accuracy test	16.13.0
2022-09	RAN#97	R5-225636	0366	1	F	TT analysis update for FR2 RLM test cases 5.5.1.x and 7.5.1.x	16.13.0
2022-09	RAN#97	R5-225637	0368	1	F	Test Tolerances for SSB based L1-RSRP measurement accuracy tests in FR2	16.13.0
2022-09	RAN#97	R5-225638	0369	1	F	Test Tolerances for FR2 CSI-RS based L1-RSRPSS-RSRP measurement accuracy tests in FR2	16.13.0
2022-09	RAN#97	R5-225663	0327	1	F	Measurement uncertainties for test case 6.2.4_1 Configured transmitted power with Power Boost	16.13.0
2022-09	RAN#97	R5-225671	0335	1	F	PC1 MU - definition for MOP in 38.903	16.13.0
2022-09	RAN#97	R5-225672	0336	1	F	PC1 MU - definition for REFSENS in 38.903	16.13.0
2022-09	RAN#97	R5-225673	0337	1	F	PC1 MU - General Update in 38.903 section B.2.2	16.13.0
2022-09	RAN#97	R5-225674	0359	1	F	Definition of PC1 MU	16.13.0
2022-09	RAN#97	R5-225675	0360	1	F	Update FR2 TRx MU in 38.903	16.13.0
2022-09	RAN#97	R5-225694	0328	1	F	Addition of test tolerance analysis for 4.7.7.1.1 and 6.7.9.1.1 EN-DC FR1 L1-SINR absolute accuracy tests	16.13.0
2022-09	RAN#97	R5-225695	0330	1	F	Addition of test tolerance analysis for 4.7.7.2 and 6.7.9.2 FR1 L1-SINR absolute measurement accuracy	16.13.0

2022-09	RAN#97	R5-225696	0331	1	F	Addition of test tolerance analysis for 4.7.7.3.1 and 6.7.9.3.1 FR1 L1-SINR absolute measurement accuracy	16.13.0
2022-09	RAN#97	R5-225697	0332	1	F	Addition of test tolerance analysis for 4.7.7.3.2 and 6.7.9.3.2 EN-DC FR1 L1-SINR absolute measurement accuracy	16.13.0
2022-09	RAN#97	R5-225854	0350	1	F	TT analysis for NR SL RRM TC 9.1.4.3 - resource re-evaluation	16.13.0
2022-09	RAN#97	R5-225860	0353	1	F	TT analysis for NR PS RRM TC 7.1.1.3 - intra-freq reselection low mobility	16.13.0
2022-09	RAN#97	R5-225861	0354	1	F	TT analysis for NR PS RRM TC 7.1.1.4 - intra-freq reselection not-at-cell-edge	16.13.0
2022-09	RAN#97	R5-225862	0355	1	F	TT analysis for NR PS RRM TC 7.1.1.5 - inter-freq reselection low mobility	16.13.0
2022-09	RAN#97	R5-225863	0356	1	F	TT analysis for NR PS RRM TC 7.1.1.6 - inter-freq reselection not-at-cell-edge	16.13.0
2022-09	RAN#97	R5-225867	0357	1	F	TT analysis for NR SA FR2 RRM TC 7.1.1.1 - intra-freq reselection	16.13.0
2022-09	RAN#97	R5-225868	0358	1	F	TT analysis for NR SA FR2 RRM TC 7.1.1.2 - inter-freq reselection	16.13.0
2022-09	RAN#97	R5-225873	0361	1	F	Addition of TT analysis for eMIMO L1-SINR test case 5.7.6.1 and 7.7.6.1	16.13.0
2022-09	RAN#97	R5-225874	0362	1	F	Addition of TT analysis for eMIMO L1-SINR test case 5.7.6.2	16.13.0
2022-09	RAN#97	R5-225875	0363	1	F	Addition of TT analysis for eMIMO L1-SINR test case 5.7.6.3	16.13.0
2022-09	RAN#97	R5-225879	0323	1	F	TT analysis for TS 37.571-1 TC 14.2.1	16.13.0
2022-09	RAN#97	R5-225880	0325	1	F	TT analysis for TS 37.571-1 TC 14.3.1	16.13.0
2022-12	RAN#98	R5-225939	0372	-	F	TT analysis for positioning test case 15.2.3	16.14.0
2022-12	RAN#98	R5-225940	0373	-	F	TT analysis for positioning test case 15.2.4	16.14.0
2022-12	RAN#98	R5-225941	0374	-	F	TT analysis for positioning test case 15.3.1	16.14.0
2022-12	RAN#98	R5-225942	0375	-	F	TT analysis for positioning test case 15.3.2	16.14.0
2022-12	RAN#98	R5-226101	0378	-	F	PC1 MU - definition for Frequency error in 38.903	16.14.0
2022-12	RAN#98	R5-226213	0408	-	F	TT analysis for Interruption TCs	16.14.0
2022-12	RAN#98	R5-226214	0409	-	F	TT analysis for SCell activation TCs	16.14.0
2022-12	RAN#98	R5-226375	0410	-	F	Test tolerance analysis for FR2 RRC-based DL active BWP switch	16.14.0
2022-12	RAN#98	R5-226534	0438	-	F	Update of MU for PC1 Demod	16.14.0
2022-12	RAN#98	R5-226642	0439	-	F	Capturing simulation results to derive the maximum testable SNR	16.14.0
2022-12	RAN#98	R5-227646	0440	2	F	PC1 update to Demod SNR range calculator	16.14.0
2022-12	RAN#98	R5-227821	0437	1	F	Update of MU for PC1 RRM	16.14.0
2022-12	RAN#98	R5-227822	0447	1	F	40cm QoQZ and XPD MU in 38.903	16.14.0
2022-12	RAN#98	R5-227841	0448	1	F	Test Tolerances for FR2 SRS-RSRP measurement in non-DRX	16.14.0
2022-12	RAN#98	R5-227842	0449	1	F	Test Tolerances for EN-DC FR2 SRS-RSRP measurement accuracy	16.14.0
2022-12	RAN#98	R5-227869	0441	1	F	Addition of TT analysis for 7.5.2.1	16.14.0
2022-12	RAN#98	R5-227967	0376	1	F	PC1 MU - definition for ACLR in 38.903	16.14.0
2022-12	RAN#98	R5-227968	0377	1	F	PC1 MU - definition for ACS in 38.903	16.14.0
2022-12	RAN#98	R5-227969	0380	1	F	PC1 MU - definition for MOP in 38.903	16.14.0
2022-12	RAN#98	R5-227970	0382	1	F	PC1 MU - definition for OFF power in 38.903	16.14.0
2022-12	RAN#98	R5-227971	0383	1	F	PC1 MU - definition for REFSENS in 38.903	16.14.0
2022-12	RAN#98	R5-227972	0384	1	F	PC1 MU - definition for SEM in 38.903	16.14.0
2022-12	RAN#98	R5-227973	0385	1	F	PC1 MU - General Update in 38.903 section B.2.2	16.14.0
2022-12	RAN#98	R5-227974	0443	1	F	Test Tolerances for Idle mode CA/DC measurement FR1 test case	16.14.0
2022-12	RAN#98	R5-227989	0442	1	F	Definition of PC1 MU	16.14.0
2022-12	RAN#98	R5-228009	0433	1	F	Update TT analysis for TC 14.2.1	16.14.0
2022-12	RAN#98	R5-228010	0434	1	F	Update TT analysis for TC 14.3.1	16.14.0
2022-12	RAN#98	R5-228011	0435	1	F	New TT analysis for TC 14.2.2	16.14.0
2022-12	RAN#98	R5-228012	0436	1	F	New TT analysis for TC 14.3.2	16.14.0
2022-12	RAN#98	R5-226428	0420	-	F	TT analysis for RedCap RRM TC 16.4.1.1 and 16.4.1.2 - Tx timing	17.0.0
2022-12	RAN#98	R5-226434	0426	-	F	TT analysis for RedCap RRM TC 17.3.2.1.1 - intra reestablish	17.0.0
2022-12	RAN#98	R5-226435	0427	-	F	TT analysis for RedCap RRM TC 17.3.2.1.2 - inter reestablish	17.0.0
2022-12	RAN#98	R5-226436	0428	-	F	TT analysis for RedCap RRM TC 17.5.1.1 - OOS non-DRX	17.0.0
2022-12	RAN#98	R5-226437	0429	-	F	TT analysis for RedCap RRM TC 17.5.1.2 - IS non-DRX	17.0.0
2022-12	RAN#98	R5-226438	0430	-	F	TT analysis for RedCap RRM TC 17.5.1.4 - IS DRX	17.0.0
2022-12	RAN#98	R5-226439	0431	-	F	TT analysis for RedCap RRM TC 17.6.1.1 - no gap non-DRX	17.0.0
2022-12	RAN#98	R5-227846	0411	1	F	TT analysis for RedCap RRM TC 16.3.1.8 - inter-RAT HO 2 Rx	17.0.0
2022-12	RAN#98	R5-227847	0412	1	F	TT analysis for RedCap RRM TC 16.3.1.10 - inter-RAT blind HO 2 Rx	17.0.0
2022-12	RAN#98	R5-227848	0413	1	F	TT analysis for RedCap RRM TC 16.3.2.1.2 - intra reestablish 2 Rx	17.0.0
2022-12	RAN#98	R5-227849	0414	1	F	TT analysis for RedCap RRM TC 16.3.2.1.4 - inter reestablish 2 Rx	17.0.0
2022-12	RAN#98	R5-227850	0415	1	F	TT analysis for RedCap RRM TC 16.3.2.1.6 - no timing reestablish 2 Rx	17.0.0
2022-12	RAN#98	R5-227851	0416	1	F	TT analysis for RedCap RRM TC 16.3.2.2.2 and 16.3.2.2.4 - 4 step RACH 2 Rx	17.0.0
2022-12	RAN#98	R5-227852	0417	1	F	TT analysis for RedCap RRM TC 16.3.2.2.6 and 16.3.2.2.8 - 2 step RACH 2 Rx	17.0.0
2022-12	RAN#98	R5-227853	0418	1	F	TT analysis for RedCap RRM TC 16.3.2.3.2 and 18.2.2.1 - NR redirection 2 Rx	17.0.0
2022-12	RAN#98	R5-227854	0419	1	F	TT analysis for RedCap RRM TC 16.3.2.3.4 - LTE redirection 2 Rx	17.0.0
2022-12	RAN#98	R5-227855	0421	1	F	TT analysis for RedCap RRM TC 16.5.1.2 - OOS SSB	17.0.0

2022-12	RAN#98	R5-227856	0422	1	F	TT analysis for RedCap RRM TC 16.5.1.4 and 16.5.1.8 - IS SSB	17.0.0
2022-12	RAN#98	R5-227857	0423	1	F	TT analysis for RedCap RRM TC 16.5.2.2 - SSB BFR	17.0.0
2022-12	RAN#98	R5-227858	0424	1	F	TT analysis for RedCap RRM TC 16.6.1.x - intra-freq	17.0.0
2022-12	RAN#98	R5-227859	0425	1	F	TT analysis for RedCap RRM TC 16.6.4.x - SSB L1-RSRP	17.0.0
2022-12	RAN#98	R5-227860	0432	1	F	TT analysis for RedCap RRM TC 18.2.1.1 - L2N HO	17.0.0
2023-03	RAN#99	R5-230030	0450	-	F	TT analysis for positioning test case 14.2.3	17.1.0
2023-03	RAN#99	R5-230031	0451	-	F	TT analysis for positioning test case 14.2.4	17.1.0
2023-03	RAN#99	R5-230033	0453	-	F	TT analysis for positioning test case 14.3.4	17.1.0
2023-03	RAN#99	R5-230034	0454	-	F	TT analysis for positioning test case 16.2.3	17.1.0
2023-03	RAN#99	R5-230180	0465	-	F	PC5 MU - definition for REFSENS test case in 38.903	17.1.0
2023-03	RAN#99	R5-230430	0469	-	F	Addition of test tolerance analysis for 5.5.3.1 EN-DC FR2 SCell activation and deactivation intra-band in non-DRX	17.1.0
2023-03	RAN#99	R5-230434	0471	-	F	Addition of test tolerance analysis for 8.4.2.6 and 8.4.2.7 and 8.4.2.8 NR Inter-RAT event triggered reporting tests for FR2 test cases	17.1.0
2023-03	RAN#99	R5-230517	0473	-	F	TT analysis for RedCap RRM TC 16.3.1.4 - intra unknown HO 2Rx	17.1.0
2023-03	RAN#99	R5-230518	0474	-	F	TT analysis for RedCap RRM TC 16.3.1.6 - inter unknown HO 2Rx	17.1.0
2023-03	RAN#99	R5-230519	0475	-	F	TT analysis for RedCap RRM TC 16.4.3.1 and 16.4.3.2 - TA	17.1.0
2023-03	RAN#99	R5-230520	0476	-	F	TT analysis for RedCap RRM TC 16.5.1.10 and 16.5.1.14 - OOS 2RX	17.1.0
2023-03	RAN#99	R5-230521	0477	-	F	TT analysis for RedCap RRM TC 16.5.1.12 and 16.5.1.16 - IS 2RX	17.1.0
2023-03	RAN#99	R5-230522	0478	-	F	TT analysis for RedCap RRM TC 16.5.2.6 and 16.5.2.8 - BFR 2RX	17.1.0
2023-03	RAN#99	R5-230523	0479	-	F	TT analysis for RedCap RRM TC 16.6.1.x - intra meas 2Rx	17.1.0
2023-03	RAN#99	R5-230524	0480	-	F	TT analysis for RedCap RRM TC 16.6.4.6 and 16.6.4.8 - CSI-RS L1-RSRP 2Rx	17.1.0
2023-03	RAN#99	R5-230525	0481	-	F	TT analysis for RedCap RRM TC 18.3.1.x - FR1 NR meas	17.1.0
2023-03	RAN#99	R5-230531	0482	-	F	TT analysis for RRM enhancement TC 6.5.8.1 - CBW change	17.1.0
2023-03	RAN#99	R5-230925	0491	-	F	New TT analysis for TC 4A.1.1.1	17.1.0
2023-03	RAN#99	R5-230926	0492	-	F	New TT analysis for TC 4A.2.1.1	17.1.0
2023-03	RAN#99	R5-231138	0494	-	F	TT analysis for RedCap RRM TC 16.1.1.4	17.1.0
2023-03	RAN#99	R5-231139	0495	-	F	TT analysis for RedCap RRM TC 16.1.1.6	17.1.0
2023-03	RAN#99	R5-231140	0496	-	F	TT analysis for RedCap RRM TC 16.1.1.8	17.1.0
2023-03	RAN#99	R5-231141	0497	-	F	TT analysis for RedCap RRM TC 16.1.2.2	17.1.0
2023-03	RAN#99	R5-231142	0498	-	F	TT analysis for RedCap RRM TC 16.1.2.4 and 16.1.2.6	17.1.0
2023-03	RAN#99	R5-231147	0499	-	F	TT analysis for Idle mode Inter-RAT CA/DC measurement test case 6.6.15.1	17.1.0
2023-03	RAN#99	R5-231148	0500	-	F	TT analysis for E-UTRA - NR Early Measurement Reporting for NR in FR1 test case 8.2.2.1	17.1.0
2023-03	RAN#99	R5-231345	0502	-	F	Max testable SNR table updates	17.1.0
2023-03	RAN#99	R5-231745	0501	1	F	TT analysis for E-UTRA - NR Early Measurement Reporting for NR in FR2 test case 8.2.2.2	17.1.0
2023-03	RAN#99	R5-231756	0452	1	F	TT analysis for positioning test case 14.3.3	17.1.0
2023-03	RAN#99	R5-231757	0455	1	F	TT analysis for positioning test case 16.2.4	17.1.0
2023-03	RAN#99	R5-231758	0490	1	F	Update TT analysis for TC 14.3.2	17.1.0
2023-03	RAN#99	R5-231762	0472	1	F	TT analysis for RedCap RRM TC 16.3.1.2 - intra known HO 2Rx	17.1.0
2023-03	RAN#99	R5-231763	0493	1	F	TT analysis for RedCap RRM TC 16.1.1.2	17.1.0
2023-03	RAN#99	R5-231765	0487	1	F	Addition of TT analysis for 7.3.1.2	17.1.0
2023-03	RAN#99	R5-231766	0488	1	F	Addition of TT analysis for 7.3.1.3 and 7.3.2.3.1	17.1.0
2023-03	RAN#99	R5-231784	0457	1	F	PC1 MU - definition for ACLR test case in 38.903	17.1.0
2023-03	RAN#99	R5-231785	0459	1	F	PC1 MU - definition for MOP test cases in 38.903	17.1.0
2023-03	RAN#99	R5-231786	0461	1	F	PC1 MU - definition for REFSENS test case in 38.903	17.1.0
2023-03	RAN#99	R5-231787	0463	1	F	PC1 MU - definition for Tx spurious test cases in 38.903	17.1.0
2023-03	RAN#99	R5-231788	0466	1	F	Definition of PC1 MU	17.1.0
2023-03	RAN#99	R5-231844	0460	1	F	PC1 MU - definition for MPR test case in 38.903	17.1.0
2023-03	RAN#99	R5-231849	0458	1	F	PC1 MU - definition for Min power test case in 38.903	17.1.0
2023-03	RAN#99	R5-231850	0464	1	F	PC1 MU - General Update in 38.903 test case section B.2.2	17.1.0
2023-03	RAN#99	R5-231899	0470	1	F	Addition of test tolerance analysis for 8.4.2.5 NR Inter-RAT event triggered reporting tests for FR2 test cases	17.1.0
2023-03	RAN#99	R5-231966	0467	1	F	Update of the uncertainty of the network analyzer	17.1.0
2023-03	RAN#99	R5-231968	0468	1	F	Update of PC1 MU	17.1.0
2023-06	RAN#100	R5-232078	0503	-	F	TT analysis for positioning test case 16.3.2	17.2.0
2023-06	RAN#100	R5-232164	0508	-	F	PC1 MU - definition for ACS Case 1 and IBB test cases in 38.903	17.2.0
2023-06	RAN#100	R5-232308	0513	-	F	Update of Test Tolerance analyses for EN-DC FR2 RLM tests for PSCell configured with CSI-RS-based RLM RS	17.2.0
2023-06	RAN#100	R5-232427	0514	-	F	TT analysis for TC 16.2.1	17.2.0
2023-06	RAN#100	R5-232428	0515	-	F	TT analysis for TC 16.2.2	17.2.0
2023-06	RAN#100	R5-232429	0516	-	F	TT analysis for TC 16.3.1	17.2.0
2023-06	RAN#100	R5-232483	0517	-	F	TT analysis for RedCap RRM TC 17.6.1.2 and 17.6.1.4 intraFreq one AoA	17.2.0
2023-06	RAN#100	R5-232484	0518	-	F	TT analysis for RedCap RRM TC 17.6.1.3 intraFreq two AoAs	17.2.0
2023-06	RAN#100	R5-232485	0519	-	F	TT analysis for RedCap RRM TC 17.6.3.1 and 17.6.3.2 SSB L1RSRP	17.2.0

2023-06	RAN#100	R5-232486	0520	-	F	TT analysis for RedCap RRM TC 17.6.3.3 and 17.6.3.4 CSIRS L1RSRP	17.2.0
2023-06	RAN#100	R5-232487	0521	-	F	TT analysis for RedCap RRM TC 18.3.1.5 interRAT nonPeak	17.2.0
2023-06	RAN#100	R5-232488	0522	-	F	TT analysis for RedCap RRM TC 18.3.1.x interRAT peak	17.2.0
2023-06	RAN#100	R5-232561	0523	-	F	Test Tolerance analysis of FR1 PDC test cases	17.2.0
2023-06	RAN#100	R5-232566	0524	-	F	Test Tolerance analysis of FR2 PDC test cases	17.2.0
2023-06	RAN#100	R5-232631	0525	-	F	Removal of Offsets in B.18	17.2.0
2023-06	RAN#100	R5-232657	0526	-	F	Addition of TT analysis for 4.6.5.1 and 6.6.6.1	17.2.0
2023-06	RAN#100	R5-232676	0529	-	F	Addition of TT analysis for test cases 6.6.3.1 and 6.6.3.2	17.2.0
2023-06	RAN#100	R5-232757	0530	-	F	Correction to test tolerance analysis for 5.6.6.1 and 7.6.6.1	17.2.0
2023-06	RAN#100	R5-233299	0538	-	F	Addition of TT analysis for NR SA FR2 BFD and BFR for RedCap	17.2.0
2023-06	RAN#100	R5-233632	0505	1	F	PC5 MU - definition for MOP test cases in 38.903	17.2.0
2023-06	RAN#100	R5-233633	0535	1	F	Updating for PC6 measurement error contribution descriptions for IFF	17.2.0
2023-06	RAN#100	R5-233639	0506	1	F	FR2 MUs - General Update in 38.903 section B.2.2	17.2.0
2023-06	RAN#100	R5-233640	0509	1	F	FR2 PC3 - Network Analyzer MU update in 38.903	17.2.0
2023-06	RAN#100	R5-233646	0527	1	F	Addition of TT analysis for 4.7.6.1 and 6.7.8.1	17.2.0
2023-06	RAN#100	R5-233653	0511	1	F	Grouping of test tolerance analysis for test Case 5.5.3.7 with 5.5.3.1	17.2.0
2023-06	RAN#100	R5-233659	0534	1	F	Test Tolerance analysis for HST event triggered test cases	17.2.0
2023-06	RAN#100	R5-233664	0504	1	F	TT analysis for FR2 UE UL carrier RRC reconfiguration delay test case	17.2.0
2023-06	RAN#100	R5-233695	0537	1	F	Editorial correction to Annex B	17.2.0
2023-06	RAN#100	R5-233750	0510	1	F	Addition of test tolerance analysis for test Case of 4.5.3.5 EN-DC FR1 direct SCell activation and test Case of 6.5.3.4 NR SA FR1 direct SCell activation	17.2.0
2023-09	RAN#101	R5-233966	0542	-	F	TT analysis for RRM test case 7.5.3.3 - SCell Activation and deactivation for SCell in FR2 inter-band in non-DR	17.3.0
2023-09	RAN#101	R5-233968	0543	-	F	Correction to Grouping of FR2 test case 7.5.11.1	17.3.0
2023-09	RAN#101	R5-233977	0545	-	F	PC5 MU definition in 38.903	17.3.0
2023-09	RAN#101	R5-233982	0547	-	F	Editorial correction Network Analyzer FR2 MU	17.3.0
2023-09	RAN#101	R5-234221	0548	-	F	Addition of missing group information for TS 37.571-1 UE Rx-Tx time difference positioning test cases	17.3.0
2023-09	RAN#101	R5-234339	0550	-	F	Test Tolerance analysis for FR2 PDC test case	17.3.0
2023-09	RAN#101	R5-234345	0551	-	F	Addition of test tolerance analysis for test Case of 6.5.3.5 NR SA FR1 direct SCell activation at handover	17.3.0
2023-09	RAN#101	R5-234346	0552	-	F	Addition of test tolerance analysis for test Case of 7.5.3.4 NR SA FR2 direct SCell activation	17.3.0
2023-09	RAN#101	R5-234347	0553	-	F	Addition of test tolerance analysis for test Case of 7.5.3.5 NR SA FR2 direct SCell activation at handover	17.3.0
2023-09	RAN#101	R5-234349	0554	-	F	Test Tolerances for NR SA FR1 DL interruptions at switching between two uplink carriers for 6.5.7A.2	17.3.0
2023-09	RAN#101	R5-234350	0555	-	F	Test Tolerances for NR SA FR1 DL interruptions at switching between two uplink bands for 6.5.7B.2	17.3.0
2023-09	RAN#101	R5-234387	0556	-	F	Update of Test Tolerance analysis for non-DRX SSB-based RLM In-sync tests in FR2	17.3.0
2023-09	RAN#101	R5-234389	0557	-	F	Update of Test Tolerance analyses for non-DRX CSI-RS-based RLM In-sync tests in FR2	17.3.0
2023-09	RAN#101	R5-234421	0561	-	F	TT analysis for RedCap RRM TC 16.5.1.x_RLM IS 1Rx	17.3.0
2023-09	RAN#101	R5-234422	0562	-	F	TT analysis for RedCap RRM TC 16.5.1.x_RLM OOS 1Rx	17.3.0
2023-09	RAN#101	R5-234423	0563	-	F	TT analysis for RedCap RRM TC 16.6.1.x_intraFreq 1Rx	17.3.0
2023-09	RAN#101	R5-234424	0564	-	F	TT analysis for RedCap RRM TC 16.6.4.1 and 16.6.4.3_SSB L1 RSRP 1Rx	17.3.0
2023-09	RAN#101	R5-234651	0567	-	F	Addition of TT analysis for test case 5.5.1.10	17.3.0
2023-09	RAN#101	R5-234663	0568	-	F	Addition of TTs for RedCap RLM OOS test cases 16.5.1.5 and 16.5.1.6	17.3.0
2023-09	RAN#101	R5-234665	0569	-	F	Addition of TTs for RedCap BFR test case 16.5.2.4	17.3.0
2023-09	RAN#101	R5-234666	0570	-	F	Addition of TTs for RedCap BFR test cases 16.5.2.3	17.3.0
2023-09	RAN#101	R5-234668	0571	-	F	Addition of TTs for RedCap BWP Switch test cases 16.5.3.1.1 and 16.5.3.1.2	17.3.0
2023-09	RAN#101	R5-234669	0572	-	F	Addition of TTs for RedCap BWP Switch test cases 16.5.3.2.1 and 16.5.3.2.2	17.3.0
2023-09	RAN#101	R5-234670	0573	-	F	Update to TT analysis for L2N latency test cases 8.4.2.x and 18.3.1.x	17.3.0
2023-09	RAN#101	R5-234678	0574	-	F	Addition of TT analysis for TCI state switch test cases 7.5.8.1.1 and 7.5.8.2.1	17.3.0
2023-09	RAN#101	R5-234882	0576	-	F	Addition of TT analysis for FeMIMO RRM TC 4.5.5.8	17.3.0
2023-09	RAN#101	R5-234966	0582	-	F	Test Tolerance for NR SA FR1 Cell reselection RedCap test case 16.1.1.5	17.3.0
2023-09	RAN#101	R5-234967	0583	-	F	Test Tolerance for NR SA FR1 Cell reselection RedCap test case 16.1.1.7	17.3.0
2023-09	RAN#101	R5-234969	0585	-	F	Test Tolerance for NR - E-UTRA FR1 Cell reselection RedCap test cases 16.1.2.3	17.3.0

2023-09	RAN#101	R5-234970	0586	-	F	Test Tolerance for NR - E-UTRA FR1 Cell reselection RedCap test case 16.1.2.5	17.3.0
2023-09	RAN#101	R5-235103	0587	-	F	TT analysis for FR1 Power saving Enh test cases 4.5.1.9 and 6.5.1.9	17.3.0
2023-09	RAN#101	R5-235104	0588	-	F	TT analysis for FR2 Power saving Enh test case 5.5.5.9	17.3.0
2023-09	RAN#101	R5-235461	0577	2	F	Addition of TT analysis for FeMIMO RRM TC 5.5.5.8& 7.5.5.9	17.3.0
2023-09	RAN#101	R5-235462	0579	2	F	Addition of TT analysis for FeMIMO RRM TC 7.5.5.10	17.3.0
2023-09	RAN#101	R5-235467	0549	2	F	Update to Demod SNR calculator for Agg BW up to 400MHz	17.3.0
2023-09	RAN#101	R5-235731	0560	1	F	TT analysis for RedCap RRM TC 16.3.1.x_intra and inter freq HO 1Rx	17.3.0
2023-09	RAN#101	R5-235732	0565	1	F	TT analysis for RedCap RRM TC 16.6.4.5 and 16.6.4.7_CSIRS L1 RSRP 1Rx	17.3.0
2023-09	RAN#101	R5-235736	0589	1	F	Addition of TT analysis grouping for test cases 5.5.9.1.1 and 7.5.9.1.1 to Table 8-2	17.3.0
2023-09	RAN#101	R5-235737	0590	1	F	Addition of TT analysis grouping for test cases 5.5.9.2.1 and 7.5.9.2.1 to Table 8-2	17.3.0
2023-09	RAN#101	R5-235740	0540	1	F	Addition of TT analysis for gap enhancement RRM test cases 6.6.18.1 and 6.6.18.2	17.3.0
2023-09	RAN#101	R5-235743	0566	1	F	TT analysis for FR1 L1 RSRP relative accuracy TCs	17.3.0
2023-09	RAN#101	R5-235751	0544	1	F	FR2c MU definition in 38.903	17.3.0
2023-09	RAN#101	R5-235920	0584	1	F	Test Tolerance for NR - E-UTRA FR1 Cell reselection RedCap test case 16.1.2.1	17.3.0
2023-09	RAN#101	R5-235921	0581	1	F	Test Tolerance for NR SA FR1 Cell reselection RedCap test case 16.1.1.3	17.3.0
2023-09	RAN#101	R5-235923	0575	1	F	Addition of TT analysis for FeMIMO RRM TC 4.5.5.7	17.3.0
2023-09	RAN#101	R5-235925	0578	1	F	Addition of TT analysis for FeMIMO RRM TC 6.5.5.7	17.3.0
2023-09	RAN#101	R5-235930	0541	1	F	Addition of TT analysis for NCSG RRM test cases 6.6.19.1,6.6.19.2, 6.6.19.3 and 6.6.19.4	17.3.0
2023-09	RAN#101	R5-235931	0539	1	F	Addition of TT analysis for MG_enh RRM test cases 6.6.17.1 and 6.6.17.2	17.3.0
2023-09	RAN#101	-	-	-	-	Administrative release upgrade to match the release of 3GPP TS 38.521-3 and TS 38.522 which were upgraded at RAN#101 to Rel-18 due to Rel-18 relevant CR(s)	18.0.0
2023-12	RAN#102	R5-236062	0598	-	F	PC5 MU - ACS Case 1 and IBB update in 38.903	18.1.0
2023-12	RAN#102	R5-236214	0602	-	F	Addition of Test Tolerances analysis for TC 6.5.7C.1	18.1.0
2023-12	RAN#102	R5-236215	0603	-	F	Addition of Test Tolerances analysis for TC 6.5.7C.2	18.1.0
2023-12	RAN#102	R5-236221	0604	-	F	Addition of test tolerances analysis for RedCap CGI identification test cases	18.1.0
2023-12	RAN#102	R5-236223	0605	-	F	Addition of Test Tolerances analysis for TC 7.6.3.6	18.1.0
2023-12	RAN#102	R5-236224	0606	-	F	Addition of test tolerance analysis for fast SCell activation test cases of 4.5.3.6, 4.5.3.7, 6.5.3.10, 6.5.3.11	18.1.0
2023-12	RAN#102	R5-236225	0607	-	F	Addition of test tolerance analysis for CPAC test cases of 4.5.11.1	18.1.0
2023-12	RAN#102	R5-236226	0608	-	F	Addition of test tolerance analysis for fast SCell activation test cases of 5.5.3.8 and 7.5.3.13	18.1.0
2023-12	RAN#102	R5-236250	0609	-	F	Removal of technical content in TR 38.903 v17.3.0 and substitution with pointer to the next Release	18.1.0
2023-12	RAN#102	R5-236391	0611	-	F	Addition of test tolerance analysis for 4.5.2.10 EN-DC FR1 interruptions due to RRM and RLM/BFD measurements on deactivated NR PSCell	18.1.0
2023-12	RAN#102	R5-236393	0612	-	F	Addition of test tolerance analysis for 4.5.10.1 EN-DC FR1 PSCell activation and deactivation delay	18.1.0
2023-12	RAN#102	R5-236395	0613	-	F	Addition of test tolerance analysis for 5.5.12.1 EN-DC FR2 PSCell activation and deactivation delay	18.1.0
2023-12	RAN#102	R5-236740	0615	-	F	TT analysis for RedCap RRM TC 16.3.1.9	18.1.0
2023-12	RAN#102	R5-236741	0616	-	F	TT analysis for RedCap RRM TC 16.3.2.1.1	18.1.0
2023-12	RAN#102	R5-236742	0617	-	F	TT analysis for RedCap RRM TC 16.3.2.1.3	18.1.0
2023-12	RAN#102	R5-236743	0618	-	F	TT analysis for RedCap RRM TC 16.3.2.1.5	18.1.0
2023-12	RAN#102	R5-236745	0620	-	F	TT analysis for RedCap RRM TC 16.3.2.3.1	18.1.0
2023-12	RAN#102	R5-236746	0621	-	F	TT analysis for RedCap RRM TC 16.3.2.3.3	18.1.0
2023-12	RAN#102	R5-236747	0622	-	F	TT analysis for RedCap RRM TC 16.5.2.x	18.1.0
2023-12	RAN#102	R5-236792	0624	-	F	Editorial correction for MU tables	18.1.0
2023-12	RAN#102	R5-236872	0627	-	F	Addition of test tolerance analysis for Conditional PSCell Addition FR2 test cases	18.1.0
2023-12	RAN#102	R5-236873	0628	-	F	Addition of test tolerance analysis for 7.5.14 PSCell activation	18.1.0
2023-12	RAN#102	R5-236989	0630	-	F	Test Tolerance for NR SA FR1 2Rx event triggered measurement RedCap test cases 16.6.2.x	18.1.0
2023-12	RAN#102	R5-236991	0632	-	F	Test Tolerance analysis correction for FR2 Inter-freq accuracy measurement test cases	18.1.0
2023-12	RAN#102	R5-237013	0633	-	F	Correction of UE gain parameters	18.1.0
2023-12	RAN#102	R5-237734	0599	1	F	FR2c MU definition in 38.903	18.1.0
2023-12	RAN#102	R5-237735	0623	1	F	Update for FR2c MU	18.1.0
2023-12	RAN#102	R5-237736	0639	1	F	Update of MU for FR2 UL MIMO	18.1.0
2023-12	RAN#102	R5-237791	0629	1	F	Test Tolerance for NR SA FR1 Cell reselection RedCap test case 16.1.1.1	18.1.0

2023-12	RAN#102	R5-237792	0631	1	F	Test Tolerance for NR SA FR1 1Rx event triggered measurement RedCap test cases 16.6.2.x	18.1.0
2023-12	RAN#102	R5-237796	0591	1	F	Addition of TT analysis for positioning test case 14.2.8	18.1.0
2023-12	RAN#102	R5-237797	0592	1	F	Addition of TT analysis for positioning test case 14.2.9	18.1.0
2023-12	RAN#102	R5-237798	0593	1	F	Addition of TT analysis for positioning test case 14.2.10	18.1.0
2023-12	RAN#102	R5-237799	0594	1	F	Addition of TT analysis for positioning test case 14.3.7	18.1.0
2023-12	RAN#102	R5-237800	0595	1	F	Addition of TT analysis for positioning test case 14.3.8	18.1.0
2023-12	RAN#102	R5-237801	0596	1	F	Addition of TT analysis for positioning test case 15.3.5	18.1.0
2023-12	RAN#102	R5-237802	0597	1	F	Addition of TT analysis for positioning test case 15.3.6	18.1.0
2023-12	RAN#102	R5-237812	0635	1	F	Addition of TTs for test case 7.5.1.5	18.1.0
2023-12	RAN#102	R5-237813	0636	1	F	Addition of TTs for test case 7.5.1.6	18.1.0
2023-12	RAN#102	R5-237814	0637	1	F	Addition of TTs for test case 7.5.1.7	18.1.0
2023-12	RAN#102	R5-237815	0638	1	F	Addition of TTs for test case 7.5.1.8	18.1.0
2023-12	RAN#102	R5-237928	0614	1	F	TT analysis for RedCap RRM TC 16.3.1.7	18.1.0
2023-12	RAN#102	R5-237929	0619	1	F	TT analysis for RedCap RRM TC 16.3.2.2.x	18.1.0
2023-12	RAN#102	R5-237952	0610	1	F	MU and TT analysis for unified TCI state switching	18.1.0
2023-12	RAN#102	R5-237956	0626	1	F	Addition of test tolerance analysis for 7.5.3.14 Fast SCell activation	18.1.0
2023-12	RAN#102	R5-237961	0634	1	F	Addition of TTs for test case 6.2.1	18.1.0
2024-03	RAN#103	R5-240129	0641	-	F	Addition of TT analysis for positioning test case 15.2.8	18.2.0
2024-03	RAN#103	R5-240131	0643	-	F	Addition of TT analysis for positioning test case 16.2.7	18.2.0
2024-03	RAN#103	R5-240132	0644	-	F	Addition of TT analysis for positioning test case 16.2.8	18.2.0
2024-03	RAN#103	R5-240133	0645	-	F	Addition of TT analysis for positioning test case 16.3.4	18.2.0
2024-03	RAN#103	R5-240373	0648	-	F	Test Tolerances for NR SA FR1 DL interruptions at switching between two uplink carriers for 6.5.7A.1	18.2.0
2024-03	RAN#103	R5-240374	0649	-	F	Test Tolerances for NR SA FR1 DL interruptions at switching between two uplink bands for 6.5.7B.1	18.2.0
2024-03	RAN#103	R5-240406	0651	-	F	FR2 MU - PC1 UL MIMO - Minimum output power test - 38.903	18.2.0
2024-03	RAN#103	R5-240735	0658	-	F	TT analysis for RedCap RRM test case 16.3.2.2.2 and 16.3.2.2.4	18.2.0
2024-03	RAN#103	R5-240736	0659	-	F	TT analysis for RedCap RRM test case 16.3.2.2.6 and 16.3.2.2.8	18.2.0
2024-03	RAN#103	R5-240737	0660	-	F	TT analysis for RedCap RRM test case 16.6.5.3	18.2.0
2024-03	RAN#103	R5-240738	0661	-	F	TT analysis for RedCap RRM test case 16.6.5.4	18.2.0
2024-03	RAN#103	R5-240739	0662	-	F	TT analysis for RedCap RRM test case 16.7.2.3.1	18.2.0
2024-03	RAN#103	R5-240741	0664	-	F	TT analysis for RedCap RRM test case 16.7.2.4.1	18.2.0
2024-03	RAN#103	R5-240742	0665	-	F	TT analysis for RedCap RRM test case 16.7.2.4.2	18.2.0
2024-03	RAN#103	R5-240743	0666	-	F	TT analysis for RedCap RRM test case 16.7.3.1 and 16.7.3.2	18.2.0
2024-03	RAN#103	R5-240747	0670	-	F	TT analysis for RedCap RRM test case 16.7.3.4.2	18.2.0
2024-03	RAN#103	R5-240748	0671	-	F	TT analysis for RedCap RRM test case 16.7.4.1.1	18.2.0
2024-03	RAN#103	R5-240749	0672	-	F	TT analysis for RedCap RRM test case 16.7.4.1.2	18.2.0
2024-03	RAN#103	R5-240752	0675	-	F	TT analysis for RedCap RRM test case 16.7.5.1	18.2.0
2024-03	RAN#103	R5-240753	0676	-	F	TT analysis for RedCap RRM test case 16.7.5.2	18.2.0
2024-03	RAN#103	R5-240754	0677	-	F	TT analysis for RedCap RRM test case 16.7.6.1	18.2.0
2024-03	RAN#103	R5-240755	0678	-	F	TT analysis for RedCap RRM test case 16.7.6.2	18.2.0
2024-03	RAN#103	R5-240787	0679	-	F	Addition of Test Tolerance for NR SA Event triggered reporting RedCap test cases	18.2.0
2024-03	RAN#103	R5-240788	0680	-	F	Test Tolerances for NR SA FR1 - E-UTRAN event-triggered reporting tests for 1 Rx RedCap UE	18.2.0
2024-03	RAN#103	R5-240789	0681	-	F	Test Tolerances for NR SA FR1 - E-UTRAN event-triggered reporting tests for 2 Rx RedCap UE	18.2.0
2024-03	RAN#103	R5-241150	0683	-	F	TT analysis for FR1 PDSCH with inter-cell interference test cases	18.2.0
2024-03	RAN#103	R5-241221	0685	-	F	Test Tolerance for NR SA FR1 SS-RSRP absolute measurement accuracy for RedCap 1 Rx UE test case 16.7.1.1.1	18.2.0
2024-03	RAN#103	R5-241222	0686	-	F	Test Tolerance for NR SA FR1 SS-RSRP relative measurement accuracy for 1 Rx UE test case 16.7.1.1.2	18.2.0
2024-03	RAN#103	R5-241223	0687	-	F	Test Tolerance for NR SA FR1 SS-RSRP absolute measurement accuracy for RedCap 2 Rx UE test case 16.7.1.2.1	18.2.0
2024-03	RAN#103	R5-241224	0688	-	F	Test Tolerance for NR SA FR1 SS-RSRP absolute measurement accuracy for RedCap 2 Rx UE test case 16.7.1.2.2	18.2.0
2024-03	RAN#103	R5-241225	0689	-	F	Test Tolerance for NR SA FR1 SS-RSRQ measurement accuracy UE test case 16.7.2.1	18.2.0
2024-03	RAN#103	R5-241226	0690	-	F	Test Tolerance NR SA FR1 SS-RSRQ measurement accuracy for 2 Rx UE test case 16.7.2.2	18.2.0
2024-03	RAN#103	R5-241337	0699	-	F	Addition of TT analysis grouping for test cases 4.5.9.1 to Table 8-1	18.2.0
2024-03	RAN#103	R5-241680	0653	1	F	Introduction of Test Tolerance analysis for FR2 SA event triggered reporting tests with Pre-MG	18.2.0
2024-03	RAN#103	R5-241681	0654	1	F	Introduction of Test Tolerance analysis for FR2 SA event triggered reporting tests with concurrent gaps	18.2.0
2024-03	RAN#103	R5-241682	0655	1	F	Introduction of Test Tolerance analysis for SA FR2 event triggered reporting tests with NCSG	18.2.0
2024-03	RAN#103	R5-241863	0650	1	F	FR2c MU definition in 38.903	18.2.0
2024-03	RAN#103	R5-241864	0652	1	F	CR to define FR2d QoQZ MUs and misc QoQZ MU corrections	18.2.0
2024-03	RAN#103	R5-241865	0682	1	F	Update for FR2c MU	18.2.0
2024-03	RAN#103	R5-241866	0702	1	F	Documentation of MU for n259	18.2.0

2024-03	RAN#103	R5-241881	0692	1	F	Addition of TTs for NR-U Test Cases 10.3.1.2 and 11.4.1.2	18.2.0
2024-03	RAN#103	R5-241882	0693	1	F	Addition of TTs for NR-U Test Cases 10.3.1.3 and 11.4.1.3	18.2.0
2024-03	RAN#103	R5-241883	0694	1	F	Addition of TTs for NR-U Test Cases 10.3.4.1, 10.3.4.2, 11.4.4.1 and 11.4.4.2	18.2.0
2024-03	RAN#103	R5-241884	0696	1	F	Addition of TTs for NR-U Test Cases 10.3.5.2.1, 10.3.5.2.2, 11.4.5.2.1 and 11.4.5.2.2	18.2.0
2024-03	RAN#103	R5-241885	0697	1	F	Addition of TTs for NR-U Test Cases 10.3.5.3.1 and 11.4.5.3.1	18.2.0
2024-03	RAN#103	R5-241887	0667	1	F	TT analysis for RedCap RRM test case 16.7.3.3.1	18.2.0
2024-03	RAN#103	R5-241888	0668	1	F	TT analysis for RedCap RRM test case 16.7.3.3.2	18.2.0
2024-03	RAN#103	R5-241889	0669	1	F	TT analysis for RedCap RRM test case 16.7.3.4.1	18.2.0
2024-03	RAN#103	R5-241890	0673	1	F	TT analysis for RedCap RRM test case 16.7.4.2.1 16.7.4.3.1 and 16.7.4.4.1	18.2.0
2024-03	RAN#103	R5-241891	0674	1	F	TT analysis for RedCap RRM test case 16.7.4.2.2 16.7.4.3.2 and 16.7.4.4.2	18.2.0
2024-03	RAN#103	R5-241892	0698	1	F	Update of TT analysis for 6.3.1.4 and 16.3.1.8	18.2.0
2024-03	RAN#103	R5-241894	0700	1	F	Addition of TT analysis grouping for test cases 5.5.6.3.1 to Table 8-2	18.2.0
2024-03	RAN#103	R5-241895	0701	1	F	Addition of TT analysis grouping for test cases 5.5.6.4.1 to Table 8-2	18.2.0
2024-03	RAN#103	R5-241900	0642	1	F	Addition of TT analysis for positioning test case 15.2.9 and 15.2.10	18.2.0
2024-03	RAN#103	R5-241902	0684	1	F	Correct of test tolerance analysis of EN-DC FR1 addition and release delay of known PSCell for test case 4.5.7.1	18.2.0
2024-03	RAN#103	R5-242000	0695	1	F	Addition of TTs for NR-U Test Cases 10.3.5.1 and 11.4.5.1	18.2.0
2024-03	RAN#103	R5-242029	0703	1	F	Measurement uncertainty definition for UE Maximum Output Power - EIRP with UL Gaps test case	18.2.0
2024-03	RAN#103	R5-242044	0663	1	F	TT analysis for RedCap RRM test case 16.7.2.3.2	18.2.0
2024-06	RAN#104	R5-242224	0713	-	F	Update TC 15.2.1 TT analysis results	18.3.0
2024-06	RAN#104	R5-242225	0714	-	F	Update TC 15.2.2 TT analysis results	18.3.0
2024-06	RAN#104	R5-242229	0718	-	F	Update TC 15.3.1 TT analysis results	18.3.0
2024-06	RAN#104	R5-242230	0719	-	F	Update TC 15.3.2 TT analysis results	18.3.0
2024-06	RAN#104	R5-242231	0720	-	F	Update TC 15.3.5 TT analysis results	18.3.0
2024-06	RAN#104	R5-242232	0721	-	F	Update TC 15.3.6 TT analysis results	18.3.0
2024-06	RAN#104	R5-242233	0722	-	F	Update TC 16.2.3, 16.2.7 and 16.2.8 TT analysis results	18.3.0
2024-06	RAN#104	R5-242234	0723	-	F	Update TC 16.2.4 TT analysis results	18.3.0
2024-06	RAN#104	R5-242235	0724	-	F	Update TC 16.3.2 TT analysis results	18.3.0
2024-06	RAN#104	R5-242236	0725	-	F	Update TC 16.3.4 TT analysis results	18.3.0
2024-06	RAN#104	R5-242259	0726	-	F	Pending UL MIMO update in 38.903	18.3.0
2024-06	RAN#104	R5-242307	0729	-	F	Removal of technical content in TR 38.903 v16.14.0 and substitution with pointer to the next Release	18.3.0
2024-06	RAN#104	R5-242439	0730	-	F	TT analysis for FR1 CQI reporting test cases with inter-cell interference	18.3.0
2024-06	RAN#104	R5-242629	0733	-	F	Test Tolerance analysis for SRS carrier based switching test cases	18.3.0
2024-06	RAN#104	R5-242631	0735	-	F	Test Tolerance analysis for event triggered reporting test without gap under DRX test case 7.6.2.11	18.3.0
2024-06	RAN#104	R5-242730	0737	-	F	Update of the QoQZ MU	18.3.0
2024-06	RAN#104	R5-242731	0738	-	F	Removal of the reference to efficiency calibration in QoQZ	18.3.0
2024-06	RAN#104	R5-243104	0745	-	F	Documentation of MU for UL MIMO	18.3.0
2024-06	RAN#104	R5-243400	0756	-	F	Addition of TTs for NR-U Timing Accuracy Test	18.3.0
2024-06	RAN#104	R5-243401	0757	-	F	Addition of TTs for NR-U Timing Advance Test	18.3.0
2024-06	RAN#104	R5-243403	0759	-	F	Addition of TTs for SCell activation and deactivation tests	18.3.0
2024-06	RAN#104	R5-243433	0762	-	F	Addition of MU/TT analysis for inter-cell CRS interference	18.3.0
2024-06	RAN#104	R5-243723	0728	1	F	PC5 FR2 MU definition in 38.903	18.3.0
2024-06	RAN#104	R5-243730	0727	1	F	FR2c MU definition in 38.903	18.3.0
2024-06	RAN#104	R5-243738	0750	1	F	Test Tolerance analysis for NR-U RSRQ intra-frequency accuracy test cases 10.5.2.1 and 11.6.2.1	18.3.0
2024-06	RAN#104	R5-243741	0753	1	F	Test Tolerance analysis for NR-U SINR inter-frequency accuracy test cases 10.5.3.2 and 11.6.3.2	18.3.0
2024-06	RAN#104	R5-243742	0754	1	F	Test Tolerance analysis for NR-U L1-RSRP accuracy test case 10.5.4.1	18.3.0
2024-06	RAN#104	R5-243745	0731	1	F	Introduction of Test Tolerance analysis for 7.6.15.3 FR2 SA event triggered reporting tests for concurrent gaps	18.3.0
2024-06	RAN#104	R5-243752	0732	1	F	Addition of Test Tolerances analysis for NR-U redirection test cases	18.3.0
2024-06	RAN#104	R5-243753	0760	1	F	Addition of TTs for PSCell addition and release test	18.3.0
2024-06	RAN#104	R5-243759	0734	1	F	Test Tolerance analysis for event triggered reporting test without gap under non-DRX test case 7.6.2.10	18.3.0
2024-06	RAN#104	R5-243769	0707	1	F	Update TC 14.2.3 and TC 14.2.10 TT analysis results	18.3.0
2024-06	RAN#104	R5-243770	0709	1	F	Update TC 14.2.8 and TC 14.2.9 TT analysis results	18.3.0
2024-06	RAN#104	R5-243771	0710	1	F	Update TC 14.3.3 and TC 14.3.8 TT analysis results	18.3.0
2024-06	RAN#104	R5-243772	0712	1	F	Update TC 14.3.7 TT analysis results	18.3.0
2024-06	RAN#104	R5-243773	0717	1	F	Update TC 15.2.8, 15.2.9 and 15.2.10 TT analysis results	18.3.0
2024-06	RAN#104	R5-243792	0708	1	F	Update TC 14.2.4 TT analysis results	18.3.0
2024-06	RAN#104	R5-243793	0711	1	F	Update TC 14.3.4 TT analysis results	18.3.0
2024-06	RAN#104	R5-243794	0715	1	F	Update TC 15.2.3 TT analysis results	18.3.0
2024-06	RAN#104	R5-243795	0716	1	F	Update TC 15.2.4 TT analysis results	18.3.0

2024-06	RAN#104	R5-243829	0744	1	F	Documentation of MU for n259	18.3.0
2024-06	RAN#104	R5-243832	0742	1	F	Update for FR2c MU	18.3.0
2024-06	RAN#104	R5-243893	0746	1	F	Test Tolerance analysis for NR-U inter-frequency measurement reporting test cases 10.4.2.3, 10.4.2.4, 10.4.2.5, 10.4.2.6	18.3.0
2024-06	RAN#104	R5-243894	0747	1	F	Test Tolerance analysis for NR-U inter-frequency measurement reporting test cases with DRX 10.4.2.7, 10.4.2.8, 10.4.2.9, 10.4.2.10	18.3.0
2024-06	RAN#104	R5-243895	0755	1	F	Addition of TTs for NR-U intra-frequency measurement reporting test	18.3.0
2024-06	RAN#104	R5-243996	0748	2	F	Test Tolerance analysis for NR-U RSRP intra-frequency accuracy test cases 10.5.1.1 and 11.6.1.1	18.3.0
2024-06	RAN#104	R5-243997	0749	2	F	Test Tolerance analysis for NR-U RSRP inter-frequency accuracy test case 10.5.1.2	18.3.0
2024-06	RAN#104	R5-243998	0751	2	F	Test Tolerance analysis for NR-U RSRQ inter-frequency accuracy test cases 10.5.2.2 and 11.6.2.2	18.3.0
2024-06	RAN#104	R5-243999	0752	2	F	Test Tolerance analysis for NR-U SINR intra-frequency accuracy test cases 10.5.3.1 and 10.5.3.3	18.3.0
2024-06	RAN#104	R5-244004	0736	1	F	Addition of test tolerance analysis for Rel-16 RRM test case EN-DC CSI-RSRP measurement accuracy with FR1 serving cell and FR1 target cell	18.3.0
2024-06	RAN#104	R5-244007	0705	2	F	Addition of TT for MG enhancements TC 6.6.18.3	18.3.0
2024-06	RAN#104	R5-244008	0706	2	F	Addition of TT for MG enhancements TC 6.6.18.4	18.3.0
2024-06	RAN#104	R5-244016	0739	2	F	TT analysis for RedCap RRM test case 16.2.1.1	18.3.0
2024-06	RAN#104	R5-244017	0740	1	F	TT analysis for RedCap RRM test case 16.2.1.2	18.3.0
2024-09	RAN#105	R5-244079	0763	-	F	Addition of TT analysis for positioning test case 14.4.3	18.4.0
2024-09	RAN#105	R5-244080	0764	-	F	Addition of TT analysis for positioning test case 14.4.4	18.4.0
2024-09	RAN#105	R5-244081	0765	-	F	Addition of TT analysis for positioning test case 14.5.3	18.4.0
2024-09	RAN#105	R5-244083	0767	-	F	Addition of TT analysis for positioning test case 15.4.3	18.4.0
2024-09	RAN#105	R5-244084	0768	-	F	Addition of TT analysis for positioning test case 15.4.4	18.4.0
2024-09	RAN#105	R5-244085	0769	-	F	Addition of TT analysis for positioning test cases 16.4.3 and 16.4.4	18.4.0
2024-09	RAN#105	R5-244086	0770	-	F	Addition of TT analysis for positioning test case 16.5.3	18.4.0
2024-09	RAN#105	R5-244087	0771	-	F	Addition of TT analysis for positioning test case 16.5.4	18.4.0
2024-09	RAN#105	R5-244168	0775	-	F	FR2c MU - MOP-TRP update in 38.903	18.4.0
2024-09	RAN#105	R5-244170	0776	-	F	FR2 MU - Tx OFF power update for in 38.903	18.4.0
2024-09	RAN#105	R5-244173	0777	-	F	PC6 FR2 MU definition in 38.903	18.4.0
2024-09	RAN#105	R5-244548	0784	-	F	Addition of Test Tolerances analysis for RRC_INACTIVE positioning test cases	18.4.0
2024-09	RAN#105	R5-244641	0786	-	F	TT analysis for RedCap RLM test cases	18.4.0
2024-09	RAN#105	R5-244642	0787	-	F	TT analysis for RedCap BWP switching test cases	18.4.0
2024-09	RAN#105	R5-245027	0799	-	F	Test Tolerance analysis for 4-step FR1 NR-U Random access tests 10.1.1.1.1 and 10.1.1.1.2	18.4.0
2024-09	RAN#105	R5-245028	0800	-	F	Test Tolerance analysis for 2-step FR1 NR-U Random access tests 10.1.1.1.3 and 10.1.1.1.4	18.4.0
2024-09	RAN#105	R5-245253	0808	-	F	MU update for RRM FR2 PC1	18.4.0
2024-09	RAN#105	R5-245257	0809	-	F	Test Tolerance for SS-RSRP RedCap test case 16.7.1.4.2	18.4.0
2024-09	RAN#105	R5-245258	0810	-	F	Test Tolerance for SS-RSRP RedCap test case 16.7.1.4.1	18.4.0
2024-09	RAN#105	R5-245261	0813	-	F	Test Tolerance for Relative Measurement Accuracy test cases	18.4.0
2024-09	RAN#105	R5-245262	0814	-	F	Test Tolerance for R15 Absolute Measurement Accuracy test cases	18.4.0
2024-09	RAN#105	R5-245263	0815	-	F	Test Tolerance for FR2 Intra-frequency measurement accuracy test cases for PC1	18.4.0
2024-09	RAN#105	R5-245264	0816	-	F	Test Tolerance for FR2 Event Triggered test cases for PC1	18.4.0
2024-09	RAN#105	R5-245265	0817	-	F	Test Tolerance for FR2 Timing Advance test cases for PC1	18.4.0
2024-09	RAN#105	R5-245266	0818	-	F	Test Tolerance for FR2 Transmit Timing test cases for PC1	18.4.0
2024-09	RAN#105	R5-245304	0819	-	F	Add TT analysis for PDSCH CRS interference mitigation under NR-LTE coexistence test cases 5.2.2.1.18, 5.2.2.2.19, 5.2.3.1.17, 5.2.3.2.18	18.4.0
2024-09	RAN#105	R5-245305	0820	-	F	Test Tolerance for SS-RSRP RedCap test case 16.7.1.3.2	18.4.0
2024-09	RAN#105	R5-245306	0821	-	F	Test Tolerance for SS-RSRP RedCap test case 16.7.1.3.1	18.4.0
2024-09	RAN#105	R5-245381	0823	-	F	Addition of TTs for PSCell HO test 10.1.2	18.4.0
2024-09	RAN#105	R5-245383	0825	-	F	Update to TT for SUL test cases 4.5.4.1 and 6.5.4.1	18.4.0
2024-09	RAN#105	R5-245384	0826	-	F	Addition of TTs for RedCap SA FR2 SSB BFR test cases 17.5.2.1 and 17.5.2.2	18.4.0
2024-09	RAN#105	R5-245385	0827	-	F	Update to TT analysis for RedCap 1Rx event-triggered test cases 16.6.3.1 and 16.6.3.3	18.4.0
2024-09	RAN#105	R5-245386	0828	-	F	Update to TT analysis for RedCap 2Rx event-triggered test cases 16.6.3.2 and 16.6.3.4	18.4.0
2024-09	RAN#105	R5-245736	0833	1	F	Addition of TT analysis grouping for RRM test cases 5.7.8.1 and 7.7.8.1	18.4.0
2024-09	RAN#105	R5-245737	0834	1	F	Addition of TT analysis grouping for RRM test cases 5.7.8.2 and 7.7.8.2	18.4.0
2024-09	RAN#105	R5-245738	0835	1	F	Addition of TT analysis grouping for RRM test cases 5.7.9.1 and 7.7.9.1	18.4.0
2024-09	RAN#105	R5-245739	0836	1	F	Addition of TT analysis grouping for RRM test cases 5.7.9.2 and 7.7.9.2	18.4.0

2024-09	RAN#105	R5-245923	0797	1	F	Test Tolerance analysis for FR1 NR-U RSSI measurement accuracy tests 10.5.5.1,10.5.5.2,11.6.5.1 and 11.6.5.2	18.4.0
2024-09	RAN#105	R5-245924	0798	1	F	Test Tolerance analysis for FR1 NR-U Inter-frequency RSSI measurement accuracy tests 10.5.5.3 and 11.6.5.3	18.4.0
2024-09	RAN#105	R5-245925	0803	1	F	Test Tolerance analysis for FR1 NR-U SS-RSRP absolute accuracy on SCC test 11.6.1.2	18.4.0
2024-09	RAN#105	R5-245928	0774	1	F	PC5 FR2 MU definition in 38.903	18.4.0
2024-09	RAN#105	R5-245933	0789	1	F	Addition of test tolerance analysis for Rel-16 RRM EN-DC event triggered reporting tests for NR FR2 cell when DRX is used	18.4.0
2024-09	RAN#105	R5-245934	0790	1	F	Addition of test tolerance analysis for Rel-16 RRM EN-DC intra-frequency case measurement accuracy with FR2 serving cell and FR2 target cell	18.4.0
2024-09	RAN#105	R5-245935	0791	1	F	Addition of test tolerance analysis for Rel-16 RRM EN-DC inter-frequency case measurement accuracy with FR2 serving cell and FR2 target cell	18.4.0
2024-09	RAN#105	R5-245943	0772	1	F	Addition of TT analysis for positioning test cases 17.2.1, 17.2.2 and 17.2.3	18.4.0
2024-09	RAN#105	R5-245944	0773	1	F	Addition of TT analysis for positioning test cases 17.2.4, 17.2.5 and 17.2.6	18.4.0
2024-09	RAN#105	R5-245964	0778	1	F	Update of TT analysis for RedCap RRM TC 16.6.4.5 and 16.6.4.7	18.4.0
2024-09	RAN#105	R5-245965	0779	1	F	Update of Test Tolerance analyses for RedCap RRM test cases 16.5.2.5 and 16.5.2.7	18.4.0
2024-09	RAN#105	R5-245966	0780	1	F	Update of Test Tolerance analyses for RedCap RRM test cases 16.7.4.3.1	18.4.0
2024-09	RAN#105	R5-245967	0781	1	F	Update of Test Tolerance analyses for RedCap RRM test cases 16.7.4.3.2	18.4.0
2024-09	RAN#105	R5-245968	0783	1	F	Definition of 40cm SE QoQZ MU	18.4.0
2024-09	RAN#105	R5-245969	0792	1	F	Update of FR2c MU	18.4.0
2024-09	RAN#105	R5-245970	0795	1	F	Documentation of MU for n259	18.4.0
2024-09	RAN#105	R5-245971	0796	1	F	Documentation of MU for UL MIMO	18.4.0
2024-09	RAN#105	R5-246014	0785	1	F	TT analysis for MCE RRM test cases	18.4.0
2024-09	RAN#105	R5-246023	0801	1	F	Test Tolerance analysis for FR1 NR-U RSSI measurement accuracy tests 10.5.6.1,10.5.6.2,11.6.6.1 and 11.6.6.2	18.4.0
2024-09	RAN#105	R5-246024	0802	1	F	Test Tolerance analysis for FR1 NR-U RSSI measurement accuracy tests 10.5.6.3 and 11.6.6.3	18.4.0
2024-09	RAN#105	R5-246025	0805	1	F	Introduction of Test Tolerance analysis for 6.6.4.6 NR SA FR1 Inter-cell SSB based L1-RSRP measurements on PCell in DRX	18.4.0
2024-12	RAN#106	R5-246117	0838	-	F	Test Tolerance for RSTD measurement reporting delay test case 14.2.5	18.5.0
2024-12	RAN#106	R5-246170	0849	-	F	Addition of TT analysis for LTM intra TC 6.3.2.4.1 and TC 6.3.2.4.3	18.5.0
2024-12	RAN#106	R5-246171	0850	-	F	Addition of TT analysis for LTM inter TC 6.3.2.4.2	18.5.0
2024-12	RAN#106	R5-246178	0851	-	F	Addition of TT analysis for LTM TC 6.6.26.1	18.5.0
2024-12	RAN#106	R5-246179	0852	-	F	Addition of TT analysis for LTM TC 6.6.27.1	18.5.0
2024-12	RAN#106	R5-246180	0853	-	F	Addition of TT analysis for LTM TC 6.6.28.1	18.5.0
2024-12	RAN#106	R5-246181	0854	-	F	Addition of TT analysis for LTM TC 6.7.17.1.1	18.5.0
2024-12	RAN#106	R5-246191	0855	-	F	Update TT grouping information for LTM clause 6.3.2.4	18.5.0
2024-12	RAN#106	R5-246195	0856	-	F	Addition of TT analysis for LTM TC 6.3.4.3	18.5.0
2024-12	RAN#106	R5-246199	0857	-	F	Addition of TT analysis for LTM TC 6.3.4.1	18.5.0
2024-12	RAN#106	R5-246200	0858	-	F	Addition of TT analysis for LTM TC 6.3.4.2	18.5.0
2024-12	RAN#106	R5-246235	0861	-	F	PC6 FR2 MU definition in 38.903	18.5.0
2024-12	RAN#106	R5-246496	0864	-	F	Introduction of Test Tolerance analysis for 18.1.1.1 E-UTRA - NR SA FR1 E-UTRA Cell reselection to higher priority NR target Cell in FR1	18.5.0
2024-12	RAN#106	R5-246723	0865	-	F	TT analysis for FR2 re-establishment without serving timing RRM TCs	18.5.0
2024-12	RAN#106	R5-246724	0866	-	F	TT analysis for FR2 RLM scheduling restriction RRM TCs	18.5.0
2024-12	RAN#106	R5-246729	0867	-	F	TT analysis for Rel-16 and 2Rx Redcap 2-step RACH RRM test cases	18.5.0
2024-12	RAN#106	R5-246739	0868	-	F	TT analysis for 1Rx Redcap 2-step RACH RRM test cases	18.5.0
2024-12	RAN#106	R5-246797	0875	-	F	Test Tolerance analysis for FR1 NR-U Intra-frequency handover known target cell tests 11.2.1.1.	18.5.0
2024-12	RAN#106	R5-246798	0876	-	F	Test Tolerance analysis for FR1 NR-U Intra-frequency handover unknown target cell tests 11.2.1.2.	18.5.0
2024-12	RAN#106	R5-246799	0877	-	F	Test Tolerance analysis for FR1 NR-U Inter-frequency handover unknown target cell tests 11.2.1.3.	18.5.0
2024-12	RAN#106	R5-246803	0881	-	F	Test Tolerance analysis for FR1 NR-U Inter-rat handover to known EUTRAN target cell tests 11.2.1.7.	18.5.0
2024-12	RAN#106	R5-246804	0882	-	F	Test Tolerance analysis for FR1 NR-U Inter-rat handover to unknown EUTRAN target cell tests 11.2.1.8.	18.5.0
2024-12	RAN#106	R5-246806	0884	-	F	Test Tolerance analysis for FR1 NR-U inter-frequency RRC Re-establishment tests 11.2.2.1.2.	18.5.0
2024-12	RAN#106	R5-246808	0886	-	F	Test Tolerance analysis for FR1 NR-U inter-frequency RRC Re-establishment to target cell under CCA tests 11.2.2.1.4.	18.5.0
2024-12	RAN#106	R5-246856	0888	-	F	Addition of TT analysis for tests 11.2.2.2.1 and 11.2.2.2.2	18.5.0

2024-12	RAN#106	R5-246857	0889	-	F	Addition of TT analysis for tests 11.2.2.2.3 and 11.2.2.2.4	18.5.0
2024-12	RAN#106	R5-246859	0891	-	F	Addition of TT analysis for test 13.4.1.1	18.5.0
2024-12	RAN#106	R5-246860	0892	-	F	Addition of TT analysis for tests 11.6.2.3 and 13.4.2.1	18.5.0
2024-12	RAN#106	R5-246864	0896	-	F	Addition of TT analysis for test 13.4.5.2	18.5.0
2024-12	RAN#106	R5-246866	0898	-	F	Addition of TT analysis for test 13.4.6.2	18.5.0
2024-12	RAN#106	R5-246867	0899	-	F	Addition of TT analysis for NR-U L1-RSRP measurement reporting tests	18.5.0
2024-12	RAN#106	R5-246868	0900	-	F	Addition of TT analysis for test 13.2.2.1, 13.2.2.2 and 13.2.2.3	18.5.0
2024-12	RAN#106	R5-246871	0903	-	F	Editorial correction to TT analysis for test cases 6.6.3.1 and 6.6.3.2	18.5.0
2024-12	RAN#106	R5-246931	0904	-	F	Addition of test tolerance analysis for 6.3.3.6	18.5.0
2024-12	RAN#106	R5-246932	0905	-	F	Addition of test tolerance analysis for 6.3.3.7	18.5.0
2024-12	RAN#106	R5-246933	0906	-	F	Addition of test tolerance analysis for 6.6.1.13	18.5.0
2024-12	RAN#106	R5-247167	0911	-	F	Update of QoQZ for QZ size 40 cm and ETC	18.5.0
2024-12	RAN#106	R5-247304	0913	-	F	Editorial correction to Table E.3.1.4-3	18.5.0
2024-12	RAN#106	R5-247305	0914	-	F	Alignment of RedCap test case numbers from 16.6.7.x to 16.6.5.x	18.5.0
2024-12	RAN#106	R5-247306	0915	-	F	Correction of Group for RRM RedCap test case 16.7.1.3.2	18.5.0
2024-12	RAN#106	R5-247317	0920	-	F	Test Tolerance for RSTD measurement reporting delay test case 14.2.6	18.5.0
2024-12	RAN#106	R5-247318	0921	-	F	Test Tolerance for RSTD measurement reporting delay with Rx TEG test case 14.2.7	18.5.0
2024-12	RAN#106	R5-247835	0887	1	F	Addition of TT analysis for NR-NTN test cases 14.5.1.x	18.5.0
2024-12	RAN#106	R5-247845	0897	1	F	Addition of TT analysis for test 13.4.6.1	18.5.0
2024-12	RAN#106	R5-247858	0860	1	F	PC7 FR2 MU definition in 38.903	18.5.0
2024-12	RAN#106	R5-247859	0862	1	F	FR2c MU definition and updates in 38.903	18.5.0
2024-12	RAN#106	R5-247860	0863	1	F	FR2 MU - Miscellaneous corrections in MU factors in 38.903	18.5.0
2024-12	RAN#106	R5-247861	0926	1	F	Documentation of MU for SISO and UL MIMO	18.5.0
2024-12	RAN#106	R5-247868	0878	1	F	Test Tolerance analysis for FR1 NR-U Inter-frequency handover from source cell under CCA to known target cell tests 11.2.1.4.	18.5.0
2024-12	RAN#106	R5-247869	0879	1	F	Test Tolerance analysis for FR1 NR-U Inter-frequency handover from source cell under CCA to unknown target cell tests 11.2.1.5.	18.5.0
2024-12	RAN#106	R5-247870	0880	1	F	Test Tolerance analysis for FR1 NR-U Inter-frequency handover from FR1 cell to unknown target cell under CCA tests 11.2.1.6.	18.5.0
2024-12	RAN#106	R5-247871	0883	1	F	Test Tolerance analysis for FR1 NR-U intra-frequency RRC Re-establishment tests 11.2.2.1.1.	18.5.0
2024-12	RAN#106	R5-247872	0885	1	F	Test Tolerance analysis for FR1 NR-U inter-frequency RRC Re-establishment without serving cell timing tests 11.2.2.1.3.	18.5.0
2024-12	RAN#106	R5-247873	0890	1	F	Addition of Test Tolerance analysis for tests 12.4.2.x and 10.4.4.x	18.5.0
2024-12	RAN#106	R5-247874	0893	1	F	Addition of TT analysis for tests 11.6.3.1, 11.6.3.3 and 13.4.3.1	18.5.0
2024-12	RAN#106	R5-247875	0894	1	F	Addition of TT analysis for tests 11.6.4.1 and 13.4.4.1	18.5.0
2024-12	RAN#106	R5-247876	0895	1	F	Addition of TT analysis for test 13.4.5.1	18.5.0
2024-12	RAN#106	R5-247877	0901	1	F	Addition of TT analysis for tests 13.3.2.x	18.5.0
2024-12	RAN#106	R5-247878	0902	1	F	Addition of TT analysis for tests 13.3.1.1, 13.3.1.2, 13.3.1.3 and 13.3.1.4	18.5.0
2024-12	RAN#106	R5-247883	0927	1	F	Test Tolerances for FR1 SSB-based beam failure detection and link recovery for Satellite access	18.5.0
2024-12	RAN#106	R5-247884	0928	1	F	Test Tolerances for FR1 CSI-RS-based beam failure detection and link recovery for Satellite access	18.5.0
2024-12	RAN#106	R5-247887	0930	1	F	Test Tolerance analysis for EN-DC FR2 Addition and Release Delay of NR PSCell test case	18.5.0
2024-12	RAN#106	R5-247896	0840	1	F	Addition of TT analysis for positioning test case 14.5.4	18.5.0
2024-12	RAN#106	R5-247897	0922	1	F	Test Tolerance for RSTD measurement accuracy test case 14.3.5	18.5.0
2024-12	RAN#106	R5-247898	0923	1	F	Test Tolerance for RSTD measurement accuracy test case 14.3.6	18.5.0
2024-12	RAN#106	R5-247899	0924	1	F	Test Tolerance for RSTD measurement accuracy test case 14.5.1	18.5.0
2024-12	RAN#106	R5-247900	0925	1	F	Test Tolerance for RSTD measurement accuracy test case 14.5.2	18.5.0
2024-12	RAN#106	R5-247902	0907	1	F	Addition of test tolerance for test case cell reselection to FR1 intra-frequency NR for UE operating on a cell with less than 5MHz BW	18.5.0
2024-12	RAN#106	R5-247903	0908	1	F	Addition of test tolerance for intra-frequency handover test case when the cell is operating with less than 5MHz BW	18.5.0
2024-12	RAN#106	R5-247905	0909	1	F	Addition of Test Tolerance for SA FR2 UE Transmit Timing with 2 TAGs for multi-DCI multi-TRP operation test case	18.5.0
2024-12	RAN#106	R5-247906	0910	1	F	Addition of test tolerance for test case of NR SA FR2 MAC-CE based active uplink TCI state switch for 2 known TCI states	18.5.0
2024-12	RAN#106	R5-247909	0837	1	F	Test Tolerance for RSTD measurement period test case 14.2.1	18.5.0
2024-12	RAN#106	R5-247910	0839	1	F	Test Tolerance for FR2 Event Triggered test cases for PC1	18.5.0
2024-12	RAN#106	R5-247911	0859	1	F	TT analysis correction for RedCap test cases 16.7.3.1	18.5.0
2024-12	RAN#106	R5-247912	0917	1	F	Test Tolerance for RSTD measurement period test case 14.2.2	18.5.0
2024-12	RAN#106	R5-247913	0918	1	F	Test Tolerance for RSTD measurement accuracy test case 14.3.1	18.5.0
2024-12	RAN#106	R5-247914	0919	1	F	Test Tolerance for RSTD measurement accuracy test case 14.3.2	18.5.0
2024-12	RAN#106	R5-247926	0841	1	F	Addition of TT analysis for positioning test case 15.4.1	18.5.0
2024-12	RAN#106	R5-247927	0842	1	F	Addition of TT analysis for positioning test case 15.4.2	18.5.0
2024-12	RAN#106	R5-247928	0843	1	F	Addition of TT analysis for positioning test case 17.3.1 and 17.5.1	18.5.0
2024-12	RAN#106	R5-247929	0844	1	F	Addition of TT analysis for positioning test case 17.3.2 and 17.5.2	18.5.0

2024-12	RAN#106	R5-247930	0845	1	F	Addition of TT analysis for positioning test case 17.3.3 and 17.5.3	18.5.0
2024-12	RAN#106	R5-247931	0847	1	F	Addition of TT analysis for positioning test case 17.4.1 and 17.4.2	18.5.0
2024-12	RAN#106	R5-247932	0848	1	F	Addition of TT analysis for positioning test case 17.4.3 and 17.4.4	18.5.0
2024-12	RAN#106	R5-247963	0929	1	F	Test Tolerance analysis for SA FR1 event-triggered reporting test cases	18.5.0
2024-12	RAN#106	R5-247977	0916	1	F	Test Tolerance for FR2 re-selection test case 7.1.1.1 for PC1	18.5.0
2024-12	RAN#106	R5-247983	0846	1	F	Addition of TT analysis for positioning test case 17.3.4 and 17.5.4	18.5.0
2024-12	RAN#106	R5-247989	0869	1	F	Test Tolerances for intra-freq NR cell reselection under CCA test 11.1.1.1	18.5.0
2024-12	RAN#106	R5-247990	0870	1	F	Test Tolerance analysis for FR1 NR-U inter-freq NR cell reselection under CCA tests 11.1.1.2.	18.5.0
2024-12	RAN#106	R5-247991	0871	1	F	Test Tolerances for inter-freq NR cell reselection when serving cell under CCA test 11.1.2.1	18.5.0
2024-12	RAN#106	R5-247992	0872	1	F	Test Tolerance analysis for FR1 NR-U cell reselection with target NR carrier under CCA tests 11.1.3.1.	18.5.0
2024-12	RAN#106	R5-247993	0873	1	F	Test Tolerance analysis for FR1 NR-U cell reselection to higher priority E-UTRAN cell tests 11.1.4.1.	18.5.0
2024-12	RAN#106	R5-247994	0874	1	F	Test Tolerance analysis for FR1 NR-U cell reselection to lower priority E-UTRAN cell tests 11.1.4.2.	18.5.0
2025-03	RAN#107	R5-250206	0932	-	F	FR2 MU - MU definition for PC6 in 38.903	18.6.0
2025-03	RAN#107	R5-250483	0935	-	F	Addition of Test Tolerances analysis for A-TRS based SSB-less SCell activation test cases	18.6.0
2025-03	RAN#107	R5-250719	0941	-	F	TT analysis for RedCap RRM test cases 16.3.1.1	18.6.0
2025-03	RAN#107	R5-250939	0962	-	F	Update of FR2 EVM MU for PUCCH	18.6.0
2025-03	RAN#107	R5-251144	0964	-	F	Test Tolerance analysis for SS-SINR measurement for Satellite Access test 14.6.3.1	18.6.0
2025-03	RAN#107	R5-251145	0965	-	F	Test Tolerance analysis for inter-frequency SS-SINR Absolute and relative accuracy for Satellite Access test 14.6.3.2	18.6.0
2025-03	RAN#107	R5-251190	0971	-	F	Addition of TT analysis for NR-NTN inter-frequency test cases 14.5.2.1, 14.5.2.2 and 14.5.2.3	18.6.0
2025-03	RAN#107	R5-251191	0972	-	F	Addition of TT analysis for NR-NTN two-gap inter-frequency test cases 14.5.2.4 and 14.5.2.6	18.6.0
2025-03	RAN#107	R5-251192	0973	-	F	Addition of TT analysis for NR-NTN Radio Link Monitoring Out-of-Sync test cases 14.4.1.1, 14.4.1.3, 14.4.1.5 and 14.4.1.7	18.6.0
2025-03	RAN#107	R5-251193	0974	-	F	Addition of TT analysis for NR-NTN Radio Link Monitoring In-Sync test cases 14.4.1.2, 14.4.1.4, 14.4.1.6 and 14.4.1.8	18.6.0
2025-03	RAN#107	R5-251194	0975	-	F	Addition of TT analysis for NR-NTN intra-frequency Handover test cases 14.2.1.1, 14.2.1.3 and 14.2.1.5	18.6.0
2025-03	RAN#107	R5-251195	0976	-	F	Addition of TT analysis for NR-NTN inter-frequency Handover test cases 14.2.1.2, 14.2.1.4 and 14.2.1.6	18.6.0
2025-03	RAN#107	R5-251607	0967	1	F	Test Tolerance analysis for E-UTRA - NR FR1 cell re-selection to higher priority NR target cell under CCA test 12.1.1.1	18.6.0
2025-03	RAN#107	R5-251608	0968	1	F	Test Tolerance analysis for E-UTRA - NR FR1 handover with known target cell under CCA test 12.2.1.1	18.6.0
2025-03	RAN#107	R5-251609	0969	1	F	Test Tolerance analysis for FR1 inter-frequency cell reselection for UE fulfilling low mobility relaxed measurement criterion for Satellite Access test 14.1.9	18.6.0
2025-03	RAN#107	R5-251610	0970	1	F	Test Tolerance analysis for FR1 inter-frequency cell reselection for UE fulfilling not-at-cell edge relaxed measurement criterion for Satellite Access test 14.1.10	18.6.0
2025-03	RAN#107	R5-251632	0944	1	F	Test Tolerance for Positioning Test Case 14.2.1	18.6.0
2025-03	RAN#107	R5-251633	0945	1	F	Test Tolerance for Positioning Test Case 14.2.2	18.6.0
2025-03	RAN#107	R5-251634	0946	1	F	Test Tolerance for Positioning Test Case 16.2.1	18.6.0
2025-03	RAN#107	R5-251635	0947	1	F	Test Tolerance for Positioning Test Case 16.2.2	18.6.0
2025-03	RAN#107	R5-251636	0948	1	F	Test Tolerance for Positioning Test Case 16.3.1	18.6.0
2025-03	RAN#107	R5-251637	0955	1	F	Test Tolerance for Positioning Test Case 16.2.5	18.6.0
2025-03	RAN#107	R5-251638	0956	1	F	Test Tolerance for Positioning Test Case 16.2.6	18.6.0
2025-03	RAN#107	R5-251639	0957	1	F	Test Tolerance for Positioning Test Case 16.3.3	18.6.0
2025-03	RAN#107	R5-251640	0958	1	F	Test Tolerance for Positioning Test Case 16.4.1	18.6.0
2025-03	RAN#107	R5-251641	0959	1	F	Test Tolerance for Positioning Test Case 16.4.2	18.6.0
2025-03	RAN#107	R5-251642	0960	1	F	Test Tolerance for Positioning Test Case 16.5.1	18.6.0
2025-03	RAN#107	R5-251643	0961	1	F	Test Tolerance for Positioning Test Case 16.5.2	18.6.0
2025-03	RAN#107	R5-251647	0942	1	F	Introduce test tolerance analysis for NR UE Transmit Timing Test of Rel-18 MIMO	18.6.0
2025-03	RAN#107	R5-251650	0940	1	F	TT analysis for RedCap RRM test cases 16.1.1.1 and 16.1.1.5	18.6.0
2025-03	RAN#107	R5-251656	0943	1	F	Test Tolerance for FR2 Rel-15 Random Access Test Cases for PC1	18.6.0
2025-03	RAN#107	R5-251659	0934	1	F	Addition of TT analysis for LTM TC 6.3.4.4	18.6.0
2025-03	RAN#107	R5-251660	0936	1	F	TT analysis for TC4.5.3.4	18.6.0
2025-03	RAN#107	R5-251661	0937	1	F	TT analysis for TC4.5.6.3.1	18.6.0
2025-03	RAN#107	R5-251662	0938	1	F	TT analysis for TC4.5.6.4.1	18.6.0
2025-03	RAN#107	R5-251663	0939	1	F	TT analysis for TC4.6.6.1	18.6.0
2025-03	RAN#107	R5-251706	0977	1	F	Addition of FR2 RF testability issue list to specification	18.6.0
2025-03	RAN#107	R5-251716	0949	1	F	Test Tolerance update for Positioning Test Case 14.2.7	18.6.0

2025-03	RAN#107	R5-251717	0950	1	F	Test Tolerance for Positioning Test Case 14.4.1	18.6.0
2025-03	RAN#107	R5-251718	0951	1	F	Test Tolerance for Positioning Test Case 14.4.2	18.6.0
2025-03	RAN#107	R5-251719	0952	1	F	Test Tolerance for Positioning Test Case 15.2.5	18.6.0
2025-03	RAN#107	R5-251720	0953	1	F	Test Tolerance for Positioning Test Case 15.2.6	18.6.0
2025-03	RAN#107	R5-251721	0954	1	F	Test Tolerance for Positioning Test Case 15.2.7	18.6.0
2025-06	RAN#108	R5-251826	0981	-	F	Addition of TT analysis for NR needforgap 6.6.24.1 and 6.6.24.5	18.7.0
2025-06	RAN#108	R5-251827	0982	-	F	Addition of TT analysis for NR needforgap 6.6.24.2,6.6.24.3, and 6.6.24.4	18.7.0
2025-06	RAN#108	R5-251840	0987	-	F	Addition of TT analysis for LTM TC 7.3.4.3	18.7.0
2025-06	RAN#108	R5-251870	0992	-	F	Test Tolerance analysis for RRM Intra-frequency handover test cases in FR1 for ATG	18.7.0
2025-06	RAN#108	R5-251872	0993	-	F	Test Tolerance analysis for RRM Inter-frequency handover test cases in FR1 for ATG	18.7.0
2025-06	RAN#108	R5-252385	1005	-	F	TT analysis for TC6.5.6.5.1	18.7.0
2025-06	RAN#108	R5-252387	1006	-	F	TT analysis for TC6.6.7.1	18.7.0
2025-06	RAN#108	R5-252652	1008	-	F	TT analysis for MUSIM RRM TC 6.6.1.9 NR SA FR1 event triggered reporting with MUSIM gap configured	18.7.0
2025-06	RAN#108	R5-252653	1009	-	F	TT analysis for MUSIM RRM TC 6.6.2.13 NR SA FR1-FR1 event triggered reporting using MUSIM gap with lower and higher priority	18.7.0
2025-06	RAN#108	R5-252777	1017	-	F	Test Tolerance analysis for intra-frequency NES triggering conditional handover test case 7.3.3.3	18.7.0
2025-06	RAN#108	R5-252799	1020	-	F	Test Tolerance analysis for inter frequency NR cell reselection for Satellite Access test 14.1.5.	18.7.0
2025-06	RAN#108	R5-252967	1030	-	F	Addition of TT analysis for NR-NTN test 14.2.2.1.1	18.7.0
2025-06	RAN#108	R5-252968	1031	-	F	Addition of TT analysis for NR-NTN test 14.2.2.1.2	18.7.0
2025-06	RAN#108	R5-252969	1032	-	F	Addition of TT analysis for NR-NTN test 14.4.3.1.1	18.7.0
2025-06	RAN#108	R5-252970	1033	-	F	Addition of TT analysis for NR-NTN test 14.4.3.2.1	18.7.0
2025-06	RAN#108	R5-252971	1034	-	F	Addition of TT analysis for NR-NTN test 14.4.4.1	18.7.0
2025-06	RAN#108	R5-252972	1035	-	F	Addition of TT analysis for NR-NTN test 14.3.1.1	18.7.0
2025-06	RAN#108	R5-252973	1036	-	F	Addition of TT analysis for NR-NTN test 14.3.2.1	18.7.0
2025-06	RAN#108	R5-252974	1037	-	F	Addition of TT analysis for NR-U test 12.4.1.1	18.7.0
2025-06	RAN#108	R5-252975	1038	-	F	Addition of TT analysis for NR-U test 12.5.1.1	18.7.0
2025-06	RAN#108	R5-253528	0990	1	F	Addition of MU for RRM FR2 in case of PC6	18.7.0
2025-06	RAN#108	R5-253533	0994	1	F	FR2 MU - Editorial alignment to capture the MU for UL MIMO	18.7.0
2025-06	RAN#108	R5-253534	0995	1	F	FR2 MU - PC7 update for ACS and IBB tests in 38.903	18.7.0
2025-06	RAN#108	R5-253535	0996	1	F	FR2 MU - Update list of test cases with testability issues in 38.903	18.7.0
2025-06	RAN#108	R5-253536	0997	1	F	FR2 MU - PC3 update for OBW UL MIMO test in 38.903	18.7.0
2025-06	RAN#108	R5-253539	0978	1	F	Addition of TT analysis for LTM TC 7.6.20.1	18.7.0
2025-06	RAN#108	R5-253540	0979	1	F	Addition of TT analysis for LTM TC 7.6.21.1	18.7.0
2025-06	RAN#108	R5-253541	0980	1	F	Addition of TT analysis for LTM TC 7.7.15.1	18.7.0
2025-06	RAN#108	R5-253543	1018	1	F	Test Tolerance analysis for intra frequency NR cell reselection for Satellite Access test 14.1.1 and 14.1.2.	18.7.0
2025-06	RAN#108	R5-253544	1019	1	F	Test Tolerance analysis for intra frequency NR cell reselection for Satellite Access test 14.1.3 and 14.1.4.	18.7.0
2025-06	RAN#108	R5-253545	1021	1	F	Test Tolerance analysis for inter frequency NR cell reselection for UE configured with enhanced requirements for Satellite Access test 14.1.6.	18.7.0
2025-06	RAN#108	R5-253549	1001	1	F	TT analysis for TC5.5.3.6	18.7.0
2025-06	RAN#108	R5-253550	1002	1	F	TT analysis for TC5.5.6.5.1 and TC7.5.6.5.1	18.7.0
2025-06	RAN#108	R5-253551	1003	1	F	TT analysis for TC7.5.6.3.1	18.7.0
2025-06	RAN#108	R5-253552	1004	1	F	TT analysis for TC6.5.6.3.1	18.7.0
2025-06	RAN#108	R5-253553	1007	1	F	TT analysis for TC6.6.7.2	18.7.0
2025-06	RAN#108	R5-253555	1013	1	F	TT analysis for ATG SS-RSRP accuracy test cases 19.6.1.X	18.7.0
2025-06	RAN#108	R5-253556	1014	1	F	TT analysis for ATG SS-RSRQ accuracy test cases 19.6.2.X	18.7.0
2025-06	RAN#108	R5-253557	1015	1	F	TT analysis for ATG SS-SINR accuracy test cases 19.6.3.X	18.7.0
2025-06	RAN#108	R5-253558	0983	1	F	Addition of TT analysis for less than 5MHz TC 6.6.1.12	18.7.0
2025-06	RAN#108	R5-253559	0984	1	F	Addition of TT analysis for less than 5MHz TC 6.6.2.15	18.7.0
2025-06	RAN#108	R5-253563	1010	1	F	TT analysis for MUSIM RRM TC 6.6.2.14 NR SA FR1-FR1 event triggered reporting using MUSIM gap with shorter MGRP	18.7.0
2025-06	RAN#108	R5-253564	1011	1	F	TT analysis for RRM TC 7.6.2.20 NR SA FR2-FR2 event triggered reporting using MUSIM gap with higher priority	18.7.0
2025-06	RAN#108	R5-253566	1000	1	F	Addition of test tolerance analysis for 4.5.3.11 SCell activation of SSB-less Cell	18.7.0
2025-06	RAN#108	R5-253567	0985	1	F	Addition of TT analysis for LTM TC 7.3.4.1	18.7.0
2025-06	RAN#108	R5-253568	0986	1	F	Addition of TT analysis for LTM TC 7.3.4.2	18.7.0
2025-06	RAN#108	R5-253577	1024	1	F	Test Tolerance for R17 UE Rx-Tx time difference measurement accuracy Test Case 15.3.3	18.7.0
2025-06	RAN#108	R5-253578	1025	1	F	Test Tolerance for R17 UE Rx-Tx time difference measurement accuracy Test Case 15.3.4	18.7.0
2025-06	RAN#108	R5-253579	1026	1	F	Test Tolerance for R17 UE Rx-Tx time difference measurement accuracy Test Case 15.5.1	18.7.0
2025-06	RAN#108	R5-253580	1027	1	F	Test Tolerance for R17 UE Rx-Tx time difference measurement accuracy Test Case 15.5.2	18.7.0

2025-06	RAN#108	R5-253618	1023	1	F	Test Tolerance for NR NTN Beam failure detection and link recovery test cases	18.7.0
2025-06	RAN#108	R5-253626	1022	1	F	Test Tolerance analysis for time based and Location based measurement initiation to inter frequency NR cell reselection for Satellite Access test 14.1.7 and 14.1.8.	18.7.0
2025-06	RAN#108	R5-253631	0988	1	F	Addition of test tolerance analysis of RLM IS 6.5.1.16 test case	18.7.0
2025-06	RAN#108	R5-253632	0989	1	F	Addition of test tolerance analysis of RLM OOS for less than 5 MHz test cases	18.7.0
2025-06	RAN#108	R5-253637	0998	1	F	Addition of test tolerance analysis of the NR-DC SA FR1 CHO test case	18.7.0
2025-06	RAN#108	R5-253638	0999	1	F	Test tolerance analysis of NR-DC SA FR1 CHO with Candidate SCG test case	18.7.0
2025-06	RAN#108	-	-	-	-	editorial fixes and re-addition of "38.533 4.6.4.1+4.6.4.2+6.6.4.1+6.6.4.2 TT v5"	18.7.1
2025-07	RAN#108	-	-	-	-	deleting empty columns in tables B.3-1 et al.	18.7.2
2025-07	RAN#108	-	-	-	-	deleting redundant TT files	18.7.3
2025-09	RAN#109	R5-253718	1039	-	F	Addition of TT analysis for E-UTRAN event-triggered TC 6.6.25.1, 6.6.25.2 and 6.6.25.3	18.8.0
2025-09	RAN#109	R5-253729	1040	-	F	Addition of TT analysis for NR NTN TC 14.2.2.2.1 and 14.2.2.2.2	18.8.0
2025-09	RAN#109	R5-253799	1041	-	F	FR2 MU - PC6 MU definition for spherical tests in 38.903	18.8.0
2025-09	RAN#109	R5-253821	1043	-	F	Test Tolerance for RRM NR NTN SS-RSRP Test Case 14.6.1.1	18.8.0
2025-09	RAN#109	R5-253822	1044	-	F	Test Tolerance for RRM NR NTN SS-RSRP Test Case 14.6.1.2	18.8.0
2025-09	RAN#109	R5-253823	1045	-	F	Test Tolerance for RRM NR NTN SS-RSRQ Test Case 14.6.2.1	18.8.0
2025-09	RAN#109	R5-253824	1046	-	F	Test Tolerance for RRM NR NTN SS-RSRQ Test Case 14.6.2.2	18.8.0
2025-09	RAN#109	R5-253826	1047	-	F	Test Tolerance analysis for RRM Intra-frequency distance-based conditional Handover from FR1 to FR1 for ATG	18.8.0
2025-09	RAN#109	R5-253828	1048	-	F	Test Tolerance analysis for RRM Inter-frequency distance-based conditional Handover from FR1 to FR1 for ATG	18.8.0
2025-09	RAN#109	R5-253830	1049	-	F	Test Tolerance analysis for RRM Intra-frequency RRC Re-establishment in FR1 for ATG	18.8.0
2025-09	RAN#109	R5-253838	1051	-	F	Introduction of Test Tolerance analysis for 14.5.3.1 NR SA FR1 SSB based L1-RSRP measurement for Satellite Access	18.8.0
2025-09	RAN#109	R5-254046	1054	-	F	CR to update acronyms and symbols	18.8.0
2025-09	RAN#109	R5-254195	1055	-	F	TT analysis for new test case 6.3.3.5	18.8.0
2025-09	RAN#109	R5-254196	1056	-	F	TT analysis for new test case 6.5.12.1	18.8.0
2025-09	RAN#109	R5-254197	1057	-	F	TT analysis for new test case 6.5.12.2	18.8.0
2025-09	RAN#109	R5-254241	1058	-	F	Test Tolerance for RRM NRU Test Case 11.6.2.4	18.8.0
2025-09	RAN#109	R5-254242	1059	-	F	Test Tolerance for RRM NRU Test Case 11.6.3.4	18.8.0
2025-09	RAN#109	R5-254350	1061	-	F	Addition of test tolerance for RLM IS in non-DRX mode with less than 5M bandwidth test case	18.8.0
2025-09	RAN#109	R5-254353	1062	-	F	Updation of Test tolerance analysis of NR-DC SA FR1 CHO with Candidate SCG test case	18.8.0
2025-09	RAN#109	R5-254354	1063	-	F	Addition of Test tolerance analysis of NR-DC SA FR2 CHO with Target SCG test case	18.8.0
2025-09	RAN#109	R5-254368	1065	-	F	Addition of test tolerances analysis for TRS based SSB-less SCell activation test case	18.8.0
2025-09	RAN#109	R5-254410	1067	-	F	TT analysis for TC5.5.2.7	18.8.0
2025-09	RAN#109	R5-254412	1068	-	F	TT analysis for TC5.5.2.8	18.8.0
2025-09	RAN#109	R5-254415	1069	-	F	TT analysis for TC5.5.10.1 and TC7.5.10.1	18.8.0
2025-09	RAN#109	R5-254419	1071	-	F	TT analysis for TC7.5.2.2	18.8.0
2025-09	RAN#109	R5-254631	1076	-	F	TT analysis for RRM TC 7.6.2.21 NR SA FR2-FR2 event triggered reporting using MUSIM gap with shorter MGRP	18.8.0
2025-09	RAN#109	R5-254705	1081	-	F	Test tolerance analysis for MG enhancement NR SA FR2 event-triggered reporting test cases	18.8.0
2025-09	RAN#109	R5-254850	1082	-	F	Addition of TT analysis for NR-NTN pathloss RS switch test case 14.4.5.1	18.8.0
2025-09	RAN#109	R5-255298	1042	1	F	FR2 MU - PC3 update for OBW UL MIMO test in 38.903	18.8.0
2025-09	RAN#109	R5-255325	1050	1	F	Test Tolerance analysis for RRM Inter-frequency RRC Re-establishment in FR1 for ATG	18.8.0
2025-09	RAN#109	R5-255326	1052	1	F	TT analysis for new test case 19.2.3.3.1 NR SA FR1-FR1 RRC connection release with Redirection	18.8.0
2025-09	RAN#109	R5-255327	1074	1	F	TT analysis for ATG L1-RSRP accuracy RRM test cases 19.6.4.x	18.8.0
2025-09	RAN#109	R5-255328	1075	1	F	TT analysis for ATG L1-SINR accuracy RRM test cases 19.6.5.x	18.8.0
2025-09	RAN#109	R5-255329	1066	1	F	Revised Test Tolerances analysis for A-TRS based SSB-less SCell activation test cases	18.8.0
2025-09	RAN#109	R5-255331	1083	1	F	TT analysis separation for NR-U and legacy SCell activation and deactivation tests	18.8.0
2025-09	RAN#109	R5-255345	1053	1	F	Clarification on the applicability of re-positioning approach for QoQZ MU	18.8.0
2025-09	RAN#109	R5-255367	1077	1	F	Test Tolerance analysis for intra-frequency RACH-less Handover for Satellite Access test 14.2.1.8.	18.8.0
2025-09	RAN#109	R5-255368	1078	1	F	Test Tolerance analysis for intra-frequency RACH-based Hard Satellite switching for Satellite Access test 14.2.2.4.	18.8.0

2025-09	RAN#109	R5-255369	1079	1	F	Test Tolerance analysis for intra-frequency RACH-less Soft Satellite switching for Satellite Access test 14.2.2.5.	18.8.0
2025-09	RAN#109	R5-255370	1064	1	F	Addition of test tolerance analysis for intra-frequency HST FR2 cell re-selection test case	18.8.0
2025-09	RAN#109	R5-255376	1060	1	F	Addition of TT analysis for NR-NTN test 14.2.2.3.1	18.8.0
2025-09	RAN#109	R5-255389	1070	1	F	TT analysis for TC5.6.5.1	18.8.0
2025-09	RAN#109	-	-	-	-	Administrative release upgrade to match the release of 3GPP TS 38.521-2 which was upgraded at RAN#109 to Rel-19 due to Rel-19 relevant CR(s)	19.0.0
2025-12	RAN#110	R5-255526	1084	-	F	Addition of TT analysis for sidelink relay test case 9.1.6.3	19.1.0
2025-12	RAN#110	R5-255528	1086	-	F	Addition of TT analysis for NR NTN intra TC 14.2.3	19.1.0
2025-12	RAN#110	R5-255529	1087	-	F	Addition of TT analysis for NR NTN inter TC 14.2.4	19.1.0
2025-12	RAN#110	R5-255537	1089	-	F	Addition of test tolerance analysis of NR-DC SA FR2 CHO with candidate SCG test case	19.1.0
2025-12	RAN#110	R5-255543	1090	-	F	Addition of test tolerance analysis for UE transmit timing test case for PC6 UEs	19.1.0
2025-12	RAN#110	R5-255546	1091	-	F	Addition of test tolerance analysis for NR SA FR2 SSB-based L1-RSRP measurement test for PC6 UEs	19.1.0
2025-12	RAN#110	R5-255710	1099	-	F	Test Tolerance update for Positioning test cases 15.2.1 and 15.4.1	19.1.0
2025-12	RAN#110	R5-255711	1100	-	F	Test Tolerance for Positioning test case 15.2.2	19.1.0
2025-12	RAN#110	R5-255712	1101	-	F	Removal of duplicated attachments	19.1.0
2025-12	RAN#110	R5-256027	1104	-	F	Addition of TT analysis for 7.5.13.4.1 and 7.5.13.5.1 TCI switch	19.1.0
2025-12	RAN#110	R5-256142	1107	-	F	TT analysis for ATG L1-SINR reporting test cases 19.5.4.x	19.1.0
2025-12	RAN#110	R5-256143	1108	-	F	TT analysis for ATG CGI reporting test cases 19.5.5.1	19.1.0
2025-12	RAN#110	R5-256153	1112	-	F	TT analysis for concurrent measurement gap with NCSG test cases 6.6.23.1 and 6.6.23.2	19.1.0
2025-12	RAN#110	R5-256464	1118	-	F	TT analysis for TC7.6.2.9	19.1.0
2025-12	RAN#110	R5-256489	1120	-	F	Test Tolerance analysis for DCI based DL active BWP switch in non DRX for ATG test 19.4.3.1.1.	19.1.0
2025-12	RAN#110	R5-256490	1121	-	F	Test Tolerance analysis for RRC based DL active BWP switch in non DRX for ATG test 19.4.3.2.1.	19.1.0
2025-12	RAN#110	R5-256491	1122	-	F	Test Tolerance analysis for UE specific CBW change on PCell in non DRX for ATG test 19.4.4.1.	19.1.0
2025-12	RAN#110	R5-256492	1123	-	F	Test Tolerance analysis for MAC CE based pathloss reference signal switch delay for ATG test 19.4.5.1.	19.1.0
2025-12	RAN#110	R5-256887	1097	1	F	Documentation of MU for FR2 multi-Rx RRM test cases	19.1.0
2025-12	RAN#110	R5-256889	1092	1	F	FR2 MU - MU and relaxation update for NS_202 and NS_205 additional spurious in 38.903	19.1.0
2025-12	RAN#110	R5-256891	1114	1	F	Update of OBW MU for FR2 UL MIMO	19.1.0
2025-12	RAN#110	R5-256892	1095	1	F	FR2 MU - PC3 update for OBW UL MIMO test in 38.903	19.1.0
2025-12	RAN#110	R5-256896	1105	1	F	Introduction of Test Tolerance analysis for 14.5.3.3 NR SA FR1 CSI-RS based L1-RSRP measurement for Satellite Access	19.1.0
2025-12	RAN#110	R5-256897	1119	1	F	TT analysis for TC7.6.5.1	19.1.0
2025-12	RAN#110	R5-256901	1096	1	F	TT analysis for ATG RRM test cases 19.2.3.2.1 and 19.2.3.2.2	19.1.0
2025-12	RAN#110	R5-256902	1106	1	F	TT analysis for ATG L1-RSRP reporting test cases 19.5.3.x	19.1.0
2025-12	RAN#110	R5-256903	1109	1	F	TT analysis for ATG intra-frequency CSI-RSRP accuracy test cases 19.6.6.1.x	19.1.0
2025-12	RAN#110	R5-256904	1110	1	F	TT analysis for ATG intra-frequency CSI-RSRQ accuracy test cases 19.6.7.1	19.1.0
2025-12	RAN#110	R5-256905	1111	1	F	TT analysis for ATG intra-frequency CSI-SINR accuracy test cases 19.6.8.1	19.1.0
2025-12	RAN#110	R5-256906	1116	1	F	Test tolerance analysis for RLM OOS test cases 19.4.1.x	19.1.0
2025-12	RAN#110	R5-256907	1117	1	F	Test tolerance analysis for RLM IS test cases 19.4.1.x	19.1.0
2025-12	RAN#110	R5-256908	1088	1	F	Addition of test tolerance for beam failure detection and link recovery test case for a UE operating on a cell with 3 MHz BW	19.1.0
2025-12	RAN#110	R5-256909	1103	1	F	Addition of TT analysis for 6.5.13.1 TCI switch for mTRP mDCI	19.1.0
2025-12	RAN#110	R5-256912	1102	1	F	Addition of Test Tolerance analysis for NR NTN TC 14.1.11 and 14.1.12	19.1.0
2025-12	RAN#110	R5-256944	1113	1	F	CR to amend missing uncertainty info of B.2.2.29 for PC6	19.1.0
2025-12	RAN#110	R5-256954	1085	1	F	Addition of TT analysis for sidelink relay test case 9.1.7.1.1	19.1.0
2026-03	RAN#111	R5-260029	1129	-	F	Addition of TT analysis for positioning test case 15.3.8	19.2.0
2026-03	RAN#111	R5-260030	1130	-	F	Addition of TT analysis for SCPAC TC 7.5.18.1	19.2.0
2026-03	RAN#111	R5-260039	1132	-	F	TT analysis for ATG RRM test case 19.3.3.1	19.2.0
2026-03	RAN#111	R5-260054	1138	-	F	Updation of test tolerance and measurement uncertainty analysis for test case 6.1.1.9	19.2.0
2026-03	RAN#111	R5-260055	1139	-	F	Updation of test tolerance and measurement uncertainty analysis for test case 6.3.1.18	19.2.0
2026-03	RAN#111	R5-260056	1140	-	F	Updation of test tolerance and measurement uncertainty analysis for test case 6.5.1.13	19.2.0
2026-03	RAN#111	R5-260057	1141	-	F	Updation of test tolerance and measurement uncertainty analysis for test case 6.5.1.14	19.2.0
2026-03	RAN#111	R5-260058	1142	-	F	Updation of test tolerance and measurement uncertainty analysis for test case 6.5.1.15	19.2.0

2026-03	RAN#111	R5-260059	1143	-	F	Updation of test tolerance and measurement uncertainty analysis for test case 6.5.1.16	19.2.0
2026-03	RAN#111	R5-260064	1145	-	F	Addition of test tolerance analysis of idle mode CA/DC measurement of SCell with less than 5M bandwidth test case	19.2.0
2026-03	RAN#111	R5-260066	1146	-	F	Modification of TT analysis for FR1 SS-RSRP intra-frequency absolute measurement accuracy test cases	19.2.0
2026-03	RAN#111	R5-260667	1149	-	F	Editorial correction to Table 8-2	19.2.0
2026-03	RAN#111	R5-260825	1160	-	F	Update for Uncertainty of the Network Analyzer in FR2 RRM test cases	19.2.0
2026-03	RAN#111	R5-260826	1161	-	F	Editorial correction in E.3.5	19.2.0
2026-03	RAN#111	R5-260926	1162	-	F	Test Tolerance update for Positioning test case 16.3.1	19.2.0
2026-03	RAN#111	R5-261519	1147	1	F	Modification of TT analysis for FR1 SS-RSRP inter-frequency absolute measurement accuracy test cases	19.2.0
2026-03	RAN#111	R5-261520	1135	1	F	TT analysis for ATG RRM test cases 19.2.3.2.3 and 19.2.3.2.4	19.2.0
2026-03	RAN#111	R5-261522	1133	1	F	TT analysis for ATG RRM test case 19.4.2.1	19.2.0
2026-03	RAN#111	R5-261523	1134	1	F	TT analysis for ATG RRM test case 19.4.2.2	19.2.0
2026-03	RAN#111	R5-261525	1150	1	F	TT analysis for NR ATG RRM test case 19.6.6.2.1	19.2.0
2026-03	RAN#111	R5-261529	1156	1	F	TT analysis for NR FeMG RRM test case 6.6.22.1	19.2.0
2026-03	RAN#111	R5-261530	1157	1	F	TT analysis for NR FeMG RRM test case 6.6.22.2	19.2.0
2026-03	RAN#111	R5-261531	1158	1	F	TT analysis for NR FeMG RRM test case 6.6.23.3	19.2.0
2026-03	RAN#111	R5-261532	1159	1	F	TT analysis for NR FeMG RRM test case 8.4.3.2	19.2.0
2026-03	RAN#111	R5-261536	1166	1	F	Test tolerance analysis for the Intra-frequency measurement test cases for ATG	19.2.0
2026-03	RAN#111	R5-261537	1167	1	F	Test tolerance analysis for the Inter-frequency measurement test cases for ATG	19.2.0
2026-03	RAN#111	R5-261558	1131	1	F	TT analysis for ATG RRM test case 19.3.1.1	19.2.0
2026-03	RAN#111	R5-261562	1144	1	F	Addition of test tolerance analysis of intra-frequency FR1 deactivated PSCell measurement test with 12 PRB SSB bandwidth	19.2.0
2026-03	RAN#111	R5-261565	1164	1	F	Addition of MU terms missing for 2AoA and 3AoA FR2 MultiRx RRM	19.2.0
2026-03	RAN#111	R5-261566	1148	1	F	Clarification on the MUs definition for minimum output power test	19.2.0
2026-03	RAN#111	R5-261603	1151	1	F	TT analysis for NR ATG RRM test case 19.6.6.2.2	19.2.0
2026-03	RAN#111	R5-261604	1152	1	F	TT analysis for NR ATG RRM test case 19.6.7.2.1	19.2.0
2026-03	RAN#111	R5-261605	1153	1	F	TT analysis for NR ATG RRM test case 19.6.7.2.2	19.2.0
2026-03	RAN#111	R5-261606	1154	1	F	TT analysis for NR ATG RRM test case 19.6.8.2.1	19.2.0
2026-03	RAN#111	R5-261607	1155	1	F	TT analysis for NR ATG RRM test case 19.6.8.2.2	19.2.0
2026-03	RAN#111	R5-261664	1125	1	F	Addition of TT analysis for positioning test case 15.2.11	19.2.0
2026-03	RAN#111	R5-261665	1126	1	F	Addition of TT analysis for positioning test case 15.2.12	19.2.0
2026-03	RAN#111	R5-261666	1127	1	F	Addition of TT analysis for positioning test case 15.2.13	19.2.0
2026-03	RAN#111	R5-261667	1128	1	F	Addition of TT analysis for positioning test case 15.3.7	19.2.0
2026-03	RAN#111	R5-261668	1136	1	F	Adding TT analysis for NR positioning test case 14.2.11	19.2.0
2026-03	RAN#111	R5-261669	1137	1	F	Adding TT analysis for NR positioning test case 14.3.9	19.2.0
2026-03	RAN#111	R5-261678	1165	1	F	Test tolerance analysis for FR2 inter-frequency SSB-based L1-RSRP measurement test case 7.6.22.1	19.2.0
2026-03	RAN#111	R5-261679	1163	1	F	Test Tolerance for RRM NR-NTN Event Triggered Test Cases without gap	19.2.0
2026-06	RAN#112	R5-261718	1168	-	F	Addition of TT analysis for SCPAC TC 7.5.18.2	19.3.0
2026-06	RAN#112	R5-261744	1169	-	F	Addition of TT analysis for eEMR and IMR test cases 7.6.23.1 and 7.6.23.2	19.3.0
2026-06	RAN#112	R5-261747	1170	-	F	Addition of TT analysis for IMR test cases 7.6.23.3	19.3.0
2026-06	RAN#112	R5-262416	1198	-	F	Test tolerance analysis for NR SA FR2 RACH-based intra-frequency LTM PSCell switch test case 7.3.5.1	19.3.0
2026-06	RAN#112	R5-262419	1201	-	F	Test tolerance analysis for event-triggered reporting test case 7.6.18.1	19.3.0
2026-06	RAN#112	R5-262694	1202	-	F	Test Tolerance analysis for SS SINR measurement for Satellite Access test 14.6.3.1	19.3.0
2026-06	RAN#112	R5-262695	1203	-	F	Test Tolerance analysis for SS SINR measurement for Satellite Access test 14.6.3.2	19.3.0
2026-06	RAN#112	R5-262696	1204	-	F	Test Tolerance analysis for L1 RSRP Absolute and relative accuracy for Satellite Access test 14.6.4.1 and 14.6.4.2	19.3.0
2026-06	RAN#112	R5-262786	1205	-	F	Addtion of TT analysis for FR2 multi-Rx RLM test cases	19.3.0
2026-06	RAN#112	R5-262787	1206	-	F	Addtion of TT analysis for FR2 multi-Rx test case 7.5.5.14	19.3.0
2026-06	RAN#112	R5-262788	1207	-	F	Addtion of TT analysis for FR2 multi-Rx test case 7.5.16	19.3.0
2026-06	RAN#112	R5-263056	1194	2	F	Test tolerance analysis for NR SA FR1 RACH-based intra-frequency LTM PSCell switch test case 6.3.5.1	19.3.0
2026-06	RAN#112	R5-263057	1195	2	F	Test tolerance analysis for NR SA FR1 Idle mode fast CADC tests 6.6.9.2 and 6.6.9.3	19.3.0
2026-06	RAN#112	R5-263227	1196	1	F	Test tolerance analysis for NR SA FR1 Idle mode fast CADC test 6.6.9.4	19.3.0
2026-06	RAN#112	R5-263230	1200	1	F	Test tolerance analysis for event-triggered reporting test case 7.6.17.2	19.3.0
2026-06	RAN#112	R5-263231	1199	1	F	Test tolerance analysis for event-triggered reporting test case 7.6.17.1	19.3.0
2026-06	RAN#112	R5-263233	1174	1	F	Addition of TT analysis for positioning test case 15.4.5	19.3.0

2026-06	RAN#112	R5-263234	1187	1	F	Completion of test tolerance analysis for 5 MHz FR1 event triggered reporting test case	19.3.0
2026-06	RAN#112	R5-263235	1186	1	F	Addition of test tolerance analysis for less than 5MHz SCell activation and deactivation test case	19.3.0
2026-06	RAN#112	R5-263236	1177	1	F	TT analysis for ATG intra-frequency cell reselection test case 19.1.1	19.3.0
2026-06	RAN#112	R5-263237	1178	1	F	TT analysis for ATG inter-frequency cell reselection test case 19.1.2	19.3.0
2026-06	RAN#112	R5-263238	1179	1	F	TT analysis for ATG inter-frequency cell reselection test case 19.1.3	19.3.0
2026-06	RAN#112	R5-263246	1175	1	F	Addition of TT analysis for positioning test case 15.4.6	19.3.0
2026-06	RAN#112	R5-263250	1188	1	F	MU factors definition and MTSU calculation for the 2AoA spherical coverage testing	19.3.0
2026-06	RAN#112	R5-263251	1208	1	F	Update for FR2 multi-Rx RRM MU	19.3.0
2026-06	RAN#112	R5-263255	1189	1	F	MU factors definition and MTSU calculation for the 2AoA TRP and EIRP measurement	19.3.0
2026-06	RAN#112	R5-263258	1197	1	F	Test tolerance analysis for NR SA FR1 Intra-frequency subsequent CPC from FR1-FR1 NR-DC to FR1-FR1 NR-DC with 12 PRB SSB bandwidth test case 6.5.12.3	19.3.0
2026-06	RAN#112	R5-263309	1184	1	F	Addition of test tolerance analysis of inter-frequency cell reselection test case for PC6	19.3.0
2026-06	RAN#112	R5-263361	1190	1	F	Test Tolerance update for RRM NR-NTN SS-RSRP test case 14.6.1.1	19.3.0
2026-06	RAN#112	R5-263362	1191	1	F	Test Tolerance update for RRM NR-NTN SS-RSRP test case 14.6.1.2	19.3.0
2026-06	RAN#112	R5-263363	1192	1	F	Test Tolerance update for RRM NR-NTN SS-RSRQ test case 14.6.2.1	19.3.0
2026-06	RAN#112	R5-263364	1193	1	F	Test Tolerance update for RRM NR-NTN SS-RSRQ test case 14.6.2.2	19.3.0
2026-06	RAN#112	R5-263387	1171	1	F	Addition of TT analysis for positioning test cases 15.2.14, 15.2.16 and 15.4.8	19.3.0
2026-06	RAN#112	R5-263388	1172	1	F	Addition of TT analysis for positioning test cases 15.3.9 and 15.5.7	19.3.0
2026-06	RAN#112	R5-263389	1173	1	F	Addition of TT analysis for positioning test cases 15.3.10, 15.3.12, 15.5.8 and 15.5.10	19.3.0
2026-06	RAN#112	R5-263390	1176	1	F	Addition of TT analysis for positioning test case 15.4.7	19.3.0

History

Version	Date	Status
V19.0.0	October 2025	Publication
V19.1.0	February 2026	Publication
V19.2.0	April 2026	Publication
V19.3.0	July 2026	Publication