

Assignment:-5

Task 1:- A user reports their laptop won't power on even when plugged in. List 5 troubleshooting steps you would take to diagnose the cause, and for each step, explain what you are checking for

Laptop Not Turning On –

1. Check the power socket – Plug another device into it to see if it has power.
2. Check the charger – Look for broken wires or other damage.
3. Check the charging port – Make sure it is clean and not loose or damaged.
4. Reset the laptop – Unplug the charger, remove the battery if possible, hold the power button for 15–20 seconds, then connect the charger again.
5. Try another charger – Use a working, compatible charger to check if the original charger is faulty.

Task 2:- You receive a helpdesk ticket: 'My monitor is showing a blank screen, but the CPU seems to be running.' Write a step-by-step troubleshooting flow you would follow to identify and resolve the issue. Consider checking both hardware connections and basic display settings.

- Check the monitor power

Make sure the monitor is turned on and the power light is on.

- Check the display cable

Make sure the HDMI, DisplayPort, or VGA cable is connected properly to the PC and monitor.

- Check the correct input

Use the monitor buttons to select the correct input, such as HDMI or DisplayPort.

- Check the PC connection

If the PC has a separate GPU, make sure the display cable is connected to the GPU, not the motherboard port.

- Restart the PC

Turn off the PC, wait a few seconds, and turn it on again.

- Try another cable or monitor

Use a working cable or another monitor to find out whether the problem is with the monitor or PC.

- Check display settings

If the display works, check the Windows display settings and make sure the correct monitor and screen resolution are selected.

- Check the RAM/GPU

If there is still no display, check that the RAM and graphics card are properly connected.

Task 3 A user complains that their wireless mouse is unresponsive, but the keyboard works fine. Describe how you would isolate whether the issue is with the mouse, the USB port, or the system settings.

Wireless Mouse Not Working

1. Check the mouse battery – Replace the battery or charge the mouse.
2. Check the USB receiver – Remove and plug the mouse receiver into the USB port again.
3. Try another USB port – If the mouse works, the first USB port may have a problem.
4. Test the mouse on another PC – If it does not work there either, the mouse may be faulty.
5. Check system settings – Make sure the mouse is detected and enabled in Windows settings.
6. Restart the PC – Restart the computer and test the mouse again.

Task 4:- Imagine you are working on a helpdesk team for a gaming cafe. One system is overheating and shutting down during use. List 3 possible hardware causes and describe how you would check each one Think about fans, dust, and thermal paste.

Gaming PC Overheating – 3 Possible Causes

1. Fan not working
 - Check: Turn on the PC and see if the CPU/GPU fans are spinning.
 - Problem: A stopped or slow fan cannot cool the PC properly.
2. Dust inside the PC
 - Check: Open the case and look for dust on the fans, heatsink, and air vents.
 - Problem: Dust blocks airflow and causes overheating.
3. Old or dry thermal paste
 - Check: Check the thermal paste between the CPU and CPU cooler.
 - Problem: Old or dry paste does not transfer heat properly. Replace it with new thermal paste.