

Continuous cloud position spectroscopy using a magneto-optical trap

Benedikt Heizenreder [1, *] Ananya Sitaram [1, *] Sana Boughdachi [1, 2] Andrew von Hörsten [2] Yan Xie [3] Andreas Brodschelm [2] and Florian Schreck [1, 4, †]

[1] *Van der Waals-Zeeman Institute, Institute of Physics, University of Amsterdam, Science Park 904, 1098 XH Amsterdam, The Netherlands*
[2] *Toptica Photonics SE, Lochhamer Schlag 19, 82166 Gräfelfing, Germany*
[3] *VSL National Metrology Institute, Thijssweg 11, 2629 JA Delft, The Netherlands*
[4] *QuSoft, Science Park 123, 1098 XG Amsterdam, The Netherlands*

(Dated: September 10, 2025)

We demonstrate a continuous spectroscopy technique with frequency sensitivity well below the natural transition linewidth, while maintaining a locking range hundreds of times larger. The method exploits the position dependence of a continuous, broadband magneto-optical trap operating on the 7.5 kHz-wide intercombination line of strontium. We show that the frequency sensitivity is fundamentally insensitive to the effective MOT laser linewidth. By applying active feedback on the MOT position to a dispersion-optimized frequency comb, which serves as the reference for stabilizing the MOT laser [1], we achieve a frequency instability below 4.4×10^{-13} after 400 s of averaging in both the optical and radio-frequency domains, surpassing the performance of conventional hot-vapor modulation transfer spectroscopy. Our method is a broadly applicable alternative route to long-term frequency references in the high 10^{-14} range around 100 s.

arXiv:2509.07736v1 [physics.atom-ph] 9 Sep 2025

Continuously operating atomic clocks, such as hydrogen masers in the RF domain [2, 3], and systems employing modulation transfer spectroscopy in the optical domain [4–7], have demonstrated frequency stability on the order of $\sim 10^{-14}$ after 100 s of averaging [4–8]. Recent advances have enabled the development of compact, field-deployable optical atomic clocks, including systems based on tetrahedral and pyramidal magneto-optical traps (MOTs) [9–11], microcell-based clocks [12, 13], and vapor-based clocks [14, 15]. While modulation transfer spectroscopy remains widely used in these systems, it is limited by short-term probe laser instability and a narrow frequency locking range, both typically on the order of the transition linewidth [16, 17]. These limitations are especially pronounced for narrow-line optical transitions, such as those found in the alkaline-earth and alkaline-earth-like atoms. Additionally, modulation transfer spectroscopy does not provide direct access to the RF domain.

In this Letter, we present a simple, continuous spectroscopy technique that exploits the dependence of the MOT position along the vertical axis (gravity) on the MOT laser frequency in a five-beam configuration. We demonstrate that this method improves both the frequency locking range and tolerance to short-term probe laser instability by two orders of magnitude compared to the natural linewidth, while simultaneously achieving a spectral resolution more than an order of magnitude below the 7.5 kHz natural linewidth of the strontium intercombination transition. By applying active feedback based on the MOT position to a dispersion-optimized frequency comb, used for stabilizing the MOT laser, we extract both an 800 MHz RF reference and an optical reference at 689 nm, reducing frequency instabilities below 4.4×10^{-13} after 400 s of averaging. Finally, we demonstrate that this technique can outperform modulation transfer spectroscopy with hot atomic vapors in terms of long-term frequency stability on the same transition.

Theory. To model the vertical dynamics of the five-beam MOT, where in comparison to a standard MOT the sixth beam propagating in gravity direction is removed [1], we consider the balance between gravitational force mg and optical force along the vertical axis for a single atom with mass m [18]. The resulting steady-state condition determines the MOT position as a function of laser detuning and magnetic field gradient [19, 20]. For strontium, using the $^1S_0 \rightarrow {}^3P_1$ intercombination line at 689 nm with a narrow linewidth of $\gamma_0 = 2\pi \cdot 7.5$ kHz, power broadening alone is insufficient to achieve large capture velocities. Instead, frequency modulation is used to extend the effective capture range by more than an order of magnitude. While this "broadband (BB) MOT" technique increases the capture velocities, it cannot be modeled simply as a power-broadened single-frequency (SF) light force. In our implementation, the RF drive of an acousto-optic modulator (AOM) is modulated from δ_{start} to $\delta_{\text{start}} - 2\pi f_{\text{bandwidth}}$, where $f_{\text{bandwidth}}$ is the modulation bandwidth. In the low-saturation regime (see Appendix A 4), the total force in the vertical direction is:

$$F_{\text{total}} = mg - \frac{\hbar k \gamma_0 I_{\text{total}}}{2I_0} \sum_{i=0}^{n} \frac{\alpha_i}{1 + (2\delta_i/\gamma_0)^2}, \qquad (1)$$

where

$$\delta_i = \delta_{\text{start}} - i2\pi f_{\text{mod}} \mp kv - \frac{\mu_B g_J B(z)}{\hbar}, \qquad (2)$$

where $n = f_{\text{bandwidth}}/f_{\text{mod}}$ where f_{mod} is the modulation frequency, $\sum_{i=0}^{n} \alpha_i = 1$ are the relative intensities of the ith frequency component and I_0 the saturation intensity. For $m_J = \pm 1$ of this transition, the Zeeman

* These authors contributed equally to this work.
† CloudPositionSpectroscopy@strontiumBEC.com