


Many-body strategies for multi-qubit gates - quantum control through Krawtchouk chain dynamics

Koen Groenland[1, 2, 3] and Kareljan Schoutens[1, 2]

[1] *QuSoft, Science Park 123, 1098 XG Amsterdam, the Netherlands*
[2] *Inst. of Physics, Univ. of Amsterdam, Science Park 904, 1098 XH Amsterdam, the Netherlands*
[3] *CWI, Science Park 123, 1098 XG Amsterdam, the Netherlands*

(Dated: April 18, 2018)

We propose a strategy for engineering multi-qubit quantum gates. As a first step, it employs an *eigengate* to map states in the computational basis to eigenstates of a suitable many-body Hamiltonian. The second step employs resonant driving to enforce a transition between a single pair of eigenstates, leaving all others unchanged. The procedure is completed by mapping back to the computational basis. We demonstrate the strategy for the case of a linear array with an even number N of qubits, with specific $XX + YY$ couplings between nearest neighbors. For this so-called Krawtchouk chain, a 2-body driving term leads to the iSWAP$_N$ gate, which we numerically test for $N = 4$ and 6.

arXiv:1707.05144v3 [quant-ph] 18 Apr 2018

I. INTRODUCTION

The universality of the CNOT plus all 1-qubit gates guarantees that all N-qubit unitaries can be composed out of elementary 1-qubit and 2-qubit gates [1]. Nevertheless, the construction of specific multi-qubit gates, such as an N-Toffoli gate (a NOT controlled by $N-1$ control qubits) can be cumbersome. As an example, the $N = 4$ Toffoli gate employed in a recent implementation of Grover's search algorithm in a trapped ion architecture [2] employed 11 2-qubit gates derived from the native XX coupling, and 22 1-qubit gates.

This work proposes an approach towards building N-qubit gates which avoids a decomposition into 1-qubit and 2-qubit building blocks. What we propose instead is a protocol which enforces N-qubit gates through resonant driving of eigenstates in a suitably engineered quantum many-body spectrum. At first sight such an approach seems hard to achieve. One needs

- an efficient quantum circuit to construct the eigenstates,
- a driving term (preferably of 1-qubit or 2-qubit nature) that is resonant with a small number of transitions between eigenstates, and
- a way to keep dynamical phases in check, either by tuning the spectrum such that all phases vanish after a known time, or by inverting the spectrum halfway through the protocol.

We here demonstrate how all this can be made to work in the specific setting of a qubit chain with 2-qubit couplings of $XX+YY$ type and adjustable 1-qubit terms. Tuning the couplings to those of the so-called Krawtchouk chain guarantees that the 1-body eigenvalues are all (half-)integer, and the existence of a Jordan-Wigner mapping to non-interacting fermions implies that this property extends to the many-body spectrum. The particular group-theoretic structure of the Krawtchouk operators (which form an **so**(3) angular momentum algebra) provides the key for the construction of an efficient quantum circuit for a *Krawtchouk eigengate* mapping computational states to eigenstates. Finally, the non-local relation between the qubits and the fermion degrees of freedom implies that a driving term involving one or two qubits can connect eigenstates with Hamming distance N. By driving resonant to the transition energy, we construct a gate we call iSWAP$_N$, which (for N even) maps states $|1^{\frac{N}{2}}0^{\frac{N}{2}}\rangle$ and $|0^{\frac{N}{2}}1^{\frac{N}{2}}\rangle$ onto each other with a phase factor i, and acts as identity on all other states. In Appendix A we explain how this gate can be efficiently mapped to more conventional gates, such as a NOT- or iSWAP$_2$-gate with $N-2$ controls.

The remainder of this paper is devoted to this specific example. We stress however, that many variations on the general strategy outlined in the above are possible.

A. Resonant driving

The prototypical example for resonant driving is a 2-level system with Hamiltonian

$$H_D(t) = \begin{pmatrix} E_1 & A\,e^{i\omega t} \\ A\,e^{-i\omega t} & E_2 \end{pmatrix}, \tag{1}$$

where we assume that the driving amplitude A is real and positive. We denote by U_D the unitary evolution of quantum states according to Schrödinger's equation after a specific time τ. For resonant driving, $\omega = E_2 - E_1$, an $H_D(t)$ pulse of duration $\tau_D = \pi/(2A)$ executes the gate $U_D = -iX$ and thus drives the transitions $1 \leftrightarrow 2$ without any error. Off resonance, with $A \ll \Delta = |\omega - (E_2 - E_1)|$, the time-evolution stays close to the identity. Putting again $\tau_D = \pi/(2A)$, and assuming that both $\tau_D(E_2 - E_1)/(2\pi)$ and $\tau_D\Delta/(2\pi)$ are integers, one finds that the