

Scraftie — Installation & Initial Build

Scraftie — Personal Music Streaming Server • Initial Build Documentation

Scraftie Installation and Initial Build Record

This document records the initial construction of Scraftie from an older HP laptop into a functioning private music streaming server.

This is a historical build record. It intentionally records mistakes and troubleshooting rather than presenting a clean-room installation procedure.

1. Server Hardware

Model: HP 15-da0037nr

The exact CPU, RAM, storage-device model/capacity, networking hardware, and original operating system were not established in the retained build record and are therefore not reproduced here.

2. Operating System

Scraftie runs:

```
Debian 13  
x86_64
```

The running kernel was verified as:

```
Linux Scraftie 6.12.107+deb13-amd64
```

A desktop/GNOME environment was accidentally installed during the initial setup. GNOME was temporarily retained because it was useful during setup and troubleshooting.

The long-term plan is to remove the desktop environment and operate Scraftie as a fully headless server.

The exact Debian installer ISO filename and checksum were not retained in the available build record and are therefore not documented.

3. Debian User and Sudo

The primary administration user was:

```
cprquecian
```

An initial problem occurred where the user did not have expected sudo access.

A root shell was used to correct the account.

The user was added to Debian's sudo group:

```
usermod -aG sudo cprquecian
```

The user then logged out/reconnected or rebooted so the new group membership applied.

Sudo access subsequently worked.

4. Music Library Migration

The original music directory:

```
OG SD Card
```

was renamed to:

```
OG_SD_Card
```

The server music directory was created:

```
sudo mkdir -p /music
```

The final server library path is:

```
/music/OG_SD_Card
```

Verification:

```
find /music/OG_SD_Card -type f | wc -l
```

Result:

```
4669
```

Size:

```
du -sh /music/OG_SD_Card
```

Result:

5. Master Copy

The Samsung T7 Shield retains the original/master music copy.

The server maintains its own copy under:

```
/music/OG_SD_Card
```

The T7 is intentionally retained as the master so the server is not the only copy.

6. Navidrome Installation

The first installation/download attempt returned:

```
HTTP 404
```

The Navidrome GitHub release API was investigated.

Architecture was determined with:

```
uname -m
```

The required architecture was:

```
amd64
```

The appropriate Debian amd64 Navidrome package was then identified and installed.

7. Navidrome Directories and Configuration

Navidrome uses:

```
/opt/navidrome  
/var/lib/navidrome  
/etc/navidrome/navidrome.toml
```

Configuration:

```
DataFolder = "/var/lib/navidrome"  
MusicFolder = "/music/OG_SD_Card"
```

A dedicated system account named navidrome was created.

8. First Navidrome Failure

Initial startup failed with:

```
Error disabling foreign_keys
unable to open database file: no such file or directory
Database could not be opened!
```

The missing/unavailable Navidrome data directory was the cause identified during the build.

9. Navidrome Fix

```
sudo mkdir -p /var/lib/navidrome
sudo chown -R navidrome:navidrome /var/lib/navidrome
sudo chown -R navidrome:navidrome /music/OG_SD_Card
sudo systemctl restart navidrome
```

Navidrome subsequently became active and scanned the library.

The web interface opened successfully and an administrator account was created. The password is intentionally omitted.

10. SSH

OpenSSH was installed and the SSH service was enabled and tested.

Administration is performed from Fedora.

Connection format:

```
ssh cprquecian@<SCARFTIE_TAILSCALE_IP>
```

The real Tailscale address is omitted.

A remote shell can be closed with:

```
exit
```

or:

```
Ctrl+D
```

A remote reboot terminates the SSH connection while the server restarts. SSH can be re-established after boot.

11. Tailscale

Tailscale was configured on:

- Scraftie
- Fedora
- Motorola Edge+ 2023

The daemon was enabled and Tailscale was brought online:

```
tailscale up
```

Connectivity was tested:

```
tailscale ping <SCARFTIE_TAILSCALE_IP>
```

The result was a successful pong.

SSH over Tailscale was verified.

12. Android Streaming

The Motorola Edge+ 2023 used Ultrasonic.

Navidrome playback was successfully verified.

Wi-Fi was then disabled and music continued playing over cellular data through Tailscale.

This proved the server was remotely reachable rather than merely functioning on local Wi-Fi.

13. Lid Behavior

Closing the laptop lid initially caused the server to stop responding over Tailscale.

/etc/systemd/logind.conf initially contained commented settings:

```
#HandleLidSwitch=ignore
#HandleLidSwitchExternalPower=ignore
#HandleLidSwitchDocked=ignore
```

The intended settings became:

```
HandleLidSwitch=ignore
HandleLidSwitchExternalPower=ignore
HandleLidSwitchDocked=ignore
LidSwitchIgnoreInhibited=yes
```

14. GNOME Power Management

The expected GNOME key:

```
lid-close-ac-action
```

did not exist.

The error was:

```
No such key "lid-close-ac-action"
```

Available power-management keys were inspected:

```
gsettings list-keys org.gnome.settings-daemon.plugins.power
```

Relevant keys included:

```
sleep-inactive-ac-timeout
sleep-inactive-ac-type
sleep-inactive-battery-timeout
sleep-inactive-battery-type
```

The initial AC inactivity configuration was:

```
sleep-inactive-ac-type = 'suspend'
sleep-inactive-ac-timeout = 900
```

The final change was:

```
gsettings set org.gnome.settings-daemon.plugins.power sleep-inactive-ac-type 'nothing'
```

Verification:

```
gsettings get org.gnome.settings-daemon.plugins.power sleep-inactive-ac-type
```

Result:

```
'nothing'
```

The gsettings change takes effect immediately and does not require a reboot.

15. Current State

At the end of the initial build:

- Debian 13 is running.

- Scraftie is reachable through Tailscale.
- SSH administration works.
- Navidrome is active.
- The music library is available to Navidrome.
- Android/Ultrasonic playback works.
- Cellular playback through Tailscale was verified.
- Lid-close/power behavior was configured.
- GNOME remains installed.
- A fully headless conversion remains future work.