Registers for aic8818_hard

April 2, 2022

1 INT_ROM

1.1 boot rom				0x00000000
S.NO.	Count	0	1	81919
0	boot rom	0x00000000	0x00000004	0x0004FFFC

2 INT_BTROM

2.1 bt rom				0x00050000
S.NO.	Count	0	1	98303
0	bt rom	0x00050000	0x00050004	0x000AFFFC

3 INT_SRAM0

3.1 int sram0				0x00100000
S.NO.	Count	0	1	16383
0	int sram0	0x00100000	0x00100004	0x0010FFFC

4 INT_SRAM1

4.1 int sram1				0x00110000
S.NO.	Count	0	1	16383
0	int sram1	0x00110000	0x00110004	0x0011FFFC

5 INT_SRAM2

5.1 int sram2				0x00120000
S.NO.	Count	0	1	16383
0	int sram2	0x00120000	0x00120004	0x0012FFFC

6 INT_SRAM3

6.1 int sram3				0x00130000
S.NO.	Count	0	1	16383
0	int sram3	0x00130000	0x00130004	0x0013FFFC

7 INT_SRAM4

7.1 int sram4				0x00140000
S.NO.	Count	0	1	32767
0	int sram4	0x00140000	0x00140004	0x0015FFFC

8 INT_SRAM5

8.1 int sram5				0x00160000
S.NO.	Count	0	1	32767
0	int sram5	0x00160000	0x00160004	0x0017FFFC

9 INT_SHARED_CACHE_SRAM

9.1 int shared_cache_sram				0x00180000
S.NO.	Count	0	1	8191
0	int shared_cache_sram	0x00180000	0x00180004	0x00187FFC

10 INT_BTRAM

10.1 bt ram				0x00188000
S.NO.	Count	0	1	16383
0	bt ram	0x00188000	0x00188004	0x00197FFC

11 FLASH_MEM

11.1 flash_mem				0x04000000
S.NO.	Count	0	1	16777215
0	flash_mem	0x04000000	0x04000004	0x07FFFFFC

12 FLASH_CACHE_MEM

12.1 flash_cache_mem				0x08000000
S.NO.	Count	0	1	16777215
0	flash_cache_mem	0x08000000	0x08000004	0x0BFFFFFC

13 cache

13.1 BUS_CFG0				0x40000000
Bits	Field Name	Acc	Default	Description
0	rf_blk_cache_en0	rw	0x0	0: block 0 cache disabled 1: block 0 cache enabled
1	rf_blk_cache_en1	rw	0x0	0: block 1 cache disabled 1: block 1 cache enabled
2	rf_blk_cache_en2	rw	0x0	0: block 2 cache disabled 1: block 2 cache enabled
3	rf_blk_cache_en3	rw	0x0	0: block 3 cache disabled 1: block 3 cache enabled
4	rf_blk_cache_en4	rw	0x1	0: block 4 cache disabled 1: block 4 cache enabled
5	rf_blk_cache_en5	rw	0x1	0: block 5 cache disabled 1: block 5 cache enabled
6	rf_blk_cache_en6	rw	0x1	0: block 6 cache disabled 1: block 6 cache enabled

7	rf_blk_cache_en7	rw	0x1	0: block 7 cache disabled 1: block 7 cache enabled
8	rf_blk_remap_en0	rw	0x0	0: block 0 cache remap disabled 1: block 0 cache remap enabled
9	rf_blk_remap_en1	rw	0x0	0: block 1 cache remap disabled 1: block 1 cache remap enabled
10	rf_blk_remap_en2	rw	0x0	0: block 2 cache remap disabled 1: block 2 cache remap enabled
11	rf_blk_remap_en3	rw	0x0	0: block 3 cache remap disabled 1: block 3 cache remap enabled
12	rf_blk_remap_en4	rw	0x1	0: block 4 cache remap disabled 1: block 4 cache remap enabled
13	rf_blk_remap_en5	rw	0x1	0: block 5 cache remap disabled 1: block 5 cache remap enabled
14	rf_blk_remap_en6	rw	0x1	0: block 6 cache remap disabled 1: block 6 cache remap enabled
15	rf_blk_remap_en7	rw	0x1	0: block 7 cache remap disabled 1: block 7 cache remap enabled
16	rf_blk_prot_en0	rw	0x0	0: block 0 protect disabled or access permitted 1: block 0 protect enabled or access forbidden
17	rf_blk_prot_en1	rw	0x0	0: block 1 protect disabled or access permitted 1: block 1 protect enabled or access forbidden
18	rf_blk_prot_en2	rw	0x0	0: block 2 protect disabled or access permitted 1: block 2 protect enabled or access forbidden
19	rf_blk_prot_en3	rw	0x0	0: block 3 protect disabled or access permitted 1: block 3 protect enabled or access forbidden
20	rf_blk_prot_en4	rw	0x0	0: block 4 protect disabled or access permitted 1: block 4 protect enabled or access forbidden
21	rf_blk_prot_en5	rw	0x0	0: block 5 protect disabled or access permitted 1: block 5 protect enabled or access forbidden
22	rf_blk_prot_en6	rw	0x0	0: block 6 protect disabled or access permitted 1: block 6 protect enabled or access forbidden
23	rf_blk_prot_en7	rw	0x0	0: block 7 protect disabled or access permitted 1: block 7 protect enabled or access forbidden

13.2 BUS_CFG1				0x40000004
Bits	Field Name	Acc	Default	Description
28 : 13	rf_blk_base_addr1	rw	0x0	block 1 start address

13.3 BUS_CFG2				0x40000008
Bits	Field Name	Acc	Default	Description
28 : 13	rf_blk_base_addr2	rw	0x0	block 2 start address

13.4 BUS_CFG3				0x4000000C
Bits	Field Name	Acc	Default	Description
28 : 13	rf_blk_base_addr3	rw	0x0	block 3 start address

13.5 BUS_CFG4				0x40000010
Bits	Field Name	Acc	Default	Description
28 : 13	rf_blk_base_addr4	rw	0x4000	block 4 start address

13.6 BUS_CFG5				0x40000014
Bits	Field Name	Acc	Default	Description
28 : 13	rf_blk_base_addr5	rw	0x4000	block 5 start address

13.7 BUS_CFG6	0x40000018

Bits	Field Name	Acc	Default	Description
28 : 13	rf_blk_base_addr6	rw	0x4000	block 6 start address

13.8 BUS_CFG7				0x4000001C
Bits	Field Name	Acc	Default	Description
28 : 13	rf_blk_base_addr7	rw	0x4000	block 7 start address

13.9 BUS_REMAP0				0x40000020
Bits	Field Name	Acc	Default	Description
31 : 12	rf_blk0_remap_offset	rw	0x0	block 0 remap offset when the block 0 remap function is enabled. The address after remap will be original addr + rf_blk0_remap_offset

13.10 BUS_REMAP1				0x40000024
Bits	Field Name	Acc	Default	Description
31 : 12	rf_blk1_remap_offset	rw	0x0	block 1 remap offset when the block 1 remap function is enabled. The address after remap will be original addr + rf_blk1_remap_offset

13.11 BUS_REMAP2				0x40000028
Bits	Field Name	Acc	Default	Description
31 : 12	rf_blk2_remap_offset	rw	0x0	block 2 remap offset when the block 2 remap function is enabled. The address after remap will be original addr + rf_blk2_remap_offset

13.12 BUS_REMAP3				0x4000002C
Bits	Field Name	Acc	Default	Description
31 : 12	rf_blk3_remap_offset	rw	0x0	block 3 remap offset when the block 3 remap function is enabled. The address after remap will be original addr + rf_blk3_remap_offset

13.13 BUS_REMAP4				0x40000030
Bits	Field Name	Acc	Default	Description
31 : 12	rf_blk4_remap_offset	rw	0xFC000	block 4 remap offset when the block 4 remap function is enabled. The address after remap will be original addr + rf_blk4_remap_offset

13.14 BUS_REMAP5				0x40000034
Bits	Field Name	Acc	Default	Description
31 : 12	rf_blk5_remap_offset	rw	0xFC000	block 5 remap offset when the block 5 remap function is enabled. The address after remap will be original addr + rf_blk5_remap_offset

13.15 BUS_REMAP6				0x40000038
Bits	Field Name	Acc	Default	Description
31 : 12	rf_blk6_remap_offset	rw	0xFC000	block 6 remap offset when the block 6 remap function is enabled. The address after remap will be original addr + rf_blk6_remap_offset

13.16 BUS_REMAP7				0x4000003C
Bits	Field Name	Acc	Default	Description
31 : 12	rf_blk7_remap_offset	rw	0xFC000	block 7 remap offset when the block 7 remap function is enabled. The address after remap will be original addr + rf_blk7_remap_offset

13.17 CACHE_CFG0				0x40000040
Bits	Field Name	Acc	Default	Description
1 : 0	rf_write_mode	rw	0x0	cache write operation mode: 2b00: write through 2b01: write back, no write allocate 2b10: write back, write allocate
5 : 2	rf_hprot_byp	rw	0x0	Bit [5]: 1b1: hprot[3] from CM4 go through cache controller without modification 1b0: hprot[3] is provided by cache controller register Bit [4]: 1b1: hprot[2] from CM4 go through cache controller without modification 1b0: hprot[2] is provided by cache controller register Bit [3]: 1b1: hprot[1] from CM4 go through cache controller without modification 1b0: hprot[1] is provided by cache controller register Bit [2]: 1b1: hprot[0] from CM4 go through cache controller without modification 1b0: hprot[0] is provided by cache controller register
9 : 6	rf_hprot_bus_reg	rw	0x3	hprot control register which provide 4bit hprot for cache bus AHB
13 : 10	rf_hprot_cache_reg	rw	0xB	hprot control register which provide 4bit hprot for cache ctrl AHB
14	ahb_ram_en	rw	0x0	Cache Data Ram Can be Write/Read Throught rf AHB Bus
29 : 28	rf_cache_size_sel	rw	0x3	cache size selection: 0: 4K Byte 1: 8K Byte 2: 16K Byte 3: 32K Byte
30	rf_cmd_exec_mode	rw	0x0	0: (recommended) software can run in cacheable region during software command processing 1: software cannot run in cacheable region during software command processing
31	rf_debug_en	rw	0x0	cache debug mode enable: 0: normal mode 1: debug mode This bit MUST always be cleared during cache operating

13.18 BUS_STS0				0x40000044
Bits	Field Name	Acc	Default	Description
27 : 0	rf_prot_detect_addr	ro	0x0	trigging address for protect block

13.19 CACHE_STS0				0x40000048
Bits	Field Name	Acc	Default	Description
3 : 0	rf_cache_st	ro	0x0	rf_cache_st
6 : 4	rf_cmd_st	ro	0x0	rf_cmd_st

7	rf_write_ongoing	ro	0x0	rf_write_ongoing, this is a status register for write through mode to avoid potential coherence issue. 1b1: the cache is still doing AHB write transaction to the main memory and the data is not written into the main memory. 1b0: the cache has finished AHB write transaction and the data is written into the main memory.

13.20 CMD_CFG0				0x40000050
Bits	Field Name	Acc	Default	Description
27 : 0	rf_cmd_str_addr	rw	0x0	cmd_all : not used cmd_range : start address cmd_entry : entry address

13.21 CMD_CFG1				0x40000054
Bits	Field Name	Acc	Default	Description
27 : 0	rf_cmd_end_addr	rw	0x0	cmd_all : not used cmd_range : end address cmd_entry : not used

13.22 CMD_CFG2				0x40000058
Bits	Field Name	Acc	Default	Description
5 : 0	rf_cmd_type	rw	0x0	software command type: 6h0 : clean all 6h1 : clean range 6h2 : clean entry 6h3 : reserved 6h4 : invalid all 6h5 : invalid range 6h6 : invalid entry 6h7 : reserved 6h8 : clean and invalid all 6h9 : clean and invalid range 6hA : clean and invalid entry 6hB : reserved
31	rf_cmd_str	wo	0x0	software command start: write 1 to this bit to issue one command

13.23 INT_EN				0x40000060
Bits	Field Name	Acc	Default	Description
0	rf_cmd_irq_en	rw	0x0	interrupt enable for software command done
1	rf_prot_irq_en	rw	0x0	interrupt enable for protect block trigging

13.24 INT_RAW				0x40000064
Bits	Field Name	Acc	Default	Description
0	rf_cmd_irq_raw	ro	0x0	interrupt raw status for software command done
1	rf_prot_irq_raw	ro	0x0	interrupt raw status for protect block trigging

13.25 INT_MASK				0x40000068
Bits	Field Name	Acc	Default	Description
0	rf_cmd_irq_mask	ro	0x0	interrupt masked status for software command done
1	rf_prot_irq_mask	ro	0x0	interrupt masked status for protect block trigging

13.26 INT_CLR				0x4000006C
Bits	Field Name	Acc	Default	Description
0	rf_cmd_irq_clr	wo	0x0	interrupt clear for software command done

1	rf_prot_irq_clr	wo	0x0	interrupt clear for protect block trigging

13.27 CACHE_WRITE_HIT_CNT				0x40000070
Bits	Field Name	Acc	Default	Description
31 : 0	rf_write_hit_cnt	ro	0x0	Cache write hit times. When cache write hit, the counter value increment by 1

13.28 CACHE_WRITE_MISS_CNT				0x40000074
Bits	Field Name	Acc	Default	Description
29 : 0	rf_write_miss_cnt	ro	0x0	Cache write miss times. When cache write miss, the counter value increment by 1
30	rf_write_cnt_run	rw	0x0	1: write hit/miss counter will run 0: write hit/miss counter will stop
31	rf_write_cnt_clr	wo	0x0	clear write counter values to zero

13.29 CACHE_READ_HIT_CNT				0x40000078
Bits	Field Name	Acc	Default	Description
31 : 0	rf_read_hit_cnt	ro	0x0	Cache read hit times. When cache read hit, the counter value increment by 1

13.30 CACHE_READ_MISS_CNT				0x4000007C
Bits	Field Name	Acc	Default	Description
29 : 0	rf_read_miss_cnt	ro	0x0	Cache read miss times. When cache read miss, the counter value increment by 1
30	rf_read_cnt_run	rw	0x0	1: read hit/miss counter will run 0: read hit/miss counter will stop
31	rf_read_cnt_clr	wo	0x0	clear read counter values to zero

13.31 CACHE_HACT_CNT				0x40000080
Bits	Field Name	Acc	Default	Description
31 : 0	rf_hact_cnt	ro	0x0	Cache master AHB active cycles in total. When master AHB is active (hsel and htrans[1]), the counter value increment by 1

13.32 CACHE_HRDY_CNT				0x40000084
Bits	Field Name	Acc	Default	Description
29 : 0	rf_hrdy_cnt	ro	0x0	The HRDY counter counts the valid cycles of HREADY signal from the cache controller to the master when the master AHB is active. When HREADY signal to the master is high and the master AHB is active, the counter value increment by 1
30	rf_hact_hrdy_run	rw	0x0	1: HACT and HRDY counters will run 0: HACT and HRDY counters will stop
31	rf_hact_hrdy_clr	wo	0x0	clear HACT and HRDY counter values to zero

14 dma_cx

14.1 DMA_PAUSE				0x40020000
Discription:				
Bits	Field Name	Acc	Default	Description
0	DMA_PAUSE	rw	0x0	Active High, pause all the channels. Note: If "DMA_PAUSE" asserted active when the DMA is busy, DMA would finish the current fragment before enter Pause State.

16	DMA_PAUSE_STATUS	ro	0x0	DMA Pause status. 0 : In active state. 1 : In Pause state.

14.2 DMA_FRAG_WAIT				0x40020004
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	DMA_FRAG_WAIT	rw	0x0	Wait Time between two successive Fragment. With unit of AHB clock.
28	O_ENDIAN	rw	0x0	DMA output endian, 0- little endian 1- big endian

14.3 REQ_PEND0_EN				0x40020008
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	REQ_PEND_EN_31to0	rw	0x0	Requests Pending Enable. Acitve high, enable DMA_REQ[31:0] to wakeup DMA, when MCU deep sleep;

14.4 REQ_PEND1_EN				0x4002000C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	REQ_PEND_EN_63to32	rw	0x0	Requests Pending Enable. Acitve high, enable DMA_REQ[63:32] to wakeup DMA, when MCU deep sleep;

14.5 DMA_INT_RAW_STATUS				0x40020010
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	DMA_INT_RAW_STATUS	ro	0x0	DMA 32 Channels Interrupt Raw Status. 0 : No Interrupt need to be served. 1 : Interrupt need to be served.

14.6 DMA_INT_MASK_STATUS				0x40020014
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	DMA_INT_MASK_STATUS	ro	0x0	DMA 32 Channels Interrupt Mask Status. 0 : No Interrupt need to be served. 1 : Interrupt need to be served.

14.7 DMA_REQ_STATUS				0x40020018
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	DMA_REQ_STATUS	ro	0x0	DMA 32 Channels Request Status. 0 : No Request need to be served. 1 : Request need to be served.

14.8 DMA_EN_STATUS				0x4002001C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	DMA_EN_STATUS	ro	0x0	DMA 32 Channels Enable Status. 0 : Channel Not Enabled. 1 : Channel Enabled.

14.9 DMA_DEBUG_STATUS				0x40020020
Discription:				
Bits	Field Name	Acc	Default	Description
3 : 0	DEST_FSM_STATUS	ro	0x0	Destination Side FSM status. 4'd0: IDLE 4'd1: calculate burst parameter 4'd2: calculate data number of burst 4'd3: wait enough data buffer space for write burst 4'd4: start write burst 4'd5: write burst execute 4'd6: wait fragment done or limit outstanding number 4'd7: fragment write done
7 : 4	SRC_FSM_STATUS	ro	0x0	Source Side FSM status. 4'd0: IDLE 4'd1: calculate burst parameter 4'd2: calculate data number of burst 4'd3: wait enough data buffer space for read burst 4'd4: start read burst 4'd5: read burst execute 4'd6: wait fragment done or limit outstanding number 4'd7: fragment read done
12 : 8	MAIN_FSM_STATUS	ro	0x0	MAIN FSM status. 5'd0: IDLE 5'd1: load link list pointer 5'd2: load link list source and dest address 5'd3: load link list fragment and block length 5'd4: load link list transaction length and src/dest transfer step 5'd5: load link list wrap_ptr and wrap_to 5'd6: load full mode source and dest address 5'd7: load full mode fragment and block length 5'd8: load full mode transaction length and src/dest transfer step 5'd9: load full mode wrap_ptr and wrap_to 5'd10: update block length 5'd11: update transaction length 5'd12: fragment execute 5'd13: load list pointer and use src/dest fragment step 5'd14: load src/dest block step 5'd15: load link list high 4bits pointer and src/dest fragment step 5'd16: load src/dest block step 5'd17: transaction or link list done 5'd18: update wrap info.
16	HREADY_DMAR	ro	0x1	dma read hready
17	HREADY_DMAW	ro	0x1	dma write hready
20	DMA_BUSY	ro	0x0	DMA Busy Status.

14.10 DMA_ARB_SEL_STATUS				0x40020024
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	CHN_ARB_SEL	ro	0x0	Channel Arbitrator Selection Status;

14.11 CRC_CFG				0x40020030
Discription:				
Bits	Field Name	Acc	Default	Description
3 : 0	DATA_MODE	rw	0xE	CRC data mode bit0: In data byte receive bit1: In data bit receive bit2: Out data byte receive bit3: Out data bit receive
5 : 4	CRC_GEN_SIZE	rw	0x3	CRC generator size 2'b0:crc8 2'b1:crc16 2'b10:crc24 2'b11:crc32
9 : 8	CRC_INIT_MODE	rw	0x0	CRC initial mode 2'b0:frag done 2'b1:blk done 2'b10:trsc done

20 : 16	CRC_CH_NUM	rw	0x1	DMA channel number for CRC check
24	CRC_HOLD	rw	0x0	CRC hold
28	CRC_EN	rw	0x0	CRC enable
29	CRC_CLK_GATE_EN	rw	0x1	CRC clock gate enable

14.12 CRC_GEN				0x40020034
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CRC_GEN	rw	0x4C11DB7	CRC32 generator

14.13 CRC_OUT_XOR				0x40020038
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CRC_OUT_XOR	rw	0xFFFFFFFF	CRC out data xor

14.14 CRC_INIT				0x4002003C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CRC_INIT	rw	0xFFFFFFFF	CRC init val

14.15 I_CRC				0x40020040
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	I_CRC	ro	0x0	

14.16 AES_KEY_0_ADDR				0x40020044
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_KEY_0_ADDR	rw	0x0	

14.17 AES_KEY_1_ADDR				0x40020048
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_KEY_1_ADDR	rw	0x0	

14.18 AES_KEY_2_ADDR				0x4002004C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_KEY_2_ADDR	rw	0x0	

14.19 AES_KEY_3_ADDR				0x40020050
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_KEY_3_ADDR	rw	0x0	

14.20 AES_KEY_4_ADDR				0x40020054
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_KEY_4_ADDR	rw	0x0	

14.21 AES_KEY_5_ADDR				0x40020058
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_KEY_5_ADDR	rw	0x0	

14.22 AES_KEY_6_ADDR				0x4002005C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_KEY_6_ADDR	rw	0x0	

14.23 AES_KEY_7_ADDR				0x40020060
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_KEY_7_ADDR	rw	0x0	

14.24 AES_IV_0_ADDR				0x40020064
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_IV_0_ADDR	rw	0x0	

14.25 AES_IV_1_ADDR				0x40020068
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_IV_1_ADDR	rw	0x0	

14.26 AES_IV_2_ADDR				0x4002006C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_IV_2_ADDR	rw	0x0	

14.27 AES_IV_3_ADDR				0x40020070
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_IV_3_ADDR	rw	0x0	

14.28 AES_PLAIN_LEN_H_ADDR				0x40020074
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_PLAIN_LEN_H_ADDR	rw	0x0	

14.29 AES_PLAIN_LEN_L_ADDR				0x40020078
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_PLAIN_LEN_L_ADDR	rw	0x0	

14.30 AES_A_LEN_H_ADDR				0x4002007C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_A_LEN_H_ADDR	rw	0x0	

14.31 AES_A_LEN_L_ADDR				0x40020080
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	AES_A_LEN_L_ADDR	rw	0x0	

14.32 CE_CTRL_ADDR				0x40020084
Discription:				
Bits	Field Name	Acc	Default	Description
0	rsa_en	rw	0x0	
1	ecc_en	rw	0x0	
2	rsa_mode	rw	0x0	
5 : 3	ecc_mode	rw	0x0	
6	kpEccAEqP3En	rw	0x0	
12 : 7	macKeyIndex	rw	0x0	
13	aes_en	rw	0x0	
14	aes_enc_dec_sel	rw	0x0	
17 : 15	aes_mode	rw	0x0	
18	key192	rw	0x0	
19	key256	rw	0x0	
20	hash_en	rw	0x0	
26 : 21	ce_chn_sel	rw	0x0	
27	dma_clr	rw	0x0	
28	hash_endian_sel	rw	0x1	
29	aes_endian_sel	rw	0x1	
30	hash_done	ro	0x1	
31	aes_done	ro	0x1	

14.33 PKA_REG0_ADDR				0x40020088
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	PKA_REG0_ADDR	rw	0x0	

14.34 CE_CLOCK_GATE_CTRL				0x4002008C
Discription:				
Bits	Field Name	Acc	Default	Description
0	PKA_CLOCK_GATE_EN	rw	0x1	
1	AES_CLOCK_GATE_EN	rw	0x1	
2	HASH_CLOCK_GATE_EN	rw	0x1	
3	reserved0	rw	0x1	

14.35 TRANS_CTRL0_ADDR				0x40020090
Discription:				
Bits	Field Name	Acc	Default	Description
2 : 0	fft_len	rw	0x0	
5 : 3	fft_scale	rw	0x0	
6	fft_dir	rw	0x0	
7	fft_en	rw	0x0	
13 : 8	trans_chn_sel	rw	0x0	
14	fft_in_format_sel	rw	0x0	
15	fft_out_format_sel	rw	0x0	
31	trans_done	ro	0x1	

14.36 TRANS_CTRL1_ADDR	0x40020094

Discription:				
Bits	Field Name	Acc	Default	Description
0	fltr_en	rw	0x0	
1	fltr_cofshw_upd	rw	0x0	
2	sbc_mode_en	rw	0x0	
3	fltr_cofcos_upd	rw	0x0	
4	fltr_cof_len	rw	0x0	
18 : 5	fltr_len	rw	0x0	
23 : 19	fltr_order	rw	0x0	
24	fltr_cof_init_sel	rw	0x0	

14.37 TRANS_CLOCK_GATE_CTRL				0x40020098
Discription:				
Bits	Field Name	Acc	Default	Description
0	fft_clk_gate_en	rw	0x1	
1	flt_clk_gate_en	rw	0x1	
2	reserved0	rw	0x0	

14.38 DMA_MON_SEL				0x4002009C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	dma_mon_sel	rw	0x0	

14.39 dma_reserved0				0x400200A0
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	dma_reserved0	rw	0x0	

14.40 dma_reserved1				0x400200A4
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	dma_reserved1	rw	0x0	

14.41 dma_reserved2				0x400200A8
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	dma_reserved2	rw	0x0	

14.42 CHKSUM_CTRL_ADDR				0x400200B8
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	chksum_len	rw	0x0	
16	chksum_en	rw	0x0	
22 : 17	chksum_chn_sel	rw	0x0	
23	chksum_endian_sel	rw	0x0	0: big endian 1: little endian
24	chksum_dest_bypass	rw	0x0	0: dest trans enable 1: dest trans bypass
25	chksum_clk_gate_en	rw	0x1	

14.43 CHKSUM_RES_ADDR	0x400200BC

Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	chksum_res	ro	0x0	
31	chksum_done	ro	0x0	

14.44 HASH_LEN_BIT_ADDR				0x400200C0
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	hash_len_bit	rw	0x0	hash padding length

14.45 CE_CTRL_2_ADDR				0x400200C4
Discription:				
Bits	Field Name	Acc	Default	Description
0	hash_hw_pad_en	rw	0x0	
2 : 1	hash_mode_sel	rw	0x0	0: sha-224 1: sha-256 2: sha-1

14.46 FULL_DMA_CHS				0x40021000
S.NO.	Count	0	1	13
0	FULL_CHN_PAUSE	0x40021000	0x40021040	0x0410B340
1	FULL_CHN_REQ	0x40021004	0x40021044	0x0410B344
2	FULL_CHN_CFG	0x40021008	0x40021048	0x0410B348
3	FULL_CHN_INT	0x4002100C	0x4002104C	0x0410B34C
4	FULL_CHN_SRC_ADDR	0x40021010	0x40021050	0x0410B350
5	FULL_CHN_DEST_ADDR	0x40021014	0x40021054	0x0410B354
6	FULL_CHN_FRAG_LEN	0x40021018	0x40021058	0x0410B358
7	FULL_CHN_BLK_LEN	0x4002101C	0x4002105C	0x0410B35C
8	FULL_CHN_TRSC_LEN	0x40021020	0x40021060	0x0410B360
9	FULL_CHN_TRSF_STEP	0x40021024	0x40021064	0x0410B364
10	FULL_CHN_WRAP_PTR	0x40021028	0x40021068	0x0410B368
11	FULL_CHN_WRAP_TO	0x4002102C	0x4002106C	0x0410B36C
12	FULL_CHN_LLIST_PTR	0x40021030	0x40021070	0x0410B370
13	FULL_CHN_FRAG_STEP	0x40021034	0x40021074	0x0410B374
14	FULL_CHN_SRC_-BLK_STEP	0x40021038	0x40021078	0x0410B378
15	FULL_CHN_DEST-_BLK_STEP	0x4002103C	0x4002107C	0x0410B37C

14.46.1 FULL_CHN_PAUSE				0x40021000
Discription :				
Bits	Field Name	Acc	Default	Description
0	CHN_PAUSE	rw	0x0	Channel Pause Enable. 0 : Channel in active mode. 1 : Channel pause. Active high, only pause the channel. If the CHN_PAUSE asserted when the channel is busy, it should be paused after the current fragment finished.
16	CHN_PAUSE_STATUS	ro	0x0	Channel Pause status.

14.46.2 FULL_CHN_REQ				0x40021004
Discription :				
Bits	Field Name	Acc	Default	Description

0	CHN_REQ	rw	0x0	Channel Software DMA Request.
1	CHN_EXREQ_MODE	rw	0x0	Channel External DMA Request Mode: 1- level, 0- edge
2	CHN_EXREQ_LEVEL	rw	0x1	Channel External DMA Valid Level: 1- high, 0- low

14.46.3 FULL_CHN_CFG 0x40021008

Discription :

Bits	Field Name	Acc	Default	Description
0	CHN_EN	rw	0x0	Channel Enable: 0 : Disable the channel. 1 : Enable the channel.
4	LLIST_EN	rw	0x0	Link list Enable, only available for full DMA channel. 0 : Disable the link list. 1 : Enable the link list.
8	LLIST_CFG_VALID	rw	0x0	If "LLIST_EN" asserted, active high indicates Link list configure valid. 0 : Link list configure in-valid. DMA controller need obtain link list configure information by link list pointer. 1 : link list configure information valid. DMA controller would continue to complete the node and clear this bit. Note: Strongly recommend to observe only. Carefully writing to this bit, which may cause DMA crashed. If had to do so, pause this channel before changing.
13 : 12	CHN_PRIORITY	rw	0x0	Channel Request Priority. Four level of Priority supported as list : 2'b00 : Lowest priority. 2'b01 : Secondary lowest priority. 2'b10 : Tertiary lowest priority. 2'b11 : Highest priority.
17 : 16	AHB_BURST_SEL	rw	0x0	AMBA Burst Select. 2'b00 : INCR8; 2'b01 : INCR4; 2'b10 : INCR16; 2'b11 : INCR16;

23 : 20	ERR_TYPE_STATUS	ro	0x0	Error Configure , which would be cleared when "ERR_INT_STATUS" cleared:
				4'b0001 : Addr Wrap Error Configure;
				4'b0010 : Request Mode Error Configure;
				4'b0100 : Length Error Configure;
				4'b1000 :Unalign Error Configure;
				1 gt; Addr wrap error configure
				Set wrap enable in standard DMA channel.
				2 gt; Request mode error configure
				Req_mode==2 or 3 in in standard DMA channel.
				3 gt; Length Error Configure
				d gt; Frag_len==0;
				e gt; Blk_len==0;
				f gt; FULL DMA channel,trsc_len==0;
				4 gt; Unalign Error Configure
				c gt; Src unsigned error
				a1 gt; address unalign in halfword width
				error=(src_data_size[1:0]==1) amp; amp;(src_addr[0] =0)
				a2 gt; address unalign and trsf_step unalign in word width
				error=(src_data_size[1:0]==2) amp; amp;(src_addr[1:0] =0)
				amp; amp;(src_trsf_step =4)
				d gt; dest unsigned error
				b1 gt; address unalign in halfword width
				error=(dst_data_size[1:0]==1) amp; amp;(dst_addr[0] =0)
				b2 gt; address unalign and trsf_step unalign in word width
				error=(dst_data_size[1:0]==2) amp; amp;(dst_addr[1:0] =0)
				amp; amp;(dst_trsf_step =4)

14.46.4 FULL_CHN_INT 0x4002100C

Discription :

Bits	Field Name	Acc	Default	Description
0	CHN_FRAGMENT_INT_EN	rw	0x0	Fragment done interrupt enable.
1	CHN_BLK_INT_EN	rw	0x0	Block done interrupt enable.
2	CHN_TRSC_INT_EN	rw	0x0	Transaction done interrupt enable
3	CHN_LLIST_INT_EN	rw	0x0	Link list done interrupt enable
4	CHN_CFG_ERR_INT_EN	rw	0x0	Configuration error interrupt enable.
8	CHN_FRAGMENT_-INT_RAW_STATUS	ro	0x0	Fragment done Raw interrupt status.
9	CHN_BLK_INT_-RAW_STATUS	ro	0x0	Block done interrupt status.
10	CHN_TRSC_INT_-RAW_STATUS	ro	0x0	Channel Transaction interrupts status.
11	CHN_LLIST_INT-_RAW_STATUS	ro	0x0	Channel Link List interrupts status.
12	CHN_CFG_ERR_-INT_RAW_STATUS	ro	0x0	Configuration error raw interrupts status.
16	CHN_FRAGMENT_-INT_MASK_STATUS	ro	0x0	Channel Fragment Masked interrupts status.
17	CHN_BLK_INT_-MASK_STATUS	ro	0x0	Channel Block Masked interrupts status.
18	CHN_TRSC_INT_-MASK_STATUS	ro	0x0	Channel Transaction Masked interrupts status.
19	CHN_LLIST_INT-_MASK_STATUS	ro	0x0	Channel Link list Masked interrupt status.
20	CHN_CFG_ERR_-INT_MASK_STATUS	ro	0x0	Configuration error masked interrupt status.
24	CHN_FRAGMENT_INT_CLR	wo	0x0	Fragment done interrupt clear.
25	CHN_BLK_INT_CLR	wo	0x0	Block done interrupt clear.

26	CHN_TRSC_INT_CLR	wo	0x0	Transaction done interrupt clear
27	CHN_LLIST_INT_CLR	wo	0x0	Link list done interrupt clear
28	CHN_CFG_ERR_INT_CLR	wo	0x0	Configuration error interrupt clear.

14.46.5 FULL_CHN_SRC_ADDR 0x40021010

Discription :

Bits	Field Name	Acc	Default	Description
31 : 0	CHN_SRC_ADDR	rw	0x0	Channel Source Address

14.46.6 FULL_CHN_DEST_ADDR 0x40021014

Discription :

Bits	Field Name	Acc	Default	Description
31 : 0	CHN_DEST_ADDR	rw	0x0	Channel Destination Address

14.46.7 FULL_CHN_FRAG_LEN 0x40021018

Discription :

Bits	Field Name	Acc	Default	Description
16 : 0	FRG_LEN	rw	0x0	Fragment Length, with byte unit. Max 128K-1 bytes
18 : 17	BLK_LEN_REC_H	rw	0x0	Block counter[16:15], update after each fragment done; Note: Normally configured to 2'b0. Only to be configured other value during state retention after wake up
19	LLIST_END	rw	0x0	Link list end flag. Active only when "LLIST_EN" asserted.
20	SRC_ADDR_FIX_EN	rw	0x0	Source Address Fix Enable: 0 : Disable Source Address Fix mode. 1 : Enable Source Address Fix mode. Active High would make source address fixed within the fragment, while "FRAG_STEP" and "BLK_STEP" would be applied to address after fragment done;
21	DEST_ADDR_FIX_EN	rw	0x0	Selection of the side using Address Fix mode. 0 : Disable Destination Address Fix mode. 1 : Enable Destination Address Fix mode. Active High would make destination address fixed within the fragment, while "FRAG_STEP" and "BLK_STEP" would be applied to address after fragment done;
22	ADDR_WRAP_EN	rw	0x0	Active High enable Address-wrapping for ring buffer. The next address of DMA jumps to "WRAP_START_ADDR" address when the current address matches "WRAP_END_ADDR" address: 0 : Disable address wrap mode. 1 : Enable address wrap mode. "WRAP_START_ADDR" and "WRAP_END_ADDR" would be used to limit the address space of either Source or Destination.
23	ADDR_WRAP_SEL	rw	0x0	Selection of the side using Address wrap mode. 0 : Address wrap on Source. 1 : Address wrap on Destination. Only one side of a DMA channel can activate address-wrapping mode at a time.
25 : 24	REQ_MODE	rw	0x0	Request mode, For Full DMA channel: 2'b00 : Fragment; 2'b01 : Block; 2'b10 : Transaction; 2'b11 : Link List;

27 : 26	SWT_MODE	rw	0x0	Data Switch mode selection. 2'b00 : ABCD = gt; ABCD; 2'b01 : ABCD = gt; DCBA 2'b10 : ABCD = gt; BADC; 2'b11 : ABCD = gt; CDAB
29 : 28	DEST_SIZE	rw	0x0	Destination AHB Size. 2'b00 : Byte; 2'b01 : Half Word 2'b10 : Word 2'b11 : DWord.
31 : 30	SRC_SIZE	rw	0x0	Source AHB Size. 2'b00 : Byte; 2'b01 : Half Word 2'b10 : Word 2'b11 : DWord.

14.46.8 FULL_CHN_BLK_LEN 0x4002101C

Discription :

Bits	Field Name	Acc	Default	Description
16 : 0	BLK_LEN	rw	0x0	Block Length, with byte unit. Max 128K-1 bytes
31 : 17	BLK_LEN_REC_L	rw	0x0	Block counter[14:0], update after each fragment done; Note: Normally configured to 15'b0. Only to be configured other value during state retention after wake up

14.46.9 FULL_CHN_TRSC_LEN 0x40021020

Discription :

Bits	Field Name	Acc	Default	Description
27 : 0	TRSC_LEN	rw	0x0	Transaction Length, with byte unit. (Max 256M-1 bytes)
28	LLIST_DEDICATED_INT_EN	rw	0x0	Interrupt global enable dedicated for a certain linklist, only valid when linklist enable
29	LLIST_DEDICATED_COUNT_EN	rw	0x0	Counter enable dedicated for a certain linklist, only valid when linklist enable

14.46.10 FULL_CHN_TRSF_STEP 0x40021024

Discription :

Bits	Field Name	Acc	Default	Description
15 : 0	SRC_TRSF_STEP	rw	0x0	Channel destination side transfer step, with byte unit.
31 : 16	DEST_TRSF_STEP	rw	0x0	Channel Source side transfer step, with byte unit.

14.46.11 FULL_CHN_WRAP_PTR 0x40021028

Discription :

Bits	Field Name	Acc	Default	Description
27 : 0	WRAP_PTR	rw	0x0	Wrap jump pointer address. Once the transfer address reaches WPPT, the next address jumps to the WPTO address after completing the WPPT data transfer.
31 : 28	CHN_SRC_ADDR_35to32	rw	0x0	Chn source address high 4bits

14.46.12 FULL_CHN_WRAP_TO				0x4002102C
Discription :				
Bits	Field Name	Acc	Default	Description
27 : 0	WRAP_TO	rw	0x0	Wrap jump-to address. Once the transfer address reaches WPPT, the next address jumps to the WPTO address after completing the WPPT data transfer.
31 : 28	CHN_DEST_ADDR_35_32	rw	0x0	Chn Destination address high 4bits

14.46.13 FULL_CHN_LLIST_PTR				0x40021030
Discription :				
Bits	Field Name	Acc	Default	Description
31 : 0	LLIST_PTR	rw	0x0	Link List pointer. Must DWord align.

14.46.14 FULL_CHN_FRAG_STEP				0x40021034
Discription :				
Bits	Field Name	Acc	Default	Description
15 : 0	SRC_FRAG_STEP	rw	0x0	Channel Source side transfer step. With byte unit.
31 : 16	DEST_FRAG_STEP	rw	0x0	Channel Destination side transfer step. With byte unit.

14.46.15 FULL_CHN_SRC_BLK_STEP				0x40021038
Discription :				
Bits	Field Name	Acc	Default	Description
27 : 0	CHN_SRC_BLK_STEP	rw	0x0	Channel Source block step. With byte unit.
31 : 28	LLIST_PTR_35_32	rw	0x0	Link List pointer high 4bits

14.46.16 FULL_CHN_DEST_BLK_STEP				0x4002103C
Discription :				
Bits	Field Name	Acc	Default	Description
27 : 0	CHN_DEST_BLK_STEP	rw	0x0	Channel Destination block step. With byte unit.

14.47 REQ_CID_0				0x40022000
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.48 REQ_CID_1				0x40022004
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.49 REQ_CID_2				0x40022008
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.50 REQ_CID_3				0x4002200C
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.51 REQ_CID_4				0x40022010
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.52 REQ_CID_5				0x40022014
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.53 REQ_CID_6				0x40022018
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.54 REQ_CID_7				0x4002201C
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.55 REQ_CID_8				0x40022020
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.56 REQ_CID_9				0x40022024
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.57 REQ_CID_10				0x40022028
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.58 REQ_CID_11				0x4002202C
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.59 REQ_CID_12				0x40022030
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.60 REQ_CID_13				0x40022034
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.61 REQ_CID_14				0x40022038
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.62 REQ_CID_15				0x4002203C
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.63 REQ_CID_16				0x40022040
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.64 REQ_CID_17				0x40022044
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.65 REQ_CID_18				0x40022048
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.66 REQ_CID_19				0x4002204C
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.67 REQ_CID_20				0x40022050
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.68 REQ_CID_21				0x40022054
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.69 REQ_CID_22				0x40022058
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.70 REQ_CID_23				0x4002205C
Discription:				
Bits	Field Name	Acc	Default	Description
5 : 0	REQ_CID	rw	0x0	Req channel identify number

14.71 CHN_1_DMA_ADDR_RD				0x40022100
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_1_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 1 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.72 CHN_1_DMA_ADDR_WR				0x40022104
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_1_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 1 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.73 CHN_2_DMA_ADDR_RD				0x40022108
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_2_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 2 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.74 CHN_2_DMA_ADDR_WR				0x4002210C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_2_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 2 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.75 CHN_3_DMA_ADDR_RD				0x40022110
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_3_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 3 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.76 CHN_3_DMA_ADDR_WR				0x40022114
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_3_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 3 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.77 CHN_4_DMA_ADDR_RD	0x40022118

Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_4_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 4 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.78 CHN_4_DMA_ADDR_WR				0x4002211C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_4_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 4 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.79 CHN_5_DMA_ADDR_RD				0x40022120
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_5_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 5 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.80 CHN_5_DMA_ADDR_WR				0x40022124
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_5_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 5 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.81 CHN_6_DMA_ADDR_RD				0x40022128
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_6_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 6 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.82 CHN_6_DMA_ADDR_WR				0x4002212C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_6_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 6 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.83 CHN_7_DMA_ADDR_RD				0x40022130
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_7_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 7 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.84 CHN_7_DMA_ADDR_WR				0x40022134
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_7_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 7 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffffff

14.85 CHN_8_DMA_ADDR_RD				0x40022138
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_8_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 8 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.86 CHN_8_DMA_ADDR_WR				0x4002213C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_8_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 8 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.87 CHN_9_DMA_ADDR_RD				0x40022140
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_9_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 9 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.88 CHN_9_DMA_ADDR_WR				0x40022144
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_9_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 9 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.89 CHN_10_DMA_ADDR_RD				0x40022148
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_10_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 10 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.90 CHN_10_DMA_ADDR_WR				0x4002214C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_10_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 10 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.91 CHN_11_DMA_ADDR_RD				0x40022150
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_11_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 11 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.92 CHN_11_DMA_ADDR_WR				0x40022154
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_11_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 11 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.93 CHN_12_DMA_ADDR_RD				0x40022158
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_12_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 12 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.94 CHN_12_DMA_ADDR_WR				0x4002215C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_12_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 12 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.95 CHN_13_DMA_ADDR_RD				0x40022160
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_13_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 13 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.96 CHN_13_DMA_ADDR_WR				0x40022164
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_13_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 13 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.97 CHN_14_DMA_ADDR_RD				0x40022168
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_14_DMA_ADDR_RD	ro	0xFFFFFFFF	channel 14 dma addr read monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.98 CHN_14_DMA_ADDR_WR				0x4002216C
Discription:				
Bits	Field Name	Acc	Default	Description
31 : 0	CHN_14_DMA_ADDR_WR	ro	0xFFFFFFFF	channel 14 dma addr write monitor write bit0 to 1'b1, dma addr monitor value reset to 0xffffff

14.99 CHN_LLI_NODE_COUNTER_0				0x40022200
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.100 CHN_LLI_NODE_COUNTER_1				0x40022204
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.101 CHN_LLI_NODE_COUNTER_2	0x40022208

Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.102 CHN_LLI_NODE_COUNTER_3				0x4002220C
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.103 CHN_LLI_NODE_COUNTER_4				0x40022210
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.104 CHN_LLI_NODE_COUNTER_5				0x40022214
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.105 CHN_LLI_NODE_COUNTER_6				0x40022218
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.106 CHN_LLI_NODE_COUNTER_7				0x4002221C
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.107 CHN_LLI_NODE_COUNTER_8				0x40022220
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.108 CHN_LLI_NODE_COUNTER_9				0x40022224
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.109 CHN_LLI_NODE_COUNTER_10				0x40022228
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.110 CHN_LLI_NODE_COUNTER_11				0x4002222C
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.111 CHN_LLI_NODE_COUNTER_12				0x40022230
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

14.112 CHN_LLI_NODE_COUNTER_13				0x40022234
Discription:				
Bits	Field Name	Acc	Default	Description
15 : 0	LLI_NODE_COUNTER	rw	0x0	Linklist Node Counter of Dma Channel n

15 cpu_p_trap

15.1 addr_in_0				0x40030000
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

15.2 addr_in_1				0x40030004
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

15.3 addr_in_2				0x40030008
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

15.4 addr_in_3				0x4003000C
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

15.5 addr_in_4				0x40030010
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

15.6 addr_in_5				0x40030014
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

15.7 addr_in_6				0x40030018
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

15.8 addr_in_7				0x4003001C
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

15.9 en				0x40030080
Bits	Field Name	Acc	Default	Description
7 : 0	en	rw	0x0	trap enable for 8 channels
31 : 8	en_reserved_0	ro	0x0	

15.10 trap_out_base				0x40030084
Bits	Field Name	Acc	Default	Description
6 : 0	base_out_reserved	ro	0x0	
31 : 7	base_out	rw	0x0	trap out base address, only high 25 bits are valid.

16 cpu_s0_trap

16.1 addr_in_0				0x40031000
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

16.2 addr_in_1				0x40031004
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

16.3 addr_in_2				0x40031008
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

16.4 addr_in_3				0x4003100C
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

16.5 addr_in_4				0x40031010
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

16.6 addr_in_5				0x40031014
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

16.7 addr_in_6				0x40031018
Bits	Field Name	Acc	Default	Description

19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

16.8 addr_in_7				0x4003101C
Bits	Field Name	Acc	Default	Description
19 : 0	addr_in	rw	0x0	address to be trapped
31 : 20	addr_in_reserved_0	ro	0x0	

16.9 en				0x40031080
Bits	Field Name	Acc	Default	Description
7 : 0	en	rw	0x0	trap enable for 8 channels
31 : 8	en_reserved_0	ro	0x0	

16.10 trap_out_base				0x40031084
Bits	Field Name	Acc	Default	Description
6 : 0	base_out_reserved	ro	0x0	
31 : 7	base_out	rw	0x0	trap out base address, only high 25 bits are valid.

17 uart0

17.1 txrx_fifo_divl				0x40032000
Bits	Field Name	Acc	Default	Description
7 : 0	txrx_data_divl	rw	0x0	Tx data(when write data), Rx data(when read data), Divisor latch(low) config when divisor latch is enable.

17.2 int_en_divh				0x40032004
Discription: Interrupt enable register; divisor latch high when divisor latch is enable.				
Bits	Field Name	Acc	Default	Description
0	rx_int_en_divh_0	rw	0x0	Enable Received Data Available Interrupt; Divisor latch high bit 0 when divisor latch is enable.
1	tx_int_en_divh_1	rw	0x0	Enable Transmit Holding Register Empty Interrupt; Divisor latch high bit 1 when divisor latch is enable.
2	lstatus_int_en_divh_2	rw	0x0	Enable Receiver Line Status Interrupt; Divisor latch high bit 2 when divisor latch is enable.
3	mstatus_int_en_divh_3	rw	0x0	Enable Modem Status Interrupt; Divisor latch high bit 3 when divisor latch is enable.
4	divh_4	rw	0x0	Divisor latch high bit 4 when divisor latch is enable.
5	timeout_int_en_divh_5	rw	0x0	Enable Timeout Interrupt; Divisor latch high bit 5 when divisor latch is enable.
6	divh_6	rw	0x0	Divisor latch high bit 6 when divisor latch is enable.
7	ptime_divh_7	rw	0x0	Programmable THRE Interrupt Mode Enable; Divisor latch high bit 7 when divisor latch is enable.

17.3 int_id_fifo_ctrl				0x40032008
Discription: Interrupt identity register or fifo control register				
Bits	Field Name	Acc	Default	Description
0	int_id_0_fifo_en	rw	0x1	Read: Interrupt identity bit 0, reset value is '0'; Write: Fifo enable, reset value is '1'
1	int_id_1_rx_reset	rw	0x0	Read: Interrupt identity bit 1; Write: Receiver reset
2	int_id_2_tx_reset	rw	0x0	Read: Interrupt identity bit 2; Write: Transmit reset
3	int_id_3_dma_mode	rw	0x0	Read: Interrupt identity bit 3; Write: Dma mode enable
7 : 6	fifo_enabled	ro	0x3	

17.4 line_ctrl				0x4003200C
Bits	Field Name	Acc	Default	Description
1 : 0	data_length_sel	rw	0x3	0: 5 bit 1: 6 bit 2: 7 bit 3: 8 bit
2	stop	rw	0x0	Number of stop bits
3	parity_en	rw	0x0	Parity enable
4	even_parity_sel	rw	0x0	'1' select even parity
6	break_irq	rw	0x0	
7	div_latch_acc	rw	0x0	Divisor Latch access enable
8	div_mode	rw	0x0	
9	break_en	rw	0x0	

17.5 modem_ctrl				0x40032010
Bits	Field Name	Acc	Default	Description
0	dtr	rw	0x0	Data terminal ready
1	rts	rw	0x0	Request to send
2	out1	rw	0x0	
3	out2	rw	0x0	
4	loopback	rw	0x0	
5	auto_flow_ctrl_enable	rw	0x0	Auto flow control enable
6	serial_infrared_radiation_en	rw	0x0	Serial infrared radiation enable
7	auto_det	rw	0x0	
8	clk_p	rw	0x0	1: 48M 0: 24M

17.6 line_status				0x40032014
Bits	Field Name	Acc	Default	Description
0	rx_data_ready	ro	0x0	Rx Data ready(rxfifo not empty)
1	rx_overflow	ro	0x0	Overflow error
5	tx_fifo_empty	ro	0x0	Tx fifo empty or almost empty
6	tx_empty	ro	0x0	Tx fifo empty and shift register empty
7	rx_fifo_error	ro	0x0	Rx fifo error
8	trigger_ready	ro	0x0	Trigger ready(rxfifo not empty)

17.7 modem_status				0x40032018
Bits	Field Name	Acc	Default	Description
0	delayed_cts	ro	0x0	
4	cts	ro	0x0	

17.8 scratchpad				0x4003201C
Bits	Field Name	Acc	Default	Description
6 : 0	scratchpad	rw	0x0	not used

17.9 fifo_status				0x40032020
Bits	Field Name	Acc	Default	Description
7 : 0	tx_count	ro	0x0	TX fifo count
16 : 9	rx_count	ro	0x0	RX fifo count
18	tx_fifo_empty	ro	0x1	TX fifo empty
19	tx_fifo_full	ro	0x0	TX fifo full
20	rx_fifo_empty	ro	0x1	RX fifo empty
21	rx_fifo_full	ro	0x0	RX fifo full

17.10 fifo_trigger				0x40032024
Bits	Field Name	Acc	Default	Description
7 : 0	rx_trigger_th	rw	0x10	
16 : 9	tx_trigger_th	rw	0x10	
18	rx_tout_trig_en	rw	0x0	Enable rx legacy dma req triggered when timeout

17.11 divisor_latch2				0x40032028
Bits	Field Name	Acc	Default	Description
7 : 0	divisor_adjust_coef	rw	0x0	accuray adjust baudrate

17.12 counter_real				0x4003203C
Bits	Field Name	Acc	Default	Description
19 : 0	counter_real	ro	0x0	

17.13 div_real_slow				0x40032040
Bits	Field Name	Acc	Default	Description
31 : 0	div_real_slow	rw	0x1000E	when clk_p is 0: slow div_real = div_real_slow[15:1]; slow div_adjust_real = div_real_slow[31:24]; when clk_p is 1: slow div_real = div_real_slow[15:0]; slow div_adjust_real = div_real_slow[23:16];

17.14 div_real_fast				0x40032044
Bits	Field Name	Acc	Default	Description
31 : 0	div_real_fast	rw	0x660001	when clk_p is 0: fast div_real = div_real_fast[15:1]; fast div_adjust_real = div_real_fast[31:24]; when clk_p is 1: fast div_real = div_real_fast[15:0]; fast div_adjust_real = div_real_fast[23:16];

17.15 tports_sel				0x40032048
Bits	Field Name	Acc	Default	Description
7 : 0	tports_sel	rw	0x0	Tports Select

18 uart1

18.1 txrx_fifo_divl				0x40033000
Bits	Field Name	Acc	Default	Description
7 : 0	txrx_data_divl	rw	0x0	Tx data(when write data), Rx data(when read data), Divisor latch(low) config when divisor latch is enable.

18.2 int_en_divh				0x40033004
Discription: Interrupt enable register; divisor latch high when divisor latch is enable.				
Bits	Field Name	Acc	Default	Description
0	rx_int_en_divh_0	rw	0x0	Enable Received Data Available Interrupt; Divisor latch high bit 0 when divisor latch is enable.
1	tx_int_en_divh_1	rw	0x0	Enable Transmit Holding Register Empty Interrupt; Divisor latch high bit 1 when divisor latch is enable.
2	lstatus_int_en_divh_2	rw	0x0	Enable Receiver Line Status Interrupt; Divisor latch high bit 2 when divisor latch is enable.
3	mstatus_int_en_divh_3	rw	0x0	Enable Modem Status Interrupt; Divisor latch high bit 3 when divisor latch is enable.
4	divh_4	rw	0x0	Divisor latch high bit 4 when divisor latch is enable.
5	timeout_int_en_divh_5	rw	0x0	Enable Timeout Interrupt; Divisor latch high bit 5 when divisor latch is enable.

6	divh_6	rw	0x0	Divisor latch high bit 6 when divisor latch is enable.
7	ptime_divh_7	rw	0x0	Programmable THRE Interrupt Mode Enable; Divisor latch high bit 7 when divisor latch is enable.

18.3 int_id_fifo_ctrl				0x40033008
Discription: Interrupt identity register or fifo control register				
Bits	Field Name	Acc	Default	Description
0	int_id_0_fifo_en	rw	0x1	Read: Interrupt identity bit 0, reset value is '0'; Write: Fifo enable, reset value is '1'
1	int_id_1_rx_reset	rw	0x0	Read: Interrupt identity bit 1; Write: Receiver reset
2	int_id_2_tx_reset	rw	0x0	Read: Interrupt identity bit 2; Write: Transmit reset
3	int_id_3_dma_mode	rw	0x0	Read: Interrupt identity bit 3; Write: Dma mode enable
7 : 6	fifo_enabled	ro	0x3	

18.4 line_ctrl				0x4003300C
Bits	Field Name	Acc	Default	Description
1 : 0	data_length_sel	rw	0x3	0: 5 bit 1: 6 bit 2: 7 bit 3: 8 bit
2	stop	rw	0x0	Number of stop bits
3	parity_en	rw	0x0	Parity enable
4	even_parity_sel	rw	0x0	'1' select even parity
6	break_irq	rw	0x0	
7	div_latch_acc	rw	0x0	Divisor Latch access enable
8	div_mode	rw	0x0	
9	break_en	rw	0x0	

18.5 modem_ctrl				0x40033010
Bits	Field Name	Acc	Default	Description
0	dtr	rw	0x0	Data terminal ready
1	rts	rw	0x0	Request to send
2	out1	rw	0x0	
3	out2	rw	0x0	
4	loopback	rw	0x0	
5	auto_flow_ctrl_enable	rw	0x0	Auto flow control enable
6	serial_infrared_radiation_en	rw	0x0	Serial infrared radiation enable
7	auto_det	rw	0x0	
8	clk_p	rw	0x0	1: 48M 0: 24M

18.6 line_status				0x40033014
Bits	Field Name	Acc	Default	Description
0	rx_data_ready	ro	0x0	Rx Data ready(rxfifo not empty)
1	rx_overflow	ro	0x0	Overflow error
5	tx_fifo_empty	ro	0x0	Tx fifo empty or almost empty
6	tx_empty	ro	0x0	Tx fifo empty and shift register empty
7	rx_fifo_error	ro	0x0	Rx fifo error
8	trigger_ready	ro	0x0	Trigger ready(rxfifo not empty)

18.7 modem_status				0x40033018
Bits	Field Name	Acc	Default	Description
0	delayed_cts	ro	0x0	
4	cts	ro	0x0	

18.8 scratchpad				0x4003301C
Bits	Field Name	Acc	Default	Description
6 : 0	scratchpad	rw	0x0	not used

18.9 fifo_status				0x40033020
Bits	Field Name	Acc	Default	Description
7 : 0	tx_count	ro	0x0	TX fifo count
16 : 9	rx_count	ro	0x0	RX fifo count
18	tx_fifo_empty	ro	0x1	TX fifo empty
19	tx_fifo_full	ro	0x0	TX fifo full
20	rx_fifo_empty	ro	0x1	RX fifo empty
21	rx_fifo_full	ro	0x0	RX fifo full

18.10 fifo_trigger				0x40033024
Bits	Field Name	Acc	Default	Description
7 : 0	rx_trigger_th	rw	0x10	
16 : 9	tx_trigger_th	rw	0x10	
18	rx_tout_trig_en	rw	0x0	Enable rx legacy dma req triggered when timeout

18.11 divisor_latch2				0x40033028
Bits	Field Name	Acc	Default	Description
7 : 0	divisor_adjust_coef	rw	0x0	accuray adjust baudrate

18.12 counter_real				0x4003303C
Bits	Field Name	Acc	Default	Description
19 : 0	counter_real	ro	0x0	

18.13 div_real_slow				0x40033040
Bits	Field Name	Acc	Default	Description

31 : 0	div_real_slow	rw	0x1000E	when clk_p is 0: slow div_real = div_real_slow[15:1];
				slow div_adjust_real = div_real_slow[31:24];
				when clk_p is 1: slow div_real = div_real_slow[15:0];
				slow div_adjust_real = div_real_slow[23:16];

18.14 div_real_fast				0x40033044
Bits	Field Name	Acc	Default	Description

31 : 0	div_real_fast	rw	0x660001	when clk_p is 0: fast div_real = div_real_fast[15:1];
				fast div_adjust_real = div_real_fast[31:24];
				when clk_p is 1: fast div_real = div_real_fast[15:0];
				fast div_adjust_real = div_real_fast[23:16];

18.15 tports_sel				0x40033048
Bits	Field Name	Acc	Default	Description
7 : 0	tports_sel	rw	0x0	Tports Select

19 uart2

19.1 txrx_fifo_divl				0x40034000
Bits	Field Name	Acc	Default	Description
7 : 0	txrx_data_divl	rw	0x0	Tx data(when write data), Rx data(when read data), Divisor latch(low) config when divisor latch is enable.

19.2 int_en_divh				0x40034004
Discription: Interrupt enable register; divisor latch high when divisor latch is enable.				
Bits	Field Name	Acc	Default	Description
0	rx_int_en_divh_0	rw	0x0	Enable Received Data Available Interrupt; Divisor latch high bit 0 when divisor latch is enable.
1	tx_int_en_divh_1	rw	0x0	Enable Transmit Holding Register Empty Interrupt; Divisor latch high bit 1 when divisor latch is enable.
2	lstatus_int_en_divh_2	rw	0x0	Enable Receiver Line Status Interrupt; Divisor latch high bit 2 when divisor latch is enable.
3	mstatus_int_en_divh_3	rw	0x0	Enable Modem Status Interrupt; Divisor latch high bit 3 when divisor latch is enable.
4	divh_4	rw	0x0	Divisor latch high bit 4 when divisor latch is enable.
5	timeout_int_en_divh_5	rw	0x0	Enable Timeout Interrupt; Divisor latch high bit 5 when divisor latch is enable.
6	divh_6	rw	0x0	Divisor latch high bit 6 when divisor latch is enable.
7	ptime_divh_7	rw	0x0	Programmable THRE Interrupt Mode Enable; Divisor latch high bit 7 when divisor latch is enable.

19.3 int_id_fifo_ctrl				0x40034008
Discription: Interrupt identity register or fifo control register				
Bits	Field Name	Acc	Default	Description
0	int_id_0_fifo_en	rw	0x1	Read: Interrupt identity bit 0, reset value is '0'; Write: Fifo enable, reset value is '1'
1	int_id_1_rx_reset	rw	0x0	Read: Interrupt identity bit 1; Write: Receiver reset
2	int_id_2_tx_reset	rw	0x0	Read: Interrupt identity bit 2; Write: Transmit reset
3	int_id_3_dma_mode	rw	0x0	Read: Interrupt identity bit 3; Write: Dma mode enable
7 : 6	fifo_enabled	ro	0x3	

19.4 line_ctrl				0x4003400C
Bits	Field Name	Acc	Default	Description
1 : 0	data_length_sel	rw	0x3	0: 5 bit 1: 6 bit 2: 7 bit 3: 8 bit
2	stop	rw	0x0	Number of stop bits
3	parity_en	rw	0x0	Parity enable
4	even_parity_sel	rw	0x0	'1' select even parity
6	break_irq	rw	0x0	
7	div_latch_acc	rw	0x0	Divisor Latch access enable
8	div_mode	rw	0x0	
9	break_en	rw	0x0	

19.5 modem_ctrl				0x40034010
Bits	Field Name	Acc	Default	Description
0	dtr	rw	0x0	Data terminal ready
1	rts	rw	0x0	Request to send
2	out1	rw	0x0	
3	out2	rw	0x0	
4	loopback	rw	0x0	
5	auto_flow_ctrl_enable	rw	0x0	Auto flow control enable
6	serial_infrared_radiation_en	rw	0x0	Serial infrared radiation enable
7	auto_det	rw	0x0	
8	clk_p	rw	0x0	1: 48M 0: 24M

19.6 line_status	0x40034014

Bits	Field Name	Acc	Default	Description
0	rx_data_ready	ro	0x0	Rx Data ready(rxfifo not empty)
1	rx_overflow	ro	0x0	Overflow error
5	tx_fifo_empty	ro	0x0	Tx fifo empty or almost empty
6	tx_empty	ro	0x0	Tx fifo empty and shift register empty
7	rx_fifo_error	ro	0x0	Rx fifo error
8	trigger_ready	ro	0x0	Trigger ready(rxfifo not empty)

19.7 modem_status				0x40034018
Bits	Field Name	Acc	Default	Description
0	delayed_cts	ro	0x0	
4	cts	ro	0x0	

19.8 scratchpad				0x4003401C
Bits	Field Name	Acc	Default	Description
6 : 0	scratchpad	rw	0x0	not used

19.9 fifo_status				0x40034020
Bits	Field Name	Acc	Default	Description
7 : 0	tx_count	ro	0x0	TX fifo count
16 : 9	rx_count	ro	0x0	RX fifo count
18	tx_fifo_empty	ro	0x1	TX fifo empty
19	tx_fifo_full	ro	0x0	TX fifo full
20	rx_fifo_empty	ro	0x1	RX fifo empty
21	rx_fifo_full	ro	0x0	RX fifo full

19.10 fifo_trigger				0x40034024
Bits	Field Name	Acc	Default	Description
7 : 0	rx_trigger_th	rw	0x10	
16 : 9	tx_trigger_th	rw	0x10	
18	rx_tout_trig_en	rw	0x0	Enable rx legacy dma req triggered when timeout

19.11 divisor_latch2				0x40034028
Bits	Field Name	Acc	Default	Description
7 : 0	divisor_adjust_coef	rw	0x0	accuray adjust baudrate

19.12 counter_real				0x4003403C
Bits	Field Name	Acc	Default	Description
19 : 0	counter_real	ro	0x0	

19.13 div_real_slow				0x40034040
Bits	Field Name	Acc	Default	Description
31 : 0	div_real_slow	rw	0x1000E	when clk_p is 0: slow div_real = div_real_slow[15:1]; slow div_adjust_real = div_real_slow[31:24]; when clk_p is 1: slow div_real = div_real_slow[15:0]; slow div_adjust_real = div_real_slow[23:16];

19.14 div_real_fast				0x40034044
Bits	Field Name	Acc	Default	Description

31 : 0	div_real_fast	rw	0x660001	when clk_p is 0: fast div_real = div_real_fast[15:1];
				fast div_adjust_real = div_real_fast[31:24];
				when clk_p is 1: fast div_real = div_real_fast[15:0];
				fast div_adjust_real = div_real_fast[23:16];

19.15 tports_sel				0x40034048
Bits	Field Name	Acc	Default	Description
7 : 0	tports_sel	rw	0x0	Tports Select

20 mailbox

20.1 app2emb_trigger				0x40035000
Bits	Field Name	Acc	Default	Description
31 : 0	app2emb_trigger	rw	0x0	write to set

20.2 emb2app_rawstatus				0x40035004
Bits	Field Name	Acc	Default	Description
31 : 0	emb2app_rawstatus	ro	0x0	

20.3 emb2app_ack				0x40035008
Bits	Field Name	Acc	Default	Description
31 : 0	emb2app_ack	wo	0x0	write to clear

20.4 emb2app_unmaskset				0x4003500C
Bits	Field Name	Acc	Default	Description
31 : 0	emb2app_unmaskset	rw	0x0	write to set

20.5 emb2app_unmaskclear				0x40035010
Bits	Field Name	Acc	Default	Description
31 : 0	emb2app_unmaskclear	rw	0x0	write to clear

20.6 emb2app_linesel_low				0x40035014
Bits	Field Name	Acc	Default	Description
31 : 0	emb2app_linesel_low	rw	0x0	

20.7 emb2app_linesel_high				0x40035018
Bits	Field Name	Acc	Default	Description
31 : 0	emb2app_linesel_high	rw	0x0	

20.8 emb2app_status				0x4003501C
Bits	Field Name	Acc	Default	Description
31 : 0	emb2app_status	ro	0x0	

20.9 mutex0				0x40035040
Bits	Field Name	Acc	Default	Description
0	mutex0	rw	0x1	read to clear

20.10 mutex1				0x40035044
Bits	Field Name	Acc	Default	Description
0	mutex1	rw	0x1	read to clear

20.11 mutex2				0x40035048
Bits	Field Name	Acc	Default	Description
0	mutex2	rw	0x1	read to clear

20.12 mutex3				0x4003504C
Bits	Field Name	Acc	Default	Description
0	mutex3	rw	0x1	read to clear

20.13 mutex4				0x40035050
Bits	Field Name	Acc	Default	Description
0	mutex4	rw	0x1	read to clear

20.14 mutex5				0x40035054
Bits	Field Name	Acc	Default	Description
0	mutex5	rw	0x1	read to clear

20.15 mutex6				0x40035058
Bits	Field Name	Acc	Default	Description
0	mutex6	rw	0x1	read to clear

20.16 mutex7				0x4003505C
Bits	Field Name	Acc	Default	Description
0	mutex7	rw	0x1	read to clear

20.17 comreg0				0x40035080
Bits	Field Name	Acc	Default	Description
31 : 0	comreg0	rw	0x0	common register

20.18 comreg1				0x40035084
Bits	Field Name	Acc	Default	Description
31 : 0	comreg1	rw	0x0	common register

20.19 comreg2				0x40035088
Bits	Field Name	Acc	Default	Description
31 : 0	comreg2	rw	0x0	common register

20.20 comreg3				0x4003508C
Bits	Field Name	Acc	Default	Description
31 : 0	comreg3	rw	0x0	common register

20.21 comreg4				0x40035090
Bits	Field Name	Acc	Default	Description
31 : 0	comreg4	rw	0x0	common register

20.22 comreg5				0x40035094
Bits	Field Name	Acc	Default	Description
31 : 0	comreg5	rw	0x0	common register

20.23 comreg6				0x40035098
Bits	Field Name	Acc	Default	Description
31 : 0	comreg6	rw	0x0	common register

20.24 comreg7				0x4003509C
Bits	Field Name	Acc	Default	Description
31 : 0	comreg7	rw	0x0	common register

20.25 emb2app_trigger				0x40035100
Bits	Field Name	Acc	Default	Description
31 : 0	emb2app_trigger	rw	0x0	write to set

20.26 app2emb_rawstatus				0x40035104
Bits	Field Name	Acc	Default	Description
31 : 0	app2emb_rawstatus	ro	0x0	

20.27 app2emb_ack				0x40035108
Bits	Field Name	Acc	Default	Description
31 : 0	app2emb_ack	wo	0x0	write to clear

20.28 app2emb_unmaskset				0x4003510C
Bits	Field Name	Acc	Default	Description
31 : 0	app2emb_unmaskset	rw	0x0	write to set

20.29 app2emb_unmaskclear				0x40035110
Bits	Field Name	Acc	Default	Description
31 : 0	app2emb_unmaskclear	rw	0x0	write to clear

20.30 app2emb_linesel_low				0x40035114
Bits	Field Name	Acc	Default	Description
31 : 0	app2emb_linesel_low	rw	0x0	

20.31 app2emb_linesel_high				0x40035118
Bits	Field Name	Acc	Default	Description
31 : 0	app2emb_linesel_high	rw	0x0	

20.32 app2emb_status				0x4003511C
Bits	Field Name	Acc	Default	Description
31 : 0	app2emb_status	ro	0x0	

20.33 g1_app2emb_trigger				0x40035200
Bits	Field Name	Acc	Default	Description
31 : 0	g1_app2emb_trigger	rw	0x0	write to set

20.34 g1_emb2app_rawstatus				0x40035204
Bits	Field Name	Acc	Default	Description
31 : 0	g1_emb2app_rawstatus	ro	0x0	

20.35 g1_emb2app_ack				0x40035208
Bits	Field Name	Acc	Default	Description
31 : 0	g1_emb2app_ack	wo	0x0	write to clear

20.36 g1_emb2app_unmaskset				0x4003520C
Bits	Field Name	Acc	Default	Description
31 : 0	g1_emb2app_unmaskset	rw	0x0	write to set

20.37 g1_emb2app_unmaskclear				0x40035210
Bits	Field Name	Acc	Default	Description
31 : 0	g1_emb2app_unmaskclear	rw	0x0	write to clear

20.38 g1_emb2app_linesel_low				0x40035214
Bits	Field Name	Acc	Default	Description
31 : 0	g1_emb2app_linesel_low	rw	0x0	

20.39 g1_emb2app_linesel_high				0x40035218
Bits	Field Name	Acc	Default	Description
31 : 0	g1_emb2app_linesel_high	rw	0x0	

20.40 g1_emb2app_status				0x4003521C
Bits	Field Name	Acc	Default	Description
31 : 0	g1_emb2app_status	ro	0x0	

20.41 g1_mutex0				0x40035240
Bits	Field Name	Acc	Default	Description
0	g1_mutex0	rw	0x1	read to clear

20.42 g1_mutex1				0x40035244
Bits	Field Name	Acc	Default	Description
0	g1_mutex1	rw	0x1	read to clear

20.43 g1_mutex2				0x40035248
Bits	Field Name	Acc	Default	Description
0	g1_mutex2	rw	0x1	read to clear

20.44 g1_mutex3				0x4003524C
Bits	Field Name	Acc	Default	Description
0	g1_mutex3	rw	0x1	read to clear

20.45 g1_mutex4				0x40035250
Bits	Field Name	Acc	Default	Description
0	g1_mutex4	rw	0x1	read to clear

20.46 g1_mutex5				0x40035254
Bits	Field Name	Acc	Default	Description
0	g1_mutex5	rw	0x1	read to clear

20.47 g1_mutex6				0x40035258
Bits	Field Name	Acc	Default	Description
0	g1_mutex6	rw	0x1	read to clear

20.48 g1_mutex7				0x4003525C
Bits	Field Name	Acc	Default	Description
0	g1_mutex7	rw	0x1	read to clear

20.49 g1_comreg0				0x40035280
Bits	Field Name	Acc	Default	Description
31 : 0	g1_comreg0	rw	0x0	common register

20.50 g1_comreg1				0x40035284
Bits	Field Name	Acc	Default	Description
31 : 0	g1_comreg1	rw	0x0	common register

20.51 g1_comreg2				0x40035288
Bits	Field Name	Acc	Default	Description
31 : 0	g1_comreg2	rw	0x0	common register

20.52 g1_comreg3				0x4003528C
Bits	Field Name	Acc	Default	Description
31 : 0	g1_comreg3	rw	0x0	common register

20.53 g1_comreg4				0x40035290
Bits	Field Name	Acc	Default	Description
31 : 0	g1_comreg4	rw	0x0	common register

20.54 g1_comreg5				0x40035294
Bits	Field Name	Acc	Default	Description
31 : 0	g1_comreg5	rw	0x0	common register

20.55 g1_comreg6				0x40035298
Bits	Field Name	Acc	Default	Description
31 : 0	g1_comreg6	rw	0x0	common register

20.56 g1_comreg7				0x4003529C
Bits	Field Name	Acc	Default	Description
31 : 0	g1_comreg7	rw	0x0	common register

20.57 g1_emb2app_trigger				0x40035300
Bits	Field Name	Acc	Default	Description
31 : 0	g1_emb2app_trigger	rw	0x0	write to set

20.58 g1_app2emb_rawstatus				0x40035304
Bits	Field Name	Acc	Default	Description
31 : 0	g1_app2emb_rawstatus	ro	0x0	

20.59 g1_app2emb_ack				0x40035308
Bits	Field Name	Acc	Default	Description
31 : 0	g1_app2emb_ack	wo	0x0	write to clear

20.60 g1_app2emb_unmaskset				0x4003530C
Bits	Field Name	Acc	Default	Description
31 : 0	g1_app2emb_unmaskset	rw	0x0	write to set

20.61 g1_app2emb_unmaskclear				0x40035310
Bits	Field Name	Acc	Default	Description
31 : 0	g1_app2emb_unmaskclear	rw	0x0	write to clear

20.62 g1_app2emb_linesel_low				0x40035314
Bits	Field Name	Acc	Default	Description
31 : 0	g1_app2emb_linesel_low	rw	0x0	

20.63 g1_app2emb_linesel_high				0x40035318
Bits	Field Name	Acc	Default	Description
31 : 0	g1_app2emb_linesel_high	rw	0x0	

20.64 g1_app2emb_status				0x4003531C
Bits	Field Name	Acc	Default	Description
31 : 0	g1_app2emb_status	ro	0x0	

21 sd_host

21.1 ctrl				0x40036000
Bits	Field Name	Acc	Default	Description
2 : 0	endian	rw	0x0	Endian Type SD TX FIFO Endian 3'b000: {pwdata_byte[3],pwdata_byte[2],pwdata_byte[1],pwdata_byte 3'b001: {pwdata_byte[0],pwdata_byte[1],pwdata_byte[2],pwdata_byte 3'b010: {pwdata_byte[1],pwdata_byte[0],pwdata_byte[3],pwdata_byte 3'b011: pwdata_bit[0-31] 3'b100: {pwdata_byte[2],pwdata_byte[3],pwdata_byte[0],pwdata_byte default: 32'h0
3	reset_n	rw	0x1	Software reset, active Low Software reset for TX and RX FIFOs of Sd host, active low
4	dma_rx_en	rw	0x0	Enable rx dma req triggered when rxfifo level arrived dma_rx_th
5	dma_tx_en	rw	0x0	Enable tx dma req triggered when txfifo level arrived dma_tx_th
11 : 8	dma_rx_th	rw	0x0	Rx dma req triggered threshold
19 : 16	dma_tx_th	rw	0x0	Tx dma req triggered threshold

21.2 txfifo_entry				0x40036008
Bits	Field Name	Acc	Default	Description

31 : 0	txfifo_entry	wo	0x0	Tx FIFO Write Entry Write data for 8x32 bit TxFIFO

21.3 rxfifo_entry				0x4003600C
Bits	Field Name	Acc	Default	Description
31 : 0	rxfifo_entry	ro	0x0	Rx FIFO Read Entry Read data from 8x32 bit RxFIFO

21.4 cfg				0x40036800
Bits	Field Name	Acc	Default	Description
0	cmd_start	rw	0x0	Configuration begin
4	response_en	rw	0x0	Response enable
6 : 5	response_type	rw	0x0	Response select register 3:Reserved 2:R2 1:R3 0:Other
8	read_write_en	rw	0x0	Read/write enable
9	write_mode	rw	0x0	'1' means write operation,'0' means read operation. 0:READ 1:WRITE
10	multi_block_mode	rw	0x0	'1' means multiple block data operation. 0:SIMPLE 1:MULTIPLE
16	auto_cmd12_en	rw	0x1	Auto cmd12 enable

21.5 status				0x40036804
Bits	Field Name	Acc	Default	Description
0	sd_not_over	ro	0x0	'1' means the sd/mmc operation is not over.
1	busy	ro	0x0	'1' means sd modem is busy.
2	data_line_busy	ro	0x0	'1' means the data line is busy.
8	response_error	ro	0x0	Response CRC checks error register, '1' means response CRC check error.
9	no_response_error	ro	0x0	'1' means the card has no response to command.

21.6 cmd_index				0x40036808
Bits	Field Name	Acc	Default	Description
5 : 0	command	rw	0x0	Sd command register.

21.7 cmd_arg				0x4003680C
Bits	Field Name	Acc	Default	Description
31 : 0	argument	rw	0x0	Sd command argument register, write data to the Sd card.

21.8 rsp_index				0x40036810
Bits	Field Name	Acc	Default	Description
5 : 0	resp	ro	0x0	Sd response index register.

21.9 rsp_arg3				0x40036814
Bits	Field Name	Acc	Default	Description
31 : 0	arg3	ro	0x0	Response argument of R1, R3 and R6, or 127 to 96 bit response argument of R2.

21.10 rsp_arg2				0x40036818
Bits	Field Name	Acc	Default	Description
31 : 0	arg2	ro	0x0	95 to 64 bit response argument of R2.

21.11 rsp_arg1				0x4003681C
Bits	Field Name	Acc	Default	Description
31 : 0	arg1	ro	0x0	63 to 32 bit response argument of R2.

21.12 rsp_arg0				0x40036820
Bits	Field Name	Acc	Default	Description
31 : 0	arg0	ro	0x0	31 to 0 bit response argument of R2.

21.13 dline_width				0x40036824
Bits	Field Name	Acc	Default	Description
3 : 0	dline_width	rw	0x0	Sd data width: 0x1: 1 data line 0x2: 2 reserved 0x4: 4 data lines 0x8: 8 data lines

21.14 block_size				0x40036828
Bits	Field Name	Acc	Default	Description
3 : 0	block_size	rw	0x0	Sd size of one block: 0-1:reserved 2: 1 word 3: 2 words 4: 4 words 5: 8 words 6: 16 words 11: 512 words 12-15 reserved

21.15 block_cnt				0x4003682C
Bits	Field Name	Acc	Default	Description
15 : 0	block_cnt	rw	0x0	Block number that wants to transfer.

21.16 int_status				0x40036830
Bits	Field Name	Acc	Default	Description
4	data_done_int	ro	0x0	Read write correct int raw status.
5	txdma_done_int	ro	0x0	'1' means rx dma done.
6	rxdma_done_int	ro	0x0	'1' means tx dma done.
14	data_done_cause	ro	0x0	Read write correct int status after masking
15	txdma_done_cause	ro	0x0	'1' means rx dma done is the source of interrupt.
16	rx_dma_done_cause	ro	0x0	'1' means tx dma done is the source of interrupt.

21.17 int_enable				0x40036834
Bits	Field Name	Acc	Default	Description
4	data_done_en	rw	0x0	When data transmission is over, '0' means INT is disable.
5	txdma_done_en	rw	0x0	When tx dma done, '0' means INT is disabled.
6	rxdma_done_en	rw	0x0	When rx dma done, '0' means INT is disabled.

21.18 int_clear	0x40036838

Bits	Field Name	Acc	Default	Description
4	data_done_clear	wo	0x0	Write a '1' to this bit to clear the data_over interrupt.
5	txdma_done_clear	wo	0x0	Write a '1' to this bit to clear the txdma_done interrupt.
6	rxdma_done_clear	wo	0x0	Write a '1' to this bit to clear the rxdma_done interrupt.

21.19 trans_speed				0x4003683C
Bits	Field Name	Acc	Default	Description
11 : 0	trans_speed	rw	0x9	Mclk = Pclk/(2*(trans_speed +1)).

21.20 mclk_ctrl				0x40036840
Bits	Field Name	Acc	Default	Description
3 : 0	mclk_delay	rw	0x0	This register may delay the mclk output. When MCLK_DELAY = n, Mclk is outputted with n Pclk.
4	mclk_inv_en	rw	0x0	Mclk invert enable
8	mclk_disable	rw	0x1	Mclk disable

21.21 fifo_status				0x40036844
Bits	Field Name	Acc	Default	Description
11 : 8	rxfifo_level	ro	0x0	Rx fifo level monitor
19 : 16	txfifo_level	ro	0x8	Tx fifo level monitor

22 aud_proc

22.1 aud_proc_function_id				0x40037000
Bits	Field Name	Acc	Default	Description
15 : 0	rev_id	ro	0x0	revision id
31 : 16	func_id	ro	0x302	function id

22.2 aud_iis_cfg				0x40037004
Bits	Field Name	Acc	Default	Description
0	aud_iis_enable	rw	0x0	enable aud_iis
1	aud_iis_adc_path_reset	rw	0x0	reset aud_iis adc path
2	aud_iis_dac_path_reset	rw	0x0	reset aud_iis dac path
3	auto_clock_gating_en	rw	0x1	enable auto clock gating to save power
5 : 4	tx_lr_fifo_share_en	rw	0x0	1: tx L/R share one buffer. 0: tx only txL one buffer
7 : 6	rx_lr_fifo_share_en	rw	0x0	1: rx L/R share one buffer. 0: only rxLone buffer
8	tx_burst_mode	rw	0x0	1: tx channel burst incr 4 mode, 0: tx channel single mode
9	rx_burst_mode	rw	0x0	1: rx channel burst incr 4 mode, 0: rx channel single mode
31 : 25	monitor_sel	rw	0x0	

22.3 aud_iis_tx_cfg_ch01				0x40037008
Bits	Field Name	Acc	Default	Description
0	tx_en_ch_01	rw	0x0	channel enable
1	tx_fifo_flush_ch_01	rw	0x0	flush fifo 1'b1: flush status 1'b0: normal status
3 : 2	tx_mode_ch_01	rw	0x0	channel 0and1 bit mode 2'b00: 16-bit mode 2'b01: 24-bit mode 2'b1x: 32-bit mode

5 : 4	tx_fifo_stat_ch_01	ro	0x0	fifo_stat 2'b00: emptyq̃uarter 2'b01: quarterh̃alf 2'b10: halfF̃ull 2'b11: full

22.4 aud_iis_tx_cfg_ch23				0x4003700C
Bits	Field Name	Acc	Default	Description
0	tx_en_ch_23	rw	0x0	channel enable
1	tx_fifo_flush_ch_23	rw	0x0	flush fifo 1'b1: flush status 1'b0: normal status
3 : 2	tx_mode_ch_23	rw	0x0	channel 0and1 bit mode 2'b00: 16-bit mode 2'b01: 24-bit mode 2'b1x: 32-bit mode
5 : 4	tx_fifo_stat_ch_23	ro	0x0	fifo_stat 2'b00: emptyq̃uarter 2'b01: quarterh̃alf 2'b10: halfF̃ull 2'b11: full

22.5 aud_iis_rx_cfg_ch01				0x40037010
Bits	Field Name	Acc	Default	Description
0	rx_en_ch_01	rw	0x0	channel enable
1	rx_fifo_flush_ch_01	rw	0x0	flush fifo 1'b1: flush status 1'b0: normal status
3 : 2	rx_mode_ch_01	rw	0x0	channel mode 1'b0: 16-bit mode 1'b1: 24-bit mode
5 : 4	rx_fifo_stat_ch_01	ro	0x0	fifo_stat 2'b00: emptyq̃uarter 2'b01: quarterh̃alf 2'b10: halfF̃ull 2'b11: full

22.6 aud_iis_rx_cfg_ch23				0x40037014
Bits	Field Name	Acc	Default	Description
0	rx_en_ch_23	rw	0x0	channel enable
1	rx_fifo_flush_ch_23	rw	0x0	flush fifo 1'b1: flush status 1'b0: normal status
3 : 2	rx_mode_ch_23	rw	0x0	channel mode 1'b0: 16-bit mode 1'b1: 24-bit mode
5 : 4	rx_fifo_stat_ch_23	ro	0x0	fifo_stat 2'b00: emptyq̃uarter 2'b01: quarterh̃alf 2'b10: halfF̃ull 2'b11: full

22.7 aud_intf_i2s_cfg0				0x4003701C
Bits	Field Name	Acc	Default	Description
1 : 0	swap_chlr_0	rw	0x0	Swap Channel L and Channel R.[0] [0] for output channel swap, 0: left, 1:right [1] for input channel swap, 0: left, 1: right
2	tx_data_half_cycle_dly_0	rw	0x0	delayed Audio data out by half cycle. 0:: NO_DLY 1:: DLY

3	lsb_0	rw	0x0	When high, the output data format is with the least significant bit first. 0:: MSB 1:: LSB
4	right_justified_0	rw	0x0	right justified mode.
9 : 5	bck_lrck_0	rw	0x0	configure extend cycles of bck after data transfer is finished. Voice_Mode:: each sample takes wlen + tx_bck_lrck BCLK cycle. Audio_Mode:: each sample takes 2*(wlen + tx_bck_lrck) BCLK cycle. 2 times than Voice
11 : 10	wlen_0	rw	0x0	i2s data length 00: 16-bit 01: 20-bit 10: 24-bit 11: 32-bit
12	lrck_pol_0	rw	0x0	configure LRCK polarity. 0:: LEFT_H_RIGHT_L: high level on LRCK means left channel, low level on LRCK means right channel. 1:: LEFT_L_RIGHT_H: high level on LRCK means right channel, low level on LRCK means left channel. Note: this bit should be set to '0' (LEFT_H_RIGHT_L) in voice mode.
13	bck_pol_0	rw	0x0	if Master Mode, invert BCLK out. if slave Mode, invert BCLK in. 0:: NORMAL 1:: INVERT
14	bckout_gate_0	rw	0x0	Sets the BckOut gating. This bit decide if aud intf continue to output BCK clock after data has been sent. 0:: NO_GATE 1:: GATED
15	rx_half_cycle_dly_0	rw	0x0	delayed Audio input data by half cycle. 0:: NO_DLY 1:: DLY
16	tx_lrck_half_cycle_dly_0	rw	0x0	delayed Audio LRCK by half cycle. 0:: NO_DLY 1:: DLY
18 : 17	rx_dly_0	rw	0x0	Indicates the delay between serial data in MSB and LRCK edge. 2'b00:: ALIGN: Digital audio in MSB is aligned with LRCLK edge. 2'b01:: DLY_1: Digital audio in MSB is 1 cycle delayed to LRCLK edge. 2'b10:: DLY_2: Digital audio in MSB is 2 cycle delayed to LRCLK edge. 2'b11:: DLY_3: Digital audio in MSB is 3 cycle delayed to LRCLK edge.
19	tx_dly_s_0	rw	0x0	ONLY for slave mode:: configure 1 cycle supplementary Tx delay. 0:: NO_DLY: No supplementary Tx delay. 1:: DLY: One Cycle supplementary Tx delay.
20	tx_dly_0	rw	0x0	configure the delay between serial data out MSB and LRCK edge. 0:: ALIGN: Digital audio out MSB is aligned with LRCLK edge. 1:: DLY_1: Digital audio out MSB is 1 cycle delayed to LRCLK edge
21	master_mode_0	rw	0x1	configure aud intf works in master mode (LRCLK and BCK timing signals are generated internally) or slave mode (LRCLK and BCK timing signals are generated externally). 0:: SLAVE 1:: MASTER

24 : 22	rx_serial_mode_0	rw	0x0	Configure serial aud intf mode. 0:: I2S_PCM 1:: VOICE 2:: DAI When mode is set DAI, the bit Master Mode should be set to '1'. Data should be sent out on falling edge, which requires either Bclk_Pol = '0' and Half_Cycle_DLY = '1' or Bclk_Pol = '1' and Half_Cycle_DLY = '0'. Bits Tx_DLY and BCK-Out_Gate must be configured to '0' and '1'. The DAI mode must NOT be modified after aud intf is enabled.
27 : 25	tx_serial_mode_0	rw	0x0	Configure serial aud intf mode. 0:: I2S_PCM 1:: VOICE 2:: DAI When mode is set DAI, the bit Master Mode should be set to '1'. Data should be sent out on falling edge, which requires either Bclk_Pol = '0' and Half_Cycle_DLY = '1' or Bclk_Pol = '1' and Half_Cycle_DLY = '0'. Bits Tx_DLY and BCK-Out_Gate must be configured to '0' and '1'. The DAI mode must NOT be modified after aud intf is enabled.
28	tx_off_0	rw	0x1	Disable aud intf Tx functions. Important:: if you want to do record only, you must set this bit otherwise aud intf state machine will not start. 0:: TX_ON: Both Tx Rx enabled. 1:: TX_OFF: Rx enabled only, Tx disabled.
30 : 29	tx_mode_0	rw	0x0	Configure mono or stereo format for Audio data out: 2'b00:: STEREO_STEREO: stereo input from DMA, stereo output to pin. 2'b01:: MONOL_STEREO_DUPLI: mono channel L input from DMA, stereo output duplicate in both channels to pin. 2'b10:: MONOR_STEREO_DUPLI: mono channel R input from DMA, stereo output duplicate in both channels to pin. 2'b11:: MONO_IN_MONO_OUT Funtion mono input from DMA, stereo output in left channel to pin, can be implemented by setting aud intf_tx_cfg_ch[1] or aud intf_tx_cfg_ch[0] disable. When works in DAI, or DSD mode, always select "00" mode STEREO_STEREO.
31	i2s_enable_0	rw	0x0	enable i2s interface

22.8 aud_intf_i2s_cfg1				0x40037020
Bits	Field Name	Acc	Default	Description
1 : 0	swap_chlr_1	rw	0x0	Swap Channel L and Channel R.[0] [0] for output channel swap, 0: left, 1:right [1] for input channel swap, 0: left, 1: right
2	tx_data_half_cycle_dly_1	rw	0x0	delayed Audio data out by half cycle. 0:: NO_DLY 1:: DLY
3	lsb_1	rw	0x0	When high, the output data format is with the least significant bit first. 0:: MSB 1:: LSB
4	right_justified_1	rw	0x0	right justified mode.
9 : 5	bck_lrck_1	rw	0x0	configure extend cycles of bck after data transfer is finished. Voice_Mode:: each sample takes wlen + tx_bck_lrck BCLK cycle. Audio_Mode:: each sample takes 2*(wlen + tx_bck_lrck) BCLK cycle. 2 times than Voice
11 : 10	wlen_1	rw	0x0	i2s data length 00: 16-bit 01: 20-bit 10: 24-bit 11: 32-bit

12	lrck_pol_1	rw	0x0	configure LRCK polarity. 0:: LEFT_H_RIGHT_L: high level on LRCK means left channel, low level on LRCK means right channel. 1:: LEFT_L_RIGHT_H: high level on LRCK means right channel, low level on LRCK means left channel. Note: this bit should be set to '0' (LEFT_H_RIGHT_L) in voice mode.
13	bck_pol_1	rw	0x0	if Master Mode, invert BCLK out. if slave Mode, invert BCLK in. 0:: NORMAL 1:: INVERT
14	bckout_gate_1	rw	0x0	Sets the BckOut gating. This bit decide if aud intf continue to output BCK clock after data has been sent. 0:: NO_GATE 1:: GATED
15	rx_half_cycle_dly_1	rw	0x0	delayed Audio input data by half cycle. 0:: NO_DLY 1:: DLY
16	tx_lrck_half_cycle_dly_1	rw	0x0	delayed Audio output LRCK by half cycle. 0:: NO_DLY 1:: DLY
18 : 17	rx_dly_1	rw	0x0	Indicates the delay between serial data in MSB and LRCK edge. 2'b00:: ALIGN: Digital audio in MSB is aligned with LRCLK edge. 2'b01:: DLY_1: Digital audio in MSB is 1 cycle delayed to LRCLK edge. 2'b10:: DLY_2: Digital audio in MSB is 2 cycle delayed to LRCLK edge. 2'b11:: DLY_3: Digital audio in MSB is 3 cycle delayed to LRCLK edge.
19	tx_dly_s_1	rw	0x0	ONLY for slave mode:: configure 1 cycle supplementary Tx delay. 0:: NO_DLY: No supplementary Tx delay. 1:: DLY: One Cycle supplementary Tx delay.
20	tx_dly_1	rw	0x0	configure the delay between serial data out MSB and LRCK edge. 0:: ALIGN: Digital audio out MSB is aligned with LRCLK edge. 1:: DLY_1: Digital audio out MSB is 1 cycle delayed to LRCLK edge
21	master_mode_1	rw	0x1	configure aud intf works in master mode (LRCLK and BCK timing signals are generated internally) or slave mode (LRCLK and BCK timing signals are generated externally). 0:: SLAVE 1:: MASTER
24 : 22	rx_serial_mode_1	rw	0x0	Configure serial aud intf mode. 0:: I2S_PCM 1:: VOICE 2:: DAI When mode is set DAI, the bit Master Mode should be set to '1'. Data should be sent out on falling edge, which requires either Bclk_Pol = '0' and Half_Cycle_DLY = '1' or Bclk_Pol = '1' and Half_Cycle_DLY = '0'. Bits Tx_DLY and BCK-Out_Gate must be configured to '0' and '1'. The DAI mode must NOT be modified after aud intf is enabled.
27 : 25	tx_serial_mode_1	rw	0x0	Configure serial aud intf mode. 0:: I2S_PCM 1:: VOICE 2:: DAI When mode is set DAI, the bit Master Mode should be set to '1'. Data should be sent out on falling edge, which requires either Bclk_Pol = '0' and Half_Cycle_DLY = '1' or Bclk_Pol = '1' and Half_Cycle_DLY = '0'. Bits Tx_DLY and BCK-Out_Gate must be configured to '0' and '1'. The DAI mode must NOT be modified after aud intf is enabled.

28	tx_off_1	rw	0x1	Disable aud intf Tx functions. Important:: if you want to do record only, you must set this bit otherwise aud intf state machine will not start. 0:: TX_ON: Both Tx Rx enabled. 1:: TX_OFF: Rx enabled only, Tx disabled.
30 : 29	tx_mode_1	rw	0x0	Configure mono or stereo format for Audio data out: 2'b00:: STEREO_STEREO: stereo input from DMA, stereo output to pin. 2'b01:: MONOL_STEREO_DUPLI: mono channel L input from DMA, stereo output duplicate in both channels to pin. 2'b10:: MONOR_STEREO_DUPLI: mono channel R input from DMA, stereo output duplicate in both channels to pin. 2'b11:: MONO_IN_MONO_OUT Funtion mono input from DMA, stereo output in left channel to pin, can be implemented by setting aud intf_tx_cfg_ch[1] or aud intf_tx_cfg_ch[0] disable. When works in DAI, or DSD mode, always select "00" mode STEREO_STEREO.
31	i2s_enable_1	rw	0x0	enable i2s interface

22.9 pcm_cfg_0				0x40037024
Bits	Field Name	Acc	Default	Description
7 : 0	slotnum_0	rw	0x0	slots number to be transferred in one frame
8	longsync_0	rw	0x0	longsync enable
9	tx_bit_mode_0	rw	0x0	0: low bit are inserted zero to 24bits 1:high bits are inserted zero to 24bits
10	rx_bit_mode_0	rw	0x0	0: low bit are inserted zero to 24bits 1:high bits are inserted zero to 24bits
11	lrck_m_dly_0	rw	0x0	1: output lrck delay one bck
12	tx_sync_mode_0	rw	0x0	1:output fast sync in master mode
13	loop_back_0	rw	0x0	Sets i2s in loop back mode. The feature is for debug only and can not work in DAI mode. 0:: NORMAL 1:: LOOPBACK
14	bckout_auto_gate_bypass_0	rw	0x0	1: bypss bck auto gate, keep bck output always ok
18 : 17	rx_mode_0	rw	0x0	
19	i2s_chn_out_sel	rw	0x0	1:i2s tx sel channel 1; 0:i2s tx sel channel 0
20	i2s_chn_in_sel	rw	0x0	1:i2s rx sel channel 1; 0:i2s rx sel channel 0

22.10 pcm_cfg_1				0x40037028
Bits	Field Name	Acc	Default	Description
7 : 0	slotnum_1	rw	0x0	slots number to be transferred in one frame
8	longsync_1	rw	0x0	longsync enable
9	tx_bit_mode_1	rw	0x0	0: low bit are inserted zero to 24bits 1:high bits are inserted zero to 24bits
10	rx_bit_mode_1	rw	0x0	0: low bit are inserted zero to 24bits 1:high bits are inserted zero to 24bits
11	lrck_m_dly_1	rw	0x0	1: output lrck delay one bck
12	tx_sync_mode_1	rw	0x0	1:output fast sync in master mode
13	loop_back_1	rw	0x0	Sets i2s in loop back mode. The feature is for debug only and can not work in DAI mode. 0:: NORMAL 1:: LOOPBACK
14	bckout_auto_gate_bypass_1	rw	0x0	1: bypss bck auto gate, keep bck output always ok
18 : 17	rx_mode_1	rw	0x0	

23 spiflash

23.1 tx_cmd_addr	0x40038000

Bits	Field Name	Acc	Default	Description
7 : 0	tx_cmd	rw	0x0	Transmit command.
31 : 8	tx_addr	rw	0x0	Transmit address.

23.2 tx_block_size				0x40038004
Bits	Field Name	Acc	Default	Description
7 : 0	tx_mode	rw	0x0	Transmit mode bits.
16 : 8	tx_block_size	rw	0x1	Transmit block size.
24	tx_cont_mode	rw	0x0	Transmit continuous mode enable.

23.3 tx_fifo_data				0x40038008
Bits	Field Name	Acc	Default	Description
7 : 0	tx_data	wo	0x0	Transmit FIFO data.

23.4 status				0x4003800C
Bits	Field Name	Acc	Default	Description
0	busy_stat	ro	0x0	Busy status.
1	tx_fifo_empty	ro	0x1	Transmit FIFO empty.
2	tx_fifo_full	ro	0x0	Transmit FIFO full.
3	rx_fifo_empty	ro	0x1	Receive FIFO empty.
7 : 4	rx_fifo_cnt	ro	0x0	Receive FIFO count.
8	read_state_busy	ro	0x0	Read state busy.

23.5 rx_fifo_data				0x40038010
Bits	Field Name	Acc	Default	Description
31 : 0	rx_data	ro	0x0	

23.6 flash_config				0x40038014
Bits	Field Name	Acc	Default	Description
0	quad_mode	rw	0x0	Quad mode.
1	wproctect_pin	rw	0x0	Set wproctect pin active.
2	hold_pin	rw	0x0	Set hold pin active.
3	dual_mode	rw	0x0	Dual mode.
6 : 4	sample_delay	rw	0x2	Sample delay.
7	din_cap_edge	rw	0x0	sample clock edge selector, 0: posedge of clk spiflash 1: negedge of clk spiflash
15 : 8	clk_divider	rw	0x8	Clock divider.
16	cmd_quad	rw	0x0	Quad Command Enable. Hardware will regard current command as quad command if this bit is active.

23.7 fifo_ctrl				0x40038018
Bits	Field Name	Acc	Default	Description
0	rx_fifo_clr	rw	0x0	Write 1 to clear rx FIFO.
1	tx_fifo_clr	rw	0x0	Write 1 to clear tx FIFO.

23.8 dual_spi				0x4003801C
Bits	Field Name	Acc	Default	Description
0	spi_cs_num	rw	0x0	SPI cs number. 1'b0: One cs; 1'b1: Two cs.
2 : 1	spi_size	rw	0x0	SPI flash size. 2'b00: 32M bits flash; 2'b01: 64M bits flash; 2'b10: 16M bits flash; 2'b11: 8M bits flash.
3	spi_128m	rw	0x0	128M bits flash.

4	ahb_read_disable	rw	0x0	
5	spi_cs1_sel	rw	0x0	
6	spi_cs1_sel1	rw	0x0	
7	diff_128m_diff_cmd_en	rw	0x0	

23.9 read_cmd				0x40038020
Bits	Field Name	Acc	Default	Description
7 : 0	qread_cmd	rw	0xEB	Quad read command.
15 : 8	fread_cmd	rw	0xB	Fast read command.
23 : 16	read_cmd	rw	0x3	Read command.
31 : 24	dread_cmd	rw	0x3B	Dual read command.

23.10 nand_cfg1				0x40038024
Bits	Field Name	Acc	Default	Description
0	nand_sel	rw	0x0	Internal nand flash selection. Nand flash also can be selected from pin. 1'b0: Nor FLASH; 1'b1: Nand flash.
2 : 1	nand_addr_26_25	rw	0x0	Bit 26 to 25 of nand_address.
15 : 8	page_read_cmd	rw	0x13	Page read command.
23 : 16	get_sts_cmd	rw	0xF	Get status command.
31 : 24	ram_read_cmd	rw	0x3	RAM read command.

23.11 nand_cfg2				0x40038028
Bits	Field Name	Acc	Default	Description
7 : 0	get_sts_addr	rw	0xC0	Get status address.
15 : 8	program_exe_cmd	rw	0x10	Program execute command.
23 : 16	stst_qip	rw	0x1	

23.12 dummy_cycle_cfg				0x4003802C
Bits	Field Name	Acc	Default	Description
0	four_byte_addr	rw	0x0	Four bytes address. 1'b0: 3 bytes address; 1'b1: 4 bytes address.
1	dummy_cycle_en	rw	0x0	Dummy cycle enable.
11 : 8	dummy_cycle	rw	0x8	Dummy cycle count.

23.13 diff_128m_cmd				0x40038030
Bits	Field Name	Acc	Default	Description
7 : 0	first_128m_cmd	ro	0x8C	1st 128M flash command.
15 : 8	second_128m_cmd	ro	0x8D	2nd 128M flash command.
23 : 16	third_128m_cmd	ro	0x0	3rd 128M flash command.
31 : 24	fourth_128m_cmd	ro	0x0	4th 128M flash command.

23.14 aesKey0				0x40038034
Bits	Field Name	Acc	Default	Description
31 : 0	aesKey0	rw	0x0	aesKey bit 255 to 224

23.15 aesKey1				0x40038038
Bits	Field Name	Acc	Default	Description
31 : 0	aesKey1	rw	0x0	aesKey bit 223 to 192

23.16 aesKey2	0x4003803C

Bits	Field Name	Acc	Default	Description
31 : 0	aesKey2	rw	0x0	aesKey bit 191 to 160

23.17 aesKey3				0x40038040
Bits	Field Name	Acc	Default	Description
31 : 0	aesKey3	rw	0x0	aesKey bit 159 to 128

23.18 aesKey4				0x40038044
Bits	Field Name	Acc	Default	Description
31 : 0	aesKey4	rw	0x0	aesKey bit 127 to 96

23.19 aesKey5				0x40038048
Bits	Field Name	Acc	Default	Description
31 : 0	aesKey5	rw	0x0	aesKey bit 95 to 64

23.20 aesKey6				0x4003804C
Bits	Field Name	Acc	Default	Description
31 : 0	aesKey6	rw	0x0	aesKey bit 63 to 32

23.21 aesKey7				0x40038050
Bits	Field Name	Acc	Default	Description
31 : 0	aesKey7	rw	0x0	aesKey bit 31 to 0

23.22 initCtrNonce0				0x40038054
Bits	Field Name	Acc	Default	Description
31 : 0	initCtrNonce0	rw	0x0	ctr bit 127 to 96 of 128 bit

23.23 initCtrNonce1				0x40038058
Bits	Field Name	Acc	Default	Description
31 : 0	initCtrNonce1	rw	0x0	ctr bit 95 to 64 of 128 bit

23.24 initCtrNonce2				0x4003805C
Bits	Field Name	Acc	Default	Description
31 : 0	initCtrNonce2	rw	0x0	ctr bit 63 to 32 of 128 bit

23.25 encStartAddr				0x40038060
Bits	Field Name	Acc	Default	Description
23 : 0	encStartAddr	rw	0x0	data encryption start addr

23.26 encEndAddr				0x40038064
Bits	Field Name	Acc	Default	Description
23 : 0	encEndAddr	rw	0xFFFFFF	data encryption end addr

23.27 flash_decrypt_ctrl				0x40038068
Bits	Field Name	Acc	Default	Description
0	flashDecrEn	rw	0x0	flash data decryption enable
1	aesKeyValid	rw	0x0	aes key valid set this bit when aes key write done

2	ce_clear	wo	0x0	decryptor rst and clear
31	debug_mode	wo	0x0	key and nonce can be read when this bit set

24 cpu_sysctrl

24.1 hclk_ctrl_mode				0x40100000
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_hclk_mode	rw	0xFFFFFFFF	1'b1: manual mode; 1'b0: auto mode

24.2 hclk1_ctrl_mode				0x40100004
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_hclk1_mode	rw	0xFFFFFFFF	1'b1: manual mode; 1'b0: auto mode

24.3 pclk_ctrl_mode				0x40100008
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_pclk_mode	rw	0xFFFFFFFF	1'b1: manual mode; 1'b0: auto mode

24.4 others_clk_ctrl_mode				0x4010000C
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_others_clk_mode	rw	0xFFFFFFFF	1'b1: manual mode; 1'b0: auto mode

24.5 cfg_mem_rom				0x40100010
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_mem_rom	rw	0x2006	memory configration

24.6 cfg_mem_1prf				0x40100014
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_mem_1prf	rw	0x2488	memory configration

24.7 cfg_mem_2prf				0x40100018
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_mem_2prf	rw	0x20D6	memory configration

24.8 trap_bypass				0x4010001C
Bits	Field Name	Acc	Default	Description
0	cfg_trap_bypass	rw	0x1	1'b1: bypass trap

24.9 cache_bypass				0x40100020
Bits	Field Name	Acc	Default	Description
0	cfg_cache_bypass	rw	0x1	1'b1: bypass cache, 32KB ram used for normal sram
1	cfg_burst_incr_only_en	rw	0x1	1'b1: trans ahb incr4/8/16 burst to incr only when noncache access

24.10 pclk_div				0x40100024
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_pclk_div_denom	rw	0x4	APB clock divider denominator
8	cfg_pclk_div_update	rw	0x0	APB clk divider update

24.11 codec_mclk_div				0x40100028
Bits	Field Name	Acc	Default	Description
5 : 0	cfg_mclk_div_denom	rw	0x4	mclk clock divider denominator
8	cfg_mclk_div_update	rw	0x0	mclk divider update

24.12 bclk_sel				0x4010002C
Bits	Field Name	Acc	Default	Description
0	cfg_bck_0_sel	rw	0x0	1'b0: pad_i2s_bck0; 1'b1: mclk_div
1	cfg_bck_0_inv	rw	0x0	bck0 invert enable
2	cfg_bck_1_sel	rw	0x0	1'b0: pad_i2s_bck1; 1'b1: mclk_div
3	cfg_bck_1_inv	rw	0x0	bck1 invert enable

24.13 cpu_sys_tports_sel				0x40100030
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_cpu_sys_tports_sel	rw	0x0	test ports selector
15 : 8	cfg_dbg_clk_sel	rw	0x0	debug clock selector

24.14 phy_dump_sel				0x40100034
Bits	Field Name	Acc	Default	Description
0	cfg_phy_dump_sel	rw	0x0	1: BT; 0: WLAN

24.15 clk_msadc_div				0x40100038
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_clk_msadc_div_denom	rw	0x8	msadc clock divider denominator
8	cfg_clk_msadc_div_update	rw	0x0	msadc clock divider update
9	cfg_clk_msadc_and_inv	rw	0x0	msadc clock invert sel for analog ADC

24.16 cfg_cpu_stclk_div				0x4010003C
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_cpu_stclk_div	rw	0x19	CPU stclk divider, default div26;26MHz/26=1MHz

24.17 cfg_misc				0x40100040
Bits	Field Name	Acc	Default	Description
0	cfg_usb_gpio_mode	rw	0x0	
2 : 1	cfg_usb_gpio_pullup	rw	0x0	
4 : 3	cfg_usb_gpio_pulldown	rw	0x0	

24.18 cfg_cpu_p_rxev				0x40100044
Bits	Field Name	Acc	Default	Description
0	cfg_cpu_p_rxev_dma_en	rw	0x0	
1	cfg_cpu_p_rxev_usb_dma_en	rw	0x0	
2	cfg_cpu_p_rxev_uart0_en	rw	0x0	
3	cfg_cpu_p_rxev_uart1_en	rw	0x0	
4	cfg_cpu_p_rxev_uart2_en	rw	0x0	
5	cfg_cpu_p_rxev_gpioa_en	rw	0x0	
6	cfg_cpu_p_rxev_trng_en	rw	0x0	
7	cfg_cpu_p_rxev_pwrctrl_en	rw	0x0	
8	cfg_cpu_p_rxev_pmu_rtc0_en	rw	0x0	
9	cfg_cpu_p_rxev_pmu_rtc1_en	rw	0x0	
10	cfg_cpu_p_rxev_aon_pwm_en	rw	0x0	
11	cfg_cpu_p_rxev_pwm_en	rw	0x0	

12	cfg_cpu_p_rxev_spi_en	rw	0x0	
13	cfg_cpu_p_rxev_i2cm_en	rw	0x0	
14	cfg_cpu_p_rxev_sdmmc_en	rw	0x0	
15	cfg_cpu_p_rxev_psi_mst_en	rw	0x0	
16	cfg_cpu_p_rxev_usb_ready_en	rw	0x0	

24.19 cfg_cpu_s0_rxev				0x40100048
Bits	Field Name	Acc	Default	Description
0	cfg_cpu_s0_rxev_dma_en	rw	0x0	
1	cfg_cpu_s0_rxev_usb_dma_en	rw	0x0	
2	cfg_cpu_s0_rxev_uart0_en	rw	0x0	
3	cfg_cpu_s0_rxev_uart1_en	rw	0x0	
4	cfg_cpu_s0_rxev_uart2_en	rw	0x0	
5	cfg_cpu_s0_rxev_gpioa_en	rw	0x0	
6	cfg_cpu_s0_rxev_trng_en	rw	0x0	
7	cfg_cpu_s0_rxev_pwrctrl_en	rw	0x0	
8	cfg_cpu_s0_rxev_pmu_rtc0_en	rw	0x0	
9	cfg_cpu_s0_rxev_pmu_rtc1_en	rw	0x0	
10	cfg_cpu_s0_rxev_aon_pwm_en	rw	0x0	
11	cfg_cpu_s0_rxev_pwm_en	rw	0x0	
12	cfg_cpu_s0_rxev_spi_en	rw	0x0	
13	cfg_cpu_s0_rxev_i2cm_en	rw	0x0	
14	cfg_cpu_s0_rxev_sdmmc_en	rw	0x0	
15	cfg_cpu_s0_rxev_psi_mst_en	rw	0x0	
16	cfg_cpu_s0_rxev_usb_ready_en	rw	0x0	

24.20 cfg_cpu_s1_rxev				0x4010004C
Bits	Field Name	Acc	Default	Description
0	cfg_cpu_s1_rxev_dma_en	rw	0x0	
1	cfg_cpu_s1_rxev_usb_dma_en	rw	0x0	
2	cfg_cpu_s1_rxev_uart0_en	rw	0x0	
3	cfg_cpu_s1_rxev_uart1_en	rw	0x0	
4	cfg_cpu_s1_rxev_uart2_en	rw	0x0	
5	cfg_cpu_s1_rxev_gpioa_en	rw	0x0	
6	cfg_cpu_s1_rxev_trng_en	rw	0x0	
7	cfg_cpu_s1_rxev_pwrctrl_en	rw	0x0	
8	cfg_cpu_s1_rxev_pmu_rtc0_en	rw	0x0	
9	cfg_cpu_s1_rxev_pmu_rtc1_en	rw	0x0	

24.21 ro_top_tports				0x40100050
Bits	Field Name	Acc	Default	Description
15 : 0	ro_top_tports	ro	0x0	

24.22 cfg_cpu_nmi_en				0x40100054
Bits	Field Name	Acc	Default	Description
0	cfg_cpu_p_nmi_en	rw	0x0	

24.23 hclk_manual_enable				0x40100100
Bits	Field Name	Acc	Default	Description
0	hclk_cpu_p_manual_enable	rw	0x1	write 1'b1 enable manual mode
1	hclk_cpu_p_g-ated_manual_enable	rw	0x1	write 1'b1 enable manual mode
2	hclk_cpu_s0_manual_enable	rw	0x1	write 1'b1 enable manual mode

3	hclk_cpu_s0_-gated_manual_enable	rw	0x1	write 1'b1 enable manual mode
4	hclk_rom_manual_enable	rw	0x1	write 1'b1 enable manual mode
5	hclk_btrom_manual_enable	rw	0x1	write 1'b1 enable manual mode
6	hclk_ram0_manual_enable	rw	0x1	write 1'b1 enable manual mode
7	hclk_ram1_manual_enable	rw	0x1	write 1'b1 enable manual mode
8	hclk_ram2_manual_enable	rw	0x1	write 1'b1 enable manual mode
9	hclk_ram3_manual_enable	rw	0x1	write 1'b1 enable manual mode
10	hclk_ram4_manual_enable	rw	0x1	write 1'b1 enable manual mode
11	hclk_ram5_manual_enable	rw	0x1	write 1'b1 enable manual mode
12	hclk_sys_matr-ix_manual_enable	rw	0x1	write 1'b1 enable manual mode
13	hclk_ahb0_manual_enable	rw	0x1	write 1'b1 enable manual mode
14	hclk_apb0_manual_enable	rw	0x1	write 1'b1 enable manual mode
15	hclk_exmem_bu-s_manual_enable	rw	0x1	write 1'b1 enable manual mode
16	hclk_cache_manual_enable	rw	0x1	write 1'b1 enable manual mode
17	hclk_dma_manual_enable	rw	0x1	write 1'b1 enable manual mode
18	hclk_flash_manual_enable	rw	0x1	write 1'b1 enable manual mode
19	hclk_trap_p_manual_enable	rw	0x1	write 1'b1 enable manual mode
20	hclk_trap_s0_manual_enable	rw	0x1	write 1'b1 enable manual mode
21	hclk_uart0_manual_enable	rw	0x1	write 1'b1 enable manual mode
22	hclk_uart1_manual_enable	rw	0x1	write 1'b1 enable manual mode
23	hclk_uart2_manual_enable	rw	0x1	write 1'b1 enable manual mode
24	hclk_usbc_manual_enable	rw	0x1	write 1'b1 enable manual mode
25	hclk_aud_proc_manual_enable	rw	0x1	write 1'b1 enable manual mode
26	hclk_mailbox_manual_enable	rw	0x1	write 1'b1 enable manual mode
27	hclk_sdio_manual_enable	rw	0x1	write 1'b1 enable manual mode
28	hclk_mm_manual_enable	rw	0x1	write 1'b1 enable manual mode
29	hclk_cpu_s1_manual_enable	rw	0x1	write 1'b1 enable manual mode
30	hclk_cpu_s1_-gated_manual_enable	rw	0x1	write 1'b1 enable manual mode
31	hclk_trap_s1_manual_enable	rw	0x1	write 1'b1 enable manual mode

24.24 hclk_manual_disable				0x40100104
Bits	Field Name	Acc	Default	Description
0	hclk_cpu_p_manual_disable	rw	0x1	write 1'b1 disable manual mode
1	hclk_cpu_p_g-ated_manual_disable	rw	0x1	write 1'b1 disable manual mode
2	hclk_cpu_s0_manual_disable	rw	0x1	write 1'b1 disable manual mode
3	hclk_cpu_s0_-gated_manual_disable	rw	0x1	write 1'b1 disable manual mode
4	hclk_rom_manual_disable	rw	0x1	write 1'b1 disable manual mode
5	hclk_btrom_manual_disable	rw	0x1	write 1'b1 disable manual mode
6	hclk_ram0_manual_disable	rw	0x1	write 1'b1 disable manual mode
7	hclk_ram1_manual_disable	rw	0x1	write 1'b1 disable manual mode
8	hclk_ram2_manual_disable	rw	0x1	write 1'b1 disable manual mode
9	hclk_ram3_manual_disable	rw	0x1	write 1'b1 disable manual mode
10	hclk_ram4_manual_disable	rw	0x1	write 1'b1 disable manual mode
11	hclk_ram5_manual_disable	rw	0x1	write 1'b1 disable manual mode
12	hclk_sys_matr-ix_manual_disable	rw	0x1	write 1'b1 disable manual mode
13	hclk_ahb0_manual_disable	rw	0x1	write 1'b1 disable manual mode
14	hclk_apb0_manual_disable	rw	0x1	write 1'b1 disable manual mode
15	hclk_exmem_bu-s_manual_disable	rw	0x1	write 1'b1 disable manual mode
16	hclk_cache_manual_disable	rw	0x1	write 1'b1 disable manual mode
17	hclk_dma_manual_disable	rw	0x1	write 1'b1 disable manual mode

18	hclk_flash_manual_disable	rw	0x1	write 1'b1 disable manual mode
19	hclk_trap_p_manual_disable	rw	0x1	write 1'b1 disable manual mode
20	hclk_trap_s0_manual_disable	rw	0x1	write 1'b1 disable manual mode
21	hclk_uart0_manual_disable	rw	0x1	write 1'b1 disable manual mode
22	hclk_uart1_manual_disable	rw	0x1	write 1'b1 disable manual mode
23	hclk_uart2_manual_disable	rw	0x1	write 1'b1 disable manual mode
24	hclk_usbc_manual_disable	rw	0x1	write 1'b1 disable manual mode
25	hclk_aud_proc_manual_disable	rw	0x1	write 1'b1 disable manual mode
26	hclk_mailbox_manual_disable	rw	0x1	write 1'b1 disable manual mode
27	hclk_sdio_manual_disable	rw	0x1	write 1'b1 disable manual mode
28	hclk_mm_manual_disable	rw	0x1	write 1'b1 disable manual mode
29	hclk_cpu_s1_manual_disable	rw	0x1	write 1'b1 disable manual mode
30	hclk_cpu_s1_-gated_manual_disable	rw	0x1	write 1'b1 disable manual mode
31	hclk_trap_s1_manual_disable	rw	0x1	write 1'b1 disable manual mode

24.25 hclk1_manual_enable				0x40100108
Bits	Field Name	Acc	Default	Description
0	hclk_sdmmc_al-ways_manual_enable	rw	0x1	write 1'b1 enable manual mode
1	hclk_sdmmc_manual_enable	rw	0x1	write 1'b1 enable manual mode
2	hclk_sram4_lo-w_manual_enable	rw	0x1	write 1'b1 enable manual mode
3	hclk_sram4_hi-gh_manual_enable	rw	0x1	write 1'b1 enable manual mode
4	hclk_sram5_lo-w_manual_enable	rw	0x1	write 1'b1 enable manual mode
5	hclk_sram5_hi-gh_manual_enable	rw	0x1	write 1'b1 enable manual mode

24.26 hclk1_manual_disable				0x4010010C
Bits	Field Name	Acc	Default	Description
0	hclk_sdmmc_al-ways_manual_disable	rw	0x1	write 1'b1 disable manual mode
1	hclk_sdmmc_manual_disable	rw	0x1	write 1'b1 disable manual mode
2	hclk_sram4_lo-w_manual_disable	rw	0x1	write 1'b1 disable manual mode
3	hclk_sram4_hi-gh_manual_disable	rw	0x1	write 1'b1 disable manual mode
4	hclk_sram5_lo-w_manual_disable	rw	0x1	write 1'b1 disable manual mode
5	hclk_sram5_hi-gh_manual_disable	rw	0x1	write 1'b1 disable manual mode

24.27 pclk_manual_enable				0x40100110
Bits	Field Name	Acc	Default	Description
0	pclk_cpu_sysc-trl_manual_enable	rw	0x1	write 1'b1 enable manual mode
1	pclk_wdg0_manual_enable	rw	0x1	write 1'b1 enable manual mode
2	pclk_wdg1_manual_enable	rw	0x1	write 1'b1 enable manual mode
3	pclk_timer0_manual_enable	rw	0x1	write 1'b1 enable manual mode
4	pclk_timer1_manual_enable	rw	0x1	write 1'b1 enable manual mode
5	pclk_pwm_manual_enable	rw	0x1	write 1'b1 enable manual mode
6	pclk_i2cm_manual_enable	rw	0x1	write 1'b1 enable manual mode
7	pclk_mod_i2cm-_manual_enable	rw	0x1	write 1'b1 enable manual mode
8	pclk_spi_manual_enable	rw	0x1	write 1'b1 enable manual mode
9	pclk_trng_manual_enable	rw	0x1	write 1'b1 enable manual mode

10	pclk_process_-mon_manual_enable	rw	0x1	write 1'b1 enable manual mode
11	pclk_analog_r-eg0_manual_enable	rw	0x1	write 1'b1 enable manual mode
12	pclk_gpioa_manual_enable	rw	0x1	write 1'b1 enable manual mode
13	pclk_msadc_manual_enable	rw	0x1	write 1'b1 enable manual mode
14	pclk_efuse_manual_enable	rw	0x1	write 1'b1 enable manual mode

24.28 pclk_manual_disable				0x40100114
Bits	Field Name	Acc	Default	Description
0	pclk_cpu_sysc-trl_manual_disable	rw	0x1	write 1'b1 disable manual mode
1	pclk_wdg0_manual_disable	rw	0x1	write 1'b1 disable manual mode
2	pclk_wdg1_manual_disable	rw	0x1	write 1'b1 disable manual mode
3	pclk_timer0_manual_disable	rw	0x1	write 1'b1 disable manual mode
4	pclk_timer1_manual_disable	rw	0x1	write 1'b1 disable manual mode
5	pclk_pwm_manual_disable	rw	0x1	write 1'b1 disable manual mode
6	pclk_i2cm_manual_disable	rw	0x1	write 1'b1 disable manual mode
7	pclk_mod_i2cm-_manual_disable	rw	0x1	write 1'b1 disable manual mode
8	pclk_spi_manual_disable	rw	0x1	write 1'b1 disable manual mode
9	pclk_trng_manual_disable	rw	0x1	write 1'b1 disable manual mode
10	pclk_process_-mon_manual_disable	rw	0x1	write 1'b1 disable manual mode
11	pclk_analog_r-eg0_manual_disable	rw	0x1	write 1'b1 disable manual mode
12	pclk_gpioa_manual_disable	rw	0x1	write 1'b1 disable manual mode
13	pclk_msadc_manual_disable	rw	0x1	write 1'b1 disable manual mode
14	pclk_efuse_manual_disable	rw	0x1	write 1'b1 disable manual mode

24.29 others_manual_enable				0x40100118
Bits	Field Name	Acc	Default	Description
0	others_sdmmc_manual_enable	rw	0x1	write 1'b1 enable manual mode
1	others_flash_manual_enable	rw	0x1	write 1'b1 enable manual mode
2	others_time0_manual_enable	rw	0x1	write 1'b1 enable manual mode
3	others_time1_manual_enable	rw	0x1	write 1'b1 enable manual mode
4	others_uart0_manual_enable	rw	0x1	write 1'b1 enable manual mode
5	others_uart1_manual_enable	rw	0x1	write 1'b1 enable manual mode
6	others_uart2_manual_enable	rw	0x1	write 1'b1 enable manual mode
7	others_sdio_manual_enable	rw	0x1	write 1'b1 enable manual mode
8	others_pwm_manual_enable	rw	0x1	write 1'b1 enable manual mode
9	others_rtc_al-ways_manual_enable	rw	0x1	write 1'b1 enable manual mode
10	others_rtc_wd-g0_manual_enable	rw	0x1	write 1'b1 enable manual mode
11	others_rtc_wd-g1_manual_enable	rw	0x1	write 1'b1 enable manual mode
12	others_audio_-proc_manual_enable	rw	0x1	write 1'b1 enable manual mode
13	others_process-_mon_manual_enable	rw	0x1	write 1'b1 enable manual mode
14	others_bck_0_manual_enable	rw	0x1	write 1'b1 enable manual mode
15	others_bck_1_manual_enable	rw	0x1	write 1'b1 enable manual mode
16	others_spdif_manual_enable	rw	0x1	write 1'b1 enable manual mode
17	others_spi_manual_enable	rw	0x1	write 1'b1 enable manual mode
18	others_msadc_manual_enable	rw	0x1	write 1'b1 enable manual mode
19	others_efuse_manual_enable	rw	0x1	write 1'b1 enable manual mode
20	others_usbc_manual_enable	rw	0x1	write 1'b1 enable manual mode

24.30 others_manual_disable				0x4010011C
Bits	Field Name	Acc	Default	Description
0	others_sdmmc_manual_disable	rw	0x1	write 1'b1 disable manual mode
1	others_flash_manual_disable	rw	0x1	write 1'b1 disable manual mode
2	others_time0_manual_disable	rw	0x1	write 1'b1 disable manual mode
3	others_time1_manual_disable	rw	0x1	write 1'b1 disable manual mode
4	others_uart0_manual_disable	rw	0x1	write 1'b1 disable manual mode
5	others_uart1_manual_disable	rw	0x1	write 1'b1 disable manual mode
6	others_uart2_manual_disable	rw	0x1	write 1'b1 disable manual mode
7	others_sdio_manual_disable	rw	0x1	write 1'b1 disable manual mode
8	others_pwm_manual_disable	rw	0x1	write 1'b1 disable manual mode
9	others_rtc_always_manual_disable	rw	0x1	write 1'b1 disable manual mode
10	others_rtc_wdg0_manual_disable	rw	0x1	write 1'b1 disable manual mode
11	others_rtc_wdg1_manual_disable	rw	0x1	write 1'b1 disable manual mode
12	others_audio_proc_manual_disable	rw	0x1	write 1'b1 disable manual mode
13	others_process_mon_manual_disable	rw	0x1	write 1'b1 disable manual mode
14	others_bck_0_manual_disable	rw	0x1	write 1'b1 disable manual mode
15	others_bck_1_manual_disable	rw	0x1	write 1'b1 disable manual mode
16	others_spdif_manual_disable	rw	0x1	write 1'b1 disable manual mode
17	others_spi_manual_disable	rw	0x1	write 1'b1 disable manual mode
18	others_msadc_manual_disable	rw	0x1	write 1'b1 disable manual mode
19	others_efuse_manual_disable	rw	0x1	write 1'b1 disable manual mode
20	others_usbc_manual_disable	rw	0x1	write 1'b1 disable manual mode

24.31 hclk_soft_resetn_set				0x40100120
Bits	Field Name	Acc	Default	Description
0	hresetn_rom_set	rw	0x1	write 1'b1 set soft reset
1	hresetn_btrom_set	rw	0x1	write 1'b1 set soft reset
2	hresetn_sram0_set	rw	0x1	write 1'b1 set soft reset
3	hresetn_sram1_set	rw	0x1	write 1'b1 set soft reset
4	hresetn_sram2_set	rw	0x1	write 1'b1 set soft reset
5	hresetn_sram3_set	rw	0x1	write 1'b1 set soft reset
6	hresetn_sram4_set	rw	0x1	write 1'b1 set soft reset
7	hresetn_sram5_set	rw	0x1	write 1'b1 set soft reset
8	hresetn_ahb0_dec_set	rw	0x1	write 1'b1 set soft reset
9	hresetn_apb0_set	rw	0x1	write 1'b1 set soft reset
10	hresetn_exmem_bus_set	rw	0x1	write 1'b1 set soft reset
11	hresetn_cache_set	rw	0x1	write 1'b1 set soft reset
12	hresetn_dma_set	rw	0x1	write 1'b1 set soft reset
13	hresetn_flash_set	rw	0x1	write 1'b1 set soft reset
14	hresetn_trap_p_set	rw	0x1	write 1'b1 set soft reset
15	hresetn_trap_s0_set	rw	0x1	write 1'b1 set soft reset
16	hresetn_uart0_set	rw	0x1	write 1'b1 set soft reset
17	hresetn_uart1_set	rw	0x1	write 1'b1 set soft reset
18	hresetn_uart2_set	rw	0x1	write 1'b1 set soft reset
19	hresetn_aud_proc_set	rw	0x1	write 1'b1 set soft reset
20	hresetn_mailbox_set	rw	0x1	write 1'b1 set soft reset
21	hresetn_sdio_set	rw	0x1	write 1'b1 set soft reset
22	hresetn_mm_sys_set	rw	0x1	write 1'b1 set soft reset
23	hresetn_sdmmc_set	rw	0x1	write 1'b1 set soft reset
24	hresetn_trap_s1_set	rw	0x1	write 1'b1 set soft reset

24.32 hclk_soft_resetn_clr				0x40100124
Bits	Field Name	Acc	Default	Description
0	hresetn_rom_clear	rw	0x1	write 1'b1 clear soft reset
1	hresetn_btrom_clear	rw	0x1	write 1'b1 clear soft reset
2	hresetn_sram0_clear	rw	0x1	write 1'b1 clear soft reset
3	hresetn_sram1_clear	rw	0x1	write 1'b1 clear soft reset
4	hresetn_sram2_clear	rw	0x1	write 1'b1 clear soft reset
5	hresetn_sram3_clear	rw	0x1	write 1'b1 clear soft reset
6	hresetn_sram4_clear	rw	0x1	write 1'b1 clear soft reset
7	hresetn_sram5_clear	rw	0x1	write 1'b1 clear soft reset
8	hresetn_ahb0_dec_clear	rw	0x1	write 1'b1 clear soft reset
9	hresetn_apb0_clear	rw	0x1	write 1'b1 clear soft reset
10	hresetn_exmem_bus_clear	rw	0x1	write 1'b1 clear soft reset
11	hresetn_cache_clear	rw	0x1	write 1'b1 clear soft reset
12	hresetn_dma_clear	rw	0x1	write 1'b1 clear soft reset
13	hresetn_flash_clear	rw	0x1	write 1'b1 clear soft reset
14	hresetn_trap_p_clear	rw	0x1	write 1'b1 clear soft reset
15	hresetn_trap_s0_clear	rw	0x1	write 1'b1 clear soft reset
16	hresetn_uart0_clear	rw	0x1	write 1'b1 clear soft reset
17	hresetn_uart1_clear	rw	0x1	write 1'b1 clear soft reset
18	hresetn_uart2_clear	rw	0x1	write 1'b1 clear soft reset
19	hresetn_aud_proc_clear	rw	0x1	write 1'b1 clear soft reset
20	hresetn_mailbox_clear	rw	0x1	write 1'b1 clear soft reset
21	hresetn_sdio_clear	rw	0x1	write 1'b1 clear soft reset
22	hresetn_mm_sys_clear	rw	0x1	write 1'b1 clear soft reset
23	hresetn_sdmmc_clear	rw	0x1	write 1'b1 clear soft reset
24	hresetn_trap_s1_clear	rw	0x1	write 1'b1 clear soft reset

24.33 hclk1_soft_resetn_set				0x40100128
Bits	Field Name	Acc	Default	Description

24.34 hclk1_soft_resetn_clr				0x4010012C
Bits	Field Name	Acc	Default	Description

24.35 pclk_soft_resetn_set				0x40100130
Bits	Field Name	Acc	Default	Description
0	presetn_cpu_sysctrl_set	rw	0x1	write 1'b1 set soft reset
1	presetn_wdg0_set	rw	0x1	write 1'b1 set soft reset
2	presetn_wdg1_set	rw	0x1	write 1'b1 set soft reset
3	presetn_timer0_set	rw	0x1	write 1'b1 set soft reset
4	presetn_timer1_set	rw	0x1	write 1'b1 set soft reset
5	presetn_pwm_set	rw	0x1	write 1'b1 set soft reset
6	presetn_i2cm_set	rw	0x1	write 1'b1 set soft reset
7	presetn_mod_i2cm_set	rw	0x1	write 1'b1 set soft reset
8	presetn_spi_set	rw	0x1	write 1'b1 set soft reset
9	presetn_trng_set	rw	0x1	write 1'b1 set soft reset
10	presetn_process_mon_set	rw	0x1	write 1'b1 set soft reset
11	presetn_analog_reg0_set	rw	0x1	write 1'b1 set soft reset
12	presetn_gpioa_set	rw	0x1	write 1'b1 set soft reset
13	presetn_msadc_set	rw	0x1	write 1'b1 set soft reset
14	presetn_efuse_set	rw	0x1	write 1'b1 set soft reset

24.36 pclk_soft_resetn_clr				0x40100134
Bits	Field Name	Acc	Default	Description

0	presetn_cpu_sysctrl_clear	rw	0x1	write 1'b1 clear soft reset
1	presetn_wdg0_clear	rw	0x1	write 1'b1 clear soft reset
2	presetn_wdg1_clear	rw	0x1	write 1'b1 clear soft reset
3	presetn_timer0_clear	rw	0x1	write 1'b1 clear soft reset
4	presetn_timer1_clear	rw	0x1	write 1'b1 clear soft reset
5	presetn_pwm_clear	rw	0x1	write 1'b1 clear soft reset
6	presetn_i2cm_clear	rw	0x1	write 1'b1 clear soft reset
7	presetn_mod_i2cm_clear	rw	0x1	write 1'b1 clear soft reset
8	presetn_spi_clear	rw	0x1	write 1'b1 clear soft reset
9	presetn_trng_clear	rw	0x1	write 1'b1 clear soft reset
10	presetn_process_mon_clear	rw	0x1	write 1'b1 clear soft reset
11	presetn_analog_reg0_clear	rw	0x1	write 1'b1 clear soft reset
12	presetn_gpioa_clear	rw	0x1	write 1'b1 clear soft reset
13	presetn_msadc_clear	rw	0x1	write 1'b1 clear soft reset
14	presetn_efuse_clear	rw	0x1	write 1'b1 clear soft reset

24.37 others_soft_resetn_set				0x40100138
Bits	Field Name	Acc	Default	Description
0	resetn_timer0_set	rw	0x1	write 1'b1 set soft reset
1	resetn_timer1_set	rw	0x1	write 1'b1 set soft reset
2	resetn_uart0_set	rw	0x1	write 1'b1 set soft reset
3	resetn_uart1_set	rw	0x1	write 1'b1 set soft reset
4	resetn_uart2_set	rw	0x1	write 1'b1 set soft reset
5	resetn_sdio_set	rw	0x1	write 1'b1 set soft reset
6	resetn_pwm_set	rw	0x1	write 1'b1 set soft reset
7	resetn_rtc_wdg0_set	rw	0x1	write 1'b1 set soft reset
8	resetn_rtc_wdg1_set	rw	0x1	write 1'b1 set soft reset
9	resetn_audio_proc_set	rw	0x1	write 1'b1 set soft reset
10	resetn_process_mon_set	rw	0x1	write 1'b1 set soft reset
11	resetn_spi_set	rw	0x1	write 1'b1 set soft reset
12	resetn_flash_set	rw	0x1	write 1'b1 set soft reset
13	resetn_msadc_set	rw	0x1	write 1'b1 set soft reset
14	resetn_efuse_set	rw	0x1	write 1'b1 set soft reset
15	resetn_usbc_set	rw	0x1	write 1'b1 set soft reset

24.38 others_soft_resetn_clr				0x4010013C
Bits	Field Name	Acc	Default	Description
0	resetn_timer0_clear	rw	0x1	write 1'b1 clear soft reset
1	resetn_timer1_clear	rw	0x1	write 1'b1 clear soft reset
2	resetn_uart0_clear	rw	0x1	write 1'b1 clear soft reset
3	resetn_uart1_clear	rw	0x1	write 1'b1 clear soft reset
4	resetn_uart2_clear	rw	0x1	write 1'b1 clear soft reset
5	resetn_sdio_clear	rw	0x1	write 1'b1 clear soft reset
6	resetn_pwm_clear	rw	0x1	write 1'b1 clear soft reset
7	resetn_rtc_wdg0_clear	rw	0x1	write 1'b1 clear soft reset
8	resetn_rtc_wdg1_clear	rw	0x1	write 1'b1 clear soft reset
9	resetn_audio_proc_clear	rw	0x1	write 1'b1 clear soft reset
10	resetn_process_mon_clear	rw	0x1	write 1'b1 clear soft reset
11	resetn_spi_clear	rw	0x1	write 1'b1 clear soft reset
12	resetn_flash_clear	rw	0x1	write 1'b1 clear soft reset
13	resetn_msadc_clear	rw	0x1	write 1'b1 clear soft reset
14	resetn_efuse_clear	rw	0x1	write 1'b1 clear soft reset
15	resetn_usbc_clear	rw	0x1	write 1'b1 clear soft reset

25 pwm

25.1 tmr0_ld_value				0x40101000
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_ld_value	rw	0x0	timer0 load value

25.2 tmr0_cnt_value				0x40101008
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_cnt_value	rw	0x0	timer0 counter value

25.3 tmr0_cfg				0x40101010
Bits	Field Name	Acc	Default	Description
0	tmr_mode	rw	0x0	0: free running 1: periodic
1	tmr_run	rw	0x0	timer0 enable

25.4 tmr0_int_ctrl				0x40101014
Bits	Field Name	Acc	Default	Description
0	tmr_int_en	rw	0x0	timer0 interrupt enable
1	tmr_int_raw	ro	0x0	timer0 interrupt raw
2	tmr_int_status	ro	0x0	timer0 interrupt status
3	tmr_int_clr	wo	0x0	timer0 interrupt clear

25.5 tmr0_cnt_read				0x40101018
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_cnt_read	rw	0x0	timer0 counter read value

25.6 tmr1_ld_value				0x40101020
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_ld_value	rw	0x0	timer1 load value

25.7 tmr1_cnt_value				0x40101028
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_cnt_value	rw	0x0	timer1 counter value

25.8 tmr1_cfg				0x40101030
Bits	Field Name	Acc	Default	Description
0	tmr_mode	rw	0x0	0: free running 1: periodic
1	tmr_run	rw	0x0	timer1 enable

25.9 tmr1_int_ctrl				0x40101034
Bits	Field Name	Acc	Default	Description
0	tmr_int_en	rw	0x0	timer1 interrupt enable
1	tmr_int_raw	ro	0x0	timer1 interrupt raw
2	tmr_int_status	ro	0x0	timer1 interrupt status
3	tmr_int_clr	wo	0x0	timer1 interrupt clear

25.10 tmr1_cnt_read				0x40101038
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_cnt_read	rw	0x0	timer1 counter read value

25.11 tmr2_ld_value				0x40101040
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_ld_value	rw	0x0	timer2 load value

25.12 tmr2_cnt_value				0x40101048
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_cnt_value	rw	0x0	timer2 counter value

25.13 tmr2_cfg				0x40101050
Bits	Field Name	Acc	Default	Description
0	tmr_mode	rw	0x0	0: free running 1: periodic
1	tmr_run	rw	0x0	timer2 enable

25.14 tmr2_int_ctrl				0x40101054
Bits	Field Name	Acc	Default	Description
0	tmr_int_en	rw	0x0	timer2 interrupt enable
1	tmr_int_raw	ro	0x0	timer2 interrupt raw
2	tmr_int_status	ro	0x0	timer2 interrupt status
3	tmr_int_clr	wo	0x0	timer2 interrupt clear

25.15 tmr2_cnt_read				0x40101058
Bits	Field Name	Acc	Default	Description
31 : 0	tmr2_cnt_read	rw	0x0	timer2 counter read value

25.16 pwm0_sta_val				0x40101100
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_sta_val	rw	0x0	

25.17 pwm0_end_val				0x40101104
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val	rw	0x0	

25.18 pwm0_step_cfg0				0x40101108
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc	rw	0x0	
31 : 16	pwm_step_num	rw	0x0	

25.19 pwm0_step_cfg1				0x4010110C
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_step_value	rw	0x0	

25.20 pwm0_cfg				0x40101110
Bits	Field Name	Acc	Default	Description
0	pwm_run	rw	0x0	
1	pwm_inc_mode	rw	0x0	
2	pwm_default_val	rw	0x0	
17 : 16	pwm_tmr_sel	rw	0x0	
31	pwm_update	rw	0x0	

25.21 pwm0_int_ctrl				0x40101114
Bits	Field Name	Acc	Default	Description
0	pwm_int_en	rw	0x0	
1	pwm_int_raw	ro	0x0	
2	pwm_int_status	ro	0x0	
3	pwm_int_clr	wo	0x0	

25.22 pwm0_end_val_use				0x40101118
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val_use	ro	0x0	

25.23 pwm0_step_cnt				0x4010111C
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc_cnt	ro	0x0	
31 : 16	pwm_step_num_cnt	ro	0x0	

25.24 pwm1_sta_val				0x40101120
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_sta_val	rw	0x0	

25.25 pwm1_end_val				0x40101124
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val	rw	0x0	

25.26 pwm1_step_cfg0				0x40101128
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc	rw	0x0	
31 : 16	pwm_step_num	rw	0x0	

25.27 pwm1_step_cfg1				0x4010112C
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_step_value	rw	0x0	

25.28 pwm1_cfg				0x40101130
Bits	Field Name	Acc	Default	Description
0	pwm_run	rw	0x0	
1	pwm_inc_mode	rw	0x0	
2	pwm_default_val	rw	0x0	
17 : 16	pwm_tmr_sel	rw	0x0	
31	pwm_update	rw	0x0	

25.29 pwm1_int_ctrl				0x40101134
Bits	Field Name	Acc	Default	Description
0	pwm_int_en	rw	0x0	
1	pwm_int_raw	ro	0x0	
2	pwm_int_status	ro	0x0	
3	pwm_int_clr	wo	0x0	

25.30 pwm1_end_val_use	0x40101138

Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val_use	ro	0x0	

25.31 pwm1_step_cnt				0x4010113C
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc_cnt	ro	0x0	
31 : 16	pwm_step_num_cnt	ro	0x0	

25.32 pwm2_sta_val				0x40101140
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_sta_val	rw	0x0	

25.33 pwm2_end_val				0x40101144
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val	rw	0x0	

25.34 pwm2_step_cfg0				0x40101148
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc	rw	0x0	
31 : 16	pwm_step_num	rw	0x0	

25.35 pwm2_step_cfg1				0x4010114C
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_step_value	rw	0x0	

25.36 pwm2_cfg				0x40101150
Bits	Field Name	Acc	Default	Description
0	pwm_run	rw	0x0	
1	pwm_inc_mode	rw	0x0	
2	pwm_default_val	rw	0x0	
17 : 16	pwm_tmr_sel	rw	0x0	
31	pwm_update	rw	0x0	

25.37 pwm2_int_ctrl				0x40101154
Bits	Field Name	Acc	Default	Description
0	pwm_int_en	rw	0x0	
1	pwm_int_raw	ro	0x0	
2	pwm_int_status	ro	0x0	
3	pwm_int_clr	wo	0x0	

25.38 pwm2_end_val_use				0x40101158
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val_use	ro	0x0	

25.39 pwm2_step_cnt				0x4010115C
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc_cnt	ro	0x0	
31 : 16	pwm_step_num_cnt	ro	0x0	

26 i2cm

26.1 IC_CON				0x40102000
Bits	Field Name	Acc	Default	Description
0	master_mode	rw	0x1	
2 : 1	speed	rw	0x3	
3	ic_10bitaddr_slave	rw	0x0	
5	ic_restart_en	rw	0x1	
6	ic_slave_disable	rw	0x1	
7	stop_det_ifaddressed	rw	0x0	
8	tx_empty_ctrl	rw	0x0	

26.2 IC_TAR				0x40102004
Bits	Field Name	Acc	Default	Description
9 : 0	ic_tar	rw	0x55	
10	gc_or_start	rw	0x0	
11	special	rw	0x0	
12	ic_10bitaddr_master	rw	0x0	

26.3 IC_SAR				0x40102008
Bits	Field Name	Acc	Default	Description
9 : 0	ic_sar	rw	0x55	

26.4 IC_HS_MADDR				0x4010200C
Bits	Field Name	Acc	Default	Description
2 : 0	ic_hs_mar	rw	0x1	

26.5 IC_DATA_CMD				0x40102010
Bits	Field Name	Acc	Default	Description
7 : 0	dat	rw	0x0	
8	cmd	wo	0x0	

26.6 IC_SS_SCL_HCNT				0x40102014
Bits	Field Name	Acc	Default	Description
15 : 0	ic_ss_scl_hcnt	rw	0x320	

26.7 IC_SS_SCL_LCNT				0x40102018
Bits	Field Name	Acc	Default	Description
15 : 0	ic_ss_scl_lcnt	rw	0x3AC	

26.8 IC_FS_SCL_HCNT				0x4010201C
Bits	Field Name	Acc	Default	Description
15 : 0	ic_fs_scl_hcnt	rw	0x78	

26.9 IC_FS_SCL_LCNT				0x40102020
Bits	Field Name	Acc	Default	Description
15 : 0	ic_fs_scl_lcnt	rw	0x104	

26.10 IC_HS_SCl_HCNT	0x40102024

Bits	Field Name	Acc	Default	Description
15 : 0	ic_hs_scl_hcnt	rw	0xC	

26.11 IC_HS_SCL_LCNT				0x40102028
Bits	Field Name	Acc	Default	Description
15 : 0	ic_hs_scl_lcnt	rw	0x20	

26.12 IC_INTR_STAT				0x4010202C
Bits	Field Name	Acc	Default	Description
0	r_rx_under	ro	0x0	
1	r_rx_over	ro	0x0	
2	r_rx_full	ro	0x0	
3	r_tx_over	ro	0x0	
4	r_tx_empty	ro	0x0	
5	r_rd_req	ro	0x0	
6	r_tx_abrt	ro	0x0	
7	r_rx_done	ro	0x0	
8	r_activity	ro	0x0	
9	r_stop_det	ro	0x0	
10	r_start_det	ro	0x0	
11	r_gen_call	ro	0x0	
12	r_restart_det	ro	0x0	
13	r_master_on_hold	ro	0x0	

26.13 IC_INTR_MASK				0x40102030
Bits	Field Name	Acc	Default	Description
0	m_rx_under	rw	0x1	
1	m_rx_over	rw	0x1	
2	m_rx_full	rw	0x1	
3	m_tx_over	rw	0x1	
4	m_tx_empty	rw	0x1	
5	m_rd_req	rw	0x1	
6	m_tx_abrt	rw	0x1	
7	m_rx_done	rw	0x0	
8	m_activity	rw	0x0	
9	m_stop_det	rw	0x0	
10	m_start_det	rw	0x0	
11	m_gen_call	rw	0x1	
12	m_restart_det	rw	0x0	
13	m_master_on_hold	rw	0x0	

26.14 IC_RAW_INTR_STAT				0x40102034
Bits	Field Name	Acc	Default	Description
0	rx_under	ro	0x0	
1	rx_over	ro	0x0	
2	rx_full	ro	0x0	
3	tx_over	ro	0x0	
4	tx_empty	ro	0x0	
5	rd_req	ro	0x0	
6	tx_abrt	ro	0x0	
7	rx_done	ro	0x0	
8	activity	ro	0x0	
9	stop_det	ro	0x0	
10	start_det	ro	0x0	

11	gen_call	ro	0x0	
12	restart_det	ro	0x0	
13	master_on_hold	ro	0x0	

26.15 IC_RX_TL				0x40102038
Bits	Field Name	Acc	Default	Description
7 : 0	rx_tl	rw	0x0	

26.16 IC_TX_TL				0x4010203C
Bits	Field Name	Acc	Default	Description
7 : 0	tx_tl	rw	0x0	

26.17 IC_CLR_INTR				0x40102040
Bits	Field Name	Acc	Default	Description
0	clr_intr	ro	0x0	

26.18 IC_CLR_RX_UNDER				0x40102044
Bits	Field Name	Acc	Default	Description
0	clr_rx_under	ro	0x0	

26.19 IC_CLR_RX_OVER				0x40102048
Bits	Field Name	Acc	Default	Description
0	clr_rx_over	ro	0x0	

26.20 IC_CLR_TX_OVER				0x4010204C
Bits	Field Name	Acc	Default	Description
0	clr_tx_over	ro	0x0	

26.21 IC_CLR_RD_REQ				0x40102050
Bits	Field Name	Acc	Default	Description
0	clr_rd_req	ro	0x0	

26.22 IC_CLR_TX_ABRT				0x40102054
Bits	Field Name	Acc	Default	Description
0	clr_tx_abrt	ro	0x0	

26.23 IC_CLR_RX_DONE				0x40102058
Bits	Field Name	Acc	Default	Description
0	clr_tx_done	ro	0x0	

26.24 IC_CLR_ACTIVITY				0x4010205C
Bits	Field Name	Acc	Default	Description
0	clr_activity	ro	0x0	

26.25 IC_CLR_STOP_DET				0x40102060
Bits	Field Name	Acc	Default	Description
0	clr_stop_det	ro	0x0	

26.26 IC_CLR_START_DET				0x40102064
Bits	Field Name	Acc	Default	Description
0	clr_start_det	ro	0x0	

26.27 IC_CLR_GEN_CALL				0x40102068
Bits	Field Name	Acc	Default	Description
0	clr_gen_call	ro	0x0	

26.28 IC_ENABLE				0x4010206C
Bits	Field Name	Acc	Default	Description
0	enable	rw	0x0	
1	abort	rw	0x0	
2	tx_cmd_block	rw	0x0	

26.29 IC_STATUS				0x40102070
Bits	Field Name	Acc	Default	Description
0	activity	ro	0x0	
1	tfnf	ro	0x1	
2	tfe	ro	0x1	
3	rfne	ro	0x0	
4	rff	ro	0x0	
5	mat_activity	ro	0x0	
6	slv_activity	ro	0x0	

26.30 IC_TXFLR				0x40102074
Bits	Field Name	Acc	Default	Description
4 : 0	txflr	ro	0x0	

26.31 IC_RXFLR				0x40102078
Bits	Field Name	Acc	Default	Description
4 : 0	rxflr	ro	0x0	

26.32 IC_SDA_HOLD				0x4010207C
Bits	Field Name	Acc	Default	Description
15 : 0	ic_sda_tx_hold	rw	0x1	
23 : 16	ic_sda_rx_hold	rw	0x0	

26.33 IC_TX_ABRT_SOURCE				0x40102080
Bits	Field Name	Acc	Default	Description
0	abrt_7b_addr_noack	ro	0x0	
1	abrt_10addr1_noack	ro	0x0	
2	abrt_10addr2_noack	ro	0x0	
3	abrt_txdata_noack	ro	0x0	
4	abrt_gcall_noack	ro	0x0	
5	abrt_gcall_read	ro	0x0	
6	abrt_hs_ackdet	ro	0x0	
7	abrt_sbyte_ackdet	ro	0x0	
8	abrt_hs_norstrt	ro	0x0	
9	abrt_sbyte_norstrt	ro	0x0	
10	abrt_10b_rd_norstrt	ro	0x0	
11	abrt_master_dis	ro	0x0	

12	arb_lost	ro	0x0	
13	abrt_slvflush_txfifo	ro	0x0	
14	abrt_slv_arblost	ro	0x0	
15	abrt_slvrd_intx	ro	0x0	
16	abrt_user_abrt	ro	0x0	
31 : 23	tx_flush_cnt	ro	0x0	

26.34 IC_DMA_CR				0x40102088
Bits	Field Name	Acc	Default	Description
0	rdmae	rw	0x0	
1	tdmae	rw	0x0	

26.35 IC_DMA_TDLR				0x4010208C
Bits	Field Name	Acc	Default	Description
3 : 0	dmatdl	rw	0x0	

26.36 IC_DMA_RDLR				0x40102090
Bits	Field Name	Acc	Default	Description
3 : 0	dmardl	rw	0x0	

26.37 IC_SDA_SETUP				0x40102094
Bits	Field Name	Acc	Default	Description
7 : 0	sda_setup	rw	0x64	

26.38 IC_ACK_GENERAL_CALL				0x40102098
Bits	Field Name	Acc	Default	Description
0	ack_gen_call	rw	0x0	

26.39 IC_ENABLE_STATUS				0x4010209C
Bits	Field Name	Acc	Default	Description
0	ic_en	ro	0x0	
1	slv_disabled_while_busy	ro	0x0	
2	slv_rx_data_lost	ro	0x0	

26.40 IC_FS_SPKLEN				0x401020A0
Bits	Field Name	Acc	Default	Description
7 : 0	ic_fs_spklen	rw	0x10	

26.41 IC_HS_SPKLEN				0x401020A4
Bits	Field Name	Acc	Default	Description
7 : 0	ic_hs_spklen	rw	0x8	

26.42 IC_CLR_RESTART_DET				0x401020A8
Bits	Field Name	Acc	Default	Description
0	clr_restart_det	ro	0x0	

26.43 IC_COMP_PARAM_1				0x401020F4
Bits	Field Name	Acc	Default	Description

1 : 0	apb_data_width	ro	0x2	
3 : 2	max_speed_mode	ro	0x3	
4	hc_count_values	ro	0x0	
5	intr_io	ro	0x1	
6	has_dma	ro	0x1	
7	add_encoded_params	ro	0x1	
15 : 8	rx_buffer_depth	ro	0x8	
23 : 16	tx_buffer_depth	ro	0x8	

26.44 IC_COMP_VERSION				0x401020F8
Bits	Field Name	Acc	Default	Description
31 : 0	ic_comp_version	ro	0x3230322A	

26.45 IC_COMP_TYPE				0x401020FC
Bits	Field Name	Acc	Default	Description
31 : 0	ic_comp_type	ro	0x44570140	

27 wdg0

27.1 WDG_LOAD_VAL				0x40103000
Bits	Field Name	Acc	Default	Description
31 : 0	wdg_load_val	rw	0x3FFFF	watchdog timer load value. In reset mode, software should load new value before timer decrease to 0. In interrupt mode, this value is counting start number. The default value is about 8 seconds.

27.2 WDG_CNT				0x40103004
Bits	Field Name	Acc	Default	Description
31 : 0	wdg_cnt	rw	0xFFFFFFFF	watchdog counter value

27.3 WDG_CTRL				0x40103008
Bits	Field Name	Acc	Default	Description
0	wdg_irq_en	rw	0x0	Watchdog interrupt enable bit 0: interrupt is disabled 1: interrupt is enabled For reset mode: wdg_rst_en =1, wdg_irq_en=0. For interrupt mode: wdg_rst_en =0, wdg_irq_en=1. For combined mode: wdg_rst_en =1, wdg_irq_en=1.
1	wdg_run	rw	0x0	Watchdog counter open: 0: counter stops. 1: counter runs.

27.4 WDG_INT_CLR				0x4010300C
Bits	Field Name	Acc	Default	Description
0	wdg_int_clr	wo	0x0	Watchdog interrupt clear Write 1 to this bit to clear interrupt Read this bit always get 0.

27.5 WDG_INT_RAW				0x40103010
Bits	Field Name	Acc	Default	Description
0	wdg_int_raw	ro	0x0	Watchdog interrupt raw status. Watch dog reset cannot clear this raw status. Write wdg_int_clr can clear this raw status.

4	wdg_ld_busy	ro	0x0	Watchdog load busy status 0: Watchdog is ready for new loading 1: Last loading is not completed Software must not load new value when this bit is busy, that is, this bit should be checked before any new loading. This bit is set after a new loading, and lasts two or three RTC clock cycles, about 60us - 92us.

27.6 WDG_INT_MASK				0x40103014
Bits	Field Name	Acc	Default	Description
0	wdg_int_mask	ro	0x0	Watchdog interrupt masked status

27.7 WDG_LOCK				0x40103C00
Bits	Field Name	Acc	Default	Description
15 : 0	wdg_lock	rw	0x0	Watchdog lock control Write 32'h1ACCE551 to this register to unlock watchdog. Write other value to this register to lock watchdog If reading this register, bit-0 is lock status, and other bits are reserved. If watchdog is locked, all control registers cannot be written by software.

28 wdg1

28.1 WDG_LOAD_VAL				0x40104000
Bits	Field Name	Acc	Default	Description
31 : 0	wdg_load_val	rw	0x3FFFF	watchdog timer load value. In reset mode, software should load new value before timer decrease to 0. In interrupt mode, this value is counting start number. The default value is about 8 seconds.

28.2 WDG_CNT				0x40104004
Bits	Field Name	Acc	Default	Description
31 : 0	wdg_cnt	rw	0xFFFFFFFF	watchdog counter value

28.3 WDG_CTRL				0x40104008
Bits	Field Name	Acc	Default	Description
0	wdg_irq_en	rw	0x0	Watchdog interrupt enable bit 0: interrupt is disabled 1: interrupt is enabled For reset mode: wdg_rst_en =1, wdg_irq_en=0. For interrupt mode: wdg_rst_en =0, wdg_irq_en=1. For combined mode: wdg_rst_en =1, wdg_irq_en=1.
1	wdg_run	rw	0x0	Watchdog counter open: 0: counter stops. 1: counter runs.

28.4 WDG_INT_CLR				0x4010400C
Bits	Field Name	Acc	Default	Description
0	wdg_int_clr	wo	0x0	Watchdog interrupt clear Write 1 to this bit to clear interrupt Read this bit always get 0.

28.5 WDG_INT_RAW	0x40104010

Bits	Field Name	Acc	Default	Description
0	wdg_int_raw	ro	0x0	Watchdog interrupt raw status. Watch dog reset cannot clear this raw status. Write wdg_int_clr can clear this raw status.
4	wdg_ld_busy	ro	0x0	Watchdog load busy status 0: Watchdog is ready for new loading 1: Last loading is not completed Software must not load new value when this bit is busy, that is, this bit should be checked before any new loading. This bit is set after a new loading, and lasts two or three RTC clock cycles, about 60us - 92us.

28.6 WDG_INT_MASK				0x40104014
Bits	Field Name	Acc	Default	Description
0	wdg_int_mask	ro	0x0	Watchdog interrupt masked status

28.7 WDG_LOCK				0x40104C00
Bits	Field Name	Acc	Default	Description
15 : 0	wdg_lock	rw	0x0	Watchdog lock control Write 32'h1ACCE551 to this register to unlock watchdog. Write other value to this register to lock watchdog If reading this register, bit-0 is lock status, and other bits are reserved. If watchdog is locked, all control registers cannot be written by software.

29 spi

29.1 SPI_TXD				0x40105000
Discription: Write data to tx fifo Read data from rx fifo				
Bits	Field Name	Acc	Default	Description
31 : 0	SPI_TXD_RXD	rw	0x0	Write data to this address initiates a character transmission through TX FIFO Read from this address retrieve data from RX FIFO

29.2 SPI_CLKD				0x40105004
Discription: Clock divider bit 15 to 0.divider is 2(n+1)				
Bits	Field Name	Acc	Default	Description
15 : 0	SPI_CLKD	rw	0x3	Specify the clock ratio between spi_sck and clk_spi spi_sck = clk_spi/2(SPI_CLKD + 1)

29.3 SPI_CTL0				0x40105008
Discription: SPI control register				
Bits	Field Name	Acc	Default	Description
0	NG_RX	rw	0x0	"1" enable RX data shift in at clock neg-edge
1	NG_TX	rw	0x1	"1" enable TX data shift out at clock neg-edge
6 : 2	CHNL_LEN	rw	0x0	"0" 32 bits per word "1" 1 bits per word "31" 31 bits per word
7	LSB	rw	0x0	"1": enable transmit data from LSB
11 : 8	SPI_CSN_PRE	rw	0xF	"1": cs is invalid "0": cs is valid
12	Reserved	rw	0x0	Reserved
13	SCK_REV	rw	0x0	SCK inverse enable
14	SYNC_MD	rw	0x0	"1" : sync mode

15	SYNC_POL	rw	0x0	Sync polarity, positive or negative pulse for SPI or 3-wire mode, read command polarity

29.4 SPI_CTL1				0x4010500C
Discription: SPI control register				
Bits	Field Name	Acc	Default	Description
4 : 0	S3W_POS	rw	0x0	3-wire mode, w/r control position or the sync pulse position
5	S3W_MD	rw	0x0	"1" enable 3-wire mode
6	CS_H_MD	rw	0x0	3-wire melody timing 1, csn high mode enable
7	S8_MD	rw	0x0	enable S8 mode
11 : 8	SYN_CSN_SEL	rw	0x0	S8 CD or SYNC signal maps to csn number 0x1 selects csn0 as cd signal 0x2 selects csn1 as cd signal in SPI_HS it must be 0x0
13 : 12	RTX_MD	rw	0x0	"0x00":idle mode "0x01":receive mode "0x10":transmit mode "0x11":transmit and receive

29.5 SPI_CTL2				0x40105010
Discription: SPI control register				
Bits	Field Name	Acc	Default	Description
4 : 0	S3W_RD_START	rw	0x0	Read date start bit, used for 3-wire mode and 3-wire 9bit RW mode
5	IS_SLVD	rw	0x0	"1" slave,only support microplus mode "0" master
6	DMA_EN	rw	0x0	"1" : enable DMA
7	RX_ONLY_HLD	rw	0x0	"0" : working on only receive mode, when rxf_realfull is high, SPI will be held until rxf realfull is low
8	RX_DMA_SEL	rw	0x0	"0" : rx_dma_req keep high until receiving the rx_dma_ack "1" : rx_dma_req is high when rx full is high
9	TX_DMA_SEL	rw	0x0	"0" : tx_dma_req keep high until receiving the tx_dma_ack "1" : tx_dma_req is high when tx full is high
10	DMA_REQ_SEL	rw	0x0	"1" enable 3-wire mode

29.6 SPI_CTL3				0x40105014
Discription: SPI control register				
Bits	Field Name	Acc	Default	Description
4 : 0	RXF_FULL_THLD	rw	0x10	Receive data empty threshold
12 : 8	RXF_EMPTY_THLD	rw	0x10	Receive data full threshold

29.7 SPI_CTL4				0x40105018
Discription: SPI control register				
Bits	Field Name	Acc	Default	Description
8 : 0	BLOCK_NUM	rw	0x0	Number of data words ready to receive in "receive only" mode. Only used for master mode
9	IS_RX_ONLY	rw	0x0	"1":receive data only.The bits should be written at last. Only used for master mode
10	SYNC_HALF	rw	0x0	Sync half,sync width is half spi_sck cycle
11	SYNC_CLKMASK	rw	0x0	"1" Mask out the first clock pulse in SPI mode
13 : 12	PHS_DLY	rw	0x0	Phase delay. Relate to fast mode When in normal mode,this bit is not used. Only used for slave mode
14	IS_FST	rw	0x0	"0": normal mode "1": fast mode

15	RX_ONLY_DO	rw	0x0	"0": SPI send all 0 to slave "1": SPI send all 1 to slave

29.8 SPI_CTL5				0x4010501C
Discription: SPI control register				
Bits	Field Name	Acc	Default	Description
15 : 0	ITVL_NUM	rw	0x0	For master, transmit data interval, programmabl n from 0 to 65535, delay is (4*n+3) clock cycle For slave, max receive data interval. If slave has not sampled data,in the interval (4*n+3) spi_clk,slave will stop the receive process and send timeout interrupt

29.9 SPI_INT_EN				0x40105020
Discription: SPI interrupt enable register				
Bits	Field Name	Acc	Default	Description
1	RXF_EMPTY_INT_EN	rw	0x0	Rx_fifo_empty interrupt enable
2	TXF_FUL_INT_EN	rw	0x0	Tx_fifo_full interrupt enable
4	RX_OVF_INT_EN	rw	0x0	Rx_overrun_reg interrupt enable
5	TIME_OUT_INT_EN	rw	0x0	Slave mode timeout interrupt enable
6	RXF_FULL_INT_EN	rw	0x0	Rx_fifo_full interrupt enable
7	TXF_EMPTY_INT_EN	rw	0x0	Tx_fifo_empty interrupt enable
8	TXF_END_INT_EN	rw	0x0	Tx end interrupt enable
9	RXF_END_INT_EN	rw	0x0	Rx end interrupt enable

29.10 SPI_INT_CLR				0x40105024
Discription: SPI interrupt clear register				
Bits	Field Name	Acc	Default	Description
0	RXF_FULL_INT_CLR	wo	0x0	Write "1" clear Rx_fifo_full interrupt
1	RXF_EMPTY_INT_CLR	wo	0x0	Write "1" clear Rx_fifo_empty interrupt
2	TXF_FULL_INT_CLR	wo	0x0	Write "1" clear Tx_fifo_full interrupt
3	TXF_EMPTY_INT_CLR	wo	0x0	Write "1" clear Tx_fifo_empty interrupt
4	RX_OVF_INT_CLR	wo	0x0	Write "1" clear Rx_overrun_reg interrupt
5	TIME_OUT_INT_CLR	wo	0x0	Write "1" clear slave mode timeout interrupt
8	TXF_END_INT_CLR	rw	0x0	Tx data end interrupt clear
9	RXF_END_INT_CLR	rw	0x0	Rx data end interrupt clear

29.11 SPI_INT_RAW_STS				0x40105028
Discription: SPI interrupt raw status				
Bits	Field Name	Acc	Default	Description
0	RX_FIFO_FULL_R	ro	0x0	Rx_fifo_full_r
1	RXF_EMPTY_RAW_STS	ro	0x1	Raw rx_fifo_empty interrupt
2	TXF_FULL_RAW_STS	ro	0x0	Raw Tx_fifo_full interrupt
3	TX_FIFO_EMPTY_W	ro	0x1	Raw txf_fifo_empty_empty interrupt
4	RX_OVF_RAW_STS	ro	0x0	Raw Rx_overrun_reg interrupt
5	TIME_OUT_RAW_STS	ro	0x0	Raw slave mode time out interrupt
6	RXF_FULL_RAW_STS	ro	0x0	Raw rxf_full interrupt. when the number of rx fifo data byte is larger than the the rx empty watermark value.Atuo clear
7	TXF_EMPTY_RAW_STS	ro	0x1	Raw txf_empty interrupt. when the number of tx fifo data byte is less than the the tx empty watermark value.Atuo clear
8	TX_END_IRQ	ro	0x0	Raw tx data end interrupt. bit is set when spi controller send TX_DATA_LEN data
9	RX_END_IRQ	ro	0x0	Raw rx data end interrupt. bit is set when spi controller receive RX_DATA_LEN data

29.12 SPI_INT_MASK_STS				0x4010502C
Discription: SPI interrupt mask status				
Bits	Field Name	Acc	Default	Description
1	RX_FIFO_EMPTY-_MASK_STS	ro	0x0	Rx_fifo_empty interrupt mask status
2	TX_FIFO_FULL_MASK_STS	ro	0x0	Tx_fifo_full interrupt mask status
4	RX_OVF_MASK_STS	ro	0x0	Rx_overrun_reg interrupt mask status
5	TIME_OUT_MASK_STS	ro	0x0	Slave mode time out interrupt mask status
6	RXF_FULL_MASK_STS	ro	0x0	Rxf_full interrupt mask status.
7	TXF_EMPTY_MASK_STS	ro	0x0	Txf_empty interrupt mask status.
8	TXF_END_IRQ_MASK_STS	ro	0x0	Raw tx data end interrupt. bit is set when spi controller send TX_DATA_LEN data
9	RXF_END_IRQ_MASK_STS	ro	0x0	Raw rx data end interrupt. bit is set when spi controller receive RX_DATA_LEN data

29.13 SPI_STS1				0x40105030
Discription: SPI status register				
Bits	Field Name	Acc	Default	Description
4 : 0	RXF_RD_ADDR	ro	0x0	RX FIFO read address
12 : 8	RXF_WR_ADDR	ro	0x0	RX FIFO write address

29.14 SPI_STS2				0x40105034
Discription: SPI status register				
Bits	Field Name	Acc	Default	Description
0	RXF_FULL	ro	0x0	This bit is set when the number of RX FIFO data byte is larger than the RX full watermark value. Auto cleared when the condition disappears.
1	RXF_EMPTY	ro	0x1	This bit is set when the number of RX FIFO data byte is less than the RX empty interrupt watermark value. Auto cleared when the condition disappears.
2	TXF_FULL	ro	0x0	This bit is set when the number of TX FIFO data byte is larger than the TX full watermark value. Auto cleared when the condition disappears.
3	TXF_EMPTY	ro	0x1	This bit is set when the number of TX FIFO data byte is less than the TX empty watermark value. Auto cleared when the condition disappears.
4	RXF_REALFULL	ro	0x0	RX FIFO is real full.(not relates to register RXF_FULL_THLD)
5	RXF_REALEMPTY	ro	0x1	RX FIFO is real empty. RX FIFO has no data
6	TXF_REALFULL	ro	0x0	TX FIFO is real full.(not relates to register TXF_FULL_THLD)
7	TXF_REALEMPTY	ro	0x1	TX FIFO is real empty. TX FIFO has no data
8	BUSY	ro	0x0	"1": busy, transmit process "0": idle state
9	SPI_RXD	ro	0x0	Spi_rxd(monitor)
10	SPI_TXD	ro	0x0	Spi_txd(monitor)
11	SPI_SCK	ro	0x0	Spi_sck(monitor)
12	SPI_CS	ro	0x0	Spi_cs(monitor)

29.15 DSP_WAIT				0x40105038
Discription: Use for DSP control				
Bits	Field Name	Acc	Default	Description
3 : 0	SPI_DSPWAIT	rw	0x1	This register is used for DSP control
5 : 4	RX_DATA_SWT	rw	0x0	Read data switch: 0: rdata[31:0] = pdata[31:0] 1: rdata = {pdata[7:0], pdata[15:8], pdata[23:16], pdata[31:24]} 2: rdata = {pdata[15:0],pdata[31:16]}

7 : 6	TX_DATA_SWT	rw	0x0	Write data switch: 0: wdata[31:0] = pdata[31:0] 1: wdata = {pdata[7:0], pdata[15:8], pdata[23:16], pdata[31:24]} 2: wdata = {pdata[15:0],pdata[31:16]}

29.16 SPI_STS3				0x4010503C
Discription: SPI status register				
Bits	Field Name	Acc	Default	Description
8 : 0	RX_CNT	ro	0x0	Working in only receive mode as master

29.17 SPI_CTL6				0x40105040
Discription: SPI control register				
Bits	Field Name	Acc	Default	Description
4 : 0	TXF_FULL_THLD	rw	0x8	TX FIFO data full threshold
12 : 8	TXF_EMPTY_THLD	rw	0x8	TX FIFO data empty threshold

29.18 SPI_STS4				0x40105044
Discription: SPI status register				
Bits	Field Name	Acc	Default	Description
4 : 0	TXF_RD_ADDR	ro	0x0	TX FIFO read address
12 : 8	TXF_WR_ADDR	ro	0x0	TX FIFO write address

29.19 SPI_FIFO_RST				0x40105048
Discription: SPI tx/rx fifo reset bit				
Bits	Field Name	Acc	Default	Description
0	SPI_FIFO_RST	rw	0x0	"1":reset all FIFOs

29.20 SPI_CTL7				0x4010504C
Discription: SPI control register				
Bits	Field Name	Acc	Default	Description
0	CSN_IE_CTL	rw	0x0	CSN IE output set 0: not support csn input 1: support csn input
2 : 1	CSN_I_SEL	rw	0x0	CSN select control: 0: CSN 0 1: CSN 1 2: CSN 2 3: CSN 3
5 : 3	SPI_MODE	rw	0x0	Used for master only 0: SPI_MODE disable 1: 3 wire 9 bit, cd bit, SDI/SDO share one IO 2: 3 wire 9 bit, cd bit, SDI,SDO 3: 4 wire 8 bit, cd pin, SDI/SDO 4: 4 wire 8 bit, cd pin, SDI,SDO
6	TX_CMD_SET	rw	0x0	1: select fmark as the dma request 0:select software dma request
7	SPI_TX_HLD_EN	rw	0x0	1: enable ahb2apb bridge write hold when tx fifo full 0: disable ahb2apb bridge write hold
8	SPI_RX_HLD_EN	rw	0x0	1: enable ahb2apb bridge read hold when rx fifo empty 0: disable ahb2apb bridge write hold
9	SPI_SLV_CLK_SEl	rw	0x0	
10	SPI_SLV_EN	rw	0x0	Used when SPI slave in High speed mode 1:enable spi slave rtx 0:disable spi slave rtx
11	SPI_SLV_SEL	rw	0x0	1: SPI slave in low speed mode 0: SPI slave in low speed mode
12	RGB_888_EN	rw	0x0	
13	RGB_666_EN	rw	0x0	
14	RGB_565_EN	rw	0x0	

15	DATA_LINE2_EN	rw	0x0	

29.21 SPI_STS5				0x40105050
Discription: SPI status register				
Bits	Field Name	Acc	Default	Description
0	CSN_IN_SYNC2	ro	0x0	CSN for slave
4	CSN_IN_ERR_SYNC2	ro	0x0	1:indicates csn occurring a exception

29.22 SPI_CTL8				0x40105054
Discription: SPI tx data control				
Bits	Field Name	Acc	Default	Description
3 : 0	SPI_TX_DATA_LEN_H	rw	0x0	Indicates tx data length from tx fifo, High 4 bits of spi tx data length
9 : 4	SPI_TX_DUMY_LEN	rw	0x0	Spi tx dummy clock length
12	RGB_PIX_MODE	rw	0x0	
13	CD_DATA2_SEL	rw	0x0	
14	SPI_CD_BIT2	rw	0x0	
15	SPI_CD_BIT	rw	0x0	Spi tx cd bit 0:indicates command 1:indicates data

29.23 SPI_CTL9				0x40105058
Discription: SPI tx data control				
Bits	Field Name	Acc	Default	Description
15 : 0	SPI_TX_DATA_LEN_L	rw	0x0	Indicates: spi tx data length from tx fifo, Low 16bit of tx data length

29.24 SPI_CTL10				0x4010505C
Discription: SPI tx data control				
Bits	Field Name	Acc	Default	Description
3 : 0	SPI_RX_DATA_LEN_H	rw	0x0	Indicates rx data length from slave, High 4 bits of spi rx data length
9 : 4	SPI_RX_DUMY_LEN	rw	0x0	Spi rx dummy clock length
15 : 10	CHNL_RX_LEN	rw	0x0	spi rx data len, used in spi mode 0

29.25 SPI_CTL11				0x40105060
Discription: SPI tx data control				
Bits	Field Name	Acc	Default	Description
15 : 0	SPI_RX_DATA_LEN_L	rw	0x0	Indicates: spi rx data length from slave, Low 16bit of rx data length

29.26 SPI_CTL12				0x40105064
Discription: SPI tx data control				
Bits	Field Name	Acc	Default	Description
0	SW_RX_REQ	wo	0x0	Software RX data request, for read LCD
1	SW_TX_REQ	wo	0x0	Software TX data request, for write LCD

29.27 SPI_STS6				0x40105068
Discription: tx data counter				
Bits	Field Name	Acc	Default	Description
15 : 0	TX_DATA_CNT	ro	0x0	Tx data cnt[15:0]

29.28 SPI_STS7				0x4010506C
Discription: SPI status register				
Bits	Field Name	Acc	Default	Description
3 : 0	TX_DATA_CNT_H	ro	0x0	Tx data cnt[19:16]
15 : 10	TX_DUMMY_CNT	ro	0x0	Tx dummy cnt

29.29 SPI_STS8				0x40105070
Discription: SPI status register				
Bits	Field Name	Acc	Default	Description
15 : 0	RX_DATA_CNT	ro	0x0	Rx data cnt[15:0]

29.30 SPI_STS9				0x40105074
Discription: SPI status register				
Bits	Field Name	Acc	Default	Description
3 : 0	RX_DATA_CNT_H	ro	0x0	Rx data cnt[19:16]
15 : 10	RX_DUMMY_CNT	ro	0x0	Rx dummy cnt

30 timer0

30.1 tmr_cfg				0x40106000
Bits	Field Name	Acc	Default	Description
0	cfg_tmr_run	rw	0x0	Timer run enable, high active.
1	cfg_tmr_reset	rw	0x0	Timer PC reset, write 1 auto clear.

30.2 tmr_pr				0x40106004
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_pr	rw	0xFFFFFFFF	Prescale register.

30.3 tmr_pc				0x40106008
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_pc	rw	0xFFFFFFFF	Current counter number.

30.4 tmr_mr0				0x4010600C
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_mr0	rw	0xFFFFFFFF	Match point for CPU0.

30.5 tmr_mr1				0x40106010
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_mr1	rw	0xFFFFFFFF	Match point for CPU1.

30.6 tmr_mr2				0x40106014
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_mr2	rw	0xFFFFFFFF	Match point for CPU2.

30.7 tmr_delta0				0x40106018
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_delta0	rw	0xFFFFFFFF	Delta counter for CPU0.

30.8 tmr_delta1				0x4010601C
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_delta1	rw	0xFFFFFFFF	Delta counter for CPU1.

30.9 tmr_delta2				0x40106020
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_delta2	rw	0xFFFFFFFF	Delta counter for CPU2.

30.10 tmr_rtc_clk_div				0x40106024
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_tmr_rtc_clk_div	rw	0x19	Timer rtc clock dividier. Default is 26M/26, 1 bit means 1us for PC.
16	cfg_tmr_rtc_clk_div_update	rw	0x0	RTC clock divider update, write auto clear.

30.11 tmr_int_mask_enable				0x40106028
Bits	Field Name	Acc	Default	Description
0	cfg_tmr_match-0_int_mask_enable	rw	0x0	Match point0 interrupt mask enable. Write1 to enable.
1	cfg_tmr_match-1_int_mask_enable	rw	0x0	Match point1 interrupt mask enable. Write1 to enable.
2	cfg_tmr_match-2_int_mask_enable	rw	0x0	Match point2 interrupt mask enable. Write1 to enable.

30.12 tmr_int_mask_clear				0x4010602C
Bits	Field Name	Acc	Default	Description
0	cfg_tmr_match-0_int_mask_clear	rw	0x0	Match point0 interrupt mask clear. Write1 to clear.
1	cfg_tmr_match-1_int_mask_clear	rw	0x0	Match point1 interrupt mask clear. Write1 to clear.
2	cfg_tmr_match-2_int_mask_clear	rw	0x0	Match point2 interrupt mask clear. Write1 to clear.

30.13 tmr_int_raw				0x40106030
Bits	Field Name	Acc	Default	Description
0	cfg_tmr_match0_int_raw	rw	0x0	Match point0 raw interrupt. Write 1 to clear.
1	cfg_tmr_match1_int_raw	rw	0x0	Match point1 raw interrupt. Write 1 to clear.
2	cfg_tmr_match2_int_raw	rw	0x0	Match point2 raw interrupt. Write 1 to clear.

30.14 tmr_int_status				0x40106034
Bits	Field Name	Acc	Default	Description
0	cfg_tmr_match0_int_status	rw	0x0	Match point0 interrupt status. Write 1 to clear.
1	cfg_tmr_match1_int_status	rw	0x0	Match point1 interrupt status. Write 1 to clear.
2	cfg_tmr_match2_int_status	rw	0x0	Match point2 interrupt status. Write 1 to clear.

31 timer1

31.1 tmr_cfg				0x40107000
Bits	Field Name	Acc	Default	Description
0	cfg_tmr_run	rw	0x0	Timer run enable, high active.
1	cfg_tmr_reset	rw	0x0	Timer PC reset, write 1 auto clear.

31.2 tmr_pr				0x40107004
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_pr	rw	0xFFFFFFFF	Prescale register.

31.3 tmr_pc				0x40107008
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_pc	rw	0xFFFFFFFF	Current counter number.

31.4 tmr_mr0				0x4010700C
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_mr0	rw	0xFFFFFFFF	Match point for CPU0.

31.5 tmr_mr1				0x40107010
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_mr1	rw	0xFFFFFFFF	Match point for CPU1.

31.6 tmr_mr2				0x40107014
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_mr2	rw	0xFFFFFFFF	Match point for CPU2.

31.7 tmr_delta0				0x40107018
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_delta0	rw	0xFFFFFFFF	Delta counter for CPU0.

31.8 tmr_delta1				0x4010701C
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_delta1	rw	0xFFFFFFFF	Delta counter for CPU1.

31.9 tmr_delta2				0x40107020
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_tmr_delta2	rw	0xFFFFFFFF	Delta counter for CPU2.

31.10 tmr_rtc_clk_div				0x40107024
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_tmr_rtc_clk_div	rw	0x19	Timer rtc clock dividier. Default is 26M/26, 1 bit means 1us for PC.
16	cfg_tmr_rtc_clk_div_update	rw	0x0	RTC clock divider update, write auto clear.

31.11 tmr_int_mask_enable				0x40107028
Bits	Field Name	Acc	Default	Description
0	cfg_tmr_match-0_int_mask_enable	rw	0x0	Match point0 interrupt mask enable. Write1 to enable.
1	cfg_tmr_match-1_int_mask_enable	rw	0x0	Match point1 interrupt mask enable. Write1 to enable.
2	cfg_tmr_match-2_int_mask_enable	rw	0x0	Match point2 interrupt mask enable. Write1 to enable.

31.12 tmr_int_mask_clear				0x4010702C
Bits	Field Name	Acc	Default	Description

0	cfg_tmr_match-0_int_mask_clear	rw	0x0	Match point0 interrupt mask clear. Write1 to clear.
1	cfg_tmr_match-1_int_mask_clear	rw	0x0	Match point1 interrupt mask clear. Write1 to clear.
2	cfg_tmr_match-2_int_mask_clear	rw	0x0	Match point2 interrupt mask clear. Write1 to clear.

31.13 tmr_int_raw				0x40107030
Bits	Field Name	Acc	Default	Description
0	cfg_tmr_match0_int_raw	rw	0x0	Match point0 raw interrupt. Write 1 to clear.
1	cfg_tmr_match1_int_raw	rw	0x0	Match point1 raw interrupt. Write 1 to clear.
2	cfg_tmr_match2_int_raw	rw	0x0	Match point2 raw interrupt. Write 1 to clear.

31.14 tmr_int_status				0x40107034
Bits	Field Name	Acc	Default	Description
0	cfg_tmr_match0_int_status	rw	0x0	Match point0 interrupt status. Write 1 to clear.
1	cfg_tmr_match1_int_status	rw	0x0	Match point1 interrupt status. Write 1 to clear.
2	cfg_tmr_match2_int_status	rw	0x0	Match point2 interrupt status. Write 1 to clear.

32 trng

32.1 trng_en				0x40108000
Bits	Field Name	Acc	Default	Description
2	sTrngEnQ	rw	0x0	Block enable, high active.
3	sTrngIEQ	rw	0x0	Interrupte enable, high active.
4	sTrngEEQ	rw	0x0	

32.2 trng_status				0x40108004
Bits	Field Name	Acc	Default	Description
0	sDRDYQ	ro	0x0	Random data ready status. Read sDRQ(0x008) to clear status.
2	sSECSQ	ro	0x0	Clock error current status. Write bit[6] 1'b0 to clear status.
6	sSEISQ	ro	0x0	Seed error interrupt status. Write bit[6] 1'b0 to clear status.

32.3 trng_data				0x40108008
Bits	Field Name	Acc	Default	Description
31 : 0	sDRQ	ro	0x0	Random 32-bit data.

32.4 trng_div_dly				0x40108010
Bits	Field Name	Acc	Default	Description
7 : 0	sDivNumQ	rw	0x40	Enable period
15 : 8	SDivHighQ	rw	0x10	Enable high duration
23 : 16	sDlyNumQ	rw	0x8	Delay number

32.5 trng_sel				0x40108014
Bits	Field Name	Acc	Default	Description
7 : 0	sTrngSel0Q	rw	0xF	Trng Sel0
15 : 8	sTrngSel1Q	rw	0xF0	Trng Sel1
23 : 16	sLfsrGen0Q	rw	0x0	LFSR gen0
31 : 24	sLfsrGen1Q	rw	0x0	LFSR gen1

33 ana_reg0

33.1 flash_pad_pull				0x40109000
Bits	Field Name	Acc	Default	Description
3 : 0	cfg_ana_fls_sio_pull_dn	rw	0xC	FLASH SIO pull down
7 : 4	cfg_ana_fls_sio_pull_up	rw	0x3	FLASH SIO pull up
8	cfg_ana_fls_cs_pull_dn	rw	0x0	FLASH CS pull down
9	cfg_ana_fls_cs_pull_up	rw	0x1	FLASH CS pull up
10	cfg_ana_fls_clk_pull_dn	rw	0x0	FLASH clock pull down
11	cfg_ana_fls_clk_pull_up	rw	0x0	FLASH clock pull up

34 proc_mon

34.1 auto_mode				0x4010A000
Bits	Field Name	Acc	Default	Description
0	cfg_auto_mode	rw	0x0	1'b1: auto pvt monitor mode; 1'b0: single mode

34.2 cfg_start				0x4010A004
Bits	Field Name	Acc	Default	Description
0	cfg_start	rw	0x0	Write to generate start pulse

34.3 cfg_auto_stop				0x4010A008
Bits	Field Name	Acc	Default	Description
0	cfg_auto_stop	rw	0x0	Write to generate stop pulse when auto monitor mode

34.4 enable_duration				0x4010A00C
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_enable_duration	rw	0x104	1'b1: manual mode; 1'b0: auto mode

34.5 cfg_auto_interval				0x4010A010
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_auto_interval	rw	0x18CBA80	1'b1: manual mode; 1'b0: auto mode

34.6 ro_pvt_cnt_hvt				0x4010A014
Bits	Field Name	Acc	Default	Description
31 : 0	ro_pvt_cnt_hvt	ro	0x0	PVT counter for HVT cell

35 gpioa

35.1 GPIODATA				0x4010B000
Bits	Field Name	Acc	Default	Description
19 : 0	GPIODATA	rw	0x0	GPIO bits data input

35.2 GPIODMSK				0x4010B004
Bits	Field Name	Acc	Default	Description
19 : 0	GPIODMSK	rw	0x0	GPIODATA register can be read/write if GPIO DMSK set "1"

35.3 GPIODIR				0x4010B008
Bits	Field Name	Acc	Default	Description
19 : 0	GPIODIR	rw	0x0	”1” configure gpio bits to be output ”0” configure gpio bits to be input

35.4 GPIOIS				0x4010B00C
Bits	Field Name	Acc	Default	Description
19 : 0	GPIOIS	rw	0xFFFFF	”1” detect signals level ”0” detect signals edge

35.5 GPIOIBE				0x4010B010
Bits	Field Name	Acc	Default	Description
19 : 0	GPIOIBE	rw	0x0	”1” both edges trigger an interrupt, ”0” interrupt generation event is controlled by GPIOIEV

35.6 GPIOIEV				0x4010B014
Bits	Field Name	Acc	Default	Description
19 : 0	GPIOIEV	rw	0xFFFFF	GPIO bits interrupt event register: ”1” high levels trigger interrupts, ”0” low levels trigger interrupts.

35.7 GPIOIE				0x4010B018
Bits	Field Name	Acc	Default	Description
19 : 0	GPIOIE	rw	0x0	GPIO bits interrupt enable register: ”1” corresponding bit interrupt is enabled. ”0” corresponding bit interrupt isn’t enabled

35.8 GPIORIS				0x4010B01C
Bits	Field Name	Acc	Default	Description
19 : 0	GPIORIS	ro	0x0	GPIO bits raw interrupt status register: ”1” interrupt condition met ”0” condition not met

35.9 GPIOMIS				0x4010B020
Bits	Field Name	Acc	Default	Description
19 : 0	GPIOMIS	ro	0x0	GPIO bits masked interrupt status register: ”1” Interrupt active ”0” interrupt not active

35.10 GPIOIC				0x4010B024
Bits	Field Name	Acc	Default	Description
19 : 0	GPIOIC	wo	0x0	GPIO bits interrupt clear register: ”1” clears detected interrupt. ”0” has no effect.

35.11 GPIOINEN				0x4010B028
Bits	Field Name	Acc	Default	Description
19 : 0	GPIOINEN	rw	0x0	GPIO input enable register: ”1” input enable. ”0” input disable.

35.12 GPIO_FILTER_NUM	0x4010B02C

Bits	Field Name	Acc	Default	Description
19 : 0	GPIO_FILTER_NUM	rw	0x33333	

35.13 GPIO_FILTER_DIV_L				0x4010B030
Bits	Field Name	Acc	Default	Description
19 : 0	GPIO_FILTER_DIV_L	rw	0x0	

35.14 GPIO_FILTER_DIV_H				0x4010B034
Bits	Field Name	Acc	Default	Description
19 : 0	GPIO_FILTER_DIV_H	rw	0x0	

36 efuse

36.1 EFUSE_ALL0_INDEX				0x4010C008
Bits	Field Name	Acc	Default	Description
15 : 0	EFUSE_ALL0_END_INDEX	rw	0x1F	All 0 check end index
31 : 16	EFUSE_ALL0_START_INDEX	rw	0x0	All 0 check start index

36.2 EFUSE_MODE_CTRL				0x4010C00C
Bits	Field Name	Acc	Default	Description
0	EFUSE_ALL0_CHECK_START	rw	0x0	write 1 to this bit will trigger all0 check to efuse, this bit is self-clear ,read this bit will always get 0.(use PREADY)
31 : 1	reserved_0	ro	0x0	RESERVED

36.3 EFUSE_IP_VER_reg				0x4010C014
Bits	Field Name	Acc	Default	Description
15 : 0	EFUSE_IP_VER	ro	0x100	IP version, now is r1p0
17 : 16	EFUSE_TYPE	ro	0x0	Efuse type: 00 TSMC
31 : 18	reserved_0	ro	0x0	RESERVED

36.4 EFUSE_CFG0				0x4010C018
Bits	Field Name	Acc	Default	Description
8 : 0	TPGM_TIME_CNT	rw	0x140	Program strobe high time. If set n, the Tpgm time will last for (n+1) clk_efuse cycle, only when PGM_EN=1 can write this field.
15 : 9	reserved_0	ro	0x0	RESERVED
23 : 16	EFUSE_STROBE_LOW_WIDTH	rw	0x1C	This counter is used to control STROBE signal low level width in PGM mode, for TSMC efuse memory, no extra requirement for this signal, For 26Mhz efuse controller clock, by default, this width will be: 38.4*28=1075ns ¿ 1us. If you want to speed up program speed, can configure the register to a smaller value.
31 : 24	CLK_EFS_DIV	rw	0x0	Clk_efs divider, if this value is n, the frequency of controller will be divided by (n+1) from clk_efs. In most case, this field not need to change.

36.5 EFUSE_SEC_EN				0x4010C040
Bits	Field Name	Acc	Default	Description
0	SEC_VDD_EN	rw	0x0	efuse vdd enable
1	SEC_AUTO_CHECK_ENABLE	rw	0x0	program read back auto-check enable

2	DOUBLE_BIT_EN_SEC	rw	0x0	efuse double bit enable
3	SEC_MARGIN_RD_ENABLE	rw	0x0	efuse margin read mode enable
4	SEC_LOCK_BIT_WR_EN	rw	0x0	If set the bit, lock bits will be written after PGM process.
31 : 5	reserved_0	ro	0x0	RESERVED

36.6 EFUSE_SEC_ERR_FLAG				0x4010C044
Bits	Field Name	Acc	Default	Description
0	block_auto_check_failed	ro	0x0	The bit indicates block auto check failed after programming. If PGM_AUTO_CHK_EN is set, and controller compared the value read after PGM from the same block, and found the two value not match, this bit will set as an error flag. But if this block is protected, the PGM command in-fact not really send, so this bit will not set.
1	shadow_block_-auto_check_failed	ro	0x0	The bit indicates shadow block auto check failed after programming if double_bit_en is set. If PGM_AUTO_CHK_EN is set, and controller compared the value read after PGM from the same block, and found the two value not match, this bit will set as an error flag. But if this block is protected, the PGM command in-fact not really send, so this bit will not set.
3 : 2	reserved_2	ro	0x0	RESERVED
4	SEC_WORD0_PROT_FLAG	ro	0x0	The bit indicates block auto check failed after programming. If PGM_AUTO_CHK_EN is set, and controller compared the value read after PGM from the same block, and found the two value not match, this bit will set as an error flag. But if this block is protected, the PGM command in-fact not really send, so this bit will not set.
5	SEC_WORD1_PROT_FLAG	ro	0x0	The bit indicates shadow block is protected and can not be programmed if double_bit_en is set. If SW send a PGM command to memory block[i], and the controller found this memory block is protected(which means the highest bit is 1), this bit will set to 1.
7 : 6	reserved_1	ro	0x0	RESERVED
8	SEC_PG_EN_WR_FLAG	ro	0x0	the bit indicates write process without setting pg_en to 1.
9	SEC_VDD_ON_RD_FLAG	ro	0x0	the bit indicates read process without setting vdd_on to 1.
10	SEC_BLOCK0_RD_FLAG	ro	0x0	the bit indicates arbiter read block0 which may indicates unexpected access.
11	SEC_MAGNUM_WR_FLAG	ro	0x0	the bit indicates write process without setting magic number.
12	SEC_ENK_ERR_FLAG	ro	0x0	the bit enk1 and enk2 is not switch correctly.
13	SEC_ALL0_CHECK_FLAG	ro	0x0	the bit indicates all 0 check fail.
31 : 14	reserved_0	ro	0x0	RESERVED

36.7 EFUSE_SEC_FLAG_CLR				0x4010C048
Bits	Field Name	Acc	Default	Description
0	SEC_WORD0_ERR_CLR	rw	0x0	write 1 will clear SEC_WORD0_ERR_FLAG. Write 0 will do nothing.
1	SEC_WORD1_ERR_CLR	rw	0x0	write 1 will clear SEC_WORD1_ERR_FLAG. Write 0 will do nothing.
3 : 2	reserved_2	ro	0x0	RESERVED
4	SEC_WORD0_PROT_CLR	rw	0x0	write 1 will clear SEC_WORD0_PROT_FLAG. Write 0 will do nothing.
5	SEC_WORD1_PROT_CLR	rw	0x0	write 1 will clear SEC_WORD1_PROT_FLAG. Write 0 will do nothing.
7 : 6	reserved_1	ro	0x0	RESERVED
8	SEC_PG_EN_WR_CLR	rw	0x0	write 1 will clear SEC_PG_EN_WR_FLAG

9	SEC_VDD_ON_RD_CLR	rw	0x0	write 1 will clear SEC_VDD_ON_RD_FLAG
10	SEC_BLOCK0_RD_CLR	rw	0x0	write 1 will clear SEC_BLOCK0_RD_FLAG
11	SEC_MAGNUM_WR_CLR	rw	0x0	write 1 will clear SEC_MAGNUM_WR_FLAG
12	SEC_ENK_ERR_CLR	rw	0x0	write 1 will clear SEC_ENK_ERR_FLAG
13	SEC_ALL0_CHECK_CLR	rw	0x0	write 1 will clear SEC_ALL0_CHECK_FLAG
31 : 14	reserved_0	ro	0x0	RESERVED

36.8 EFUSE_SEC_MAGIC_NUMBER 0x4010C04C

Bits	Field Name	Acc	Default	Description
15 : 0	SEC_EFUSE_MAGIC_NUMBER	rw	0x0	Magic number, only when this field is 0x8800, the efuse programming command can be handle. Set the magic number right will lock the power switch and PGM enable. So if SW want to program efuse memory, except open clocks and power, 2 other conditions must be met : (1) SEC_EFUSE_MAGIC_NUMBER =0x8800 (2) PG_EN=1; (3) Switch the power right;
31 : 16	reserved_0	ro	0x0	RESERVED

36.9 EFUSE_FW_CFG 0x4010C050

Bits	Field Name	Acc	Default	Description
0	CONF_PROT	rw	0x0	SEC/NON-SEC address configure. 1: indicates SEC can access EFUSE_CFG0; 0: indicates NON-SEC can access EFUSE_CFG0;
1	ACCESS_PROT	rw	0x0	0: SEC access; 1: NON SEC address enable switch
31 : 2	reserved_0	ro	0x0	RESERVED

36.10 EFUSE_PW_SWT 0x4010C054

Bits	Field Name	Acc	Default	Description
0	EFS_ENK1_ON	rw	0x0	VDDQ power switch K2, to safely control this power switch.
1	EFS_ENK2_ON	rw	0x1	VDDQ power switch K2, to safely control this power switch.
2	NS_S_PG_EN	rw	0x0	set this bit will open static power supply for efuse memory, before any operation towards to efuse memory this bit have to set to 1. once this bit is cleared, the efuse will go to power down mose.
3	ANLG_CFG_EFUSE_SAR_READ_MODE	rw	0x0	read mode, 1'b1: sar mode; 1'b0: normal mode
4	ANLG_CFG_EFUSE_SAR_LCH_BIAS_MODE	rw	0x0	SAR bias mode
8 : 5	ANLG_CFG_EFUSE_SAR_DLY_BIT	rw	0x0	SAR delay bits
11 : 9	ANLG_CFG_EFUSE_SAR_BIAS_BIT	rw	0x0	SAR bias bit control
16 : 12	SAR_READ_BITS	rw	0x0	Read bits index for SAR mode
31 : 17	reserved_0	ro	0x0	RESERVED

36.11 EFUSE_FUNC_EN_0 0x4010C058

Bits	Field Name	Acc	Default	Description
0	efuse_func_en_0	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.12 EFUSE_FUNC_EN_1 0x4010C05C

Bits	Field Name	Acc	Default	Description

0	efuse_func_en_1	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.13 EFUSE_FUNC_EN_2				0x4010C060
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_2	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.14 EFUSE_FUNC_EN_3				0x4010C064
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_3	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.15 EFUSE_FUNC_EN_4				0x4010C068
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_4	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.16 EFUSE_FUNC_EN_5				0x4010C06C
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_5	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.17 EFUSE_FUNC_EN_6				0x4010C070
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_6	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.18 EFUSE_FUNC_EN_7				0x4010C074
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_7	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.19 EFUSE_FUNC_EN_8				0x4010C078
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_8	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.20 EFUSE_FUNC_EN_9				0x4010C07C
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_9	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.21 EFUSE_FUNC_EN_10				0x4010C080
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_10	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.22 EFUSE_FUNC_EN_11				0x4010C084
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_11	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.23 EFUSE_FUNC_EN_12				0x4010C088
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_12	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.24 EFUSE_FUNC_EN_13				0x4010C08C
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_13	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.25 EFUSE_FUNC_EN_14				0x4010C090
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_14	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.26 EFUSE_FUNC_EN_15				0x4010C094
Bits	Field Name	Acc	Default	Description
0	efuse_func_en_15	rw	0x1	write once register, security function control bit: 0 = disabled 1 = enabled
31 : 1	reserved_0	ro	0x0	RESERVED

36.27 efuse_bist_en_reg				0x4010C098
Bits	Field Name	Acc	Default	Description
0	efuse_bist_en	rw	0x0	efuse bist enable, write once register
31 : 1	reserved_0	ro	0x0	RESERVED

36.28 efuse_block0_rw_ctrl_reg				0x4010C09C
Bits	Field Name	Acc	Default	Description
0	efuse_block0_rw_ctrl	rw	0x1	control efuse block0 read/write, write once register: 0 = not enable read/write efuse block0 1 = enable read/write efuse block0
31 : 1	reserved_0	ro	0x0	RESERVED

36.29 efuse_block1_rw_ctrl_reg				0x4010C0A0
Bits	Field Name	Acc	Default	Description
0	efuse_block1_rw_ctrl	rw	0x1	control efuse block1 read/write, write once register: 0 = not enable read/write efuse block1 1 = enable read/write efuse block1
31 : 1	reserved_0	ro	0x0	RESERVED

36.30 efuse_block2_rw_ctrl_reg				0x4010C0A4
Bits	Field Name	Acc	Default	Description
0	efuse_block2_rw_ctrl	rw	0x1	control efuse block2 read/write, write once register: 0 = not enable read/write efuse block2 1 = enable read/write efuse block2
31 : 1	reserved_0	ro	0x0	RESERVED

36.31 efuse_block3_rw_ctrl_reg				0x4010C0A8
Bits	Field Name	Acc	Default	Description
0	efuse_block3_rw_ctrl	rw	0x1	control efuse block3 read/write, write once register: 0 = not enable read/write efuse block3 1 = enable read/write efuse block3
31 : 1	reserved_0	ro	0x0	RESERVED

36.32 efuse_block4_rw_ctrl_reg				0x4010C0AC
Bits	Field Name	Acc	Default	Description
0	efuse_block4_rw_ctrl	rw	0x1	control efuse block4 read/write, write once register: 0 = not enable read/write efuse block4 1 = enable read/write efuse block4
31 : 1	reserved_0	ro	0x0	RESERVED

36.33 efuse_block5_rw_ctrl_reg				0x4010C0B0
Bits	Field Name	Acc	Default	Description
0	efuse_block5_rw_ctrl	rw	0x1	control efuse block5 read/write, write once register: 0 = not enable read/write efuse block5 1 = enable read/write efuse block5
31 : 1	reserved_0	ro	0x0	RESERVED

36.34 efuse_block6_rw_ctrl_reg				0x4010C0B4
Bits	Field Name	Acc	Default	Description
0	efuse_block6_rw_ctrl	rw	0x1	control efuse block6 read/write, write once register: 0 = not enable read/write efuse block6 1 = enable read/write efuse block6
31 : 1	reserved_0	ro	0x0	RESERVED

36.35 efuse_block7_rw_ctrl_reg				0x4010C0B8
Bits	Field Name	Acc	Default	Description
0	efuse_block7_rw_ctrl	rw	0x1	control efuse block7 read/write, write once register: 0 = not enable read/write efuse block7 1 = enable read/write efuse block7
31 : 1	reserved_0	ro	0x0	RESERVED

36.36 efuse_block8_rw_ctrl_reg				0x4010C0BC
Bits	Field Name	Acc	Default	Description
0	efuse_block8_rw_ctrl	rw	0x1	control efuse block8 read/write, write once register: 0 = not enable read/write efuse block8 1 = enable read/write efuse block8
31 : 1	reserved_0	ro	0x0	RESERVED

36.37 efuse_block9_rw_ctrl_reg				0x4010C0C0
Bits	Field Name	Acc	Default	Description
0	efuse_block9_rw_ctrl	rw	0x1	control efuse block9 read/write, write once register: 0 = not enable read/write efuse block9 1 = enable read/write efuse block9
31 : 1	reserved_0	ro	0x0	RESERVED

36.38 efuse_block10_rw_ctrl_reg				0x4010C0C4
Bits	Field Name	Acc	Default	Description
0	efuse_block10_rw_ctrl	rw	0x1	control efuse block10 read/write, write once register: 0 = not enable read/write efuse block10 1 = enable read/write efuse block10
31 : 1	reserved_0	ro	0x0	RESERVED

36.39 efuse_block11_rw_ctrl_reg				0x4010C0C8
Bits	Field Name	Acc	Default	Description
0	efuse_block11_rw_ctrl	rw	0x1	control efuse block11 read/write, write once register: 0 = not enable read/write efuse block11 1 = enable read/write efuse block11
31 : 1	reserved_0	ro	0x0	RESERVED

36.40 efuse_block12_rw_ctrl_reg				0x4010C0CC
Bits	Field Name	Acc	Default	Description
0	efuse_block12_rw_ctrl	rw	0x1	control efuse block12 read/write, write once register: 0 = not enable read/write efuse block12 1 = enable read/write efuse block12
31 : 1	reserved_0	ro	0x0	RESERVED

36.41 efuse_block13_rw_ctrl_reg				0x4010C0D0
Bits	Field Name	Acc	Default	Description
0	efuse_block13_rw_ctrl	rw	0x1	control efuse block13 read/write, write once register: 0 = not enable read/write efuse block13 1 = enable read/write efuse block13
31 : 1	reserved_0	ro	0x0	RESERVED

36.42 efuse_block14_rw_ctrl_reg				0x4010C0D4
Bits	Field Name	Acc	Default	Description
0	efuse_block14_rw_ctrl	rw	0x1	control efuse block14 read/write, write once register: 0 = not enable read/write efuse block14 1 = enable read/write efuse block14
31 : 1	reserved_0	ro	0x0	RESERVED

36.43 efuse_block15_rw_ctrl_reg				0x4010C0D8
Bits	Field Name	Acc	Default	Description
0	efuse_block15_rw_ctrl	rw	0x1	control efuse block15 read/write, write once register: 0 = not enable read/write efuse block15 1 = enable read/write efuse block15
31 : 1	reserved_0	ro	0x0	RESERVED

36.44 efuse_block16_rw_ctrl_reg				0x4010C0DC
Bits	Field Name	Acc	Default	Description
0	efuse_block16_rw_ctrl	rw	0x1	control efuse block16 read/write, write once register: 0 = not enable read/write efuse block16 1 = enable read/write efuse block16
31 : 1	reserved_0	ro	0x0	RESERVED

36.45 efuse_block17_rw_ctrl_reg				0x4010C0E0
Bits	Field Name	Acc	Default	Description
0	efuse_block17_rw_ctrl	rw	0x1	control efuse block17 read/write, write once register: 0 = not enable read/write efuse block17 1 = enable read/write efuse block17
31 : 1	reserved_0	ro	0x0	RESERVED

36.46 efuse_block18_rw_ctrl_reg				0x4010C0E4
Bits	Field Name	Acc	Default	Description
0	efuse_block18_rw_ctrl	rw	0x1	control efuse block18 read/write, write once register: 0 = not enable read/write efuse block18 1 = enable read/write efuse block18
31 : 1	reserved_0	ro	0x0	RESERVED

36.47 efuse_block19_rw_ctrl_reg				0x4010C0E8
Bits	Field Name	Acc	Default	Description
0	efuse_block19_rw_ctrl	rw	0x1	control efuse block19 read/write, write once register: 0 = not enable read/write efuse block19 1 = enable read/write efuse block19
31 : 1	reserved_0	ro	0x0	RESERVED

36.48 efuse_block20_rw_ctrl_reg				0x4010C0EC
Bits	Field Name	Acc	Default	Description
0	efuse_block20_rw_ctrl	rw	0x1	control efuse block20 read/write, write once register: 0 = not enable read/write efuse block20 1 = enable read/write efuse block20
31 : 1	reserved_0	ro	0x0	RESERVED

36.49 efuse_block21_rw_ctrl_reg				0x4010C0F0
Bits	Field Name	Acc	Default	Description
0	efuse_block21_rw_ctrl	rw	0x1	control efuse block21 read/write, write once register: 0 = not enable read/write efuse block21 1 = enable read/write efuse block21
31 : 1	reserved_0	ro	0x0	RESERVED

36.50 efuse_block22_rw_ctrl_reg				0x4010C0F4
Bits	Field Name	Acc	Default	Description
0	efuse_block22_rw_ctrl	rw	0x1	control efuse block22 read/write, write once register: 0 = not enable read/write efuse block22 1 = enable read/write efuse block22
31 : 1	reserved_0	ro	0x0	RESERVED

36.51 efuse_block23_rw_ctrl_reg				0x4010C0F8
Bits	Field Name	Acc	Default	Description
0	efuse_block23_rw_ctrl	rw	0x1	control efuse block23 read/write, write once register: 0 = not enable read/write efuse block23 1 = enable read/write efuse block23
31 : 1	reserved_0	ro	0x0	RESERVED

36.52 efuse_block24_rw_ctrl_reg				0x4010C0FC
Bits	Field Name	Acc	Default	Description
0	efuse_block24_rw_ctrl	rw	0x1	control efuse block24 read/write, write once register: 0 = not enable read/write efuse block24 1 = enable read/write efuse block24
31 : 1	reserved_0	ro	0x0	RESERVED

36.53 efuse_block25_rw_ctrl_reg				0x4010C100
Bits	Field Name	Acc	Default	Description
0	efuse_block25_rw_ctrl	rw	0x1	control efuse block25 read/write, write once register: 0 = not enable read/write efuse block25 1 = enable read/write efuse block25
31 : 1	reserved_0	ro	0x0	RESERVED

36.54 efuse_block26_rw_ctrl_reg				0x4010C104
Bits	Field Name	Acc	Default	Description
0	efuse_block26_rw_ctrl	rw	0x1	control efuse block26 read/write, write once register: 0 = not enable read/write efuse block26 1 = enable read/write efuse block26
31 : 1	reserved_0	ro	0x0	RESERVED

36.55 efuse_block27_rw_ctrl_reg				0x4010C108
Bits	Field Name	Acc	Default	Description
0	efuse_block27_rw_ctrl	rw	0x1	control efuse block27 read/write, write once register: 0 = not enable read/write efuse block27 1 = enable read/write efuse block27
31 : 1	reserved_0	ro	0x0	RESERVED

36.56 efuse_block28_rw_ctrl_reg				0x4010C10C
Bits	Field Name	Acc	Default	Description
0	efuse_block28_rw_ctrl	rw	0x1	control efuse block28 read/write, write once register: 0 = not enable read/write efuse block28 1 = enable read/write efuse block28
31 : 1	reserved_0	ro	0x0	RESERVED

36.57 efuse_block29_rw_ctrl_reg				0x4010C110
Bits	Field Name	Acc	Default	Description
0	efuse_block29_rw_ctrl	rw	0x1	control efuse block29 read/write, write once register: 0 = not enable read/write efuse block29 1 = enable read/write efuse block29
31 : 1	reserved_0	ro	0x0	RESERVED

36.58 efuse_block30_rw_ctrl_reg				0x4010C114
Bits	Field Name	Acc	Default	Description
0	efuse_block30_rw_ctrl	rw	0x1	control efuse block30 read/write, write once register: 0 = not enable read/write efuse block30 1 = enable read/write efuse block30
31 : 1	reserved_0	ro	0x0	RESERVED

36.59 efuse_block31_rw_ctrl_reg				0x4010C118
Bits	Field Name	Acc	Default	Description
0	efuse_block31_rw_ctrl	rw	0x1	control efuse block31 read/write, write once register: 0 = not enable read/write efuse block31 1 = enable read/write efuse block31
31 : 1	reserved_0	ro	0x0	RESERVED

36.60 por_read_done_reg				0x4010C128
Bits	Field Name	Acc	Default	Description
0	por_read_done	ro	0x0	read config bits done status from efuse macro after por, then this bit is set to 1.
31 : 1	reserved_0	ro	0x0	RESERVED

36.61 efuse_cfg_reg				0x4010C12C
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_efuse_func_en	ro	0xFFFF	efuse function enable control bit
16	cfg_efuse_bist_en	ro	0x0	efuse bist enable
31 : 17	reserved_0	ro	0x0	RESERVED

36.62 efuse_block_en_reg				0x4010C130
Bits	Field Name	Acc	Default	Description
31 : 0	efuse_block_en	ro	0xFFFFFFFF	every block(31$\tilde{0}$) read/write enable status

36.63 por_read_data0_reg				0x4010C134
Bits	Field Name	Acc	Default	Description
31 : 0	por_read_data0	ro	0x0	read block1 config bit

36.64 por_read_data1_reg				0x4010C138
Bits	Field Name	Acc	Default	Description
31 : 0	por_read_data1	ro	0x0	read block2 config bit

36.65 por_read_data2_reg				0x4010C13C
Bits	Field Name	Acc	Default	Description
31 : 0	por_read_data2	ro	0x0	read block3 config bit

36.66 por_read_data3_reg				0x4010C140
Bits	Field Name	Acc	Default	Description
31 : 0	por_read_data3	ro	0x0	read block4 config bit

36.67 EFUSE_MEM				0x4010C7F8
Bits	Field Name	Acc	Default	Description
31 : 0	EFUSE_DATA	rw	0x0	the registers are the mapping address to efuse macro. Write the 12'hxxx address means burn the data into block (12'hxxx¡¡2) of efuse. Read the 12'hxxx address will get the block (12'hxxx¡¡2) data of efuse.

37 msadc

37.1 cfg_msadc_mode				0x4010D000
Bits	Field Name	Acc	Default	Description
0	cfg_msadc_mode	rw	0x0	1'b1: hardware mode auto test; 1'b0: software mode;
1	cfg_msadc_hw_test_channel	rw	0x0	1'b1: 2 channels; 1'b0: 1 channel

37.2 cfg_msadc_sw_ctrl0				0x4010D004
Bits	Field Name	Acc	Default	Description
0	cfg_msadc_sw_start_pulse	rw	0x0	Start pulse, write 1'b1 to generate one cycle pulse

1	cfg_msadc_sw_stop_pulse	rw	0x0	Stop pulse, write 1'b1 to generate one cycle pulse
2	cfg_msadc_sw_clear_pulse	rw	0x0	Clear pulse, write 1'b1 to generate one cycle pulse

37.3 cfg_msadc_sw_ctrl1				0x4010D008
Bits	Field Name	Acc	Default	Description
3 : 0	cfg_msadc_sw_mux_bits	rw	0x0	msadc meter mux bits when software mode
7 : 4	cfg_msadc_test_0_mux_bits	rw	0x0	msadc meter mux bits when power off
11 : 8	cfg_msadc_test_1_mux_bits	rw	0x0	msadc meter mux bits when power off
15 : 12	cfg_msadc_wait_cnt	rw	0x3	msadc meter wait counter
27 : 16	cfg_msadc_window	rw	0x200	msadc meter window
28	cfg_msadc_sw_diff_mode	rw	0x0	msadc diff mode

37.4 cfg_msadc_ana_ctrl0				0x4010D00C
Bits	Field Name	Acc	Default	Description
0	cfg_ana_msadc_chnp_sel	rw	0x0	
1	cfg_ana_msadc_cmp_bit	rw	0x0	
9 : 2	cfg_ana_msadc_vbe_cal_bit	rw	0x80	
10	cfg_ana_msadc_sdm_mode	rw	0x1	
11	cfg_ana_msadc_test_mode	rw	0x0	
14 : 12	cfg_ana_msadc_ibias_bit	rw	0x1	
15	cfg_ana_msadc_chop_en	rw	0x1	
16	cfg_ana_msadc_sdm_gain_bit	rw	0x0	
18 : 17	cfg_ana_msadc_dem_en	rw	0x3	
19	cfg_ana_msadc_adc_ff_en	rw	0x1	
20	cfg_ana_msadc_ts_mode	rw	0x0	
24 : 21	cfg_ana_msadc_rsvd_bit	rw	0x0	
26 : 25	cfg_ana_msadc_dither_mode	rw	0x0	
28 : 27	cfg_ana_msadc_vcom_bit	rw	0x1	

37.5 cfg_msadc_ro_acc				0x4010D010
Bits	Field Name	Acc	Default	Description
21 : 0	ro_msadc_dat_acc	ro	0x0	read only, msadc acc vaule when software

37.6 cfg_msadc_ro_test_acc_0				0x4010D014
Bits	Field Name	Acc	Default	Description
21 : 0	ro_msadc_test_acc_0	ro	0x0	read only, msadc acc vaule when power off

37.7 cfg_msadc_ro_test_acc_1				0x4010D018
Bits	Field Name	Acc	Default	Description
21 : 0	ro_msadc_test_acc_1	ro	0x0	read only, msadc acc vaule when power off

37.8 cfg_msadc_int_raw				0x4010D01C
Bits	Field Name	Acc	Default	Description
0	masdc_int_raw	rw	0x0	masdc interrupt raw status, write 1'b1 to clear

37.9 cfg_msadc_int_status				0x4010D020
Bits	Field Name	Acc	Default	Description
0	msadc_int_status	rw	0x0	masdc interrupt status, write 1'b1 to clear

37.10 cfg_msadc_int_mask	0x4010D024

Bits	Field Name	Acc	Default	Description
0	cfg_msadc_int_mask	rw	0x0	masdc interrupt mask

38 usbc

38.1 GOTGCTL				0x40200000
Bits	Field Name	Acc	Default	Description
0	SesReqScs	ro	0x0	
1	SesReq	rw	0x0	
2	VbvalidOvEn	rw	0x0	
3	VbvalidOvVal	rw	0x0	
4	AvalidOvEn	rw	0x0	
5	AvalidOvVal	rw	0x0	
6	BvalidOvEn	rw	0x0	
7	BvalidOvVal	rw	0x0	
8	HstNegScs	ro	0x0	
9	HNPReq	rw	0x0	
10	HstSetHNPEn	rw	0x0	
11	DevHNPEn	rw	0x0	
12	EHEn	rw	0x0	
14 : 13	GOTGCTL_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	DbnceFltrBypass	rw	0x0	
16	ConIDSts	ro	0x1	
17	DbncTime	ro	0x0	
18	ASesVld	rw	0x0	bit type is changed from ru to rw.
19	BSesVld	ro	0x0	
20	OTGVer	rw	0x0	
21	CurMod	ro	0x0	
31 : 22	GOTGCTL_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.2 GOTGINT				0x40200004
Bits	Field Name	Acc	Default	Description
1 : 0	GOTGINT_reserved_0	rc	0x0	bit type is changed from dc to rc.
2	SesEndDet	rc	0x0	bit type is changed from w1c to rc.
7 : 3	GOTGINT_reserved_1	rc	0x0	bit type is changed from dc to rc.
8	SesReqSucStsChng	rc	0x0	bit type is changed from w1c to rc.
9	HstNegSucStsChng	rc	0x0	bit type is changed from w1c to rc.
16 : 10	GOTGINT_reserved_2	rc	0x0	bit type is changed from dc to rc.
17	HstNegDet	rc	0x0	bit type is changed from w1c to rc.
18	ADevTOUTChg	rc	0x0	bit type is changed from w1c to rc.
19	DbnceDone	rc	0x0	bit type is changed from w1c to rc.
31 : 20	GOTGINT_reserved_3	rc	0x0	bit type is changed from dc to rc.

38.3 GAHBCFG				0x40200008
Bits	Field Name	Acc	Default	Description
0	GlblIntrMsk	rw	0x0	
4 : 1	HBstLen	rw	0x0	
5	DMAEn	rw	0x0	
6	GAHBCFG_reserved_0	rc	0x0	bit type is changed from dc to rc.
7	NPTxFEmpLvl	rw	0x0	
8	PTxFEmpLvl	rw	0x0	
20 : 9	GAHBCFG_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	RemMemSupp	rw	0x0	
22	NotiAllDmaWrit	rw	0x0	

23	AHBSingle	rw	0x0	
24	InvDescEndianess	rw	0x0	
31 : 25	GAHBCFG_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.4 GUSBCFG				0x4020000C
Bits	Field Name	Acc	Default	Description
2 : 0	TOutCal	rw	0x0	
3	PHYIf	ro	0x0	
4	ULPI_UTMI_Sel	rw	0x0	bit type is changed from ru to rw.
5	FSIntf	rw	0x0	bit type is changed from othr to rw.
6	PHYSel	rw	0x0	
7	GUSBCFG_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	SRPCap	rw	0x0	
9	HNPCap	rw	0x0	
13 : 10	USBTrdTim	rw	0x5	
14	GUSBCFG_reserved_1	rc	0x0	bit type is changed from dc to rc.
15	PhyLPwrClkSel	rw	0x0	
21 : 16	GUSBCFG_reserved_2	rc	0x0	bit type is changed from dc to rc.
22	TermSelDLPulse	rw	0x0	
25 : 23	GUSBCFG_reserved_3	rc	0x0	bit type is changed from dc to rc.
26	IC_USBCap	ro	0x0	
27	GUSBCFG_reserved_4	rc	0x0	bit type is changed from dc to rc.
28	TxEndDelay	rw	0x0	
29	ForceHstMode	rw	0x0	
30	ForceDevMode	rw	0x0	
31	CorruptTxPkt	rw	0x0	bit type is changed from w1 to rw.

38.5 GRSTCTL				0x40200010
Bits	Field Name	Acc	Default	Description
0	CSftRst	rw	0x0	bit type is changed from othr to rw.
1	PIUFSSftRst	rw	0x0	bit type is changed from othr to rw.
2	FrmCntrRst	rw	0x0	bit type is changed from othr to rw.
3	GRSTCTL_reserved_0	rc	0x0	bit type is changed from dc to rc.
4	RxFFlsh	rw	0x0	bit type is changed from othr to rw.
5	TxFFlsh	rw	0x0	bit type is changed from othr to rw.
10 : 6	TxFNum	rw	0x0	
11	GRSTCTL_reserved_1	rc	0x0	bit type is changed from dc to rc.
15 : 12	StreamSwRstChannel	rw	0x0	
16	StreamSwRstReq	rw	0x0	
17	StreamStsFifoSwRst	rw	0x0	
29 : 18	GRSTCTL_reserved_2	rc	0x0	bit type is changed from dc to rc.
30	DMAReq	ro	0x0	
31	AHBIdle	ro	0x1	

38.6 GINTSTS				0x40200014
Bits	Field Name	Acc	Default	Description
0	CurMod	ro	0x0	
1	ModeMis	rc	0x0	bit type is changed from w1c to rc.
2	OTGInt	rw	0x0	bit type is changed from ru to rw.
3	Sof	rw	0x0	bit type is changed from othr to rw.
4	RxFLvl	ro	0x0	
5	NPTxFEmp	ro	0x1	
6	GINNakEff	ro	0x0	
7	GOUTNakEff	ro	0x0	
8	StreamStsFifoNotEmpt	ro	0x0	

9	StreamStsFifoOvf	ro	0x0	
10	ErlySusp	rc	0x0	bit type is changed from w1c to rc.
11	USBSusp	rc	0x0	bit type is changed from w1c to rc.
12	USBRst	rc	0x0	bit type is changed from w1c to rc.
13	EnumDone	rc	0x0	bit type is changed from w1c to rc.
14	ISOOutDrop	rc	0x0	bit type is changed from w1c to rc.
15	EOPF	rc	0x0	bit type is changed from w1c to rc.
16	GINTSTS_reserved_1	rc	0x0	bit type is changed from dc to rc.
17	EPMis	rc	0x0	bit type is changed from w1c to rc.
18	IEPInt	ro	0x0	
19	OEPInt	ro	0x0	
20	incompISOIN	rc	0x0	bit type is changed from w1c to rc.
21	incomplP	rc	0x0	bit type is changed from w1c to rc.
22	FetSusp	rc	0x0	bit type is changed from w1c to rc.
23	ResetDet	rc	0x0	bit type is changed from w1c to rc.
24	PrtInt	ro	0x0	
25	HChInt	ro	0x0	
26	PTxFEmp	rw	0x1	bit type is changed from ru to rw.
27	GINTSTS_reserved_2	rc	0x0	bit type is changed from dc to rc.
28	ConIDStsChng	rw	0x0	bit type is changed from othr to rw.
29	DisconnInt	rc	0x0	bit type is changed from w1c to rc.
30	SessReqInt	rc	0x0	bit type is changed from w1c to rc.
31	WkUpInt	rc	0x0	bit type is changed from w1c to rc.

38.7 GINTMSK				0x40200018
Bits	Field Name	Acc	Default	Description
0	GINTMSK_reserved_0	rc	0x0	bit type is changed from dc to rc.
1	ModeMisMsk	rw	0x0	
2	OTGIntMsk	rw	0x0	
3	SofMsk	rw	0x0	
4	RxFLvlMsk	rw	0x0	
5	NPTxFEmpMsk	rw	0x0	
6	GINNakEffMsk	rw	0x0	
7	GOUTNakEffMsk	rw	0x0	
8	StreamStsFifoNotEmptMsk	ro	0x0	
9	StreamStsFifoOvfMsk	ro	0x0	
10	ErlySuspMsk	rw	0x0	
11	USBSuspMsk	rw	0x0	
12	USBRstMsk	rw	0x0	
13	EnumDoneMsk	rw	0x0	
14	ISOOutDropMsk	rw	0x0	
15	EOPFMsk	rw	0x0	
16	GINTMSK_reserved_2	rc	0x0	bit type is changed from dc to rc.
17	EPMisMsk	rw	0x0	
18	IEPIntMsk	rw	0x0	
19	OEPIntMsk	rw	0x0	
20	GINTMSK_reserved_3	rc	0x0	bit type is changed from dc to rc.
21	incomplPMsK	rw	0x0	
22	FetSuspMsk	rw	0x0	
23	ResetDetMsk	rw	0x0	
24	PrtIntMsk	rw	0x0	
25	HChIntMsk	rw	0x0	
26	PTxFEmpMsk	rw	0x0	
27	GINTMSK_reserved_4	rc	0x0	bit type is changed from dc to rc.
28	ConIDStsChngMsk	rw	0x0	
29	DisconnIntMsk	rw	0x0	
30	SessReqIntMsk	rw	0x0	

31	WkUpIntMsk	rw	0x0	

38.8 GRXSTSR				0x4020001C
Bits	Field Name	Acc	Default	Description
3 : 0	ChNum	rw	0x0	bit type is changed from ru to rw.
14 : 4	BCnt	ro	0x0	
16 : 15	DPID	ro	0x0	
20 : 17	PktSts	rw	0x0	bit type is changed from ru to rw.
24 : 21	FN	ro	0x0	
31 : 25	GRXSTSR_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.9 GRXSTSP				0x40200020
Bits	Field Name	Acc	Default	Description
3 : 0	ChNum	rw	0x0	bit type is changed from ru to rw.
14 : 4	BCnt	ro	0x0	
16 : 15	DPID	ro	0x0	
20 : 17	PktSts	rw	0x0	bit type is changed from ru to rw.
24 : 21	FN	ro	0x0	
31 : 25	GRXSTSP_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.10 GRXFSIZ				0x40200024
Bits	Field Name	Acc	Default	Description
11 : 0	RxFDep	rw	0xEAF	
31 : 12	GRXFSIZ_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.11 GNPTXFSIZ				0x40200028
Bits	Field Name	Acc	Default	Description
11 : 0	NPTXFStAddr	rw	0xEAF	
15 : 12	GNPTXFSIZ_reserved_0	rc	0x0	bit type is changed from dc to rc.
27 : 16	NPTXFDep	rw	0xEAF	
31 : 28	GNPTXFSIZ_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.12 GNPTXSTS				0x4020002C
Bits	Field Name	Acc	Default	Description
15 : 0	NPTxFSpcAvail	ro	0xEAF	
23 : 16	NPTxQSpcAvail	ro	0x8	
30 : 24	NPTxQTop	ro	0x0	
31	GNPTXSTS_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.13 GPVNDCTL				0x40200034
Bits	Field Name	Acc	Default	Description
7 : 0	RegData	rw	0x0	Register Data (RegData) Contains the write data for register write. Read data for register read, valid when VStatus Done is set.
15 : 8	VCtrl	rw	0x0	UTMI+ Vendor Control Register Address (VCtrl) The 4-bit register address a vendor defined 4-bit parallel output bus. Bits 11:8 of this field are placed on utmi_vcontrol[3:0]. ULPI Extended Register Address (ExtRegAddr) The 6-bit PHY extended register address.

21 : 16	RegAddr	rw	0x0	Register Address (RegAddr) The 6-bit PHY register address for immediate PHY Register set access. Set to 6'h2F for Extended PHY Register set access.
22	RegWr	rw	0x0	Register Write (RegWr) Set this bit for register writes, and clear it for register reads.
25	NewRegReq	rw	0x0	New Register Request (NewRegReq) The application sets this bit for a new vendor control access. Values: 0x0 (INACTIVE): New Register Request not active 0x1 (ACTIVE): New Register Request active
26	VStsBsy	ro	0x0	VStatus Busy (VStsBsy) The core sets this bit when the vendor control access is in progress and clears this bit when done.
27	VStsDone	rw	0x0	VStatus Done (VStsDone) The core sets this bit when the vendor control access is done. This bit is cleared by the core when the application sets the New Register Request bit (bit 25). Values: 0x0 (INACTIVE): VStatus Done inactive 0x1 (ACTIVE): VStatus Done active

38.14 GGPIO				0x40200038
Bits	Field Name	Acc	Default	Description
15 : 0	GPI	ro	0x0	
31 : 16	GPO	rw	0x0	

38.15 GUID				0x4020003C
Bits	Field Name	Acc	Default	Description
31 : 0	GUID	rw	0x88000000	

38.16 GSNPSID				0x40200040
Bits	Field Name	Acc	Default	Description
31 : 0	SynopsysID	ro	0x4F54400A	

38.17 GHWCFG1				0x40200044
Bits	Field Name	Acc	Default	Description
31 : 0	EpDir	ro	0x0	

38.18 GHWCFG2				0x40200048
Bits	Field Name	Acc	Default	Description
2 : 0	OtgMode	ro	0x0	
4 : 3	OtgArch	ro	0x2	
5	SingPnt	ro	0x0	
7 : 6	HSPhyType	ro	0x1	
9 : 8	FSPhyType	ro	0x1	
13 : 10	NumDevEps	ro	0xC	
17 : 14	NumHstChnl	ro	0xF	
18	PerioSupport	ro	0x1	
19	DynFifoSizing	ro	0x1	
20	MultiProcIntrpt	ro	0x0	
21	GHWCFG2_reserved_0	rc	0x0	bit type is changed from dc to rc.

23 : 22	NPTxQDepth	ro	0x2	
25 : 24	PTxQDepth	ro	0x2	
30 : 26	TknQDepth	ro	0x8	
31	GHWCFG2_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.19 GHWCFG3				0x4020004C
Bits	Field Name	Acc	Default	Description
3 : 0	XferSizeWidth	ro	0x8	
6 : 4	PktSizeWidth	ro	0x6	
7	OtgEn	ro	0x1	
8	I2CIntSel	ro	0x0	
9	VndctlSupt	ro	0x0	
10	OptFeature	ro	0x0	
11	RstType	ro	0x0	
12	ADPSupport	ro	0x1	
13	HSICMode	ro	0x0	
14	BCSupport	ro	0x0	
15	LPMMode	ro	0x0	
31 : 16	DfifoDepth	ro	0xE47	

38.20 GHWCFG4				0x40200050
Bits	Field Name	Acc	Default	Description
3 : 0	NumDevPerioEps	ro	0x0	
4	PartialPwrDn	ro	0x0	
5	AhbFreq	ro	0x1	
6	Hibernation	ro	0x0	
7	ExtendedHibernation	ro	0x0	
11 : 8	GHWCFG4_reserved_0	rc	0x0	bit type is changed from dc to rc.
12	ACGSupt	ro	0x0	
13	EnhancedLPMSupt	ro	0x1	
15 : 14	PhyDataWidth	ro	0x0	
19 : 16	NumCtlEps	ro	0x0	
20	IddgFltr	ro	0x1	
21	VBusValidFltr	ro	0x1	
22	AValidFltr	ro	0x1	
23	BValidFltr	ro	0x1	
24	SessEndFltr	ro	0x1	
25	DedFifoMode	ro	0x1	
29 : 26	INEps	ro	0x8	
30	DescDMAEnabled	ro	0x1	
31	DescDMA	ro	0x1	

38.21 GPWRDN				0x40200058
Bits	Field Name	Acc	Default	Description
0	PMUIntSel	rw	0x0	
1	PMUActv	rw	0x0	
2	GPWRDN_reserved_0	rc	0x0	bit type is changed from dc to rc.
3	PwrDnClmp	rw	0x0	
4	PwrDnRst_n	rw	0x1	
5	PwrDnSwtch	rw	0x0	
6	DisableVBUS	rw	0x0	
14 : 7	GPWRDN_reserved_1	rc	0x0	bit type is changed from dc to rc.
15	SRPDetect	rc	0x0	bit type is changed from w1c to rc.
16	SRPDetectMsk	rw	0x0	
17	StsChngInt	rc	0x0	bit type is changed from w1c to rc.

18	StsChngIntMsk	rw	0x0	
20 : 19	LineState	ro	0x0	
21	IDDIG	ro	0x0	
22	BSessVld	ro	0x0	
23	ADPInt	rc	0x0	bit type is changed from w1c to rc.
31 : 24	GPWRDN_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.22 GDFIFOCFG				0x4020005C
Bits	Field Name	Acc	Default	Description
15 : 0	GDFIFOCfg	rw	0xEAF	
31 : 16	EPInfoBaseAddr	rw	0xE47	

38.23 GADPCTL				0x40200060
Bits	Field Name	Acc	Default	Description
1 : 0	PrbDschg	rw	0x0	
3 : 2	PrbDelta	rw	0x0	
5 : 4	PrbPer	rw	0x0	
16 : 6	RTIM	ro	0x0	
17	EnaPrb	rw	0x0	
18	EnaSns	rw	0x0	
19	ADPRes	rw	0x0	bit type is changed from othr to rw.
20	ADPEn	rw	0x0	
21	AdpPrbInt	rc	0x0	bit type is changed from w1c to rc.
22	AdpSnsInt	rc	0x0	bit type is changed from w1c to rc.
23	AdpToutInt	rc	0x0	bit type is changed from w1c to rc.
24	AdpPrbIntMsk	rw	0x0	
25	AdpSnsIntMsk	rw	0x0	
26	AdpToutMsk	rw	0x0	
28 : 27	AR	rw	0x0	
31 : 29	GADPCTL_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.24 STREAMSTSFIFO				0x40200080
Bits	Field Name	Acc	Default	Description
0	StreamValid	ro	0x0	
1	StreamSwRsted	ro	0x0	
3 : 2	STREAMSTSFIFO_-reserved_0	rc	0x0	
7 : 4	StreamEpNum	ro	0x0	
15 : 8	StreamFileNum	ro	0x0	
31 : 16	STREAMSTSFIFO_-reserved_1	rc	0x0	

38.25 STREAMFIRSTPTRFIFO				0x40200084
Bits	Field Name	Acc	Default	Description
31 : 0	StreamFirstPtr	ro	0x0	

38.26 STREAMLASTPTRFIFO				0x40200088
Bits	Field Name	Acc	Default	Description
31 : 0	StreamLastPtr	ro	0x0	

38.27 HPTXFSIZ				0x40200100
Bits	Field Name	Acc	Default	Description

12 : 0	PTxFStAddr	rw	0x1D5E	
15 : 13	HPTXFSIZ_reserved_0	rc	0x0	bit type is changed from dc to rc.
27 : 16	PTxFSize	rw	0xEAF	
31 : 28	HPTXFSIZ_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.28 DIEPTXF1				0x40200104
Bits	Field Name	Acc	Default	Description
11 : 0	INEPnTxFStAddr	rw	0xECF	
15 : 12	DIEPTXF1_reserved_0	rc	0x0	bit type is changed from dc to rc.
25 : 16	INEPnTxFDep	rw	0x300	
31 : 26	DIEPTXF1_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.29 DIEPTXF2				0x40200108
Bits	Field Name	Acc	Default	Description
12 : 0	INEPnTxFStAddr	rw	0x11CF	
15 : 13	DIEPTXF2_reserved_0	rc	0x0	bit type is changed from dc to rc.
25 : 16	INEPnTxFDep	rw	0x300	
31 : 26	DIEPTXF2_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.30 DIEPTXF3				0x4020010C
Bits	Field Name	Acc	Default	Description
12 : 0	INEPnTxFStAddr	rw	0x14CF	
15 : 13	DIEPTXF3_reserved_0	rc	0x0	bit type is changed from dc to rc.
24 : 16	INEPnTxFDep	rw	0x100	
31 : 25	DIEPTXF3_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.31 DIEPTXF4				0x40200110
Bits	Field Name	Acc	Default	Description
12 : 0	INEPnTxFStAddr	rw	0x15CF	
15 : 13	DIEPTXF4_reserved_0	rc	0x0	bit type is changed from dc to rc.
24 : 16	INEPnTxFDep	rw	0x100	
31 : 25	DIEPTXF4_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.32 DIEPTXF5				0x40200114
Bits	Field Name	Acc	Default	Description
12 : 0	INEPnTxFStAddr	rw	0x16CF	
15 : 13	DIEPTXF5_reserved_0	rc	0x0	bit type is changed from dc to rc.
24 : 16	INEPnTxFDep	rw	0x100	
31 : 25	DIEPTXF5_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.33 DIEPTXF6				0x40200118
Bits	Field Name	Acc	Default	Description
12 : 0	INEPnTxFStAddr	rw	0x17CF	
15 : 13	DIEPTXF6_reserved_0	rc	0x0	bit type is changed from dc to rc.
24 : 16	INEPnTxFDep	rw	0x100	
31 : 25	DIEPTXF6_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.34 DIEPTXF7				0x4020011C
Bits	Field Name	Acc	Default	Description
12 : 0	INEPnTxFStAddr	rw	0x18CF	
15 : 13	DIEPTXF7_reserved_0	rc	0x0	bit type is changed from dc to rc.

24 : 16	INEPnTxFDep	rw	0x100	
31 : 25	DIEPTXF7_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.35 DIEPTXF8				0x40200120
Bits	Field Name	Acc	Default	Description
12 : 0	INEPnTxFStAddr	rw	0x19CF	
15 : 13	DIEPTXF8_reserved_0	rc	0x0	bit type is changed from dc to rc.
24 : 16	INEPnTxFDep	rw	0x100	
31 : 25	DIEPTXF8_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.36 HCFG				0x40200400
Bits	Field Name	Acc	Default	Description
1 : 0	FSLSPclkSel	rw	0x0	
2	FSLSSupp	rw	0x0	
6 : 3	HCFG_reserved_0	rc	0x0	bit type is changed from dc to rc.
7	Ena32KHzS	rw	0x0	
15 : 8	ResValid	rw	0x2	
22 : 16	HCFG_reserved_1	rc	0x0	bit type is changed from dc to rc.
23	DescDMA	rw	0x0	
25 : 24	FrListEn	rw	0x0	
26	PerSchedEna	rw	0x0	
30 : 27	HCFG_reserved_2	rc	0x0	bit type is changed from dc to rc.
31	ModeChTimEn	rw	0x0	

38.37 HFIR				0x40200404
Bits	Field Name	Acc	Default	Description
15 : 0	FrInt	rw	0xEA60	
16	HFIRRldCtrl	rw	0x0	
31 : 17	HFIR_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.38 HFNUM				0x40200408
Bits	Field Name	Acc	Default	Description
15 : 0	FrNum	ro	0x3FFF	
31 : 16	FrRem	ro	0x0	

38.39 HPTXSTS				0x40200410
Bits	Field Name	Acc	Default	Description
15 : 0	PTxFSpcAvail	ro	0xEAF	
23 : 16	PTxQSpcAvail	ro	0x8	
31 : 24	PTxQTop	ro	0x0	

38.40 HAINT				0x40200414
Bits	Field Name	Acc	Default	Description
15 : 0	HAINT	ro	0x0	
31 : 16	HAINT_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.41 HAINTMSK				0x40200418
Bits	Field Name	Acc	Default	Description
15 : 0	HAINTMsk	rw	0x0	
31 : 16	HAINTMSK_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.42 HFLBAddr				0x4020041C
Bits	Field Name	Acc	Default	Description
31 : 0	HFLBAddr	rw	0x0	

38.43 HPRT				0x40200440
Bits	Field Name	Acc	Default	Description
0	PrtConnSts	ro	0x0	
1	PrtConnDet	rc	0x0	bit type is changed from w1c to rc.
2	PrtEna	rc	0x0	bit type is changed from w1c to rc.
3	PrtEnChng	rc	0x0	bit type is changed from w1c to rc.
4	PrtOvrCurrAct	ro	0x0	
5	PrtOvrCurrChng	rc	0x0	bit type is changed from w1c to rc.
6	PrtRes	rw	0x0	
7	PrtSusp	rw	0x0	bit type is changed from othr to rw.
8	PrtRst	rw	0x0	
9	HPRT_reserved_0	rc	0x0	bit type is changed from dc to rc.
11 : 10	PrtLnSts	ro	0x0	
12	PrtPwr	rw	0x0	
16 : 13	PrtTstCtl	rw	0x0	
18 : 17	PrtSpd	ro	0x0	
31 : 19	HPRT_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.44 HCCHAR0				0x40200500
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR0_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.45 HCSPLT0				0x40200504
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT0_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.46 HCINT0				0x40200508
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.

7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT0_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.47 HCINTMSK0				0x4020050C
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK0_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK0_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK0_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.48 HCTSIZ0				0x40200510
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.49 HCDMA0				0x40200514
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.50 HCDMAB0				0x4020051C
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.51 HCCHAR1				0x40200520
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR1_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.52 HCSPLT1				0x40200524
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	

13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT1_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.53 HCINT1				0x40200528
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.54 HCINTMSK1				0x4020052C
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK1_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK1_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK1_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.55 HCTSIZ1				0x40200530
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.56 HCDMA1				0x40200534
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.57 HCDMAB1				0x4020053C
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.58 HCCHAR2				0x40200540
Bits	Field Name	Acc	Default	Description

10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR2_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.59 HCSPLT2				0x40200544
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT2_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.60 HCINT2				0x40200548
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT2_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.61 HCINTMSK2				0x4020054C
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK2_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK2_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK2_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.62 HCTSIZ2				0x40200550
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	

30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.63 HCDMA2				0x40200554
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.64 HCDMAB2				0x4020055C
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.65 HCCHAR3				0x40200560
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR3_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.66 HCSPLT3				0x40200564
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT3_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.67 HCINT3				0x40200568
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT3_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.68 HCINTMSK3				0x4020056C
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK3_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK3_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK3_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.69 HCTSIZ3				0x40200570
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.70 HCDMA3				0x40200574
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.71 HCDMAB3				0x4020057C
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.72 HCCHAR4				0x40200580
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR4_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.73 HCSPLT4				0x40200584
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT4_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.74 HCINT4				0x40200588
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.

1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT4_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.75 HCINTMSK4				0x4020058C
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK4_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK4_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK4_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.76 HCTSIZ4				0x40200590
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.77 HCDMA4				0x40200594
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.78 HCDMAB4				0x4020059C
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.79 HCCHAR5				0x402005A0
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR5_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.

31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.80 HCSPLT5				0x402005A4
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT5_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.81 HCINT5				0x402005A8
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT5_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.82 HCINTMSK5				0x402005AC
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK5_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK5_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK5_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.83 HCTSIZ5				0x402005B0
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.84 HCDMA5				0x402005B4
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.85 HCDMAB5	0x402005BC

Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.86 HCCHAR6				0x402005C0
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR6_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.87 HCSPLT6				0x402005C4
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT6_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.88 HCINT6				0x402005C8
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT6_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.89 HCINTMSK6				0x402005CC
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK6_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK6_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK6_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.90 HCTSIZ6				0x402005D0
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.91 HCDMA6				0x402005D4
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.92 HCDMAB6				0x402005DC
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.93 HCCHAR7				0x402005E0
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR7_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.94 HCSPLT7				0x402005E4
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT7_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.95 HCINT7				0x402005E8
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.

13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT7_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.96 HCINTMSK7				0x402005EC
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK7_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK7_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK7_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.97 HCTSIZ7				0x402005F0
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.98 HCDMA7				0x402005F4
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.99 HCDMAB7				0x402005FC
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.100 HCCHAR8				0x40200600
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR8_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.101 HCSPLT8				0x40200604
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT8_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.102 HCINT8				0x40200608
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT8_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.103 HCINTMSK8				0x4020060C
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK8_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK8_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK8_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.104 HCTSIZ8				0x40200610
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.105 HCDMA8				0x40200614
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.106 HCDMAB8				0x4020061C
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.107 HCCHAR9				0x40200620
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR9_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	

28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.108 HCSPLT9				0x40200624
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT9_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.109 HCINT9				0x40200628
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT9_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.110 HCINTMSK9				0x4020062C
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK9_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK9_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK9_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.111 HCTSIZ9				0x40200630
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.112 HCDMA9				0x40200634
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.113 HCDMAB9				0x4020063C
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.114 HCCHAR10				0x40200640
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR10_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.115 HCSPLT10				0x40200644
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT10_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.116 HCINT10				0x40200648
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT10_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.117 HCINTMSK10				0x4020064C
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK10_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK10_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	

31 : 14	HCINTMSK10_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.118 HCTSIZ10				0x40200650
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.119 HCDMA10				0x40200654
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.120 HCDMAB10				0x4020065C
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.121 HCCHAR11				0x40200660
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR11_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.122 HCSPLT11				0x40200664
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT11_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.123 HCINT11				0x40200668
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.

10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT11_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.124 HCINTMSK11				0x4020066C
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK11_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK11_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK11_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.125 HCTSIZ11				0x40200670
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.126 HCDMA11				0x40200674
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.127 HCDMAB11				0x4020067C
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.128 HCCHAR12				0x40200680
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR12_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.129 HCSPLT12				0x40200684
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	

30 : 17	HCSPLT12_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.130 HCINT12				0x40200688
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT12_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.131 HCINTMSK12				0x4020068C
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK12_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK12_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK12_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.132 HCTSIZ12				0x40200690
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.133 HCDMA12				0x40200694
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.134 HCDMAB12				0x4020069C
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.135 HCCHAR13				0x402006A0
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	

16	HCCHAR13_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.136 HCSPLT13				0x402006A4
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT13_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.137 HCINT13				0x402006A8
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT13_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.138 HCINTMSK13				0x402006AC
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK13_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK13_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK13_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.139 HCTSIZ13				0x402006B0
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.140 HCDMA13				0x402006B4
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.141 HCDMAB13				0x402006BC
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.142 HCCHAR14				0x402006C0
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR14_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.143 HCSPLT14				0x402006C4
Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT14_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.144 HCINT14				0x402006C8
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.
5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT14_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.145 HCINTMSK14				0x402006CC
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	

2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK14_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK14_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK14_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.146 HCTSIZ14 0x402006D0

Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.147 HCDMA14 0x402006D4

Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.148 HCDMAB14 0x402006DC

Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.149 HCCHAR15 0x402006E0

Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	EPNum	rw	0x0	
15	EPDir	rw	0x0	
16	HCCHAR15_reserved_0	rc	0x0	bit type is changed from dc to rc.
17	LSpdDev	rw	0x0	
19 : 18	EPType	rw	0x0	
21 : 20	EC	rw	0x0	
28 : 22	DevAddr	rw	0x0	
29	OddFrm	rw	0x0	
30	ChDis	rw	0x0	bit type is changed from othr to rw.
31	ChEna	rw	0x0	bit type is changed from othr to rw.

38.150 HCSPLT15 0x402006E4

Bits	Field Name	Acc	Default	Description
6 : 0	PrtAddr	rw	0x0	
13 : 7	HubAddr	rw	0x0	
15 : 14	XactPos	rw	0x0	
16	CompSplt	rw	0x0	
30 : 17	HCSPLT15_reserved_0	rc	0x0	bit type is changed from dc to rc.
31	SpltEna	rw	0x0	

38.151 HCINT15 0x402006E8

Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	ChHltd	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	STALL	rc	0x0	bit type is changed from w1c to rc.
4	NAK	rc	0x0	bit type is changed from w1c to rc.

5	ACK	rc	0x0	bit type is changed from w1c to rc.
6	NYET	rc	0x0	bit type is changed from w1c to rc.
7	XactErr	rc	0x0	bit type is changed from w1c to rc.
8	BblErr	rc	0x0	bit type is changed from w1c to rc.
9	FrmOvrun	rc	0x0	bit type is changed from w1c to rc.
10	DataTglErr	rc	0x0	bit type is changed from w1c to rc.
11	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
12	XCS_XACT_ERR	rc	0x0	bit type is changed from w1c to rc.
13	DESC_LST_ROLLIntr	rc	0x0	bit type is changed from w1c to rc.
31 : 14	HCINT15_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.152 HCINTMSK15				0x402006EC
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	ChHltdMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
10 : 3	HCINTMSK15_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	BNAIntrMsk	rw	0x0	
12	HCINTMSK15_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	DESC_LST_ROLLIntrMsk	rw	0x0	
31 : 14	HCINTMSK15_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.153 HCTSIZ15				0x402006F0
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	Pid	rw	0x0	
31	DoPng	rw	0x0	

38.154 HCDMA15				0x402006F4
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.155 HCDMAB15				0x402006FC
Bits	Field Name	Acc	Default	Description
31 : 0	HCDMAB	ro	0x0	

38.156 DCFG				0x40200800
Bits	Field Name	Acc	Default	Description
1 : 0	DevSpd	rw	0x0	
2	NZStsOUTHShk	rw	0x0	
3	Ena32KHzSusp	rw	0x0	
10 : 4	DevAddr	rw	0x0	
12 : 11	PerFrInt	rw	0x0	
13	EnDevOutNak	rw	0x0	
14	XCVRDLY	rw	0x0	
15	ErraticIntMsk	rw	0x0	
22 : 16	DCFG_reserved_0	rc	0x0	bit type is changed from dc to rc.
23	DescDMA	rw	0x0	
25 : 24	PerSchIntvl	rw	0x0	
31 : 26	ResValid	rw	0x2	

38.157 DCTL				0x40200804
Bits	Field Name	Acc	Default	Description
0	RmtWkUpSig	rw	0x0	
1	SftDiscon	rw	0x1	
2	GNPINNakSts	ro	0x0	
3	GOUTNakSts	ro	0x0	
6 : 4	TstCtl	rw	0x0	
7	SGNPInNak	rw	0x0	bit type is changed from w1 to rw.
8	CGNPInNak	rw	0x0	bit type is changed from w1 to rw.
9	SGOUTNak	rw	0x0	bit type is changed from w1 to rw.
10	CGOUTNak	rw	0x0	bit type is changed from w1 to rw.
11	PWROnPrgDone	rw	0x0	
12	DCTL_reserved_0	rc	0x0	bit type is changed from dc to rc.
14 : 13	GMC	rw	0x0	
15	IgnrFrmNum	rw	0x0	
16	NakOnBble	rw	0x0	
17	EnContOnBNA	rw	0x0	
31 : 18	DCTL_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.158 DSTS				0x40200808
Bits	Field Name	Acc	Default	Description
0	SuspSts	ro	0x0	
2 : 1	EnumSpd	ro	0x1	
3	ErrticErr	ro	0x0	
7 : 4	DSTS_reserved_0	rc	0x0	bit type is changed from dc to rc.
21 : 8	SOFFN	rw	0x0	bit type is changed from ru to rw.
23 : 22	DevLnSts	ro	0x0	
28 : 24	StreamStsFifoUsedCnt	ro	0x0	
31 : 29	DSTS_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.159 DIEPMSK				0x40200810
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	EPDisbldMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
3	TimeOUTMsk	rw	0x0	
4	INTknTXFEmpMsk	rw	0x0	
5	INTknEPMisMsk	rw	0x0	
6	INEPNakEffMsk	rw	0x0	
7	DIEPMSK_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	TxfifoUndrnMsk	rw	0x0	
9	BNAInIntrMsk	rw	0x0	
12 : 10	DIEPMSK_reserved_1	rc	0x0	bit type is changed from dc to rc.
13	NAKMsk	rw	0x0	
31 : 14	DIEPMSK_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.160 DOEPMSK				0x40200814
Bits	Field Name	Acc	Default	Description
0	XferComplMsk	rw	0x0	
1	EPDisbldMsk	rw	0x0	
2	AHBErrMsk	rw	0x0	
3	SetUPMsk	rw	0x0	
4	OUTTknEPdisMsk	rw	0x0	
5	StsPhseRcvdMsk	rw	0x0	
6	Back2BackSETup	rw	0x0	

7	DOEPMSK_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErrMsk	rw	0x0	
9	BnaOutIntrMsk	rw	0x0	
11 : 10	DOEPMSK_reserved_1	rc	0x0	bit type is changed from dc to rc.
12	BbleErrMsk	rw	0x0	
13	NAKMsk	rw	0x0	
14	NYETMsk	rw	0x0	
15	DOEPMSK_reserved_3	rc	0x0	bit type is changed from dc to rc.
16	StreamTimeOutMsk	rw	0x0	
17	StreamHdrErrMsk	rw	0x0	
18	StreamEndErrMsk	rw	0x0	
19	StreamLenIllegalMsk	rw	0x0	
31 : 20	DOEPMSK_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.161 DAINT				0x40200818
Bits	Field Name	Acc	Default	Description
0	InEpInt0	ro	0x0	
1	InEpInt1	ro	0x0	
2	InEpInt2	ro	0x0	
3	InEpInt3	ro	0x0	
4	InEpInt4	ro	0x0	
5	InEpInt5	ro	0x0	
6	InEpInt6	ro	0x0	
7	InEpInt7	ro	0x0	
8	InEpInt8	ro	0x0	
9	InEpInt9	ro	0x0	
10	InEpInt10	ro	0x0	
11	InEpInt11	ro	0x0	
12	InEpInt12	ro	0x0	
15 : 13	DAINT_reserved_0	rc	0x0	bit type is changed from dc to rc.
16	OutEPInt0	ro	0x0	
17	OutEPInt1	ro	0x0	
18	OutEPInt2	ro	0x0	
19	OutEPInt3	ro	0x0	
20	OutEPInt4	ro	0x0	
21	OutEPInt5	ro	0x0	
22	OutEPInt6	ro	0x0	
23	OutEPInt7	ro	0x0	
24	OutEPInt8	ro	0x0	
25	OutEPInt9	ro	0x0	
26	OutEPInt10	ro	0x0	
27	OutEPInt11	ro	0x0	
28	OutEPInt12	ro	0x0	
31 : 29	DAINT_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.162 DAINTMSK				0x4020081C
Bits	Field Name	Acc	Default	Description
0	InEpMsk0	rw	0x0	
1	InEpMsk1	rw	0x0	
2	InEpMsk2	rw	0x0	
3	InEpMsk3	rw	0x0	
4	InEpMsk4	rw	0x0	
5	InEpMsk5	rw	0x0	
6	InEpMsk6	rw	0x0	
7	InEpMsk7	rw	0x0	
8	InEpMsk8	rw	0x0	

9	InEpMsk9	rw	0x0	
10	InEpMsk10	rw	0x0	
11	InEpMsk11	rw	0x0	
12	InEpMsk12	rw	0x0	
15 : 13	DAINTMSK_reserved_0	rc	0x0	bit type is changed from dc to rc.
16	OutEPMsk0	rw	0x0	
17	OutEPMsk1	rw	0x0	
18	OutEPMsk2	rw	0x0	
19	OutEPMsk3	rw	0x0	
20	OutEPMsk4	rw	0x0	
21	OutEPMsk5	rw	0x0	
22	OutEPMsk6	rw	0x0	
23	OutEPMsk7	rw	0x0	
24	OutEPMsk8	rw	0x0	
25	OutEPMsk9	rw	0x0	
26	OutEPMsk10	rw	0x0	
27	OutEPMsk11	rw	0x0	
28	OutEPMsk12	rw	0x0	
31 : 29	DAINTMSK_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.163 DVBUSDIS				0x40200828
Bits	Field Name	Acc	Default	Description
15 : 0	DVBUSDis	rw	0x17D7	
31 : 16	DVBUSDIS_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.164 DVBUSPULSE				0x4020082C
Bits	Field Name	Acc	Default	Description
11 : 0	DVBUSPulse	rw	0x5B8	
31 : 12	DVBUSPULSE_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.165 DTHRCTL				0x40200830
Bits	Field Name	Acc	Default	Description
0	NonISOThrEn	rw	0x0	
1	ISOThrEn	rw	0x0	
10 : 2	TxThrLen	rw	0x8	
12 : 11	AHBThrRatio	rw	0x0	
15 : 13	DTHRCTL_reserved_0	rc	0x0	bit type is changed from dc to rc.
16	RxThrEn	rw	0x0	
25 : 17	RxThrLen	rw	0x8	
26	DTHRCTL_reserved_1	rc	0x0	bit type is changed from dc to rc.
27	ArbPrkEn	rw	0x1	
31 : 28	DTHRCTL_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.166 DIEPEMPMSK				0x40200834
Bits	Field Name	Acc	Default	Description
15 : 0	InEpTxfEmpMsk	rw	0x0	
31 : 16	DIEPEMPMSK_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.167 DOEPSTREAMTIMEOUTTH				0x402008C0
Bits	Field Name	Acc	Default	Description
15 : 0	StreamTimeoutTh	rw	0xFFFF	
31 : 16	DOEPSTREAMTIMEO-UTTH_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.168 DOEPSTREAMDBGCTRL				0x402008C4
Bits	Field Name	Acc	Default	Description
2 : 0	StreamDbgEpNum	rw	0x0	
31 : 3	DOEPSTREAMDBGCT-RL_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.169 DOEPSTREAMDBGSTATUS1				0x402008C8
Bits	Field Name	Acc	Default	Description
31 : 0	LpCurDescAddr	ro	0x0	

38.170 DOEPSTREAMDBGSTATUS2				0x402008CC
Bits	Field Name	Acc	Default	Description
10 : 0	LpState	ro	0x0	
17 : 13	AiuEffChannel	ro	0x0	
31 : 18	TxRxBytes	ro	0x0	

38.171 DOEPSTREAMDBGSTATUS3				0x402008D0
Bits	Field Name	Acc	Default	Description
10 : 0	RxPktCnt	ro	0x0	
20 : 11	RxPktRem	ro	0x0	
31 : 21	RxFileCnt	ro	0x0	

38.172 DOEPSTREAMDBGSTATUS4				0x402008D4
Bits	Field Name	Acc	Default	Description
15 : 0	RxFileLen	ro	0x0	
31 : 16	RxFileRem	ro	0x0	

38.173 DIEPCTL0				0x40200900
Bits	Field Name	Acc	Default	Description
1 : 0	MPS	rw	0x0	
14 : 2	DIEPCTL0_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	ro	0x1	
16	DIEPCTL0_reserved_1	rc	0x0	bit type is changed from dc to rc.
17	NAKSts	ro	0x0	
19 : 18	EPType	ro	0x0	
20	DIEPCTL0_reserved_2	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	wo	0x0	
29 : 28	DIEPCTL0_reserved_3	rc	0x0	bit type is changed from dc to rc.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.174 DIEPINT0				0x40200908
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.

6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT0_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT0_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.175 DIEPTSIZ0				0x40200910
Bits	Field Name	Acc	Default	Description
6 : 0	XferSize	rw	0x0	
18 : 7	DIEPTSIZ0_reserved_0	rc	0x0	bit type is changed from dc to rc.
20 : 19	PktCnt	rw	0x0	
31 : 21	DIEPTSIZ0_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.176 DIEPDMA0				0x40200914
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.177 DTXFSTS0				0x40200918
Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS0_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.178 DIEPDMAB0				0x4020091C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	ro	0x0	

38.179 DIEPCTL1				0x40200920
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL1_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL1_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.180 DIEPINT1				0x40200928
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.

1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT1_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT1_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.181 DIEPTSIZ1				0x40200930
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	MC	rw	0x0	
31	DIEPTSIZ1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.182 DIEPDMA1				0x40200934
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.183 DTXFSTS1				0x40200938
Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.184 DIEPDMAB1				0x4020093C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.185 DIEPCTL2				0x40200940
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL2_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL2_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.186 DIEPINT2				0x40200948
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT2_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT2_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.187 DIEPTSIZ2				0x40200950
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	MC	rw	0x0	
31	DIEPTSIZ2_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.188 DIEPDMA2				0x40200954
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.189 DTXFSTS2				0x40200958
Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS2_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.190 DIEPDMAB2				0x4020095C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.191 DIEPCTL3				0x40200960
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL3_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL3_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.

29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.192 DIEPINT3				0x40200968
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT3_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT3_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.193 DIEPTSIZ3				0x40200970
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	MC	rw	0x0	
31	DIEPTSIZ3_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.194 DIEPDMA3				0x40200974
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.195 DTXFSTS3				0x40200978
Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS3_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.196 DIEPDMAB3				0x4020097C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.197 DIEPCTL4				0x40200980
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL4_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL4_reserved_1	rc	0x0	bit type is changed from dc to rc.

21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.198 DIEPINT4				0x40200988
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT4_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT4_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.199 DIEPTSIZ4				0x40200990
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	MC	rw	0x0	
31	DIEPTSIZ4_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.200 DIEPDMA4				0x40200994
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.201 DTXFSTS4				0x40200998
Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS4_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.202 DIEPDMAB4				0x4020099C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.203 DIEPCTL5				0x402009A0
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL5_reserved_0	rc	0x0	bit type is changed from dc to rc.

15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL5_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.204 DIEPINT5 — 0x402009A8

Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT5_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT5_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.205 DIEPTSIZ5 — 0x402009B0

Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	MC	rw	0x0	
31	DIEPTSIZ5_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.206 DIEPDMA5 — 0x402009B4

Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.207 DTXFSTS5 — 0x402009B8

Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS5_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.208 DIEPDMAB5 — 0x402009BC

Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.209 DIEPCTL6				0x402009C0
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL6_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL6_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.210 DIEPINT6				0x402009C8
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT6_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT6_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.211 DIEPTSIZ6				0x402009D0
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	MC	rw	0x0	
31	DIEPTSIZ6_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.212 DIEPDMA6				0x402009D4
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.213 DTXFSTS6				0x402009D8
Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS6_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.214 DIEPDMAB6				0x402009DC
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.215 DIEPCTL7				0x402009E0
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL7_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL7_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.216 DIEPINT7				0x402009E8
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT7_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT7_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.217 DIEPTSIZ7				0x402009F0
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	MC	rw	0x0	
31	DIEPTSIZ7_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.218 DIEPDMA7				0x402009F4
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.219 DTXFSTS7	0x402009F8

Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS7_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.220 DIEPDMAB7				0x402009FC
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.221 DIEPCTL8				0x40200A00
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL8_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL8_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.222 DIEPINT8				0x40200A08
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT8_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT8_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.223 DIEPTSIZ8				0x40200A10
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	MC	rw	0x0	
31	DIEPTSIZ8_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.224 DIEPDMA8	0x40200A14

Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.225 DTXFSTS8				0x40200A18
Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS8_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.226 DIEPDMAB8				0x40200A1C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.227 DIEPCTL9				0x40200A20
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL9_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL9_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.228 DIEPINT9				0x40200A28
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT9_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT9_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.229 DIEPTSIZ9				0x40200A30
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	

30 : 29	MC	rw	0x0	
31	DIEPTSIZ9_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.230 DIEPDMA9				0x40200A34
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.231 DTXFSTS9				0x40200A38
Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS9_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.232 DIEPDMAB9				0x40200A3C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.233 DIEPCTL10				0x40200A40
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL10_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL10_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.234 DIEPINT10				0x40200A48
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT10_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT10_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.235 DIEPTSIZ10				0x40200A50
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	MC	rw	0x0	
31	DIEPTSIZ10_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.236 DIEPDMA10				0x40200A54
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.237 DTXFSTS10				0x40200A58
Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS10_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.238 DIEPDMAB10				0x40200A5C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.239 DIEPCTL11				0x40200A60
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL11_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL11_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.240 DIEPINT11				0x40200A68
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	
8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT11_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.

13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT11_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.241 DIEPTSIZ11				0x40200A70
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	MC	rw	0x0	
31	DIEPTSIZ11_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.242 DIEPDMA11				0x40200A74
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.243 DTXFSTS11				0x40200A78
Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS11_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.244 DIEPDMAB11				0x40200A7C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.245 DIEPCTL12				0x40200A80
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
14 : 11	DIEPCTL12_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	DIEPCTL12_reserved_1	rc	0x0	bit type is changed from dc to rc.
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	TxFNum	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.246 DIEPINT12				0x40200A88
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	TimeOUT	rc	0x0	bit type is changed from w1c to rc.
4	INTknTXFEmp	rc	0x0	bit type is changed from w1c to rc.
5	INTknEPMis	rc	0x0	bit type is changed from w1c to rc.
6	INEPNakEff	rc	0x0	bit type is changed from w1c to rc.
7	TxFEmp	ro	0x1	

8	TxfifoUndrn	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DIEPINT12_reserved_0	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
31 : 15	DIEPINT12_reserved_1	rc	0x0	bit type is changed from dc to rc.

38.247 DIEPTSIZ12				0x40200A90
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	MC	rw	0x0	
31	DIEPTSIZ12_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.248 DIEPDMA12				0x40200A94
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.249 DTXFSTS12				0x40200A98
Bits	Field Name	Acc	Default	Description
15 : 0	INEPTxFSpcAvail	ro	0xEAF	
31 : 16	DTXFSTS12_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.250 DIEPDMAB12				0x40200A9C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.251 DOEPCTL0				0x40200B00
Bits	Field Name	Acc	Default	Description
1 : 0	MPS	ro	0x0	
14 : 2	DOEPCTL0_reserved_0	rc	0x0	bit type is changed from dc to rc.
15	USBActEP	ro	0x1	
16	DOEPCTL0_reserved_1	rc	0x0	bit type is changed from dc to rc.
17	NAKSts	ro	0x0	
19 : 18	EPType	ro	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
25 : 22	DOEPCTL0_reserved_2	rc	0x0	bit type is changed from dc to rc.
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
29 : 28	DOEPCTL0_reserved_3	rc	0x0	bit type is changed from dc to rc.
30	EPDis	ro	0x0	
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.252 DOEPINT0				0x40200B08
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.

4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT0_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT0_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT0_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.253 DOEPTSIZ0				0x40200B10
Bits	Field Name	Acc	Default	Description
6 : 0	XferSize	rw	0x0	
18 : 7	DOEPTSIZ0_reserved_0	rc	0x0	bit type is changed from dc to rc.
19	PktCnt	rw	0x0	
28 : 20	DOEPTSIZ0_reserved_1	rc	0x0	bit type is changed from dc to rc.
30 : 29	SUPCnt	rw	0x0	
31	DOEPTSIZ0_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.254 DOEPDMA0				0x40200B14
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.255 DOEPDMAB0				0x40200B1C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.256 DOEPCTL1				0x40200B20
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	
25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.

28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.257 DOEPCTL1_1				0x40200B24
Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT1_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.258 DOEPINT1				0x40200B28
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT1_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT1_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT1_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.259 DOEPTSIZ1				0x40200B30
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.260 DOEPDMA1				0x40200B34
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.261 DOEPDMAB1				0x40200B3C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.262 DOEPCTL2				0x40200B40
Bits	Field Name	Acc	Default	Description

10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	
25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.263 DOEPCTL2_1				0x40200B44
Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT2_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.264 DOEPINT2				0x40200B48
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT2_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT2_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT2_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.265 DOEPTSIZ2				0x40200B50
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	

28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ2_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.266 DOEPDMA2				0x40200B54
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.267 DOEPDMAB2				0x40200B5C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.268 DOEPCTL3				0x40200B60
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	
25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.269 DOEPCTL3_1				0x40200B64
Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT3_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.270 DOEPINT3				0x40200B68
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT3_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.

9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT3_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT3_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.271 DOEPTSIZ3				0x40200B70
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ3_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.272 DOEPDMA3				0x40200B74
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.273 DOEPDMAB3				0x40200B7C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.274 DOEPCTL4				0x40200B80
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	
25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.275 DOEPCTL4_1	0x40200B84

Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT4_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.276 DOEPINT4				0x40200B88
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT4_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT4_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT4_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.277 DOEPTSIZ4				0x40200B90
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ4_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.278 DOEPDMA4				0x40200B94
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.279 DOEPDMAB4				0x40200B9C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.280 DOEPCTL5				0x40200BA0
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	

17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	
25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.281 DOEPCTL5_1				0x40200BA4
Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT5_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.282 DOEPINT5				0x40200BA8
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT5_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT5_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT5_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.283 DOEPTSIZ5				0x40200BB0
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ5_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.284 DOEPDMA5				0x40200BB4
Bits	Field Name	Acc	Default	Description

31 : 0	DMAAddr	rw	0x0	

38.285 DOEPDMAB5				0x40200BBC
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.286 DOEPCTL6				0x40200BC0
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	
25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.287 DOEPCTL6_1				0x40200BC4
Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT6_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.288 DOEPINT6				0x40200BC8
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT6_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT6_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.

16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT6_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.289 DOEPTSIZ6				0x40200BD0
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ6_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.290 DOEPDMA6				0x40200BD4
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.291 DOEPDMAB6				0x40200BDC
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.292 DOEPCTL7				0x40200BE0
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	
25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.293 DOEPCTL7_1				0x40200BE4
Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT7_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.294 DOEPINT7	0x40200BE8

Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT7_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT7_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT7_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.295 DOEPTSIZ7				0x40200BF0
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ7_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.296 DOEPDMA7				0x40200BF4
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.297 DOEPDMAB7				0x40200BFC
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.298 DOEPCTL8				0x40200C00
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	

25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.299 DOEPCTL8_1				0x40200C04
Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT8_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.300 DOEPINT8				0x40200C08
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT8_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT8_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT8_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.301 DOEPTSIZ8				0x40200C10
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ8_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.302 DOEPDMA8				0x40200C14
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.303 DOEPDMAB8				0x40200C1C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.304 DOEPCTL9				0x40200C20
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	
25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.305 DOEPCTL9_1				0x40200C24
Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT9_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.306 DOEPINT9				0x40200C28
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT9_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT9_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT9_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.307 DOEPTSIZ9	0x40200C30

Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ9_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.308 DOEPDMA9				0x40200C34
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.309 DOEPDMAB9				0x40200C3C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.310 DOEPCTL10				0x40200C40
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	
25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.311 DOEPCTL10_1				0x40200C44
Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT10_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.312 DOEPINT10				0x40200C48
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.

7	DOEPINT10_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT10_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT10_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.313 DOEPTSIZ10				0x40200C50
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ10_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.314 DOEPDMA10				0x40200C54
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.315 DOEPDMAB10				0x40200C5C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.316 DOEPCTL11				0x40200C60
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	
16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	
25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.317 DOEPCTL11_1				0x40200C64
Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT11_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.318 DOEPINT11				0x40200C68
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT11_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT11_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT11_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.319 DOEPTSIZ11				0x40200C70
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ11_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.320 DOEPDMA11				0x40200C74
Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.321 DOEPDMAB11				0x40200C7C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.322 DOEPCTL12				0x40200C80
Bits	Field Name	Acc	Default	Description
10 : 0	MPS	rw	0x0	
11	StreamLenChkEn	rw	0x0	
12	StreamEndChkEn	rw	0x0	
13	StreamHdrChkEn	rw	0x0	
14	XferCmpltIntDis	rw	0x0	
15	USBActEP	rw	0x0	

16	DPID	ro	0x0	
17	NAKSts	ro	0x0	
19 : 18	EPType	rw	0x0	
20	Snp	rw	0x0	
21	Stall	rw	0x0	bit type is changed from othr to rw.
22	StreamEn	rw	0x0	
23	XferCmpltCtrl	rw	0x0	
24	EPDisCtrl	rw	0x0	
25	StreamTimeOutEn	rw	0x0	
26	CNAK	rw	0x0	bit type is changed from w1 to rw.
27	SNAK	rw	0x0	bit type is changed from w1 to rw.
28	SetD0PID	rw	0x0	bit type is changed from w1 to rw.
29	SetD1PID	rw	0x0	bit type is changed from w1 to rw.
30	EPDis	rw	0x0	bit type is changed from othr to rw.
31	EPEna	rw	0x0	bit type is changed from othr to rw.

38.323 DOEPCTL12_1				0x40200C84
Bits	Field Name	Acc	Default	Description
0	EnNakAfterShort	rw	0x0	Enable Set Nak after receiving a Short packet.
1	EnAvoidDmaOvf	rw	0x0	Enable function to avoid dma buffer overflow
31 : 2	DOEPINT12_1_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.324 DOEPINT12				0x40200C88
Bits	Field Name	Acc	Default	Description
0	XferCompl	rc	0x0	bit type is changed from w1c to rc.
1	EPDisbld	rc	0x0	bit type is changed from w1c to rc.
2	AHBErr	rc	0x0	bit type is changed from w1c to rc.
3	SetUp	rc	0x0	bit type is changed from w1c to rc.
4	OUTTknEPdis	rc	0x0	bit type is changed from w1c to rc.
5	StsPhseRcvd	rc	0x0	bit type is changed from w1c to rc.
6	Back2BackSETup	rc	0x0	bit type is changed from w1c to rc.
7	DOEPINT12_reserved_0	rc	0x0	bit type is changed from dc to rc.
8	OutPktErr	rc	0x0	bit type is changed from w1c to rc.
9	BNAIntr	rc	0x0	bit type is changed from w1c to rc.
10	DOEPINT12_reserved_1	rc	0x0	bit type is changed from dc to rc.
11	PktDrpSts	rc	0x0	bit type is changed from w1c to rc.
12	BbleErr	rc	0x0	bit type is changed from w1c to rc.
13	NAKIntrpt	rc	0x0	bit type is changed from w1c to rc.
14	NYETIntrpt	rc	0x0	bit type is changed from w1c to rc.
15	StupPktRcvd	rc	0x0	bit type is changed from w1c to rc.
16	StreamTimeOut	rc	0x0	bit type is changed from w1c to rc.
17	StreamHdrErr	rc	0x0	bit type is changed from w1c to rc.
18	StreamEndErr	rc	0x0	bit type is changed from w1c to rc.
19	StreamLenIllegal	rc	0x0	bit type is changed from w1c to rc.
31 : 20	DOEPINT12_reserved_2	rc	0x0	bit type is changed from dc to rc.

38.325 DOEPTSIZ12				0x40200C90
Bits	Field Name	Acc	Default	Description
18 : 0	XferSize	rw	0x0	
28 : 19	PktCnt	rw	0x0	
30 : 29	RxDPID	ro	0x0	
31	DOEPTSIZ12_reserved_0	rc	0x0	bit type is changed from dc to rc.

38.326 DOEPDMA12	0x40200C94

Bits	Field Name	Acc	Default	Description
31 : 0	DMAAddr	rw	0x0	

38.327 DOEPDMAB12				0x40200C9C
Bits	Field Name	Acc	Default	Description
31 : 0	DMABufferAddr	rw	0x0	bit type is changed from ru to rw.

38.328 PCGCCTL				0x40200E00
Bits	Field Name	Acc	Default	Description
0	StopPclk	rw	0x0	
2 : 1	PCGCCTL_reserved_0	rc	0x0	bit type is changed from dc to rc.
3	RstPdwnModule	rw	0x0	
5 : 4	PCGCCTL_reserved_1	rc	0x0	bit type is changed from dc to rc.
6	PhySleep	ro	0x0	
7	L1Suspended	ro	0x0	
31 : 8	PCGCCTL_reserved_2	rc	0x0	bit type is changed from dc to rc.

39 mm_sys_ctrl

39.1 mem_cfg				0x40241000
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_mem_1pram	rw	0x24C4	memory configration
31 : 16	cfg_mem_2prf	rw	0x20D6	memory configration

39.2 usb_cfg0				0x40241004
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_usb0	rw	0x4220	

39.3 usb_cfg1				0x40241008
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_usb1	rw	0xFFFF03	

39.4 usb_cfg2				0x4024100C
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_usb2	rw	0x4	

39.5 usb_tport_sel				0x40241010
Bits	Field Name	Acc	Default	Description
5 : 0	rg_usb_tport_sel	rw	0x3F	

39.6 usb_status				0x40241014
Bits	Field Name	Acc	Default	Description
0	ro_usb_ready	ro	0x0	
4	ro_usb_rxovf_int_raw_status	ro	0x0	
5	ro_usb_hseof_-err_int_raw_status	ro	0x0	
6	ro_usb_fseof_err_int_raw_status	ro	0x0	
7	ro_usb_busact-_err_int_raw_status	ro	0x0	

8	ro_usb_sync_-timeout_int_raw_status	ro	0x0	
12	ro_usb_rxovf_int_status	ro	0x0	
13	ro_usb_hseof_err_int_status	ro	0x0	
14	ro_usb_fseof_err_int_status	ro	0x0	
15	ro_usb_busact_err_int_status	ro	0x0	
16	ro_usb_sync_-timeout_int_status	ro	0x0	

39.7 usb_digphy_int_enable				0x40241018
Bits	Field Name	Acc	Default	Description
0	rg_usb_rxovf_int_enable	rw	0x0	
1	rg_usb_hseof_err_int_enable	rw	0x0	
2	rg_usb_fseof_err_int_enable	rw	0x0	
3	rg_usb_busact_err_int_enable	rw	0x0	
4	rg_usb_sync_-timeout_int_enable	rw	0x0	

39.8 usb_digphy_int_clr				0x4024101C
Bits	Field Name	Acc	Default	Description
0	rg_usb_rxovf_int_clr_tgl	rw	0x0	
1	rg_usb_hseof_err_int_clr_tgl	rw	0x0	
2	rg_usb_fseof_err_int_clr_tgl	rw	0x0	
3	rg_usb_busact_err_int_clr_tgl	rw	0x0	
4	rg_usb_sync_-timeout_int_clr_tgl	rw	0x0	

39.9 cfg_mm_sys_tports_sel				0x40241020
Bits	Field Name	Acc	Default	Description
1 : 0	cfg_mm_sys_tports_sel	rw	0x0	mm system test ports select

39.10 mem_cfg1				0x40241024
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_mem_1prf	rw	0x2488	

39.11 usb_prbs_cfg				0x40241028
Bits	Field Name	Acc	Default	Description
0	rg_usb_tx_prbs_mode	rw	0x0	
1	rg_usb_tx_prbs_load	rw	0x0	
8 : 2	rg_usb_tx_prbs_seed	rw	0x1	
9	rg_usb_rx_prbs_mode	rw	0x0	
13 : 10	rg_usb_rx_prbs_time	rw	0x0	
20 : 14	rg_usb_rx_err_tolerance	rw	0x0	

39.12 usb_prbs_status				0x4024102C
Bits	Field Name	Acc	Default	Description
0	ro_usb_rx_prbs_valid	ro	0x0	
1	ro_usb_rx_prbs_end	ro	0x0	
2	ro_usb_rx_prbs_pass	ro	0x0	
19 : 4	ro_usb_rx_prbs_errcnt	ro	0x0	

39.13 cfg_pu_usb	0x40241050

Bits	Field Name	Acc	Default	Description
0	rg_pu_usb_dr	rw	0x1	
1	rg_pu_usb	rw	0x0	
2	rg_pu_usb_ana_dr	rw	0x0	
3	rg_pu_usb_ana	rw	0x0	
4	rg_usb_dll_rst_dr	rw	0x0	
5	rg_usb_dll_rst	rw	0x0	
6	rg_usb_dll_clk_en_dr	rw	0x0	
7	rg_usb_dll_clk_en	rw	0x0	
8	rg_usb_dll_clk2dig_en_dr	rw	0x0	
9	rg_usb_dll_clk2dig_en	rw	0x0	
10	rg_usb_hs_bypass	rw	0x1	
15 : 11	rg_pu_usb_dll_us_x2	rw	0x10	
20 : 16	rg_usb_dll_rst_us_x2	rw	0x10	
26 : 21	rg_timer_0p5us_th	rw	0x27	
27	rg_sw_resetn_usbc_core	rw	0x1	
28	rg_sw_resetn_usbc_digphy	rw	0x1	
29	rg_usb_cdr_clk_dis	rw	0x0	

39.14 usb_ana_cfg0				0x40241054
Bits	Field Name	Acc	Default	Description
0	rg_usb_JC_mode	rw	0x1	
1	rg_usb_zps_mode	rw	0x1	
2	rg_usb_rst_intp_mode	rw	0x1	
3	rg_usb_hold_last_mode	rw	0x0	
4	rg_usb_loop_back	rw	0x0	
5	rg_usb_sel_terr	rw	0x1	
6	rg_usb_sel_hs_gain	rw	0x0	
7	rg_usb_squach_det_mode	rw	0x0	
8	rg_usb_en_idcheck_sel	rw	0x0	
9	rg_usb_en_idcheck_reg	rw	0x1	
11 : 10	rg_usb_hs_clk_sel	rw	0x0	
14 : 12	rg_usb_iset_seq	rw	0x4	
18 : 16	rg_usb_iset_otg	rw	0x0	
22 : 20	rg_usb_iset_hs_disconnect	rw	0x4	
23	rg_usb_gpio_mode	rw	0x0	
25 : 24	rg_usb_cdr_gn_	rw	0x1	
27 : 26	rg_usb_hs_idac_mode	rw	0x0	
31 : 28	rg_usb_hs_idac_bit	rw	0x7	

39.15 usb_ana_cfg1				0x40241058
Bits	Field Name	Acc	Default	Description
3 : 0	rg_usb_rterm_hs	rw	0x8	
17 : 12	rg_usb_en_otg	rw	0x0	
19 : 18	rg_usb_dll_pu_bit	rw	0x3	
21 : 20	rg_usb_fsls_drv_bit	rw	0x3	

40 dfe_reg_bank

40.1 a0x000				0x40342000
Bits	Field Name	Acc	Default	Description
9 : 0	stop_delay_reg___	rw	0x199	
11 : 10	dump_size_____	rw	0x0	
15 : 12	dump_start_wr_addr	rw	0x0	

19 : 16	dump_data_sel	rw	0x1	
23 : 20	stop_trig_sel	rw	0x0	
27 : 24	mon_i_sel	rw	0x0	
31 : 28	mon_q_sel	rw	0x0	

40.2 a0x004				0x40342004
Bits	Field Name	Acc	Default	Description
0	dump_enable_____	rw	0x0	
2 : 1	dump_ram_en____	rw	0x0	
3	manual_stop_reg___	rw	0x0	
4	dump_wrap_mode_n___	rw	0x0	
6 : 5	dump_sampl_rate_sel	rw	0x1	
7	restop_trig_mode__	rw	0x0	
31	dump_clk_sel_	rw	0x0	

40.3 a0x008				0x40342008
Bits	Field Name	Acc	Default	Description
0	imbala_cancel_bypass	rw	0x1	
1	imbala_calc_rels	rw	0x0	
2	imbala_cal_dr	rw	0x0	
3	imbala_cancel_hold_dr	rw	0x0	
7 : 4	imbala_cancel_bw_ct_wa	rw	0x3	
11 : 8	imbala_cancel_bw_ct_wq	rw	0x4	
15 : 12	rx_iqim_mem_addr_reg	rw	0x0	
16	rx_iqim_mem_addr_dr	rw	0x0	
17	rx_iqim_mem_wen0	rw	0x0	
18	rx_iqim_mem_cen0	rw	0x1	
19	dac_iq_80m_swap	rw	0x0	
20	adc_i_clkedge_sel	rw	0x0	
21	adc_q_clkedge_sel	rw	0x0	
22	adc_i_dly	rw	0x0	
23	adc_q_dly	rw	0x0	
24	adc_iq_format	rw	0x0	
25	adc_iq_swap	rw	0x0	
26	adc_i_negate	rw	0x0	
27	adc_q_negate	rw	0x0	
28	dac_iq_format	rw	0x0	
29	dac_iq_swap	rw	0x0	
30	dac_i_negate	rw	0x0	
31	dac_q_negate	rw	0x0	

40.4 a0x00c				0x4034200C
Bits	Field Name	Acc	Default	Description
30 : 0	rx_iqim_mem_din0	rw	0x0	

40.5 a0x010				0x40342010
Bits	Field Name	Acc	Default	Description
30 : 0	sdm_freq_reg	rw	0xB989D8A	

40.6 a0x014				0x40342014
Bits	Field Name	Acc	Default	Description
0	vco_cal_resetn_dr	rw	0x0	
1	vco_cal_resetn_reg	rw	0x0	

2	pll_cal_resetn_dr	rw	0x0	
3	pll_cal_resetn_reg	rw	0x0	
4	timer_sdm_resetn_dr	rw	0x0	
5	timer_sdm_resetn_reg	rw	0x0	
6	vco_aac_polarity	rw	0x1	
7	vco_aac_freq_chg	rw	0x0	
9 : 8	reset_pll_lock_delay	rw	0x0	
11 : 10	vco_band_mode	rw	0x0	
12	pll_cal_freq_chg	rw	0x0	
13	pll_cal_eachtime	rw	0x1	
14	pll_cal_det_en	rw	0x0	
15	pll_recal_en	rw	0x0	
16	pll_cal_opt	rw	0x0	
17	pll_cal_manual	rw	0x0	
18	pll_cal_cnt_en_sel	rw	0x0	
19	pll_cal_cnt_up	rw	0x0	
24 : 20	pll_cal_lock_delay	rw	0x0	
27 : 25	pll_cal_init_delay	rw	0x3	
30 : 28	pll_cal_wait_time	rw	0x0	
31	sdm_freq_dr	rw	0x0	

40.7 a0x018				0x40342018
Bits	Field Name	Acc	Default	Description
3 : 0	reset_pll_sdm_delay	rw	0x1	
4	pll_sdm_resetn_dr	rw	0x0	
5	pll_sdm_resetn_reg	rw	0x0	
7 : 6	pll_sdm_clk_sel_reg	rw	0x1	
17 : 8	pll_cal_each_cnt_time_reg	rw	0xA	
18	pll_cal_each_cnt_time_dr	rw	0x1	
20 : 19	pll_cal_eachbit_time	rw	0x0	
21	vco_aac_en_dr	rw	0x0	
22	vco_aac_en_reg	rw	0x0	
23	vco_reg_vbit_dr	rw	0x0	
27 : 24	vco_reg_vbit_reg	rw	0x0	
28	pll_cal_en_dr	rw	0x0	
29	pll_cal_en_reg	rw	0x0	
30	pll_vco_band_dr	rw	0x0	

40.8 a0x01c				0x4034201C
Bits	Field Name	Acc	Default	Description
11 : 0	pll_vco_band_reg	rw	0x0	
28 : 12	pll_cal_freq_reg	rw	0x11	
29	pll_cal_freq_dr	rw	0x1	
30	pll_freq_change_bt_en	rw	0x0	

40.9 a0x020				0x40342020
Bits	Field Name	Acc	Default	Description
11 : 0	idac_data_reg	rw	0x0	
23 : 12	idac_data_reg_bt	rw	0x0	
27	tx_dsp_ramp_dr	rw	0x0	
28	tx_dsp_ramp_reg	rw	0x0	
29	tx_dsp_ramp_sel	rw	0x0	
31 : 30	idac_data_dr	rw	0x1	

40.10 a0x024				0x40342024
Bits	Field Name	Acc	Default	Description
3 : 0	ramp_speed	rw	0xC	
7 : 4	ramp_dly	rw	0x0	
12 : 8	ramp_init	rw	0x0	
13	ramp_bypass	rw	0x1	
21 : 16	gain_ct_u	rw	0x0	
26 : 24	ampm_calib_lpf_bw	rw	0x5	
28 : 27	ampm_calib_en	rw	0x0	
29	ampm_calib_sel_pm	rw	0x0	
30	ampm_calib_out_lock	rw	0x0	

40.11 a0x028				0x40342028
Bits	Field Name	Acc	Default	Description
11 : 0	ref_amp	rw	0x0	
23 : 12	amp_offset	rw	0x0	
28 : 24	tx_iq_dly_sel	rw	0x0	
31 : 29	lpf_ct_u	rw	0x0	

40.12 a0x02c				0x4034202C
Bits	Field Name	Acc	Default	Description
5 : 0	dfe_clken_cfg1	rw	0x0	
8	aux_adc_i_clkedge_sel	rw	0x0	
9	aux_adc_q_clkedge_sel	rw	0x0	
10	aux_adc_iq_format	rw	0x0	
11	aux_adc_iq_swap	rw	0x0	
15 : 12	aux_fifo_din_sel___	rw	0x0	
16	tx_cal_en_____	rw	0x0	
17	rx_cal_en_____	rw	0x0	
18	gain_index_test_sel	rw	0x0	
19	rx_sel_aux_adc	rw	0x0	
20	aux_fifo_wr_sel	rw	0x0	
22	dac_iq45_swap	rw	0x0	
23	dac_iq45_no_rot	rw	0x0	
29 : 28	pre_gain	rw	0x0	
30	pre_gain_en	rw	0x0	
31	regb_fmetre_start	rw	0x0	

40.13 a0x030				0x40342030
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_clken_cfg	rw	0x1B7E7	

40.14 a0x04c				0x4034204C
Bits	Field Name	Acc	Default	Description
9 : 0	rc_interval_offset_n	rw	0x3F0	
25 : 16	rc_interval_offset_p	rw	0x10	

40.15 a0x050				0x40342050
Bits	Field Name	Acc	Default	Description
0	rc_mode_clk_adc	rw	0x1	
1	rc_core_bypass	rw	0x0	
2	rc_iqm_bypass	rw	0x0	
3	rc_hbf_bypass	rw	0x0	

4	rc_bypass_rx	rw	0x0	
5	rc_bypass_tx	rw	0x0	
6	bypass_intf_for_agc	rw	0x0	
7	rc_fifo_wr_en_ctrl	rw	0x1	
11 : 8	rc_fifo_empty_threshold	rw	0x5	
15 : 12	rc_fifo_full_threshold	rw	0xB	
19 : 16	rc_fifo_rd_en_threshold	rw	0x4	
21 : 20	rc_interval_dr_tx	rw	0x2	
23 : 22	rc_interval_dr_rx	rw	0x2	

40.16 a0x054				0x40342054
Bits	Field Name	Acc	Default	Description
27 : 0	rc_interval_reg_tx	rw	0x21F6A8F	

40.17 a0x058				0x40342058
Bits	Field Name	Acc	Default	Description
27 : 0	rc_interval_reg_rx	rw	0x20B4807	

40.18 a0x05c				0x4034205C
Bits	Field Name	Acc	Default	Description
0	dc_calib_en	rw	0x0	
1	dc_cancel_en	rw	0x0	
2	dc_reg_update_en	rw	0x1	
3	dc_est_mode	rw	0x0	
6 : 4	dc_reg_wr_ctrl	rw	0x3	
7	dc_reg_set_en	rw	0x0	
10 : 8	dc_alpha_rst_ctrl	rw	0x6	
14 : 12	dc_avg_len_coef	rw	0x3	
15	dcc_fil_bypass	rw	0x1	
23 : 16	dc_est_wait_time	rw	0x8	
26 : 24	dcc_mode_ct	rw	0x0	
29 : 27	dc_scale_factor	rw	0x3	
31 : 30	dcc_bw_ct2	rw	0x1	

40.19 a0x060				0x40342060
Bits	Field Name	Acc	Default	Description
11 : 0	aux_adc_dc_set_q	rw	0x0	
15 : 12	dc_reg_index	rw	0x0	
27 : 16	aux_adc_dc_set_i	rw	0x0	
29 : 28	dc_reg_rd_sel	rw	0x0	
30	aux_adc_dccancel_en	rw	0x0	
31	agc_dccancel_en	rw	0x0	

40.20 a0x064				0x40342064
Bits	Field Name	Acc	Default	Description
15 : 0	dcc_bw_ct	rw	0xA008	
23 : 16	dcc_tmr_ct	rw	0x30	
30 : 24	dcc_tmr_ct2	rw	0x10	
31	dc_reg_set_dr	rw	0x0	

40.21 a0x068				0x40342068
Bits	Field Name	Acc	Default	Description

13 : 1	dc_reg_set_q	rw	0x0	
29 : 17	dc_reg_set_i	rw	0x0	

40.22 a0x06c				0x4034206C
Bits	Field Name	Acc	Default	Description
11 : 0	amp_tone1	rw	0x500	
25 : 12	tone_freq_num1	rw	0xCCD	
27 : 26	tone_typ	rw	0x0	
28	tx_tone_sel	rw	0x0	
31 : 30	slope_mode	rw	0x0	

40.23 a0x070				0x40342070
Bits	Field Name	Acc	Default	Description
11 : 0	amp_tone2	rw	0xFFC	
25 : 12	tone_freq_num2	rw	0x99A	
26	repeat_mode	rw	0x1	
29 : 28	dac_i_dly_sel	rw	0x0	
31 : 30	dac_q_dly_sel	rw	0x0	

40.24 a0x074				0x40342074
Bits	Field Name	Acc	Default	Description
3 : 0	t_low_amp	rw	0xF	
7 : 4	t_high_amp	rw	0xF	
20	angle_init_set	rw	0x0	
21	tone_com_sel	rw	0x0	
22	tx_tone_150m_sel	rw	0x0	

40.25 a0x078				0x40342078
Bits	Field Name	Acc	Default	Description
11 : 0	coef0_imag	rw	0x0	
23 : 12	coef0_real	rw	0x0	
27 : 24	coef0_k	rw	0x0	
31	bypass_notch0	rw	0x1	

40.26 a0x07c				0x4034207C
Bits	Field Name	Acc	Default	Description
11 : 0	coef1_imag	rw	0x0	
23 : 12	coef1_real	rw	0x0	
27 : 24	coef1_k	rw	0x0	
31	bypass_notch1	rw	0x1	

40.27 a0x080				0x40342080
Bits	Field Name	Acc	Default	Description
0	bypass_ampm	rw	0x1	
1	am_comp_bypass	rw	0x1	
2	pm_comp_bypass	rw	0x1	
5 : 4	am_shift	rw	0x0	
7 : 6	am_p_shift	rw	0x0	
10 : 8	pm_shift	rw	0x0	
15 : 12	ampm_bypass_thr	rw	0xF	

40.28 a0x084				0x40342084
Bits	Field Name	Acc	Default	Description
9 : 0	am_p0	rw	0x0	
25 : 16	pm_p0	rw	0x0	

40.29 a0x088				0x40342088
Bits	Field Name	Acc	Default	Description
9 : 0	am_p1	rw	0x20	
25 : 16	pm_p1	rw	0x0	

40.30 a0x08c				0x4034208C
Bits	Field Name	Acc	Default	Description
9 : 0	am_p2	rw	0x40	
25 : 16	pm_p2	rw	0x0	

40.31 a0x090				0x40342090
Bits	Field Name	Acc	Default	Description
9 : 0	am_p3	rw	0x60	
25 : 16	pm_p3	rw	0x0	

40.32 a0x094				0x40342094
Bits	Field Name	Acc	Default	Description
9 : 0	am_p4	rw	0x80	
25 : 16	pm_p4	rw	0x0	

40.33 a0x098				0x40342098
Bits	Field Name	Acc	Default	Description
9 : 0	am_p5	rw	0xA0	
25 : 16	pm_p5	rw	0x0	

40.34 a0x09c				0x4034209C
Bits	Field Name	Acc	Default	Description
9 : 0	am_p6	rw	0xC0	
25 : 16	pm_p6	rw	0x0	

40.35 a0x0a0				0x403420A0
Bits	Field Name	Acc	Default	Description
9 : 0	am_p7	rw	0xE0	
25 : 16	pm_p7	rw	0x0	

40.36 a0x0a4				0x403420A4
Bits	Field Name	Acc	Default	Description
9 : 0	am_p8	rw	0x100	
25 : 16	pm_p8	rw	0x0	

40.37 a0x0a8				0x403420A8
Bits	Field Name	Acc	Default	Description
9 : 0	am_p9	rw	0x120	
25 : 16	pm_p9	rw	0x0	

40.38 a0x0ac				0x403420AC
Bits	Field Name	Acc	Default	Description
9 : 0	am_p10	rw	0x140	
25 : 16	pm_p10	rw	0x0	

40.39 a0x0b0				0x403420B0
Bits	Field Name	Acc	Default	Description
9 : 0	am_p11	rw	0x160	
25 : 16	pm_p11	rw	0x0	

40.40 a0x0b4				0x403420B4
Bits	Field Name	Acc	Default	Description
9 : 0	am_p12	rw	0x180	
25 : 16	pm_p12	rw	0x0	

40.41 a0x0b8				0x403420B8
Bits	Field Name	Acc	Default	Description
9 : 0	am_p13	rw	0x1A0	
25 : 16	pm_p13	rw	0x0	

40.42 a0x0bc				0x403420BC
Bits	Field Name	Acc	Default	Description
9 : 0	am_p14	rw	0x1C0	
25 : 16	pm_p14	rw	0x0	

40.43 a0x0c0				0x403420C0
Bits	Field Name	Acc	Default	Description
9 : 0	am_p15	rw	0x1E0	
25 : 16	pm_p15	rw	0x0	

40.44 a0x0c4				0x403420C4
Bits	Field Name	Acc	Default	Description
9 : 0	am_p16	rw	0x1FF	
25 : 16	pm_p16	rw	0x0	

40.45 a0x0c8				0x403420C8
Bits	Field Name	Acc	Default	Description
0	loft_calib_en	rw	0x0	
1	loft_cancel_bypass	rw	0x1	
2	lpf_bypass	rw	0x0	
3	bpf_bypass	rw	0x0	
6 : 4	pwr_lpf_ct	rw	0x5	
13 : 8	gain1_ct	rw	0x0	
14	gain1_ct_sel	rw	0x0	
15	gain2_ct_sel	rw	0x0	
21 : 16	gain2_ct	rw	0x0	
26 : 24	rfgain_setting_time_ctrl	rw	0x5	
30 : 28	fdb_ring_delay_ctrl	rw	0x2	

40.46 a0x0cc	0x403420CC

Bits	Field Name	Acc	Default	Description
5 : 0	gain1_dyna_p1	rw	0x0	
13 : 8	gain1_dyna_p2	rw	0x0	
21 : 16	gain1_dyna_p3	rw	0x0	
29 : 24	gain1_dyna_p4	rw	0x0	

40.47 a0x0d0				0x403420D0
Bits	Field Name	Acc	Default	Description
5 : 0	gain2_dyna_p1	rw	0x0	
13 : 8	gain2_dyna_p2	rw	0x0	
21 : 16	gain2_dyna_p3	rw	0x0	
29 : 24	gain2_dyna_p4	rw	0x0	

40.48 a0x0d4				0x403420D4
Bits	Field Name	Acc	Default	Description
5 : 0	gain2_dyna_p5	rw	0x0	
6	din_loft_sel	rw	0x0	
7	bpf_din_sel	rw	0x0	
11 : 8	loft_bit_ctrl	rw	0x0	
14 : 12	phase_bit_ctrl	rw	0x0	
18 : 16	amp_bit_ctrl	rw	0x0	
19	pwr_sel_abs	rw	0x0	
20	phase_err_dr	rw	0x0	
21	amp_err_dr	rw	0x0	
22	loft_offset_dr	rw	0x0	
23	loft_offset_i_dr	rw	0x0	
24	loft_calib_set_dr	rw	0x0	
25	loft_calib_set_reg	rw	0x0	
26	pwr_out_lock	rw	0x0	
27	loft_calib_reg_clear	rw	0x0	
29 : 28	loft_calib_sel	rw	0x0	
30	loft_calib_singl_mode	rw	0x0	

40.49 a0x0d8				0x403420D8
Bits	Field Name	Acc	Default	Description
11 : 0	phase_err_reg	rw	0x0	
15 : 12	gain_index_ph	rw	0x0	
27 : 16	amp_err_reg	rw	0x0	
31 : 28	gain_index_amp	rw	0x0	

40.50 a0x0dc				0x403420DC
Bits	Field Name	Acc	Default	Description
11 : 0	loft_offset_i_reg	rw	0x0	
15 : 12	gain_index_loft_i	rw	0x0	
27 : 16	loft_offset_reg	rw	0x0	
31 : 28	gain_index_loft_q	rw	0x0	

40.51 a0x0e0				0x403420E0
Bits	Field Name	Acc	Default	Description
13 : 0	bpf_iqim_coef_a11	rw	0x37A4	
29 : 16	bpf_iqim_coef_a12	rw	0xAB8	

40.52 a0x0e4				0x403420E4
Bits	Field Name	Acc	Default	Description
13 : 0	bpf_iqim_coef_a21	rw	0x3180	
29 : 16	bpf_iqim_coef_a22	rw	0xE52	

40.53 a0x0e8				0x403420E8
Bits	Field Name	Acc	Default	Description
13 : 0	bpf_iqim_coef_a31	rw	0x3C34	
29 : 16	bpf_iqim_coef_a32	rw	0xE1E	

40.54 a0x0ec				0x403420EC
Bits	Field Name	Acc	Default	Description
13 : 0	bpf_iqim_coef_a41	rw	0x3456	
29 : 16	bpf_iqim_coef_a42	rw	0xBCA	

40.55 a0x0f0				0x403420F0
Bits	Field Name	Acc	Default	Description
13 : 0	bpf_iqim_coef_a51	rw	0x3A93	
29 : 16	bpf_iqim_coef_a52	rw	0xB7F	

40.56 a0x0f4				0x403420F4
Bits	Field Name	Acc	Default	Description
3 : 0	bpf_iqim_coef_g1	rw	0x3	
7 : 4	bpf_iqim_coef_g2	rw	0x2	
11 : 8	bpf_iqim_coef_g3	rw	0x5	
15 : 12	bpf_iqim_coef_g4	rw	0x3	
19 : 16	bpf_iqim_coef_g5	rw	0x4	
23 : 20	bpf_loleakage_coef_g1	rw	0x2	
27 : 24	bpf_loleakage_coef_g2	rw	0x4	
31 : 28	bpf_loleakage_coef_g3	rw	0x3	

40.57 a0x104				0x40342104
Bits	Field Name	Acc	Default	Description
13 : 0	bpf_loleakage_coef_a11	rw	0x2595	
29 : 16	bpf_loleakage_coef_a12	rw	0xE1B	

40.58 a0x108				0x40342108
Bits	Field Name	Acc	Default	Description
13 : 0	bpf_loleakage_coef_a21	rw	0x2B09	
29 : 16	bpf_loleakage_coef_a22	rw	0xD50	

40.59 a0x10c				0x4034210C
Bits	Field Name	Acc	Default	Description
13 : 0	bpf_loleakage_coef_a31	rw	0x2991	
29 : 16	bpf_loleakage_coef_a32	rw	0xBA5	

40.60 a0x110				0x40342110
Bits	Field Name	Acc	Default	Description
7 : 0	in11nsbw20txscale0	rw	0x80	
15 : 8	in11nsbw20txscale1	rw	0x80	

23 : 16	in11nsbw20txscale2	rw	0x80	
31 : 24	in11nsbw20txscale3	rw	0x80	

40.61 a0x114				0x40342114
Bits	Field Name	Acc	Default	Description
7 : 0	in11nsbw40txscale0	rw	0x80	
15 : 8	in11nsbw40txscale1	rw	0x80	
23 : 16	in11nsbw40txscale2	rw	0x80	
31 : 24	in11nsbw40txscale3	rw	0x80	

40.62 a0x118				0x40342118
Bits	Field Name	Acc	Default	Description
7 : 0	in11nsbw20txscale4	rw	0x80	
15 : 8	in11nsbw20txscale5	rw	0x80	
23 : 16	in11nsbw40txscale4	rw	0x80	
31 : 24	in11nsbw40txscale5	rw	0x80	

40.63 a0x11c				0x4034211C
Bits	Field Name	Acc	Default	Description
3 : 0	in11ntxgainidx6	rw	0x0	
7 : 4	in11ntxgainidx7	rw	0x0	
11 : 8	in11btxgainidx0	rw	0x0	
15 : 12	in11btxgainidx1	rw	0x0	
23 : 16	in11btxscale0	rw	0x80	
31 : 24	in11btxscale1	rw	0x80	

40.64 a0x120				0x40342120
Bits	Field Name	Acc	Default	Description
11 : 8	in11ntxgainidx0	rw	0x0	
15 : 12	in11ntxgainidx1	rw	0x0	
19 : 16	in11ntxgainidx2	rw	0x0	
23 : 20	in11ntxgainidx3	rw	0x0	
27 : 24	in11ntxgainidx4	rw	0x0	
31 : 28	in11ntxgainidx5	rw	0x0	

40.65 a0x124				0x40342124
Bits	Field Name	Acc	Default	Description
11 : 0	dlpf_det_fine1_thresh	rw	0x1E0	
23 : 12	dlpf_det_fine2_thresh	rw	0x1E0	
30 : 24	gro_mode2_digital_offset	rw	0x0	

40.66 a0x128				0x40342128
Bits	Field Name	Acc	Default	Description
0	dlpf_restart	rw	0x0	
1	dlpf_freq_mode	rw	0x1	
3 : 2	dlpf_mode	rw	0x0	
4	dlpf_coarse_bypass_lpf1	rw	0x1	
5	dlpf_bypass_sdm	rw	0x0	
6	gro_mode_sel	rw	0x0	
7	gro_sample_clkedge_sel	rw	0x0	
9 : 8	dlpf_sinc_order	rw	0x3	
11 : 10	dlpf_sinc_order1	rw	0x3	

13 : 12	cors_avg_num	rw	0x1	
14	cors_avg_bps	rw	0x0	
15	dlpf_det_bypass	rw	0x0	
27 : 16	dlpf_det_coarse_thresh	rw	0x1E0	

40.67 a0x12c				0x4034212C
Bits	Field Name	Acc	Default	Description
15 : 0	dlpf_phase_offset	rw	0xC8	

40.68 a0x130				0x40342130
Bits	Field Name	Acc	Default	Description
11 : 0	dlpf_coarse_code_initial	rw	0x800	
28 : 16	dlpf_dco_code_initial	rw	0x1000	

40.69 a0x134				0x40342134
Bits	Field Name	Acc	Default	Description
1 : 0	dlpf_k1_idx	rw	0x2	
3 : 2	dlpf_k2_idx	rw	0x2	
5 : 4	dlpf_k5_idx	rw	0x2	
7 : 6	dlpf_k6_idx	rw	0x2	
10 : 8	dlpf_k3_idx_fine1	rw	0x2	
14 : 12	dlpf_k4_idx_fine1	rw	0x2	
18 : 16	dlpf_k3_idx_fine2	rw	0x2	
22 : 20	dlpf_k4_idx_fine2	rw	0x2	
26 : 24	dlpf_k3_idx_coarse	rw	0x2	
30 : 28	dlpf_k4_idx_coarse	rw	0x2	

40.70 a0x138				0x40342138
Bits	Field Name	Acc	Default	Description
9 : 0	dlpf_cnt_fine1	rw	0x1F4	
21 : 12	dlpf_cnt_fine2	rw	0x1F4	

40.71 a0x13c				0x4034213C
Bits	Field Name	Acc	Default	Description
9 : 0	dlpf_cycle_slip_fine_code	rw	0x0	
21 : 12	dlpf_cycle_slip_coarse_code	rw	0x3C	
25 : 24	dlpf_kp_idx_fine1	rw	0x1	
27 : 26	dlpf_kp_idx_fine2	rw	0x1	
29 : 28	dlpf_kp_idx_coarse	rw	0x1	
30	dlpf_cycle_slip_coarse_en	rw	0x1	
31	dlpf_cycle_slip_fine_en	rw	0x0	

40.72 a0x140				0x40342140
Bits	Field Name	Acc	Default	Description
3 : 0	mon_sel_dlpf	rw	0x0	
4	mon_clk_sel	rw	0x0	
5	mon_lock_en	rw	0x0	
7	dlpf_coarse_code_dr	rw	0x0	
19 : 8	dlpf_coarse_code_dr_reg	rw	0x800	
29 : 20	dlpf_cnt_coarse	rw	0x190	

40.73 a0x144				0x40342144
Bits	Field Name	Acc	Default	Description
15 : 0	txon_start	rw	0x20	
31 : 16	txon_end	rw	0x800	

40.74 a0x148				0x40342148
Bits	Field Name	Acc	Default	Description
1 : 0	feedback_pow_en_reg	rw	0x0	
2	is_maxpow_dr	rw	0x1	
3	is_maxpow_reg	rw	0x0	
7 : 4	maxpow_thr	rw	0xF	
11 : 8	txgain_cmp_reg	rw	0x8	
12	txgain_cmp_dr	rw	0x1	
19 : 16	sw_cfg_pow	rw	0x8	
23 : 20	notch_bypass_thr	rw	0xF	

40.75 a0x14c				0x4034214C
Bits	Field Name	Acc	Default	Description
31 : 0	pow_acc_upthr	rw	0x0	

40.76 a0x150				0x40342150
Bits	Field Name	Acc	Default	Description
31 : 0	pow_acc_lowthr	rw	0x0	

40.77 a0x15c				0x4034215C
Bits	Field Name	Acc	Default	Description
9 : 0	cfg_a	rw	0x1D8	
22 : 12	cfg_b	rw	0x7B3	
27 : 24	cfg_et_cmp	rw	0x8	
31 : 28	et_bypass_thr	rw	0xF	

40.78 a0x160				0x40342160
Bits	Field Name	Acc	Default	Description
8 : 0	cfg_v0	rw	0xE6	
14 : 12	cfg_v1	rw	0x3	
15	et_max_sel	rw	0x0	
24 : 16	cfg_c	rw	0xD7	

40.79 a0x164				0x40342164
Bits	Field Name	Acc	Default	Description
0	generator_mem_hw_access	rw	0x0	
1	generator_mem_rd_only_once	rw	0x0	
2	generator_mem_hw_rden	rw	0x0	
4	generator_mem_clk_sel	rw	0x0	
6 : 5	generator_mem_en	rw	0x0	
11 : 8	generator_addr_offset	rw	0x0	
30 : 16	generator_mem_end_addr	rw	0x0	

40.80 a0x168				0x40342168
Bits	Field Name	Acc	Default	Description
14 : 0	generator_mem_repeat_addr1	rw	0x0	

30 : 16	generator_mem_repeat_addr0	rw	0x0	

40.81 a0x16c				0x4034216C
Bits	Field Name	Acc	Default	Description
7 : 0	generator_mem_repeat_num	rw	0x0	
15 : 8	generator_mem_tx_ramp_time	rw	0x0	
23 : 16	generator_mem_interval_time	rw	0x0	
31 : 24	num_1us_in_tx_clk	rw	0x0	

40.82 a0x170				0x40342170
Bits	Field Name	Acc	Default	Description
0	papr_bypass0	rw	0x1	
1	papr_bypass1	rw	0x1	
2	papr_lpf_bypass	rw	0x0	
3	tx_scale_bypass	rw	0x0	
7 : 4	dly_ct_din	rw	0x0	
11 : 8	dly_ct_clipflg	rw	0x0	
12	papr_lpf_coef_sel	rw	0x0	
13	clip_thres_sel_11ax	rw	0x0	
15 : 14	is_software_ctrl	rw	0x3	
19 : 16	papr_bypass_thr	rw	0xF	
20	papr_bypass_11b	rw	0x1	
31 : 24	generator_mem_rd_pkt_num	rw	0x0	

40.83 a0x174				0x40342174
Bits	Field Name	Acc	Default	Description
5 : 0	clip1_threshold0	rw	0x2C	
13 : 8	clip1_threshold1	rw	0x2C	
21 : 16	clip1_threshold2	rw	0x2C	
29 : 24	clip1_threshold3	rw	0x2C	

40.84 a0x178				0x40342178
Bits	Field Name	Acc	Default	Description
5 : 0	clip2_threshold0	rw	0x2C	
13 : 8	clip2_threshold1	rw	0x2C	
21 : 16	clip2_threshold2	rw	0x2C	
29 : 24	clip2_threshold3	rw	0x2C	

40.85 a0x17c				0x4034217C
Bits	Field Name	Acc	Default	Description
5 : 0	clip1_threshold4	rw	0x2C	
13 : 8	clip1_threshold5	rw	0x2C	
21 : 16	clip2_threshold4	rw	0x2C	
29 : 24	clip2_threshold5	rw	0x2C	

40.86 a0x180				0x40342180
Bits	Field Name	Acc	Default	Description
0	pll_freq_change_dr	rw	0x0	
1	dc_est_restart_dr	rw	0x0	
11 : 8	tpd_sel_dpll	rw	0x0	
15 : 12	mon_port_sel	rw	0x0	
23 : 16	tpm_dac	rw	0x0	

26 : 24	mon_to_dac_sel	rw	0x0	

40.87 a0x184				0x40342184
Bits	Field Name	Acc	Default	Description
0	pll_freq_change_reg	wo	0x0	WT Reg.
1	dc_est_restart_reg	wo	0x0	WT Reg. (normal regs, do not use this addr)

40.88 a0x188				0x40342188
Bits	Field Name	Acc	Default	Description
5 : 0	clip1_threshold6	rw	0x2C	
13 : 8	clip2_threshold6	rw	0x2C	

40.89 a0x200				0x40342200
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg0	ro	0x0	

40.90 a0x204				0x40342204
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg1	ro	0x0	

40.91 a0x208				0x40342208
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg2	ro	0x0	

40.92 a0x20c				0x4034220C
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg3	ro	0x0	

40.93 a0x210				0x40342210
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg4	ro	0x0	

40.94 a0x214				0x40342214
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg5	ro	0x0	

40.95 a0x218				0x40342218
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg6	ro	0x0	

40.96 a0x21c				0x4034221C
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg7	ro	0x0	

40.97 a0x220				0x40342220
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg8	ro	0x0	

40.98 a0x224				0x40342224
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg9	ro	0x0	

40.99 a0x228				0x40342228
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg10	ro	0x0	

40.100 a0x22c				0x4034222C
Bits	Field Name	Acc	Default	Description
31 : 0	dfe_rd_reg11	ro	0x0	

41 wf_rf_interface

41.1 reg_00				0x40344000
Bits	Field Name	Acc	Default	Description
0	wf_pu_adc_vreg_com_reg	rw	0x0	
1	wf_pu_adc_vreg_com_dr	rw	0x0	
2	wf_pu_adc_reg	rw	0x0	
3	wf_pu_adc_dr	rw	0x0	
4	wf_rxflt_rstn_reg	rw	0x0	
5	wf_rxflt_rstn_dr	rw	0x0	
6	wf_pu_rxflt_reg	rw	0x0	
7	wf_pu_rxflt_dr	rw	0x0	
8	wf_pu_iref_reg	rw	0x0	
9	wf_pu_iref_dr	rw	0x0	
10	wf_dtmx_cdr_rstn_reg	rw	0x0	
11	wf_dtmx_cdr_rstn_dr	rw	0x0	
12	wf_pu_dtmx_reg	rw	0x0	
13	wf_pu_dtmx_dr	rw	0x0	
14	wf_pa_trxsw_sel_avdd13_reg	rw	0x0	
15	wf_pa_trxsw_sel_avdd13_dr	rw	0x0	
16	wf_pu_trx_capsw_reg	rw	0x0	
17	wf_pu_trx_capsw_dr	rw	0x0	
18	wf_pa_pkdet_rstn_reg	rw	0x0	
19	wf_pa_pkdet_rstn_dr	rw	0x0	
20	wf_pa_gain_en_reg	rw	0x0	
21	wf_pa_gain_en_dr	rw	0x0	
22	wf_pu_pa_reg	rw	0x0	
23	wf_pu_pa_dr	rw	0x0	
24	wf_tia_rstn_reg	rw	0x0	
25	wf_tia_rstn_dr	rw	0x0	
26	wf_pu_tia_reg	rw	0x0	
27	wf_pu_tia_dr	rw	0x0	
28	wf_pu_rmx_reg	rw	0x0	
29	wf_pu_rmx_dr	rw	0x0	
30	wf_pu_lna_reg	rw	0x0	
31	wf_pu_lna_dr	rw	0x0	

41.2 reg_01				0x40344004
Bits	Field Name	Acc	Default	Description
1 : 0	wf_rfpll_pu_bit	rw	0x0	
3 : 2	wf_adc_pu_bit	rw	0x2	
5 : 4	wf_rxflt_pu_bit	rw	0x2	

7 : 6	wf_dtmx_pu_bit_avdd13	rw	0x2	
9 : 8	wf_dtmx_pu_bit_avdd33	rw	0x2	
11 : 10	wf_tia_pu_bit	rw	0x1	
13 : 12	wf_rmx_pu_bit	rw	0x1	
15 : 14	wf_lna_pu_bit	rw	0x1	
16	wf_pu_ts_hub	rw	0x0	
17	wf_vco_rxlo_en_reg	rw	0x0	
18	wf_vco_rxlo_en_dr	rw	0x0	
19	wf_vco_txlo_en_reg	rw	0x0	
20	wf_vco_txlo_en_dr	rw	0x0	
21	wf_pu_vco_reg	rw	0x0	
22	wf_pu_vco_dr	rw	0x0	
23	wf_rfpll_sar_clk_en_reg	rw	0x0	
24	wf_rfpll_sar_clk_en_dr	rw	0x0	
25	wf_pu_rfpll_reg	rw	0x0	
26	wf_pu_rfpll_dr	rw	0x0	
27	wf_pu_pdadc_reg	rw	0x0	
28	wf_pu_pdadc_dr	rw	0x0	
29	wf_pu_adc_vref_pdt_reg	rw	0x0	
30	wf_pu_adc_vref_pdt_dr	rw	0x0	

41.3 reg_02				0x40344008
Bits	Field Name	Acc	Default	Description
1 : 0	wf_pu_adc_vref_pdt_td1	rw	0x1	
3 : 2	wf_rxflt_rstn_td1	rw	0x1	
5 : 4	wf_tia_rstn_td1	rw	0x1	
8 : 6	wf_pu_rfpll_td3	rw	0x5	
10 : 9	wf_pu_vco_td2	rw	0x1	
11	wf_test_enable_vco	rw	0x0	
12	wf_test_enable_rfpll	rw	0x0	
15 : 13	wf_test_bit	rw	0x0	
16	wf_test_enable_ts_hub	rw	0x0	
17	wf_test_enable_adc	rw	0x0	
19 : 18	wf_test_enable_rxflt	rw	0x0	
20	wf_rxflt_test2gpio_en	rw	0x0	
22 : 21	wf_rxflt_test_mode	rw	0x0	
23	wf_test_enable_iref	rw	0x0	
24	wf_test_enable_dtmx	rw	0x0	
26 : 25	wf_test_enable_tia	rw	0x0	
27	wf_test_enable_rmx	rw	0x0	
28	wf_test_enable_lna	rw	0x0	
29	wf_dtmx_pll_test	rw	0x0	
31 : 30	wf_vco_pu_bit	rw	0x3	

41.4 reg_03				0x4034400C
Bits	Field Name	Acc	Default	Description
3 : 0	wf_lna_cg_vbit	rw	0x5	
7 : 4	wf_lna_ibias_bit	ro	0x8	
9 : 8	wf_lna_gbit	ro	0x3	
10	wf_lna_mixer1st_en	ro	0x0	
13 : 11	wf_lna_reg_vbit	rw	0x4	
15 : 14	wf_pd_td0	rw	0x1	
17 : 16	wf_pa_gain_en_td1	rw	0x1	
19 : 18	wf_pa_pkdet_rstn_td2	rw	0x1	
21 : 20	wf_pa_pkdet_rstn_td1	rw	0x1	
23 : 22	wf_pu_pa_td1	rw	0x1	

25 : 24	wf_dtmx_cdr_rstn_td1	rw	0x1	
27 : 26	wf_pu_dtmx_td1	rw	0x1	
29 : 28	wf_pu_lna_td1	rw	0x1	
31 : 30	wf_pu_rmx_td1	rw	0x1	

41.5 reg_04				0x40344010
Bits	Field Name	Acc	Default	Description
1 : 0	wf_tia_reg_vbit	rw	0x1	
4 : 2	wf_rmx_cload_bit	ro	0x2	
7 : 5	wf_rmx_lobias_vbit	rw	0x2	
10 : 8	wf_rmx_reg_vbit	rw	0x3	
12 : 11	wf_lna_pwrdet_level	rw	0x0	
13	wf_lna_pwrdet_en	rw	0x0	
14	wf_lna_comp_von	ro	0x0	
15	wf_lna_comp_vop	ro	0x0	
16	wf_lna_cal_clk_edge	rw	0x0	
17	wf_lna_cal_en	rw	0x0	
22 : 18	wf_lna_vcm_n_reg	rw	0x10	
23	wf_lna_vcm_n_dr	rw	0x0	
28 : 24	wf_lna_vcm_p_reg	rw	0x10	
29	wf_lna_vcm_p_dr	rw	0x0	
30	wf_lna_iref_sel	rw	0x0	

41.6 reg_05				0x40344014
Bits	Field Name	Acc	Default	Description
2 : 0	wf_tia_gain_bit	ro	0x7	
5 : 3	wf_tia_dccal_rdac_range	rw	0x2	
8 : 6	wf_tia_op_mil_rbit	rw	0x3	
11 : 9	wf_tia_op_mil_cbit	rw	0x3	
16 : 12	wf_tia_op_ibit	ro	0x19	
19 : 17	wf_tia_vcm_vbit	rw	0x4	
20	wf_tia_op_hp_mode	ro	0x0	
21	wf_tia_op_lb_mode	ro	0x0	
24 : 22	wf_tia_bw_r_bit	ro	0x4	
29 : 25	wf_tia_bw_c_bit	ro	0x14	
31 : 30	wf_tia_input_sel	rw	0x0	

41.7 reg_06				0x40344018
Bits	Field Name	Acc	Default	Description
0	wf_pa_iref_sel_bg	rw	0x1	
2 : 1	wf_pa_vbg_tc_bit	rw	0x1	
4 : 3	wf_pa_vbg_vbit	rw	0x3	
10 : 5	wf_pa_gbit	ro	0x3F	
11	wf_pa_ms	rw	0x0	
19 : 12	wf_tia_q_calbit_reg	rw	0x80	
20	wf_tia_q_calbit_dr	rw	0x0	
28 : 21	wf_tia_i_calbit_reg	rw	0x80	
29	wf_tia_i_calbit_dr	rw	0x0	

41.8 reg_07				0x4034401C
Bits	Field Name	Acc	Default	Description
0	wf_pa_loft_lowpass_en	rw	0x1	
1	wf_pa_loft_en	rw	0x0	
4 : 2	wf_pa_vl_vbit	ro	0x4	

8 : 5	wf_pa_vl_cgm_ibit	rw	0x8	
11 : 9	wf_pa_vl_ic_sel_bit	rw	0x1	
12	wf_pa_vl_opam_en	rw	0x1	
13	wf_pa_vm_opam_ibit	rw	0x1	
16 : 14	wf_pa_vm_vbit	ro	0x4	
20 : 17	wf_pa_vm_vbit2	ro	0x8	
24 : 21	wf_pa_vm_vbit1	ro	0x8	
25	wf_pa_vm_dym_en	ro	0x0	
28 : 26	wf_pa_bias_vh_vbit	rw	0x6	
31 : 29	wf_pa_input_cbit	ro	0x0	

41.9 reg_08				0x40344020
Bits	Field Name	Acc	Default	Description
1 : 0	wf_dtmx_path_mode_bit	rw	0x3	
2	wf_dtmx_ms	rw	0x0	
5 : 3	wf_dtmx_dvdd_vbit	rw	0x4	
9 : 6	wf_pa_rfop_hd2_cbit	rw	0x8	
10	wf_pa_pkdet_out	ro	0x0	
14 : 11	wf_pa_trx_cap_sw_bit	ro	0x8	
17 : 15	wf_pa_dpd_att_cbit	rw	0x4	
18	wf_pa_dpd_en	rw	0x0	
21 : 19	wf_pa_isense_resbit	rw	0x4	
22	wf_pa_isense_icsel_bit	rw	0x0	
23	wf_pa_isense_en	rw	0x0	
26 : 24	wf_pa_pkdet_vth_vbit	rw	0x4	
27	wf_pa_pkd_en	rw	0x0	
30 : 28	wf_pa_loft_gbit	rw	0x4	

41.10 reg_09				0x40344024
Bits	Field Name	Acc	Default	Description
0	wf_dtmx_lo_div4_en	rw	0x1	
1	wf_dtmx_capbit_h_en	rw	0x0	
5 : 2	wf_dtmx_tuning_cbit	ro	0x8	
9 : 6	wf_dtmx_idac_offset_bit	ro	0x0	
10	wf_dtmx_idac_clk_sel_pos_edge	rw	0x1	
11	wf_dtmx_idac_en	ro	0x0	
14 : 12	wf_dtmx_dac_vcasd_vbit2	ro	0x4	
18 : 15	wf_dtmx_dac_vcasd_vbit1	ro	0xB	
22 : 19	wf_dtmx_dac_gbit2	ro	0x7	
25 : 23	wf_dtmx_dac_gbit1	ro	0x4	
28 : 26	wf_dtmx_lobias_vbit	rw	0x1	
31 : 29	wf_dtmx_cscd_hbias_vbit	rw	0x6	

41.11 reg_0A				0x40344028
Bits	Field Name	Acc	Default	Description
0	wf_dtmx_dpd_cal_en	rw	0x0	
5 : 1	wf_dtmx_clk2dig_dly_bit	rw	0x0	
8 : 6	wf_dtmx_clk_freq_sel_bit	rw	0x4	
9	wf_dtmx_clk_-path0_45_delay_en	rw	0x1	
10	wf_dtmx_clk_iq_delay_en	rw	0x1	
13 : 11	wf_dtmx_clk_phase_sel_bit	rw	0x4	
14	wf_dtmx_clk_sel_pos_edge	rw	0x1	
19 : 15	wf_dtmx_offset_bits	rw	0x0	
20	wf_dtmx_cdr_en	rw	0x1	

22 : 21	wf_dtmx_cdr_div_mode_bit	rw	0x2	
23	wf_dtmx_clk2dac_sel_dig	rw	0x0	
24	wf_dtmx_div_rstn	rw	0x1	
25	wf_dtmx_clk2cdr_en	rw	0x1	
27 : 26	wf_dtmx_lo_path_phase_sel	rw	0x3	
30 : 28	wf_dtmx_lo_reg_vbit	rw	0x4	

41.12 reg_0B				0x4034402C
Bits	Field Name	Acc	Default	Description
1 : 0	wf_rxflt_bw_mode	ro	0x2	
2	wf_rxflt_iq_swap	rw	0x0	
4 : 3	wf_rxflt_notch_mode	ro	0x0	
6 : 5	wf_rxflt_pwres_bit	rw	0x2	
10 : 7	wf_trx_rsvd_bit	rw	0xC	
11	wf_iref_current_start_enb	rw	0x1	
12	wf_dtmx_bias_ref_sel_bg	rw	0x1	
14 : 13	wf_dtmx_vbg_vbit	rw	0x3	
16 : 15	wf_dtmx_vbg_tc_bit	rw	0x1	
18 : 17	wf_dtmx_att_bit	ro	0x0	
21 : 19	wf_dtmx_clk_phase_sel_lck_bit	ro	0x0	
23 : 22	wf_dtmx_cdr_dly_lck_bit	ro	0x0	
24	wf_dtmx_clk2dig_phase_lock	ro	0x0	
27 : 25	wf_dtmx_dpd_lobias_vbit	rw	0x4	

41.13 reg_0C				0x40344030
Bits	Field Name	Acc	Default	Description
0	wf_adc_en_core	rw	0x1	
4 : 1	wf_rxflt_op_rq_bit	ro	0x6	
8 : 5	wf_rxflt_op_rm_bit	ro	0x6	
12 : 9	wf_rxflt_op_cm_bit	ro	0x4	
18 : 13	wf_rxflt_op_ibit	ro	0x20	
21 : 19	wf_rxflt_vcm_bit	rw	0x5	
23 : 22	wf_rxflt_gbit2	ro	0x0	
26 : 24	wf_rxflt_gbit1	ro	0x0	
31 : 27	wf_rxflt_bw_cbit	ro	0xC	

41.14 reg_0D				0x40344034
Bits	Field Name	Acc	Default	Description
0	wf_adc_dac_lp_mode	rw	0x0	
5 : 1	wf_adc_vref_vbit	rw	0x8	
10 : 6	wf_adc_vref_ibit	rw	0x4	
13 : 11	wf_adc_vcm_vbit	rw	0x2	
17 : 14	wf_adc_vreg_ibit	rw	0x2	
20 : 18	wf_adc_vreg_vbit	rw	0x3	
24 : 21	wf_adc_dly_bit	rw	0x1	
25	wf_adc_clk_edge	rw	0x0	
29 : 26	wf_adc_cmp_ibit	rw	0x4	
31 : 30	wf_adc_clk_sel	rw	0x0	

41.15 reg_0E				0x40344038
Bits	Field Name	Acc	Default	Description
1 : 0	wf_rfpll_ldo_vbit	rw	0x2	
5 : 2	wf_rfpll_pll_reg_vbit	rw	0x8	
6	wf_rfpll_enable_dpll_mode	rw	0x0	

7	wf_rfpll_enable_presc	rw	0x1	
8	wf_rfpll_enable_loop	rw	0x1	
12 : 9	wf_abb_rsvd_bit	rw	0xC	
15 : 13	wf_rx_iq2gpio_en	rw	0x0	
17 : 16	wf_ts_hub_vref_vbit	rw	0x2	
19 : 18	wf_ts_hub_vptat_vbit	rw	0x2	
23 : 20	wf_ts_hub_channel_sel	rw	0x1	
24	wf_ts_hub_chopper_fq	rw	0x0	
25	wf_pdadc_clk_edge_sel	rw	0x0	
29 : 26	wf_pdadc_dly_bit	rw	0x2	

41.16 reg_0F				0x4034403C
Bits	Field Name	Acc	Default	Description
0	wf_rfpll_fbc_sel	rw	0x0	
1	wf_rfpll_sdm_clk_sel	ro	0x0	
7 : 2	wf_rfpll_pdt_res_bit	rw	0x0	
9 : 8	wf_rfpll_lpf_gain_bit	rw	0x3	
11 : 10	wf_rfpll_lpf_rbit	rw	0x2	
15 : 12	wf_rfpll_cp_ibit	rw	0x4	
17 : 16	wf_rfpll_cp_rbit	rw	0x0	
21 : 18	wf_rfpll_vco_gain	rw	0xF	
22	wf_rfpll_lpf_notch_bypass	rw	0x0	
24 : 23	wf_rfpll_sinc_mode	rw	0x1	
25	wf_rfpll_loop_mode	rw	0x0	
26	wf_rfpll_ref_multi2_en	rw	0x0	
27	wf_rfpll_fref_sel	rw	0x1	
31 : 28	wf_rfpll_pll_presc_reg_vbit	rw	0x8	

41.17 reg_10				0x40344040
Bits	Field Name	Acc	Default	Description
0	wf_rfpll_vctrl_detect_en	rw	0x0	
1	wf_rfpll_div_edge_sel	rw	0x0	
10 : 2	wf_rfpll_div_clk_gen	rw	0x3B	
12 : 11	wf_rfpll_sinc_clk_sel	rw	0x0	
14 : 13	wf_rfpll_pll_vco_cal_sel	rw	0x1	
16 : 15	wf_rfpll_cal_bit	rw	0x2	
17	wf_rfpll_pll_cal_en	ro	0x0	
18	wf_rfpll_cal_clk_sel	rw	0x0	

41.18 reg_11				0x40344044
Bits	Field Name	Acc	Default	Description
11 : 0	wf_vco_band_bit	ro	0x200	
12	wf_vco_buf_en	rw	0x1	
13	wf_rfpll_lock	ro	0x0	
30 : 14	wf_rfpll_dout	ro	0x0	

41.19 reg_12				0x40344048
Bits	Field Name	Acc	Default	Description
3 : 0	wf_lo_rsvd_bit	rw	0xC	
4	wf_vco_trx_mode	rw	0x1	
5	wf_vco_presclo_en	rw	0x1	
10 : 6	wf_vco_vctrl_biasn_bit	rw	0x7	
15 : 11	wf_vco_vctrl_biasp_bit	rw	0x19	
19 : 16	wf_vco_buf_reg_bit	rw	0x8	

20	wf_vco_core_reg_imode	rw	0x0	
24 : 21	wf_vco_core_reg_bit	ro	0x8	
28 : 25	wf_vco_band_temp_bit	rw	0x7	

41.20 reg_13				0x4034404C
Bits	Field Name	Acc	Default	Description
7 : 0	wf_apc_rsvd	ro	0xF0	
15 : 8	wf_agc_rsvd	ro	0xF0	

41.21 wf_soft_reset_reg				0x40344050
Bits	Field Name	Acc	Default	Description
0	soft_reset	rw	0x0	

41.22 wf_man_ctrl_reg				0x40344054
Bits	Field Name	Acc	Default	Description
5 : 0	tx_gain_reg	rw	0x0	
6	tx_gain_dr	rw	0x0	
7	tx_gain_dr_pulse	rw	0x0	
16 : 8	rx_gain_reg	rw	0x0	
17	rx_gain_dr	rw	0x0	
18	rx_gain_dr_pulse	rw	0x0	
19	rxon_reg	rw	0x0	
20	rxon_dr	rw	0x0	
21	txon_reg	rw	0x0	
22	txon_dr	rw	0x0	
23	bton_reg	rw	0x0	
24	bton_dr	rw	0x1	
25	bttws_reg	rw	0x0	
26	bttws_dr	rw	0x0	
27	pllon_reg	rw	0x0	
28	pllon_trx	rw	0x1	
29	rxgain_page	rw	0x0	
30	wf_pllon_sleep_en	rw	0x1	

41.23 wf_calclk_reg				0x40344058
Bits	Field Name	Acc	Default	Description
9 : 0	cal_clk_div_num	rw	0x4F	
10	cal_clk_en	rw	0x0	
16 : 11	cal_clk_div_num_p1	rw	0x6	
22 : 17	cal_clk_div_num_p2	rw	0x13	
23	vco_loen_ctrl	rw	0x0	
25 : 24	debug_mux	rw	0x0	
26	debug_clk_en	rw	0x0	

41.24 wf_ext_trxon_delay_reg				0x4034405C
Bits	Field Name	Acc	Default	Description
3 : 0	ext_pa_idle_ctrl_reg	rw	0x0	
7 : 4	ext_pa_tx_ctrl_reg	rw	0x2	
11 : 8	ext_pa_rx_ctrl_reg	rw	0x5	
20 : 12	ext_txon_delay	rw	0x41	
29 : 21	ext_rxon_delay	rw	0x87	

41.25 gain_mem_ctrl_reg				0x40344060
Bits	Field Name	Acc	Default	Description
0	clk_txgain_en	rw	0x0	
1	clk_txgain_sel	rw	0x0	
2	txgain_mem_cfg	rw	0x0	
4	clk_rxgain_en	rw	0x0	
5	clk_rxgain_sel	rw	0x0	
6	rxgain_mem_cfg	rw	0x0	

41.26 gain_mem_fetch_reg				0x40344064
Bits	Field Name	Acc	Default	Description
5 : 0	txgain_mem_fetch_addr	rw	0x0	
15	txgain_mem_fetch_p	rw	0x0	
22 : 16	rxgain_mem_fetch_addr	rw	0x0	
31	rxgain_mem_fetch_p	rw	0x0	

41.27 wf_dpd_txcal_ctrl_reg				0x40344068
Bits	Field Name	Acc	Default	Description
2 : 0	wf_tia_gain_bit_reg	rw	0x0	
3	wf_tia_gain_bit_dr	rw	0x0	
6 : 4	wf_rxflt_gbit1_reg	rw	0x0	
7	wf_rxflt_gbit1_dr	rw	0x0	
9 : 8	wf_rxflt_gbit2_reg	rw	0x0	
10	wf_rxflt_gbit2_dr	rw	0x0	

41.28 pu_done_reg				0x4034406C
Bits	Field Name	Acc	Default	Description
0	txon_done	ro	0x0	
1	rxon_done	ro	0x0	
2	pllon_done	ro	0x0	

41.29 dig_reserved_reg				0x40344070
Bits	Field Name	Acc	Default	Description

41.30 agc_table_out_reg0				0x40344074
Bits	Field Name	Acc	Default	Description
31 : 0	agc_table_out_0	ro	0x8F925146	

41.31 agc_table_out_reg1				0x40344078
Bits	Field Name	Acc	Default	Description
31 : 0	agc_table_out_1	ro	0x920000C8	

41.32 agc_table_out_reg2				0x4034407C
Bits	Field Name	Acc	Default	Description
31 : 0	agc_table_out_2	ro	0x80808419	

41.33 agc_table_out_reg3				0x40344080
Bits	Field Name	Acc	Default	Description
31 : 0	agc_table_out_3	ro	0xF0	

41.34 apc_table_out_reg0				0x40344084
Bits	Field Name	Acc	Default	Description
31 : 0	apc_table_out_0	ro	0xBC92203F	

41.35 apc_table_out_reg1				0x40344088
Bits	Field Name	Acc	Default	Description
31 : 0	apc_table_out_1	ro	0x4025	

42 sys_ctrl

42.1 chip_id				0x40500000
Bits	Field Name	Acc	Default	Description
15 : 0	CHIP_ID	ro	0x8818	AIC8818 chip ID
23 : 16	METAL_ID	ro	0x0	Metal ID
31 : 24	BOND_ID	ro	0x0	Bonding ID

42.2 aon_clk_sel				0x40500004
Bits	Field Name	Acc	Default	Description
0	cfg_aon_clk_sel_52m_or_div	rw	0x0	1'b0: 80MHz ; 1'b1: 80MHz divider

42.3 aon_clk_mode				0x40500008
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_aon_clk_mode	rw	0xFFFFFFFF	1'b1: manual mode; 1'b0: auto mode

42.4 aon_clk_div				0x4050000C
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_aon_clk_div_denom	rw	0x1	aon clock divider denominator, default div1
8	cfg_aon_clk_div_update	rw	0x0	aon clock divider update

42.5 top_clk_sel				0x40500010
Bits	Field Name	Acc	Default	Description
0	cfg_top_fast_hwen	rw	0x0	1'b0: SW control; 1'b1: power FSM control
1	cfg_top_fast_sel	rw	0x0	1'b0: slow clock; 1'b1: fast clock
2	cfg_top_pll_480m_sel	rw	0x0	1'b0: 480MHz ; 1'b1: 320MHz
3	cfg_top_psram_clk_fast_sel	rw	0x0	1'b0: slow clock; 1'b1: fast clock
4	cfg_top_psram_clk_480m_sel	rw	0x0	1'b0: 480MHz ; 1'b1: 320MHz

42.6 top_hclk_mode				0x40500014
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_top_hclk_mode	rw	0xFF	1'b1: manual mode; 1'b0: auto mode

42.7 top_fclk_mode				0x40500018
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_top_fclk_mode	rw	0xFF	1'b1: manual mode; 1'b0: auto mode

42.8 top_others_clk_mode				0x4050001C
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_top_others_clk_mode	rw	0xFFFF	1'b1: manual mode; 1'b0: auto mode

42.9 hclk_div				0x40500020
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_top_hclk_div_denom	rw	0x1	ahb clock divider denominator, default div1
8	cfg_top_hclk_div_update	rw	0x0	hclk divider update

42.10 fclk_div				0x40500024
Bits	Field Name	Acc	Default	Description
3 : 0	cfg_top_fclk_div_denom	rw	0xD	fast clock divider denominator, default div2
4	cfg_top_fclk_div_update	rw	0x0	fast clock divider update

42.11 psram_clk_div				0x40500028
Bits	Field Name	Acc	Default	Description
3 : 0	cfg_top_psram_clk_div_denom	rw	0xD	psram clock divider denominator, default div2
4	cfg_top_psram_clk_div_update	rw	0x0	psram clk divider update

42.12 cfg_480m_clk_div				0x4050002C
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_top_480m_gen_sel	rw	0x0	clock divider
9 : 8	cfg_top_480m_clk_mode_sel	rw	0x0	mode selector
12	cfg_top_480m_div_update	rw	0x0	real 480M clock divider update

42.13 real_320m_clk_div				0x40500030
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_top_320m_gen_sel	rw	0x0	clock divider
9 : 8	cfg_top_320m_clk_mode_sel	rw	0x0	mode selector
12	cfg_top_320m_div_update	rw	0x0	real 320M clock divider update

42.14 real_480m_clk_div				0x40500034
Bits	Field Name	Acc	Default	Description
3 : 0	cfg_top_real_480m_div_denom	rw	0xF	480M clock divider denominator, default div1
4	cfg_top_real_480m_div_update	rw	0x0	480M clk divider update

42.15 cfg_osc_enable				0x40500038
Bits	Field Name	Acc	Default	Description
0	cfg_top_bt_osc_en	rw	0x0	BT OSC control enable, high active
1	cfg_top_wlan_osc_en	rw	0x0	WLAN OSC control enable, high active
2	cfg_top_bt_osc_manual	rw	0x1	BT OSC manual control, high active
3	cfg_top_wlan_osc_manual	rw	0x1	WLAN OSC manual control, high active
4	cfg_top_wlan_osc_comb_en	rw	0x0	Enable ahb_clk_wifi when comb mode, high active
5	cfg_top_clk_40m_rf_hwen	rw	0x0	1'b0: SW control; 1'b1: wf_rf_en
6	cfg_top_clk_40m_rf_manual	rw	0x1	clk_40m_rf manual enable control, high active.

42.16 reset_cause				0x4050003C
Bits	Field Name	Acc	Default	Description
0	wdg0_rst_happened	ro	0x0	reset happened, high active
1	wdg1_rst_happened	ro	0x0	reset happened, high active
2	wdg2_rst_happened	ro	0x0	reset happened, high active
3	cpu_p_sysrst_req_happened	ro	0x0	reset happened, high active
4	cpu_s0_sysrst_req_happened	ro	0x0	reset happened, high active
5	cpu_s1_sysrst_req_happened	ro	0x0	reset happened, high active
6	global_soft_reset_happened	ro	0x0	reset happened, high active

42.17 tports_sel				0x40500040
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_aon_tports_sel	rw	0x0	aon system test ports select
11 : 8	cfg_top_tports_sel_low	rw	0x0	digitial top test ports low 16-bit selector
15 : 12	cfg_top_tports_sel_high	rw	0x0	digitial top test ports high 16-bit selector

42.18 cpu_p_reset_addr				0x40500044
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_cpu_p_reset_addr	rw	0x0	Main CPU boot address

42.19 cpu_s0_reset_addr				0x40500048
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_cpu_s0_reset_addr	rw	0x10000	Second CPU0 boot address

42.20 cfg_cpu_sys_ctrl				0x4050004C
Bits	Field Name	Acc	Default	Description
3 : 0	cfg_cpu_sys_matrix_remap	rw	0x0	sys matrix remap
4	cfg_cpu_sys_flash_clk_sel	rw	0x0	1'b0: XTAL_2X; 1'b1: fast clock
5	cfg_cpu_sys_uart0_clk_sel	rw	0x0	1'b0: XTAL_2X; 1'b1: fast clock
6	cfg_cpu_sys_uart1_clk_sel	rw	0x0	1'b0: XTAL_2X; 1'b1: fast clock
7	cfg_cpu_sys_uart2_clk_sel	rw	0x0	1'b0: XTAL_2X; 1'b1: fast clock

42.21 cfg_rtc1_pu_dcdc_resetn_bypass				0x40500050
Bits	Field Name	Acc	Default	Description
1	cfg_dcdc_rf_- dcdc_clk_lpo_sel_sw	rw	0x0	
2	cfg_dcdc_rf_dcdc_clk_lpo_sel	rw	0x0	

42.22 cfg_sdio_iomux_sel				0x40500054
Bits	Field Name	Acc	Default	Description
0	cfg_sdio_iomux_bypass_sel	rw	0x1	1'b0: iomux; 1'b1: SDIO function
15 : 1	cfg_gpio_awake_mux_sel	rw	0x20	
17 : 16	cfg_sdio_clk_pulse_bit	rw	0x2	

42.23 cfg_mem_cpu_sys_1pram				0x40500058
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_mem_cpu_sys_1pram	rw	0x24C4	cpu sys 1p sram configuration

42.24 bt_hclk_div				0x4050005C
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_top_bt_hclk_div_denom	rw	0x2	BT ahb clock divider denominator, default div2
8	cfg_top_bt_hclk_div_update	rw	0x0	BT hclk divider update

42.25 top_tports_bits_sel0				0x40500060
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_top_tports_bit_sel0	rw	0x3020100	top tports sel0

42.26 top_tports_bits_sel1				0x40500064
Bits	Field Name	Acc	Default	Description

31 : 0	cfg_top_tports_bit_sel1	rw	0x7060504	top tports sel1

42.27 top_tports_bits_sel2				0x40500068
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_top_tports_bit_sel2	rw	0xB0A0908	top tports sel2

42.28 top_tports_bits_sel3				0x4050006C
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_top_tports_bit_sel3	rw	0xF0E0D0C	top tports sel3

42.29 cpu_s1_reset_addr				0x40500070
Bits	Field Name	Acc	Default	Description
31 : 0	cfg_cpu_s1_reset_addr	rw	0x50000	Second CPU1 boot address

42.30 hclk_manual_enable				0x40500100
Bits	Field Name	Acc	Default	Description
0	hclk_cpu_sys_manual_enable	rw	0x1	write 1 enable manual mode
1	hclk_bt_sys_manual_enable	rw	0x1	write 1 enable manual mode
2	hclk_bt_free_manual_enable	rw	0x1	write 1 enable manual mode
3	hclk_wifi_sys_manual_enable	rw	0x1	write 1 enable manual mode
4	hclk_top_vcore_enable	rw	0x1	write 1 enable manual mode

42.31 hclk_manual_disable				0x40500104
Bits	Field Name	Acc	Default	Description
0	hclk_cpu_sys_manual_disable	rw	0x1	write 1 disable manual mode
1	hclk_bt_sys_manual_disable	rw	0x1	write 1 disable manual mode
2	hclk_bt_free_manual_disable	rw	0x1	write 1 disable manual mode
3	hclk_wifi_sys_manual_disable	rw	0x1	write 1 disable manual mode
4	hclk_top_vcore_manual_disable	rw	0x1	write 1 disable manual mode

42.32 fclk_manual_enable				0x40500108
Bits	Field Name	Acc	Default	Description
0	fclk_cpu_sys_manual_enable	rw	0x1	write 1 enable manual mode

42.33 fclk_manual_disable				0x4050010C
Bits	Field Name	Acc	Default	Description
0	fclk_cpu_sys_manual_disable	rw	0x1	write 1 disable manual mode

42.34 others_manual_enable				0x40500110
Bits	Field Name	Acc	Default	Description
0	clk_26m_cpu_-sys_manual_enable	rw	0x1	write 1 enable manual mode
1	clk_52m_cpu_-sys_manual_enable	rw	0x1	write 1 enable manual mode
2	clk_32k_cpu_-sys_manual_enable	rw	0x1	write 1 enable manual mode
3	clk_26m_bt_sys_manual_enable	rw	0x1	write 1 enable manual mode
4	clk_52m_bt_sys_manual_enable	rw	0x1	write 1 enable manual mode
5	clk_32k_bt_sys_manual_enable	rw	0x1	write 1 enable manual mode
6	clk_26m_wifi_-sys_manual_enable	rw	0x1	write 1 enable manual mode

7	clk_52m_wifi_-sys_manual_enable	rw	0x1	write 1 enable manual mode
8	clk_32k_wifi_-sys_manual_enable	rw	0x1	write 1 enable manual mode
9	clk_flash_manual_enable	rw	0x1	write 1 enable manual mode

42.35 others_manual_disable				0x40500114
Bits	Field Name	Acc	Default	Description
0	clk_26m_cpu_-sys_manual_disable	rw	0x1	write 1 disable manual mode
1	clk_52m_cpu_-sys_manual_disable	rw	0x1	write 1 disable manual mode
2	clk_32k_cpu_-sys_manual_disable	rw	0x1	write 1 disable manual mode
3	clk_26m_bt_s-ys_manual_disable	rw	0x1	write 1 disable manual mode
4	clk_52m_bt_s-ys_manual_disable	rw	0x1	write 1 disable manual mode
5	clk_32k_bt_sys_manual_disable	rw	0x1	write 1 disable manual mode
6	clk_26m_wifi_-sys_manual_disable	rw	0x1	write 1 disable manual mode
7	clk_52m_wifi_-sys_manual_disable	rw	0x1	write 1 disable manual mode
8	clk_32k_wifi_-sys_manual_disable	rw	0x1	write 1 disable manual mode
9	clk_flash_manual_disable	rw	0x1	write 1 disable manual mode

42.36 aon_clk_manual_enable				0x40500118
Bits	Field Name	Acc	Default	Description
0	clk_26m_aon_-sys_manual_enable	rw	0x1	write 1 enable manual mode
1	clk_timer2_manual_enable	rw	0x1	write 1 enable manual mode
2	clk_32k_aon_-sys_manual_enable	rw	0x1	write 1 enable manual mode
3	clk_32k_bt_aon_manual_enable	rw	0x1	write 1 enable manual mode
4	clk_32k_wifi_-aon_manual_enable	rw	0x1	write 1 enable manual mode
5	clk_rtc_wdg2_manual_enable	rw	0x1	write 1 enable manual mode
6	clk_cm_rf_intf_manual_enable	rw	0x1	write 1 enable manual mode
7	clk_pmu_top_manual_enable	rw	0x1	write 1 enable manual mode
8	clk_aon_pwm_manual_enable	rw	0x1	write 1 enable manual mode
9	pclk_sys_ctrl_manual_enable	rw	0x1	write 1 enable manual mode
10	pclk_timer2_manual_enable	rw	0x1	write 1 enable manual mode
11	pclk_analog_r-eg1_manual_enable	rw	0x1	write 1 enable manual mode
12	pclk_psi_mst_manual_enable	rw	0x1	write 1 enable manual mode
13	pclk_iomux_manual_enable	rw	0x1	write 1 enable manual mode
14	pclk_cm_rf_intf_manual_enable	rw	0x1	write 1 enable manual mode
15	pclk_pwr_ctrl_manual_enable	rw	0x1	write 1 enable manual mode
16	pclk_aon_pwm_manual_enable	rw	0x1	write 1 enable manual mode
17	pclk_wdg2_manual_enable	rw	0x1	write 1 enable manual mode
18	pclk_wcn_aon_manual_enable	rw	0x1	write 1 enable manual mode
19	pclk_aon_sys_-ctrl_manual_enable	rw	0x1	write 1 enable manual mode

42.37 aon_clk_manual_disable				0x4050011C
Bits	Field Name	Acc	Default	Description

0	clk_26m_aon_sys_manual_disable	rw	0x1	write 1 disable manual mode
1	clk_timer2_manual_disable	rw	0x1	write 1 disable manual mode
2	clk_32k_aon_sys_manual_disable	rw	0x1	write 1 disable manual mode
3	clk_32k_bt_aon_manual_disable	rw	0x1	write 1 disable manual mode
4	clk_32k_wifi_aon_manual_disable	rw	0x1	write 1 disable manual mode
5	clk_rtc_wdg2_manual_disable	rw	0x1	write 1 disable manual mode
6	clk_cm_rf_intf_manual_disable	rw	0x1	write 1 disable manual mode
7	clk_pmu_top_manual_disable	rw	0x1	write 1 disable manual mode
8	clk_aon_pwm_manual_disable	rw	0x1	write 1 disable manual mode
9	pclk_sys_ctrl_manual_disable	rw	0x1	write 1 disable manual mode
10	pclk_timer2_manual_disable	rw	0x1	write 1 disable manual mode
11	pclk_analog_reg1_manual_disable	rw	0x1	write 1 disable manual mode
12	pclk_psi_mst_manual_disable	rw	0x1	write 1 disable manual mode
13	pclk_iomux_manual_disable	rw	0x1	write 1 disable manual mode
14	pclk_cm_rf_intf_manual_disable	rw	0x1	write 1 disable manual mode
15	pclk_pwr_ctrl_manual_disable	rw	0x1	write 1 disable manual mode
16	pclk_aon_pwm_manual_disable	rw	0x1	write 1 disable manual mode
17	pclk_wdg2_manual_disable	rw	0x1	write 1 disable manual mode
18	pclk_wcn_aon_manual_disable	rw	0x1	write 1 disable manual mode
19	pclk_aon_sys_ctrl_manual_disable	rw	0x1	write 1 disable manual mode

42.38 global_soft_resetn_set				0x40500120
Bits	Field Name	Acc	Default	Description
0	global_soft_resetn_set	rw	0x1	write 1 set soft reset

42.39 global_soft_resetn_clr				0x40500124
Bits	Field Name	Acc	Default	Description
0	global_soft_resetn_clear	rw	0x1	write 1 clear soft reset

42.40 hclk_soft_resetn_set				0x40500128
Bits	Field Name	Acc	Default	Description
0	hresetn_cpu_sys_set	rw	0x1	write 1 set soft reset
1	hresetn_bt_sys_set	rw	0x1	write 1 set soft reset
2	hresetn_bt_free_set	rw	0x1	write 1 set soft reset
3	hresetn_wifi_sys_set	rw	0x1	write 1 set soft reset
4	hresetn_aon_merge_set	rw	0x1	write 1 set soft reset
5	hresetn_cpu_p_set	rw	0x1	write 1 set soft reset
6	hresetn_cpu_s0_set	rw	0x0	write 1 set soft reset
7	hresetn_cpu_s1_set	rw	0x0	write 1 set soft reset

42.41 hclk_soft_resetn_clr				0x4050012C
Bits	Field Name	Acc	Default	Description
0	hresetn_cpu_sys_clear	rw	0x1	write 1 clear soft reset
1	hresetn_bt_sys_clear	rw	0x1	write 1 clear soft reset
2	hresetn_bt_free_clear	rw	0x1	write 1 clear soft reset
3	hresetn_wifi_sys_clear	rw	0x1	write 1 clear soft reset
4	hresetn_aon_merge_clear	rw	0x1	write 1 clear soft reset
5	hresetn_cpu_p_clear	rw	0x1	write 1 clear soft reset

6	hresetn_cpu_s0_clear	rw	0x0	write 1 clear soft reset
7	hresetn_cpu_s1_clear	rw	0x0	write 1 clear soft reset

42.42 fclk_soft_resetn_set				0x40500130
Bits	Field Name	Acc	Default	Description
0	fresetn_cpu_sys_set	rw	0x1	write 1 set soft reset

42.43 fclk_soft_resetn_clr				0x40500134
Bits	Field Name	Acc	Default	Description
0	fresetn_cpu_sys_clear	rw	0x1	write 1 clear soft reset

42.44 others_soft_resetn_set				0x40500138
Bits	Field Name	Acc	Default	Description
0	resetn_26m_cpu_sys_set	rw	0x1	write 1 set soft reset
1	resetn_52m_cpu_sys_set	rw	0x1	write 1 set soft reset
2	resetn_32k_cpu_sys_set	rw	0x1	write 1 set soft reset
3	resetn_26m_bt_sys_set	rw	0x1	write 1 set soft reset
4	resetn_52m_bt_sys_set	rw	0x1	write 1 set soft reset
5	resetn_32k_bt_sys_set	rw	0x1	write 1 set soft reset
6	resetn_32k_wifi_sys_set	rw	0x1	write 1 set soft reset
14	resetn_bt_sys_set	rw	0x1	write 1 set soft reset
15	resetn_wifi_sys_set	rw	0x1	write 1 set soft reset

42.45 others_soft_resetn_clr				0x4050013C
Bits	Field Name	Acc	Default	Description
0	resetn_26m_cpu_sys_clear	rw	0x1	write 1 clear soft reset
1	resetn_52m_cpu_sys_clear	rw	0x1	write 1 clear soft reset
2	resetn_32k_cpu_sys_clear	rw	0x1	write 1 clear soft reset
3	resetn_26m_bt_sys_clear	rw	0x1	write 1 clear soft reset
4	resetn_52m_bt_sys_clear	rw	0x1	write 1 clear soft reset
5	resetn_32k_bt_sys_clear	rw	0x1	write 1 clear soft reset
6	resetn_32k_wifi_sys_clear	rw	0x1	write 1 clear soft reset
14	resetn_bt_sys_clear	rw	0x1	write 1 clear soft reset
15	resetn_wifi_sys_clear	rw	0x1	write 1 clear soft reset

42.46 aon_soft_resetn_set				0x40500140
Bits	Field Name	Acc	Default	Description
0	resetn_26m_aon_sys_set	rw	0x1	write 1 set soft reset
1	resetn_timer2_set	rw	0x1	write 1 set soft reset
2	resetn_32k_aon_sys_set	rw	0x1	write 1 set soft reset
3	resetn_32k_bt_aon_set	rw	0x0	write 1 set soft reset
4	resetn_32k_wifi_aon_set	rw	0x0	write 1 set soft reset
5	resetn_rtc_wdg2_set	rw	0x1	write 1 set soft reset
6	resetn_cm_rf_intf_set	rw	0x1	write 1 set soft reset
7	resetn_pmu_top_set	rw	0x1	write 1 set soft reset
8	resetn_aon_pwm_set	rw	0x1	write 1 set soft reset
9	resetn_pwr_ctrl_set	rw	0x1	write 1 set soft reset
10	presetn_pmu_psi_slv_set	rw	0x1	write 1 set soft reset
11	presetn_sys_ctrl_set	rw	0x1	write 1 set soft reset
12	presetn_timer2_set	rw	0x1	write 1 set soft reset
13	presetn_analog_reg1_set	rw	0x1	write 1 set soft reset
14	presetn_psi_mst_set	rw	0x1	write 1 set soft reset
15	presetn_iomux_set	rw	0x0	write 1 set soft reset

16	presetn_cm_rf_intf_set	rw	0x1	write 1 set soft reset
17	presetn_pwr_ctrl_set	rw	0x1	write 1 set soft reset
18	presetn_aon_pwm_set	rw	0x1	write 1 set soft reset
19	presetn_wdg2_set	rw	0x1	write 1 set soft reset
20	presetn_wcn_aon_set	rw	0x1	write 1 set soft reset
21	presetn_aon_sys_ctrl_set	rw	0x1	write 1 set soft reset
31	resetn_wcn_aon_set	rw	0x1	write 1 set soft reset

42.47 aon_soft_resetn_clr				0x40500144
Bits	Field Name	Acc	Default	Description
0	resetn_26m_aon_sys_clear	rw	0x1	write 1 clear soft reset
1	resetn_timer2_clear	rw	0x1	write 1 clear soft reset
2	resetn_32k_aon_sys_clear	rw	0x1	write 1 clear soft reset
3	resetn_32k_bt_aon_clear	rw	0x0	write 1 clear soft reset
4	resetn_32k_wifi_aon_clear	rw	0x0	write 1 clear soft reset
5	resetn_rtc_wdg2_clear	rw	0x1	write 1 clear soft reset
6	resetn_cm_rf_intf_clear	rw	0x1	write 1 clear soft reset
7	resetn_pmu_top_clear	rw	0x1	write 1 clear soft reset
8	resetn_aon_pwm_clear	rw	0x1	write 1 clear soft reset
9	resetn_pwr_ctrl_clear	rw	0x1	write 1 clear soft reset
10	presetn_pmu_psi_slv_clear	rw	0x1	write 1 clear soft reset
11	presetn_sys_ctrl_clear	rw	0x1	write 1 clear soft reset
12	presetn_timer2_clear	rw	0x1	write 1 clear soft reset
13	presetn_analog_reg1_clear	rw	0x1	write 1 clear soft reset
14	presetn_psi_mst_clear	rw	0x1	write 1 clear soft reset
15	presetn_iomux_clear	rw	0x0	write 1 clear soft reset
16	presetn_cm_rf_intf_clear	rw	0x1	write 1 clear soft reset
17	presetn_pwr_ctrl_clear	rw	0x1	write 1 clear soft reset
18	presetn_aon_pwm_clear	rw	0x1	write 1 clear soft reset
19	presetn_wdg2_clear	rw	0x1	write 1 clear soft reset
20	presetn_wcn_aon_clear	rw	0x1	write 1 clear soft reset
21	presetn_aon_sys_ctrl_clear	rw	0x1	write 1 clear soft reset
31	resetn_wcn_aon_clear	rw	0x1	

42.48 boot_mode				0x40500148
Bits	Field Name	Acc	Default	Description
3 : 0	hw_boot_mode	rw	0x0	hardware boot pins
7 : 4	sw_boot_mode	rw	0x0	softeware boot mode

42.49 wdg_reset_en				0x4050014C
Bits	Field Name	Acc	Default	Description
0	wdg0_rst_en	rw	0x0	watchdog0 reset enable, high active
1	wdg1_rst_en	rw	0x0	watchdog1 reset enable, high active
2	wdg2_rst_en	rw	0x0	watchdog2 reset enable, high active
3	cpu_p_sysrst_en	rw	0x0	CPU_P system reset enable, high active
4	cpu_s0_sysrst_en	rw	0x0	CPU_S0 system reset enable, high active
5	cpu_s1_sysrst_en	rw	0x0	CPU_S1 system reset enable, high active

42.50 reserved_reg0				0x40500150
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg0	rw	0x0	SW reserved register 0

42.51 reserved_reg1	0x40500154

Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg1	rw	0x0	SW reserved register 1

42.52 reserved_reg2				0x40500158
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg2	rw	0x0	SW reserved register 2

42.53 reserved_reg3				0x4050015C
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg3	rw	0x0	SW reserved register 3

42.54 reserved_reg4				0x40500160
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg4	rw	0x0	SW reserved register 4

42.55 reserved_reg5				0x40500164
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg5	rw	0x0	SW reserved register 5

42.56 reserved_reg6				0x40500168
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg6	rw	0x0	SW reserved register 6

42.57 reserved_reg7				0x4050016C
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg7	rw	0x0	SW reserved register 7

42.58 reserved_reg8				0x40500170
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg8	rw	0x0	SW reserved register 8

42.59 reserved_reg9				0x40500174
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg9	rw	0x0	SW reserved register 9

42.60 reserved_reg10				0x40500178
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg10	rw	0x0	SW reserved register 10

42.61 reserved_reg11				0x4050017C
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg11	rw	0x0	SW reserved register 11

42.62 reserved_reg12				0x40500180
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg12	rw	0x0	SW reserved register 12

42.63 reserved_reg13				0x40500184
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg13	rw	0x0	SW reserved register 13

42.64 reserved_reg14				0x40500188
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg14	rw	0x0	SW reserved register 14

42.65 reserved_reg15				0x4050018C
Bits	Field Name	Acc	Default	Description
31 : 0	sw_res_reg15	rw	0x0	SW reserved register 15

43 timer2

43.1 TIMER0_CTL				0x40501000
Bits	Field Name	Acc	Default	Description
0	timer0_en	rw	0x0	timer0 enable
1	timer0_reset	rw	0x0	timer0 reset, active high, cleared automatically. When one, the Timer Counter is synchronously reset on the next positive edge of PCLK.
3	timer0_tick_div_bypass	ro	0x0	1, bypass tick divider, TIMER0_TICK_DIV register does not exist. 0, tick divider exists.
7 : 4	timer0_tc_hi_dis	rw	0x0	1, the High 16bit of TC and MR is ignored when generating match/wrap interrupt. 0, this feature is ignored.
9 : 8	timer0_tick_freq	rw	0x1	timer0 tick frequency, used to select TC and adjust counter increment value. 2'b00: tick is 64KHz 2'b01: tick is 64KHz 2'b10: tick is 32KHz 2'b11: tick is 16KHz
12	timer0_match0_en	rw	0x0	1, match0 enable. 0, match0 disable.
13	timer0_match1_en	rw	0x0	1, match1 enable. 0, match1 disable.
14	timer0_match2_en	rw	0x0	1, match2 enable. 0, match2 disable.
15	timer0_match3_en	rw	0x0	1, match3 enable. 0, match3 disable.

43.2 TIMER0_TICK_DIV				0x40501004
Bits	Field Name	Acc	Default	Description
1 : 0	timer0_tick_div	rw	0x1	timer0 tick div value 2'b00: disable tick 2'b01: tick is div2 from rtc clock 2'b10: tick is div4 from rtc clock 2'b11: tick is div8 from rtc clock
4	timer0_tick_div_up	wo	0x0	timer0 tick div value update, cleared automatically

43.3 TIMER0_INT_CTRL				0x40501008
Bits	Field Name	Acc	Default	Description

0	timer0_match0_int_en_set	rw	0x0	Write: timer0 match0 interrupt enable set 1: Set Enable. An interrupt is generated when MR0 matches the value in the TC. 0: Ignored. Read: timer0 match0 interrupt enabled 1: Enalbed. An interrupt is generated when MR0 matches the value in the TC. 0: not Enabled.
1	timer0_match1_int_en_set	rw	0x0	Write: timer0 match1 interrupt enable set 1: Set Enable. An interrupt is generated when MR1 matches the value in the TC. 0: Ignored. Read: timer0 match1 interrupt enabled 1: Enalbed. An interrupt is generated when MR1 matches the value in the TC. 0: not Enabled.
2	timer0_match2_int_en_set	rw	0x0	Write: timer0 match2 interrupt enable set 1: Set Enable. An interrupt is generated when MR2 matches the value in the TC. 0: Ignored. Read: timer0 match2 interrupt enabled 1: Enalbed. An interrupt is generated when MR2 matches the value in the TC. 0: not Enabled.
3	timer0_match3_int_en_set	rw	0x0	Write: timer0 match3 interrupt enable set 1: Set Enable. An interrupt is generated when MR3 matches the value in the TC. 0: Ignored. Read: timer0 match3 interrupt enabled 1: Enalbed. An interrupt is generated when MR3 matches the value in the TC. 0: not Enabled.
4	timer0_wrap0_int_en_set	rw	0x0	Write: timer0 wrap0 interrupt enable set 1: Set Enable. An interrupt is generated when TC count from all1 to 0x0. 0: Ignored. Read: timer0 wrap0 interrupt enabled 1: Enalbed. An interrupt is generated when TC count from all1 to 0x0. 0: not Enabled.
5	timer0_wrap1_int_en_set	rw	0x0	Write: timer0 wrap1 interrupt enable set 1: Set Enable. An interrupt is generated when TC count from all1 to 0x0. 0: Ignored. Read: timer0 wrap1 interrupt enabled 1: Enalbed. An interrupt is generated when TC count from all1 to 0x0. 0: not Enabled.
6	timer0_wrap2_int_en_set	rw	0x0	Write: timer0 wrap2 interrupt enable set 1: Set Enable. An interrupt is generated when TC count from all1 to 0x0. 0: Ignored. Read: timer0 wrap2 interrupt enabled 1: Enalbed. An interrupt is generated when TC count from all1 to 0x0. 0: not Enabled.
7	timer0_wrap3_int_en_set	rw	0x0	Write: timer0 wrap3 interrupt enable set 1: Set Enable. An interrupt is generated when TC count from all1 to 0x0. 0: Ignored. Read: timer0 wrap3 interrupt enabled 1: Enalbed. An interrupt is generated when TC count from all1 to 0x0. 0: not Enabled.
8	timer0_match0_int_en_clr	wo	0x0	Timer0 match0 interrupt enable clear 1: Clear Enable. 0: Ignored.
9	timer0_match1_int_en_clr	wo	0x0	Timer0 match1 interrupt enable clear 1: Clear Enable. 0: Ignored.

10	timer0_match2_int_en_clr	wo	0x0	Timer0 match2 interrupt enable clear 1: Clear Enable. 0: Ignored.
11	timer0_match3_int_en_clr	wo	0x0	Timer0 match3 interrupt enable clear 1: Clear Enable. 0: Ignored.
12	timer0_wrap0_int_en_clr	wo	0x0	Timer0 wrap0 interrupt enable clear 1: Clear Enable. An interrupt is generated when TC count from all1 to 0x0. 0: Ignored.
13	timer0_wrap1_int_en_clr	wo	0x0	Timer0 wrap1 interrupt enable clear 1: Clear Enable. An interrupt is generated when TC count from all1 to 0x0. 0: Ignored.
14	timer0_wrap2_int_en_clr	wo	0x0	Timer0 wrap2 interrupt enable clear 1: Clear Enable. An interrupt is generated when TC count from all1 to 0x0. 0: Ignored.
15	timer0_wrap3_int_en_clr	wo	0x0	Timer0 wrap3 interrupt enable clear 1: Clear Enable. An interrupt is generated when TC count from all1 to 0x0. 0: Ignored.
16	timer0_match0_int_clr	wo	0x0	timer0 match0 interrupt clear, active high
17	timer0_match1_int_clr	wo	0x0	timer0 match1 interrupt clear, active high
18	timer0_match2_int_clr	wo	0x0	timer0 match2 interrupt clear, active high
19	timer0_match3_int_clr	wo	0x0	timer0 match3 interrupt clear, active high
20	timer0_wrap0_int_clr	wo	0x0	timer0 wrap0 interrupt clear
21	timer0_wrap1_int_clr	wo	0x0	timer0 wrap1 interrupt clear
22	timer0_wrap2_int_clr	wo	0x0	timer0 wrap2 interrupt clear
23	timer0_wrap3_int_clr	wo	0x0	timer0 wrap3 interrupt clear

43.4 TIMER0_INT_STATUS				0x4050100C
Bits	Field Name	Acc	Default	Description
0	timer0_match0_int_raw_status	ro	0x0	timer0 match0 interrupt raw status
1	timer0_match1_int_raw_status	ro	0x0	timer0 match1 interrupt raw status
2	timer0_match2_int_raw_status	ro	0x0	timer0 match2 interrupt raw status
3	timer0_match3_int_raw_status	ro	0x0	timer0 match3 interrupt raw status
4	timer0_wrap0_int_raw_status	ro	0x0	timer0 wrap0 interrupt raw status
5	timer0_wrap1_int_raw_status	ro	0x0	timer0 wrap1 interrupt raw status
6	timer0_wrap2_int_raw_status	ro	0x0	timer0 wrap2 interrupt raw status
7	timer0_wrap3_int_raw_status	ro	0x0	timer0 wrap3 interrupt raw status
8	timer0_match0_- int_masked_status	ro	0x0	timer0 match0 interrupt masked status
9	timer0_match1_- int_masked_status	ro	0x0	timer0 match1 interrupt masked status
10	timer0_match2_- int_masked_status	ro	0x0	timer0 match2 interrupt masked status
11	timer0_match3_- int_masked_status	ro	0x0	timer0 match3 interrupt masked status
12	timer0_wrap0_- int_masked_status	ro	0x0	timer0 wrap0 interrupt masked status
13	timer0_wrap1_- int_masked_status	ro	0x0	timer0 wrap1 interrupt masked status
14	timer0_wrap2_- int_masked_status	ro	0x0	timer0 wrap2 interrupt masked status
15	timer0_wrap3_- int_masked_status	ro	0x0	timer0 wrap3 interrupt masked status

43.5 TIMER0_TC_LO				0x40501010
Bits	Field Name	Acc	Default	Description
31 : 0	timer0_tc_lo	rw	0x0	timer0 counter low 32bit The 48-bit TC, unit is 1us.

43.6 TIMER0_TC_HI				0x40501014
Bits	Field Name	Acc	Default	Description
15 : 0	timer0_tc_hi	rw	0x0	timer0 counter high 16bit The 48-bit TC, unit is 1us. Make sure that this high 16bit written before the low 16bit if initialized.

43.7 TIMER0_MR0_LO				0x40501020
Bits	Field Name	Acc	Default	Description
31 : 0	timer0_mr0_lo	rw	0xFFFFFFFF	timer0 match0 register, low 32bit MR0 can be enabled ot generate an interrupt every time MR0 matches the TC

43.8 TIMER0_MR0_HI				0x40501024
Bits	Field Name	Acc	Default	Description
15 : 0	timer0_mr0_hi	rw	0x0	timer0 match0 register, high 16bit MR0 can be enabled to generate an interrupt every time MR0 matches the TC Make sure that this high 16bit configured before the low 16bit.

43.9 TIMER0_MR1_LO				0x40501028
Bits	Field Name	Acc	Default	Description
31 : 0	timer0_mr1_lo	rw	0xFFFFFFFF	timer0 match1 register, low 32bit MR1 can be enabled ot generate an interrupt every time MR1 matches the TC

43.10 TIMER0_MR1_HI				0x4050102C
Bits	Field Name	Acc	Default	Description
15 : 0	timer0_mr1_hi	rw	0x0	timer0 match1 register, high 16bit MR1 can be enabled to generate an interrupt every time MR1 matches the TC Make sure that this high 16bit configured before the low 16bit.

43.11 TIMER0_MR2_LO				0x40501030
Bits	Field Name	Acc	Default	Description
31 : 0	timer0_mr2_lo	rw	0xFFFFFFFF	timer0 match2 register, low 32bit MR2 can be enabled ot generate an interrupt every time MR2 matches the TC

43.12 TIMER0_MR2_HI				0x40501034
Bits	Field Name	Acc	Default	Description
15 : 0	timer0_mr2_hi	rw	0x0	timer0 match2 register, high 16bit MR2 can be enabled to generate an interrupt every time MR2 matches the TC Make sure that this high 16bit configured before the low 16bit.

43.13 TIMER0_MR3_LO				0x40501038
Bits	Field Name	Acc	Default	Description
31 : 0	timer0_mr3_lo	rw	0xFFFFFFFF	timer0 match3 register, low 32bit MR3 can be enabled ot generate an interrupt every time MR3 matches the TC

43.14 TIMER0_MR3_HI				0x4050103C
Bits	Field Name	Acc	Default	Description
15 : 0	timer0_mr3_hi	rw	0x0	timer0 match3 register, high 16bit MR3 can be enabled to generate an interrupt every time MR3 matches the TC Make sure that this high 16bit configured before the low 16bit.

44 ana_reg1

44.1 gpioa_ibit				0x40502000
Bits	Field Name	Acc	Default	Description
2 : 0	cfg_ana_gpioa_ibit	rw	0x3	GPIOA drive strength
31 : 16	cfg_ana_gpioa-_wakeup_polarity	rw	0x0	

44.2 gpioa_slew_rate				0x40502004
Bits	Field Name	Acc	Default	Description
5 : 0	cfg_ana_gpioa_slew_rate	rw	0x3F	GPIOA slew rate selection

44.3 gpioa_ie				0x40502008
Bits	Field Name	Acc	Default	Description
1 : 0	cfg_ana_gpioa_ie	rw	0x3	GPIOA IE
18 : 16	cfg_ana_gpioa_pull_up_sel	rw	0x0	

44.4 gpiob_ibit				0x4050200C
Bits	Field Name	Acc	Default	Description
0	cfg_ana_gpiob_ibit	rw	0x1	GPIOB drive strength
31 : 28	cfg_ana_gpiob-_wakeup_polarity	rw	0x0	

44.5 gpiob_slew_rata				0x40502010
Bits	Field Name	Acc	Default	Description
1 : 0	cfg_ana_gpiob_slew_rate	rw	0x3	GPIOB slew rate

44.6 gpiob_ie				0x40502014
Bits	Field Name	Acc	Default	Description
0	cfg_ana_gpiob_ie	rw	0x1	GPIOB IE
16	cfg_ana_gpiob_pull_up_sel	rw	0x0	
17	cfg_ana_gpiob_mux_enb	rw	0x1	
18	cfg_ana_gpiob_mux_en	rw	0x0	

44.7 ana_port_ctrl				0x40502018
Bits	Field Name	Acc	Default	Description
3 : 0	cfg_ana_test_bit	rw	0x0	
4	cfg_ana_test_enable_usb	rw	0x0	
5	cfg_ana_io_i-ref_current_start_enb	rw	0x1	
6	cfg_ana_test_enable_iref_io	rw	0x0	
7	cfg_ana_testPort_iq_enb	rw	0x1	
8	cfg_ana_testPort_iq_en	rw	0x0	
9	cfg_ana_pu_iref_io	rw	0x0	

11	cfg_ana_gpio_- vio13_sleep_mode	rw	0x0	
12	cfg_ana_io_test_enable_bbpll	rw	0x0	

44.8 misc_reg				0x4050201C
Bits	Field Name	Acc	Default	Description
7 : 0	cfg_ana_io_rsvd_bit	rw	0xF0	analog reserved bits
12	pmu_psi_slv_- rdata_wait_timeout_err	ro	0x0	
20 : 13	psi_mst_sig_event	rw	0x0	
24 : 21	cfg_ana_rsvd_bit_core	rw	0xC	
25	cfg_bt_bbpll_auto_pu	rw	0x0	

44.9 flash_ctrl				0x40502020
Bits	Field Name	Acc	Default	Description
0	cfg_ana_fls_ie	rw	0x1	
1	cfg_ana_fls_ibit	rw	0x1	
2	cfg_ana_fls_pull_up_sel	rw	0x1	
4 : 3	cfg_ana_fls_slew_rate	rw	0x3	
5	cfg_ana_fls_ms	rw	0x0	

45 psi_mst

45.1 ip_revision				0x40503000
Bits	Field Name	Acc	Default	Description
15 : 0	ip_revision	ro	0x200	revision id

45.2 psi_mst_ctrl				0x40503004
Bits	Field Name	Acc	Default	Description
0	write_bit	rw	0x0	write bit flag configure

45.3 psi_mst_pri00				0x40503008
Bits	Field Name	Acc	Default	Description
2 : 0	chnl0_pri	rw	0x0	
5 : 3	chnl1_pri	rw	0x0	
8 : 6	chnl2_pri	rw	0x0	
11 : 9	chnl3_pri	rw	0x0	
14 : 12	chnl4_pri	rw	0x0	
17 : 15	chnl5_pri	rw	0x0	

45.4 psi_mst_pri10				0x4050300C
Bits	Field Name	Acc	Default	Description
2 : 0	chnl10_pri	rw	0x0	
5 : 3	chnl11_pri	rw	0x0	
8 : 6	chnl12_pri	rw	0x0	
11 : 9	chnl13_pri	rw	0x0	

45.5 psi_mst_pri20				0x40503010
Bits	Field Name	Acc	Default	Description
2 : 0	chnl20_pri	rw	0x0	
5 : 3	chnl21_pri	rw	0x0	

8 : 6	chnl22_pri	rw	0x0	
11 : 9	chnl23_pri	rw	0x0	
14 : 12	chnl24_pri	rw	0x0	
17 : 15	chnl25_pri	rw	0x0	
20 : 18	chnl26_pri	rw	0x0	
23 : 21	chnl27_pri	rw	0x0	

45.6 psi_mst_pri30				0x40503014
Bits	Field Name	Acc	Default	Description

45.7 psi_mst_int_en				0x40503018
Bits	Field Name	Acc	Default	Description
0	evt0_fifo_ovf_int_en	rw	0x0	
1	evt1_fifo_ovf_int_en	rw	0x0	
2	evt2_fifo_ovf_int_en	rw	0x0	
3	evt3_fifo_ovf_int_en	rw	0x0	
4	rx_ssc_timeout_err_int_en	rw	0x0	
31	psi_fifo_ovf_int_en	rw	0x0	

45.8 psi_mst_raw_status				0x4050301C
Bits	Field Name	Acc	Default	Description
0	evt0_fifo_ovf_raw_sts	ro	0x0	
1	evt1_fifo_ovf_raw_sts	ro	0x0	
2	evt2_fifo_ovf_raw_sts	ro	0x0	
3	evt3_fifo_ovf_raw_sts	ro	0x0	
4	rx_ssc_timeout_err_raw_sts	ro	0x0	
31	psi_fifo_ovf_raw_sts	ro	0x0	

45.9 psi_mst_mask_status				0x40503020
Bits	Field Name	Acc	Default	Description
0	evt0_fifo_ovf_mask_sts	ro	0x0	
1	evt1_fifo_ovf_mask_sts	ro	0x0	
2	evt2_fifo_ovf_mask_sts	ro	0x0	
3	evt3_fifo_ovf_mask_sts	ro	0x0	
4	rx_ssc_timeout_err_mask_sts	ro	0x0	
31	psi_fifo_ovf_mask_sts	ro	0x0	

45.10 psi_mst_int_clr				0x40503024
Bits	Field Name	Acc	Default	Description
0	evt0_fifo_ovf_int_clr	w1c	0x0	
1	evt1_fifo_ovf_int_clr	w1c	0x0	
2	evt2_fifo_ovf_int_clr	w1c	0x0	
3	evt3_fifo_ovf_int_clr	w1c	0x0	
4	rx_ssc_timeout_err_int_clr	w1c	0x0	
31	psi_fifo_ovf_int_clr	w1c	0x0	

45.11 psi_gssi_cfg0				0x40503028
Bits	Field Name	Acc	Default	Description
6 : 0	rf_gssi_frame_len	rw	0x7	
12 : 7	rf_gssi_cmd_len	rw	0x6	
18 : 13	rf_gssi_data_len	rw	0x6	
24 : 19	rf_gssi_wr_pos	rw	0x6	

25	rf_gssi_wr_pol	rw	0x0	
26	rf_gssi_sck_rev	rw	0x0	
27	rf_gssi_oe_cfg	rw	0x0	
28	rf_gssi_ie_cfg	rw	0x0	
29	rf_gssi_dummy_clk_en	rw	0x1	
30	rf_gssi_fast_mode	rw	0x0	
31	rf_gssi_sck_all_on	rw	0x0	

45.12 psi_gssi_cfg1				0x4050302C
Bits	Field Name	Acc	Default	Description
0	rf_gssi_ng_tx	rw	0x1	
1	rf_gssi_ng_rx	rw	0x1	
9 : 2	rf_gssi_clk_div	rw	0x1	
15 : 10	rf_gssi_wbp_len	rw	0x8	
19 : 16	rf_gssi_dummy_len	rw	0x4	
20	rf_gssi_sample_dly	rw	0x0	
21	rf_gssi_wr_disable	rw	0x0	
22	rf_gssi_rx_ssc_mode	rw	0x1	1: wait rx sync mode , 0: wait fix ssc len mode
25 : 23	rf_gssi_rbp_len	rw	0x0	

45.13 psi_arm_rd_cmd_addr				0x40503030
Bits	Field Name	Acc	Default	Description
0	psi_busy	ro	0x0	
30 : 1	psi_arm_rd_cmd_addr	ro	0x0	
31	psi_arm_rd_req	ro	0x0	

45.14 psi_arm_rd_cmd_data				0x40503034
Bits	Field Name	Acc	Default	Description
31 : 0	psi_arm_rd_cmd_data	ro	0x0	

45.15 psi_arm_debug0				0x40503038
Bits	Field Name	Acc	Default	Description
2 : 0	fifo_wptr	ro	0x0	
6 : 4	fifo_rptr	ro	0x0	
10	fifo_empty_r	ro	0x0	
11	fifo_full_w	ro	0x0	

45.16 psi_arm_debug1				0x4050303C
Bits	Field Name	Acc	Default	Description
5 : 0	psi_sel	ro	0x0	
6	psi_trans_req_pending	ro	0x0	
11 : 9	current_state	ro	0x0	
16 : 13	st_gssi	ro	0x0	

45.17 psi_arm_debug2				0x40503040
Bits	Field Name	Acc	Default	Description
0	evt0_fifo_ovf_req	ro	0x0	
1	evt0_fifo_empty	ro	0x0	
3 : 2	evt0_fifo_rptr	ro	0x0	
5 : 4	evt0_fifo_wptr	ro	0x0	
8	evt1_fifo_ovf_req	ro	0x0	
9	evt1_fifo_empty	ro	0x0	

11 : 10	evt1_fifo_rptr	ro	0x0	
13 : 12	evt1_fifo_wptr	ro	0x0	
16	evt2_fifo_ovf_req	ro	0x0	
17	evt2_fifo_empty	ro	0x0	
19 : 18	evt2_fifo_rptr	ro	0x0	
21 : 20	evt2_fifo_wptr	ro	0x0	
24	evt3_fifo_ovf_req	ro	0x0	
25	evt3_fifo_empty	ro	0x0	
27 : 26	evt3_fifo_rptr	ro	0x0	
29 : 28	evt3_fifo_wptr	ro	0x0	

45.18 psi_cmd_status				0x40503044
Bits	Field Name	Acc	Default	Description
0	arm_wr_req	ro	0x0	
1	arm_rd_req	ro	0x0	
2	chnl2_req	ro	0x0	
3	chnl3_req	ro	0x0	
4	chnl4_req	ro	0x0	
5	chnl5_req	ro	0x0	
10	chnl10_req	ro	0x0	
11	chnl11_req	ro	0x0	
12	chnl12_req	ro	0x0	
13	chnl13_req	ro	0x0	
20	chnl20_req	ro	0x0	
21	chnl21_req	ro	0x0	
22	chnl22_req	ro	0x0	
23	chnl23_req	ro	0x0	
24	chnl24_req	ro	0x0	
25	chnl25_req	ro	0x0	
26	chnl26_req	ro	0x0	
27	chnl27_req	ro	0x0	

45.19 psi_chnl_en				0x40503048
Bits	Field Name	Acc	Default	Description
2	chnl2_trans_en	rw	0x0	
3	chnl3_trans_en	rw	0x0	
4	chnl4_trans_en	rw	0x0	
5	chnl5_trans_en	rw	0x0	
10	chnl10_trans_en	rw	0x0	
11	chnl11_trans_en	rw	0x0	
12	chnl12_trans_en	rw	0x0	
13	chnl13_trans_en	rw	0x0	
20	chnl20_trans_en	rw	0x0	
21	chnl21_trans_en	rw	0x0	
22	chnl22_trans_en	rw	0x0	
23	chnl23_trans_en	rw	0x0	
24	chnl24_trans_en	rw	0x0	
25	chnl25_trans_en	rw	0x0	
26	chnl26_trans_en	rw	0x0	
27	chnl27_trans_en	rw	0x0	

45.20 chnl2_wr_addr				0x4050304C
Bits	Field Name	Acc	Default	Description
31 : 0	chnl2_waddr	rw	0x0	

45.21 chnl3_wr_addr				0x40503050
Bits	Field Name	Acc	Default	Description
31 : 0	chnl3_waddr	rw	0x0	

45.22 chnl4_wr_addr				0x40503054
Bits	Field Name	Acc	Default	Description
31 : 0	chnl4_waddr	rw	0x0	

45.23 chnl5_wr_addr				0x40503058
Bits	Field Name	Acc	Default	Description
31 : 0	chnl5_waddr	rw	0x0	

45.24 chnl10_wr_addr				0x4050306C
Bits	Field Name	Acc	Default	Description
31 : 0	chnl10_waddr	rw	0x0	

45.25 chnl11_wr_addr				0x40503070
Bits	Field Name	Acc	Default	Description
31 : 0	chnl11_waddr	rw	0x0	

45.26 chnl12_wr_addr				0x40503074
Bits	Field Name	Acc	Default	Description
31 : 0	chnl12_waddr	rw	0x0	

45.27 chnl13_wr_addr				0x40503078
Bits	Field Name	Acc	Default	Description
31 : 0	chnl13_waddr	rw	0x0	

45.28 chnl20_wr_addr				0x40503094
Bits	Field Name	Acc	Default	Description
31 : 0	chnl20_waddr	rw	0x0	

45.29 chnl21_wr_addr				0x40503098
Bits	Field Name	Acc	Default	Description
31 : 0	chnl21_waddr	rw	0x0	

45.30 chnl22_wr_addr				0x4050309C
Bits	Field Name	Acc	Default	Description
31 : 0	chnl22_waddr	rw	0x0	

45.31 chnl23_wr_addr				0x405030A0
Bits	Field Name	Acc	Default	Description
31 : 0	chnl23_waddr	rw	0x0	

45.32 chnl24_wr_addr				0x405030A4
Bits	Field Name	Acc	Default	Description
31 : 0	chnl24_waddr	rw	0x0	

45.33 chnl25_wr_addr				0x405030A8
Bits	Field Name	Acc	Default	Description
31 : 0	chnl25_waddr	rw	0x0	

45.34 chnl26_wr_addr				0x405030AC
Bits	Field Name	Acc	Default	Description
31 : 0	chnl26_waddr	rw	0x0	

45.35 chnl27_wr_addr				0x405030B0
Bits	Field Name	Acc	Default	Description
31 : 0	chnl27_waddr	rw	0x0	

45.36 chnl2_wr_low_data				0x40503140
Bits	Field Name	Acc	Default	Description
31 : 0	chnl2_wr_low_data	rw	0x0	

45.37 chnl2_wr_high_data				0x40503144
Bits	Field Name	Acc	Default	Description
31 : 0	chnl2_wr_high_data	rw	0x0	

45.38 chnl3_wr_low_data				0x40503148
Bits	Field Name	Acc	Default	Description
31 : 0	chnl3_wr_low_data	rw	0x0	

45.39 chnl3_wr_high_data				0x4050314C
Bits	Field Name	Acc	Default	Description
31 : 0	chnl3_wr_high_data	rw	0x0	

45.40 chnl4_wr_low_data				0x40503150
Bits	Field Name	Acc	Default	Description
31 : 0	chnl4_wr_low_data	rw	0x0	

45.41 chnl4_wr_high_data				0x40503154
Bits	Field Name	Acc	Default	Description
31 : 0	chnl4_wr_high_data	rw	0x0	

45.42 chnl5_wr_low_data				0x40503158
Bits	Field Name	Acc	Default	Description
31 : 0	chnl5_wr_low_data	rw	0x0	

45.43 chnl5_wr_high_data				0x4050315C
Bits	Field Name	Acc	Default	Description
31 : 0	chnl5_wr_high_data	rw	0x0	

45.44 chnl10_wr_low_data				0x40503180
Bits	Field Name	Acc	Default	Description
31 : 0	chnl10_wr_low_data	rw	0x0	

45.45 chnl10_wr_high_data				0x40503184
Bits	Field Name	Acc	Default	Description
31 : 0	chnl10_wr_high_data	rw	0x0	

45.46 chnl11_wr_low_data				0x40503188
Bits	Field Name	Acc	Default	Description
31 : 0	chnl11_wr_low_data	rw	0x0	

45.47 chnl11_wr_high_data				0x4050318C
Bits	Field Name	Acc	Default	Description
31 : 0	chnl11_wr_high_data	rw	0x0	

45.48 chnl12_wr_low_data				0x40503190
Bits	Field Name	Acc	Default	Description
31 : 0	chnl12_wr_low_data	rw	0x0	

45.49 chnl12_wr_high_data				0x40503194
Bits	Field Name	Acc	Default	Description
31 : 0	chnl12_wr_high_data	rw	0x0	

45.50 chnl13_wr_low_data				0x40503198
Bits	Field Name	Acc	Default	Description
31 : 0	chnl13_wr_low_data	rw	0x0	

45.51 chnl13_wr_high_data				0x4050319C
Bits	Field Name	Acc	Default	Description
31 : 0	chnl13_wr_high_data	rw	0x0	

45.52 evt_trg_cfg00				0x405031C0
Bits	Field Name	Acc	Default	Description
1 : 0	evt0_fifo_trg_cfg	rw	0x0	
3 : 2	evt1_fifo_trg_cfg	rw	0x0	
5 : 4	evt2_fifo_trg_cfg	rw	0x0	
7 : 6	evt3_fifo_trg_cfg	rw	0x0	

45.53 evt_trg_cfg10				0x405031C4
Bits	Field Name	Acc	Default	Description
1 : 0	evt10_nofifo_trg_cfg	rw	0x0	
3 : 2	evt11_nofifo_trg_cfg	rw	0x0	
5 : 4	evt12_nofifo_trg_cfg	rw	0x0	
7 : 6	evt13_nofifo_trg_cfg	rw	0x0	

45.54 psi_rd_cmd_addr				0x40503200
Bits	Field Name	Acc	Default	Description
31 : 0	psi_rd_cmd_addr	rw	0x0	

45.55 psi_wr_cmd_addr				0x40503204
Bits	Field Name	Acc	Default	Description

31 : 0	psi_wr_cmd_addr	rw	0x0	

45.56 psi_wr_cmd_data				0x40503208
Bits	Field Name	Acc	Default	Description
31 : 0	psi_wr_cmd_data	rw	0x0	

45.57 psi_timeout_cfg				0x4050320C
Bits	Field Name	Acc	Default	Description
15 : 0	rx_ssc_timeout_th	rw	0x40	

45.58 pmu_psi_slv_cfg0				0x40503210
Bits	Field Name	Acc	Default	Description
29 : 0	pmu_psi_addr_ll_th	rw	0x1C000000	
30	pmu_psi_auto_det_en	rw	0x0	
31	pmu_psi_force_en	rw	0x1	

45.59 pmu_psi_slv_cfg1				0x40503214
Bits	Field Name	Acc	Default	Description
29 : 0	pmu_psi_addr_hh_th	rw	0x1C003FFF	

46 iomux

46.1 pad_gpioa_0_cfg_reg				0x40504000
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_0_sel	rw	0x0	gpioa_0 select 0 fun_cpu_p_swclk_sel 1 fun_gpioa_0_sel 2 fun_i2cm_scl_sel 3 fun_debug_clk_sel 4 fun_i2s_lrck_0_sel 5 fun_pcm_fsync_sel 6 fun_spi_lcd_sck_sel 7 fun_tports0_sel 8 fun_psi_m_scl_sel 9 fun_wf_ext_pa_ctrl_0_sel
7 : 4	pad_gpioa_0_ana	rw	0x0	gpioa_0 ANA_Alter_SEL
8	pad_gpioa_0_pull_dn	rw	0x0	gpioa_0 PUll down
9	pad_gpioa_0_pull_up	rw	0x0	gpioa_0 PUll up
16	pad_gpioa_0_pull_frc	rw	0x0	gpioa_0 force enable for pu/pd
17	pad_gpioa_0_oen_reg	rw	0x0	gpioa_0 force outoen value.
19 : 18	pad_gpioa_0_drv_strength	rw	0x0	gpioa_0 driving strength.
20	pad_gpioa_0_out_reg	rw	0x0	gpioa_0 pin output value.
24	pad_gpioa_0_out_frc	rw	0x0	gpioa_0 force output value for output.
28	pad_gpioa_0_oen_frc	rw	0x0	gpioa_0 force enable for outoen.

46.2 pad_gpioa_1_cfg_reg				0x40504004
Bits	Field Name	Acc	Default	Description

3 : 0	pad_gpioa_1_sel	rw	0x0	gpioa_1 select 0 fun_cpu_p_swd_sel 1 fun_gpioa_1_sel 2 fun_i2cm_sda_sel 3 fun_aon_uart_tx_sel 4 fun_i2s_bck_0_sel 5 fun_pcm_clk_sel 6 fun_spi_lcd_csn_0_sel 7 fun_tports1_sel 8 fun_psi_m_sda_sel 9 fun_wf_ext_pa_ctrl_1_sel
7 : 4	pad_gpioa_1_ana	rw	0x0	gpioa_1 ANA_Alter_SEL
8	pad_gpioa_1_pull_dn	rw	0x0	gpioa_1 PUll down
9	pad_gpioa_1_pull_up	rw	0x0	gpioa_1 PUll up
16	pad_gpioa_1_pull_frc	rw	0x0	gpioa_1 force enable for pu/pd
17	pad_gpioa_1_oen_reg	rw	0x0	gpioa_1 force outoen value.
19 : 18	pad_gpioa_1_drv_strength	rw	0x0	gpioa_1 driving strength.
20	pad_gpioa_1_out_reg	rw	0x0	gpioa_1 pin output value.
24	pad_gpioa_1_out_frc	rw	0x0	gpioa_1 force output value for output.
28	pad_gpioa_1_oen_frc	rw	0x0	gpioa_1 force enable for outoen.

46.3 pad_gpioa_2_cfg_reg 0x40504008

Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_2_sel	rw	0x0	gpioa_2 select 0 fun_gpioa_2_sel 1 fun_uart0_rx_sel 2 fun_uart1_rx_sel 3 fun_i2cm_scl_sel 4 fun_i2s_dat_in_0_sel 5 fun_pcm_din_sel 6 fun_spi_lcd_di_sel 7 fun_tports2_sel 9 fun_wf_ext_pa_ctrl_2_sel
7 : 4	pad_gpioa_2_ana	rw	0x0	gpioa_2 ANA_Alter_SEL
8	pad_gpioa_2_pull_dn	rw	0x0	gpioa_2 PUll down
9	pad_gpioa_2_pull_up	rw	0x0	gpioa_2 PUll up
16	pad_gpioa_2_pull_frc	rw	0x0	gpioa_2 force enable for pu/pd
17	pad_gpioa_2_oen_reg	rw	0x0	gpioa_2 force outoen value.
19 : 18	pad_gpioa_2_drv_strength	rw	0x0	gpioa_2 driving strength.
20	pad_gpioa_2_out_reg	rw	0x0	gpioa_2 pin output value.
24	pad_gpioa_2_out_frc	rw	0x0	gpioa_2 force output value for output.
28	pad_gpioa_2_oen_frc	rw	0x0	gpioa_2 force enable for outoen.

46.4 pad_gpioa_3_cfg_reg 0x4050400C

Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_3_sel	rw	0x0	gpioa_3 select 0 fun_gpioa_3_sel 1 fun_uart0_tx_sel 2 fun_uart1_tx_sel 3 fun_i2cm_sda_sel 4 fun_i2s_dat_out_0_sel 5 fun_pcm_dout_sel 6 fun_spi_lcd_do_sel 7 fun_tports3_sel 8 fun_mbist_clock_sel 9 fun_wf_ext_pa_ctrl_3_sel
7 : 4	pad_gpioa_3_ana	rw	0x0	gpioa_3 ANA_Alter_SEL
8	pad_gpioa_3_pull_dn	rw	0x0	gpioa_3 PUll down
9	pad_gpioa_3_pull_up	rw	0x0	gpioa_3 PUll up
16	pad_gpioa_3_pull_frc	rw	0x0	gpioa_3 force enable for pu/pd
17	pad_gpioa_3_oen_reg	rw	0x0	gpioa_3 force outoen value.
19 : 18	pad_gpioa_3_drv_strength	rw	0x0	gpioa_3 driving strength.

20	pad_gpioa_3_out_reg	rw	0x0	gpioa_3 pin output value.
24	pad_gpioa_3_out_frc	rw	0x0	gpioa_3 force output value for output.
28	pad_gpioa_3_oen_frc	rw	0x0	gpioa_3 force enable for outoen.

46.5 pad_gpioa_4_cfg_reg				0x40504010
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_4_sel	rw	0x0	gpioa_4 select 0 fun_gpioa_4_sel 1 fun_uart0_cts_sel 2 fun_uart1_cts_sel 3 fun_uart1_rx_sel 4 fun_codec_mclk_sel 5 fun_pwm_0_sel 6 fun_spi_lcd_cd_sel 7 fun_tports4_sel 8 fun_dft_jtag_tck_sel
7 : 4	pad_gpioa_4_ana	rw	0x0	gpioa_4 ANA_Alter_SEL
8	pad_gpioa_4_pull_dn	rw	0x0	gpioa_4 PUll down
9	pad_gpioa_4_pull_up	rw	0x0	gpioa_4 PUll up
16	pad_gpioa_4_pull_frc	rw	0x0	gpioa_4 force enable for pu/pd
17	pad_gpioa_4_oen_reg	rw	0x0	gpioa_4 force outoen value.
19 : 18	pad_gpioa_4_drv_strength	rw	0x0	gpioa_4 driving strength.
20	pad_gpioa_4_out_reg	rw	0x0	gpioa_4 pin output value.
24	pad_gpioa_4_out_frc	rw	0x0	gpioa_4 force output value for output.
28	pad_gpioa_4_oen_frc	rw	0x0	gpioa_4 force enable for outoen.

46.6 pad_gpioa_5_cfg_reg				0x40504014
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_5_sel	rw	0x0	gpioa_5 select 0 fun_gpioa_5_sel 1 fun_uart0_rts_sel 2 fun_uart1_rts_sel 3 fun_uart1_tx_sel 4 fun_debug_clk_sel 5 fun_pwm_1_sel 6 fun_spi_lcd_fmark_sel 7 fun_tports5_sel 8 fun_dft_jtag_trst_sel
7 : 4	pad_gpioa_5_ana	rw	0x0	gpioa_5 ANA_Alter_SEL
8	pad_gpioa_5_pull_dn	rw	0x0	gpioa_5 PUll down
9	pad_gpioa_5_pull_up	rw	0x0	gpioa_5 PUll up
16	pad_gpioa_5_pull_frc	rw	0x0	gpioa_5 force enable for pu/pd
17	pad_gpioa_5_oen_reg	rw	0x0	gpioa_5 force outoen value.
19 : 18	pad_gpioa_5_drv_strength	rw	0x0	gpioa_5 driving strength.
20	pad_gpioa_5_out_reg	rw	0x0	gpioa_5 pin output value.
24	pad_gpioa_5_out_frc	rw	0x0	gpioa_5 force output value for output.
28	pad_gpioa_5_oen_frc	rw	0x0	gpioa_5 force enable for outoen.

46.7 pad_gpioa_6_cfg_reg				0x40504018
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_6_sel	rw	0x0	gpioa_6 select 0 fun_gpioa_6_sel 1 fun_i2cm_scl_sel 2 fun_uart2_rx_sel 3 fun_uart1_cts_sel 4 fun_aon_pwm_0_sel 5 fun_i2s_bck_0_sel 6 fun_spi_lcd_csn_1_sel 7 fun_tports6_sel
7 : 4	pad_gpioa_6_ana	rw	0x0	gpioa_6 ANA_Alter_SEL
8	pad_gpioa_6_pull_dn	rw	0x0	gpioa_6 PUll down

9	pad_gpioa_6_pull_up	rw	0x0	gpioa_6 PUll up
16	pad_gpioa_6_pull_frc	rw	0x0	gpioa_6 force enable for pu/pd
17	pad_gpioa_6_oen_reg	rw	0x0	gpioa_6 force outoen value.
19 : 18	pad_gpioa_6_drv_strength	rw	0x0	gpioa_6 driving strength.
20	pad_gpioa_6_out_reg	rw	0x0	gpioa_6 pin output value.
24	pad_gpioa_6_out_frc	rw	0x0	gpioa_6 force output value for output.
28	pad_gpioa_6_oen_frc	rw	0x0	gpioa_6 force enable for outoen.

46.8 pad_gpioa_7_cfg_reg				0x4050401C
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_7_sel	rw	0x0	gpioa_7 select 0 fun_gpioa_7_sel 1 fun_i2cm_sda_sel 2 fun_uart2_tx_sel 3 fun_uart1_rts_sel 4 fun_aon_pwm_1_sel 5 fun_i2s_lrck_0_sel 6 fun_spi_lcd_csn_2_sel 7 fun_tports7_sel
7 : 4	pad_gpioa_7_ana	rw	0x0	gpioa_7 ANA_Alter_SEL
8	pad_gpioa_7_pull_dn	rw	0x0	gpioa_7 PUll down
9	pad_gpioa_7_pull_up	rw	0x0	gpioa_7 PUll up
16	pad_gpioa_7_pull_frc	rw	0x0	gpioa_7 force enable for pu/pd
17	pad_gpioa_7_oen_reg	rw	0x0	gpioa_7 force outoen value.
19 : 18	pad_gpioa_7_drv_strength	rw	0x0	gpioa_7 driving strength.
20	pad_gpioa_7_out_reg	rw	0x0	gpioa_7 pin output value.
24	pad_gpioa_7_out_frc	rw	0x0	gpioa_7 force output value for output.
28	pad_gpioa_7_oen_frc	rw	0x0	gpioa_7 force enable for outoen.

46.9 pad_gpioa_8_cfg_reg				0x40504020
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_8_sel	rw	0x0	gpioa_8 select 0 fun_uart0_rx_sel 1 fun_gpioa_8_sel 2 fun_uart2_cts_sel
7 : 4	pad_gpioa_8_ana	rw	0x0	gpioa_8 ANA_Alter_SEL
8	pad_gpioa_8_pull_dn	rw	0x0	gpioa_8 PUll down
9	pad_gpioa_8_pull_up	rw	0x0	gpioa_8 PUll up
16	pad_gpioa_8_pull_frc	rw	0x0	gpioa_8 force enable for pu/pd
17	pad_gpioa_8_oen_reg	rw	0x0	gpioa_8 force outoen value.
19 : 18	pad_gpioa_8_drv_strength	rw	0x0	gpioa_8 driving strength.
20	pad_gpioa_8_out_reg	rw	0x0	gpioa_8 pin output value.
24	pad_gpioa_8_out_frc	rw	0x0	gpioa_8 force output value for output.
28	pad_gpioa_8_oen_frc	rw	0x0	gpioa_8 force enable for outoen.

46.10 pad_gpioa_9_cfg_reg				0x40504024
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_9_sel	rw	0x0	gpioa_9 select 0 fun_uart0_tx_sel 1 fun_gpioa_9_sel 2 fun_uart2_rts_sel 4 fun_aon_pwm_2_sel 5 fun_i2s_dat_out_0_sel 6 fun_spi_lcd_csn_3_sel 7 fun_tports9_sel
7 : 4	pad_gpioa_9_ana	rw	0x0	gpioa_9 ANA_Alter_SEL
8	pad_gpioa_9_pull_dn	rw	0x0	gpioa_9 PUll down
9	pad_gpioa_9_pull_up	rw	0x0	gpioa_9 PUll up
16	pad_gpioa_9_pull_frc	rw	0x0	gpioa_9 force enable for pu/pd

17	pad_gpioa_9_oen_reg	rw	0x0	gpioa_9 force outoen value.
19 : 18	pad_gpioa_9_drv_strength	rw	0x0	gpioa_9 driving strength.
20	pad_gpioa_9_out_reg	rw	0x0	gpioa_9 pin output value.
24	pad_gpioa_9_out_frc	rw	0x0	gpioa_9 force output value for output.
28	pad_gpioa_9_oen_frc	rw	0x0	gpioa_9 force enable for outoen.

46.11 pad_gpioa_10_cfg_reg				0x40504028
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_10_sel	rw	0x0	gpioa_10 select 0 fun_gpioa_10_sel 1 fun_uart1_rx_sel 2 fun_spi_lcd_sck_sel 3 fun_psi_m_scl_sel 4 fun_sdmmc_data_2_sel 5 fun_i2s_bck_1_sel 6 fun_uart2_rx_sel 7 fun_tports10_sel 8 fun_dft_jtag_tms_sel
7 : 4	pad_gpioa_10_ana	rw	0x0	gpioa_10 ANA_Alter_SEL
8	pad_gpioa_10_pull_dn	rw	0x0	gpioa_10 PUll down
9	pad_gpioa_10_pull_up	rw	0x0	gpioa_10 PUll up
16	pad_gpioa_10_pull_frc	rw	0x0	gpioa_10 force enable for pu/pd
17	pad_gpioa_10_oen_reg	rw	0x0	gpioa_10 force outoen value.
19 : 18	pad_gpioa_10_drv_strength	rw	0x0	gpioa_10 driving strength.
20	pad_gpioa_10_out_reg	rw	0x0	gpioa_10 pin output value.
24	pad_gpioa_10_out_frc	rw	0x0	gpioa_10 force output value for output.
28	pad_gpioa_10_oen_frc	rw	0x0	gpioa_10 force enable for outoen.

46.12 pad_gpioa_11_cfg_reg				0x4050402C
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_11_sel	rw	0x0	gpioa_11 select 0 fun_gpioa_11_sel 1 fun_uart1_tx_sel 2 fun_spi_lcd_csn_0_sel 3 fun_psi_m_sda_sel 4 fun_sdmmc_data_3_sel 5 fun_i2s_lrck_1_sel 6 fun_uart2_tx_sel 7 fun_tports11_sel 8 fun_dft_jtag_tdi_sel
7 : 4	pad_gpioa_11_ana	rw	0x0	gpioa_11 ANA_Alter_SEL
8	pad_gpioa_11_pull_dn	rw	0x0	gpioa_11 PUll down
9	pad_gpioa_11_pull_up	rw	0x0	gpioa_11 PUll up
16	pad_gpioa_11_pull_frc	rw	0x0	gpioa_11 force enable for pu/pd
17	pad_gpioa_11_oen_reg	rw	0x0	gpioa_11 force outoen value.
19 : 18	pad_gpioa_11_drv_strength	rw	0x0	gpioa_11 driving strength.
20	pad_gpioa_11_out_reg	rw	0x0	gpioa_11 pin output value.
24	pad_gpioa_11_out_frc	rw	0x0	gpioa_11 force output value for output.
28	pad_gpioa_11_oen_frc	rw	0x0	gpioa_11 force enable for outoen.

46.13 pad_gpioa_12_cfg_reg				0x40504030
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_12_sel	rw	0x0	gpioa_12 select 0 fun_gpioa_12_sel 1 fun_uart1_cts_sel 2 fun_spi_lcd_di_sel 3 fun_pcm_fsync_sel 4 fun_sdmmc_cmd_sel 5 fun_i2s_dat_in_1_sel 6 fun_uart2_cts_sel 7 fun_tports14_sel

7 : 4	pad_gpioa_12_ana	rw	0x0	gpioa_12 ANA_Alter_SEL
8	pad_gpioa_12_pull_dn	rw	0x0	gpioa_12 PUll down
9	pad_gpioa_12_pull_up	rw	0x0	gpioa_12 PUll up
16	pad_gpioa_12_pull_frc	rw	0x0	gpioa_12 force enable for pu/pd
17	pad_gpioa_12_oen_reg	rw	0x0	gpioa_12 force outoen value.
19 : 18	pad_gpioa_12_drv_strength	rw	0x0	gpioa_12 driving strength.
20	pad_gpioa_12_out_reg	rw	0x0	gpioa_12 pin output value.
24	pad_gpioa_12_out_frc	rw	0x0	gpioa_12 force output value for output.
28	pad_gpioa_12_oen_frc	rw	0x0	gpioa_12 force enable for outoen.

46.14 pad_gpioa_13_cfg_reg				0x40504034
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_13_sel	rw	0x0	gpioa_13 select 0 fun_gpioa_13_sel 1 fun_uart1_rts_sel 2 fun_spi_lcd_do_sel 3 fun_pcm_clk_sel 4 fun_sdmmc_clk_sel 5 fun_codec_mclk_sel 6 fun_uart2_rts_sel 7 fun_tports15_sel
7 : 4	pad_gpioa_13_ana	rw	0x0	gpioa_13 ANA_Alter_SEL
8	pad_gpioa_13_pull_dn	rw	0x0	gpioa_13 PUll down
9	pad_gpioa_13_pull_up	rw	0x0	gpioa_13 PUll up
16	pad_gpioa_13_pull_frc	rw	0x0	gpioa_13 force enable for pu/pd
17	pad_gpioa_13_oen_reg	rw	0x0	gpioa_13 force outoen value.
19 : 18	pad_gpioa_13_drv_strength	rw	0x0	gpioa_13 driving strength.
20	pad_gpioa_13_out_reg	rw	0x0	gpioa_13 pin output value.
24	pad_gpioa_13_out_frc	rw	0x0	gpioa_13 force output value for output.
28	pad_gpioa_13_oen_frc	rw	0x0	gpioa_13 force enable for outoen.

46.15 pad_gpioa_14_cfg_reg				0x40504038
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpioa_14_sel	rw	0x0	gpioa_14 select 0 fun_gpioa_14_sel 1 fun_i2cm_scl_sel 2 fun_spi_lcd_cd_sel 3 fun_pcm_din_sel 4 fun_sdmmc_data_0_sel 5 fun_i2s_dat_out_1_sel 6 fun_pwm_2_sel 7 fun_tports12_sel 8 fun_dft_jtag_tdo_sel
7 : 4	pad_gpioa_14_ana	rw	0x0	gpioa_14 ANA_Alter_SEL
8	pad_gpioa_14_pull_dn	rw	0x0	gpioa_14 PUll down
9	pad_gpioa_14_pull_up	rw	0x0	gpioa_14 PUll up
16	pad_gpioa_14_pull_frc	rw	0x0	gpioa_14 force enable for pu/pd
17	pad_gpioa_14_oen_reg	rw	0x0	gpioa_14 force outoen value.
19 : 18	pad_gpioa_14_drv_strength	rw	0x0	gpioa_14 driving strength.
20	pad_gpioa_14_out_reg	rw	0x0	gpioa_14 pin output value.
24	pad_gpioa_14_out_frc	rw	0x0	gpioa_14 force output value for output.
28	pad_gpioa_14_oen_frc	rw	0x0	gpioa_14 force enable for outoen.

46.16 pad_gpioa_15_cfg_reg				0x4050403C
Bits	Field Name	Acc	Default	Description

3 : 0	pad_gpioa_15_sel	rw	0x0	gpioa_15 select 0 fun_gpioa_15_sel 1 fun_i2cm_sda_sel 2 fun_spi_lcd_fmark_sel 3 fun_pcm_dout_sel 4 fun_sdmmc_data_1_sel 5 fun_i2s_dat_in_0_sel 6 fun_debug_clk_sel 7 fun_tports13_sel
7 : 4	pad_gpioa_15_ana	rw	0x0	gpioa_15 ANA_Alter_SEL
8	pad_gpioa_15_pull_dn	rw	0x0	gpioa_15 PUll down
9	pad_gpioa_15_pull_up	rw	0x0	gpioa_15 PUll up
16	pad_gpioa_15_pull_frc	rw	0x0	gpioa_15 force enable for pu/pd
17	pad_gpioa_15_oen_reg	rw	0x0	gpioa_15 force outoen value.
19 : 18	pad_gpioa_15_drv_strength	rw	0x0	gpioa_15 driving strength.
20	pad_gpioa_15_out_reg	rw	0x0	gpioa_15 pin output value.
24	pad_gpioa_15_out_frc	rw	0x0	gpioa_15 force output value for output.
28	pad_gpioa_15_oen_frc	rw	0x0	gpioa_15 force enable for outoen.

46.17 pad_gpiob_0_cfg_reg				0x40504040
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpiob_0_sel	rw	0x0	gpiob_0 select 0 fun_gpioa_16_sel 1 fun_pcm_fsync_sel 2 fun_tports0_sel 3 fun_uart1_rx_sel 4 fun_pwm_0_sel 5 fun_spi_lcd_csn_1_sel
7 : 4	pad_gpiob_0_ana	rw	0x0	gpiob_0 ANA_Alter_SEL
8	pad_gpiob_0_pull_dn	rw	0x0	gpiob_0 PUll down
9	pad_gpiob_0_pull_up	rw	0x0	gpiob_0 PUll up
16	pad_gpiob_0_pull_frc	rw	0x0	gpiob_0 force enable for pu/pd
17	pad_gpiob_0_oen_reg	rw	0x0	gpiob_0 force outoen value.
19 : 18	pad_gpiob_0_drv_strength	rw	0x0	gpiob_0 driving strength.
20	pad_gpiob_0_out_reg	rw	0x0	gpiob_0 pin output value.
24	pad_gpiob_0_out_frc	rw	0x0	gpiob_0 force output value for output.
28	pad_gpiob_0_oen_frc	rw	0x0	gpiob_0 force enable for outoen.

46.18 pad_gpiob_1_cfg_reg				0x40504044
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpiob_1_sel	rw	0x0	gpiob_1 select 0 fun_gpioa_17_sel 1 fun_pcm_clk_sel 2 fun_tports1_sel 3 fun_uart1_tx_sel 4 fun_pwm_1_sel 5 fun_spi_lcd_csn_2_sel
7 : 4	pad_gpiob_1_ana	rw	0x0	gpiob_1 ANA_Alter_SEL
8	pad_gpiob_1_pull_dn	rw	0x0	gpiob_1 PUll down
9	pad_gpiob_1_pull_up	rw	0x0	gpiob_1 PUll up
16	pad_gpiob_1_pull_frc	rw	0x0	gpiob_1 force enable for pu/pd
17	pad_gpiob_1_oen_reg	rw	0x0	gpiob_1 force outoen value.
19 : 18	pad_gpiob_1_drv_strength	rw	0x0	gpiob_1 driving strength.
20	pad_gpiob_1_out_reg	rw	0x0	gpiob_1 pin output value.
24	pad_gpiob_1_out_frc	rw	0x0	gpiob_1 force output value for output.
28	pad_gpiob_1_oen_frc	rw	0x0	gpiob_1 force enable for outoen.

46.19 pad_gpiob_2_cfg_reg				0x40504048
Bits	Field Name	Acc	Default	Description

3 : 0	pad_gpiob_2_sel	rw	0x0	gpiob_2 select 0 fun_gpioa_18_sel 1 fun_pcm_din_sel 2 fun_tports2_sel 3 fun_uart1_cts_sel 4 fun_pwm_2_sel 5 fun_spi_lcd_csn_3_sel
7 : 4	pad_gpiob_2_ana	rw	0x0	gpiob_2 ANA_Alter_SEL
8	pad_gpiob_2_pull_dn	rw	0x0	gpiob_2 PUll down
9	pad_gpiob_2_pull_up	rw	0x0	gpiob_2 PUll up
16	pad_gpiob_2_pull_frc	rw	0x0	gpiob_2 force enable for pu/pd
17	pad_gpiob_2_oen_reg	rw	0x0	gpiob_2 force outoen value.
19 : 18	pad_gpiob_2_drv_strength	rw	0x0	gpiob_2 driving strength.
20	pad_gpiob_2_out_reg	rw	0x0	gpiob_2 pin output value.
24	pad_gpiob_2_out_frc	rw	0x0	gpiob_2 force output value for output.
28	pad_gpiob_2_oen_frc	rw	0x0	gpiob_2 force enable for outoen.

46.20 pad_gpiob_3_cfg_reg				0x4050404C
Bits	Field Name	Acc	Default	Description
3 : 0	pad_gpiob_3_sel	rw	0x0	gpiob_3 select 0 fun_gpioa_19_sel 1 fun_pcm_dout_sel 2 fun_tports3_sel 3 fun_uart1_rts_sel 7 fun_tports8_sel
7 : 4	pad_gpiob_3_ana	rw	0x0	gpiob_3 ANA_Alter_SEL
8	pad_gpiob_3_pull_dn	rw	0x0	gpiob_3 PUll down
9	pad_gpiob_3_pull_up	rw	0x0	gpiob_3 PUll up
16	pad_gpiob_3_pull_frc	rw	0x0	gpiob_3 force enable for pu/pd
17	pad_gpiob_3_oen_reg	rw	0x0	gpiob_3 force outoen value.
19 : 18	pad_gpiob_3_drv_strength	rw	0x0	gpiob_3 driving strength.
20	pad_gpiob_3_out_reg	rw	0x0	gpiob_3 pin output value.
24	pad_gpiob_3_out_frc	rw	0x0	gpiob_3 force output value for output.
28	pad_gpiob_3_oen_frc	rw	0x0	gpiob_3 force enable for outoen.

47 cm_rf_interface

47.1 reg_00				0x40505000
Bits	Field Name	Acc	Default	Description
3 : 0	cm_xtal_reg_buf_vbit	rw	0xF	
4	bbpll_vco_high_test_mode	rw	0x0	
5	bbpll_vco_low_test_mode	rw	0x0	
6	cm_test_enable_mdll_clk	rw	0x0	
7	cm_test_enable_mdll	rw	0x0	
8	cm_test_enable_xdblr	rw	0x0	
9	cm_test_enable_xtal	rw	0x0	
12 : 10	cm_test_bit	rw	0x0	
14 : 13	cm_mdll_pu_bit	rw	0x3	
16 : 15	cm_xtal_pu_bit	rw	0x1	
17	cm_pu_mdll_clk26m	rw	0x0	
18	pu_bbpll_reg	rw	0x0	
19	pu_bbpll_dr	rw	0x0	
20	cm_mdll_rstn_reg	rw	0x0	
21	cm_mdll_rstn_dr	rw	0x0	
25 : 22	cm_mdll_outclk_en_reg	rw	0x0	
29 : 26	cm_mdll_outclk_en_dr	rw	0x0	
30	cm_pu_mdll_reg	rw	0x0	
31	cm_pu_mdll_dr	rw	0x0	

47.2 reg_01				0x40505004
Bits	Field Name	Acc	Default	Description
0	cm_mdll_frefx2_en	rw	0x1	
4 : 1	cm_mdll_reg_clk_bit	rw	0x8	
7 : 5	cm_mdll_psw_rosc_freq	rw	0x0	
8	cm_mdll_psw_mode	rw	0x1	
9	cm_mdll_sf_mode	rw	0x0	
10	cm_mdll_sel_ldo18	rw	0x0	
13 : 11	cm_xtal_comp_ibit	rw	0x3	
16 : 14	cm_xtal_clk_delay_bit	rw	0x0	
22 : 17	cm_xtal_cap_fine_bit	rw	0x1F	
25 : 23	cm_xtal_iref_lp_bit	rw	0x3	
29 : 26	cm_xtal_ibias_lp_bit	rw	0xA	
30	cm_xtal_vbcg_en	rw	0x1	

47.3 reg_02				0x40505008
Bits	Field Name	Acc	Default	Description
0	cm_mdll_fb_sel_self_bias	rw	0x1	
1	cm_mdll_fref_edge_sel_rise	rw	0x1	
5 : 2	cm_mdll_dcc_ref_bit	rw	0x3	
6	cm_mdll_dcc_en	rw	0x0	
12 : 7	cm_mdll_dcc_dly_bit	rw	0x20	
16 : 13	cm_mdll_clk26m_en	rw	0x0	
19 : 17	cm_mdll_rstn_vbit	rw	0x7	
22 : 20	cm_mdll_band_bit	rw	0x2	
23	cm_mdll_band_sel	rw	0x1	
28 : 24	cm_mdll_div_num	rw	0x4	

47.4 reg_03				0x4050500C
Bits	Field Name	Acc	Default	Description
3 : 0	bbpll_reg_vbit	rw	0x8	
4	bbpll_frefx2_en	rw	0x1	
6 : 5	bbpll_pu_bit	rw	0x3	
10 : 7	cm_rsvd_bit	rw	0xC	
11	cm_mdll_fast_lock_disable	rw	0x0	
13 : 12	cm_mdll_aux_cp_bit	rw	0x1	
14	cm_mdll_dcc_out	ro	0x0	
18 : 15	cm_mdll_rsvd1	rw	0x3	
22 : 19	cm_mdll_rsvd0	rw	0x3	
29 : 23	cm_mdll_fb_res	rw	0x5	

47.5 reg_04				0x40505010
Bits	Field Name	Acc	Default	Description
0	bbpll_clk_64m_dly_bit	rw	0x0	
2 : 1	bbpll_clk_64m_dly_en	rw	0x0	
3	bbpll_clk_64m_dly_sel	rw	0x0	
7 : 4	bbpll_pfd_dn_dlyf_bit	rw	0x1	
11 : 8	bbpll_pfd_dn_dlyc_bit	rw	0x0	
15 : 12	bbpll_pfd_up_dlyf_bit	rw	0x1	
19 : 16	bbpll_pfd_up_dlyc_bit	rw	0x0	
21 : 20	bbpll_clk_80m_duty_bit	rw	0x3	
23 : 22	bbpll_clk_64m_en	rw	0x0	
25 : 24	bbpll_clk_80m_en	rw	0x0	
27 : 26	bbpll_clk_vco_en	rw	0x3	
28	bbpll_clk_usb_en	rw	0x1	

31 : 29	bbpll_cp_ibit	rw	0x7	

47.6 reg_05				0x40505014
Bits	Field Name	Acc	Default	Description
0	bbpll_lock_out	ro	0x0	
1	bbpll_lpf_notch_en	rw	0x0	
2	bbpll_clk_adc_sel	rw	0x0	
3	bbpll_div1p5_en	rw	0x1	
5 : 4	bbpll_clk_div1p5_en	rw	0x1	
6	bbpll_vco_band_sel	rw	0x1	
7	bbpll_div4_en	rw	0x0	
8	bbpll_pcon_mode	rw	0x1	

47.7 cm_1m_reg				0x40505018
Bits	Field Name	Acc	Default	Description
5 : 0	div_num_1m	rw	0xC	
6	clk_1m_div_en	rw	0x1	
13 : 8	cal_clk_div_num	rw	0x9	
14	cal_clk_en	rw	0x0	
15	debug_clk_en	rw	0x0	

47.8 bbpll_sdm_reg1				0x4050501C
Bits	Field Name	Acc	Default	Description
0	bbpll_sdm_resetn_reg	rw	0x0	
1	bbpll_sdm_resetn_dr	rw	0x0	
11 : 2	bbpll_sdm_resetn_delay	rw	0x32C	
13 : 12	bbpll_sdm_clk_sel_reg	rw	0x1	
16 : 14	bbpll_sdm_intdec_sel	rw	0x3	
17	bbpll_sdm_dither_bypass	rw	0x0	
27 : 26	triangle_wave_cyc_ct	rw	0x0	
29 : 28	triangle_wave_amp_ct	rw	0x0	
30	spread_spectrum_en	rw	0x0	

47.9 bbpll_sdm_reg2				0x40505020
Bits	Field Name	Acc	Default	Description
27 : 0	bbpll_sdm_freq_cfg	rw	0x49D89D9	
28	bbpll_sdm_freq_cfg_pulse	rw	0x0	

47.10 wf_wr_only_reg				0x40505024
Bits	Field Name	Acc	Default	Description
31 : 0	wf_wo_reg	rw	0x0	

47.11 bt_wr_only_reg				0x40505028
Bits	Field Name	Acc	Default	Description
31 : 0	bt_wo_reg	rw	0x0	

47.12 mdll_fref_reg				0x4050502C
Bits	Field Name	Acc	Default	Description
0	mdll_fref_lo	rw	0x0	
1	mdll_fref_md	rw	0x0	

47.13 dig_reserved_reg				0x40505030
Bits	Field Name	Acc	Default	Description

48 pwr_ctrl

48.1 cpu_sys_pwr_ctrl				0x40506000
Bits	Field Name	Acc	Default	Description
9 : 0	cpu_sys_awake_src_en	rw	0x0	
11 : 10	cpu_sys_slp_src_en	rw	0x0	
12	cpu_sys_slp_soft_req	w1c	0x0	
13	cpu_sys_slp_req_vld_clr	w1c	0x0	
15	pon_hwen_cpu_sys	rw	0x1	
16	poff_hwen_cpu_sys	rw	0x1	
17	pon_cpu_sys	rw	0x1	
18	poff_cpu_sys	rw	0x0	
19	timer_poff_pw-r_sys_by_cpu_sys_en	rw	0x0	
20	pwr_sys_pon_by_cpu_sys_en	rw	0x1	
21	pwr_sys_poff_by_cpu_sys_en	rw	0x1	
22	cpu_sys_soft_wakeup_req	w1c	0x0	
23	cpu_sys_awake_req_vld_clr	w1c	0x0	
26 : 24	cfg_cpu_sys_slp_req_mask	rw	0x1	
27	cfg_wifi_core_slep_cpu_sys_en	rw	0x0	
28	cfg_bt_core_slep_cpu_sys_en	rw	0x0	
29	bt_sys_slp_cpu_sys_soft_req	w1c	0x0	
30	wifi_sys_slp_cpu_sys_soft_req	w1c	0x0	
31	cpu_sys_awake_mode	rw	0x1	

48.2 bt_core_pwr_ctrl				0x40506004
Bits	Field Name	Acc	Default	Description
9 : 0	bt_core_awake_src_en	rw	0x0	
11 : 10	bt_core_slp_src_en	rw	0x0	
12	bt_core_slp_soft_req	w1c	0x0	
13	bt_core_slp_req_vld_clr	w1c	0x0	
15	pon_hwen_bt_core	rw	0x1	
16	poff_hwen_bt_core	rw	0x1	
17	pon_bt_core	rw	0x0	
18	poff_bt_core	rw	0x1	
19	timer_poff_pw-r_sys_by_bt_core_en	rw	0x0	
20	pwr_sys_pon_by_bt_core_en	rw	0x1	
21	pwr_sys_poff_by_bt_core_en	rw	0x1	
22	bt_core_soft_wakeup_req	w1c	0x0	
23	bt_core_awake_req_vld_clr	w1c	0x0	
24	bt_core_soft_wakeup_req_to_bt	rw	0x0	
25	bt_core_hw_clr_cpu_sys_slp_en	rw	0x0	
26	bt_sys_awake_mode	rw	0x1	

48.3 wifi_core_pwr_ctrl				0x40506008
Bits	Field Name	Acc	Default	Description
9 : 0	wifi_core_awake_src_en	rw	0x0	
11 : 10	wifi_core_slp_src_en	rw	0x0	
12	wifi_core_slp_soft_req	w1c	0x0	
13	wifi_core_slp_req_vld_clr	w1c	0x0	
15	pon_hwen_wifi_core	rw	0x1	

16	poff_hwen_wifi_core	rw	0x1	
17	pon_wifi_core	rw	0x0	
18	poff_wifi_core	rw	0x1	
19	timer_poff_pw-r_sys_by_wifi_core_en	rw	0x0	
20	pwr_sys_pon_by_wifi_core_en	rw	0x1	
21	pwr_sys_poff_by_wifi_core_en	rw	0x1	
22	wifi_core_soft_wakeup_req	w1c	0x0	
23	wifi_core_awake_req_vld_clr	w1c	0x0	
24	wifi_core_sof-t_wakeup_req_to_wifi	rw	0x0	
25	wifi_core_hw_-clr_cpu_sys_slp_en	rw	0x0	
26	wifi_sys_awake_mode	rw	0x1	

48.4 pwr_sys_ctrl				0x40506010
Bits	Field Name	Acc	Default	Description
15 : 0	dejitter	rw	0x0	
16	pwr_sys_pon_soft	rw	0x0	
17	pwr_sys_pon_soft_en	rw	0x0	
18	pu_pll_soft	rw	0x0	
19	pu_pll_soft_en	rw	0x0	
20	chip_slp_soft	rw	0x0	
21	chip_slp_soft_en	rw	0x0	
22	cg_pll_soft	rw	0x0	
23	cg_pll_soft_en	rw	0x0	
24	clk_32k_52m_sel_soft	rw	0x1	
25	clk_32k_52m_sel_soft_en	rw	0x0	
26	clk_32k_52m_sw_en	rw	0x1	
27	pwr_sys_poff_hw_en	rw	0x1	
28	xtal_pd_en	rw	0x1	
29	pu_xtal_soft	rw	0x0	
30	pu_xtal_soft_en	rw	0x0	
31	chip_sleep_hw_en	rw	0x1	

48.5 pwr_off_timmer_th1				0x40506014
Bits	Field Name	Acc	Default	Description
15 : 0	cpu_sys_timer_th	rw	0x0	
31 : 16	pwr_sys_timer_th	rw	0x0	

48.6 pwr_off_timmer_th2				0x40506018
Bits	Field Name	Acc	Default	Description
15 : 0	wifi_core_timer_th	rw	0x0	
31 : 16	bt_core_timer_th	rw	0x0	

48.7 pwr_ctrl_delay1				0x4050601C
Bits	Field Name	Acc	Default	Description
15 : 0	pwr_ctrl_pre_delay	rw	0x100	
31 : 16	pwr_ctrl_delay	rw	0x400	

48.8 pwr_ctrl_delay2				0x40506020
Bits	Field Name	Acc	Default	Description
7 : 0	pwr_ctrl_state_delay	rw	0x80	

15 : 8	pwr_sys_xtal_close_delay	rw	0x2	
23 : 16	pwr_sys_xtal_open_delay	rw	0x2	
31 : 24	pwr_sys_pupd_xtal_delay	rw	0x1	

48.9 pwr_sys_delay1				0x40506024
Bits	Field Name	Acc	Default	Description
7 : 0	pwr_sys_dp_open_delay	rw	0xA0	
15 : 8	pwr_sys_dp_close_delay	rw	0x3	
23 : 16	pwr_sys_cg_open_delay	rw	0x1	
31 : 24	pwr_sys_cg_close_delay	rw	0x3	

48.10 pwr_sys_delay2				0x40506028
Bits	Field Name	Acc	Default	Description
7 : 0	pwr_sys_pwr_open_delay	rw	0xC	
15 : 8	pwr_sys_pwr_close_delay	rw	0x1	
23 : 16	pwr_sys_pll_open_delay	rw	0x2	
31 : 24	pwr_sys_pll_close_delay	rw	0x1	

48.11 pwr_ctrl_state1				0x40506030
Bits	Field Name	Acc	Default	Description
1	pon_stab_wifi_core	ro	0x0	
2	pon_stab_bt_core	ro	0x0	
3	pon_stab_cpu_sys	ro	0x0	
5	poff_stab_wifi_core	ro	0x0	
6	poff_stab_bt_core	ro	0x0	
7	poff_stab_cpu_sys	ro	0x0	
11 : 8	state_wifi_core	ro	0x0	
15 : 12	state_bt_core	ro	0x0	
19 : 16	state_cpu_sys	ro	0x0	
21 : 20	wifi_core_cur_state	ro	0x0	
23 : 22	bt_core_cur_state	ro	0x0	
25 : 24	cpu_sys_cur_state	ro	0x0	
29 : 26	pwr_sys_cur_state	ro	0x0	
31 : 30	vcore_sys_cur_state	ro	0x0	

48.12 pwr_ctrl_state2				0x40506034
Bits	Field Name	Acc	Default	Description
0	pon_stab_vcore_sys	ro	0x0	
3	pon_stab_mm_sys	ro	0x0	
4	poff_stab_vcore_sys	ro	0x0	
7	poff_stab_mm_sys	ro	0x0	
19 : 16	state_mm_sys	ro	0x0	
23 : 20	state_vcore_sys	ro	0x0	
24	pu_pll_o	ro	0x0	
25	cg_pll_o	ro	0x0	
26	chip_slp_o	ro	0x0	
27	pwr_ctrl_pu_xtal	ro	0x0	
28	sys_clk_slow_sel	ro	0x0	
29	slow_clk_slow_sel	ro	0x0	
30	pwr_sys_pon	ro	0x0	

48.13 pwr_ctrl_soft_mode1				0x40506038
Bits	Field Name	Acc	Default	Description

5 : 0	cpu_sys_pwr_ctrl_soft	rw	0x0	
11 : 6	bt_core_pwr_ctrl_soft	rw	0x0	
17 : 12	wifi_core_pwr_ctrl_soft	rw	0x0	
31 : 24	pwr_ctrl_clk_32k_div_th	rw	0x98	

48.14 pwr_ctrl_irq_ctrl				0x40506044
Bits	Field Name	Acc	Default	Description
9 : 0	awake_state_clr	w1c	0x0	
13 : 10	slp_state_clr	w1c	0x0	
25 : 16	awake_state_mask	rw	0x0	
29 : 26	slp_state_mask	rw	0x0	
31	pwr_ctrl_irq_en	rw	0x0	

48.15 pwr_ctrl_irq_status				0x40506048
Bits	Field Name	Acc	Default	Description
9 : 0	awake_pos_pulse_raw_state	ro	0x0	
13 : 10	slp_pos_pulse_raw_state	ro	0x0	
14	vcore_sys_awake_raw_status	ro	0x0	
15	cpu_sys_awake_raw_status	ro	0x0	
25 : 16	awake_pos_pulse_state_masked	ro	0x0	
29 : 26	slp_pos_pulse_state_masked	ro	0x0	
30	bt_core_awake_raw_status	ro	0x0	
31	wifi_core_awake_raw_status	ro	0x0	

48.16 mm_sys_pwr_ctrl				0x4050604C
Bits	Field Name	Acc	Default	Description
17	pon_mm_sys	rw	0x1	
18	poff_mm_sys	rw	0x0	

48.17 pwr_ctrl_soft_mode2				0x40506050
Bits	Field Name	Acc	Default	Description
5 : 0	mm_sys_pwr_ctrl_soft	rw	0x0	
11 : 6	vcore_sys_pwr_ctrl_soft	rw	0x36	
14	slp_mode_sel_bt_core	rw	0x0	
15	slp_mode_sel_cpu_sys	rw	0x0	
16	slp_mode_sel_mm_sys	rw	0x0	
17	slp_mode_sel_vcore_sys	rw	0x0	
18	slp_mode_sel_wifi_core	rw	0x0	
21 : 19	cpu_sys_slp_req_mask_d	ro	0x0	
22	cfg_io_mmsys_en_soft	rw	0x0	
23	cfg_io_mmsys_en	rw	0x1	
24	cfg_io_cpusys_en_soft	rw	0x0	
25	cfg_io_cpusys_en	rw	0x1	
26	rtc_slp_out_done_mode_en	rw	0x1	

48.18 vcore_sys_pwr_ctrl				0x40506054
Bits	Field Name	Acc	Default	Description
9 : 0	vcore_sys_awake_src_en	rw	0x0	
11 : 10	vcore_sys_slp_src_en	rw	0x0	
12	vcore_sys_slp_soft_req	w1c	0x0	
13	vcore_sys_slp_req_vld_clr	w1c	0x0	
15	pon_hwen_vcore_sys	rw	0x1	
16	poff_hwen_vcore_sys	rw	0x1	

17	pon_vcore_sys	rw	0x1	
18	poff_vcore_sys	rw	0x0	
19	timer_poff_pwr_sys_by_vcore_sys_en	rw	0x0	
20	pwr_sys_pon_by_vcore_sys_en	rw	0x1	
21	pwr_sys_poff_by_vcore_sys_en	rw	0x1	
22	vcore_sys_soft_wakeup_req	w1c	0x0	
23	vcore_sys_awake_req_vld_clr	w1c	0x0	
24	vcore_sys_awake_mode	rw	0x1	

48.19 pwr_off_timmer_th3				0x40506058
Bits	Field Name	Acc	Default	Description
15 : 0	vcore_sys_timer_th	rw	0x0	

48.20 pwr_ctrl_mode				0x4050605C
Bits	Field Name	Acc	Default	Description
30 : 0	pwr_ctrl_mode	rw	0x0	
31	pwr_ctrl_mode_update	rw	0x0	

48.21 ret_ram_ctrl				0x40506060
Bits	Field Name	Acc	Default	Description
3 : 0	cfg_ret_ctrl_cpu_sys_ram	rw	0x0	
7 : 4	cfg_pwr_mux_cpu_sys_lram	rw	0x0	
11 : 8	cfg_pwr_mux_cpu_sys_hram	rw	0x0	
15 : 12	cfg_ret_ctrl_wifi_core_ram	rw	0x0	
19 : 16	cfg_pwr_mux_wifi_core_ram	rw	0x0	
23 : 20	cfg_ret_ctrl_bt_core_ram	rw	0x0	
27 : 24	cfg_pwr_mux_bt_core_ram	rw	0x0	

48.22 pwr_ctrl_monitor				0x40506064
Bits	Field Name	Acc	Default	Description
3 : 0	pwr_ctrl_dbg_mux	rw	0x0	
7 : 4	slp_req_sel	rw	0x0	
11 : 8	awake_req_mask	rw	0x0	
15 : 12	awake_req_raw_clr	w1c	0x0	
19 : 16	awake_vld_state_masked	ro	0x0	
23 : 20	awake_req_sel	rw	0x0	

48.23 pwr_ctrl_soft_mode3				0x40506068
Bits	Field Name	Acc	Default	Description
1 : 0	bt_coreon_soft	rw	0x0	
3 : 2	bt_hold_soft	rw	0x1	
5 : 4	wf_coreon_soft	rw	0x0	
7 : 6	wf_hold_soft	rw	0x1	
9 : 8	cpu_coreon_soft	rw	0x0	
11 : 10	cpu_hold_soft	rw	0x1	
13 : 12	mm_coreon_soft	rw	0x0	
15 : 14	mm_hold_soft	rw	0x1	
17 : 16	top_coreon_soft	rw	0x0	
19 : 18	top_hold_soft	rw	0x1	
22 : 20	cm_coreon_soft	rw	0x0	
26 : 23	cfg_rg_irq_timer2_h_awake_en	rw	0xF	
30 : 27	cfg_rg_irq_uart_h_awake_en	rw	0x1	

49 aon_pwm

49.1 tmr0_ld_value				0x40507000
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_ld_value	rw	0x0	timer0 load value

49.2 tmr0_cnt_value				0x40507008
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_cnt_value	rw	0x0	timer0 counter value

49.3 tmr0_cfg				0x40507010
Bits	Field Name	Acc	Default	Description
0	tmr_mode	rw	0x0	0: free running 1: periodic
1	tmr_run	rw	0x0	timer0 enable

49.4 tmr0_int_ctrl				0x40507014
Bits	Field Name	Acc	Default	Description
0	tmr_int_en	rw	0x0	timer0 interrupt enable
1	tmr_int_raw	ro	0x0	timer0 interrupt raw
2	tmr_int_status	ro	0x0	timer0 interrupt status
3	tmr_int_clr	wo	0x0	timer0 interrupt clear

49.5 tmr0_cnt_read				0x40507018
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_cnt_read	rw	0x0	timer0 counter read value

49.6 tmr1_ld_value				0x40507020
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_ld_value	rw	0x0	timer1 load value

49.7 tmr1_cnt_value				0x40507028
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_cnt_value	rw	0x0	timer1 counter value

49.8 tmr1_cfg				0x40507030
Bits	Field Name	Acc	Default	Description
0	tmr_mode	rw	0x0	0: free running 1: periodic
1	tmr_run	rw	0x0	timer1 enable

49.9 tmr1_int_ctrl				0x40507034
Bits	Field Name	Acc	Default	Description
0	tmr_int_en	rw	0x0	timer1 interrupt enable
1	tmr_int_raw	ro	0x0	timer1 interrupt raw
2	tmr_int_status	ro	0x0	timer1 interrupt status
3	tmr_int_clr	wo	0x0	timer1 interrupt clear

49.10 tmr1_cnt_read				0x40507038
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_cnt_read	rw	0x0	timer1 counter read value

49.11 tmr2_ld_value				0x40507040
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_ld_value	rw	0x0	timer2 load value

49.12 tmr2_cnt_value				0x40507048
Bits	Field Name	Acc	Default	Description
31 : 0	tmr_cnt_value	rw	0x0	timer2 counter value

49.13 tmr2_cfg				0x40507050
Bits	Field Name	Acc	Default	Description
0	tmr_mode	rw	0x0	0: free running 1: periodic
1	tmr_run	rw	0x0	timer2 enable

49.14 tmr2_int_ctrl				0x40507054
Bits	Field Name	Acc	Default	Description
0	tmr_int_en	rw	0x0	timer2 interrupt enable
1	tmr_int_raw	ro	0x0	timer2 interrupt raw
2	tmr_int_status	ro	0x0	timer2 interrupt status
3	tmr_int_clr	wo	0x0	timer2 interrupt clear

49.15 tmr2_cnt_read				0x40507058
Bits	Field Name	Acc	Default	Description
31 : 0	tmr2_cnt_read	rw	0x0	timer2 counter read value

49.16 pwm0_sta_val				0x40507100
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_sta_val	rw	0x0	

49.17 pwm0_end_val				0x40507104
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val	rw	0x0	

49.18 pwm0_step_cfg0				0x40507108
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc	rw	0x0	
31 : 16	pwm_step_num	rw	0x0	

49.19 pwm0_step_cfg1				0x4050710C
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_step_value	rw	0x0	

49.20 pwm0_cfg				0x40507110
Bits	Field Name	Acc	Default	Description
0	pwm_run	rw	0x0	
1	pwm_inc_mode	rw	0x0	
2	pwm_default_val	rw	0x0	
17 : 16	pwm_tmr_sel	rw	0x0	
31	pwm_update	rw	0x0	

49.21 pwm0_int_ctrl				0x40507114
Bits	Field Name	Acc	Default	Description
0	pwm_int_en	rw	0x0	
1	pwm_int_raw	ro	0x0	
2	pwm_int_status	ro	0x0	
3	pwm_int_clr	wo	0x0	

49.22 pwm0_end_val_use				0x40507118
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val_use	ro	0x0	

49.23 pwm0_step_cnt				0x4050711C
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc_cnt	ro	0x0	
31 : 16	pwm_step_num_cnt	ro	0x0	

49.24 pwm1_sta_val				0x40507120
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_sta_val	rw	0x0	

49.25 pwm1_end_val				0x40507124
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val	rw	0x0	

49.26 pwm1_step_cfg0				0x40507128
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc	rw	0x0	
31 : 16	pwm_step_num	rw	0x0	

49.27 pwm1_step_cfg1				0x4050712C
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_step_value	rw	0x0	

49.28 pwm1_cfg				0x40507130
Bits	Field Name	Acc	Default	Description
0	pwm_run	rw	0x0	
1	pwm_inc_mode	rw	0x0	
2	pwm_default_val	rw	0x0	
17 : 16	pwm_tmr_sel	rw	0x0	
31	pwm_update	rw	0x0	

49.29 pwm1_int_ctrl				0x40507134
Bits	Field Name	Acc	Default	Description
0	pwm_int_en	rw	0x0	
1	pwm_int_raw	ro	0x0	
2	pwm_int_status	ro	0x0	
3	pwm_int_clr	wo	0x0	

49.30 pwm1_end_val_use	0x40507138

Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val_use	ro	0x0	

49.31 pwm1_step_cnt				0x4050713C
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc_cnt	ro	0x0	
31 : 16	pwm_step_num_cnt	ro	0x0	

49.32 pwm2_sta_val				0x40507140
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_sta_val	rw	0x0	

49.33 pwm2_end_val				0x40507144
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val	rw	0x0	

49.34 pwm2_step_cfg0				0x40507148
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc	rw	0x0	
31 : 16	pwm_step_num	rw	0x0	

49.35 pwm2_step_cfg1				0x4050714C
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_step_value	rw	0x0	

49.36 pwm2_cfg				0x40507150
Bits	Field Name	Acc	Default	Description
0	pwm_run	rw	0x0	
1	pwm_inc_mode	rw	0x0	
2	pwm_default_val	rw	0x0	
17 : 16	pwm_tmr_sel	rw	0x0	
31	pwm_update	rw	0x0	

49.37 pwm2_int_ctrl				0x40507154
Bits	Field Name	Acc	Default	Description
0	pwm_int_en	rw	0x0	
1	pwm_int_raw	ro	0x0	
2	pwm_int_status	ro	0x0	
3	pwm_int_clr	wo	0x0	

49.38 pwm2_end_val_use				0x40507158
Bits	Field Name	Acc	Default	Description
31 : 0	pwm_end_val_use	ro	0x0	

49.39 pwm2_step_cnt				0x4050715C
Bits	Field Name	Acc	Default	Description
15 : 0	pwm_step_cyc_cnt	ro	0x0	
31 : 16	pwm_step_num_cnt	ro	0x0	

50 wdg2

50.1 WDG_LOAD_VAL				0x40508000
Bits	Field Name	Acc	Default	Description
31 : 0	wdg_load_val	rw	0x3FFFF	watchdog timer load value. In reset mode, software should load new value before timer decrease to 0. In interrupt mode, this value is counting start number. The default value is about 8 seconds.

50.2 WDG_CNT				0x40508004
Bits	Field Name	Acc	Default	Description
31 : 0	wdg_cnt	rw	0xFFFFFFFF	watchdog counter value

50.3 WDG_CTRL				0x40508008
Bits	Field Name	Acc	Default	Description
0	wdg_irq_en	rw	0x0	Watchdog interrupt enable bit 0: interrupt is disabled 1: interrupt is enabled For reset mode: wdg_rst_en =1, wdg_irq_en=0. For interrupt mode: wdg_rst_en =0, wdg_irq_en=1. For combined mode: wdg_rst_en =1, wdg_irq_en=1.
1	wdg_run	rw	0x0	Watchdog counter open: 0: counter stops. 1: counter runs.

50.4 WDG_INT_CLR				0x4050800C
Bits	Field Name	Acc	Default	Description
0	wdg_int_clr	wo	0x0	Watchdog interrupt clear Write 1 to this bit to clear interrupt Read this bit always get 0.

50.5 WDG_INT_RAW				0x40508010
Bits	Field Name	Acc	Default	Description
0	wdg_int_raw	ro	0x0	Watchdog interrupt raw status. Watch dog reset cannot clear this raw status. Write wdg_int_clr can clear this raw status.
4	wdg_ld_busy	ro	0x0	Watchdog load busy status 0: Watchdog is ready for new loading 1: Last loading is not completed Software must not load new value when this bit is busy, that is, this bit should be checked before any new loading. This bit is set after a new loading, and lasts two or three RTC clock cycles, about 60us - 92us.

50.6 WDG_INT_MASK				0x40508014
Bits	Field Name	Acc	Default	Description
0	wdg_int_mask	ro	0x0	Watchdog interrupt masked status

50.7 WDG_LOCK				0x40508C00
Bits	Field Name	Acc	Default	Description

15 : 0	wdg_lock	rw	0x0	Watchdog lock control Write 32'h1ACCE551 to this register to unlock watchdog. Write other value to this register to lock watchdog If reading this register, bit-0 is lock status, and other bits are reserved. If watchdog is locked, all control registers cannot be written by software.

51 bt_dfe_cfg

51.1 a0x000				0x40620000
Bits	Field Name	Acc	Default	Description
0	rxon_val	rw	0x0	
1	rxon_for	rw	0x0	
2	dm_sync_val	rw	0x0	
3	dm_sync_fix	rw	0x0	
4	fix_rxm	rw	0x0	
5	rx_le_mode	rw	0x0	
7 : 6	rx_rate	rw	0x0	
8	mrx_rstn	rw	0x1	
10	rf_rxon_val	rw	0x0	
11	rf_rxon_for	rw	0x0	
16	txon_val	rw	0x0	
17	txon_for	rw	0x0	
18	tx_tone	rw	0x0	
19	tx_pwr_fix	rw	0x0	
20	fix_txm	rw	0x0	
21	tx_le_mode	rw	0x0	
23 : 22	tx_rate	rw	0x0	
24	mtx_rstn	rw	0x1	
26	rf_txon_val	rw	0x0	
27	rf_txon_for	rw	0x0	

51.2 a0x004				0x40620004
Bits	Field Name	Acc	Default	Description
1 : 0	cfg_fix_rstn	rw	0x0	
27 : 16	cfg_fix_clk	rw	0xF00	

51.3 a0x008				0x40620008
Bits	Field Name	Acc	Default	Description
3 : 0	mslb_idx	rw	0x4	
16 : 8	cfg_clk_mdm	rw	0x0	

51.4 gll_ctrl				0x40620020
Bits	Field Name	Acc	Default	Description
0	gll_rxon_val	rw	0x0	
1	gll_rxon_fix	rw	0x0	
2	gll_txon_val	rw	0x0	
3	gll_txon_fix	rw	0x0	
4	gll_btle_val	rw	0x0	
5	gll_btle_fix	rw	0x0	
6	gll_tedr_val	rw	0x0	
7	gll_tedr_fix	rw	0x0	
9 : 8	gll_rate_val	rw	0x0	

10	gll_sync_fix	rw	0x0	
11	gll_rate_fix	rw	0x0	
12	gll_ifsl_val	rw	0x0	
13	gll_ifsl_fix	rw	0x0	
14	gll_trmp_val	rw	0x0	
15	gll_trmp_fix	rw	0x0	
22 : 16	gll_freq_val	rw	0x0	
23	gll_freq_fix	rw	0x0	
31 : 24	gll_tpwr_val	rw	0x0	

51.5 gll_ctrl2				0x40620024
Bits	Field Name	Acc	Default	Description
0	gll_tpwr_fix	rw	0x0	

51.6 a0x094				0x40620094
Bits	Field Name	Acc	Default	Description
14 : 0	dac_dc_i	rw	0x0	
30 : 16	dac_dc_q	rw	0x0	

51.7 a0x098				0x40620098
Bits	Field Name	Acc	Default	Description
14 : 0	tx_iqim_phase_err	rw	0x0	
30 : 16	tx_iqim_amp_err	rw	0x0	
31	tx_iqim_bypass	rw	0x1	

51.8 txdfe_rtcv0				0x4062009C
Bits	Field Name	Acc	Default	Description
27 : 0	txdfe_rtcv_val	rw	0x0	
28	txdfe_rtcv_fix	rw	0x0	

51.9 txdfe_rtcv1				0x406200A0
Bits	Field Name	Acc	Default	Description
3 : 0	txdfe_rtcv_thdr	rw	0x2	
7 : 4	txdfe_rtcv_coef_adj	rw	0x0	
11 : 8	txdfe_rtcv_thdr_min	rw	0x3	
15 : 12	txdfe_rtcv_thdr_max	rw	0xC	

51.10 rxdfe_rtcv0				0x406200A4
Bits	Field Name	Acc	Default	Description
27 : 0	rxdfe_rtcv_val	rw	0x0	
28	rxdfe_rtcv_fix	rw	0x0	

51.11 rxdfe_rtcv1				0x406200A8
Bits	Field Name	Acc	Default	Description
3 : 0	rxdfe_rtcv_thdr	rw	0x2	
7 : 4	rxdfe_rtcv_coef_adj	rw	0x0	
11 : 8	rxdfe_rtcv_thdr_min	rw	0x3	
15 : 12	rxdfe_rtcv_thdr_max	rw	0xC	
16	bt_rc_lpf_bypass	rw	0x0	
17	bt_rc_lpf_fir	rw	0x1	

51.12 a0x0f0				0x406200F0
Bits	Field Name	Acc	Default	Description
2 : 0	dbg_sel_top0	rw	0x7	
6 : 4	dbg_sel_top1	rw	0x7	
10 : 8	dbg_sel_top2	rw	0x7	
14 : 12	dbg_sel_top3	rw	0x7	
23 : 16	dbg_sel_mdm	rw	0xFF	
27 : 24	gdb_sel_dpll	rw	0xF	
31 : 28	gdb_sel_fpga	rw	0xF	

51.13 a0x100				0x40620100
Bits	Field Name	Acc	Default	Description
4 : 0	gdb_sel_bit00	rw	0x0	
12 : 8	gdb_sel_bit01	rw	0x1	
20 : 16	gdb_sel_bit02	rw	0x2	
28 : 24	gdb_sel_bit03	rw	0x3	

51.14 a0x104				0x40620104
Bits	Field Name	Acc	Default	Description
4 : 0	gdb_sel_bit04	rw	0x4	
12 : 8	gdb_sel_bit05	rw	0x5	
20 : 16	gdb_sel_bit06	rw	0x6	
28 : 24	gdb_sel_bit07	rw	0x7	

51.15 a0x108				0x40620108
Bits	Field Name	Acc	Default	Description
4 : 0	gdb_sel_bit08	rw	0x8	
12 : 8	gdb_sel_bit09	rw	0x9	
20 : 16	gdb_sel_bit10	rw	0xA	
28 : 24	gdb_sel_bit11	rw	0xB	

51.16 a0x10c				0x4062010C
Bits	Field Name	Acc	Default	Description
4 : 0	gdb_sel_bit12	rw	0xC	
12 : 8	gdb_sel_bit13	rw	0xD	
20 : 16	gdb_sel_bit14	rw	0xE	
28 : 24	gdb_sel_bit15	rw	0xF	

51.17 a0x110				0x40620110
Bits	Field Name	Acc	Default	Description
4 : 0	gdb_sel_bit16	rw	0x10	
12 : 8	gdb_sel_bit17	rw	0x11	
20 : 16	gdb_sel_bit18	rw	0x12	
28 : 24	gdb_sel_bit19	rw	0x13	

51.18 a0x114				0x40620114
Bits	Field Name	Acc	Default	Description
4 : 0	gdb_sel_bit20	rw	0x14	
12 : 8	gdb_sel_bit21	rw	0x15	
20 : 16	gdb_sel_bit22	rw	0x16	
28 : 24	gdb_sel_bit23	rw	0x17	

51.19 a0x118				0x40620118
Bits	Field Name	Acc	Default	Description
4 : 0	gdb_sel_bit24	rw	0x18	
12 : 8	gdb_sel_bit25	rw	0x19	
20 : 16	gdb_sel_bit26	rw	0x1A	
28 : 24	gdb_sel_bit27	rw	0x1B	

51.20 a0x11c				0x4062011C
Bits	Field Name	Acc	Default	Description
4 : 0	gdb_sel_bit28	rw	0x1C	
12 : 8	gdb_sel_bit29	rw	0x1D	
20 : 16	gdb_sel_bit30	rw	0x1E	
28 : 24	gdb_sel_bit31	rw	0x1F	

51.21 a0x120				0x40620120
Bits	Field Name	Acc	Default	Description
31 : 0	gdb_out_dat	rw	0x0	

51.22 a0x200				0x40620200
Bits	Field Name	Acc	Default	Description
15 : 0	cgen_val0	rw	0x0	
31 : 16	cgen_fix0	rw	0x0	

51.23 a0x204				0x40620204
Bits	Field Name	Acc	Default	Description
15 : 0	cgen_val1	rw	0x0	
31 : 16	cgen_fix1	rw	0x0	

51.24 a0x208				0x40620208
Bits	Field Name	Acc	Default	Description
15 : 0	cgen_val2	rw	0x0	
31 : 16	cgen_fix2	rw	0x0	

51.25 a0x20c				0x4062020C
Bits	Field Name	Acc	Default	Description
7 : 0	cgen_val3	rw	0x0	
23 : 16	cgen_fix3	rw	0x0	
31 : 24	cgen_free	rw	0xFF	

51.26 a0x210				0x40620210
Bits	Field Name	Acc	Default	Description
0	rxmdm_lp	rw	0x0	
1	ghdr_fec_en	rw	0x1	

51.27 cass_ctrl				0x40620280
Bits	Field Name	Acc	Default	Description
0	cass_en	rw	0x0	
1	cass_trx_en	rw	0x0	
2	afh_cass_rsten	rw	0x0	
3	afh_cass_clken	rw	0x0	

4	cass_clr	rw	0x0	
5	cass_ok	ro	0x0	
7 : 6	cass_ct	ro	0x0	
13 : 8	tim_cass_on	rw	0x6	
21 : 16	cass_num	rw	0x20	
29 : 24	cass_cnt	ro	0x0	

51.28 cass_var				0x40620284
Bits	Field Name	Acc	Default	Description
2 : 0	cass_prt_num	rw	0x5	
3	cass_frm_sel	rw	0x0	
6 : 4	tim_norm_dn	rw	0x2	
10 : 8	tim_cass_dn	rw	0x0	
14 : 12	cass_beta	rw	0x3	
18 : 16	cass_idx	rw	0x1	
19	cass_idx_fix	rw	0x1	
20	cass_mem_sel	rw	0x1	
21	cass_mem_stp	rw	0x1	

51.29 cass_rfpwr				0x40620288
Bits	Field Name	Acc	Default	Description
1 : 0	cass_rfpwr_grp0	rw	0x0	
5 : 4	cass_rfpwr_grp1	rw	0x1	
10 : 8	cass_rfpwr_grp2	rw	0x2	
14 : 12	cass_rfpwr_grp3	rw	0x4	
19 : 16	cass_rfpwr_grp4	rw	0x6	
23 : 20	cass_rfpwr_grp5	rw	0x0	
27 : 24	cass_rfpwr_grp6	rw	0x0	

51.30 cass_map0				0x40620290
Bits	Field Name	Acc	Default	Description
31 : 0	cass_map0	rw	0xFFFFFFFF	

51.31 cass_map1				0x40620294
Bits	Field Name	Acc	Default	Description
7 : 0	cass_map1	rw	0xFF	

51.32 cass_rssi0				0x406202A0
Bits	Field Name	Acc	Default	Description
31 : 0	cass_rssi0	ro	0x0	

51.33 cass_rssi1				0x406202A4
Bits	Field Name	Acc	Default	Description
31 : 0	cass_rssi1	ro	0x0	

51.34 cass_rssi2				0x406202A8
Bits	Field Name	Acc	Default	Description
31 : 0	cass_rssi2	ro	0x0	

51.35 cass_rssi3	0x406202AC

Bits	Field Name	Acc	Default	Description
31 : 0	cass_rssi3	ro	0x0	

51.36 cass_rssi4				0x406202B0
Bits	Field Name	Acc	Default	Description
31 : 0	cass_rssi4	ro	0x0	

51.37 cass_rssi5				0x406202B4
Bits	Field Name	Acc	Default	Description
31 : 0	cass_rssi5	ro	0x0	

51.38 cass_rssi6				0x406202B8
Bits	Field Name	Acc	Default	Description
31 : 0	cass_rssi6	ro	0x0	

51.39 cass_rssi7				0x406202BC
Bits	Field Name	Acc	Default	Description
31 : 0	cass_rssi7	ro	0x0	

51.40 cass_rssi8				0x406202C0
Bits	Field Name	Acc	Default	Description
31 : 0	cass_rssi8	ro	0x0	

51.41 cass_rssi9				0x406202C4
Bits	Field Name	Acc	Default	Description
31 : 0	cass_rssi9	ro	0x0	

51.42 a0x500				0x40620500
Bits	Field Name	Acc	Default	Description
0	adc_i_clkedge_sel	rw	0x0	
1	adc_q_clkedge_sel	rw	0x0	
2	adc_iq_format	rw	0x0	
3	adc_iq_swap	rw	0x0	
4	adc_i_negate	rw	0x0	
5	adc_q_negate	rw	0x0	
6	adc_i_dly	rw	0x0	
7	adc_q_dly	rw	0x0	
8	bypass_srrc	rw	0x0	
9	bypass_mixer	rw	0x0	
10	sdm_adc_dith_bypass	rw	0x1	
11	sdm_adc_dith_clkedge_sel	rw	0x0	

51.43 a0x504				0x40620504
Bits	Field Name	Acc	Default	Description
12 : 0	corsrrc_dphi_1m	rw	0x0	
28 : 16	corsrrc_dphi_2m	rw	0x0	

51.44 a0x508				0x40620508
Bits	Field Name	Acc	Default	Description

0	agc_fix_en	rw	0x0	
1	rfpwr_frm_sel	rw	0x1	
2	agc_rx_comb	rw	0x0	
3	pdet_vld_k_en	rw	0x0	
7 : 4	idx_ini	rw	0x3	
11 : 8	idx_min	rw	0x1	
15 : 12	idx_max	rw	0x3	
17 : 16	step_norm	rw	0x1	
19 : 18	step_thlg	rw	0x1	
21 : 20	step_upfl	rw	0x1	
23 : 22	step_dnfl	rw	0x1	
25 : 24	flg_thlg_fix	rw	0x0	
26	en_lg_stp	rw	0x1	
28	en_fix7	rw	0x1	
29	mod_fix7	rw	0x0	
30	agc_ramp_sel	rw	0x1	

51.45 a0x50c				0x4062050C
Bits	Field Name	Acc	Default	Description
1 : 0	sinc_over_th	rw	0x3	
3	sinc_over_en	rw	0x0	
6 : 4	time_init	rw	0x1	
14 : 8	time_pcal0	rw	0x20	
22 : 16	time_pcal1	rw	0x20	
30 : 24	time_tran_dig	rw	0x38	

51.46 a0x510				0x40620510
Bits	Field Name	Acc	Default	Description
5 : 0	time_lpfrst	rw	0xA	
15 : 8	dagc_mask	rw	0xFF	
19 : 16	thpup_val	rw	0x6	
23 : 20	thpdn_val	rw	0x6	
29 : 24	time_digtr	rw	0x14	
31 : 30	agc_din_sel	rw	0x2	

51.47 a0x514				0x40620514
Bits	Field Name	Acc	Default	Description
3 : 0	dagc_pth_ovr	rw	0x3	
7 : 4	tim_notch	rw	0x1	
14 : 8	dagc_pin_tar	rw	0x1A	
22 : 16	dagc_pth_max	rw	0xC	
30 : 24	dagc_pth_min	rw	0x28	
31	dagc_fix_en	rw	0x0	

51.48 a0x518				0x40620518
Bits	Field Name	Acc	Default	Description
6 : 0	vitb_pin_tar	rw	0xA	
11 : 8	thpup_val_vitb	rw	0x8	
15 : 12	thpdn_val_vitb	rw	0x8	
18 : 16	agc_din_sht	rw	0x0	
21 : 20	dagc_rssi_ps	rw	0x1	
23 : 22	dagc_rssi_ps_lr	rw	0x2	
24	rsten_srrc	rw	0x0	
25	rsten_notch	rw	0x1	

26	rsten_lpf	rw	0x1	
31 : 27	tim_rcdly	rw	0x6	

51.49 a0x51c				0x4062051C
Bits	Field Name	Acc	Default	Description
0	bypass_dccancel	rw	0x0	
1	dc_calib_en	rw	0x1	
2	dc_cancel_en	rw	0x1	
3	dc_est_restart_dr	rw	0x0	
6 : 4	dc_alpha_rst_ctrl	rw	0x6	
11 : 8	dc_est_wait_time	rw	0x7	
13 : 12	dcc_bw_ct2	rw	0x1	
15 : 14	dc_est_ctrl	rw	0x1	
18 : 16	dc_scale_factor	rw	0x3	
19	dcc_fil_bypass	rw	0x1	
22 : 20	dc_avg_len_coef	rw	0x4	
23	dc_est_mode	rw	0x0	
26 : 24	dcc_mode_ct	rw	0x6	
30 : 28	dc_reg_wr_ctrl	rw	0x1	
31	dc_reg_update_en	rw	0x1	

51.50 a0x520				0x40620520
Bits	Field Name	Acc	Default	Description
15 : 0	dcc_bw_ct	rw	0x0	
23 : 16	dcc_tmr_ct	rw	0x30	
30 : 24	dcc_tmr_ct2	rw	0x10	

51.51 a0x528				0x40620528
Bits	Field Name	Acc	Default	Description
0	notch_en	rw	0x0	
7 : 4	notch_a	rw	0xC	
21 : 8	notch_b	rw	0x3BF3	
26 : 24	dc_reg_index	rw	0x0	
29 : 28	dc_reg_rd_sel	rw	0x0	
30	dc_reg_set_en	rw	0x0	
31	dc_reg_set_dr	rw	0x0	

51.52 a0x52c				0x4062052C
Bits	Field Name	Acc	Default	Description
3 : 0	dagc_pth_ovr_lr	rw	0x3	
14 : 8	dagc_pin_tar_lr	rw	0x14	
22 : 16	dagc_pth_max_lr	rw	0xC	
30 : 24	dagc_pth_min_lr	rw	0x1C	
31	dagc_fix_en_lr	rw	0x0	

51.53 a0x530				0x40620530
Bits	Field Name	Acc	Default	Description
3 : 0	rfdb_idx00	rw	0x0	
7 : 4	rfdb_idx01	rw	0x0	
11 : 8	rfdb_idx02	rw	0x2	
15 : 12	rfdb_idx03	rw	0x1	
19 : 16	rfdb_idx04	rw	0x7	
23 : 20	rfdb_idx05	rw	0x1	

27 : 24	rfdb_idx06	rw	0x3	
31 : 28	rfdb_idx07	rw	0x1	

51.54 a0x534				0x40620534
Bits	Field Name	Acc	Default	Description
6 : 0	rfdb_offset	rw	0x6E	
13 : 8	time_tran_ana	rw	0xD	
19 : 16	pdet_tbl_val	rw	0x4	
20	pdet_tbl_fix	rw	0x1	

51.55 a0x544				0x40620544
Bits	Field Name	Acc	Default	Description
14 : 0	rx_data_i_reg	rw	0x0	
15	rx_data_i_set_dr	rw	0x0	
30 : 16	rx_data_q_reg	rw	0x0	
31	rx_data_q_set_dr	rw	0x0	

51.56 a0x5a0				0x406205A0
Bits	Field Name	Acc	Default	Description
6 : 0	thmax_val0	rw	0x0	
14 : 8	thmax_val1	rw	0x18	
22 : 16	thmax_val2	rw	0x21	
30 : 24	thmax_val3	rw	0x20	

51.57 a0x5a4				0x406205A4
Bits	Field Name	Acc	Default	Description
6 : 0	thmin_val0	rw	0x30	
14 : 8	thmin_val1	rw	0x42	
22 : 16	thmin_val2	rw	0x39	
30 : 24	thmin_val3	rw	0x42	

51.58 a0x5a8				0x406205A8
Bits	Field Name	Acc	Default	Description
2 : 0	agc_alp_a1	rw	0x4	
6 : 4	agc_alp_b1	rw	0x4	
10 : 8	agc_alp_a2	rw	0x2	
14 : 12	agc_alp_b2	rw	0x2	
18 : 16	agc_alp_a3	rw	0x2	
22 : 20	agc_alp_b3	rw	0x2	
26 : 24	agc_alp_c	rw	0x3	
28	agc_alp_alt	rw	0x0	
29	agc_alp_infrm	rw	0x1	

51.59 a0x5ac				0x406205AC
Bits	Field Name	Acc	Default	Description
3 : 0	thmin_dlt	rw	0x6	
7 : 4	thmax_dlt	rw	0x6	
10 : 8	thmin_mrg	rw	0x3	
14 : 12	thmax_mrg	rw	0x3	
22 : 16	thmin_too	rw	0x7F	
30 : 24	thmax_too	rw	0x0	

51.60 a0x5b0				0x406205B0
Bits	Field Name	Acc	Default	Description
2 : 0	prt_num_bt	rw	0x5	
6 : 4	prt_num_le1m	rw	0x5	
10 : 8	prt_num_le2m	rw	0x3	
14 : 12	prt_num_lelr	rw	0x5	

51.61 a0x5b4				0x406205B4
Bits	Field Name	Acc	Default	Description
14 : 0	corlpf_dphi_1m	rw	0x4A4	
15	corlpf_dphi_fix	rw	0x0	
30 : 16	corlpf_dphi_2m	rw	0x3DE	
31	corlpf_bps	rw	0x0	

51.62 a0x5b8				0x406205B8
Bits	Field Name	Acc	Default	Description
6 : 0	thmin_wb	rw	0xC	
14 : 8	thmax_wb	rw	0xA	
18 : 16	agc_alp_wb	rw	0x2	

51.63 a0x5bc				0x406205BC
Bits	Field Name	Acc	Default	Description
6 : 0	thmin_sb	rw	0x9	
14 : 8	thmax_sb	rw	0x0	
21 : 16	dgc_bagc_tar	rw	0x24	
23	dgc_bagc_en	rw	0x1	
27 : 24	dgc_bagc_thd	rw	0x3	

51.64 a0x5c0				0x406205C0
Bits	Field Name	Acc	Default	Description
31 : 0	clkn_th_a0	rw	0x2000100	

51.65 a0x5c4				0x406205C4
Bits	Field Name	Acc	Default	Description
31 : 0	clkn_th_a1	rw	0x2000100	

51.66 a0x5c8				0x406205C8
Bits	Field Name	Acc	Default	Description
31 : 0	clkn_th_a2	rw	0x2000100	

51.67 a0x5cc				0x406205CC
Bits	Field Name	Acc	Default	Description
31 : 0	clkn_th_a3	rw	0x2000100	

51.68 a0x5d0				0x406205D0
Bits	Field Name	Acc	Default	Description
31 : 0	clkn_th_a4	rw	0x2000100	

51.69 a0x5d4	0x406205D4

Bits	Field Name	Acc	Default	Description
31 : 0	clkn_th_a5	rw	0x2000100	

51.70 a0x5d8				0x406205D8
Bits	Field Name	Acc	Default	Description
31 : 0	clkn_th_a6	rw	0x2000100	

51.71 a0x5dc				0x406205DC
Bits	Field Name	Acc	Default	Description
31 : 0	clkn_th_a7	rw	0x2000100	

51.72 a0x5f0				0x406205F0
Bits	Field Name	Acc	Default	Description
2 : 0	idx_tws	rw	0x7	
6 : 4	idx_nul	rw	0x7	
15 : 8	frm_en_ll	rw	0x0	
23 : 16	frm_en_mrx	ro	0x0	

51.73 a0x810				0x40620810
Bits	Field Name	Acc	Default	Description
9 : 0	StopDelayReg	rw	0x0	
11 : 10	DumpSize	rw	0x0	
15 : 12	DumpStartWrAddr	rw	0x0	
19 : 16	DumpDataSel	rw	0x0	
23 : 20	StopTrigSel	rw	0x0	

51.74 a0x814				0x40620814
Bits	Field Name	Acc	Default	Description
0	DumpEnable	rw	0x0	
1	bt_dump_clken	rw	0x0	
2	ReStopTrigMode	rw	0x0	
3	ManualStopReg	rw	0x0	
4	DumpWrapModeN	rw	0x0	
5	PhyDumpMuxSel	rw	0x1	
7 : 6	DumpSamplRateSel	rw	0x0	
11 : 8	PhyDumpRamEn	rw	0x0	
16 : 12	bt_dump_clksel	rw	0x0	
19	bt_dump_clkinv	rw	0x0	

51.75 a0x81c				0x4062081C
Bits	Field Name	Acc	Default	Description
0	imbala_cancel_bypass__	rw	0x1	
1	imbala_cal_dr_____	rw	0x0	
2	imbala_calc_rels_____	rw	0x0	
3	imbala_cancel_hold_dr_	rw	0x0	
7 : 4	imbala_cancel_bw_ct_wq	rw	0x4	
11 : 8	imbala_cancel_bw_ct_wa	rw	0x3	
31 : 16	imbala_reg_sel_____	rw	0x0	

51.76 a0x820				0x40620820
Bits	Field Name	Acc	Default	Description

14 : 0	imbala_cancel_wq_reg0_	rw	0x0	
30 : 16	imbala_cancel_wa_reg0_	rw	0x0	

51.77 a0x824				0x40620824
Bits	Field Name	Acc	Default	Description
14 : 0	imbala_cancel_wq_reg1	rw	0x0	
30 : 16	imbala_cancel_wa_reg1_	rw	0x0	

51.78 a0x828				0x40620828
Bits	Field Name	Acc	Default	Description
14 : 0	imbala_cancel_wq_reg2_	rw	0x0	
30 : 16	imbala_cancel_wa_reg2	rw	0x0	

51.79 a0x82c				0x4062082C
Bits	Field Name	Acc	Default	Description
14 : 0	imbala_cancel_wq_reg3_	rw	0x0	
30 : 16	imbala_cancel_wa_reg3	rw	0x0	

51.80 a0x830				0x40620830
Bits	Field Name	Acc	Default	Description
30 : 0	rfpll_sdm_freq_reg	rw	0x0	x*(1-v¿¿(11))
31	rfpll_sdm_freq_dr	rw	0x0	

51.81 a0x834				0x40620834
Bits	Field Name	Acc	Default	Description
3 : 0	fif_tx2m	rw	0x5	
7 : 4	fif_tx1m	rw	0x3	
11 : 8	fif_rx2m	rw	0x5	
15 : 12	fif_rx1m	rw	0x3	
29 : 16	freq_flo_val	rw	0x0	
31	freq_flo_fix	rw	0x0	

51.82 ppm_838				0x40620838
Bits	Field Name	Acc	Default	Description
9 : 0	ppm_val	rw	0x0	
12	ppm_en	rw	0x0	
13	ppm_up	rw	0x0	
27 : 16	flo_shnk	rw	0x0	

51.83 fref_tx_hm				0x4062083C
Bits	Field Name	Acc	Default	Description
14 : 0	fref_num_tx_lo	rw	0x9C	
30 : 16	fref_num_tx_md	rw	0xB6	

51.84 fref_tx				0x40620840
Bits	Field Name	Acc	Default	Description
15 : 8	fref_den_tx	rw	0x1	
30 : 16	fref_num_tx	rw	0xD0	

51.85 fref_rx				0x40620844
Bits	Field Name	Acc	Default	Description
31	fref_num_tx_fix_hi	rw	0x0	

51.86 coef_rfwf				0x4062084C
Bits	Field Name	Acc	Default	Description
9 : 0	rfwf_rx_den	rw	0x1D8	
25 : 16	rfwf_tx_num	rw	0x280	

51.87 a0x86c				0x4062086C
Bits	Field Name	Acc	Default	Description
0	dc_est_restart_reg	rw	0x0	

51.88 a0x880				0x40620880
Bits	Field Name	Acc	Default	Description
31 : 0	bt_mdm_st0	ro	0x0	

51.89 a0x884				0x40620884
Bits	Field Name	Acc	Default	Description
31 : 0	bt_mdm_st1	ro	0x0	

51.90 a0x888				0x40620888
Bits	Field Name	Acc	Default	Description
31 : 0	bt_mdm_st2	ro	0x0	

51.91 a0x88c				0x4062088C
Bits	Field Name	Acc	Default	Description
31 : 0	bt_mdm_st3	ro	0x0	

51.92 a0x890				0x40620890
Bits	Field Name	Acc	Default	Description
31 : 0	bt_mdm_st4	ro	0x0	

51.93 a0x894				0x40620894
Bits	Field Name	Acc	Default	Description
31 : 0	bt_mdm_st5	ro	0x0	

51.94 a0x898				0x40620898
Bits	Field Name	Acc	Default	Description
31 : 0	bt_mdm_st6	ro	0x0	

51.95 a0x89c				0x4062089C
Bits	Field Name	Acc	Default	Description
31 : 0	bt_mdm_st7	ro	0x0	

51.96 a0x8ac				0x406208AC
Bits	Field Name	Acc	Default	Description

31 : 0	bt_mdm_st8	ro	0x0	

51.97 a0x8b0				0x406208B0
Bits	Field Name	Acc	Default	Description
23 : 0	lna_pdet_st	ro	0x0	

52 bt_mdm_cfg

52.1 cfg_mem_sr1rw				0x40621000
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_mem_sr1rw	rw	0x2488	

52.2 cfg_mem_sr2rw				0x40621004
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_mem_sr2rw	rw	0x20D6	

52.3 cfg_mem_spram				0x40621008
Bits	Field Name	Acc	Default	Description
15 : 0	cfg_mem_spram	rw	0x24C4	

52.4 a0x010				0x40621010
Bits	Field Name	Acc	Default	Description
9 : 0	gh_bt	rw	0x143	
25 : 16	gh_le	rw	0x200	
29 : 28	edr_coef	rw	0x0	

52.5 a0x014				0x40621014
Bits	Field Name	Acc	Default	Description
3 : 0	dly_spt_tran	rw	0x8	
7 : 4	dly_sym_tran	rw	0x4	
11 : 8	dly_spt_edr	rw	0x0	
15 : 12	dly_sym_edr	rw	0x1	
19 : 16	dly_spt_gfsk	rw	0xA	
23 : 20	dly_sym_gfsk	rw	0x3	
27 : 24	dly_sym_gend	rw	0x4	
30 : 28	edr_s0	rw	0x0	
31	txiq13m_swap	rw	0x0	

52.6 a0x018				0x40621018
Bits	Field Name	Acc	Default	Description
1 : 0	amp_dly_13m	rw	0x2	
4	tx_notch_en	rw	0x1	
5	tx_gegap_en	rw	0x1	
11 : 8	tx_notch_step	rw	0x4	
15 : 12	dly_spt_tranp	rw	0x3	
19 : 16	dly_sym_tranp	rw	0x6	
23 : 20	tx_gegap_step	rw	0x5	

52.7 a0x01c	0x4062101C

Bits	Field Name	Acc	Default	Description
14 : 0	dphi_fo	rw	0x762	

52.8 a0x020				0x40621020
Bits	Field Name	Acc	Default	Description
7 : 0	phi_ini	rw	0x20	
11 : 8	dly_spt_gfsk_2m	rw	0xB	
15 : 12	dly_sym_gfsk_2m	rw	0x3	
19 : 16	aup_step_2m	rw	0x7	
23 : 20	adn_step_2m	rw	0x7	
27 : 24	dly_txen_off	rw	0x6	

52.9 a0x024				0x40621024
Bits	Field Name	Acc	Default	Description
3 : 0	dly_sym_txen_2m	rw	0x2	
7 : 4	dly_spt_txen_2m	rw	0x3	
11 : 8	dly_sym_txen	rw	0x2	
15 : 12	dly_spt_txen	rw	0x3	
19 : 16	phi_step	rw	0x2	
23 : 20	aup_step	rw	0x7	
27 : 24	atr_step	rw	0x4	
31 : 28	adn_step	rw	0x7	

52.10 a0x028				0x40621028
Bits	Field Name	Acc	Default	Description
7 : 0	tx_pwr_val	rw	0x60	
15 : 8	tx_pwr_val_tws	rw	0x60	
16	tx_pwr_fix_tws	rw	0x1	
29 : 20	gh_tws	rw	0x143	

52.11 a0x030				0x40621030
Bits	Field Name	Acc	Default	Description
5 : 0	scl_gfsk	rw	0x1C	
13 : 8	scl_gedr	rw	0x1C	
21 : 16	scl_edr	rw	0x20	

52.12 a0x034				0x40621034
Bits	Field Name	Acc	Default	Description
7 : 0	th_dphi	rw	0x80	
15 : 8	th_amp	rw	0x30	
17 : 16	zcp_sel	rw	0x1	
23 : 20	mask_flt_mode	rw	0x3	
31 : 24	dph_prot_th	rw	0x64	

52.13 a0x040				0x40621040
Bits	Field Name	Acc	Default	Description
0	am_bps	rw	0x1	
1	pm_bps	rw	0x1	
6 : 4	pm_shift	rw	0x0	
11 : 8	ampm_thr	rw	0xF	

52.14 a0x044				0x40621044
Bits	Field Name	Acc	Default	Description
9 : 0	am_p0	rw	0x0	
25 : 16	pm_p0	rw	0x0	

52.15 a0x048				0x40621048
Bits	Field Name	Acc	Default	Description
9 : 0	am_p1	rw	0x20	
25 : 16	pm_p1	rw	0x0	

52.16 a0x04c				0x4062104C
Bits	Field Name	Acc	Default	Description
9 : 0	am_p2	rw	0x40	
25 : 16	pm_p2	rw	0x0	

52.17 a0x050				0x40621050
Bits	Field Name	Acc	Default	Description
9 : 0	am_p3	rw	0x60	
25 : 16	pm_p3	rw	0x0	

52.18 a0x054				0x40621054
Bits	Field Name	Acc	Default	Description
9 : 0	am_p4	rw	0x80	
25 : 16	pm_p4	rw	0x0	

52.19 a0x058				0x40621058
Bits	Field Name	Acc	Default	Description
9 : 0	am_p5	rw	0xA0	
25 : 16	pm_p5	rw	0x0	

52.20 a0x05c				0x4062105C
Bits	Field Name	Acc	Default	Description
9 : 0	am_p6	rw	0xC0	
25 : 16	pm_p6	rw	0x0	

52.21 a0x060				0x40621060
Bits	Field Name	Acc	Default	Description
9 : 0	am_p7	rw	0xE0	
25 : 16	pm_p7	rw	0x0	

52.22 a0x064				0x40621064
Bits	Field Name	Acc	Default	Description
9 : 0	am_p8	rw	0x100	
25 : 16	pm_p8	rw	0x0	

52.23 a0x068				0x40621068
Bits	Field Name	Acc	Default	Description
9 : 0	am_p9	rw	0x120	
25 : 16	pm_p9	rw	0x0	

52.24 a0x06c				0x4062106C
Bits	Field Name	Acc	Default	Description
9 : 0	am_p10	rw	0x140	
25 : 16	pm_p10	rw	0x0	

52.25 a0x070				0x40621070
Bits	Field Name	Acc	Default	Description
9 : 0	am_p11	rw	0x160	
25 : 16	pm_p11	rw	0x0	

52.26 a0x074				0x40621074
Bits	Field Name	Acc	Default	Description
9 : 0	am_p12	rw	0x180	
25 : 16	pm_p12	rw	0x0	

52.27 a0x078				0x40621078
Bits	Field Name	Acc	Default	Description
9 : 0	am_p13	rw	0x1A0	
25 : 16	pm_p13	rw	0x0	

52.28 a0x07c				0x4062107C
Bits	Field Name	Acc	Default	Description
9 : 0	am_p14	rw	0x1C0	
25 : 16	pm_p14	rw	0x0	

52.29 a0x080				0x40621080
Bits	Field Name	Acc	Default	Description
9 : 0	am_p15	rw	0x1E0	
25 : 16	pm_p15	rw	0x0	

52.30 a0x084				0x40621084
Bits	Field Name	Acc	Default	Description
9 : 0	am_p16	rw	0x1FF	
25 : 16	pm_p16	rw	0x0	

52.31 a0x400				0x40621400
Bits	Field Name	Acc	Default	Description
23 : 0	demd_g_bt	rw	0xB3B0B	

52.32 a0x404				0x40621404
Bits	Field Name	Acc	Default	Description
23 : 0	demd_g_le	rw	0x135A13	

52.33 a0x408				0x40621408
Bits	Field Name	Acc	Default	Description
23 : 0	sync_g_bt	rw	0xB3B0B	

52.34 a0x40c	0x4062140C

Bits	Field Name	Acc	Default	Description
23 : 0	sync_g_le	rw	0x135A13	

52.35 a0x410				0x40621410
Bits	Field Name	Acc	Default	Description
4 : 0	vit_u_err	rw	0xA	
13 : 8	vit_u_dc	rw	0x8	
21 : 16	vit_angle_th_sel	rw	0x10	
26 : 24	vit_u_sam	rw	0x4	
28	vit_amp_en	rw	0x1	

52.36 a0x414				0x40621414
Bits	Field Name	Acc	Default	Description
23 : 0	sync_g_tws	rw	0xB3B0B	

52.37 a0x418				0x40621418
Bits	Field Name	Acc	Default	Description
23 : 0	demd_g_tws	rw	0xB3B0B	

52.38 a0x420				0x40621420
Bits	Field Name	Acc	Default	Description
4 : 0	gbt_dof_u_err	rw	0x8	
13 : 8	gbt_dof_u_dc	rw	0x1	
20 : 16	gbt_dof_coef_ek	rw	0x8	

52.39 a0x424				0x40621424
Bits	Field Name	Acc	Default	Description
4 : 0	gbt_don_u_err	rw	0xA	
13 : 8	gbt_don_u_dc	rw	0x8	
20 : 16	gbt_don_coef_ek	rw	0x8	

52.40 a0x428				0x40621428
Bits	Field Name	Acc	Default	Description
4 : 0	gbt_cci_u_err	rw	0x8	
13 : 8	gbt_cci_u_dc	rw	0x1	
20 : 16	gbt_cci_coef_ek	rw	0x10	
31 : 24	gbt_phie_max	rw	0x80	

52.41 a0x42c				0x4062142C
Bits	Field Name	Acc	Default	Description
4 : 0	gle_dof_u_err	rw	0x8	
13 : 8	gle_dof_u_dc	rw	0x1	
20 : 16	gle_dof_coef_ek	rw	0x8	

52.42 a0x430				0x40621430
Bits	Field Name	Acc	Default	Description
4 : 0	gle_don_u_err	rw	0xA	
13 : 8	gle_don_u_dc	rw	0x8	
20 : 16	gle_don_coef_ek	rw	0x8	

52.43 a0x434				0x40621434
Bits	Field Name	Acc	Default	Description
4 : 0	gle_cci_u_err	rw	0x8	
13 : 8	gle_cci_u_dc	rw	0x1	
20 : 16	gle_cci_coef_ek	rw	0xA	
31 : 24	gle_phie_max	rw	0x80	

52.44 a0x438				0x40621438
Bits	Field Name	Acc	Default	Description
0	gfsk_mode_ek	rw	0x0	
7 : 4	gfsk_cci_bias	rw	0x8	
13 : 8	gfsk_path_alpha	rw	0x8	
21 : 16	gfsk_angle_th_sel	rw	0x8	
26 : 24	gfsk_u_sam	rw	0x4	

52.45 a0x43c				0x4062143C
Bits	Field Name	Acc	Default	Description
4 : 0	edr_u_step0	rw	0xA	
13 : 8	edr_u_dc0	rw	0x28	
20 : 16	edr_u_step1	rw	0x2	
29 : 24	edr_u_dc1	rw	0x2	

52.46 a0x440				0x40621440
Bits	Field Name	Acc	Default	Description
4 : 0	edr_u_step2	rw	0x8	
13 : 8	edr_u_dc2	rw	0x1	
23 : 16	edr_thdadapt	rw	0x80	
24	edr_enhance	rw	0x1	

52.47 a0x444				0x40621444
Bits	Field Name	Acc	Default	Description
3 : 0	edr_u_sam	rw	0x4	
12 : 8	edr_angle_th_sel	rw	0x8	

52.48 a0x448				0x40621448
Bits	Field Name	Acc	Default	Description
3 : 0	edr_dof_bias	rw	0x8	
7 : 4	edr_cci_bias	rw	0x7	
11 : 8	edr_sym_alpha	rw	0x4	
23 : 16	edr_path_alpha	rw	0x4	
24	edr_dphi_mode	rw	0x0	
25	foini_en	rw	0x0	

52.49 a0x44c				0x4062144C
Bits	Field Name	Acc	Default	Description
8 : 4	edr_sync_len	rw	0xC	
13 : 12	edr_fo_scl	rw	0x3	
17 : 16	edr_ini_md	rw	0x1	
20	edr_err_md	rw	0x0	
21	edr_dc_en	rw	0x0	
30 : 24	sync_ng2e	rw	0x48	

52.50 a0x450				0x40621450
Bits	Field Name	Acc	Default	Description
5 : 0	sync_align_leco	rw	0x4	
13 : 8	sync_align_le1m	rw	0x4	
21 : 16	sync_align_le2m	rw	0x4	
29 : 24	sync_align_bt	rw	0x4	

52.51 a0x454				0x40621454
Bits	Field Name	Acc	Default	Description
5 : 0	sync_align_edr	rw	0x2	

52.52 a0x458				0x40621458
Bits	Field Name	Acc	Default	Description
7 : 0	lr_gmax_p	rw	0x66	
15 : 8	lr_gmax_n	rw	0x66	
23 : 16	bt_gmax_p	rw	0xFF	
31 : 24	bt_gmax_n	rw	0xFF	

52.53 a0x45c				0x4062145C
Bits	Field Name	Acc	Default	Description
7 : 0	lr_gstm_thd	rw	0x1D	
12 : 8	lr_getm_thd	rw	0x4	
23 : 16	lr_gsmd_thd	rw	0x1A	
28 : 24	lr_gemd_thd	rw	0x6	

52.54 a0x460				0x40621460
Bits	Field Name	Acc	Default	Description
7 : 0	lr_gscr_thd	rw	0x16	
12 : 8	lr_gecr_thd	rw	0x4	
17 : 16	lr_cors_thc	rw	0x2	
21 : 20	lr_slid_win	rw	0x1	
29 : 24	foe_mro	rw	0x4	

52.55 a0x464				0x40621464
Bits	Field Name	Acc	Default	Description
4 : 0	bt_g_ratio_thd	rw	0x16	
14 : 8	bt_crg_thd	rw	0x12	
21 : 16	bt_hde_thd	rw	0x3F	
29 : 24	bt_cre_thd	rw	0xD	

52.56 a0x468				0x40621468
Bits	Field Name	Acc	Default	Description
1 : 0	bt_crs_win	rw	0x2	
6 : 4	bt_crs_thd	rw	0x4	
9 : 8	bt_fin_win	rw	0x1	

52.57 a0x46c				0x4062146C
Bits	Field Name	Acc	Default	Description
4 : 0	l1_g_ratio_thd	rw	0x16	
14 : 8	l1_crg_thd	rw	0xF	
21 : 16	l1_hde_thd	rw	0x3F	

29 : 24	l1_cre_thd	rw	0xA	

52.58 a0x470				0x40621470
Bits	Field Name	Acc	Default	Description
1 : 0	l1_crs_win	rw	0x2	
6 : 4	l1_crs_thd	rw	0x4	
9 : 8	l1_fin_win	rw	0x1	

52.59 a0x474				0x40621474
Bits	Field Name	Acc	Default	Description
4 : 0	l2_g_ratio_thd	rw	0x16	
14 : 8	l2_crg_thd	rw	0xF	
21 : 16	l2_hde_thd	rw	0x3F	
29 : 24	l2_cre_thd	rw	0xA	

52.60 a0x478				0x40621478
Bits	Field Name	Acc	Default	Description
1 : 0	l2_crs_win	rw	0x2	
6 : 4	l2_crs_thd	rw	0x4	
9 : 8	l2_fin_win	rw	0x1	

52.61 a0x47c				0x4062147C
Bits	Field Name	Acc	Default	Description
10 : 0	sync_foe_val	rw	0x0	
12	sync_foe_fix	rw	0x0	

52.62 a0x480				0x40621480
Bits	Field Name	Acc	Default	Description
0	edr_sym_len_vld	rw	0x0	
7 : 4	edr_sym_len_adj	rw	0x2	
29 : 16	edr_sym_len	rw	0x0	

52.63 a0x484				0x40621484
Bits	Field Name	Acc	Default	Description
11 : 0	vit_bit_num	rw	0x100	
12	vit_len_fix	rw	0x0	
18 : 16	vit_hdr_tbs	rw	0x2	

52.64 a0x488				0x40621488
Bits	Field Name	Acc	Default	Description
7 : 0	snr_cnte_th	rw	0x0	
15 : 8	snr_eth	rw	0x1E	
23 : 16	snr_avg_th	rw	0x0	
24	snr_elen	rw	0x0	
25	snr_err_mode	rw	0x0	

52.65 a0x48c				0x4062148C
Bits	Field Name	Acc	Default	Description
2 : 0	gfsk_snr_enul	rw	0x4	
6 : 4	gfsk_snr_anul	rw	0x4	

10 : 8	edr_snr_enul	rw	0x5	
14 : 12	edr_snr_anul	rw	0x5	

52.66 a0x544				0x40621544
Bits	Field Name	Acc	Default	Description
19 : 0	wr_gpadc1	rw	0x0	

52.67 a0x548				0x40621548
Bits	Field Name	Acc	Default	Description
15 : 0	wr_gpadc2	rw	0x0	

52.68 a0x57c				0x4062157C
Bits	Field Name	Acc	Default	Description
0	notchp_bps	rw	0x1	
1	notchp_fix	rw	0x0	
7 : 4	notchp_bw	rw	0x4	
19 : 8	notchp_frqi	rw	0x0	
31 : 20	notchp_frqq	rw	0x0	

52.69 a0x580				0x40621580
Bits	Field Name	Acc	Default	Description
0	notchn_bps	rw	0x1	
1	notchn_fix	rw	0x0	
7 : 4	notchn_bw	rw	0x4	
19 : 8	notchn_frqi	rw	0x0	
31 : 20	notchn_frqq	rw	0x0	

52.70 a0x584				0x40621584
Bits	Field Name	Acc	Default	Description
3 : 0	aci_agcth	rw	0x0	
9 : 4	aci_mask	rw	0x0	
15 : 12	aci_iir_dly	rw	0x2	

52.71 a0x588				0x40621588
Bits	Field Name	Acc	Default	Description
31 : 0	notch_chmap0	rw	0x0	

52.72 a0x58c				0x4062158C
Bits	Field Name	Acc	Default	Description
31 : 0	notch_chmap1	rw	0x0	

52.73 a0x590				0x40621590
Bits	Field Name	Acc	Default	Description
15 : 0	notch_chmap2	rw	0x0	
19 : 16	notch_bw_lelr	rw	0xB	
23 : 20	notch_bw_le2m	rw	0xB	
27 : 24	notch_bw_bt2m	rw	0xB	
31 : 28	notch_bw_bt1m	rw	0xB	

52.74 a0x594				0x40621594
Bits	Field Name	Acc	Default	Description
11 : 0	notch_frqi_1m	rw	0x7EA	
23 : 12	notch_frqq_1m	rw	0x12D	

52.75 a0x598				0x40621598
Bits	Field Name	Acc	Default	Description
11 : 0	notch_frqi_2m	rw	0x7C3	
23 : 12	notch_frqq_2m	rw	0x1F2	

52.76 a0x870				0x40621870
Bits	Field Name	Acc	Default	Description
31 : 0	bt_rsvd_cfg0	rw	0x766C6003	

52.77 a0x874				0x40621874
Bits	Field Name	Acc	Default	Description
31 : 0	bt_rsvd_cfg1	rw	0x7B756F69	

52.78 a0x878				0x40621878
Bits	Field Name	Acc	Default	Description
31 : 0	bt_rsvd_cfg2	rw	0x0	

52.79 a0x87c				0x4062187C
Bits	Field Name	Acc	Default	Description
31 : 0	bt_rsvd_cfg3	rw	0x0	

52.80 a0x8b4				0x406218B4
Bits	Field Name	Acc	Default	Description
23 : 0	phie_crc_st	ro	0x0	

53 bt_rf_interface

53.1 bt_pu_reg1				0x40622000
Bits	Field Name	Acc	Default	Description
0	bt_pu_dpa_reg	rw	0x0	
1	bt_pu_dpa_dr	rw	0x0	
2	bt_sdm_adc_ana_rstn_reg	rw	0x0	
3	bt_sdm_adc_ana_rstn_dr	rw	0x0	
4	bt_sdm_adc_dig_rstn_reg	rw	0x0	
5	bt_sdm_adc_dig_rstn_dr	rw	0x0	
6	bt_sdm_adc_byp_mode_reg	rw	0x0	
7	bt_sdm_adc_byp_mode_dr	rw	0x0	
8	bt_pu_sdm_adc_reg	rw	0x0	
9	bt_pu_sdm_adc_dr	rw	0x0	
10	bt_tia_rstn_reg	rw	0x0	
11	bt_tia_rstn_dr	rw	0x0	
12	bt_pu_tia_reg	rw	0x0	
13	bt_pu_tia_dr	rw	0x0	
14	bt_pu_rmx_reg	rw	0x0	
15	bt_pu_rmx_dr	rw	0x0	
16	bt_pu_lna_reg	rw	0x0	

17	bt_pu_lna_dr	rw	0x0	
18	bt_dpll_gro_rstn_reg	rw	0x0	
19	bt_dpll_gro_rstn_dr	rw	0x0	
20	bt_pu_dpll_reg	rw	0x0	
21	bt_pu_dpll_dr	rw	0x0	
22	bt_pu_dco_reg	rw	0x0	
23	bt_pu_dco_dr	rw	0x0	
24	bt_pu_dly_dpa_ldo_reg	rw	0x0	
25	bt_pu_dly_dpa_ldo_dr	rw	0x0	
26	bt_pu_dpa_ldo_reg	rw	0x0	
27	bt_pu_dpa_ldo_dr	rw	0x0	
28	bt_chop_bg_en_reg	rw	0x0	
29	bt_chop_bg_en_dr	rw	0x0	
30	bt_pu_chop_bg_reg	rw	0x0	
31	bt_pu_chop_bg_dr	rw	0x0	

53.2 bt_pu_reg2				0x40622004
Bits	Field Name	Acc	Default	Description
1 : 0	bt_dpa_reg_pu_bit	rw	0x2	
3 : 2	bt_dpa_pu_bit	rw	0x2	
5 : 4	bt_dpll_pu_bit	rw	0x2	
7 : 6	bt_dco_pu_bit	rw	0x2	
9 : 8	bt_sdm_adc_pu_bit	rw	0x2	
11 : 10	bt_tia_pu_bit	rw	0x2	
13 : 12	bt_rmx_pu_bit	rw	0x2	
15 : 14	bt_lna_pu_bit	rw	0x2	
16	bt_pu_tdac	rw	0x0	
17	bt_trx_cap_sw_sel_reg	rw	0x0	
18	bt_trx_cap_sw_sel_dr	rw	0x0	

53.3 bt_test_reg				0x40622008
Bits	Field Name	Acc	Default	Description
2 : 0	bt_test_ac_enable	rw	0x0	
3	bt_tia2gpio_en	rw	0x0	
4	bt_test_enable_dpa_ldo	rw	0x0	
5	bt_test_enable_dpa	rw	0x0	
6	bt_test_ac_enable_dpll	rw	0x0	
7	bt_test_enable_chop_bg	rw	0x0	
8	bt_test_enable_tdac	rw	0x0	
9	bt_test_enable_sdm_adc	rw	0x0	
10	bt_test_enable_tia	rw	0x0	
11	bt_test_enable_rmx	rw	0x0	
12	bt_test_enable_lna	rw	0x0	
15 : 13	bt_test_bit	rw	0x0	

53.4 bt_td_reg1				0x4062200C
Bits	Field Name	Acc	Default	Description
1 : 0	bt_pd_td0	rw	0x2	
4 : 2	cm_mdll_dcc_rstn_td2	rw	0x3	
6 : 5	bt_pu_lna_td1	rw	0x2	
8 : 7	bt_pu_rmx_td1	rw	0x2	
10 : 9	bt_sdm_adc_byp_mode_td1	rw	0x2	
12 : 11	bt_tia_rstn_1_td1	rw	0x2	
14 : 13	bt_tia_rstn_0_td1	rw	0x2	
17 : 15	bt_dpll_gro_rstn_tx_td2	rw	0x3	

20 : 18	bt_dpll_gro_rstn_rx_td2	rw	0x3	
22 : 21	bt_pu_dco_td1	rw	0x2	
25 : 23	bt_pu_dly_dpa_ldo_td2	rw	0x3	
27 : 26	bt_pu_dpa_ldo_td3	rw	0x2	
29 : 28	bt_chop_bg_en_td1	rw	0x2	
31 : 30	bt_pu_chop_bg_td1	rw	0x2	

53.5 bt_td_reg2				0x40622010
Bits	Field Name	Acc	Default	Description
2 : 0	bt_dpa_cal_en_td2	rw	0x3	
4 : 3	bt_pu_dpa_tws_td1	rw	0x2	
6 : 5	bt_pu_dpa_td1	rw	0x2	
9 : 7	simple_kvco_cal_en_td2	rw	0x3	

53.6 bt_lna_reg				0x40622014
Bits	Field Name	Acc	Default	Description
0	bt_tia_vcm_sel	rw	0x0	
2 : 1	bt_tia_pwrdet_ibit	rw	0x2	
3	bt_tia_pwrdet_en	rw	0x0	
4	bt_rmx_decap_en	rw	0x0	
5	bt_lna_fb_res_en	rw	0x0	
6	bt_lna_ppf_sel	rw	0x0	
7	bt_lna_vcmn_cal_in	ro	0x0	
8	bt_lna_vcmp_cal_in	ro	0x0	
9	bt_lna_vcm_cal_en	rw	0x0	
10	bt_lna_vcm_cal_clk_edge_sel	rw	0x0	
12 : 11	bt_lna_pwrdet_level	rw	0x2	
13	bt_lna_iref_sel	rw	0x0	
17 : 14	bt_lna_reg_vbit	rw	0x4	
18	bt_lna_pwrdet_en	rw	0x0	

53.7 bt_tia_reg				0x40622018
Bits	Field Name	Acc	Default	Description
2 : 0	bt_tia_cal_v_range	rw	0x3	
5 : 3	bt_tia_cal_i_range	rw	0x3	
8 : 6	bt_tia_vcm_vbit	rw	0x3	
11 : 9	bt_tia_ldo_vref_vbit	rw	0x3	
14 : 12	bt_tia_op_q_rbit	rw	0x3	
17 : 15	bt_tia_op_mil_rbit	rw	0x3	
20 : 18	bt_tia_op_mil_cbit	rw	0x3	

53.8 bt_sdmadc_reg				0x4062201C
Bits	Field Name	Acc	Default	Description
1 : 0	bt_sdm_adc_dvdd_pwrsw_bit	rw	0x0	
3 : 2	bt_sdm_adc_sar_insel	rw	0x0	
7 : 4	bt_sdm_adc_dly_bit	rw	0x1	
8	bt_sdm_adc_clk_phsel	rw	0x0	
9	bt_sdm_adc_cal_en	rw	0x0	
12 : 10	bt_sdm_adc_cbit	rw	0x4	
16 : 13	bt_sdm_adc_vcal_bit	rw	0x6	
18 : 17	bt_sdm_adc_sar_en	rw	0x0	
19	bt_sdm_adc_sdm_en	rw	0x1	
20	bt_sdm_adc_dwa_en	rw	0x1	
21	bt_sdm_adc_dith_en	rw	0x1	

22	bt_sdm_adc_clk_sar_div2_en	rw	0x1	

53.9 bt_dpa_reg1				0x40622020
Bits	Field Name	Acc	Default	Description
0	bt_dpa_pm_edge_sel	rw	0x1	
1	bt_dpa_vref_cal_sel	rw	0x1	
2	bt_dpa_drv_pwr_sel	rw	0x1	
3	bt_dpa_reg_bypass	rw	0x1	
4	bt_dpa_clk_edge_sel	rw	0x1	
5	bt_dpa_retime_sel	rw	0x1	
7 : 6	bt_dpa_sign_dly_sel	rw	0x2	
8	bt_dpa_mode_sel	rw	0x1	
9	bt_dpa_cal_in	ro	0x0	
12 : 10	bt_dpa_div2p5_dly_sel	rw	0x3	
13	bt_dpa_cal_clk_edge_sel	rw	0x1	
14	bt_dpa_cal_input_swap	rw	0x1	
16 : 15	bt_dpa_cal_clk_sel	rw	0x2	
17	bt_dpa_comp_en_reg	rw	0x1	
18	bt_dpa_comp_en_dr	rw	0x1	
19	bt_dpa_out_cal_sel	rw	0x1	
20	bt_dpa_vco_cal_sel	rw	0x1	
23 : 21	bt_dpa_capbank_bit	rw	0x3	
25 : 24	bt_chop_bg_osc_bit	rw	0x2	
26	bt_chop_bg_osc_en	rw	0x1	

53.10 bt_dpa_reg2				0x40622024
Bits	Field Name	Acc	Default	Description
7 : 0	bt_dpa_rdac_data_out	ro	0x0	
8	bt_dpa_rdac_data_out_sel	rw	0x1	
9	bt_dpa_pll_test_mode	rw	0x1	
11 : 10	bt_dpa_balun_tap_bit	rw	0x2	
12	bt_dpa_auto_pm_sync	rw	0x1	
15 : 13	bt_dpa_ant_cbit_tx	rw	0x3	
18 : 16	bt_dpa_ant_cbit_rx	rw	0x3	
19	bt_dpa_ant_cbit_dr	rw	0x1	
20	bt_dpa_div_mode_sel_dr	rw	0x1	

53.11 bt_dpa_ldo_reg				0x40622028
Bits	Field Name	Acc	Default	Description
7 : 0	bt_dpa_ldo_r-dac_data_out_tws_rx	rw	0x8	
8	bt_dpa_ldo_rdac_data_out_dr	rw	0x1	
16 : 9	bt_dpa_ldo_rdac_data_out_rx	rw	0x8	
20 : 17	bt_dpa_ldo_rbit1	rw	0x4	
21	bt_dpa_ldo_vref_sel	rw	0x1	
22	bt_dpa_ldo_vref_cal_en	rw	0x1	
23	bt_dpa_ldo_sink_current_en	rw	0x1	
24	bt_dpa_ldo_current_limit_en	rw	0x1	
27 : 25	bt_dpa_ldo_current_limit_bit	rw	0x3	
30 : 28	bt_dpa_ldo_sink_current_bit	rw	0x3	
31	bt_dpa_ldo_pull0	rw	0x1	

53.12 bt_dpll_reg1				0x4062202C
Bits	Field Name	Acc	Default	Description

5 : 0	bt_dpll_drv_bit	rw	0x6	
9 : 6	bt_dpll_presc_reg_vbit	rw	0x4	
13 : 10	bt_dpll_gro_reg_vbit	rw	0x4	
15 : 14	bt_dpll_gro_ldo_vbit	rw	0x2	
16	bt_dco_mode_6g_dr	rw	0x0	
17	bt_dco_var_reg_bypass	rw	0x0	
21 : 18	bt_dco_var_reg_vbit	rw	0x4	
22	bt_dco_dvar_clk_edge_sel	rw	0x1	

53.13 bt_dpll_reg2 — 0x40622030

Bits	Field Name	Acc	Default	Description
0	bt_dpll_div_mode_dr	rw	0x1	
1	bt_dpll_sdadc_clk_en_reg	rw	0x1	
2	bt_dpll_sdadc_clk_en_dr	rw	0x1	
4 : 3	bt_dpll_dly_sel0	rw	0x2	
6 : 5	bt_dpll_dly_sel1	rw	0x2	
8 : 7	bt_dpll_dly_sel2	rw	0x2	
10 : 9	bt_dpll_dly_sel3	rw	0x2	
12 : 11	bt_dpll_dly_sel4	rw	0x2	
14 : 13	bt_dpll_dly_sel5	rw	0x2	
16 : 15	bt_dpll_switch_rbit	rw	0x2	
17	bt_dpll_div_clk_edge_sel	rw	0x1	
18	bt_dpll_fref_sel_tx	rw	0x1	
19	bt_dpll_fref_sel_tws_tx	rw	0x1	
20	bt_dpll_fref_sel_rx	rw	0x1	
21	bt_dpll_fref_sel_tws_rx	rw	0x1	
22	bt_dpll_fref_sel_dr	rw	0x1	
23	bt_dpll_fbc_sel	rw	0x1	
24	bt_dpll_cal_clk_sel	rw	0x1	
26 : 25	bt_dpll_vco_cal_sel	rw	0x2	
28 : 27	bt_dpll_chopper_clk_sel	rw	0x2	
29	bt_dpll_clk2p4g_en	rw	0x1	

53.14 bt_tdac_reg — 0x40622034

Bits	Field Name	Acc	Default	Description
4 : 0	bt_tdac_ibit	rw	0x5	
5	bt_tdac_iref_sel	rw	0x1	
8 : 6	bt_tdac_vtr_ibit	rw	0x3	
11 : 9	bt_tdac_cscd_vbit	rw	0x3	
12	bt_tdac_clk_edge_sel	rw	0x1	
17 : 13	bt_tdac_offset_bit	rw	0x5	
18	bt_tdac_classb_en	rw	0x1	

53.15 bt_misc_reg — 0x40622038

Bits	Field Name	Acc	Default	Description

53.16 bt_ifconf_reg1 — 0x4062203C

Bits	Field Name	Acc	Default	Description
0	bt_tia_swap_en_1m_l	rw	0x0	
1	bt_tia_swap_en_1m_h	rw	0x1	
2	bt_tia_swap_en_2m_l	rw	0x0	
3	bt_tia_swap_en_2m_h	rw	0x1	
4	bt_tia_lpf_mode_1m_l	rw	0x0	
5	bt_tia_lpf_mode_1m_h	rw	0x0	

6	bt_tia_lpf_mode_2m_l	rw	0x0	
7	bt_tia_lpf_mode_2m_h	rw	0x0	
8	bt_tia_swap_en_dr	rw	0x0	
9	bt_tia_lpf_mode_dr	rw	0x0	
10	bt_tia_rf_rbit_dr	rw	0x0	
11	bt_tia_if_bit_dr	rw	0x0	
12	bt_tia_bw_cbit_dr	rw	0x0	

53.17 bt_ifconf_reg2				0x40622040
Bits	Field Name	Acc	Default	Description
1 : 0	bt_sdm_adc_nr_mode_1m_l	rw	0x2	
3 : 2	bt_sdm_adc_nr_mode_1m_h	rw	0x2	
5 : 4	bt_sdm_adc_nr_mode_2m_l	rw	0x2	
7 : 6	bt_sdm_adc_nr_mode_2m_h	rw	0x2	
8	bt_sdm_adc_iq_swap_en_1m_l	rw	0x0	
9	bt_sdm_adc_iq_swap_en_1m_h	rw	0x1	
10	bt_sdm_adc_iq_swap_en_2m_l	rw	0x0	
11	bt_sdm_adc_iq_swap_en_2m_h	rw	0x1	
13 : 12	bt_sdm_adc_iq_mode_1m_l	rw	0x2	
15 : 14	bt_sdm_adc_iq_mode_1m_h	rw	0x2	
17 : 16	bt_sdm_adc_iq_mode_2m_l	rw	0x2	
19 : 18	bt_sdm_adc_iq_mode_2m_h	rw	0x2	
20	bt_sdm_adc_nr_mode_dr	rw	0x0	
21	bt_sdm_adc_iq_swap_en_dr	rw	0x0	
22	bt_sdm_adc_iq_mode_dr	rw	0x0	

53.18 bt_agc_dc_reg1				0x40622044
Bits	Field Name	Acc	Default	Description
0	bt_lna_vcmn_cal_bit_dr	rw	0x0	
1	bt_lna_vcmp_cal_bit_dr	rw	0x0	
2	bt_tia_q_cal_bit_dr	rw	0x0	
3	bt_tia_i_cal_bit_dr	rw	0x0	
8 : 4	bt_lna_vcmn_cal_bit_reg	rw	0x0	
13 : 9	bt_lna_vcmp_cal_bit_reg	rw	0x0	
19 : 14	bt_tia_q_cal_bit_reg	rw	0x20	
25 : 20	bt_tia_i_cal_bit_reg	rw	0x20	

53.19 bt_soft_reset_reg				0x40622048
Bits	Field Name	Acc	Default	Description
0	soft_reset	rw	0x0	

53.20 bt_man_crtl_reg				0x4062204C
Bits	Field Name	Acc	Default	Description
3 : 0	tx_gain_reg	rw	0x0	
4	tx_gain_dr	rw	0x0	
5	tx_gain_dr_pulse	rw	0x0	
9 : 6	rx_gain_reg	rw	0x0	
10	rx_gain_dr	rw	0x0	
11	rx_gain_dr_pulse	rw	0x0	
12	rxon_reg	rw	0x0	
13	rxon_dr	rw	0x0	
14	txon_reg	rw	0x0	
15	txon_dr	rw	0x0	
16	rfon	rw	0x0	

17	twson_reg	rw	0x0	
18	twson_dr	rw	0x0	
19	high_flo_reg	rw	0x0	
20	high_flo_dr	rw	0x0	
21	gfsk_2m_reg	rw	0x0	
22	gfsk_2m_dr	rw	0x0	
23	bt_gro_rstn_sel	rw	0x1	
24	simple_kvco_cal_bypass	rw	0x0	
25	debug_cfg	rw	0x0	

53.21 bt_calclk_reg				0x40622050
Bits	Field Name	Acc	Default	Description
5 : 0	cal_clk_div_num	rw	0x6	
6	cal_clk_en	rw	0x0	

53.22 bt_dpa_cal_ctrl_reg				0x40622054
Bits	Field Name	Acc	Default	Description
7 : 0	bt_dpa_cal_init_wait_time	rw	0x8	
13 : 8	bt_dpa_cal_loop_wait_time	rw	0x6	
14	bt_dpa_cal_en_reg	rw	0x0	
15	bt_dpa_cal_en_dr	rw	0x0	
16	bt_dpa_cal_in_polar	rw	0x0	
17	bt_dpa_cal_done	ro	0x0	

53.23 bt_rxgain_mem_ctrl_reg				0x40622058
Bits	Field Name	Acc	Default	Description
5 : 0	rxgain_mem_addr_cfg	rw	0x0	
6	rxgain_mem_wen_pulse	rw	0x0	
7	rxgain_mem_ren_pulse	rw	0x0	
8	rxgain_mem_cfg	rw	0x0	
9	clk_rxgain_en	rw	0x0	
10	clk_rxgain_sel	rw	0x0	
11	rxgain_mem_rw_done	ro	0x0	

53.24 bt_rxgain_mem_wdata_reg				0x4062205C
Bits	Field Name	Acc	Default	Description
31 : 0	rxgain_mem_in_cfg	rw	0x0	

53.25 bt_rxgain_mem_rdata_reg				0x40622060
Bits	Field Name	Acc	Default	Description
31 : 0	rxgain_mem_out_rd	ro	0x0	

53.26 bt_txgain_mem_ctrl_reg				0x40622064
Bits	Field Name	Acc	Default	Description
4 : 0	txgain_mem_addr_cfg	rw	0x0	
5	txgain_mem_wen_pulse	rw	0x0	
6	txgain_mem_ren_pulse	rw	0x0	
7	txgain_mem_cfg	rw	0x0	
8	clk_txgain_en	rw	0x0	
9	clk_txgain_sel	rw	0x0	
10	txgain_mem_rw_done	ro	0x0	

53.27 bt_txgain_mem_wdata_reg				0x40622068
Bits	Field Name	Acc	Default	Description
31 : 0	txgain_mem_in_cfg	rw	0x0	

53.28 bt_txgain_mem_rdata_reg				0x4062206C
Bits	Field Name	Acc	Default	Description
31 : 0	txgain_mem_out_rd	ro	0x0	

53.29 bt_dig_reserved_reg				0x40622070
Bits	Field Name	Acc	Default	Description

53.30 bt_pu_done_reg				0x40622074
Bits	Field Name	Acc	Default	Description
0	txon_done	ro	0x0	
1	rxon_done	ro	0x0	
2	rfon_done	ro	0x0	

53.31 bt_rxgain_table_out_reg0				0x40622078
Bits	Field Name	Acc	Default	Description
31 : 0	rxgain_table_out_0	ro	0x0	

53.32 bt_rxgain_table_out_reg1				0x4062207C
Bits	Field Name	Acc	Default	Description
31 : 0	rxgain_table_out_1	ro	0x0	

53.33 bt_rxgain_table_out_reg2				0x40622080
Bits	Field Name	Acc	Default	Description
31 : 0	rxgain_table_out_2	ro	0x0	

53.34 bt_rxgain_table_out_reg3				0x40622084
Bits	Field Name	Acc	Default	Description
31 : 0	rxgain_table_out_3	ro	0x0	

53.35 bt_txgain_table_out_reg0				0x40622088
Bits	Field Name	Acc	Default	Description
31 : 0	txgain_table_out_0	ro	0x0	

53.36 bt_txgain_table_out_reg1				0x4062208C
Bits	Field Name	Acc	Default	Description
31 : 0	txgain_table_out_1	ro	0x0	

53.37 bt_agc_reserved_reg				0x40622090
Bits	Field Name	Acc	Default	Description

53.38 bt_apc_reserved_reg				0x40622094
Bits	Field Name	Acc	Default	Description

54 pmu_rtc0

54.1 pmu_rtc0_cfg0				0x70000000
Bits	Field Name	Acc	Default	Description
0	pmu_rtc0_rg_update	w1c	0x0	
1	rtc_rg_pb_in-t_debc_seq_pd_bypass0	rw	0x1	
2	rtc_rg_pb_in-t_debc_seq_pd_bypass1	rw	0x0	
3	rtc_rg_gpio_-debc_seq_pd_bypass0	rw	0x0	
4	rtc_rg_gpio_-debc_seq_pd_bypass1	rw	0x0	
7 : 5	rtc_rg_bg_pd_seq_num	rw	0x1	
8	rtc_rg_force_pbint_neg_pwroff	rw	0x0	
9	rtc_rg_cm_co_xtal_det_out	ro	0x0	
10	rtc_rg_cm_co_xtal_det_clr_en	rw	0x0	
11	rtc_rg_cm_co_xtal_det_hw_en	rw	0x1	
12	rtc_rg_cm_co_xtal_det_sw_en	rw	0x0	
14 : 13	rtc_rg_cm_co_xtal_det_th	rw	0x3	

54.2 pmu_rtc0_cfg1				0x70000004
Bits	Field Name	Acc	Default	Description
4 : 0	rtc_rg_ldo_rf_pu_seq_num	rw	0x8	
9 : 5	rtc_rg_ldo_vrtc08_pu_seq_num	rw	0x5	
17 : 10	rtc_rg_vbat_rstn_th	rw	0x10	
18	rtc_rg_pbint_-long_rst_repower_en	rw	0x0	
19	rtc_rg_pbint_long_rst_pd_en	rw	0x0	
20	rtc_rg_bor_repower_en	rw	0x0	
21	rtc_rg_bor_pwroff_en	rw	0x0	
29 : 22	rtc_rg_bor_high_deglitch_th	rw	0xA	
30	rtc_rg_bor_high_deglitch_en	rw	0x0	
31	rtc_rg_bor_en	rw	0x0	

54.3 pmu_rtc0_cfg2				0x70000008
Bits	Field Name	Acc	Default	Description
3 : 0	rtc_rg_ldo_rf_vbit	rw	0xC	
11 : 4	rtc_rg_pbint_-por_trig_cnt_low_th	rw	0x8	
19 : 12	rtc_rg_pbint_-por_trig_cnt_high_th	rw	0x0	
23 : 20	rtc_rg_gpio_cfg	rw	0x0	
24	rtc_rg_charger_on_en	rw	0x1	
25	rtc_rg_charger_on_inv_sel	rw	0x0	
26	rtc_rg_pu_clk_32k_rc_sw	rw	0x0	
27	rtc_rg_pwr_on_rdy_sw	rw	0x0	
31 : 28	rtc_rg_dbg_mux	rw	0x0	

54.4 pmu_rtc0_cfg3				0x7000000C
Bits	Field Name	Acc	Default	Description
7 : 0	rtc_rg_gpio_-por_trig_cnt_low_th	rw	0x8	
15 : 8	rtc_rg_gpio_-por_trig_cnt_high_th	rw	0x8	
16	rtc_rg_wdg_rstn_repower_en	rw	0x0	
17	rtc_rg_wdg_rstn_pd_en	rw	0x1	

18	rtc_rg_pu_dcdc_ldo_mode_sel	rw	0x0	
19	rtc_rg_alm_power_on_en	rw	0x0	
20	rtc_rg_aon_gpio_pwr_on_en	rw	0x0	
21	rtc_rg_aon_gpio_pwr_off_en	rw	0x0	
22	rtc_rg_power_off_pmu_rtc0_en	rw	0x1	
23	rtc_rg_gpio_power_off_rtc0_en	rw	0x0	
24	rtc_rg_wdg_r-stn_power_off_rtc0_en	rw	0x1	
25	rtc_rg_long_pbint_power_off_en	rw	0x1	
26	rtc_rg_pb_in-t_long_rst_power_off_rtc0_en	rw	0x0	
27	rtc_rg_device_set	rw	0x1	
28	rtc_rg_resetn_rtc_cnt	rw	0x0	
29	rtc_rg_presetn_rtc_cnt	rw	0x0	
30	rtc_rg_wdg_rst_rtc_rf_en	rw	0x0	
31	rtc_rg_aon_gpio_neg_clr_en	rw	0x1	

54.5 pmu_rtc0_cfg4				0x70000010
Bits	Field Name	Acc	Default	Description
0	rtc_rg_int_en	rw	0x0	
1	rtc_rg_rtc_cnt_int_en	rw	0x0	
6 : 2	rtc_rg_int_mask	rw	0x0	
7	rtc_rg_rtc_cnt_irq_mask	rw	0x0	
8	rtc_rg_int_clr1	w1c	0x0	
9	rtc_rg_int_clr2	w1c	0x0	
10	rtc_rg_int_clr3	w1c	0x0	
11	rtc_rg_int_clr4	w1c	0x0	
12	rtc_rg_int_clr5	w1c	0x0	
13	rtc_rg_rtc_cnt_irq_clr	w1c	0x0	
18 : 14	rtc_rg_int_raw_status	ro	0x0	
19	rtc_cnt_irq_raw_status	ro	0x0	
24 : 20	rtc_rg_int_mask_status	ro	0x0	
25	rtc_cnt_irq_mask_status	ro	0x0	
28 : 26	rtc_rg_gpioa_hold	rw	0x0	
29	rtc_rg_gpiob_hold	rw	0x0	
30	rtc_rg_fls_hold	rw	0x0	

54.6 pmu_rtc0_cfg5				0x70000014
Bits	Field Name	Acc	Default	Description
31 : 0	rtc_rg_rtc_cnt_ld_value	rw	0x0	

54.7 pmu_rtc0_cfg6				0x70000018
Bits	Field Name	Acc	Default	Description
31 : 0	rtc_cnt_value	ro	0x0	

54.8 pmu_rtc0_cfg7				0x7000001C
Bits	Field Name	Acc	Default	Description
0	rtc_rg_rtc_cnt_enable	rw	0x0	
1	rtc_rg_rtc_cnt_ld_vld	w1c	0x0	
2	rtc_rg_rtc_cnt_mode	rw	0x1	
6 : 3	rtc_rg_bor_low_deglitch_th	rw	0x4	
7	rtc_rg_bor_low_deglitch_en	rw	0x0	
8	rtc_rg_xtal_40m_26m_soft_sel	rw	0x0	

9	rtc_rg_xtal_-40m_26m_hw_detect_high_latch_clr	rw	0x0	
10	xtal_40m_26m_-hw_detect_high_latch	ro	0x0	
11	rtc_rg_pb_int_long_por_set_clr	w1c	0x0	
12	rtc_rg_alm_int_set_clr	w1c	0x0	
13	rtc_rg_wdg_pwr_on_set_clr	w1c	0x0	
14	rtc_rg_bor_pwr_on_set_clr	w1c	0x0	
15	rtc_rg_por_chip_vbat_flag	ro	0x0	
23 : 16	rtc_rg_pwr_on_src_status	ro	0x0	
31 : 24	rtc_rg_pbint_debc_cnt_th	rw	0x0	

54.9 pmu_rtc0_wdg4_cnt_ini				0x70000020
Bits	Field Name	Acc	Default	Description
31 : 0	rtc_rg_wdg4_cnt_ini	rw	0x2625A00	

54.10 rtc_rg_reserved0				0x70000024
Bits	Field Name	Acc	Default	Description

54.11 rtc_rg_reserved1				0x70000028
Bits	Field Name	Acc	Default	Description

55 pmu_rtc1

55.1 pmu_pd_ctrl0				0x70001000
Bits	Field Name	Acc	Default	Description
0	rtc_rg_dcdc_ldo_rf_mode_sel	rw	0x0	
1	rtc_rg_pwr_force_ldo_avdd18	rw	0x0	
2	rtc_rg_pwr_force_ldo_vcore08	rw	0x0	
3	rtc_rg_pwr_force_dcdc_vcore08	rw	0x0	
4	rtc_rg_pwr_force_ldo_pa	rw	0x0	
5	rtc_rg_ldo_avdd18_pd	rw	0x0	
6	rtc_rg_ldo_vcore08_pd	rw	0x0	
7	rtc_rg_dcdc_vcore08_pd	rw	0x1	
8	rtc_rg_ldo_pa_pd	rw	0x0	
9	rtc_rg_bg_pd_set	rw	0x0	
10	rtc_rg_ldo_vrtc08_pd_set	rw	0x0	
11	rtc_rg_dcdc_ldo_rf_pd_set	rw	0x0	
12	rtc_rg_pmu_core_rstn_set	rw	0x0	
13	rtc_rg_pmu_core_iso_set	rw	0x0	
14	rtc_rg_pwr_force_ldo_vflash	rw	0x0	
15	rtc_rg_ldo_vflash_pd	rw	0x0	
16	rtc_rg_ret_n	rw	0x0	
17	rtc_rg_pwr_force_chopp_bg	rw	0x0	
18	rtc_rg_chopp_bg_pd	rw	0x0	
19	rtc_rg_chopp_bg_choppen	rw	0x1	
20	rtc_rg_pmu_c-hopp_bg_pu_lpvref	rw	0x0	
21	rtc_rg_pmu_c-hopp_bg_sw_lpvref_set	rw	0x0	
22	rtc_rg_gpio_sel_ldo18	rw	0x1	
23	rtc_rg_reg18_ulp_pu_set	rw	0x0	
24	rtc_rg_pu_dcdc_core_mode_sel	rw	0x0	
25	rtc_rg_auto_pd_ldo_vcore08_en	rw	0x0	

55.2 pmu_pd_ctrl1				0x70001004
Bits	Field Name	Acc	Default	Description
0	rtc_rg_pwr_off_seq_en	rw	0x0	
1	rtc_rg_ext_soft_rst	w1c	0x0	
2	rtc_rg_core_iso_en	rw	0x0	
3	rtc_rg_global_rstn_en	rw	0x0	
5	rtc_rg_dcdc_en_avdd18int	rw	0x1	
6	rtc_rg_dcdc_en_avdd18	rw	0x0	
7	rtc_rg_coreon_set	rw	0x1	
8	rtc_rg_lvl_pullr_enb	rw	0x1	
9	rtc_rg_core_sw_fast_clk_sel_set	rw	0x1	
11 : 10	rtc_rg_avddsense_sel	rw	0x0	
12	rtc_rg_pu_vrtc0sense	rw	0x0	
13	rtc_rg_pu_vbatsense	rw	0x0	

55.3 pmu_seq_num0				0x70001008
Bits	Field Name	Acc	Default	Description
4 : 0	rtc_rg_slp_xtal_pu_seq_num	rw	0x2	
9 : 5	rtc_rg_reset_b_seq_num	rw	0x6	
14 : 10	rtc_rg_ldo_pa_pu_seq_num	rw	0xA	
19 : 15	rtc_rg_ldo_avdd18_pu_seq_num	rw	0x6	
24 : 20	rtc_rg_ldo_d-cdc_vcore08_pu_seq_num	rw	0x1	
31 : 25	rtc_rg_dcdc_dll_start_th	rw	0x30	

55.4 pmu_seq_num1				0x7000100C
Bits	Field Name	Acc	Default	Description
4 : 0	rtc_rg_slp_reset_b_seq_num	rw	0x3	
9 : 5	rtc_rg_slp_xen_en_seq_num	rw	0x2	
14 : 10	rtc_rg_ldo_d-cdc_vcore08_dvfs_seq_num	rw	0xF	
19 : 15	rtc_rg_ldo_v-rtc08_dvfs_seq_num	rw	0xF	
24 : 20	rtc_rg_dcdc_rf_dvfs_seq_num	rw	0xF	
31 : 25	rtc_rg_dcdc_dll_rstn_th	rw	0x18	

55.5 pmu_slp_ctrl0				0x70001010
Bits	Field Name	Acc	Default	Description
0	rtc_rg_slp_ldo_pd_en	rw	0x0	
1	rtc_rg_rtc_slp_pmu_rtc0_pd_en	rw	0x0	
2	rtc_rg_rtc_slp_pmu_rtc1_pd_en	rw	0x0	
3	rtc_rg_ldo_pa_slp_pd_en	rw	0x0	
4	rtc_rg_reg18_ulp_slp_pu_en	rw	0x0	
5	rtc_rg_ldo_d-cdc_vcore08_slp_pd_en	rw	0x0	
6	rtc_rg_ldo_avdd18_slp_pd_en	rw	0x0	
7	rtc_rg_ldo_vrtc08_slp_pd_en	rw	0x0	
8	rtc_rg_core_iso_slp_en	rw	0x0	
9	rtc_rg_coreon_slp_pd_en	rw	0x0	
10	rtc_rg_xtal_slp_pd_en	rw	0x0	
11	rtc_rg_lpo26m_slp_pd_en	rw	0x0	
12	rtc_rg_rc_256k_slp_pd_en	rw	0x0	
13	rtc_rg_ldo_vflash_slp_pd_en	rw	0x0	
14	rtc_rg_gpio_sel_ldo18_slp_en	rw	0x0	
15	rtc_rg_dcdc_-core_adc_slp_pd_en	rw	0x0	

16	rtc_rg_dcdc_rf_adc_slp_pd_en	rw	0x0	
17	rtc_rg_chopp_bg_slp_pd_en	rw	0x0	
18	rtc_rg_cm_xt-al_slp_reg_buf_bypass	rw	0x0	
19	rtc_rg_xdblr_slp_pd_en	rw	0x0	
20	rtc_rg_ldo_v-core08_awake_pu_en	rw	0x0	
21	rtc_rg_aon13_sw2v13_slp_en	rw	0x0	
22	rtc_rg_ldo_a-vdd18_ulpmode_slp_en	rw	0x0	
26 : 23	rtc_rg_deep_sleep_awake_en	rw	0x0	
27	rtc_rg_xtal_slp_hold_en	rw	0x0	

55.6 pmu_slp_ctrl1				0x70001014
Bits	Field Name	Acc	Default	Description
0	rtc_rg_reset_b_slp_en	rw	0x0	
1	rtc_rg_slp_rtc_pclk_gate_en	rw	0x0	
2	rtc_rg_slp_core_clk_fast_sel_en	rw	0x0	
3	rtc_rg_xtal_slp_lp_en	rw	0x0	
4	rtc_rg_gate_to_dbb_slp_en	rw	0x0	
5	rtc_rg_ldo_pa_slp_drop_en	rw	0x0	
6	rtc_rg_ldo_vrtc08_dvfs_slp_en	rw	0x0	
7	rtc_rg_ldo_d-cdc_vcore08_dvfs_slp_en	rw	0x0	
8	rtc_rg_ldo_avdd18_slp_lp_en	rw	0x0	
9	rtc_rg_ldo_avdd18_slp_drop_en	rw	0x0	
10	rtc_rg_dcdc_-core_hys_pfm_mode_slp_en	rw	0x0	
11	rtc_rg_dcdc_-rf_hys_pfm_mode_slp_en	rw	0x0	
12	rtc_rg_dcdc_rf_dvfs_slp_en	rw	0x0	
13	rtc_rg_dcdc_-core_deep_slp_slp_en	rw	0x0	
14	rtc_rg_ldo_pa_slp_lp_en	rw	0x0	
15	rtc_rg_lpo26m_slp_dis_en	rw	0x0	
16	rtc_rg_rc_256k_slp_dis_en	rw	0x0	
17	rtc_rg_clk_26m_slp_dis_en	rw	0x0	
18	rtc_rg_clk_comp_slp_dis_en	rw	0x0	
19	rtc_rg_clk_buf_slp_dis_en	rw	0x0	
20	rtc_rg_clk_6p5m_slp_dis_en	rw	0x0	
21	rtc_rg_dcdc_rf_clk_sel_slp_en	rw	0x0	
22	rtc_rg_dcdc_rf_deep_slp_slp_en	rw	0x0	
23	rtc_rg_clk_52m_slp_dis_en	rw	0x0	
24	rtc_rg_clk_26m_dly_slp_dis_en	rw	0x0	
25	rtc_rg_ldo_vflash_slp_lp_en	rw	0x0	
26	rtc_rg_ldo_vflash_slp_drop_en	rw	0x0	
27	rtc_rg_xtal_avdd_sel_slp_en	rw	0x0	
28	rtc_rg_xtal_clk_div4_sel_slp_en	rw	0x0	
29	rtc_rg_dcdc_core_clk_sel_slp_en	rw	0x0	
30	rtc_rg_ldo_vcore08_slp_lp_en	rw	0x0	
31	rtc_rg_chopp_-bg_sw_lpvref_lp_en	rw	0x0	

55.7 pmu_clk_ctrl0				0x70001018
Bits	Field Name	Acc	Default	Description
0	rtc_rg_clk_d-iv_128k_step_offset_update	rw	0x0	

8 : 1	rtc_rg_clk_d-iv_128k_step_offset_normal	rw	0x0	
16 : 9	rtc_rg_clk_d-iv_128k_step_offset_lp	rw	0x0	
17	rtc_rg_clk_d-iv_128k_lp_mode_h_reg	rw	0x0	
18	rtc_rg_clk_d-iv_128k_lp_mode_h_dr	rw	0x0	
19	rtc_rg_clk_6p5m_div_128k_en	rw	0x1	
20	rtc_rg_xtal_hold_set	rw	0x0	
28 : 21	rtc_rg_pmu_clk_manual_enable	rw	0xFF	

55.8 pmu_clk_ctrl1				0x7000101C
Bits	Field Name	Acc	Default	Description
4 : 0	rtc_rg_xtal_cap_rf_on_bit	rw	0x8	
10 : 5	rtc_rg_xtal_cap_rf_on_delta	rw	0x0	
15 : 11	rtc_rg_xtal_cap_nor_bit	rw	0x8	
21 : 16	rtc_rg_xtal_cap_nor_delta	rw	0x0	
26 : 22	rtc_rg_xtal_cap_step	rw	0x0	
31 : 27	rtc_rg_xtal_ibias_step	rw	0x0	

55.9 pmu_clk_ctrl2				0x70001020
Bits	Field Name	Acc	Default	Description
4 : 0	rtc_rg_xtal_cap_lp_bit	rw	0x8	
10 : 5	rtc_rg_xtal_cap_lp_delta	rw	0x0	
11	rtc_rg_xtal_buf_en_set	rw	0x1	
12	rtc_rg_xtal_comp_en_set	rw	0x1	
13	rtc_rg_xtal_clk_26m_en_set	rw	0x1	
14	rtc_rg_xtal_clk_6p5m_en_set	rw	0x1	
15	rtc_rg_rc_256k_en_set	rw	0x1	
16	rtc_rg_rc_128k_sel_set	rw	0x0	
17	rtc_rg_rc_128k_sel	rw	0x1	
18	rtc_rg_pclk_pmu_rtc1_en	rw	0x1	
19	rtc_rg_pu_xtal_set	rw	0x1	
20	rtc_rg_lpo26m_en_set	rw	0x1	
21	rtc_rg_pu_lpo26m_set	rw	0x1	
22	rtc_rg_pu_lpo256k_set	rw	0x1	
23	rtc_rg_clk_128k_out_en_sw_set	rw	0x0	
24	rtc_rg_clk_1-28k_out_en_sw_mode	rw	0x0	
25	rtc_rg_xtal_clk_52m_en_set	rw	0x1	
26	rtc_rg_xtal_clk_26m_dly_en_set	rw	0x1	
27	rtc_rg_xtal_slp_lp_en_set	rw	0x0	
28	rtc_rg_xtal_comp_clk_en_set	rw	0x1	
29	rtc_rg_pu_xdblr_set	rw	0x1	
30	rtc_rg_xdblr_clk_en_set	rw	0x1	
31	rtc_rg_xdblr_clk_sel	rw	0x0	

55.10 pmu_clk_ctrl3				0x70001024
Bits	Field Name	Acc	Default	Description
4 : 0	rtc_rg_xtal_ibias_rf_on_bit	rw	0x14	
9 : 5	rtc_rg_xtal_ibias_nor_bit	rw	0x14	
13 : 10	rtc_rg_lpo256k_fbit	rw	0x7	
23 : 16	rtc_rg_clk_26m_en_sw_set	rw	0x0	
31 : 24	rtc_rg_clk_26m_en_sw_mode	rw	0xF8	

55.11 pmu_rstn_ctrl				0x70001028
Bits	Field Name	Acc	Default	Description
0	rtc_rg_presetn_en	rw	0x0	
1	rtc_rg_wdg_soft_rst_en	rw	0x0	
5 : 2	rtc_rg_vbit_uvlo	rw	0x3	
6	rtc_rg_vbit_vio18	rw	0x0	
7	rtc_rg_bor_sel_dly	rw	0x0	
9 : 8	rtc_rg_vbit_ms_vio	rw	0x2	
13 : 10	rtc_rg_bor_vbit	rw	0x6	
14	rtc_rg_bor_sel	rw	0x0	
15	rtc_rg_bor_enable	rw	0x0	
16	rtc_rg_bor_soft_rstn_en	rw	0x0	
17	rtc_rg_chopp_bg_test_en	rw	0x0	
20 : 18	rtc_rg_chopp_bg_test_bit	rw	0x0	
22 : 21	rtc_rg_chopp_bg_fbit	rw	0x2	
23	rtc_rg_chopp_bg_osc_en	rw	0x1	
24	rtc_rg_chopp_bg_clk_en	rw	0x0	
31 : 25	rtc_rg_pmu_r-eset_manual_enable	w1c	0x0	

55.12 pmu_dcdc_rf_ctrl0				0x7000102C
Bits	Field Name	Acc	Default	Description
4 : 0	rtc_rg_dcdc_-rf_vbit_vofb_lpvref_th	rw	0x12	
5	rtc_rg_pu_dc-dc_rf_resetn_bypass	rw	0x0	
11 : 6	rtc_rg_dcdc_rf_dvfs_step_vol	rw	0x0	
12	rtc_rg_dcdc_rf_dvfs_step_en	rw	0x0	
14 : 13	rtc_rg_dcdc_rf_dvfs_step_delay	rw	0x0	
23 : 15	rtc_rg_dcdc_rf_soft_cfg	rw	0x0	
24	rtc_rg_dcdc_-rf_dcdc_clk_lpo_sel_sw	rw	0x0	
25	rtc_rg_dcdc_rf_dcdc_clk_lpo_sel	rw	0x0	
28 : 26	rtc_rg_dcdc_rf_bit_vfb_decap	rw	0x0	
29	rtc_rg_dcdc_rf_force_res_on	rw	0x0	

55.13 pmu_dcdc_rf_ctrl1				0x70001030
Bits	Field Name	Acc	Default	Description
5 : 0	rtc_rg_dcdc_rf_vbit_nor_tune	rw	0x19	
11 : 6	rtc_rg_dcdc_rf_vbit_nor_rf	rw	0x19	
17 : 12	rtc_rg_dcdc_rf_vbit_ds_sw	rw	0x19	
23 : 18	rtc_rg_dcdc_-rf_vbit_vout_valley_delta	rw	0xC	
24	rtc_rg_dcdc_-rf_nor_pfm_mode_en	rw	0x0	
26 : 25	rtc_rg_dcdc_rf_pulse_time	rw	0x1	
27	rtc_rg_dcdc_rf_en_chopp	rw	0x0	
28	rtc_rg_dcdc_rf_en_autozero	rw	0x1	
29	rtc_rg_dcdc_rf_dis_nld	rw	0x1	
30	rtc_rg_dcdc_rf_en_ldo_curlim	rw	0x1	
31	rtc_rg_dcdc_rf_en_nsw	rw	0x0	

55.14 pmu_dcdc_rf_ctrl2				0x70001034
Bits	Field Name	Acc	Default	Description
3 : 0	rtc_rg_dcdc_rf_adc_dly_bit	rw	0x1	
6 : 4	rtc_rg_dcdc_rf_adc_cmp_ibit	rw	0x4	

8 : 7	rtc_rg_dcdc_rf_op_ibit	rw	0x1	
10 : 9	rtc_rg_dcdc_rf_pga_gain_bit	rw	0x1	
11	rtc_rg_aon13_sw2v13_sw_en	rw	0x0	
12	rtc_rg_aon13_sw2v13_sw_set	rw	0x0	
14	rtc_rg_dcdc_rf_pu_pga	rw	0x1	
15	rtc_rg_dcdc_rf_pu_dpwm	rw	0x1	
19 : 16	rtc_rg_dcdc_rf_noverlap_bit	rw	0x8	
20	rtc_rg_dcdc_rf_dll_band	rw	0x1	
25 : 21	rtc_rg_dcdc_rf_start_count	rw	0x10	
28 : 26	rtc_rg_dcdc_rf_lpo_freq_bit	rw	0x4	
31 : 29	rtc_rg_dcdc_rf_dly_bit_clk_zcs	rw	0x4	

55.15 pmu_dcdc_rf_ctrl3				0x70001038
Bits	Field Name	Acc	Default	Description
0	rtc_rg_dcdc_rf_ldo_lpm	rw	0x0	
3 : 1	rtc_rg_dcdc_rf_ibit_ldo	rw	0x7	
4	rtc_rg_dcdc_en_fresp_nm18	rw	0x1	
5	rtc_rg_dcdc_en_fresp_vbp	rw	0x1	
6	rtc_rg_dcdc_sw_vnm_tov13	rw	0x0	
7	rtc_rg_dcdc_-rf_noverlap_ana_hold	rw	0x1	
8	rtc_rg_dcdc_-rf_noverlap_ana_pw	rw	0x0	
9	rtc_rg_dcdc_-rf_pu_res_sample_soft_set	rw	0x0	
10	rtc_rg_dcdc_-rf_pu_res_sample_soft_en	rw	0x0	
23 : 21	rtc_rg_dcdc_rf_en_pmos	rw	0x7	
26 : 24	rtc_rg_dcdc_rf_en_nmos	rw	0x7	
30 : 28	rtc_rg_dcdc_fbit_lpo_1p6m	rw	0x4	

55.16 pmu_ldo_vcore08_ctrl				0x7000103C
Bits	Field Name	Acc	Default	Description
4 : 0	rtc_rg_ldo_v-core08_vosel_nor_tune	rw	0x16	
9 : 5	rtc_rg_ldo_vcore08_vosel_nor_rf	rw	0x16	
14 : 10	rtc_rg_ldo_vcore08_vosel_ds_sw	rw	0x16	
19 : 15	rtc_rg_ldo_v-core08_dvfs_step_vol	rw	0x0	
20	rtc_rg_ldo_v-core08_dvfs_step_en	rw	0x0	
22 : 21	rtc_rg_ldo_v-core08_dvfs_step_delay	rw	0x0	
23	rtc_rg_ldo_vcore08_soft_lim	rw	0x1	
24	rtc_rg_ldo_v-core08_slp_lp_en_set	rw	0x0	
28 : 25	rtc_rg_ldo_vcore08_ibit_lim	rw	0xF	
29	rtc_rg_ldo_vcore08_en_lim	rw	0x1	

55.17 pmu_ldo_vrtc08_ctrl				0x70001040
Bits	Field Name	Acc	Default	Description
4 : 0	rtc_rg_ldo_v-rtc08_vosel_nor_tune	rw	0x19	
9 : 5	rtc_rg_ldo_vrtc08_vosel_ds_sw	rw	0x19	
14 : 10	rtc_rg_ldo_v-rtc08_dvfs_step_vol	rw	0x0	
15	rtc_rg_ldo_vrtc08_dvfs_step_en	rw	0x0	

17 : 16	rtc_rg_ldo_v-rtc08_dvfs_step_delay	rw	0x0	
18	rtc_rg_ldo_vrtc08_disable_clk	rw	0x0	

55.18 pmu_other_ldo_ctrl0				0x70001044
Bits	Field Name	Acc	Default	Description
3 : 0	rtc_rg_ldo_pa_vbit_ds_sw	rw	0xD	
7 : 4	rtc_rg_ldo_pa_vbit_nor_tune	rw	0xD	
15 : 11	rtc_rg_vbit_ret	rw	0xC	
19 : 16	rtc_rg_ldo_avdd18_vbit_ds_sw	rw	0x5	
23 : 20	rtc_rg_ldo_a-vdd18_vbit_nor_tune	rw	0x5	
24	rtc_rg_ldo_avdd18_lp_en_set	rw	0x0	
25	rtc_rg_ldo_pa_en_ldo_curlim	rw	0x1	
28 : 26	rtc_rg_ldo_pa_ibit_lim	rw	0x4	
30	rtc_rg_ldo_pa_lp_en_set	rw	0x0	

55.19 pmu_other_ldo_ctrl1				0x70001048
Bits	Field Name	Acc	Default	Description
0	rtc_rg_reg18_ulp_vbit	rw	0x0	
2	rtc_rg_ldo_avdd18_lpmode_set	rw	0x0	
3	rtc_rg_reg18_ulp_enclamp_set	rw	0x0	
4	rtc_rg_ldo18_en_curlim	rw	0x1	
7 : 5	rtc_rg_ldo18_ibit	rw	0x4	
8	rtc_rg_ldo_a-vdd18_ulpmode_set	rw	0x0	
10 : 9	rtc_rg_vrtc0_vbit_ms_avdd33	rw	0x2	
11	rtc_rg_vrtc0_low_detclk	rw	0x0	

55.20 pmu_long_pwr_key_cfg				0x7000104C
Bits	Field Name	Acc	Default	Description
0	rtc_rg_pbint_7s_sw_rst_mode	rw	0x0	
4 : 1	rtc_rg_pbint_7s_rst_threshold	rw	0x8	
5	rtc_rg_pbint_7s_rst_mode	rw	0x0	
6	rtc_rg_pbint_7s_rst_disable	rw	0x1	

55.21 pmu_rf_on_cfg				0x70001050
Bits	Field Name	Acc	Default	Description
0	rtc_rg_rf_tx_on_xtal_mode_en	rw	0x0	
1	rtc_rg_rf_tx-_on_ldo_dcdc_vcore08_dvfs_mode_en	rw	0x0	
2	rtc_rg_rf_tx-_on_dcdc_rf_hys_pfm_mode_en	rw	0x0	
3	rtc_rg_rf_tx-_on_dcdc_core_hys_pfm_mode_en	rw	0x0	
4	rtc_rg_rf_tx-_on_dcdc_rf_dvfs_mode_en	rw	0x0	
5	rtc_rg_rf_rx_on_xtal_mode_en	rw	0x0	
6	rtc_rg_rf_rx-_on_ldo_dcdc_vcore08_dvfs_mode_en	rw	0x0	
7	rtc_rg_rf_rx-_on_dcdc_core_hys_pfm_mode_en	rw	0x0	
8	rtc_rg_rf_rx-_on_dcdc_rf_hys_pfm_mode_en	rw	0x0	
9	rtc_rg_rf_rx-_on_dcdc_rf_dvfs_mode_en	rw	0x0	

10	rtc_rg_pu_md-ll_ldo_dcdc_vcore08_dvfs_mode_en	rw	0x0	
11	rtc_rg_pu_md-ll_dcdc_core_hys_pfm_mode_en	rw	0x0	
12	rtc_rg_pu_md-ll_dcdc_rf_hys_pfm_mode_en	rw	0x0	
13	rtc_rg_pu_md-ll_dcdc_rf_dvfs_mode_en	rw	0x0	
14	rtc_rg_pu_mdll_xtal_mode_en	rw	0x0	
15	rtc_rg_wf_rf_rx_en	rw	0x0	
16	rtc_rg_wf_rf_tx_en	rw	0x0	
17	rtc_rg_bt_rf_rx_en	rw	0x0	
18	rtc_rg_bt_rf_tx_en	rw	0x0	

55.22 pmu_psm_cfg0 0x70001054

Bits	Field Name	Acc	Default	Description
0	rtc_rg_psm_reg_update	rw	0x0	
1	rtc_rg_psm_soft_reset	rw	0x0	
2	rtc_rg_psm_26m_cal_cnt_sw_en	rw	0x0	
3	rtc_rg_psm_clk_32k_gate_en	rw	0x1	
4	rtc_rg_psm_sw_cal_en	rw	0x0	
5	rtc_rg_psm_xtal_lp_cal_en	rw	0x0	
6	rtc_rg_psm_deep_sleep_cal_en	rw	0x0	
7	rtc_rg_psm_auto_cal_en	rw	0x0	
8	rtc_rg_psm_cal_en	rw	0x0	
9	rtc_rg_psm_en	rw	0x0	
31 : 13	rtc_rg_psm_div_demon_factor	rw	0x4C4B4	

55.23 pmu_psm_cfg1 0x70001058

Bits	Field Name	Acc	Default	Description
15 : 0	rtc_rg_psm_xtal_lp_cal_offset	rw	0x0	

55.24 pmu_psm_cfg2 0x7000105C

Bits	Field Name	Acc	Default	Description
9 : 0	rtc_rg_psm_d-eep_sleep_cnt_interval_th	rw	0x0	
17 : 10	rtc_rg_psm_cal_pre_cnt_th	rw	0x2	
21 : 18	rtc_rg_psm_128k_cal_cnt_p	rw	0xA	
25 : 22	rtc_rg_psm_128k_cal_cnt_n	rw	0x3	

55.25 pmu_psm_cfg3 0x70001060

Bits	Field Name	Acc	Default	Description
15 : 0	rtc_rg_psm_26m_cal_cnt_up_th	rw	0x1000	
31 : 16	rtc_rg_psm_26m_cal_cnt_dn_th	rw	0x0	

55.26 pmu_psm_cfg4 0x70001064

Bits	Field Name	Acc	Default	Description
15 : 0	rtc_rg_psm_cnt_interval_phase	rw	0x0	
31 : 16	rtc_rg_psm_cnt_interval_th	rw	0x0	

55.27 pmu_psm_cfg5 0x70001068

Bits	Field Name	Acc	Default	Description
27 : 0	rtc_rg_psm_26m_cal_cnt_sw_set	rw	0x0	

55.28 pmu_psm_cfg6				0x7000106C
Bits	Field Name	Acc	Default	Description
27 : 0	psm_cal_cnt_ro	ro	0x0	
28	psm_reg_update_pulse_vld	ro	0x0	

55.29 pmu_psm_cfg7				0x70001070
Bits	Field Name	Acc	Default	Description
3 : 0	psm_cal_cnt_n_lat_ro	ro	0x0	
31 : 4	psm_cal_cnt_lat_ro	ro	0x0	

55.30 pmu_monitor_cfg				0x70001074
Bits	Field Name	Acc	Default	Description
3 : 0	rtc_rg_dbg_mux	rw	0x0	
7 : 4	rtc_rg_pmu_top_monitor_mux	rw	0x0	

55.31 pmu_status				0x70001078
Bits	Field Name	Acc	Default	Description
0	rtc_rg_por_chip_pd_flag_clr	w1c	0x0	
1	rtc_rg_hard_-long_chip_pd_flag_clr	w1c	0x0	
2	rtc_rg_pbint_7s_flag_clr	w1c	0x0	
3	rtc_rg_pb_int_7s_sw_rst_flag_clr	w1c	0x0	
4	rtc_rg_wdg_soft_rst_flag_clr	w1c	0x0	
5	rtc_rg_soft_rst_flag_clr	w1c	0x0	
8	reg_soft_rst_flag	ro	0x0	
9	pb_int_7s_sw_rst_flag	ro	0x0	
10	wdg_soft_rst_flag	ro	0x0	
11	lp_mode_h_flag	ro	0x0	
15 : 12	rtc_slp_out0_cur_state	ro	0x0	
19 : 16	rtc_slp_out1_cur_state	ro	0x0	
20	rtc_xtal_ibias_stab	ro	0x0	
21	rtc_xtal_cap_stab	ro	0x0	
25 : 22	por_seq_cur_state	ro	0x0	
29 : 26	deep_sleep_awake_status	ro	0x0	

55.32 pmu_int_irq				0x7000107C
Bits	Field Name	Acc	Default	Description
0	rtc_psm_cal_done_raw_status	ro	0x0	
1	rtc_psm_cal_-update_raw_status	ro	0x0	
2	bor_rst_raw_status	ro	0x0	
4	rtc_psm_cal_done_mask_status	ro	0x0	
5	rtc_psm_cal_-update_mask_status	ro	0x0	
6	rtc_bor_rst_mask_status	ro	0x0	
8	rtc_rg_psm_c-al_done_status_mask	rw	0x0	
9	rtc_rg_psm_c-al_update_status_mask	rw	0x0	
10	rtc_rg_bor_rst_status_mask	rw	0x0	
12	rtc_rg_psm_cal_done_status_clr	w1c	0x0	
13	rtc_rg_psm_c-al_update_status_clr	w1c	0x0	
14	rtc_rg_bor_rst_status_clr	w1c	0x0	
16	rtc_rg_pmu_rtc1_int_en	rw	0x0	

55.33 pmu_xtal_clk_detect				0x70001080
Bits	Field Name	Acc	Default	Description
11 : 0	rtc_rg_xtal_-clk_lpo256k_detect_th	rw	0x514	
12	rtc_rg_xtal_detect_clk_soft_en	w1c	0x0	
27 : 16	xtal_clk_lpo2-56k_detect_cnt_latch	ro	0x0	
28	xtal_40m_26m_hw_detect	ro	0x0	
29	xtal_detect_busy	ro	0x0	

55.34 pmu_cm_xtal_cfg1				0x70001084
Bits	Field Name	Acc	Default	Description
0	rtc_rg_cm_xt-al_rf_on_reg_buf_bypass	rw	0x0	
5 : 1	rtc_rg_xtal_ibias_lp_bit	rw	0x5	
8 : 6	rtc_rg_cm_xtal_iref_lp_bit	rw	0x5	
12 : 10	rtc_rg_cm_xtal_iref_bit	rw	0x5	
14 : 13	rtc_rg_cm_xdblr_pulse_bit	rw	0x2	
22	rtc_rg_cm_xtal_reg_buf_bypass	rw	0x0	
26 : 23	rtc_rg_cm_xtal_reg_vbit	rw	0xF	
27	rtc_rg_cm_xtal_reg_bypass	rw	0x0	
28	rtc_rg_cm_xt-al_rf_on_reg_bypass	rw	0x0	
31	rtc_rg_cm_xtal_avdd_sel	rw	0x0	

55.35 pmu_cm_xtal_cfg2				0x70001088
Bits	Field Name	Acc	Default	Description
6 : 4	rtc_rg_cm_xtal_comp_ibit	rw	0x4	
10	rtc_rg_cm_xtal2dig_en_set	rw	0x1	
18 : 11	rtc_rg_pmic_rsvd_bit	rw	0xF0	
21 : 19	rtc_rg_cm_xtal_rf_on_iref_bit	rw	0x5	
25 : 22	rtc_rg_cm_xtal_rf_on_reg_vbit	rw	0xF	
27	rtc_rg_xtal_clk_div4_sel	rw	0x1	
28	rtc_rg_xtal_coreon_set	rw	0x1	

55.36 pmu_clk_div_128k				0x7000108C
Bits	Field Name	Acc	Default	Description
14 : 0	rtc_rg_clk_div_128k_cnt_frc	rw	0x25D4	
22 : 16	rtc_rg_clk_div_128k_cnt_int	rw	0x31	

55.37 pmu_ldo_vflash_ctrl				0x70001090
Bits	Field Name	Acc	Default	Description
3 : 0	rtc_rg_ldo_vflash_vbit_ds_sw	rw	0x9	
7 : 4	rtc_rg_ldo_v-flash_vbit_nor_tune	rw	0x9	
12	rtc_rg_ldo_vflash_ulpmode	rw	0x0	
13	rtc_rg_ldo_vflash_lpmode_set	rw	0x0	
16 : 14	rtc_rg_ldo_vflash_ibit_lim	rw	0x4	
17	rtc_rg_ldo_v-flash_en_ldo_curlim	rw	0x1	

55.38 pmu_dcdc_core_ctrl0				0x70001094
Bits	Field Name	Acc	Default	Description
1 : 0	rtc_rg_dcdc_vbit_vbp	rw	0x2	

3 : 2	rtc_rg_dcdc_vbit_nm18	rw	0x2	
11 : 6	rtc_rg_dcdc_core_dvfs_step_vol	rw	0x0	
12	rtc_rg_dcdc_core_dvfs_step_en	rw	0x0	
14 : 13	rtc_rg_dcdc_-core_dvfs_step_delay	rw	0x0	
23 : 15	rtc_rg_dcdc_core_soft_cfg	rw	0x0	
24	rtc_rg_dcdc_-core_dcdc_clk_lpo_sel_sw	rw	0x0	
25	rtc_rg_dcdc_-core_dcdc_clk_lpo_sel	rw	0x0	
28 : 26	rtc_rg_dcdc_core_bit_vfb_decap	rw	0x0	
29	rtc_rg_dcdc_core_force_res_on	rw	0x0	

55.39 pmu_dcdc_core_ctrl1				0x70001098
Bits	Field Name	Acc	Default	Description
4 : 0	rtc_rg_dcdc_-core_vbit_nor_tune	rw	0x16	
9 : 5	rtc_rg_dcdc_core_vbit_nor_rf	rw	0x16	
14 : 10	rtc_rg_dcdc_core_vbit_ds_sw	rw	0x16	
22 : 18	rtc_rg_dcdc_-core_vbit_vout_valley_delta	rw	0x6	
24	rtc_rg_dcdc_-core_nor_pfm_mode_en	rw	0x0	
26 : 25	rtc_rg_dcdc_core_pulse_time	rw	0x1	
27	rtc_rg_dcdc_core_en_chopp	rw	0x0	
28	rtc_rg_dcdc_core_en_autozero	rw	0x1	
29	rtc_rg_dcdc_core_dis_nld	rw	0x1	
31	rtc_rg_pu_dc-dc_core_resetn_bypass	rw	0x0	

55.40 pmu_dcdc_core_ctrl2				0x7000109C
Bits	Field Name	Acc	Default	Description
3 : 0	rtc_rg_dcdc_core_adc_dly_bit	rw	0x1	
6 : 4	rtc_rg_dcdc_core_adc_cmp_ibit	rw	0x4	
8 : 7	rtc_rg_dcdc_core_op_ibit	rw	0x1	
10 : 9	rtc_rg_dcdc_core_pga_gain_bit	rw	0x1	
14	rtc_rg_dcdc_core_pu_pga	rw	0x1	
15	rtc_rg_dcdc_core_pu_dpwm	rw	0x1	
19 : 16	rtc_rg_dcdc_core_noverlap_bit	rw	0x8	
20	rtc_rg_dcdc_core_dll_band	rw	0x1	
25 : 21	rtc_rg_dcdc_core_start_count	rw	0x10	
28 : 26	rtc_rg_dcdc_core_lpo_freq_bit	rw	0x4	
31 : 29	rtc_rg_dcdc_-core_dly_bit_clk_zcs	rw	0x4	

55.41 pmu_dcdc_core_ctrl3				0x700010A0
Bits	Field Name	Acc	Default	Description
6	rtc_rg_dcdc_-core_pu_res_sample_soft_set	rw	0x0	
7	rtc_rg_dcdc_-core_pu_res_sample_soft_en	rw	0x0	
8	rtc_rg_dcdc_core_en_nsw	rw	0x0	
9	rtc_rg_dcdc_-core_noverlap_ana_pw	rw	0x0	
10	rtc_rg_dcdc_-core_noverlap_ana_hold	rw	0x1	
11	rtc_rg_dcdc_core_sw_2_rf	rw	0x0	

14 : 12	rtc_rg_dcdc_core_time_adder	rw	0x5	
23 : 21	rtc_rg_dcdc_core_en_pmos	rw	0x7	
26 : 24	rtc_rg_dcdc_core_en_nmos	rw	0x7	
27	rtc_rg_dcdc_- vcore_ss_end_mode	rw	0x0	
28	rtc_rg_dcdc_vcore_ss_end_set	rw	0x0	

56 wdg4

56.1 WDG_LOAD_VAL				0x70001400
Bits	Field Name	Acc	Default	Description
31 : 0	wdg_load_val	rw	0x3FFFF	watchdog timer load value. In reset mode, software should load new value before timer decrease to 0. In interrupt mode, this value is counting start number. The default value is about 8 seconds.

56.2 WDG_CNT				0x70001404
Bits	Field Name	Acc	Default	Description
31 : 0	wdg_cnt	rw	0xFFFFFFFF	watchdog counter value

56.3 WDG_CTRL				0x70001408
Bits	Field Name	Acc	Default	Description
0	wdg_irq_en	rw	0x0	Watchdog interrupt enable bit 0: interrupt is disabled 1: interrupt is enabled For reset mode: wdg_rst_en =1, wdg_irq_en=0. For interrupt mode: wdg_rst_en =0, wdg_irq_en=1. For combined mode: wdg_rst_en =1, wdg_irq_en=1.
1	wdg_run	rw	0x0	Watchdog counter open: 0: counter stops. 1: counter runs.

56.4 WDG_INT_CLR				0x7000140C
Bits	Field Name	Acc	Default	Description
0	wdg_int_clr	wo	0x0	Watchdog interrupt clear Write 1 to this bit to clear interrupt Read this bit always get 0.

56.5 WDG_INT_RAW				0x70001410
Bits	Field Name	Acc	Default	Description
0	wdg_int_raw	ro	0x0	Watchdog interrupt raw status. Watch dog reset cannot clear this raw status. Write wdg_int_clr can clear this raw status.
4	wdg_ld_busy	ro	0x0	Watchdog load busy status 0: Watchdog is ready for new loading 1: Last loading is not completed Software must not load new value when this bit is busy, that is, this bit should be checked before any new loading. This bit is set after a new loading, and lasts two or three RTC clock cycles, about 60us - 92us.

56.6 WDG_INT_MASK				0x70001414
Bits	Field Name	Acc	Default	Description
0	wdg_int_mask	ro	0x0	Watchdog interrupt masked status

56.7 WDG_LOCK				0x70002000
Bits	Field Name	Acc	Default	Description
15 : 0	wdg_lock	rw	0x0	Watchdog lock control Write 32'h1ACCE551 to this register to unlock watchdog. Write other value to this register to lock watchdog If reading this register, bit-0 is lock status, and other bits are reserved. If watchdog is locked, all control registers cannot be written by software.

57 dcdc_common

57.1 dcdc_ref_clk_div				0x70002000
Bits	Field Name	Acc	Default	Description
6 : 0	rg_dcdc_ref_clk_div_denom	rw	0x10	
7	rg_dcdc_ref_clk_div_update	rw	0x0	

57.2 dcdc_clk_ctrl0				0x70002004
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_ref_clk_sel	rw	0x1	

57.3 dcdc_clk_ctrl1				0x70002008
Bits	Field Name	Acc	Default	Description
3 : 0	rg_dcdc_rf_clk_offset	rw	0x0	
7 : 4	rg_dcdc_aud_clk_offset	rw	0x8	

57.4 dcdc_clk_ctrl2				0x7000200C
Bits	Field Name	Acc	Default	Description
6 : 0	rg_dcdc_ref_clk_div_denom_tx	rw	0x10	
7	rg_tx_on_ref_clk_enable	rw	0x0	

57.5 dcdc_clk_ctrl3				0x70002010
Bits	Field Name	Acc	Default	Description
6 : 0	rg_dcdc_ref_clk_div_denom_rx	rw	0x10	
7	rg_rx_on_ref_clk_enable	rw	0x0	

58 dcdc_rf_ctrl

58.1 dcdc_clk_ctrl0				0x70002100
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_clk_lpo_inv_en	rw	0x1	
2	rg_dcdc_clk_en	rw	0x1	
3	rg_dcdc_clk_lpo_sel	rw	0x0	
4	rg_dcdc_clk_- out_dly_deepsleep_en	rw	0x1	
5	rg_dcdc_clk_- updn_deepsleep_en	rw	0x1	

58.2 dcdc_clk_ctrl1				0x70002104
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_pfm_denom	rw	0x1	
6	rg_dcdc_pfm_denom_update	rw	0x0	

58.3 dcdc_clk_ctrl2				0x70002108
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dcm_clk_mod0_denom	rw	0x1	
6	rg_dcdc_dcm_-clk_mod0_denom_update	rw	0x0	

58.4 dcdc_clk_ctrl3				0x7000210C
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dcm_clk_mod1_denom	rw	0x4	
6	rg_dcdc_dcm_-clk_mod1_denom_update	rw	0x0	

58.5 dcdc_clk_ctrl4				0x70002110
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dcm_clk_mod2_denom	rw	0x2	
6	rg_dcdc_dcm_-clk_mod2_denom_update	rw	0x0	

58.6 dcdc_clk_ctrl5				0x70002114
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dcm_clk_mod3_denom	rw	0x1	
6	rg_dcdc_dcm_-clk_mod3_denom_update	rw	0x0	

58.7 dcdc_clk_ctrl6				0x70002118
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_smpl_mode	rw	0x0	
2	rg_dcdc_clk_dn_sel	rw	0x0	
6 : 4	rg_dcdc_clk_lpo_denom	rw	0x2	
7	rg_dcdc_clk_-lpo_denom_update	rw	0x0	

58.8 dcdc_clk_ctrl7				0x7000211C
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_clk_dn_phase	rw	0x1	
3 : 2	rg_dcdc_clk_up_phase	rw	0x1	

58.9 dcdc_ctrl_cfg0				0x70002130
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_ss_bypass	rw	0x1	soft start bypss
1	rg_dcdc_clk_auto_enable_mode	rw	0x1	
2	rg_dcdc_ns_auto_track_en	rw	0x1	
4	rg_dcdc_clk_sel	rw	0x0	
7 : 5	rg_dcdc_offset_l	rw	0x0	

58.10 dcdc_ctrl_cfg1				0x70002134
Bits	Field Name	Acc	Default	Description
6 : 0	rg_dcdc_offset_h	rw	0x40	
7	rg_dcdc_offset_update	rw	0x0	

58.11 dcdc_ctrl_cfg2	0x70002138

Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_cnt_mode_th	rw	0x10	

58.12 dcdc_ctrl_cfg3				0x7000213C
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_cnt_mode1_th	rw	0x10	

58.13 dcdc_ctrl_cfg4				0x70002140
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_dcm_clk_int_up_th	rw	0x10	

58.14 dcdc_ctrl_cfg5				0x70002144
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_dcm_clk_int_dn_th	rw	0x10	

58.15 dcdc_ctrl_cfg6				0x70002148
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_flagp_th0	rw	0x5	
6 : 4	rg_dcdc_flagp_th1	rw	0x6	

58.16 dcdc_ctrl_cfg7				0x7000214C
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_flagp_th2	rw	0x7	

58.17 dcdc_ctrl_cfg8				0x70002150
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_flagn_th0	rw	0x2	
6 : 4	rg_dcdc_flagn_th1	rw	0x4	

58.18 dcdc_ctrl_cfg9				0x70002154
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_flagn_th2	rw	0x5	

58.19 dcdc_ctrl_cfg10				0x70002158
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_pfm_clk_div	rw	0xC	

58.20 dcdc_ctrl_cfg11				0x7000215C
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_pfm_low_cnt_vth1	rw	0x4	

58.21 dcdc_ctrl_cfg12				0x70002160
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_pfm_low_cnt_vth2	rw	0x7	

58.22 dcdc_ctrl_cfg13				0x70002164
Bits	Field Name	Acc	Default	Description

7 : 0	rg_dcdc_pfm_low_cnt_vth3	rw	0xD	

58.23 dcdc_ctrl_cfg14				0x70002168
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_pfm_high_cnt_vth	rw	0x19	
6	rg_dcdc_hysco-mp_high_det_bps	rw	0x0	
7	rg_dcdc_pfm_low_det_mode	rw	0x0	

58.24 dcdc_ctrl_cfg15				0x7000216C
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_nlg_scale0	rw	0x0	
3 : 2	rg_dcdc_nlg_scale1	rw	0x0	
5 : 4	rg_dcdc_nlg_scale2	rw	0x1	
7 : 6	rg_dcdc_nlg_scale3	rw	0x2	

58.25 dcdc_ctrl_cfg16				0x70002170
Bits	Field Name	Acc	Default	Description
3 : 0	rg_dcdc_ks	rw	0x2	
6 : 4	rg_dcdc_kp	rw	0x3	

58.26 dcdc_ctrl_cfg17				0x70002174
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_kz	rw	0x2	
7 : 4	rg_dcdc_kw_l	rw	0x8	

58.27 dcdc_ctrl_cfg18				0x70002178
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_kw_h	rw	0xD	
7	rg_dcdc_kw_update	rw	0x0	

58.28 dcdc_ctrl_cfg19				0x7000217C
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_diff_vth_sel	rw	0x2	
6 : 4	rg_dcdc_fp_int	rw	0x5	

58.29 dcdc_ctrl_cfg20				0x70002180
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_fp_gain	rw	0x5	
5 : 4	rg_dcdc_w_step	rw	0x1	

58.30 dcdc_ctrl_cfg21				0x70002184
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_vx_int_vth	rw	0x2	

58.31 dcdc_ctrl_cfg22				0x70002188
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_add2d_init	rw	0x5F	

58.32 dcdc_ctrl_cfg23				0x7000218C
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_add3d_init	rw	0x5F	

58.33 dcdc_ctrl_cfg24				0x70002190
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_hys_pfm_gain3	rw	0x10	

58.34 dcdc_ctrl_cfg25				0x70002194
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dout_pw_lim	rw	0x1E	

58.35 dcdc_ctrl_cfg26				0x70002198
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dout_offset	rw	0x28	

58.36 dcdc_ctrl_cfg27				0x7000219C
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dout1_offset	rw	0x28	

58.37 dcdc_ctrl_cfg28				0x700021A0
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_ss_step0_dout	rw	0x2	
6 : 4	rg_dcdc_ss_step1_dout	rw	0x2	

58.38 dcdc_ctrl_cfg29				0x700021A4
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_ss_step2_dout	rw	0x3	
6 : 4	rg_dcdc_ss_step3_dout	rw	0x4	

58.39 dcdc_ctrl_cfg30				0x700021A8
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_ss_step4_dout	rw	0x4	
6 : 4	rg_dcdc_ss_step5_dout	rw	0x4	

58.40 dcdc_ctrl_cfg31				0x700021AC
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_ss_step6_dout	rw	0x5	
6 : 4	rg_dcdc_ss_step7_dout	rw	0x5	

58.41 dcdc_ctrl_cfg32				0x700021B0
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_ss_step8_dout	rw	0x5	
6 : 4	rg_dcdc_ss_step9_dout	rw	0x5	

58.42 dcdc_ctrl_cfg33				0x700021B4
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_dcm_clk_mode_init	rw	0x1	

58.43 dcdc_ctrl_cfg34				0x700021B8
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_dcm_clk_mode	rw	0x0	
2	rg_dcdc_dcm_clk_mode_force	rw	0x0	
3	rg_dcdc_ns_hys_gain	rw	0x0	
4	rg_dcdc_pu_lpo_sw_mode	rw	0x0	
5	rg_dcdc_pu_lpo_sw	rw	0x0	

58.44 dcdc_ctrl_cfg35				0x700021BC
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_vth_scale0	rw	0x0	
3 : 2	rg_dcdc_vth_scale1	rw	0x2	
5 : 4	rg_dcdc_vth_scale2	rw	0x1	
7 : 6	rg_dcdc_vth_scale3	rw	0x0	

58.45 dcdc_ctrl_cfg36				0x700021C0
Bits	Field Name	Acc	Default	Description
3 : 0	rg_tports_sel	rw	0x0	
5 : 4	rg_dcdc_adc_gain_norm	rw	0x2	

58.46 dcdc_ctrl_cfg37				0x700021C4
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_gain3_limit_vth	rw	0x14	

58.47 dcdc_ctrl_cfg38				0x700021C8
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_deepsleep_sw_mode	rw	0x0	
1	rg_dcdc_deepsleep_sw	rw	0x0	
2	rg_dcdc_hys_-pfm_mode_sw_mode	rw	0x0	
3	rg_dcdc_hys_pfm_mode_sw	rw	0x0	
4	rg_dcdc_force_res_on_sw_mode	rw	0x0	
5	rg_dcdc_force_res_on	rw	0x1	

58.48 dcdc_ctrl_cfg39				0x700021CC
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_en_pmos	rw	0x3	
6 : 4	rg_dcdc_en_nmos	rw	0x3	
7	rg_dcdc_en_n-mos_pmos_sw_mode	rw	0x0	

58.49 dcdc_ctrl_cfg40				0x700021D0
Bits	Field Name	Acc	Default	Description
3 : 0	rg_dcdc_dcm_flag_th	rw	0x5	
4	rg_dcdc_dcm_flag_sel	rw	0x0	
5	rg_dcdc_mode_flag_frc_en	rw	0x0	
6	rg_dcdc_mode_flag_frc_value	rw	0x0	

58.50 dcdc_ctrl_cfg41				0x700021D4
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_tx_on_dcm_enable	rw	0x0	

2 : 1	rg_dcdc_tx_on_dcm_clk_mode	rw	0x1	
4	rg_dcdc_rx_on_dcm_enable	rw	0x0	
6 : 5	rg_dcdc_rx_on_dcm_clk_mode	rw	0x1	

58.51 dcdc_ctrl_cfg42				0x700021D8
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_tx_on_mode_flag_enable	rw	0x0	
1	rg_dcdc_tx_on_mode_flag	rw	0x0	
2	rg_dcdc_rx_on_mode_flag_enable	rw	0x0	
3	rg_dcdc_rx_on_mode_flag	rw	0x0	
5 : 4	rg_dcdc_clk_dly_mode	rw	0x2	

58.52 dcdc_ctrl_cfg43				0x700021DC
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_dpwm_frc_on_deepsleep	rw	0x0	
1	rg_dcdc_dpwm_frc_on_norm	rw	0x1	
2	rg_dcdc_dpwm_frc_on_sw_mode	rw	0x0	

58.53 dcdc_status				0x700021E0
Bits	Field Name	Acc	Default	Description
0	ro_dcdc_mode_flag	ro	0x0	
1	ro_dcdc_pw_lim	ro	0x0	
3 : 2	ro_dcdc_dcm_clk_mode	ro	0x1	
4	ro_dcdc_hys_pfm_mode	ro	0x0	
5	ro_dcdc_ss_win_end	ro	0x0	
6	ro_dcdc_ss_fail_flag	ro	0x0	

59 dcdc_core_ctrl

59.1 dcdc_clk_ctrl0				0x70002200
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_clk_lpo_inv_en	rw	0x1	
2	rg_dcdc_clk_en	rw	0x1	
3	rg_dcdc_clk_lpo_sel	rw	0x0	
4	rg_dcdc_clk_out_dly_deepsleep_en	rw	0x1	
5	rg_dcdc_clk_updn_deepsleep_en	rw	0x1	

59.2 dcdc_clk_ctrl1				0x70002204
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_pfm_denom	rw	0x1	
6	rg_dcdc_pfm_denom_update	rw	0x0	

59.3 dcdc_clk_ctrl2				0x70002208
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dcm_clk_mod0_denom	rw	0x1	
6	rg_dcdc_dcm_clk_mod0_denom_update	rw	0x0	

59.4 dcdc_clk_ctrl3				0x7000220C
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dcm_clk_mod1_denom	rw	0x4	
6	rg_dcdc_dcm_-clk_mod1_denom_update	rw	0x0	

59.5 dcdc_clk_ctrl4				0x70002210
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dcm_clk_mod2_denom	rw	0x2	
6	rg_dcdc_dcm_-clk_mod2_denom_update	rw	0x0	

59.6 dcdc_clk_ctrl5				0x70002214
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dcm_clk_mod3_denom	rw	0x1	
6	rg_dcdc_dcm_-clk_mod3_denom_update	rw	0x0	

59.7 dcdc_clk_ctrl6				0x70002218
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_smpl_mode	rw	0x0	
2	rg_dcdc_clk_dn_sel	rw	0x0	
6 : 4	rg_dcdc_clk_lpo_denom	rw	0x2	
7	rg_dcdc_clk_-lpo_denom_update	rw	0x0	

59.8 dcdc_clk_ctrl7				0x7000221C
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_clk_dn_phase	rw	0x1	
3 : 2	rg_dcdc_clk_up_phase	rw	0x1	

59.9 dcdc_ctrl_cfg0				0x70002230
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_ss_bypass	rw	0x1	soft start bypss
1	rg_dcdc_clk_auto_enable_mode	rw	0x1	
2	rg_dcdc_ns_auto_track_en	rw	0x1	
4	rg_dcdc_clk_sel	rw	0x0	
7 : 5	rg_dcdc_offset_l	rw	0x0	

59.10 dcdc_ctrl_cfg1				0x70002234
Bits	Field Name	Acc	Default	Description
6 : 0	rg_dcdc_offset_h	rw	0x40	
7	rg_dcdc_offset_update	rw	0x0	

59.11 dcdc_ctrl_cfg2				0x70002238
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_cnt_mode_th	rw	0x10	

59.12 dcdc_ctrl_cfg3				0x7000223C
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_cnt_mode1_th	rw	0x10	

59.13 dcdc_ctrl_cfg4				0x70002240
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_dcm_clk_int_up_th	rw	0x10	

59.14 dcdc_ctrl_cfg5				0x70002244
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_dcm_clk_int_dn_th	rw	0x10	

59.15 dcdc_ctrl_cfg6				0x70002248
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_flagp_th0	rw	0x5	
6 : 4	rg_dcdc_flagp_th1	rw	0x6	

59.16 dcdc_ctrl_cfg7				0x7000224C
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_flagp_th2	rw	0x7	

59.17 dcdc_ctrl_cfg8				0x70002250
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_flagn_th0	rw	0x2	
6 : 4	rg_dcdc_flagn_th1	rw	0x4	

59.18 dcdc_ctrl_cfg9				0x70002254
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_flagn_th2	rw	0x5	

59.19 dcdc_ctrl_cfg10				0x70002258
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_pfm_clk_div	rw	0xC	

59.20 dcdc_ctrl_cfg11				0x7000225C
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_pfm_low_cnt_vth1	rw	0x4	

59.21 dcdc_ctrl_cfg12				0x70002260
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_pfm_low_cnt_vth2	rw	0x7	

59.22 dcdc_ctrl_cfg13				0x70002264
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_pfm_low_cnt_vth3	rw	0xD	

59.23 dcdc_ctrl_cfg14				0x70002268
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_pfm_high_cnt_vth	rw	0x19	
6	rg_dcdc_hysco-mp_high_det_bps	rw	0x0	
7	rg_dcdc_pfm_low_det_mode	rw	0x0	

59.24 dcdc_ctrl_cfg15				0x7000226C
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_nlg_scale0	rw	0x0	
3 : 2	rg_dcdc_nlg_scale1	rw	0x0	
5 : 4	rg_dcdc_nlg_scale2	rw	0x1	
7 : 6	rg_dcdc_nlg_scale3	rw	0x2	

59.25 dcdc_ctrl_cfg16				0x70002270
Bits	Field Name	Acc	Default	Description
3 : 0	rg_dcdc_ks	rw	0x2	
6 : 4	rg_dcdc_kp	rw	0x3	

59.26 dcdc_ctrl_cfg17				0x70002274
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_kz	rw	0x2	
7 : 4	rg_dcdc_kw_l	rw	0x8	

59.27 dcdc_ctrl_cfg18				0x70002278
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_kw_h	rw	0xD	
7	rg_dcdc_kw_update	rw	0x0	

59.28 dcdc_ctrl_cfg19				0x7000227C
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_diff_vth_sel	rw	0x2	
6 : 4	rg_dcdc_fp_int	rw	0x5	

59.29 dcdc_ctrl_cfg20				0x70002280
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_fp_gain	rw	0x5	
5 : 4	rg_dcdc_w_step	rw	0x1	

59.30 dcdc_ctrl_cfg21				0x70002284
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_vx_int_vth	rw	0x2	

59.31 dcdc_ctrl_cfg22				0x70002288
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_add2d_init	rw	0x5F	

59.32 dcdc_ctrl_cfg23				0x7000228C
Bits	Field Name	Acc	Default	Description
7 : 0	rg_dcdc_add3d_init	rw	0x5F	

59.33 dcdc_ctrl_cfg24				0x70002290
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_hys_pfm_gain3	rw	0x10	

59.34 dcdc_ctrl_cfg25				0x70002294
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dout_pw_lim	rw	0x1E	

59.35 dcdc_ctrl_cfg26				0x70002298
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dout_offset	rw	0x28	

59.36 dcdc_ctrl_cfg27				0x7000229C
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_dout1_offset	rw	0x28	

59.37 dcdc_ctrl_cfg28				0x700022A0
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_ss_step0_dout	rw	0x2	
6 : 4	rg_dcdc_ss_step1_dout	rw	0x2	

59.38 dcdc_ctrl_cfg29				0x700022A4
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_ss_step2_dout	rw	0x3	
6 : 4	rg_dcdc_ss_step3_dout	rw	0x4	

59.39 dcdc_ctrl_cfg30				0x700022A8
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_ss_step4_dout	rw	0x4	
6 : 4	rg_dcdc_ss_step5_dout	rw	0x4	

59.40 dcdc_ctrl_cfg31				0x700022AC
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_ss_step6_dout	rw	0x5	
6 : 4	rg_dcdc_ss_step7_dout	rw	0x5	

59.41 dcdc_ctrl_cfg32				0x700022B0
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_ss_step8_dout	rw	0x5	
6 : 4	rg_dcdc_ss_step9_dout	rw	0x5	

59.42 dcdc_ctrl_cfg33				0x700022B4
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_dcm_clk_mode_init	rw	0x1	

59.43 dcdc_ctrl_cfg34				0x700022B8
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_dcm_clk_mode	rw	0x0	
2	rg_dcdc_dcm_clk_mode_force	rw	0x0	
3	rg_dcdc_ns_hys_gain	rw	0x0	
4	rg_dcdc_pu_lpo_sw_mode	rw	0x0	
5	rg_dcdc_pu_lpo_sw	rw	0x0	

59.44 dcdc_ctrl_cfg35				0x700022BC
Bits	Field Name	Acc	Default	Description
1 : 0	rg_dcdc_vth_scale0	rw	0x0	
3 : 2	rg_dcdc_vth_scale1	rw	0x2	
5 : 4	rg_dcdc_vth_scale2	rw	0x1	
7 : 6	rg_dcdc_vth_scale3	rw	0x0	

59.45 dcdc_ctrl_cfg36				0x700022C0
Bits	Field Name	Acc	Default	Description
3 : 0	rg_tports_sel	rw	0x0	
5 : 4	rg_dcdc_adc_gain_norm	rw	0x2	

59.46 dcdc_ctrl_cfg37				0x700022C4
Bits	Field Name	Acc	Default	Description
5 : 0	rg_dcdc_gain3_limit_vth	rw	0x14	

59.47 dcdc_ctrl_cfg38				0x700022C8
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_deepsleep_sw_mode	rw	0x0	
1	rg_dcdc_deepsleep_sw	rw	0x0	
2	rg_dcdc_hys_-pfm_mode_sw_mode	rw	0x0	
3	rg_dcdc_hys_pfm_mode_sw	rw	0x0	
4	rg_dcdc_force_res_on_sw_mode	rw	0x0	
5	rg_dcdc_force_res_on	rw	0x1	

59.48 dcdc_ctrl_cfg39				0x700022CC
Bits	Field Name	Acc	Default	Description
2 : 0	rg_dcdc_en_pmos	rw	0x3	
6 : 4	rg_dcdc_en_nmos	rw	0x3	
7	rg_dcdc_en_n-mos_pmos_sw_mode	rw	0x0	

59.49 dcdc_ctrl_cfg40				0x700022D0
Bits	Field Name	Acc	Default	Description
3 : 0	rg_dcdc_dcm_flag_th	rw	0x5	
4	rg_dcdc_dcm_flag_sel	rw	0x0	
5	rg_dcdc_mode_flag_frc_en	rw	0x0	
6	rg_dcdc_mode_flag_frc_value	rw	0x0	

59.50 dcdc_ctrl_cfg41				0x700022D4
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_tx_on_dcm_enable	rw	0x0	
2 : 1	rg_dcdc_tx_on_dcm_clk_mode	rw	0x1	
4	rg_dcdc_rx_on_dcm_enable	rw	0x0	
6 : 5	rg_dcdc_rx_on_dcm_clk_mode	rw	0x1	

59.51 dcdc_ctrl_cfg42				0x700022D8
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_tx_o-n_mode_flag_enable	rw	0x0	

1	rg_dcdc_tx_on_mode_flag	rw	0x0	
2	rg_dcdc_rx_o-n_mode_flag_enable	rw	0x0	
3	rg_dcdc_rx_on_mode_flag	rw	0x0	
5 : 4	rg_dcdc_clk_dly_mode	rw	0x2	

59.52 dcdc_ctrl_cfg43				0x700022DC
Bits	Field Name	Acc	Default	Description
0	rg_dcdc_dpwm_-frc_on_deepsleep	rw	0x0	
1	rg_dcdc_dpwm_frc_on_norm	rw	0x1	
2	rg_dcdc_dpwm_-frc_on_sw_mode	rw	0x0	

59.53 dcdc_status				0x700022E0
Bits	Field Name	Acc	Default	Description
0	ro_dcdc_mode_flag	ro	0x0	
1	ro_dcdc_pw_lim	ro	0x0	
3 : 2	ro_dcdc_dcm_clk_mode	ro	0x1	
4	ro_dcdc_hys_pfm_mode	ro	0x0	
5	ro_dcdc_ss_win_end	ro	0x0	
6	ro_dcdc_ss_fail_flag	ro	0x0	

List of Tables

INT_ROM

1.1 boot rom 1

INT_BTROM

2.1 bt rom 1

INT_SRAM0

3.1 int sram0 1

INT_SRAM1

4.1 int sram1 1

INT_SRAM2

5.1 int sram2 1

INT_SRAM3

6.1 int sram3 1

INT_SRAM4

7.1 int sram4 1

INT_SRAM5

8.1 int sram5 2

INT_SHARED_CACHE_SRAM

9.1 int shared_cache_sram 2

INT_BTRAM

10.1 bt ram 2

FLASH_MEM

11.1 flash_mem 2

FLASH_CACHE_MEM

12.1 flash_cache_mem 2

cache

13.1 BUS_CFG0 2
13.2 BUS_CFG1 3
13.3 BUS_CFG2 3
13.4 BUS_CFG3 3
13.5 BUS_CFG4 3
13.6 BUS_CFG5 3
13.7 BUS_CFG6 3
13.8 BUS_CFG7 4
13.9 BUS_REMAP0 4
13.10 BUS_REMAP1 4
13.11 BUS_REMAP2 4
13.12 BUS_REMAP3 4
13.13 BUS_REMAP4 4
13.14 BUS_REMAP5 4
13.15 BUS_REMAP6 4
13.16 BUS_REMAP7 5
13.17 CACHE_CFG0 5
13.18 BUS_STS0 5
13.19 CACHE_STS0 5
13.20 CMD_CFG0 6
13.21 CMD_CFG1 6
13.22 CMD_CFG2 6
13.23 INT_EN 6
13.24 INT_RAW 6
13.25 INT_MASK 6
13.26 INT_CLR 6
13.27 CACHE_WRITE_HIT_CNT 7
13.28 CACHE_WRITE_MISS_CNT 7

13.29 CACHE_READ_HIT_CNT . . . 7
13.30 CACHE_READ_MISS_CNT . . . 7
13.31 CACHE_HACT_CNT . . . 7
13.32 CACHE_HRDY_CNT . . . 7
dma_cx
14.1 DMA_PAUSE . . . 7
14.2 DMA_FRAG_WAIT . . . 8
14.3 REQ_PEND0_EN . . . 8
14.4 REQ_PEND1_EN . . . 8
14.5 DMA_INT_RAW_STATUS . . . 8
14.6 DMA_INT_MASK_STATUS . . . 8
14.7 DMA_REQ_STATUS . . . 8
14.8 DMA_EN_STATUS . . . 8
14.9 DMA_DEBUG_STATUS . . . 8
14.10 DMA_ARB_SEL_STATUS . . . 9
14.11 CRC_CFG . . . 9
14.12 CRC_GEN . . . 10
14.13 CRC_OUT_XOR . . . 10
14.14 CRC_INIT . . . 10
14.15 I_CRC . . . 10
14.16 AES_KEY_0_ADDR . . . 10
14.17 AES_KEY_1_ADDR . . . 10
14.18 AES_KEY_2_ADDR . . . 10
14.19 AES_KEY_3_ADDR . . . 10
14.20 AES_KEY_4_ADDR . . . 10
14.21 AES_KEY_5_ADDR . . . 11
14.22 AES_KEY_6_ADDR . . . 11
14.23 AES_KEY_7_ADDR . . . 11
14.24 AES_IV_0_ADDR . . . 11
14.25 AES_IV_1_ADDR . . . 11
14.26 AES_IV_2_ADDR . . . 11
14.27 AES_IV_3_ADDR . . . 11
14.28 AES_PLAIN_LEN_H_ADDR . . . 11
14.29 AES_PLAIN_LEN_L_ADDR . . . 11
14.30 AES_A_LEN_H_ADDR . . . 11
14.31 AES_A_LEN_L_ADDR . . . 12
14.32 CE_CTRL_ADDR . . . 12
14.33 PKA_REG0_ADDR . . . 12
14.34 CE_CLOCK_GATE_CTRL . . . 12
14.35 TRANS_CTRL0_ADDR . . . 12
14.36 TRANS_CTRL1_ADDR . . . 12
14.37 TRANS_CLOCK_GATE_CTRL . . . 13
14.38 DMA_MON_SEL . . . 13
14.39 dma_reserved0 . . . 13
14.40 dma_reserved1 . . . 13
14.41 dma_reserved2 . . . 13
14.42 CHKSUM_CTRL_ADDR . . . 13
14.43 CHKSUM_RES_ADDR . . . 13
14.44 HASH_LEN_BIT_ADDR . . . 14
14.45 CE_CTRL_2_ADDR . . . 14
14.46 FULL_DMA_CHS . . . 14
14.46.46 FULL_CHN_PAUSE . . . 14
14.46.46 FULL_CHN_REQ . . . 14
14.46.46 FULL_CHN_CFG . . . 15
14.46.46 FULL_CHN_INT . . . 16
14.46.46 FULL_CHN_SRC_ADDR . . . 17
14.46.46 FULL_CHN_DEST_ADDR . . . 17
14.46.46 FULL_CHN_FRAG_LEN . . . 17
14.46.46 FULL_CHN_BLK_LEN . . . 18

14.46.46 FULL_CHN_TRSC_LEN . . . 18
14.46.46 FULL_CHN_TRSF_STEP . . . 18
14.46.46 FULL_CHN_WRAP_PTR . . . 18
14.46.46 FULL_CHN_WRAP_TO . . . 19
14.46.46 FULL_CHN_LLIST_PTR . . . 19
14.46.46 FULL_CHN_FRAG_STEP . . . 19
14.46.46 FULL_CHN_SRC_BLK_STEP . . . 19
14.46.46 FULL_CHN_DEST_BLK_STEP . . . 19
14.47 REQ_CID_0 . . . 19
14.48 REQ_CID_1 . . . 19
14.49 REQ_CID_2 . . . 19
14.50 REQ_CID_3 . . . 20
14.51 REQ_CID_4 . . . 20
14.52 REQ_CID_5 . . . 20
14.53 REQ_CID_6 . . . 20
14.54 REQ_CID_7 . . . 20
14.55 REQ_CID_8 . . . 20
14.56 REQ_CID_9 . . . 20
14.57 REQ_CID_10 . . . 20
14.58 REQ_CID_11 . . . 20
14.59 REQ_CID_12 . . . 21
14.60 REQ_CID_13 . . . 21
14.61 REQ_CID_14 . . . 21
14.62 REQ_CID_15 . . . 21
14.63 REQ_CID_16 . . . 21
14.64 REQ_CID_17 . . . 21
14.65 REQ_CID_18 . . . 21
14.66 REQ_CID_19 . . . 21
14.67 REQ_CID_20 . . . 21
14.68 REQ_CID_21 . . . 21
14.69 REQ_CID_22 . . . 22
14.70 REQ_CID_23 . . . 22
14.71 CHN_1_DMA_ADDR_RD . . . 22
14.72 CHN_1_DMA_ADDR_WR . . . 22
14.73 CHN_2_DMA_ADDR_RD . . . 22
14.74 CHN_2_DMA_ADDR_WR . . . 22
14.75 CHN_3_DMA_ADDR_RD . . . 22
14.76 CHN_3_DMA_ADDR_WR . . . 22
14.77 CHN_4_DMA_ADDR_RD . . . 22
14.78 CHN_4_DMA_ADDR_WR . . . 23
14.79 CHN_5_DMA_ADDR_RD . . . 23
14.80 CHN_5_DMA_ADDR_WR . . . 23
14.81 CHN_6_DMA_ADDR_RD . . . 23
14.82 CHN_6_DMA_ADDR_WR . . . 23
14.83 CHN_7_DMA_ADDR_RD . . . 23
14.84 CHN_7_DMA_ADDR_WR . . . 23
14.85 CHN_8_DMA_ADDR_RD . . . 24
14.86 CHN_8_DMA_ADDR_WR . . . 24
14.87 CHN_9_DMA_ADDR_RD . . . 24
14.88 CHN_9_DMA_ADDR_WR . . . 24
14.89 CHN_10_DMA_ADDR_RD . . . 24
14.90 CHN_10_DMA_ADDR_WR . . . 24
14.91 CHN_11_DMA_ADDR_RD . . . 24
14.92 CHN_11_DMA_ADDR_WR . . . 24
14.93 CHN_12_DMA_ADDR_RD . . . 25
14.94 CHN_12_DMA_ADDR_WR . . . 25
14.95 CHN_13_DMA_ADDR_RD . . . 25
14.96 CHN_13_DMA_ADDR_WR . . . 25
14.97 CHN_14_DMA_ADDR_RD . . . 25
14.98 CHN_14_DMA_ADDR_WR . . . 25

14.99 CHN_LLI_NODE_COUNTER_0 . . . 25
14.100 CHN_LLI_NODE_COUNTER_1 . . . 25
14.101 CHN_LLI_NODE_COUNTER_2 . . . 25
14.102 CHN_LLI_NODE_COUNTER_3 . . . 26
14.103 CHN_LLI_NODE_COUNTER_4 . . . 26
14.104 CHN_LLI_NODE_COUNTER_5 . . . 26
14.105 CHN_LLI_NODE_COUNTER_6 . . . 26
14.106 CHN_LLI_NODE_COUNTER_7 . . . 26
14.107 CHN_LLI_NODE_COUNTER_8 . . . 26
14.108 CHN_LLI_NODE_COUNTER_9 . . . 26
14.109 CHN_LLI_NODE_COUNTER_10 . . . 26
14.110 CHN_LLI_NODE_COUNTER_11 . . . 26
14.111 CHN_LLI_NODE_COUNTER_12 . . . 26
14.112 CHN_LLI_NODE_COUNTER_13 . . . 27

cpu_p_trap

15.1 addr_in_0 . . . 27
15.2 addr_in_1 . . . 27
15.3 addr_in_2 . . . 27
15.4 addr_in_3 . . . 27
15.5 addr_in_4 . . . 27
15.6 addr_in_5 . . . 27
15.7 addr_in_6 . . . 27
15.8 addr_in_7 . . . 27
15.9 en . . . 28
15.10 trap_out_base . . . 28

cpu_s0_trap

16.1 addr_in_0 . . . 28
16.2 addr_in_1 . . . 28
16.3 addr_in_2 . . . 28
16.4 addr_in_3 . . . 28
16.5 addr_in_4 . . . 28
16.6 addr_in_5 . . . 28
16.7 addr_in_6 . . . 28
16.8 addr_in_7 . . . 29
16.9 en . . . 29
16.10 trap_out_base . . . 29

uart0

17.1 txrx_fifo_divl . . . 29
17.2 int_en_divh . . . 29
17.3 int_id_fifo_ctrl . . . 29
17.4 line_ctrl . . . 29
17.5 modem_ctrl . . . 30
17.6 line_status . . . 30
17.7 modem_status . . . 30
17.8 scratchpad . . . 30
17.9 fifo_status . . . 30
17.10 fifo_trigger . . . 30
17.11 divisor_latch2 . . . 31
17.12 counter_real . . . 31
17.13 div_real_slow . . . 31
17.14 div_real_fast . . . 31
17.15 tports_sel . . . 31

uart1

18.1 txrx_fifo_divl . . . 31
18.2 int_en_divh . . . 31
18.3 int_id_fifo_ctrl . . . 32
18.4 line_ctrl . . . 32
18.5 modem_ctrl . . . 32

18.6 line_status . . . 32
18.7 modem_status . . . 32
18.8 scratchpad . . . 33
18.9 fifo_status . . . 33
18.10 fifo_trigger . . . 33
18.11 divisor_latch2 . . . 33
18.12 counter_real . . . 33
18.13 div_real_slow . . . 33
18.14 div_real_fast . . . 33
18.15 tports_sel . . . 33
uart2
19.1 txrx_fifo_divl . . . 33
19.2 int_en_divh . . . 34
19.3 int_id_fifo_ctrl . . . 34
19.4 line_ctrl . . . 34
19.5 modem_ctrl . . . 34
19.6 line_status . . . 34
19.7 modem_status . . . 35
19.8 scratchpad . . . 35
19.9 fifo_status . . . 35
19.10 fifo_trigger . . . 35
19.11 divisor_latch2 . . . 35
19.12 counter_real . . . 35
19.13 div_real_slow . . . 35
19.14 div_real_fast . . . 35
19.15 tports_sel . . . 36
mailbox
20.1 app2emb_trigger . . . 36
20.2 emb2app_rawstatus . . . 36
20.3 emb2app_ack . . . 36
20.4 emb2app_unmaskset . . . 36
20.5 emb2app_unmaskclear . . . 36
20.6 emb2app_linesel_low . . . 36
20.7 emb2app_linesel_high . . . 36
20.8 emb2app_status . . . 36
20.9 mutex0 . . . 36
20.10 mutex1 . . . 36
20.11 mutex2 . . . 37
20.12 mutex3 . . . 37
20.13 mutex4 . . . 37
20.14 mutex5 . . . 37
20.15 mutex6 . . . 37
20.16 mutex7 . . . 37
20.17 comreg0 . . . 37
20.18 comreg1 . . . 37
20.19 comreg2 . . . 37
20.20 comreg3 . . . 37
20.21 comreg4 . . . 37
20.22 comreg5 . . . 38
20.23 comreg6 . . . 38
20.24 comreg7 . . . 38
20.25 emb2app_trigger . . . 38
20.26 app2emb_rawstatus . . . 38
20.27 app2emb_ack . . . 38
20.28 app2emb_unmaskset . . . 38
20.29 app2emb_unmaskclear . . . 38
20.30 app2emb_linesel_low . . . 38
20.31 app2emb_linesel_high . . . 38
20.32 app2emb_status . . . 38

20.33 g1_app2emb_trigger . . . 38
20.34 g1_emb2app_rawstatus . . . 39
20.35 g1_emb2app_ack . . . 39
20.36 g1_emb2app_unmaskset . . . 39
20.37 g1_emb2app_unmaskclear . . . 39
20.38 g1_emb2app_linesel_low . . . 39
20.39 g1_emb2app_linesel_high . . . 39
20.40 g1_emb2app_status . . . 39
20.41 g1_mutex0 . . . 39
20.42 g1_mutex1 . . . 39
20.43 g1_mutex2 . . . 39
20.44 g1_mutex3 . . . 39
20.45 g1_mutex4 . . . 39
20.46 g1_mutex5 . . . 40
20.47 g1_mutex6 . . . 40
20.48 g1_mutex7 . . . 40
20.49 g1_comreg0 . . . 40
20.50 g1_comreg1 . . . 40
20.51 g1_comreg2 . . . 40
20.52 g1_comreg3 . . . 40
20.53 g1_comreg4 . . . 40
20.54 g1_comreg5 . . . 40
20.55 g1_comreg6 . . . 40
20.56 g1_comreg7 . . . 40
20.57 g1_emb2app_trigger . . . 40
20.58 g1_app2emb_rawstatus . . . 41
20.59 g1_app2emb_ack . . . 41
20.60 g1_app2emb_unmaskset . . . 41
20.61 g1_app2emb_unmaskclear . . . 41
20.62 g1_app2emb_linesel_low . . . 41
20.63 g1_app2emb_linesel_high . . . 41
20.64 g1_app2emb_status . . . 41
sd_host
21.1 ctrl . . . 41
21.2 txfifo_entry . . . 41
21.3 rxfifo_entry . . . 42
21.4 cfg . . . 42
21.5 status . . . 42
21.6 cmd_index . . . 42
21.7 cmd_arg . . . 42
21.8 rsp_index . . . 42
21.9 rsp_arg3 . . . 42
21.10 rsp_arg2 . . . 42
21.11 rsp_arg1 . . . 43
21.12 rsp_arg0 . . . 43
21.13 dline_width . . . 43
21.14 block_size . . . 43
21.15 block_cnt . . . 43
21.16 int_status . . . 43
21.17 int_enable . . . 43
21.18 int_clear . . . 43
21.19 trans_speed . . . 44
21.20 mclk_ctrl . . . 44
21.21 fifo_status . . . 44
aud_proc
22.1 aud_proc_function_id . . . 44
22.2 aud_iis_cfg . . . 44
22.3 aud_iis_tx_cfg_ch01 . . . 44
22.4 aud_iis_tx_cfg_ch23 . . . 45

22.5 aud_iis_rx_cfg_ch01 . . . 45
22.6 aud_iis_rx_cfg_ch23 . . . 45
22.7 aud_intf_i2s_cfg0 . . . 45
22.8 aud_intf_i2s_cfg1 . . . 47
22.9 pcm_cfg_0 . . . 49
22.10 pcm_cfg_1 . . . 49
spiflash
23.1 tx_cmd_addr . . . 49
23.2 tx_block_size . . . 50
23.3 tx_fifo_data . . . 50
23.4 status . . . 50
23.5 rx_fifo_data . . . 50
23.6 flash_config . . . 50
23.7 fifo_ctrl . . . 50
23.8 dual_spi . . . 50
23.9 read_cmd . . . 51
23.10 nand_cfg1 . . . 51
23.11 nand_cfg2 . . . 51
23.12 dummy_cycle_cfg . . . 51
23.13 diff_128m_cmd . . . 51
23.14 aesKey0 . . . 51
23.15 aesKey1 . . . 51
23.16 aesKey2 . . . 51
23.17 aesKey3 . . . 52
23.18 aesKey4 . . . 52
23.19 aesKey5 . . . 52
23.20 aesKey6 . . . 52
23.21 aesKey7 . . . 52
23.22 initCtrNonce0 . . . 52
23.23 initCtrNonce1 . . . 52
23.24 initCtrNonce2 . . . 52
23.25 encStartAddr . . . 52
23.26 encEndAddr . . . 52
23.27 flash_decrypt_ctrl . . . 52
cpu_sysctrl
24.1 hclk_ctrl_mode . . . 53
24.2 hclk1_ctrl_mode . . . 53
24.3 pclk_ctrl_mode . . . 53
24.4 others_clk_ctrl_mode . . . 53
24.5 cfg_mem_rom . . . 53
24.6 cfg_mem_1prf . . . 53
24.7 cfg_mem_2prf . . . 53
24.8 trap_bypass . . . 53
24.9 cache_bypass . . . 53
24.10 pclk_div . . . 53
24.11 codec_mclk_div . . . 53
24.12 bclk_sel . . . 54
24.13 cpu_sys_tports_sel . . . 54
24.14 phy_dump_sel . . . 54
24.15 clk_msadc_div . . . 54
24.16 cfg_cpu_stclk_div . . . 54
24.17 cfg_misc . . . 54
24.18 cfg_cpu_p_rxev . . . 54
24.19 cfg_cpu_s0_rxev . . . 55
24.20 cfg_cpu_s1_rxev . . . 55
24.21 ro_top_tports . . . 55
24.22 cfg_cpu_nmi_en . . . 55
24.23 hclk_manual_enable . . . 55
24.24 hclk_manual_disable . . . 56

24.25 hclk1_manual_enable . . . 57
24.26 hclk1_manual_disable . . . 57
24.27 pclk_manual_enable . . . 57
24.28 pclk_manual_disable . . . 58
24.29 others_manual_enable . . . 58
24.30 others_manual_disable . . . 59
24.31 hclk_soft_resetn_set . . . 59
24.32 hclk_soft_resetn_clr . . . 59
24.33 hclk1_soft_resetn_set . . . 60
24.34 hclk1_soft_resetn_clr . . . 60
24.35 pclk_soft_resetn_set . . . 60
24.36 pclk_soft_resetn_clr . . . 60
24.37 others_soft_resetn_set . . . 61
24.38 others_soft_resetn_clr . . . 61
pwm
25.1 tmr0_ld_value . . . 62
25.2 tmr0_cnt_value . . . 62
25.3 tmr0_cfg . . . 62
25.4 tmr0_int_ctrl . . . 62
25.5 tmr0_cnt_read . . . 62
25.6 tmr1_ld_value . . . 62
25.7 tmr1_cnt_value . . . 62
25.8 tmr1_cfg . . . 62
25.9 tmr1_int_ctrl . . . 62
25.10 tmr1_cnt_read . . . 62
25.11 tmr2_ld_value . . . 63
25.12 tmr2_cnt_value . . . 63
25.13 tmr2_cfg . . . 63
25.14 tmr2_int_ctrl . . . 63
25.15 tmr2_cnt_read . . . 63
25.16 pwm0_sta_val . . . 63
25.17 pwm0_end_val . . . 63
25.18 pwm0_step_cfg0 . . . 63
25.19 pwm0_step_cfg1 . . . 63
25.20 pwm0_cfg . . . 63
25.21 pwm0_int_ctrl . . . 63
25.22 pwm0_end_val_use . . . 64
25.23 pwm0_step_cnt . . . 64
25.24 pwm1_sta_val . . . 64
25.25 pwm1_end_val . . . 64
25.26 pwm1_step_cfg0 . . . 64
25.27 pwm1_step_cfg1 . . . 64
25.28 pwm1_cfg . . . 64
25.29 pwm1_int_ctrl . . . 64
25.30 pwm1_end_val_use . . . 64
25.31 pwm1_step_cnt . . . 65
25.32 pwm2_sta_val . . . 65
25.33 pwm2_end_val . . . 65
25.34 pwm2_step_cfg0 . . . 65
25.35 pwm2_step_cfg1 . . . 65
25.36 pwm2_cfg . . . 65
25.37 pwm2_int_ctrl . . . 65
25.38 pwm2_end_val_use . . . 65
25.39 pwm2_step_cnt . . . 65
i2cm
26.1 IC_CON . . . 66
26.2 IC_TAR . . . 66
26.3 IC_SAR . . . 66
26.4 IC_HS_MADDR . . . 66

26.5 IC_DATA_CMD . . . 66
26.6 IC_SS_SCL_HCNT . . . 66
26.7 IC_SS_SCL_LCNT . . . 66
26.8 IC_FS_SCL_HCNT . . . 66
26.9 IC_FS_SCL_LCNT . . . 66
26.10 IC_HS_SCl_HCNT . . . 66
26.11 IC_HS_SCL_LCNT . . . 67
26.12 IC_INTR_STAT . . . 67
26.13 IC_INTR_MASK . . . 67
26.14 IC_RAW_INTR_STAT . . . 67
26.15 IC_RX_TL . . . 68
26.16 IC_TX_TL . . . 68
26.17 IC_CLR_INTR . . . 68
26.18 IC_CLR_RX_UNDER . . . 68
26.19 IC_CLR_RX_OVER . . . 68
26.20 IC_CLR_TX_OVER . . . 68
26.21 IC_CLR_RD_REQ . . . 68
26.22 IC_CLR_TX_ABRT . . . 68
26.23 IC_CLR_RX_DONE . . . 68
26.24 IC_CLR_ACTIVITY . . . 68
26.25 IC_CLR_STOP_DET . . . 68
26.26 IC_CLR_START_DET . . . 69
26.27 IC_CLR_GEN_CALL . . . 69
26.28 IC_ENABLE . . . 69
26.29 IC_STATUS . . . 69
26.30 IC_TXFLR . . . 69
26.31 IC_RXFLR . . . 69
26.32 IC_SDA_HOLD . . . 69
26.33 IC_TX_ABRT_SOURCE . . . 69
26.34 IC_DMA_CR . . . 70
26.35 IC_DMA_TDLR . . . 70
26.36 IC_DMA_RDLR . . . 70
26.37 IC_SDA_SETUP . . . 70
26.38 IC_ACK_GENERAL_CALL . . . 70
26.39 IC_ENABLE_STATUS . . . 70
26.40 IC_FS_SPKLEN . . . 70
26.41 IC_HS_SPKLEN . . . 70
26.42 IC_CLR_RESTART_DET . . . 70
26.43 IC_COMP_PARAM_1 . . . 70
26.44 IC_COMP_VERSION . . . 71
26.45 IC_COMP_TYPE . . . 71

wdg0

27.1 WDG_LOAD_VAL . . . 71
27.2 WDG_CNT . . . 71
27.3 WDG_CTRL . . . 71
27.4 WDG_INT_CLR . . . 71
27.5 WDG_INT_RAW . . . 71
27.6 WDG_INT_MASK . . . 72
27.7 WDG_LOCK . . . 72

wdg1

28.1 WDG_LOAD_VAL . . . 72
28.2 WDG_CNT . . . 72
28.3 WDG_CTRL . . . 72
28.4 WDG_INT_CLR . . . 72
28.5 WDG_INT_RAW . . . 72
28.6 WDG_INT_MASK . . . 73
28.7 WDG_LOCK . . . 73

spi

29.1 SPI_TXD . . . 73

29.2 SPI_CLKD . . . 73
29.3 SPI_CTL0 . . . 73
29.4 SPI_CTL1 . . . 74
29.5 SPI_CTL2 . . . 74
29.6 SPI_CTL3 . . . 74
29.7 SPI_CTL4 . . . 74
29.8 SPI_CTL5 . . . 75
29.9 SPI_INT_EN . . . 75
29.10 SPI_INT_CLR . . . 75
29.11 SPI_INT_RAW_STS . . . 75
29.12 SPI_INT_MASK_STS . . . 75
29.13 SPI_STS1 . . . 76
29.14 SPI_STS2 . . . 76
29.15 DSP_WAIT . . . 76
29.16 SPI_STS3 . . . 77
29.17 SPI_CTL6 . . . 77
29.18 SPI_STS4 . . . 77
29.19 SPI_FIFO_RST . . . 77
29.20 SPI_CTL7 . . . 77
29.21 SPI_STS5 . . . 78
29.22 SPI_CTL8 . . . 78
29.23 SPI_CTL9 . . . 78
29.24 SPI_CTL10 . . . 78
29.25 SPI_CTL11 . . . 78
29.26 SPI_CTL12 . . . 78
29.27 SPI_STS6 . . . 78
29.28 SPI_STS7 . . . 78
29.29 SPI_STS8 . . . 79
29.30 SPI_STS9 . . . 79
timer0
30.1 tmr_cfg . . . 79
30.2 tmr_pr . . . 79
30.3 tmr_pc . . . 79
30.4 tmr_mr0 . . . 79
30.5 tmr_mr1 . . . 79
30.6 tmr_mr2 . . . 79
30.7 tmr_delta0 . . . 79
30.8 tmr_delta1 . . . 79
30.9 tmr_delta2 . . . 80
30.10 tmr_rtc_clk_div . . . 80
30.11 tmr_int_mask_enable . . . 80
30.12 tmr_int_mask_clear . . . 80
30.13 tmr_int_raw . . . 80
30.14 tmr_int_status . . . 80
timer1
31.1 tmr_cfg . . . 80
31.2 tmr_pr . . . 80
31.3 tmr_pc . . . 81
31.4 tmr_mr0 . . . 81
31.5 tmr_mr1 . . . 81
31.6 tmr_mr2 . . . 81
31.7 tmr_delta0 . . . 81
31.8 tmr_delta1 . . . 81
31.9 tmr_delta2 . . . 81
31.10 tmr_rtc_clk_div . . . 81
31.11 tmr_int_mask_enable . . . 81
31.12 tmr_int_mask_clear . . . 81
31.13 tmr_int_raw . . . 82
31.14 tmr_int_status . . . 82

trng

32.1 trng_en . . . 82
32.2 trng_status . . . 82
32.3 trng_data . . . 82
32.4 trng_div_dly . . . 82
32.5 trng_sel . . . 82

ana_reg0

33.1 flash_pad_pull . . . 83

proc_mon

34.1 auto_mode . . . 83
34.2 cfg_start . . . 83
34.3 cfg_auto_stop . . . 83
34.4 enable_duration . . . 83
34.5 cfg_auto_interval . . . 83
34.6 ro_pvt_cnt_hvt . . . 83

gpioa

35.1 GPIODATA . . . 83
35.2 GPIODMSK . . . 83
35.3 GPIODIR . . . 83
35.4 GPIOIS . . . 84
35.5 GPIOIBE . . . 84
35.6 GPIOIEV . . . 84
35.7 GPIOIE . . . 84
35.8 GPIORIS . . . 84
35.9 GPIOMIS . . . 84
35.10 GPIOIC . . . 84
35.11 GPIOINEN . . . 84
35.12 GPIO_FILTER_NUM . . . 84
35.13 GPIO_FILTER_DIV_L . . . 85
35.14 GPIO_FILTER_DIV_H . . . 85

efuse

36.1 EFUSE_ALL0_INDEX . . . 85
36.2 EFUSE_MODE_CTRL . . . 85
36.3 EFUSE_IP_VER_reg . . . 85
36.4 EFUSE_CFG0 . . . 85
36.5 EFUSE_SEC_EN . . . 85
36.6 EFUSE_SEC_ERR_FLAG . . . 86
36.7 EFUSE_SEC_FLAG_CLR . . . 86
36.8 EFUSE_SEC_MAGIC_NUMBER . . . 87
36.9 EFUSE_FW_CFG . . . 87
36.10 EFUSE_PW_SWT . . . 87
36.11 EFUSE_FUNC_EN_0 . . . 87
36.12 EFUSE_FUNC_EN_1 . . . 87
36.13 EFUSE_FUNC_EN_2 . . . 88
36.14 EFUSE_FUNC_EN_3 . . . 88
36.15 EFUSE_FUNC_EN_4 . . . 88
36.16 EFUSE_FUNC_EN_5 . . . 88
36.17 EFUSE_FUNC_EN_6 . . . 88
36.18 EFUSE_FUNC_EN_7 . . . 88
36.19 EFUSE_FUNC_EN_8 . . . 88
36.20 EFUSE_FUNC_EN_9 . . . 88
36.21 EFUSE_FUNC_EN_10 . . . 89
36.22 EFUSE_FUNC_EN_11 . . . 89
36.23 EFUSE_FUNC_EN_12 . . . 89
36.24 EFUSE_FUNC_EN_13 . . . 89
36.25 EFUSE_FUNC_EN_14 . . . 89
36.26 EFUSE_FUNC_EN_15 . . . 89
36.27 efuse_bist_en_reg . . . 89

36.28 efuse_block0_rw_ctrl_reg . . . 89
36.29 efuse_block1_rw_ctrl_reg . . . 90
36.30 efuse_block2_rw_ctrl_reg . . . 90
36.31 efuse_block3_rw_ctrl_reg . . . 90
36.32 efuse_block4_rw_ctrl_reg . . . 90
36.33 efuse_block5_rw_ctrl_reg . . . 90
36.34 efuse_block6_rw_ctrl_reg . . . 90
36.35 efuse_block7_rw_ctrl_reg . . . 90
36.36 efuse_block8_rw_ctrl_reg . . . 91
36.37 efuse_block9_rw_ctrl_reg . . . 91
36.38 efuse_block10_rw_ctrl_reg . . . 91
36.39 efuse_block11_rw_ctrl_reg . . . 91
36.40 efuse_block12_rw_ctrl_reg . . . 91
36.41 efuse_block13_rw_ctrl_reg . . . 91
36.42 efuse_block14_rw_ctrl_reg . . . 91
36.43 efuse_block15_rw_ctrl_reg . . . 91
36.44 efuse_block16_rw_ctrl_reg . . . 92
36.45 efuse_block17_rw_ctrl_reg . . . 92
36.46 efuse_block18_rw_ctrl_reg . . . 92
36.47 efuse_block19_rw_ctrl_reg . . . 92
36.48 efuse_block20_rw_ctrl_reg . . . 92
36.49 efuse_block21_rw_ctrl_reg . . . 92
36.50 efuse_block22_rw_ctrl_reg . . . 92
36.51 efuse_block23_rw_ctrl_reg . . . 92
36.52 efuse_block24_rw_ctrl_reg . . . 93
36.53 efuse_block25_rw_ctrl_reg . . . 93
36.54 efuse_block26_rw_ctrl_reg . . . 93
36.55 efuse_block27_rw_ctrl_reg . . . 93
36.56 efuse_block28_rw_ctrl_reg . . . 93
36.57 efuse_block29_rw_ctrl_reg . . . 93
36.58 efuse_block30_rw_ctrl_reg . . . 93
36.59 efuse_block31_rw_ctrl_reg . . . 93
36.60 por_read_done_reg . . . 94
36.61 efuse_cfg_reg . . . 94
36.62 efuse_block_en_reg . . . 94
36.63 por_read_data0_reg . . . 94
36.64 por_read_data1_reg . . . 94
36.65 por_read_data2_reg . . . 94
36.66 por_read_data3_reg . . . 94
36.67 EFUSE_MEM . . . 94

msadc

37.1 cfg_msadc_mode . . . 94
37.2 cfg_msadc_sw_ctrl0 . . . 94
37.3 cfg_msadc_sw_ctrl1 . . . 95
37.4 cfg_msadc_ana_ctrl0 . . . 95
37.5 cfg_msadc_ro_acc . . . 95
37.6 cfg_msadc_ro_test_acc_0 . . . 95
37.7 cfg_msadc_ro_test_acc_1 . . . 95
37.8 cfg_msadc_int_raw . . . 95
37.9 cfg_msadc_int_status . . . 95
37.10 cfg_msadc_int_mask . . . 95

usbc

38.1 GOTGCTL . . . 96
38.2 GOTGINT . . . 96
38.3 GAHBCFG . . . 96
38.4 GUSBCFG . . . 97
38.5 GRSTCTL . . . 97
38.6 GINTSTS . . . 97
38.7 GINTMSK . . . 98

38.8 GRXSTSR . . . 99
38.9 GRXSTSP . . . 99
38.10 GRXFSIZ . . . 99
38.11 GNPTXFSIZ . . . 99
38.12 GNPTXSTS . . . 99
38.13 GPVNDCTL . . . 99
38.14 GGPIO . . . 100
38.15 GUID . . . 100
38.16 GSNPSID . . . 100
38.17 GHWCFG1 . . . 100
38.18 GHWCFG2 . . . 100
38.19 GHWCFG3 . . . 101
38.20 GHWCFG4 . . . 101
38.21 GPWRDN . . . 101
38.22 GDFIFOCFG . . . 102
38.23 GADPCTL . . . 102
38.24 STREAMSTSFIFO . . . 102
38.25 STREAMFIRSTPTRFIFO . . . 102
38.26 STREAMLASTPTRFIFO . . . 102
38.27 HPTXFSIZ . . . 102
38.28 DIEPTXF1 . . . 103
38.29 DIEPTXF2 . . . 103
38.30 DIEPTXF3 . . . 103
38.31 DIEPTXF4 . . . 103
38.32 DIEPTXF5 . . . 103
38.33 DIEPTXF6 . . . 103
38.34 DIEPTXF7 . . . 103
38.35 DIEPTXF8 . . . 104
38.36 HCFG . . . 104
38.37 HFIR . . . 104
38.38 HFNUM . . . 104
38.39 HPTXSTS . . . 104
38.40 HAINT . . . 104
38.41 HAINTMSK . . . 104
38.42 HFLBAddr . . . 104
38.43 HPRT . . . 105
38.44 HCCHAR0 . . . 105
38.45 HCSPLT0 . . . 105
38.46 HCINT0 . . . 105
38.47 HCINTMSK0 . . . 106
38.48 HCTSIZ0 . . . 106
38.49 HCDMA0 . . . 106
38.50 HCDMAB0 . . . 106
38.51 HCCHAR1 . . . 106
38.52 HCSPLT1 . . . 106
38.53 HCINT1 . . . 107
38.54 HCINTMSK1 . . . 107
38.55 HCTSIZ1 . . . 107
38.56 HCDMA1 . . . 107
38.57 HCDMAB1 . . . 107
38.58 HCCHAR2 . . . 107
38.59 HCSPLT2 . . . 108
38.60 HCINT2 . . . 108
38.61 HCINTMSK2 . . . 108
38.62 HCTSIZ2 . . . 108
38.63 HCDMA2 . . . 109
38.64 HCDMAB2 . . . 109
38.65 HCCHAR3 . . . 109
38.66 HCSPLT3 . . . 109
38.67 HCINT3 . . . 109

38.68 HCINTMSK3 . . . 109
38.69 HCTSIZ3 . . . 110
38.70 HCDMA3 . . . 110
38.71 HCDMAB3 . . . 110
38.72 HCCHAR4 . . . 110
38.73 HCSPLT4 . . . 110
38.74 HCINT4 . . . 110
38.75 HCINTMSK4 . . . 111
38.76 HCTSIZ4 . . . 111
38.77 HCDMA4 . . . 111
38.78 HCDMAB4 . . . 111
38.79 HCCHAR5 . . . 111
38.80 HCSPLT5 . . . 112
38.81 HCINT5 . . . 112
38.82 HCINTMSK5 . . . 112
38.83 HCTSIZ5 . . . 112
38.84 HCDMA5 . . . 112
38.85 HCDMAB5 . . . 112
38.86 HCCHAR6 . . . 113
38.87 HCSPLT6 . . . 113
38.88 HCINT6 . . . 113
38.89 HCINTMSK6 . . . 113
38.90 HCTSIZ6 . . . 114
38.91 HCDMA6 . . . 114
38.92 HCDMAB6 . . . 114
38.93 HCCHAR7 . . . 114
38.94 HCSPLT7 . . . 114
38.95 HCINT7 . . . 114
38.96 HCINTMSK7 . . . 115
38.97 HCTSIZ7 . . . 115
38.98 HCDMA7 . . . 115
38.99 HCDMAB7 . . . 115
38.100 HCCHAR8 . . . 115
38.101 HCSPLT8 . . . 115
38.102 HCINT8 . . . 115
38.103 HCINTMSK8 . . . 116
38.104 HCTSIZ8 . . . 116
38.105 HCDMA8 . . . 116
38.106 HCDMAB8 . . . 116
38.107 HCCHAR9 . . . 116
38.108 HCSPLT9 . . . 117
38.109 HCINT9 . . . 117
38.110 HCINTMSK9 . . . 117
38.111 HCTSIZ9 . . . 117
38.112 HCDMA9 . . . 117
38.113 HCDMAB9 . . . 118
38.114 HCCHAR10 . . . 118
38.115 HCSPLT10 . . . 118
38.116 HCINT10 . . . 118
38.117 HCINTMSK10 . . . 118
38.118 HCTSIZ10 . . . 119
38.119 HCDMA10 . . . 119
38.120 HCDMAB10 . . . 119
38.121 HCCHAR11 . . . 119
38.122 HCSPLT11 . . . 119
38.123 HCINT11 . . . 119
38.124 HCINTMSK11 . . . 120
38.125 HCTSIZ11 . . . 120
38.126 HCDMA11 . . . 120
38.127 HCDMAB11 . . . 120

38.128 HCCHAR12 . . . 120
38.129 HCSPLT12 . . . 120
38.130 HCINT12 . . . 121
38.131 HCINTMSK12 . . . 121
38.132 HCTSIZ12 . . . 121
38.133 HCDMA12 . . . 121
38.134 HCDMAB12 . . . 121
38.135 HCCHAR13 . . . 121
38.136 HCSPLT13 . . . 122
38.137 HCINT13 . . . 122
38.138 HCINTMSK13 . . . 122
38.139 HCTSIZ13 . . . 122
38.140 HCDMA13 . . . 123
38.141 HCDMAB13 . . . 123
38.142 HCCHAR14 . . . 123
38.143 HCSPLT14 . . . 123
38.144 HCINT14 . . . 123
38.145 HCINTMSK14 . . . 123
38.146 HCTSIZ14 . . . 124
38.147 HCDMA14 . . . 124
38.148 HCDMAB14 . . . 124
38.149 HCCHAR15 . . . 124
38.150 HCSPLT15 . . . 124
38.151 HCINT15 . . . 124
38.152 HCINTMSK15 . . . 125
38.153 HCTSIZ15 . . . 125
38.154 HCDMA15 . . . 125
38.155 HCDMAB15 . . . 125
38.156 DCFG . . . 125
38.157 DCTL . . . 125
38.158 DSTS . . . 126
38.159 DIEPMSK . . . 126
38.160 DOEPMSK . . . 126
38.161 DAINT . . . 127
38.162 DAINTMSK . . . 127
38.163 DVBUSDIS . . . 128
38.164 DVBUSPULSE . . . 128
38.165 DTHRCTL . . . 128
38.166 DIEPEMPMSK . . . 128
38.167 DOEPSTREAMTIMEOUTTH . . . 128
38.168 DOEPSTREAMDBGCTRL . . . 129
38.169 DOEPSTREAMDBGSTATUS1 . . . 129
38.170 DOEPSTREAMDBGSTATUS2 . . . 129
38.171 DOEPSTREAMDBGSTATUS3 . . . 129
38.172 DOEPSTREAMDBGSTATUS4 . . . 129
38.173 DIEPCTL0 . . . 129
38.174 DIEPINT0 . . . 129
38.175 DIEPTSIZ0 . . . 130
38.176 DIEPDMA0 . . . 130
38.177 DTXFSTS0 . . . 130
38.178 DIEPDMAB0 . . . 130
38.179 DIEPCTL1 . . . 130
38.180 DIEPINT1 . . . 130
38.181 DIEPTSIZ1 . . . 131
38.182 DIEPDMA1 . . . 131
38.183 DTXFSTS1 . . . 131
38.184 DIEPDMAB1 . . . 131
38.185 DIEPCTL2 . . . 131
38.186 DIEPINT2 . . . 132
38.187 DIEPTSIZ2 . . . 132

38.188 DIEPDMA2 . . . 132
38.189 DTXFSTS2 . . . 132
38.190 DIEPDMAB2 . . . 132
38.191 DIEPCTL3 . . . 132
38.192 DIEPINT3 . . . 133
38.193 DIEPTSIZ3 . . . 133
38.194 DIEPDMA3 . . . 133
38.195 DTXFSTS3 . . . 133
38.196 DIEPDMAB3 . . . 133
38.197 DIEPCTL4 . . . 133
38.198 DIEPINT4 . . . 134
38.199 DIEPTSIZ4 . . . 134
38.200 DIEPDMA4 . . . 134
38.201 DTXFSTS4 . . . 134
38.202 DIEPDMAB4 . . . 134
38.203 DIEPCTL5 . . . 134
38.204 DIEPINT5 . . . 135
38.205 DIEPTSIZ5 . . . 135
38.206 DIEPDMA5 . . . 135
38.207 DTXFSTS5 . . . 135
38.208 DIEPDMAB5 . . . 135
38.209 DIEPCTL6 . . . 136
38.210 DIEPINT6 . . . 136
38.211 DIEPTSIZ6 . . . 136
38.212 DIEPDMA6 . . . 136
38.213 DTXFSTS6 . . . 136
38.214 DIEPDMAB6 . . . 136
38.215 DIEPCTL7 . . . 137
38.216 DIEPINT7 . . . 137
38.217 DIEPTSIZ7 . . . 137
38.218 DIEPDMA7 . . . 137
38.219 DTXFSTS7 . . . 137
38.220 DIEPDMAB7 . . . 138
38.221 DIEPCTL8 . . . 138
38.222 DIEPINT8 . . . 138
38.223 DIEPTSIZ8 . . . 138
38.224 DIEPDMA8 . . . 138
38.225 DTXFSTS8 . . . 139
38.226 DIEPDMAB8 . . . 139
38.227 DIEPCTL9 . . . 139
38.228 DIEPINT9 . . . 139
38.229 DIEPTSIZ9 . . . 139
38.230 DIEPDMA9 . . . 140
38.231 DTXFSTS9 . . . 140
38.232 DIEPDMAB9 . . . 140
38.233 DIEPCTL10 . . . 140
38.234 DIEPINT10 . . . 140
38.235 DIEPTSIZ10 . . . 141
38.236 DIEPDMA10 . . . 141
38.237 DTXFSTS10 . . . 141
38.238 DIEPDMAB10 . . . 141
38.239 DIEPCTL11 . . . 141
38.240 DIEPINT11 . . . 141
38.241 DIEPTSIZ11 . . . 142
38.242 DIEPDMA11 . . . 142
38.243 DTXFSTS11 . . . 142
38.244 DIEPDMAB11 . . . 142
38.245 DIEPCTL12 . . . 142
38.246 DIEPINT12 . . . 142
38.247 DIEPTSIZ12 . . . 143

38.248 DIEPDMA12 . . . 143
38.249 DTXFSTS12 . . . 143
38.250 DIEPDMAB12 . . . 143
38.251 DOEPCTL0 . . . 143
38.252 DOEPINT0 . . . 143
38.253 DOEPTSIZ0 . . . 144
38.254 DOEPDMA0 . . . 144
38.255 DOEPDMAB0 . . . 144
38.256 DOEPCTL1 . . . 144
38.257 DOEPCTL1_1 . . . 145
38.258 DOEPINT1 . . . 145
38.259 DOEPTSIZ1 . . . 145
38.260 DOEPDMA1 . . . 145
38.261 DOEPDMAB1 . . . 145
38.262 DOEPCTL2 . . . 145
38.263 DOEPCTL2_1 . . . 146
38.264 DOEPINT2 . . . 146
38.265 DOEPTSIZ2 . . . 146
38.266 DOEPDMA2 . . . 147
38.267 DOEPDMAB2 . . . 147
38.268 DOEPCTL3 . . . 147
38.269 DOEPCTL3_1 . . . 147
38.270 DOEPINT3 . . . 147
38.271 DOEPTSIZ3 . . . 148
38.272 DOEPDMA3 . . . 148
38.273 DOEPDMAB3 . . . 148
38.274 DOEPCTL4 . . . 148
38.275 DOEPCTL4_1 . . . 148
38.276 DOEPINT4 . . . 149
38.277 DOEPTSIZ4 . . . 149
38.278 DOEPDMA4 . . . 149
38.279 DOEPDMAB4 . . . 149
38.280 DOEPCTL5 . . . 149
38.281 DOEPCTL5_1 . . . 150
38.282 DOEPINT5 . . . 150
38.283 DOEPTSIZ5 . . . 150
38.284 DOEPDMA5 . . . 150
38.285 DOEPDMAB5 . . . 151
38.286 DOEPCTL6 . . . 151
38.287 DOEPCTL6_1 . . . 151
38.288 DOEPINT6 . . . 151
38.289 DOEPTSIZ6 . . . 152
38.290 DOEPDMA6 . . . 152
38.291 DOEPDMAB6 . . . 152
38.292 DOEPCTL7 . . . 152
38.293 DOEPCTL7_1 . . . 152
38.294 DOEPINT7 . . . 152
38.295 DOEPTSIZ7 . . . 153
38.296 DOEPDMA7 . . . 153
38.297 DOEPDMAB7 . . . 153
38.298 DOEPCTL8 . . . 153
38.299 DOEPCTL8_1 . . . 154
38.300 DOEPINT8 . . . 154
38.301 DOEPTSIZ8 . . . 154
38.302 DOEPDMA8 . . . 154
38.303 DOEPDMAB8 . . . 154
38.304 DOEPCTL9 . . . 155
38.305 DOEPCTL9_1 . . . 155
38.306 DOEPINT9 . . . 155
38.307 DOEPTSIZ9 . . . 155

38.308 DOEPDMA9 . . . 156
38.309 DOEPDMAB9 . . . 156
38.310 DOEPCTL10 . . . 156
38.311 DOEPCTL10_1 . . . 156
38.312 DOEPINT10 . . . 156
38.313 DOEPTSIZ10 . . . 157
38.314 DOEPDMA10 . . . 157
38.315 DOEPDMAB10 . . . 157
38.316 DOEPCTL11 . . . 157
38.317 DOEPCTL11_1 . . . 158
38.318 DOEPINT11 . . . 158
38.319 DOEPTSIZ11 . . . 158
38.320 DOEPDMA11 . . . 158
38.321 DOEPDMAB11 . . . 158
38.322 DOEPCTL12 . . . 158
38.323 DOEPCTL12_1 . . . 159
38.324 DOEPINT12 . . . 159
38.325 DOEPTSIZ12 . . . 159
38.326 DOEPDMA12 . . . 159
38.327 DOEPDMAB12 . . . 160
38.328 PCGCCTL . . . 160
mm_sys_ctrl
39.1 mem_cfg . . . 160
39.2 usb_cfg0 . . . 160
39.3 usb_cfg1 . . . 160
39.4 usb_cfg2 . . . 160
39.5 usb_tport_sel . . . 160
39.6 usb_status . . . 160
39.7 usb_digphy_int_enable . . . 161
39.8 usb_digphy_int_clr . . . 161
39.9 cfg_mm_sys_tports_sel . . . 161
39.10 mem_cfg1 . . . 161
39.11 usb_prbs_cfg . . . 161
39.12 usb_prbs_status . . . 161
39.13 cfg_pu_usb . . . 161
39.14 usb_ana_cfg0 . . . 162
39.15 usb_ana_cfg1 . . . 162
dfe_reg_bank
40.1 a0x000 . . . 162
40.2 a0x004 . . . 163
40.3 a0x008 . . . 163
40.4 a0x00c . . . 163
40.5 a0x010 . . . 163
40.6 a0x014 . . . 163
40.7 a0x018 . . . 164
40.8 a0x01c . . . 164
40.9 a0x020 . . . 164
40.10 a0x024 . . . 164
40.11 a0x028 . . . 165
40.12 a0x02c . . . 165
40.13 a0x030 . . . 165
40.14 a0x04c . . . 165
40.15 a0x050 . . . 165
40.16 a0x054 . . . 166
40.17 a0x058 . . . 166
40.18 a0x05c . . . 166
40.19 a0x060 . . . 166
40.20 a0x064 . . . 166
40.21 a0x068 . . . 166

40.22 a0x06c . . . 167
40.23 a0x070 . . . 167
40.24 a0x074 . . . 167
40.25 a0x078 . . . 167
40.26 a0x07c . . . 167
40.27 a0x080 . . . 167
40.28 a0x084 . . . 167
40.29 a0x088 . . . 168
40.30 a0x08c . . . 168
40.31 a0x090 . . . 168
40.32 a0x094 . . . 168
40.33 a0x098 . . . 168
40.34 a0x09c . . . 168
40.35 a0x0a0 . . . 168
40.36 a0x0a4 . . . 168
40.37 a0x0a8 . . . 168
40.38 a0x0ac . . . 169
40.39 a0x0b0 . . . 169
40.40 a0x0b4 . . . 169
40.41 a0x0b8 . . . 169
40.42 a0x0bc . . . 169
40.43 a0x0c0 . . . 169
40.44 a0x0c4 . . . 169
40.45 a0x0c8 . . . 169
40.46 a0x0cc . . . 169
40.47 a0x0d0 . . . 170
40.48 a0x0d4 . . . 170
40.49 a0x0d8 . . . 170
40.50 a0x0dc . . . 170
40.51 a0x0e0 . . . 170
40.52 a0x0e4 . . . 170
40.53 a0x0e8 . . . 171
40.54 a0x0ec . . . 171
40.55 a0x0f0 . . . 171
40.56 a0x0f4 . . . 171
40.57 a0x104 . . . 171
40.58 a0x108 . . . 171
40.59 a0x10c . . . 171
40.60 a0x110 . . . 171
40.61 a0x114 . . . 172
40.62 a0x118 . . . 172
40.63 a0x11c . . . 172
40.64 a0x120 . . . 172
40.65 a0x124 . . . 172
40.66 a0x128 . . . 172
40.67 a0x12c . . . 173
40.68 a0x130 . . . 173
40.69 a0x134 . . . 173
40.70 a0x138 . . . 173
40.71 a0x13c . . . 173
40.72 a0x140 . . . 173
40.73 a0x144 . . . 173
40.74 a0x148 . . . 174
40.75 a0x14c . . . 174
40.76 a0x150 . . . 174
40.77 a0x15c . . . 174
40.78 a0x160 . . . 174
40.79 a0x164 . . . 174
40.80 a0x168 . . . 174
40.81 a0x16c . . . 175

40.82 a0x170 . . . 175
40.83 a0x174 . . . 175
40.84 a0x178 . . . 175
40.85 a0x17c . . . 175
40.86 a0x180 . . . 175
40.87 a0x184 . . . 176
40.88 a0x188 . . . 176
40.89 a0x200 . . . 176
40.90 a0x204 . . . 176
40.91 a0x208 . . . 176
40.92 a0x20c . . . 176
40.93 a0x210 . . . 176
40.94 a0x214 . . . 176
40.95 a0x218 . . . 176
40.96 a0x21c . . . 176
40.97 a0x220 . . . 176
40.98 a0x224 . . . 177
40.99 a0x228 . . . 177
40.100 a0x22c . . . 177
wf_rf_interface
41.1 reg_00 . . . 177
41.2 reg_01 . . . 177
41.3 reg_02 . . . 178
41.4 reg_03 . . . 178
41.5 reg_04 . . . 179
41.6 reg_05 . . . 179
41.7 reg_06 . . . 179
41.8 reg_07 . . . 179
41.9 reg_08 . . . 180
41.10 reg_09 . . . 180
41.11 reg_0A . . . 180
41.12 reg_0B . . . 181
41.13 reg_0C . . . 181
41.14 reg_0D . . . 181
41.15 reg_0E . . . 181
41.16 reg_0F . . . 182
41.17 reg_10 . . . 182
41.18 reg_11 . . . 182
41.19 reg_12 . . . 182
41.20 reg_13 . . . 183
41.21 wf_soft_reset_reg . . . 183
41.22 wf_man_ctrl_reg . . . 183
41.23 wf_calclk_reg . . . 183
41.24 wf_ext_trxon_delay_reg . . . 183
41.25 gain_mem_ctrl_reg . . . 183
41.26 gain_mem_fetch_reg . . . 184
41.27 wf_dpd_txcal_ctrl_reg . . . 184
41.28 pu_done_reg . . . 184
41.29 dig_reserved_reg . . . 184
41.30 agc_table_out_reg0 . . . 184
41.31 agc_table_out_reg1 . . . 184
41.32 agc_table_out_reg2 . . . 184
41.33 agc_table_out_reg3 . . . 184
41.34 apc_table_out_reg0 . . . 184
41.35 apc_table_out_reg1 . . . 185
sys_ctrl
42.1 chip_id . . . 185
42.2 aon_clk_sel . . . 185
42.3 aon_clk_mode . . . 185

42.4 aon_clk_div . . . 185
42.5 top_clk_sel . . . 185
42.6 top_hclk_mode . . . 185
42.7 top_fclk_mode . . . 185
42.8 top_others_clk_mode . . . 185
42.9 hclk_div . . . 186
42.10 fclk_div . . . 186
42.11 psram_clk_div . . . 186
42.12 cfg_480m_clk_div . . . 186
42.13 real_320m_clk_div . . . 186
42.14 real_480m_clk_div . . . 186
42.15 cfg_osc_enable . . . 186
42.16 reset_cause . . . 186
42.17 tports_sel . . . 187
42.18 cpu_p_reset_addr . . . 187
42.19 cpu_s0_reset_addr . . . 187
42.20 cfg_cpu_sys_ctrl . . . 187
42.21 cfg_rtc1_pu_dcdc_resetn_bypass . . . 187
42.22 cfg_sdio_iomux_sel . . . 187
42.23 cfg_mem_cpu_sys_1pram . . . 187
42.24 bt_hclk_div . . . 187
42.25 top_tports_bits_sel0 . . . 187
42.26 top_tports_bits_sel1 . . . 187
42.27 top_tports_bits_sel2 . . . 188
42.28 top_tports_bits_sel3 . . . 188
42.29 cpu_s1_reset_addr . . . 188
42.30 hclk_manual_enable . . . 188
42.31 hclk_manual_disable . . . 188
42.32 fclk_manual_enable . . . 188
42.33 fclk_manual_disable . . . 188
42.34 others_manual_enable . . . 188
42.35 others_manual_disable . . . 189
42.36 aon_clk_manual_enable . . . 189
42.37 aon_clk_manual_disable . . . 189
42.38 global_soft_resetn_set . . . 190
42.39 global_soft_resetn_clr . . . 190
42.40 hclk_soft_resetn_set . . . 190
42.41 hclk_soft_resetn_clr . . . 190
42.42 fclk_soft_resetn_set . . . 191
42.43 fclk_soft_resetn_clr . . . 191
42.44 others_soft_resetn_set . . . 191
42.45 others_soft_resetn_clr . . . 191
42.46 aon_soft_resetn_set . . . 191
42.47 aon_soft_resetn_clr . . . 192
42.48 boot_mode . . . 192
42.49 wdg_reset_en . . . 192
42.50 reserved_reg0 . . . 192
42.51 reserved_reg1 . . . 192
42.52 reserved_reg2 . . . 193
42.53 reserved_reg3 . . . 193
42.54 reserved_reg4 . . . 193
42.55 reserved_reg5 . . . 193
42.56 reserved_reg6 . . . 193
42.57 reserved_reg7 . . . 193
42.58 reserved_reg8 . . . 193
42.59 reserved_reg9 . . . 193
42.60 reserved_reg10 . . . 193
42.61 reserved_reg11 . . . 193
42.62 reserved_reg12 . . . 193
42.63 reserved_reg13 . . . 193

42.64 reserved_reg14 . . . 194
42.65 reserved_reg15 . . . 194
timer2
43.1 TIMER0_CTL . . . 194
43.2 TIMER0_TICK_DIV . . . 194
43.3 TIMER0_INT_CTRL . . . 194
43.4 TIMER0_INT_STATUS . . . 196
43.5 TIMER0_TC_LO . . . 196
43.6 TIMER0_TC_HI . . . 197
43.7 TIMER0_MR0_LO . . . 197
43.8 TIMER0_MR0_HI . . . 197
43.9 TIMER0_MR1_LO . . . 197
43.10 TIMER0_MR1_HI . . . 197
43.11 TIMER0_MR2_LO . . . 197
43.12 TIMER0_MR2_HI . . . 197
43.13 TIMER0_MR3_LO . . . 197
43.14 TIMER0_MR3_HI . . . 197
ana_reg1
44.1 gpioa_ibit . . . 198
44.2 gpioa_slew_rate . . . 198
44.3 gpioa_ie . . . 198
44.4 gpiob_ibit . . . 198
44.5 gpiob_slew_rata . . . 198
44.6 gpiob_ie . . . 198
44.7 ana_port_ctrl . . . 198
44.8 misc_reg . . . 199
44.9 flash_ctrl . . . 199
psi_mst
45.1 ip_revision . . . 199
45.2 psi_mst_ctrl . . . 199
45.3 psi_mst_pri00 . . . 199
45.4 psi_mst_pri10 . . . 199
45.5 psi_mst_pri20 . . . 199
45.6 psi_mst_pri30 . . . 200
45.7 psi_mst_int_en . . . 200
45.8 psi_mst_raw_status . . . 200
45.9 psi_mst_mask_status . . . 200
45.10 psi_mst_int_clr . . . 200
45.11 psi_gssi_cfg0 . . . 200
45.12 psi_gssi_cfg1 . . . 201
45.13 psi_arm_rd_cmd_addr . . . 201
45.14 psi_arm_rd_cmd_data . . . 201
45.15 psi_arm_debug0 . . . 201
45.16 psi_arm_debug1 . . . 201
45.17 psi_arm_debug2 . . . 201
45.18 psi_cmd_status . . . 202
45.19 psi_chnl_en . . . 202
45.20 chnl2_wr_addr . . . 202
45.21 chnl3_wr_addr . . . 203
45.22 chnl4_wr_addr . . . 203
45.23 chnl5_wr_addr . . . 203
45.24 chnl10_wr_addr . . . 203
45.25 chnl11_wr_addr . . . 203
45.26 chnl12_wr_addr . . . 203
45.27 chnl13_wr_addr . . . 203
45.28 chnl20_wr_addr . . . 203
45.29 chnl21_wr_addr . . . 203
45.30 chnl22_wr_addr . . . 203
45.31 chnl23_wr_addr . . . 203

45.32 chnl24_wr_addr . . . 203
45.33 chnl25_wr_addr . . . 204
45.34 chnl26_wr_addr . . . 204
45.35 chnl27_wr_addr . . . 204
45.36 chnl2_wr_low_data . . . 204
45.37 chnl2_wr_high_data . . . 204
45.38 chnl3_wr_low_data . . . 204
45.39 chnl3_wr_high_data . . . 204
45.40 chnl4_wr_low_data . . . 204
45.41 chnl4_wr_high_data . . . 204
45.42 chnl5_wr_low_data . . . 204
45.43 chnl5_wr_high_data . . . 204
45.44 chnl10_wr_low_data . . . 204
45.45 chnl10_wr_high_data . . . 205
45.46 chnl11_wr_low_data . . . 205
45.47 chnl11_wr_high_data . . . 205
45.48 chnl12_wr_low_data . . . 205
45.49 chnl12_wr_high_data . . . 205
45.50 chnl13_wr_low_data . . . 205
45.51 chnl13_wr_high_data . . . 205
45.52 evt_trg_cfg00 . . . 205
45.53 evt_trg_cfg10 . . . 205
45.54 psi_rd_cmd_addr . . . 205
45.55 psi_wr_cmd_addr . . . 205
45.56 psi_wr_cmd_data . . . 206
45.57 psi_timeout_cfg . . . 206
45.58 pmu_psi_slv_cfg0 . . . 206
45.59 pmu_psi_slv_cfg1 . . . 206
iomux
46.1 pad_gpioa_0_cfg_reg . . . 206
46.2 pad_gpioa_1_cfg_reg . . . 206
46.3 pad_gpioa_2_cfg_reg . . . 207
46.4 pad_gpioa_3_cfg_reg . . . 207
46.5 pad_gpioa_4_cfg_reg . . . 208
46.6 pad_gpioa_5_cfg_reg . . . 208
46.7 pad_gpioa_6_cfg_reg . . . 208
46.8 pad_gpioa_7_cfg_reg . . . 209
46.9 pad_gpioa_8_cfg_reg . . . 209
46.10 pad_gpioa_9_cfg_reg . . . 209
46.11 pad_gpioa_10_cfg_reg . . . 210
46.12 pad_gpioa_11_cfg_reg . . . 210
46.13 pad_gpioa_12_cfg_reg . . . 210
46.14 pad_gpioa_13_cfg_reg . . . 211
46.15 pad_gpioa_14_cfg_reg . . . 211
46.16 pad_gpioa_15_cfg_reg . . . 211
46.17 pad_gpiob_0_cfg_reg . . . 212
46.18 pad_gpiob_1_cfg_reg . . . 212
46.19 pad_gpiob_2_cfg_reg . . . 212
46.20 pad_gpiob_3_cfg_reg . . . 213
cm_rf_interface
47.1 reg_00 . . . 213
47.2 reg_01 . . . 214
47.3 reg_02 . . . 214
47.4 reg_03 . . . 214
47.5 reg_04 . . . 214
47.6 reg_05 . . . 215
47.7 cm_1m_reg . . . 215
47.8 bbpll_sdm_reg1 . . . 215
47.9 bbpll_sdm_reg2 . . . 215

47.10 wf_wr_only_reg . . . 215
47.11 bt_wr_only_reg . . . 215
47.12 mdll_fref_reg . . . 215
47.13 dig_reserved_reg . . . 215
pwr_ctrl
48.1 cpu_sys_pwr_ctrl . . . 216
48.2 bt_core_pwr_ctrl . . . 216
48.3 wifi_core_pwr_ctrl . . . 216
48.4 pwr_sys_ctrl . . . 217
48.5 pwr_off_timmer_th1 . . . 217
48.6 pwr_off_timmer_th2 . . . 217
48.7 pwr_ctrl_delay1 . . . 217
48.8 pwr_ctrl_delay2 . . . 217
48.9 pwr_sys_delay1 . . . 218
48.10 pwr_sys_delay2 . . . 218
48.11 pwr_ctrl_state1 . . . 218
48.12 pwr_ctrl_state2 . . . 218
48.13 pwr_ctrl_soft_mode1 . . . 218
48.14 pwr_ctrl_irq_ctrl . . . 219
48.15 pwr_ctrl_irq_status . . . 219
48.16 mm_sys_pwr_ctrl . . . 219
48.17 pwr_ctrl_soft_mode2 . . . 219
48.18 vcore_sys_pwr_ctrl . . . 219
48.19 pwr_off_timmer_th3 . . . 220
48.20 pwr_ctrl_mode . . . 220
48.21 ret_ram_ctrl . . . 220
48.22 pwr_ctrl_monitor . . . 220
48.23 pwr_ctrl_soft_mode3 . . . 220
aon_pwm
49.1 tmr0_ld_value . . . 221
49.2 tmr0_cnt_value . . . 221
49.3 tmr0_cfg . . . 221
49.4 tmr0_int_ctrl . . . 221
49.5 tmr0_cnt_read . . . 221
49.6 tmr1_ld_value . . . 221
49.7 tmr1_cnt_value . . . 221
49.8 tmr1_cfg . . . 221
49.9 tmr1_int_ctrl . . . 221
49.10 tmr1_cnt_read . . . 221
49.11 tmr2_ld_value . . . 222
49.12 tmr2_cnt_value . . . 222
49.13 tmr2_cfg . . . 222
49.14 tmr2_int_ctrl . . . 222
49.15 tmr2_cnt_read . . . 222
49.16 pwm0_sta_val . . . 222
49.17 pwm0_end_val . . . 222
49.18 pwm0_step_cfg0 . . . 222
49.19 pwm0_step_cfg1 . . . 222
49.20 pwm0_cfg . . . 222
49.21 pwm0_int_ctrl . . . 222
49.22 pwm0_end_val_use . . . 223
49.23 pwm0_step_cnt . . . 223
49.24 pwm1_sta_val . . . 223
49.25 pwm1_end_val . . . 223
49.26 pwm1_step_cfg0 . . . 223
49.27 pwm1_step_cfg1 . . . 223
49.28 pwm1_cfg . . . 223
49.29 pwm1_int_ctrl . . . 223
49.30 pwm1_end_val_use . . . 223

49.31 pwm1_step_cnt . . . 224
49.32 pwm2_sta_val . . . 224
49.33 pwm2_end_val . . . 224
49.34 pwm2_step_cfg0 . . . 224
49.35 pwm2_step_cfg1 . . . 224
49.36 pwm2_cfg . . . 224
49.37 pwm2_int_ctrl . . . 224
49.38 pwm2_end_val_use . . . 224
49.39 pwm2_step_cnt . . . 224
wdg2
50.1 WDG_LOAD_VAL . . . 225
50.2 WDG_CNT . . . 225
50.3 WDG_CTRL . . . 225
50.4 WDG_INT_CLR . . . 225
50.5 WDG_INT_RAW . . . 225
50.6 WDG_INT_MASK . . . 225
50.7 WDG_LOCK . . . 225
bt_dfe_cfg
51.1 a0x000 . . . 226
51.2 a0x004 . . . 226
51.3 a0x008 . . . 226
51.4 gll_ctrl . . . 226
51.5 gll_ctrl2 . . . 227
51.6 a0x094 . . . 227
51.7 a0x098 . . . 227
51.8 txdfe_rtcv0 . . . 227
51.9 txdfe_rtcv1 . . . 227
51.10 rxdfe_rtcv0 . . . 227
51.11 rxdfe_rtcv1 . . . 227
51.12 a0x0f0 . . . 227
51.13 a0x100 . . . 228
51.14 a0x104 . . . 228
51.15 a0x108 . . . 228
51.16 a0x10c . . . 228
51.17 a0x110 . . . 228
51.18 a0x114 . . . 228
51.19 a0x118 . . . 228
51.20 a0x11c . . . 229
51.21 a0x120 . . . 229
51.22 a0x200 . . . 229
51.23 a0x204 . . . 229
51.24 a0x208 . . . 229
51.25 a0x20c . . . 229
51.26 a0x210 . . . 229
51.27 cass_ctrl . . . 229
51.28 cass_var . . . 230
51.29 cass_rfpwr . . . 230
51.30 cass_map0 . . . 230
51.31 cass_map1 . . . 230
51.32 cass_rssi0 . . . 230
51.33 cass_rssi1 . . . 230
51.34 cass_rssi2 . . . 230
51.35 cass_rssi3 . . . 230
51.36 cass_rssi4 . . . 231
51.37 cass_rssi5 . . . 231
51.38 cass_rssi6 . . . 231
51.39 cass_rssi7 . . . 231
51.40 cass_rssi8 . . . 231
51.41 cass_rssi9 . . . 231

51.42 a0x500 . . . 231
51.43 a0x504 . . . 231
51.44 a0x508 . . . 231
51.45 a0x50c . . . 232
51.46 a0x510 . . . 232
51.47 a0x514 . . . 232
51.48 a0x518 . . . 232
51.49 a0x51c . . . 233
51.50 a0x520 . . . 233
51.51 a0x528 . . . 233
51.52 a0x52c . . . 233
51.53 a0x530 . . . 233
51.54 a0x534 . . . 234
51.55 a0x544 . . . 234
51.56 a0x5a0 . . . 234
51.57 a0x5a4 . . . 234
51.58 a0x5a8 . . . 234
51.59 a0x5ac . . . 234
51.60 a0x5b0 . . . 234
51.61 a0x5b4 . . . 235
51.62 a0x5b8 . . . 235
51.63 a0x5bc . . . 235
51.64 a0x5c0 . . . 235
51.65 a0x5c4 . . . 235
51.66 a0x5c8 . . . 235
51.67 a0x5cc . . . 235
51.68 a0x5d0 . . . 235
51.69 a0x5d4 . . . 235
51.70 a0x5d8 . . . 236
51.71 a0x5dc . . . 236
51.72 a0x5f0 . . . 236
51.73 a0x810 . . . 236
51.74 a0x814 . . . 236
51.75 a0x81c . . . 236
51.76 a0x820 . . . 236
51.77 a0x824 . . . 237
51.78 a0x828 . . . 237
51.79 a0x82c . . . 237
51.80 a0x830 . . . 237
51.81 a0x834 . . . 237
51.82 ppm_838 . . . 237
51.83 fref_tx_hm . . . 237
51.84 fref_tx . . . 237
51.85 fref_rx . . . 237
51.86 coef_rfwf . . . 238
51.87 a0x86c . . . 238
51.88 a0x880 . . . 238
51.89 a0x884 . . . 238
51.90 a0x888 . . . 238
51.91 a0x88c . . . 238
51.92 a0x890 . . . 238
51.93 a0x894 . . . 238
51.94 a0x898 . . . 238
51.95 a0x89c . . . 238
51.96 a0x8ac . . . 238
51.97 a0x8b0 . . . 239
bt_mdm_cfg
52.1 cfg_mem_sr1rw . . . 239
52.2 cfg_mem_sr2rw . . . 239

52.3 cfg_mem_spram . . . 239
52.4 a0x010 . . . 239
52.5 a0x014 . . . 239
52.6 a0x018 . . . 239
52.7 a0x01c . . . 239
52.8 a0x020 . . . 240
52.9 a0x024 . . . 240
52.10 a0x028 . . . 240
52.11 a0x030 . . . 240
52.12 a0x034 . . . 240
52.13 a0x040 . . . 240
52.14 a0x044 . . . 240
52.15 a0x048 . . . 241
52.16 a0x04c . . . 241
52.17 a0x050 . . . 241
52.18 a0x054 . . . 241
52.19 a0x058 . . . 241
52.20 a0x05c . . . 241
52.21 a0x060 . . . 241
52.22 a0x064 . . . 241
52.23 a0x068 . . . 241
52.24 a0x06c . . . 242
52.25 a0x070 . . . 242
52.26 a0x074 . . . 242
52.27 a0x078 . . . 242
52.28 a0x07c . . . 242
52.29 a0x080 . . . 242
52.30 a0x084 . . . 242
52.31 a0x400 . . . 242
52.32 a0x404 . . . 242
52.33 a0x408 . . . 242
52.34 a0x40c . . . 242
52.35 a0x410 . . . 243
52.36 a0x414 . . . 243
52.37 a0x418 . . . 243
52.38 a0x420 . . . 243
52.39 a0x424 . . . 243
52.40 a0x428 . . . 243
52.41 a0x42c . . . 243
52.42 a0x430 . . . 243
52.43 a0x434 . . . 243
52.44 a0x438 . . . 244
52.45 a0x43c . . . 244
52.46 a0x440 . . . 244
52.47 a0x444 . . . 244
52.48 a0x448 . . . 244
52.49 a0x44c . . . 244
52.50 a0x450 . . . 244
52.51 a0x454 . . . 245
52.52 a0x458 . . . 245
52.53 a0x45c . . . 245
52.54 a0x460 . . . 245
52.55 a0x464 . . . 245
52.56 a0x468 . . . 245
52.57 a0x46c . . . 245
52.58 a0x470 . . . 246
52.59 a0x474 . . . 246
52.60 a0x478 . . . 246
52.61 a0x47c . . . 246
52.62 a0x480 . . . 246

52.63 a0x484 . . . 246
52.64 a0x488 . . . 246
52.65 a0x48c . . . 246
52.66 a0x544 . . . 247
52.67 a0x548 . . . 247
52.68 a0x57c . . . 247
52.69 a0x580 . . . 247
52.70 a0x584 . . . 247
52.71 a0x588 . . . 247
52.72 a0x58c . . . 247
52.73 a0x590 . . . 247
52.74 a0x594 . . . 247
52.75 a0x598 . . . 248
52.76 a0x870 . . . 248
52.77 a0x874 . . . 248
52.78 a0x878 . . . 248
52.79 a0x87c . . . 248
52.80 a0x8b4 . . . 248
bt_rf_interface
53.1 bt_pu_reg1 . . . 248
53.2 bt_pu_reg2 . . . 249
53.3 bt_test_reg . . . 249
53.4 bt_td_reg1 . . . 249
53.5 bt_td_reg2 . . . 250
53.6 bt_lna_reg . . . 250
53.7 bt_tia_reg . . . 250
53.8 bt_sdmadc_reg . . . 250
53.9 bt_dpa_reg1 . . . 251
53.10 bt_dpa_reg2 . . . 251
53.11 bt_dpa_ldo_reg . . . 251
53.12 bt_dpll_reg1 . . . 251
53.13 bt_dpll_reg2 . . . 252
53.14 bt_tdac_reg . . . 252
53.15 bt_misc_reg . . . 252
53.16 bt_ifconf_reg1 . . . 252
53.17 bt_ifconf_reg2 . . . 253
53.18 bt_agc_dc_reg1 . . . 253
53.19 bt_soft_reset_reg . . . 253
53.20 bt_man_crtl_reg . . . 253
53.21 bt_calclk_reg . . . 254
53.22 bt_dpa_cal_ctrl_reg . . . 254
53.23 bt_rxgain_mem_ctrl_reg . . . 254
53.24 bt_rxgain_mem_wdata_reg . . . 254
53.25 bt_rxgain_mem_rdata_reg . . . 254
53.26 bt_txgain_mem_ctrl_reg . . . 254
53.27 bt_txgain_mem_wdata_reg . . . 254
53.28 bt_txgain_mem_rdata_reg . . . 255
53.29 bt_dig_reserved_reg . . . 255
53.30 bt_pu_done_reg . . . 255
53.31 bt_rxgain_table_out_reg0 . . . 255
53.32 bt_rxgain_table_out_reg1 . . . 255
53.33 bt_rxgain_table_out_reg2 . . . 255
53.34 bt_rxgain_table_out_reg3 . . . 255
53.35 bt_txgain_table_out_reg0 . . . 255
53.36 bt_txgain_table_out_reg1 . . . 255
53.37 bt_agc_reserved_reg . . . 255
53.38 bt_apc_reserved_reg . . . 255
pmu_rtc0
54.1 pmu_rtc0_cfg0 . . . 256

54.2 pmu_rtc0_cfg1 . . . 256
54.3 pmu_rtc0_cfg2 . . . 256
54.4 pmu_rtc0_cfg3 . . . 256
54.5 pmu_rtc0_cfg4 . . . 257
54.6 pmu_rtc0_cfg5 . . . 257
54.7 pmu_rtc0_cfg6 . . . 257
54.8 pmu_rtc0_cfg7 . . . 257
54.9 pmu_rtc0_wdg4_cnt_ini . . . 258
54.10 rtc_rg_reserved0 . . . 258
54.11 rtc_rg_reserved1 . . . 258
pmu_rtc1
55.1 pmu_pd_ctrl0 . . . 258
55.2 pmu_pd_ctrl1 . . . 259
55.3 pmu_seq_num0 . . . 259
55.4 pmu_seq_num1 . . . 259
55.5 pmu_slp_ctrl0 . . . 259
55.6 pmu_slp_ctrl1 . . . 260
55.7 pmu_clk_ctrl0 . . . 260
55.8 pmu_clk_ctrl1 . . . 261
55.9 pmu_clk_ctrl2 . . . 261
55.10 pmu_clk_ctrl3 . . . 261
55.11 pmu_rstn_ctrl . . . 261
55.12 pmu_dcdc_rf_ctrl0 . . . 262
55.13 pmu_dcdc_rf_ctrl1 . . . 262
55.14 pmu_dcdc_rf_ctrl2 . . . 262
55.15 pmu_dcdc_rf_ctrl3 . . . 263
55.16 pmu_ldo_vcore08_ctrl . . . 263
55.17 pmu_ldo_vrtc08_ctrl . . . 263
55.18 pmu_other_ldo_ctrl0 . . . 264
55.19 pmu_other_ldo_ctrl1 . . . 264
55.20 pmu_long_pwr_key_cfg . . . 264
55.21 pmu_rf_on_cfg . . . 264
55.22 pmu_psm_cfg0 . . . 265
55.23 pmu_psm_cfg1 . . . 265
55.24 pmu_psm_cfg2 . . . 265
55.25 pmu_psm_cfg3 . . . 265
55.26 pmu_psm_cfg4 . . . 265
55.27 pmu_psm_cfg5 . . . 265
55.28 pmu_psm_cfg6 . . . 266
55.29 pmu_psm_cfg7 . . . 266
55.30 pmu_monitor_cfg . . . 266
55.31 pmu_status . . . 266
55.32 pmu_int_irq . . . 266
55.33 pmu_xtal_clk_detect . . . 267
55.34 pmu_cm_xtal_cfg1 . . . 267
55.35 pmu_cm_xtal_cfg2 . . . 267
55.36 pmu_clk_div_128k . . . 267
55.37 pmu_ldo_vflash_ctrl . . . 267
55.38 pmu_dcdc_core_ctrl0 . . . 267
55.39 pmu_dcdc_core_ctrl1 . . . 268
55.40 pmu_dcdc_core_ctrl2 . . . 268
55.41 pmu_dcdc_core_ctrl3 . . . 268
wdg4
56.1 WDG_LOAD_VAL . . . 269
56.2 WDG_CNT . . . 269
56.3 WDG_CTRL . . . 269
56.4 WDG_INT_CLR . . . 269
56.5 WDG_INT_RAW . . . 269
56.6 WDG_INT_MASK . . . 269

56.7 WDG_LOCK . . . 269
dcdc_common
57.1 dcdc_ref_clk_div . . . 270
57.2 dcdc_clk_ctrl0 . . . 270
57.3 dcdc_clk_ctrl1 . . . 270
57.4 dcdc_clk_ctrl2 . . . 270
57.5 dcdc_clk_ctrl3 . . . 270
dcdc_rf_ctrl
58.1 dcdc_clk_ctrl0 . . . 270
58.2 dcdc_clk_ctrl1 . . . 270
58.3 dcdc_clk_ctrl2 . . . 271
58.4 dcdc_clk_ctrl3 . . . 271
58.5 dcdc_clk_ctrl4 . . . 271
58.6 dcdc_clk_ctrl5 . . . 271
58.7 dcdc_clk_ctrl6 . . . 271
58.8 dcdc_clk_ctrl7 . . . 271
58.9 dcdc_ctrl_cfg0 . . . 271
58.10 dcdc_ctrl_cfg1 . . . 271
58.11 dcdc_ctrl_cfg2 . . . 271
58.12 dcdc_ctrl_cfg3 . . . 272
58.13 dcdc_ctrl_cfg4 . . . 272
58.14 dcdc_ctrl_cfg5 . . . 272
58.15 dcdc_ctrl_cfg6 . . . 272
58.16 dcdc_ctrl_cfg7 . . . 272
58.17 dcdc_ctrl_cfg8 . . . 272
58.18 dcdc_ctrl_cfg9 . . . 272
58.19 dcdc_ctrl_cfg10 . . . 272
58.20 dcdc_ctrl_cfg11 . . . 272
58.21 dcdc_ctrl_cfg12 . . . 272
58.22 dcdc_ctrl_cfg13 . . . 272
58.23 dcdc_ctrl_cfg14 . . . 273
58.24 dcdc_ctrl_cfg15 . . . 273
58.25 dcdc_ctrl_cfg16 . . . 273
58.26 dcdc_ctrl_cfg17 . . . 273
58.27 dcdc_ctrl_cfg18 . . . 273
58.28 dcdc_ctrl_cfg19 . . . 273
58.29 dcdc_ctrl_cfg20 . . . 273
58.30 dcdc_ctrl_cfg21 . . . 273
58.31 dcdc_ctrl_cfg22 . . . 273
58.32 dcdc_ctrl_cfg23 . . . 273
58.33 dcdc_ctrl_cfg24 . . . 274
58.34 dcdc_ctrl_cfg25 . . . 274
58.35 dcdc_ctrl_cfg26 . . . 274
58.36 dcdc_ctrl_cfg27 . . . 274
58.37 dcdc_ctrl_cfg28 . . . 274
58.38 dcdc_ctrl_cfg29 . . . 274
58.39 dcdc_ctrl_cfg30 . . . 274
58.40 dcdc_ctrl_cfg31 . . . 274
58.41 dcdc_ctrl_cfg32 . . . 274
58.42 dcdc_ctrl_cfg33 . . . 274
58.43 dcdc_ctrl_cfg34 . . . 275
58.44 dcdc_ctrl_cfg35 . . . 275
58.45 dcdc_ctrl_cfg36 . . . 275
58.46 dcdc_ctrl_cfg37 . . . 275
58.47 dcdc_ctrl_cfg38 . . . 275
58.48 dcdc_ctrl_cfg39 . . . 275
58.49 dcdc_ctrl_cfg40 . . . 275
58.50 dcdc_ctrl_cfg41 . . . 275
58.51 dcdc_ctrl_cfg42 . . . 276

58.52 dcdc_ctrl_cfg43 . . . 276
58.53 dcdc_status . . . 276
dcdc_core_ctrl
59.1 dcdc_clk_ctrl0 . . . 276
59.2 dcdc_clk_ctrl1 . . . 276
59.3 dcdc_clk_ctrl2 . . . 276
59.4 dcdc_clk_ctrl3 . . . 277
59.5 dcdc_clk_ctrl4 . . . 277
59.6 dcdc_clk_ctrl5 . . . 277
59.7 dcdc_clk_ctrl6 . . . 277
59.8 dcdc_clk_ctrl7 . . . 277
59.9 dcdc_ctrl_cfg0 . . . 277
59.10 dcdc_ctrl_cfg1 . . . 277
59.11 dcdc_ctrl_cfg2 . . . 277
59.12 dcdc_ctrl_cfg3 . . . 277
59.13 dcdc_ctrl_cfg4 . . . 278
59.14 dcdc_ctrl_cfg5 . . . 278
59.15 dcdc_ctrl_cfg6 . . . 278
59.16 dcdc_ctrl_cfg7 . . . 278
59.17 dcdc_ctrl_cfg8 . . . 278
59.18 dcdc_ctrl_cfg9 . . . 278
59.19 dcdc_ctrl_cfg10 . . . 278
59.20 dcdc_ctrl_cfg11 . . . 278
59.21 dcdc_ctrl_cfg12 . . . 278
59.22 dcdc_ctrl_cfg13 . . . 278
59.23 dcdc_ctrl_cfg14 . . . 278
59.24 dcdc_ctrl_cfg15 . . . 279
59.25 dcdc_ctrl_cfg16 . . . 279
59.26 dcdc_ctrl_cfg17 . . . 279
59.27 dcdc_ctrl_cfg18 . . . 279
59.28 dcdc_ctrl_cfg19 . . . 279
59.29 dcdc_ctrl_cfg20 . . . 279
59.30 dcdc_ctrl_cfg21 . . . 279
59.31 dcdc_ctrl_cfg22 . . . 279
59.32 dcdc_ctrl_cfg23 . . . 279
59.33 dcdc_ctrl_cfg24 . . . 279
59.34 dcdc_ctrl_cfg25 . . . 279
59.35 dcdc_ctrl_cfg26 . . . 280
59.36 dcdc_ctrl_cfg27 . . . 280
59.37 dcdc_ctrl_cfg28 . . . 280
59.38 dcdc_ctrl_cfg29 . . . 280
59.39 dcdc_ctrl_cfg30 . . . 280
59.40 dcdc_ctrl_cfg31 . . . 280
59.41 dcdc_ctrl_cfg32 . . . 280
59.42 dcdc_ctrl_cfg33 . . . 280
59.43 dcdc_ctrl_cfg34 . . . 280
59.44 dcdc_ctrl_cfg35 . . . 280
59.45 dcdc_ctrl_cfg36 . . . 281
59.46 dcdc_ctrl_cfg37 . . . 281
59.47 dcdc_ctrl_cfg38 . . . 281
59.48 dcdc_ctrl_cfg39 . . . 281
59.49 dcdc_ctrl_cfg40 . . . 281
59.50 dcdc_ctrl_cfg41 . . . 281
59.51 dcdc_ctrl_cfg42 . . . 281
59.52 dcdc_ctrl_cfg43 . . . 282
59.53 dcdc_status . . . 282