

# pana\_vp\_VMZx

Command reference — **generated based on the Python file** `device/pana_vp_VMZx.py`. This document was produced automatically by parsing the driver module (no vendor documentation was available for this device); it lists the control/status commands the module implements.

Generated 2026-07-17

## Device information

| Property    | Value                                                                                      |
|-------------|--------------------------------------------------------------------------------------------|
| Device type | projector                                                                                  |
| Models      | PT-VMZ51S, PT-BMZ51, PT-VMZ41, PT-VMZ71, PT-VMZ61, PT-VMW61, PT-VMW51, PT-VMZ50U, PT-VMZ50 |
| Connection  | com_type=Network, protocol=TCP, net_port=1024, service_port=0                              |

## Commands

| Command        | Set | Update | Allowed values / Parameters                                                               |
|----------------|-----|--------|-------------------------------------------------------------------------------------------|
| AspectRatio    | Yes | Yes    | Auto, Normal, Wide, Native, Full, H-Fit, V-Fit                                            |
| AudioMute      | Yes | Yes    | On, Off                                                                                   |
| AutoImage      | Yes | -      | -                                                                                         |
| FilterUsage    | -   | Yes    | -                                                                                         |
| Freeze         | Yes | Yes    | On, Off                                                                                   |
| Input          | Yes | Yes    | Computer 1, Computer 2, HDMI 1, HDMI 2, Network/USB, Network, Memory Viewer, Digital Link |
| Keypad         | Yes | -      | -                                                                                         |
| LampMode       | Yes | Yes    | Normal, Eco, Quiet, User                                                                  |
| LampUsage      | -   | Yes    | -                                                                                         |
| MenuNavigation | Yes | -      | Menu, Return, Enter, Up, Down, Left, Right                                                |
| OperationHours | -   | Yes    | -                                                                                         |
| PictureMode    | Yes | Yes    | Dynamic, Natural, Standard, White Board, Cinema, Dicom Sim.                               |
| Power          | Yes | Yes    | On, Off                                                                                   |
| Shutter        | Yes | Yes    | On, Off                                                                                   |
| Volume         | Yes | Yes    | -                                                                                         |

## Command strings

Raw command / query strings sent to the device, extracted from each Set/Update method (control characters shown as Python escapes, e.g. `\r`).

### SetAspectRatio

```
'\x02AD{};VSE: {}\x03'.format(...)
```

values: Auto→0, Normal→1, Wide→2, Native→5, Full→6, H-Fit→9, V-Fit→10

### SetAudioMute

'\x02AD{};AMT:{}\x03'.format(...)  
values: On→1, Off→0

### ***SetAutolmage***

'\x02AD{};0AS\x03'.format(...)

### ***SetFreeze***

'\x02AD{};0FZ:{}\x03'.format(...)  
values: On→1, Off→0

### ***SetInput***

'\x02AD{};IIS:{}\x03'.format(...)

### ***SetKeypad***

'\x02AD{};ONK:{}\x03'.format(...)

### ***SetLampMode***

'\x02AD{};VXX:LPWI1=+\{}\x03'.format(...)  
values: Normal→00000, Eco→00001, Quiet→00040, User→00100

### ***SetMenuNavigation***

'\x02AD{};{}\x03'.format(...)  
values: Menu→OMN, Return→OBK, Enter→OEN, Up→OCU, Down→OCD, Left→OCL, Right→OCR

### ***SetPictureMode***

'\x02AD{};VPM:{}\x03'.format(...)  
values: Dynamic→DYN, Natural→NAT, Standard→STD, White Board→WBD, Cinema→CIN, Dicom Sim.→DIC

### ***SetPower***

'\x02AD{};{}\x03'.format(...)  
values: On→PON, Off→POF

### ***SetShutter***

'\x02AD{};0SH:{}\x03'.format(...)  
values: On→1, Off→0

### ***SetVolume***

'\x02AD{};AVL:{:>03}\x03'.format(...)

### ***UpdateAspectRatio***

'\x02AD{};QS1\x03'.format(...)  
values: 0→Auto, 1→Normal, 2→Wide, 5→Native, 6→Full, 9→H-Fit, 10→V-Fit

### ***UpdateAudioMute***

'\x02AD{};QMT\x03'.format(...)  
values: 1→On, 0→Off

### ***UpdateFilterUsage***

'\x02AD{};QFI:0\x03'.format(...)

### ***UpdateFreeze***

'\x02AD{};QFZ\x03'.format(...)  
values: 1→On, 0→Off

### ***UpdateInput***

'\x02AD{};QIN\x03'.format(...)

### ***UpdateLampMode***

'\x02AD{};QLP\x03'.format(...)

values: 00000→Normal, 00001→Eco, 00040→Quiet, 00100→User

### ***UpdateLampUsage***

'\x02AD{};Q\$L\x03'.format(...)

### ***UpdateOperationHours***

'\x02AD{};QVX:RTMI0\x03'.format(...)

### ***UpdatePictureMode***

'\x02AD{};QPM\x03'.format(...)

values: DYN→Dynamic, NAT→Natural, STD→Standard, WBD→White Board, CIN→Cinema, DIC→Dicom Sim.

### ***UpdatePower***

'\x02AD{};QPW\x03'.format(...)

values: 001→On, 000→Off

### ***UpdateShutter***

'\x02AD{};QSH\x03'.format(...)

values: 1→On, 0→Off

### ***UpdateVolume***

'\x02AD{};QAV\x03'.format(...)