

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Camera
Manufacturer: AVer
Firmware Version: N/A
Model(s): PTZ310, PTZ330, PTZ310W, PTZ330W

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.16.0000-b013	2.19.0

Version History

Module Version	Date	Notes
1_0_4_0	3/15/2023	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- DeviceID variable must be set accordingly. Default value is '1'. DeviceID ranges from '1' to '7'.
Example: `InterfaceName.DeviceID = '1'`

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='PTZ310')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='PTZ310')</code>
EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 52381, Model='PTZ310')</code>

Control Commands (Serial)

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command AutoExposure	Value 'Full Auto' 'Manual'	Value 'Iris Priority'	Value 'Shutter Priority'
# AutoExposure example InterfaceName.Set('AutoExposure', 'Full Auto')			
Command Backlight	Value 'On'	Value 'Off'	
# Backlight example InterfaceName.Set('Backlight', 'On')			
Command ExposureValue ¹	Value 'Reset'	Value 'Up'	Value 'Down'
# ExposureValue example InterfaceName.Set('ExposureValue', 'Reset')			
Command Focus	Value 'Far'	Value 'Near'	Value 'Stop'
# Focus example InterfaceName.Set('Focus', 'Far')			
Command FocusMode	Value 'Auto Focus'	Value 'Manual Focus'	
# FocusMode example InterfaceName.Set('FocusMode', 'Auto Focus')			
Command GainLevel ¹	Value 'Reset'	Value 'Up'	Value 'Down'
# GainLevel example InterfaceName.Set('GainLevel', 'Reset')			
Command Home	Value None		
# Home example InterfaceName.Set('Home', None)			
Command IrisLevel ¹	Value 'Reset'	Value 'Up'	Value 'Down'
# IrisLevel example InterfaceName.Set('IrisLevel', 'Reset')			
Command PanTilt	Value 'Up' 'Right' 'Down Left'	Value 'Down' 'Up Left' 'Down Right'	Value 'Left' 'Up Right' 'Stop'
Qualifier Key 'Pan Speed'	Qualifier Value 1 – 24		
Qualifier Key 'Tilt Speed'	Qualifier Value 1 – 24		
# PanTilt example InterfaceName.Set('PanTilt', 'Up', {'Pan Speed': 24, 'Tilt Speed': 24})			

Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Set('Power', 'On')			
Command PresetRecall	Value '0' – '255'		
# PresetRecall example InterfaceName.Set('PresetRecall', '0')			
Command PresetSave	Value '0' – '255'		
# PresetSave example InterfaceName.Set('PresetSave', '0')			
Command ShutterSpeed ¹	Value 'Reset'	Value 'Up'	Value 'Down'
# ShutterSpeed example InterfaceName.Set('ShutterSpeed', 'Reset')			
Command SmartShoot	Value 'On'	Value 'Off'	
# SmartShoot example InterfaceName.Set('SmartShoot', 'On')			
Command SystemMenu ²	Value 'On'	Value 'Off'	Value 'Enter'
# SystemMenu example InterfaceName.Set('SystemMenu', 'On')			
Command WhiteBalance	Value 'Auto' 'One Push'	Value 'Indoor' 'Manual'	Value 'Outdoor'
# WhiteBalance example InterfaceName.Set('WhiteBalance', 'Auto')			
Command Zoom	Value 'Tele'	Value 'Wide'	Value 'Stop'
Qualifier Key 'Speed'	Qualifier Value 0 – 7		
# Zoom example InterfaceName.Set('Zoom', 'Tele', {'Speed': 7})			

¹ This command is only available based on the value being used in the Auto Exposure command.

² When System Menu is 'On', the Pan Tilt directional commands can be used to navigate through the menus. System Menu must be 'Off' for the Pan Tilt directional commands to control the camera.

Status Available (Serial)

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command	Value	Value
ConnectionStatus	'Connected'	'Disconnected'
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)		
Command	Value	Value
Power	'On'	'Off'
# Power example InterfaceName.Update('Power') Value = InterfaceName.ReadStatus('Power') InterfaceName.SubscribeStatus('Power', None, FeedbackHandler)		

Control Commands (Ethernet)

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command AutoExposure	Value 'Full Auto' 'Manual'	Value 'Iris Priority'	Value 'Shutter Priority'
# AutoExposure example InterfaceName.Set('AutoExposure', 'Full Auto')			
Command Backlight	Value 'On'	Value 'Off'	
# Backlight example InterfaceName.Set('Backlight', 'On')			
Command ExposureValue ¹	Value 'Reset'	Value 'Up'	Value 'Down'
# ExposureValue example InterfaceName.Set('ExposureValue', 'Reset')			
Command Focus	Value 'Far'	Value 'Near'	Value 'Stop'
# Focus example InterfaceName.Set('Focus', 'Far')			
Command FocusMode	Value 'Auto Focus'	Value 'Manual Focus'	
# FocusMode example InterfaceName.Set('FocusMode', 'Auto Focus')			
Command GainLevel ¹	Value 'Reset'	Value 'Up'	Value 'Down'
# GainLevel example InterfaceName.Set('GainLevel', 'Reset')			
Command Home	Value None		
# Home example InterfaceName.Set('Home', None)			
Command IrisLevel ¹	Value 'Reset'	Value 'Up'	Value 'Down'
# IrisLevel example InterfaceName.Set('IrisLevel', 'Reset')			
Command PanTilt	Value 'Up' 'Right' 'Down Left'	Value 'Down' 'Up Left' 'Down Right'	Value 'Left' 'Up Right' 'Stop'
Qualifier Key 'Pan Speed'	Qualifier Value 1 – 24		
Qualifier Key 'Tilt Speed'	Qualifier Value 1 – 24		
# PanTilt example InterfaceName.Set('PanTilt', 'Up', {'Pan Speed': 24, 'Tilt Speed': 24})			

Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Set('Power', 'On')			
Command PresetRecall	Value '0' – '255'		
# PresetRecall example InterfaceName.Set('PresetRecall', '0')			
Command PresetSave	Value '0' – '255'		
# PresetSave example InterfaceName.Set('PresetSave', '0')			
Command ShutterSpeed ¹	Value 'Reset'	Value 'Up'	Value 'Down'
# ShutterSpeed example InterfaceName.Set('ShutterSpeed', 'Reset')			
Command SmartShoot	Value 'On'	Value 'Off'	
# SmartShoot example InterfaceName.Set('SmartShoot', 'On')			
Command SystemMenu ²	Value 'On'	Value 'Off'	Value 'Enter'
# SystemMenu example InterfaceName.Set('SystemMenu', 'On')			
Command WhiteBalance	Value 'Auto' 'One Push'	Value 'Indoor' 'Manual'	Value 'Outdoor'
# WhiteBalance example InterfaceName.Set('WhiteBalance', 'Auto')			
Command Zoom	Value 'Tele'	Value 'Wide'	Value 'Stop'
Qualifier Key 'Speed'	Qualifier Value 0 – 7		
# Zoom example InterfaceName.Set('Zoom', 'Tele', {'Speed': 7})			

¹ This command is only available based on the value being used in the Auto Exposure command.

² When System Menu is 'On', the Pan Tilt directional commands can be used to navigate through the menus. System Menu must be 'Off' for the Pan Tilt directional commands to control the camera.

Cable and Adapter Requirements

RS-232: Captive Screw to Din8.

RS-422: Captive Screw to Cat5e.

Notes for the Device

For the module to work, ensure the following setting is set within the device menu:

- Advanced Setting → Control → Protocol → VISCA

Serial communication

Port Type: RS-232, RS-422

Baud Rate: 9600

Data Bits: 8


Parity: None

Stop Bits: One


Flow Control: None

Pin Assignments Diagram


RS-232:




Signal	Main Cable	Pin	Signal
TxD	→	5	RxD
RxD	←	3	TxD
GND	→	4/6	GND



RS-422:



Signal	Main Cable	Pin	Signal
TxD+	→	6/8	RxD+
TxD-	→	3/7	RxD-
RxD+	←	2/5	TxD+
RxD-	←	1/4	TxD-



Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scripter ethernet interface.

Port Type: Ethernet (UDP)

Device Listen Port: 52381

Logon Credentials Supported: No

Multi-Connection Capabilities: Undetermined

Listen Port Changeability: No

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

For the module to work, ensure the following setting is set within the device menu:

- Advanced Setting → Control → Protocol → VISCA

Appendix A. Set Commands(Serial, Device ID: 1)

Auto Exposure Full Auto	\x81\x01\x049\x00\xff
Auto Exposure Iris Priority	\x81\x01\x049\x0B\xff
Auto Exposure Manual	\x81\x01\x049\x03\xff
Auto Exposure Shutter Priority	\x81\x01\x049\x0A\xff
Backlight Off	\x81\x01\x043\x03\xff
Backlight On	\x81\x01\x043\x02\xff
Exposure Value Down	\x81\x01\x04\x0E\x03\xff
Exposure Value Reset	\x81\x01\x04\x0E\x00\xff
Exposure Value Up	\x81\x01\x04\x0E\x02\xff
Focus Far	\x81\x01\x04\x08\x02\xff
Focus Mode Auto Focus	\x81\x01\x048\x02\xff
Focus Mode Manual Focus	\x81\x01\x048\x03\xff
Focus Near	\x81\x01\x04\x08\x03\xff
Focus Stop	\x81\x01\x04\x08\x00\xff
Gain Level Down	\x81\x01\x04\x0C\x03\xff
Gain Level Reset	\x81\x01\x04\x0C\x00\xff
Gain Level Up	\x81\x01\x04\x0C\x02\xff
Home None	\x81\x01\x06\x04\xff
Iris Level Down	\x81\x01\x04\x0B\x03\xff
Iris Level Reset	\x81\x01\x04\x0B\x00\xff
Iris Level Up	\x81\x01\x04\x0B\x02\xff
Pan Tilt Down Left Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\xff
Pan Tilt Down Left Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\x02\xff
Pan Tilt Down Left Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\x02\xff
Pan Tilt Down Left Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\x02\xff
Pan Tilt Down Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\x02\xff
Pan Tilt Down Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\x02\xff
Pan Tilt Down Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x02\xff
Pan Tilt Down Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\x02\xff
Pan Tilt Down Right Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\x02\xff
Pan Tilt Down Right Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\x02\xff
Pan Tilt Down Right Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x02\xff
Pan Tilt Down Right Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\x02\xff
Pan Tilt Left Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\xff
Pan Tilt Left Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\x03\xff
Pan Tilt Left Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\x03\xff
Pan Tilt Left Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\x03\xff
Pan Tilt Right Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\x03\xff
Pan Tilt Right Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\x03\xff
Pan Tilt Right Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x03\xff
Pan Tilt Right Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\x03\xff
Pan Tilt Stop Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\x03\xff

Global Scriptor Module Communication Sheet

Pan Tilt Stop Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\x03\xff
Pan Tilt Stop Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x03\xff
Pan Tilt Stop Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\x03\xff
Pan Tilt Up Left Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x01\xff
Pan Tilt Up Left Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\x01\xff
Pan Tilt Up Left Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\xff
Pan Tilt Up Left Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\x01\xff
Pan Tilt Up Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x03\x01\xff
Pan Tilt Up Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\x01\xff
Pan Tilt Up Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x01\xff
Pan Tilt Up Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\x01\xff
Pan Tilt Up Right Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x02\x01\xff
Pan Tilt Up Right Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\x01\xff
Pan Tilt Up Right Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x01\xff
Pan Tilt Up Right Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\x01\xff
Power Off	\x81\x01\x04\x00\x03\xff
Power On	\x81\x01\x04\x00\x02\xff
Preset Recall 0	\x81\x01\x04?\x02\x00\xff
Preset Recall 255	\x81\x01\x04?\x02\xff\xff
Preset Save 0	\x81\x01\x04?\x01\x00\xff
Preset Save 255	\x81\x01\x04?\x01\xff\xff
Shutter Speed Down	\x81\x01\x04\x0A\x03\xff
Shutter Speed Reset	\x81\x01\x04\x0A\x00\xff
Shutter Speed Up	\x81\x01\x04\x0A\x02\xff
SmartShoot Off	\x81\x01\x04?\x01^\xff
SmartShoot On	\x81\x01\x04?\x01]\xff
System Menu Enter	\x81\x01~\x01\x02\x00\x01\xff
System Menu Off	\x81\x01\x06\x06\x03\xff
System Menu On	\x81\x01\x06\x06\x02\xff
White Balance Auto	\x81\x01\x045\x00\xff
White Balance Indoor	\x81\x01\x045\x01\xff
White Balance Manual	\x81\x01\x045\x05\xff
White Balance One Push	\x81\x01\x045\x03\xff
White Balance Outdoor	\x81\x01\x045\x02\xff
Zoom Stop Speed 0	\x81\x01\x04\x07\x00\xff
Zoom Stop Speed 7	\x81\x01\x04\x07\x00\xff
Zoom Tele Speed 0	\x81\x01\x04\x07 \xff
Zoom Tele Speed 7	\x81\x01\x04\x07' \xff
Zoom Wide Speed 0	\x81\x01\x04\x070\xff
Zoom Wide Speed 7	\x81\x01\x04\x077\xff

Appendix B. Update Commands(Serial, Device ID: 1)

Power	\x81\x09\x04\x00\xff
-------	----------------------

Appendix C. Set Commands(Ethernet, Device ID: 1)

Auto Exposure Full Auto	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x049\x00\xFF
Auto Exposure Iris Priority	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x049\x0B\xFF
Auto Exposure Manual	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x049\x03\xFF
Auto Exposure Shutter Priority	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x049\x0A\xFF
Backlight Off	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x043\x03\xFF
Backlight On	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x043\x02\xFF
Exposure Value Down	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0E\x03\xFF
Exposure Value Reset	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0E\x00\xFF
Exposure Value Up	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0E\x02\xFF
Focus Far	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x08\x02\xFF
Focus Mode Auto Focus	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x048\x02\xFF
Focus Mode Manual Focus	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x048\x03\xFF
Focus Near	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x08\x03\xFF
Focus Stop	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x08\x00\xFF
Gain Level Down	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0C\x03\xFF
Gain Level Reset	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0C\x00\xFF
Gain Level Up	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0C\x02\xFF
Home None	\x01\x00\x00\x05\x00\x00\x00\x01\x81\x01\x06\x04\xFF
Iris Level Down	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0B\x03\xFF
Iris Level Reset	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0B\x00\xFF
Iris Level Up	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0B\x02\xFF
Pan Tilt Down Left Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x02\xFF
Pan Tilt Down Left Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x01\x02\xFF
Pan Tilt Down Left Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x01\x02\xFF
Pan Tilt Down Left Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x01\x02\xFF
Pan Tilt Down Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x03\x02\xFF
Pan Tilt Down Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x03\x02\xFF
Pan Tilt Down Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x03\x02\xFF
Pan Tilt Down Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x03\x02\xFF
Pan Tilt Down Right Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x02\x02\xFF
Pan Tilt Down Right Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x02\x02\xFF
Pan Tilt Down Right Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x02\x02\xFF
Pan Tilt Down Right Pan Speed	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x02\x02\xFF

Global Scripter Module Communication Sheet

24 Tilt Speed 24	
Pan Tilt Left Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x03\xff
Pan Tilt Left Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x01\x03\xff
Pan Tilt Left Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x01\x03\xff
Pan Tilt Left Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x01\x03\xff
Pan Tilt Right Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x02\x03\xff
Pan Tilt Right Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x02\x03\xff
Pan Tilt Right Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x02\x03\xff
Pan Tilt Right Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x02\x03\xff
Pan Tilt Stop Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x03\x03\xff
Pan Tilt Stop Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x03\x03\xff
Pan Tilt Stop Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x03\x03\xff
Pan Tilt Stop Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x03\x03\xff
Pan Tilt Up Left Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x01\xff
Pan Tilt Up Left Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x01\x01\xff
Pan Tilt Up Left Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x01\x01\xff
Pan Tilt Up Left Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x01\x01\xff
Pan Tilt Up Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x03\x01\xff
Pan Tilt Up Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x03\x01\xff
Pan Tilt Up Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x03\x01\xff
Pan Tilt Up Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x03\x01\xff
Pan Tilt Up Right Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x02\x01\xff
Pan Tilt Up Right Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x02\x01\xff
Pan Tilt Up Right Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x02\x01\xff

Global Scripter Module Communication Sheet

Pan Tilt Up Right Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x02\x01\xFF
Power Off	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x00\x03\xFF
Power On	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x00\x02\xFF
Preset Recall 0	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x04?\x02\x00\xFF
Preset Recall 255	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x04?\x02\xFF\xFF
Preset Save 0	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x04?\x01\x00\xFF
Preset Save 255	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x04?\x01\xFF\xFF
Shutter Speed Down	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0A\x03\xFF
Shutter Speed Reset	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0A\x00\xFF
Shutter Speed Up	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x0A\x02\xFF
SmartShoot Off	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x04?\x01^\xFF
SmartShoot On	\x01\x00\x00\x07\x00\x00\x00\x01\x81\x01\x04?\x01]\xFF
System Menu Enter	\x01\x00\x00\x08\x00\x00\x00\x01\x81\x01~\x01\x02\x00\x01\xFF
System Menu Off	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x06\x06\x03\xFF
System Menu On	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x06\x06\x02\xFF
White Balance Auto	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x00\xFF
White Balance Indoor	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x01\xFF
White Balance Manual	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x05\xFF
White Balance One Push	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x03\xFF
White Balance Outdoor	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x045\x02\xFF
Zoom Stop Speed 0	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x07\x00\xFF
Zoom Stop Speed 7	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x07\x00\xFF
Zoom Tele Speed 0	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x07 \xFF
Zoom Tele Speed 7	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x07'\xFF
Zoom Wide Speed 0	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x070\xFF
Zoom Wide Speed 7	\x01\x00\x00\x06\x00\x00\x00\x01\x81\x01\x04\x077\xFF