

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Scaler
Manufacturer: Extron
Firmware Version: 2.36.0003
Model(s): IN1608 xi, IN1608 xi SA, IN1608 xi MA 70, IN1608 xi IPCP SA, IN1608 xi IPCP MA 70

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
2.08.0002-b001	1.4.2

Version History

Module Version	Date	Notes
1_1_3_0	9/4/2018	Added Phantom Power command and fixed error messages.
1_1_1_0	4/23/2018	Updated module version to match driver version.
1_1_0_0	3/28/2018	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- If login credentials are required, devicePassword must be set accordingly.
Example: `InterfaceName.devicePassword = 'extron'`
- InputSignalType command will not display status if the input selected does not have an active signal
- Audio breakaway is not allowed to an input configured for any digital audio format.
- Video breakaway is not allowed from an input configured for any digital audio format.

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='IN1608 xi')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='IN1608 xi')</code>
EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 23, Model='IN1608 xi')</code>

Set Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	Value	
AmplifiedOutputMic ¹	'Include Mic'	'Exclude Mic'	
# AmplifiedOutputMic example InterfaceName.Set('AmplifiedOutputMic', 'Include Mic')			
Command	Value	Value	Value
AmplifiedOutputProgram ¹	'Stereo' ⁵	'L+R (Mono)'	'No Program'
# AmplifiedOutputProgram example InterfaceName.Set('AmplifiedOutputProgram', 'Stereo')			
Command	Value	Value	Value
AnalogOutput1Program	'Left'	'L+R (Mono)'	'No Program'
# AnalogOutput1Program example InterfaceName.Set('AnalogOutput1Program', 'Left')			
Command	Value	Value	Value
AnalogOutput2Program	'Right'	'L+R (Mono)'	'No Program'
# AnalogOutput2Program example InterfaceName.Set('AnalogOutput2Program', 'Right')			
Command	Value	Value	
AnalogOutputMic	'Include Mic'	'Exclude Mic'	
Qualifier Key	Qualifier Value		
'Output'	'1' – '2'		
# AnalogOutputMic example InterfaceName.Set('AnalogOutputMic', 'Include Mic', {'Output': '1'})			
Command	Value	Value	
AspectRatio	'Fill'	'Follow'	
Qualifier Key	Qualifier Value		
'Input'	'1' – '8'		
# AspectRatio example InterfaceName.Set('AspectRatio', 'Fill', {'Input': '1'})			
Command	Value	Value	Value
AudioFormat ²	'Analog'	'LPCM-2Ch'	'Multi-Ch'
	'LPCM-2Ch Auto'	'Multi-Ch Auto'	None
Qualifier Key	Qualifier Value		
'Input'	'1' – '8'		

Global Scriptor Module Communication Sheet

# AudioFormat example InterfaceName.Set('AudioFormat', 'Analog', {'Input': '1'})			
Command AudioMute	Value 'On'	Value 'Off'	
Qualifier Key 'Output'	Qualifier Value 'Output 1' 'Right Variable Output' 'Amplified Output' ⁶	Qualifier Value 'Output 2' 'Left Digital Output' 'Left Amplified Output' ⁵	Qualifier Value 'Left Variable Output' 'Right Digital Output' 'Right Amplified Output' ⁵
# AudioMute example InterfaceName.Set('AudioMute', 'On', {'Output': 'Output 1'})			
Command AutoImage	Value 'Execute'	Value 'Execute and Fill'	Value 'Execute and Follow'
# AutoImage example InterfaceName.Set('AutoImage', 'Execute')			
Command AutoSwitchMode	Value 'Off'	Value 'Highest Active Input'	Value 'Lowest Active Input'
# AutoSwitchMode example InterfaceName.Set('AutoSwitchMode', 'Off')			
Command Bass	Value -24 to 12 in steps of 0.1 dB		
# Bass example InterfaceName.Set('Bass', 12)			
Command DigitalOutputMic	Value 'Include Mic'	Value 'Exclude Mic'	
# DigitalOutputMic example InterfaceName.Set('DigitalOutputMic', 'Include Mic')			
Command DigitalOutputProgram	Value 'Stereo'	Value 'Dual Mono'	Value 'No Program'
# DigitalOutputProgram example InterfaceName.Set('DigitalOutputProgram', 'Stereo')			
Command Ducking	Value 'Enable'	Value 'Disable'	
Qualifier Key 'Mic'	Qualifier Value '1' – '2'		
# Ducking example InterfaceName.Set('Ducking', 'Enable', {'Mic': '1'})			
Command ExecutiveMode ³	Value 'Off'	Value 'Mode 1'	Value 'Mode 2'
# ExecutiveMode example InterfaceName.Set('ExecutiveMode', 'Off')			
Command Freeze	Value 'On'	Value 'Off'	

Global Scripter Module Communication Sheet

# Freeze example InterfaceName.Set('Freeze', 'On')			
Command GlobalVideoMute	Value 'On'	Value 'On with Sync'	Value 'Off'
# GlobalVideoMute example InterfaceName.Set('GlobalVideoMute', 'On')			
Command GroupMicMute	Value 'On'	Value 'Off'	
# GroupMicMute example InterfaceName.Set('GroupMicMute', 'On')			
Command GroupMicVolume	Value -100 to 0 in steps of 0.1		
# GroupMicVolume example InterfaceName.Set('GroupMicVolume', 0)			
Command GroupOutputMute	Value 'On'	Value 'Off'	
# GroupOutputMute example InterfaceName.Set('GroupOutputMute', 'On')			
Command GroupOutputVolume	Value -100 to 0 in steps of 0.1 dB		
# GroupOutputVolume example InterfaceName.Set('GroupOutputVolume', 0)			
Command GroupProgramMute	Value 'On'	Value 'Off'	
# GroupProgramMute example InterfaceName.Set('GroupProgramMute', 'On')			
Command GroupProgramVolume	Value -100 to 0 in steps of 0.1 dB		
# GroupProgramVolume example InterfaceName.Set('GroupProgramVolume', 0)			
Command HDCPInputAuthorization	Value 'On'	Value 'Off'	
Qualifier Key 'Input'	Qualifier Value '3' – '8'		
# HDCPInputAuthorization example InterfaceName.Set('HDCPInputAuthorization', 'On', {'Input': '3'})			
Command Input ⁴	Value '1' – '8'		
Qualifier Key 'Type'	Qualifier Value 'Audio'	Qualifier Value 'Video'	Qualifier Value 'Audio/Video'
# Input example InterfaceName.Set('Input', '1', {'Type': 'Audio'})			

Global Scriptor Module Communication Sheet

Revision: 9/4/2018

Command InputGain	Value -18 to 24 in steps of 0.1		
Qualifier Key 'Type'	Qualifier Value 'Analog'	Qualifier Value 'Digital'	
Qualifier Key 'Channel'	Qualifier Value 'Left'	Qualifier Value 'Right'	
Qualifier Key 'Input'	Qualifier Value '1' – '8'		
# InputGain example InterfaceName.Set('InputGain', 24, {'Type': 'Analog', 'Channel': 'Left', 'Input': '1'})			
Command InputPresetRecall	Value '1' – '128'		
# InputPresetRecall example InterfaceName.Set('InputPresetRecall', '1')			
Command InputPresetSave	Value '1' – '128'		
# InputPresetSave example InterfaceName.Set('InputPresetSave', '1')			
Command InputSignalType	Value 'RGB' 'S-Video'	Value 'YUV' 'Composite'	Value 'RGBcvS'
Qualifier Key 'Input'	Qualifier Value '1' – '2'		
# InputSignalType example InterfaceName.Set('InputSignalType', 'RGB', {'Input': '1'})			
Command MicMixLevel	Value -100 to 0 in steps of 0.1 dB		
Qualifier Key 'Mic'	Qualifier Value '1' – '2'		
# MicMixLevel example InterfaceName.Set('MicMixLevel', 0, {'Mic': '1'})			
Command MicMixMute	Value 'On'	Value 'Off'	
Qualifier Key 'Mic'	Qualifier Value '1' – '2'		
# MicMixMute example InterfaceName.Set('MicMixMute', 'On', {'Mic': '1'})			
Command OutputFormat	Value 'Auto' 'HDMI RGB Limited' 'HDMI YUV 422 Full'	Value 'DVI RGB 444' 'HDMI YUV 444 Full' 'HDMI YUV 422 Limited'	Value 'HDMI RGB Full' 'HDMI YUV 444 Limited'

Global Scriptor Module
Communication Sheet

Qualifier Key 'Output'	Qualifier Value 'A'	Qualifier Value 'B'	Qualifier Value 'C'
# OutputFormat example InterfaceName.Set('OutputFormat', 'Auto', {'Output': 'A'})			
Command OutputGain	Value -100 to 0 in steps of 0.1 dB		
Qualifier Key 'Output'	Qualifier Value 'Output 1'	Qualifier Value 'Output 2'	Qualifier Value 'Left Variable Output'
	'Right Variable Output'	'Left Digital Output'	'Right Digital Output'
	'Left Amplified Output' ⁵	'Right Amplified Output' ⁵	'Amplified Output' ⁶
# OutputGain example InterfaceName.Set('OutputGain', 0, {'Output': 'Output 1'})			
Command OutputResolution	Value	Value	Value
	'640x480 (50Hz)'	'800x600 (50Hz)'	'852x480 (50Hz)'
	'1024x768 (50Hz)'	'1024x852 (50Hz)'	'1024x1024 (50Hz)'
	'1280x768 (50Hz)'	'1280x800 (50Hz)'	'1280x1024 (50Hz)'
	'1360x765 (50Hz)'	'1360x768 (50Hz)'	'1365x768 (50Hz)'
	'1366x768 (50Hz)'	'1365x1024 (50Hz)'	'1440x900 (50Hz)'
	'1400x1050 (50Hz)'	'1600x900 (50Hz)'	'1680x1050 (50Hz)'
	'1600x1200 (50Hz)'	'1920x1200 (50Hz)'	'576p (50Hz)'
	'720p (50Hz)'	'1080i (50Hz)'	'1080p (50Hz)'
	'640x480 (60Hz)'	'800x600 (60Hz)'	'852x480 (60Hz)'
	'1024x768 (60Hz)'	'1024x852 (60Hz)'	'1024x1024 (60Hz)'
	'1280x768 (60Hz)'	'1280x800 (60Hz)'	'1280x1024 (60Hz)'
	'1360x765 (60Hz)'	'1360x768 (60Hz)'	'1365x768 (60Hz)'
	'1366x768 (60Hz)'	'1365x1024 (60Hz)'	'1440x900 (60Hz)'
	'1400x1050 (60Hz)'	'1600x900 (60Hz)'	'1680x1050 (60Hz)'
	'1600x1200 (60Hz)'	'1920x1200 (60Hz)'	'480p (60Hz)'
	'720p (60Hz)'	'1080i (60Hz)'	'1080p (60Hz)'
	'2048x1080 (60Hz)'	'640x480 (75Hz)'	'800x600 (75Hz)'
	'852x480 (75Hz)'	'1024x768 (75Hz)'	'1024x852 (75Hz)'
	'1024x1024 (75Hz)'	'1280x768 (75Hz)'	'1280x800 (75Hz)'
	'1280x1024 (75Hz)'	'1360x765 (75Hz)'	'1360x768 (75Hz)'
	'1365x768 (75Hz)'	'1366x768 (75Hz)'	'1365x1024 (75Hz)'
	'1440x900 (75Hz)'	'1080p (23.98Hz)'	'2048x1080 (23.98Hz)'
	'1080p (24Hz)'	'2048x1080 (24Hz)'	'720p (25Hz)'
	'1080p (25Hz)'	'2048x1080 (25Hz)'	'720p (29.97Hz)'

Global Scriptor Module
Communication Sheet

	'1080p (29.97Hz)'	'2048x1080 (29.97Hz)'	'720p (30Hz)'
	'1080p (30Hz)'	'2048x1080 (30Hz)'	'720p (59.94Hz)'
	'1080i (59.94Hz)'	'1080p (59.94Hz)'	'2048x1080 (59.94Hz)'
	'480p (59.94Hz)'	'2048x1080 (50Hz)'	
# OutputResolution example InterfaceName.Set('OutputResolution', '640x480 (50Hz)')			
Command PhantomPower	Value 'On'	Value 'Off'	
Qualifier Key 'Mic'	Qualifier Value '1'	Qualifier Value '2'	
# PhantomPower example InterfaceName.Set('PhantomPower', 'On', {'Mic': '1'})			
Command PowerSaveMode	Value 'On'	Value 'Off'	
# PowerSaveMode example InterfaceName.Set('PowerSaveMode', 'On')			
Command SwitchingEffect	Value 'Cut'	Value 'Fade'	
# SwitchingEffect example InterfaceName.Set('SwitchingEffect', 'Cut')			
Command TestPattern	Value 'Crop'	Value 'Alternating Pixels'	Value 'Color Bars'
	'Grayscale'	'Blue Mode'	'Audio Test Pattern'
	None		
# TestPattern example InterfaceName.Set('TestPattern', 'Crop')			
Command Treble	Value -24 to 12 in steps of 0.1 dB		
# Treble example InterfaceName.Set('Treble', 12)			
Command UserPresetRecall	Value '1' – '16'		
# UserPresetRecall example InterfaceName.Set('UserPresetRecall', '1')			
Command UserPresetSave	Value '1' – '16'		
# UserPresetSave example InterfaceName.Set('UserPresetSave', '1')			
Command VariableAnalogOutputMic	Value 'Include Mic'	Value 'Exclude Mic'	
# VariableAnalogOutputMic example			

Global Scripter Module Communication Sheet

InterfaceName.Set('VariableAnalogOutputMic', 'Include Mic')			
Command VariableAnalogOutputProgram	Value 'Stereo'	Value 'Dual Mono'	Value 'No Program'
# VariableAnalogOutputProgram example InterfaceName.Set('VariableAnalogOutputProgram', 'Stereo')			
Command VideoMute	Value 'On'	Value 'Off'	Value 'On with Sync'
Qualifier Key 'Output'	Qualifier Value 'A'	Qualifier Value 'B'	Qualifier Value 'C'
# VideoMute example InterfaceName.Set('VideoMute', 'On', {'Output': 'A'})			

¹ only available on SA/MA models

² Input Qualifier value '1' and '2' only support 'Analog' or 'Off' states.

³ Mode 1: Lock the entire front panel

Mode 2: Limit front panel control to input switching and volume control only.

⁴ Command will not work unless AutoSwitchMode is set to Off.

⁵ only available on SA models

⁶ only available on MA models

Status Available

For all commands except for InputSignalStatus, Update should be called only once since the command's status will be updated automatically as the device's status changes. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'}, FeedbackHandler)
FeedbackHandler will be called only when the specified qualifier gets a new status.
```

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command	Value	Value	
AspectRatio	'Fill'	'Follow'	
Qualifier Key	Qualifier Value		
'Input'	'1' – '8'		
# AspectRatio examples InterfaceName.Update('AspectRatio', {'Input': '1'}) Value = InterfaceName.ReadStatus('AspectRatio', {'Input': '1'}) InterfaceName.SubscribeStatus('AspectRatio', None, FeedbackHandler)			
Command	Value	Value	Value
AudioFormat ¹	'Analog'	'LPCM-2Ch'	'Multi-Ch'
	'LPCM-2Ch Auto'	'Multi-Ch Auto'	None
Qualifier Key	Qualifier Value		
'Input'	'1' – '8'		
# AudioFormat examples InterfaceName.Update('AudioFormat', {'Input': '1'}) Value = InterfaceName.ReadStatus('AudioFormat', {'Input': '1'}) InterfaceName.SubscribeStatus('AudioFormat', None, FeedbackHandler)			
Command	Value	Value	
AudioMute	'On'	'Off'	
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Output'	'Output 1'	'Output 2'	'Left Variable Output'
	'Right Variable Output'	'Left Digital Output'	'Right Digital Output'
	'Amplified Output' ⁴	'Left Amplified Output' ³	'Right Amplified Output' ³
# AudioMute examples InterfaceName.Update('AudioMute', {'Output': 'Output 1'}) Value = InterfaceName.ReadStatus('AudioMute', {'Output': 'Output 1'}) InterfaceName.SubscribeStatus('AudioMute', None, FeedbackHandler)			

Global Scriptor Module Communication Sheet

Command	Value	Value	Value
AutoSwitchMode	'Off'	'Highest Active Input'	'Lowest Active Input'
# AutoSwitchMode examples InterfaceName.Update('AutoSwitchMode') Value = InterfaceName.ReadStatus('AutoSwitchMode') InterfaceName.SubscribeStatus('AutoSwitchMode', None, FeedbackHandler)			
Command	Value		
Bass	-24 to 12 in steps of 0.1 dB		
# Bass examples InterfaceName.Update('Bass') Value = InterfaceName.ReadStatus('Bass') InterfaceName.SubscribeStatus('Bass', None, FeedbackHandler)			
Command	Value	Value	
ConnectionStatus	'Connected'	'Disconnected'	
# ConnectionStatus examples Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command	Value	Value	
Ducking	'Enable'	'Disable'	
Qualifier Key	Qualifier Value		
'Mic'	'1' – '2'		
# Ducking examples InterfaceName.Update('Ducking', {'Mic': '1'}) Value = InterfaceName.ReadStatus('Ducking', {'Mic': '1'}) InterfaceName.SubscribeStatus('Ducking', None, FeedbackHandler)			
Command	Value	Value	Value
ExecutiveMode	'Off'	'Mode 1'	'Mode 2'
# ExecutiveMode examples InterfaceName.Update('ExecutiveMode') Value = InterfaceName.ReadStatus('ExecutiveMode') InterfaceName.SubscribeStatus('ExecutiveMode', None, FeedbackHandler)			
Command	Value	Value	
Freeze	'On'	'Off'	
# Freeze examples InterfaceName.Update('Freeze') Value = InterfaceName.ReadStatus('Freeze') InterfaceName.SubscribeStatus('Freeze', None, FeedbackHandler)			
Command	Value	Value	Value
GlobalVideoMute	'On'	'On with Sync'	'Off'
# GlobalVideoMute examples InterfaceName.Update('GlobalVideoMute') Value = InterfaceName.ReadStatus('GlobalVideoMute') InterfaceName.SubscribeStatus('GlobalVideoMute', None, FeedbackHandler)			
Command	Value	Value	
GroupMicMute	'On'	'Off'	

<pre># GroupMicMute examples InterfaceName.Update('GroupMicMute') Value = InterfaceName.ReadStatus('GroupMicMute') InterfaceName.SubscribeStatus('GroupMicMute', None, FeedbackHandler)</pre>				
Command GroupMicVolume		Value -100 to 0 in steps of 0.1 dB		
<pre># GroupMicVolume examples InterfaceName.Update('GroupMicVolume') Value = InterfaceName.ReadStatus('GroupMicVolume') InterfaceName.SubscribeStatus('GroupMicVolume', None, FeedbackHandler)</pre>				
Command GroupOutputMute		Value 'On'	Value 'Off'	
<pre># GroupOutputMute examples InterfaceName.Update('GroupOutputMute') Value = InterfaceName.ReadStatus('GroupOutputMute') InterfaceName.SubscribeStatus('GroupOutputMute', None, FeedbackHandler)</pre>				
Command GroupOutputVolume		Value -100 to 0 in steps of 0.1 dB		
<pre># GroupOutputVolume examples InterfaceName.Update('GroupOutputVolume') Value = InterfaceName.ReadStatus('GroupOutputVolume') InterfaceName.SubscribeStatus('GroupOutputVolume', None, FeedbackHandler)</pre>				
Command GroupProgramMute		Value 'On'	Value 'Off'	
<pre># GroupProgramMute examples InterfaceName.Update('GroupProgramMute') Value = InterfaceName.ReadStatus('GroupProgramMute') InterfaceName.SubscribeStatus('GroupProgramMute', None, FeedbackHandler)</pre>				
Command GroupProgramVolume		Value -100 to 0 in steps of 0.1 dB		
<pre># GroupProgramVolume examples InterfaceName.Update('GroupProgramVolume') Value = InterfaceName.ReadStatus('GroupProgramVolume') InterfaceName.SubscribeStatus('GroupProgramVolume', None, FeedbackHandler)</pre>				
Command HDCPInputAuthorization		Value 'On'	Value 'Off'	
Qualifier Key 'Input'		Qualifier Value '3' – '8'		
<pre># HDCPInputAuthorization examples InterfaceName.Update('HDCPInputAuthorization', {'Input': '3'}) Value = InterfaceName.ReadStatus('HDCPInputAuthorization', {'Input': '3'}) InterfaceName.SubscribeStatus('HDCPInputAuthorization', None, FeedbackHandler)</pre>				
Command HDCPInputStatus		Value 'No Source Device Detected'	Value 'Source Detected with HDCP'	Value 'Source Detected without HDCP'

Global Scripter Module Communication Sheet

Revision: 9/4/2018

Qualifier Key 'Input'	Qualifier Value '3' – '8'		
# HDCPInputStatus examples InterfaceName.Update('HDCPInputStatus', {'Input': '3'}) Value = InterfaceName.ReadStatus('HDCPInputStatus', {'Input': '3'}) InterfaceName.SubscribeStatus('HDCPInputStatus', None, FeedbackHandler)			
Command HDCPOutputStatus	Value 'No Sink Device Detected'	Value 'Sink Detected with HDCP'	Value 'Sink Detected without HDCP'
Qualifier Key 'Output'	Qualifier Value 'A'	Qualifier Value 'B'	Qualifier Value 'C'
# HDCPOutputStatus examples InterfaceName.Update('HDCPOutputStatus', {'Output': 'A'}) Value = InterfaceName.ReadStatus('HDCPOutputStatus', {'Output': 'A'}) InterfaceName.SubscribeStatus('HDCPOutputStatus', None, FeedbackHandler)			
Command Input	Value '0' – '8'		
Qualifier Key 'Type'	Qualifier Value 'Audio'	Qualifier Value 'Video'	Qualifier Value 'Audio/Video'
# Input examples InterfaceName.Update('Input', {'Type': 'Audio'}) Value = InterfaceName.ReadStatus('Input', {'Type': 'Audio'}) InterfaceName.SubscribeStatus('Input', None, FeedbackHandler)			
Command InputGain	Value -18 to 24 in steps of 0.1 dB		
Qualifier Key 'Type'	Qualifier Value 'Analog'	Qualifier Value 'Digital'	
Qualifier Key 'Channel'	Qualifier Value 'Left'	Qualifier Value 'Right'	
Qualifier Key 'Input'	Qualifier Value '1' – '8'		
# InputGain examples InterfaceName.Update('InputGain', {'Type': 'Analog', 'Channel': 'Left', 'Input': '1'}) Value = InterfaceName.ReadStatus('InputGain', {'Type': 'Analog', 'Channel': 'Left', 'Input': '1'}) InterfaceName.SubscribeStatus('InputGain', None, FeedbackHandler)			
Command InputSignalStatus ⁵	Value 'Active'	Value 'Not Active'	
Qualifier Key 'Input'	Qualifier Value '1' – '8'		
# InputSignalStatus examples InterfaceName.Update('InputSignalStatus') Value = InterfaceName.ReadStatus('InputSignalStatus', {'Input': '1'}) InterfaceName.SubscribeStatus('InputSignalStatus', None, FeedbackHandler)			
Command	Value	Value	Value

Global Scriptor Module Communication Sheet

InputSignalType	'RGB'	'YUV'	'RGBcvS'
	'S-Video'	'Composite'	
Qualifier Key 'Input'	Qualifier Value '1' – '2'		
# InputSignalType examples InterfaceName.Update('InputSignalType', {'Input': '1'}) Value = InterfaceName.ReadStatus('InputSignalType', {'Input': '1'}) InterfaceName.SubscribeStatus('InputSignalType', None, FeedbackHandler)			
Command MicMixLevel	Value -100 to 0 in steps of 0.1 dB		
Qualifier Key 'Mic'	Qualifier Value '1' – '2'		
# MicMixLevel examples InterfaceName.Update('MicMixLevel', {'Mic': '1'}) Value = InterfaceName.ReadStatus('MicMixLevel', {'Mic': '1'}) InterfaceName.SubscribeStatus('MicMixLevel', None, FeedbackHandler)			
Command MicMixMute	Value 'On'	Value 'Off'	
Qualifier Key 'Mic'	Qualifier Value '1' – '2'		
# MicMixMute examples InterfaceName.Update('MicMixMute', {'Mic': '1'}) Value = InterfaceName.ReadStatus('MicMixMute', {'Mic': '1'}) InterfaceName.SubscribeStatus('MicMixMute', None, FeedbackHandler)			
Command OutputFormat	Value 'Auto'	Value 'DVI RGB 444'	Value 'HDMI RGB Full'
	'HDMI RGB Limited'	'HDMI YUV 444 Full'	'HDMI YUV 444 Limited'
	'HDMI YUV 422 Full'	'HDMI YUV 422 Limited'	
Qualifier Key 'Output'	Qualifier Value 'A'	Qualifier Value 'B'	Qualifier Value 'C'
# OutputFormat examples InterfaceName.Update('OutputFormat', {'Output': 'A'}) Value = InterfaceName.ReadStatus('OutputFormat', {'Output': 'A'}) InterfaceName.SubscribeStatus('OutputFormat', None, FeedbackHandler)			
Command OutputGain	Value -100 to 0 in steps of 0.1 dB		
Qualifier Key 'Output'	Qualifier Value 'Output 1'	Qualifier Value 'Output 2'	Qualifier Value 'Left Variable Output'
	'Right Variable Output'	'Left Digital Output'	'Right Digital Output'
	'Left Amplified Output' ³	'Right Amplified Output' ³	'Amplified Output' ⁴
# OutputGain examples InterfaceName.Update('OutputGain', {'Output': 'Output 1'}) Value = InterfaceName.ReadStatus('OutputGain', {'Output': 'Output 1'})			

Global Scriptor Module Communication Sheet

InterfaceName.SubscribeStatus('OutputGain', None, FeedbackHandler)			
Command	Value	Value	Value
OutputResolution	'640x480 (50Hz)'	'800x600 (50Hz)'	'852x480 (50Hz)'
	'1024x768 (50Hz)'	'1024x852 (50Hz)'	'1024x1024 (50Hz)'
	'1280x768 (50Hz)'	'1280x800 (50Hz)'	'1280x1024 (50Hz)'
	'1360x765 (50Hz)'	'1360x768 (50Hz)'	'1365x768 (50Hz)'
	'1366x768 (50Hz)'	'1365x1024 (50Hz)'	'1440x900 (50Hz)'
	'1400x1050 (50Hz)'	'1600x900 (50Hz)'	'1680x1050 (50Hz)'
	'1600x1200 (50Hz)'	'1920x1200 (50Hz)'	'576p (50Hz)'
	'720p (50Hz)'	'1080i (50Hz)'	'1080p (50Hz)'
	'640x480 (60Hz)'	'800x600 (60Hz)'	'852x480 (60Hz)'
	'1024x768 (60Hz)'	'1024x852 (60Hz)'	'1024x1024 (60Hz)'
	'1280x768 (60Hz)'	'1280x800 (60Hz)'	'1280x1024 (60Hz)'
	'1360x765 (60Hz)'	'1360x768 (60Hz)'	'1365x768 (60Hz)'
	'1366x768 (60Hz)'	'1365x1024 (60Hz)'	'1440x900 (60Hz)'
	'1400x1050 (60Hz)'	'1600x900 (60Hz)'	'1680x1050 (60Hz)'
	'1600x1200 (60Hz)'	'1920x1200 (60Hz)'	'480p (60Hz)'
	'720p (60Hz)'	'1080i (60Hz)'	'1080p (60Hz)'
	'2048x1080 (60Hz)'	'640x480 (75Hz)'	'800x600 (75Hz)'
	'852x480 (75Hz)'	'1024x768 (75Hz)'	'1024x852 (75Hz)'
	'1024x1024 (75Hz)'	'1280x768 (75Hz)'	'1280x800 (75Hz)'
	'1280x1024 (75Hz)'	'1360x765 (75Hz)'	'1360x768 (75Hz)'
	'1365x768 (75Hz)'	'1366x768 (75Hz)'	'1365x1024 (75Hz)'
	'1440x900 (75Hz)'	'1080p (23.98Hz)'	'2048x1080 (23.98Hz)'
	'1080p (24Hz)'	'2048x1080 (24Hz)'	'720p (25Hz)'
	'1080p (25Hz)'	'2048x1080 (25Hz)'	'720p (29.97Hz)'
	'1080p (29.97Hz)'	'2048x1080 (29.97Hz)'	'720p (30Hz)'
	'1080p (30Hz)'	'2048x1080 (30Hz)'	'720p (59.94Hz)'
	'1080i (59.94Hz)'	'1080p (59.94Hz)'	'2048x1080 (59.94Hz)'
	'480p (59.94Hz)'	'2048x1080 (50Hz)'	
# OutputResolution examples InterfaceName.Update('OutputResolution') Value = InterfaceName.ReadStatus('OutputResolution') InterfaceName.SubscribeStatus('OutputResolution', None, FeedbackHandler)			
Command	Value	Value	
PhantomPower	'On'	'Off'	
Qualifier Key	Qualifier Value	Qualifier Value	

Global Scripter Module Communication Sheet

'Mic'	'1'	'2'	
<pre># PhantomPower examples InterfaceName.Update('PhantomPower', {'Mic': '1'}) Value = InterfaceName.ReadStatus('PhantomPower', {'Mic': '1'}) InterfaceName.SubscribeStatus('PhantomPower', None, FeedbackHandler)</pre>			
Command PowerSaveMode	Value 'On'	Value 'Off'	
<pre># PowerSaveMode examples InterfaceName.Update('PowerSaveMode') Value = InterfaceName.ReadStatus('PowerSaveMode') InterfaceName.SubscribeStatus('PowerSaveMode', None, FeedbackHandler)</pre>			
Command ScreenSaverStatus	Value 'Active Input Detected; Timer not running'	Value 'No Active Input; Timer expired; Output sync disabled'	Value 'No Active Input; Timer running; Output sync enabled'
<pre># ScreenSaverStatus examples InterfaceName.Update('ScreenSaverStatus') Value = InterfaceName.ReadStatus('ScreenSaverStatus') InterfaceName.SubscribeStatus('ScreenSaverStatus', None, FeedbackHandler)</pre>			
Command SwitchingEffect	Value 'Cut'	Value 'Fade'	
<pre># SwitchingEffect examples InterfaceName.Update('SwitchingEffect') Value = InterfaceName.ReadStatus('SwitchingEffect') InterfaceName.SubscribeStatus('SwitchingEffect', None, FeedbackHandler)</pre>			
Command Temperature	Value Degrees in Celsius		
<pre># Temperature examples InterfaceName.Update('Temperature') Value = InterfaceName.ReadStatus('Temperature') InterfaceName.SubscribeStatus('Temperature', None, FeedbackHandler)</pre>			
Command TestPattern	Value 'Crop' 'Grayscale' None	Value 'Alternating Pixels' 'Blue Mode'	Value 'Color Bars' 'Audio Test Pattern'
<pre># TestPattern examples InterfaceName.Update('TestPattern') Value = InterfaceName.ReadStatus('TestPattern') InterfaceName.SubscribeStatus('TestPattern', None, FeedbackHandler)</pre>			
Command Treble	Value -24 to 12 in steps of 0.1 dB		
<pre># Treble examples InterfaceName.Update('Treble') Value = InterfaceName.ReadStatus('Treble') InterfaceName.SubscribeStatus('Treble', None, FeedbackHandler)</pre>			

Global Scripter Module Communication Sheet

Command VideoMute	Value 'On'	Value 'Off'	Value 'On with Sync'
Qualifier Key 'Output'	Qualifier Value 'A'	Qualifier Value 'B'	Qualifier Value 'C'
<pre># VideoMute examples InterfaceName.Update('VideoMute', {'Output': 'A'}) Value = InterfaceName.ReadStatus('VideoMute', {'Output': 'A'}) InterfaceName.SubscribeStatus('VideoMute', None, FeedbackHandler)</pre>			

¹ Input Qualifier value '1' and '2' only support 'Analog' or 'Off' states.

² Mode 1: Lock the entire front panel

Mode 2: Limit front panel control to input switching and volume control only.

³ only available on SA models

⁴ only available on MA models

⁵ Qualifier parameters is not required when calling the Update method with this command because the response returns statuses for all qualifier states.

Cable and Adapter Requirements

Captive Screw to Captive Screw RS-232 Serial Cable

Notes for the Device

Serial communication

Port Type: RS-232

Baud Rate: 9600


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Signal
TxD		TxD
RxD		RxD
GND		GND



Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scripter ethernet interface

Port Type:	Ethernet
Default Port:	23
Logon Credentials Supported:	Yes
Multi-Connection Capabilities:	Yes
Port Changeability:	Yes

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication. User Login provides limited functionality.

Notes for the Device

Appendix A. Set Commands

Amplified Output Mic Exclude Mic	\x1Bm20808*1au\x0D\x1Bm20809*1au\x0D\x1Bm20908*1au\x0D\x1Bm20909*1au\x0D
Amplified Output Mic Include Mic	\x1Bm20808*0au\x0D\x1Bm20809*0au\x0D\x1Bm20908*0au\x0D\x1Bm20909*0au\x0D
Amplified Output Program Stereo	\x1Bn50008*0au\x0D\x1Bn50009*0au\x0D\x1Bm50008*0au\x0D\x1Bm50009*0au\x0D
Amplified Output Program L+R (Mono)	\x1Bn50008*1au\x0D\x1Bn50009*1au\x0D\x1Bm50008*0au\x0D\x1Bm50009*0au\x0D
Amplified Output Program No Program	\x1Bm50008*1au\x0D\x1Bm50009*1au\x0D
Analog Output 1 Program L+R (Mono)	\x1Bn50000*1au\x0D\x1Bm50000*0au\x0D\x1Bm50001*0au\x0D
Analog Output 1 Program Left	\x1Bn50000*0au\x0D\x1Bm50000*0au\x0D\x1Bm50001*0au\x0D
Analog Output 1 Program No Program	\x1Bm50000*1au\x0D\x1Bm50001*1au\x0D
Analog Output 2 Program L+R (Mono)	\x1Bn50002*1au\x0D\x1Bm50002*0au\x0D\x1Bm50003*0au\x0D
Analog Output 2 Program No Program	\x1Bm50002*1au\x0D\x1Bm50003*1au\x0D
Analog Output 2 Program Right	\x1Bn50002*0au\x0D\x1Bm50002*0au\x0D\x1Bm50003*0au\x0D
Analog Output Mic Exclude Mic Output 1	\x1Bm20800*1au\x0D\x1Bm20900*1au\x0D
Analog Output Mic Include Mic Output 1	\x1Bm20800*0au\x0D\x1Bm20900*0au\x0D
Analog Output Mic Exclude Mic Output 2	\x1Bm20802*1au\x0D\x1Bm20902*1au\x0D
Analog Output Mic Include Mic Output 2	\x1Bm20802*0au\x0D\x1Bm20902*0au\x0D
Aspect Ratio Fill Input 1	w1*1ASPR\x0D
Aspect Ratio Follow Input 1	w1*2ASPR\x0D
Aspect Ratio Fill Input 8	w8*1ASPR\x0D
Aspect Ratio Follow Input 8	w8*2ASPR\x0D
Audio Format Analog Input 1	wI1*1AFMT\x0D
Audio Format None Input 1	wI1*0AFMT\x0D
Audio Mute Off Output Left Digital Output	wM60006*0AU\x0D
Audio Mute On Output Left Digital Output	wM60006*1AU\x0D
Audio Mute Off Output Left Variable Output	wM60004*0AU\x0D
Audio Mute On Output Left Variable Output	wM60004*1AU\x0D
Audio Mute Off Output Output 1	wM60000*0AU\x0D
Audio Mute On Output Output 1	wM60000*1AU\x0D
Audio Mute Off Output Output 2	wM60002*0AU\x0D
Audio Mute On Output Output 2	wM60002*1AU\x0D
Audio Mute Off Output Right Digital Output	wM60007*0AU\x0D
Audio Mute On Output Right Digital Output	wM60007*1AU\x0D
Audio Mute Off Output Right Variable Output	wM60005*0AU\x0D

Global Scriptor Module Communication Sheet

Audio Mute On Output Right Variable Output	wM60005*1AU\x0D
Audio Mute Off Output Amplified Output	wM60008*0AU\x0D
Audio Mute On Output Amplified Output	wM60008*1AU\x0D
Audio Mute Off Output Left Amplified Output	wM60008*0AU\x0D
Audio Mute On Output Left Amplified Output	wM60009*1AU\x0D
Audio Mute Off Output Right Amplified Output	wM60009*0AU\x0D
Audio Mute On Output Right Amplified Output	wM60009*1AU\x0D
Auto Image Execute	0*A
Auto Image Execute and Fill	1*A
Auto Image Execute and Follow	2*A
Auto Switch Mode Highest Active Input	w1AUSW\x0D
Auto Switch Mode Lowest Active Input	w2AUSW\x0D
Auto Switch Mode Off	w0AUSW\x0D
Bass -24	wD5*-240GRPM\x0D
Bass 12	wD5*+120GRPM\x0D
Digital Output Mic Exclude Mic	\x1Bm20806*1au\x0D\x1Bm20807*1au\x0D\x1Bm20906*1au\x0D\x1Bm20907*1au\x0D
Digital Output Mic Include Mic	\x1Bm20806*0au\x0D\x1Bm20807*0au\x0D\x1Bm20906*0au\x0D\x1Bm20907*0au\x0D
Digital Output Program Dual Mono	\x1Bn50006*1au\x0D\x1Bn50007*1au\x0D\x1Bm50006*0au\x0D\x1Bm50007*0au\x0D
Digital Output Program No Program	\x1Bm50006*1au\x0D\x1Bm50007*1au\x0D
Digital Output Program Stereo	\x1Bn50006*0au\x0D\x1Bn50007*0au\x0D\x1Bm50006*0au\x0D\x1Bm50007*0au\x0D
Ducking Disable Mic 1	we44800*0au\x0D
Ducking Enable Mic 1	we44800*1au\x0D
Ducking Disable Mic 2	we44801*0au\x0D
Ducking Enable Mic 2	we44801*1au\x0D
Executive Mode Mode 1	1X
Executive Mode Mode 2	2X
Executive Mode Off	0X
Freeze Off	0F
Freeze On	1F
Global Video Mute Off	0B
Global Video Mute On	1B
Global Video Mute On with Sync	2B
Group Mic Mute Off	wD4*0GRPM\x0D
Group Mic Mute On	wD4*1GRPM\x0D
Group Mic Volume -100	wD3*-01000GRPM\x0D
Group Mic Volume 0	wD3*+00000GRPM\x0D

Global Scriptor Module Communication Sheet

Group Output Mute Off	WD7*0GRPM\x0D
Group Output Mute On	WD7*1GRPM\x0D
Group Output Volume -100	WD8*-01000GRPM\x0D
Group Output Volume 0	WD8*+00000GRPM\x0D
Group Program Mute Off	WD2*0GRPM\x0D
Group Program Mute On	WD2*1GRPM\x0D
Group Program Volume -100	WD1*-01000GRPM\x0D
Group Program Volume 0	WD1*+00000GRPM\x0D
HDCP Input Authorization Off Input 3	WE3*0HDCP\x0D
HDCP Input Authorization On Input 3	WE3*1HDCP\x0D
HDCP Input Authorization Off Input 8	WE8*0HDCP\x0D
HDCP Input Authorization On Input 8	WE8*1HDCP\x0D
Input 1 Type Audio	1\$
Input 8 Type Audio	8\$
Input 1 Type Audio/Video	1!
Input 8 Type Audio/Video	8!
Input 1 Type Video	1&
Input 8 Type Video	8&
Input Gain -18 Type Analog Channel Left Input 1	WG30000*-180AU\x0D
Input Gain 24 Type Analog Channel Left Input 1	WG30000*240AU\x0D
Input Gain -18 Type Analog Channel Left Input 8	WG30014*-180AU\x0D
Input Gain 24 Type Analog Channel Left Input 8	WG30014*240AU\x0D
Input Gain -18 Type Analog Channel Right Input 1	WG30001*-180AU\x0D
Input Gain 24 Type Analog Channel Right Input 1	WG30001*240AU\x0D
Input Gain -18 Type Analog Channel Right Input 8	WG30015*-180AU\x0D
Input Gain 24 Type Analog Channel Right Input 8	WG30015*240AU\x0D
Input Gain -18 Type Digital Channel Left Input 1	WD30100*-180AU\x0D
Input Gain 24 Type Digital Channel Left Input 1	WD30100*240AU\x0D
Input Gain -18 Type Digital Channel Left Input 8	WD30114*-180AU\x0D
Input Gain 24 Type Digital Channel Left Input 8	WD30114*240AU\x0D
Input Gain -18 Type Digital Channel Right Input 1	WD30101*-180AU\x0D
Input Gain 24 Type Digital Channel Right Input 1	WD30101*240AU\x0D
Input Gain -18 Type Digital Channel Right Input 8	WD30115*-180AU\x0D
Input Gain 24 Type Digital Channel Right Input 8	WD30115*240AU\x0D
Input Preset Recall 1	2*1.
Input Preset Recall 128	2*128.
Input Preset Save 1	2*1,
Input Preset Save 128	2*128,
Input Signal Type Composite Input 1	1*5\

Global Scriptor Module Communication Sheet

Input Signal Type RGB Input 1	1*1\
Input Signal Type RGBcvS Input 1	1*3\
Input Signal Type S-Video Input 1	1*4\
Input Signal Type YUV Input 1	1*2\
Input Signal Type Composite Input 2	2*5\
Input Signal Type RGB Input 2	2*1\
Input Signal Type RGBcvS Input 2	2*3\
Input Signal Type S-Video Input 2	2*4\
Input Signal Type YUV Input 2	2*2\
Mic Mix Level -100 Mic 1	wG40100*-1000AU\x0D
Mic Mix Level 0 Mic 1	wG40100*0AU\x0D
Mic Mix Level -100 Mic 2	wG40101*-1000AU\x0D
Mic Mix Level 0 Mic 2	wG40101*0AU\x0D
Mic Mix Mute Off Mic 1	wM40000*0AU\x0D
Mic Mix Mute On Mic 1	wM40000*1AU\x0D
Mic Mix Mute Off Mic 2	wM40001*0AU\x0D
Mic Mix Mute On Mic 2	wM40001*1AU\x0D
Output Format Auto Output A	w1*0VTPO\x0D
Output Format DVI RGB 444 Output A	w1*1VTPO\x0D
Output Format HDMI RGB Full Output A	w1*2VTPO\x0D
Output Format HDMI RGB Limited Output A	w1*3VTPO\x0D
Output Format HDMI YUV 422 Full Output A	w1*6VTPO\x0D
Output Format HDMI YUV 422 Limited Output A	w1*7VTPO\x0D
Output Format HDMI YUV 444 Full Output A	w1*4VTPO\x0D
Output Format HDMI YUV 444 Limited Output A	w1*5VTPO\x0D
Output Format Auto Output B	w2*0VTPO\x0D
Output Format DVI RGB 444 Output B	w2*1VTPO\x0D
Output Format HDMI RGB Full Output B	w2*2VTPO\x0D
Output Format HDMI RGB Limited Output B	w2*3VTPO\x0D
Output Format HDMI YUV 422 Full Output B	w2*6VTPO\x0D
Output Format HDMI YUV 422 Limited Output B	w2*7VTPO\x0D
Output Format HDMI YUV 444 Full Output B	w2*4VTPO\x0D
Output Format HDMI YUV 444 Limited Output B	w2*5VTPO\x0D
Output Format Auto Output C	w3*0VTPO\x0D
Output Format DVI RGB 444 Output C	w3*1VTPO\x0D
Output Format HDMI RGB Full Output C	w3*2VTPO\x0D
Output Format HDMI RGB Limited Output C	w3*3VTPO\x0D
Output Format HDMI YUV 422 Full Output C	w3*6VTPO\x0D
Output Format HDMI YUV 422 Limited Output C	w3*7VTPO\x0D

Global Scriptor Module Communication Sheet

Output Format HDMI YUV 444 Full Output C	w3*4VTPO\x0D
Output Format HDMI YUV 444 Limited Output C	w3*5VTPO\x0D
Output Gain -100 Output Left Digital Output	wG60006*-1000AU\x0D
Output Gain 0 Output Left Digital Output	wG60006*0AU\x0D
Output Gain -100 Output Left Variable Output	wG60004*-1000AU\x0D
Output Gain 0 Output Left Variable Output	wG60004*0AU\x0D
Output Gain -100 Output Output 1	wG60000*-1000AU\x0D
Output Gain 0 Output Output 1	wG60000*0AU\x0D
Output Gain -100 Output Output 2	wG60002*-1000AU\x0D
Output Gain 0 Output Output 2	wG60002*0AU\x0D
Output Gain -100 Output Right Digital Output	wG60007*-1000AU\x0D
Output Gain 0 Output Right Digital Output	wG60007*0AU\x0D
Output Gain -100 Output Right Variable Output	wG60005*-1000AU\x0D
Output Gain 0 Output Right Variable Output	wG60005*0AU\x0D
Output Gain -100 Output Amplified Output	wG60008*-1000AU\x0D
Output Gain 0 Output Amplified Output	wG60008*0AU\x0D
Output Gain -100 Output Left Amplified Output	wG60008*-1000AU\x0D
Output Gain 0 Output Left Amplified Output	wG60008*0AU\x0D
Output Gain -100 Output Right Amplified Output	wG60009*-1000AU\x0D
Output Gain 0 Output Right Amplified Output	wG60009*0AU\x0D
Output Resolution 1024x1024 (50Hz)	w25RATE\x0D
Output Resolution 1024x1024 (60Hz)	w26RATE\x0D
Output Resolution 1024x1024 (75Hz)	w27RATE\x0D
Output Resolution 1024x768 (50Hz)	w19RATE\x0D
Output Resolution 1024x768 (60Hz)	w20RATE\x0D
Output Resolution 1024x768 (75Hz)	w21RATE\x0D
Output Resolution 1024x852 (50Hz)	w22RATE\x0D
Output Resolution 1024x852 (60Hz)	w23RATE\x0D
Output Resolution 1024x852 (75Hz)	w24RATE\x0D
Output Resolution 1080i (50Hz)	w74RATE\x0D
Output Resolution 1080i (59.94Hz)	w75RATE\x0D
Output Resolution 1080i (60Hz)	w76RATE\x0D
Output Resolution 1080p (23.98Hz)	w77RATE\x0D
Output Resolution 1080p (24Hz)	w78RATE\x0D
Output Resolution 1080p (25Hz)	w79RATE\x0D
Output Resolution 1080p (29.97Hz)	w80RATE\x0D
Output Resolution 1080p (30Hz)	w81RATE\x0D
Output Resolution 1080p (50Hz)	w82RATE\x0D
Output Resolution 1080p (59.94Hz)	w83RATE\x0D

Global Scriptor Module Communication Sheet

Output Resolution 1080p (60Hz)	w84RATE\x0D
Output Resolution 1280x1024 (50Hz)	w34RATE\x0D
Output Resolution 1280x1024 (60Hz)	w35RATE\x0D
Output Resolution 1280x1024 (75Hz)	w36RATE\x0D
Output Resolution 1280x768 (50Hz)	w28RATE\x0D
Output Resolution 1280x768 (60Hz)	w29RATE\x0D
Output Resolution 1280x768 (75Hz)	w30RATE\x0D
Output Resolution 1280x800 (50Hz)	w31RATE\x0D
Output Resolution 1280x800 (60Hz)	w32RATE\x0D
Output Resolution 1280x800 (75Hz)	w33RATE\x0D
Output Resolution 1360x765 (50Hz)	w37RATE\x0D
Output Resolution 1360x765 (60Hz)	w38RATE\x0D
Output Resolution 1360x765 (75Hz)	w39RATE\x0D
Output Resolution 1360x768 (50Hz)	w40RATE\x0D
Output Resolution 1360x768 (60Hz)	w41RATE\x0D
Output Resolution 1360x768 (75Hz)	w42RATE\x0D
Output Resolution 1365x1024 (50Hz)	w49RATE\x0D
Output Resolution 1365x1024 (60Hz)	w50RATE\x0D
Output Resolution 1365x1024 (75Hz)	w51RATE\x0D
Output Resolution 1365x768 (50Hz)	w43RATE\x0D
Output Resolution 1365x768 (60Hz)	w44RATE\x0D
Output Resolution 1365x768 (75Hz)	w45RATE\x0D
Output Resolution 1366x768 (50Hz)	w46RATE\x0D
Output Resolution 1366x768 (60Hz)	w47RATE\x0D
Output Resolution 1366x768 (75Hz)	w48RATE\x0D
Output Resolution 1400x1050 (50Hz)	w55RATE\x0D
Output Resolution 1400x1050 (60Hz)	w56RATE\x0D
Output Resolution 1440x900 (50Hz)	w52RATE\x0D
Output Resolution 1440x900 (60Hz)	w53RATE\x0D
Output Resolution 1440x900 (75Hz)	w54RATE\x0D
Output Resolution 1600x1200 (50Hz)	w61RATE\x0D
Output Resolution 1600x1200 (60Hz)	w62RATE\x0D
Output Resolution 1600x900 (50Hz)	w57RATE\x0D
Output Resolution 1600x900 (60Hz)	w58RATE\x0D
Output Resolution 1680x1050 (50Hz)	w59RATE\x0D
Output Resolution 1680x1050 (60Hz)	w60RATE\x0D
Output Resolution 1920x1200 (50Hz)	w63RATE\x0D
Output Resolution 1920x1200 (60Hz)	w64RATE\x0D
Output Resolution 2048x1080 (23.98Hz)	w85RATE\x0D

Global Scriptor Module Communication Sheet

Output Resolution 2048x1080 (24Hz)	w86RATE\x0D
Output Resolution 2048x1080 (25Hz)	w87RATE\x0D
Output Resolution 2048x1080 (29.97Hz)	w88RATE\x0D
Output Resolution 2048x1080 (30Hz)	w89RATE\x0D
Output Resolution 2048x1080 (50Hz)	w90RATE\x0D
Output Resolution 2048x1080 (59.94Hz)	w91RATE\x0D
Output Resolution 2048x1080 (60Hz)	w92RATE\x0D
Output Resolution 480p (59.94Hz)	w65RATE\x0D
Output Resolution 480p (60Hz)	w66RATE\x0D
Output Resolution 576p (50Hz)	w67RATE\x0D
Output Resolution 640x480 (50Hz)	w10RATE\x0D
Output Resolution 640x480 (60Hz)	w11RATE\x0D
Output Resolution 640x480 (75Hz)	w12RATE\x0D
Output Resolution 720p (25Hz)	w68RATE\x0D
Output Resolution 720p (29.97Hz)	w69RATE\x0D
Output Resolution 720p (30Hz)	w70RATE\x0D
Output Resolution 720p (50Hz)	w71RATE\x0D
Output Resolution 720p (59.94Hz)	w72RATE\x0D
Output Resolution 720p (60Hz)	w73RATE\x0D
Output Resolution 800x600 (50Hz)	w13RATE\x0D
Output Resolution 800x600 (60Hz)	w14RATE\x0D
Output Resolution 800x600 (75Hz)	w15RATE\x0D
Output Resolution 852x480 (50Hz)	w16RATE\x0D
Output Resolution 852x480 (60Hz)	w17RATE\x0D
Output Resolution 852x480 (75Hz)	w18RATE\x0D
Phantom Power On Mic 1	wZ40000*1AU\x0D
Phantom Power Off Mic 1	wZ40000*0AU\x0D
Phantom Power On Mic 2	wZ40001*1AU\x0D
Phantom Power Off Mic 2	wZ40001*0AU\x0D
Power Save Mode Off	w0PSAV\x0D
Power Save Mode On	w1PSAV\x0D
Switching Effect Cut	w0SWEF\x0D
Switching Effect Fade	w1SWEF\x0D
Test Pattern Alternating Pixels	w2TEST\x0D
Test Pattern Audio Test Pattern	w6TEST\x0D
Test Pattern Blue Mode	w5TEST\x0D
Test Pattern Color Bars	w3TEST\x0D
Test Pattern Crop	w1TEST\x0D
Test Pattern Grayscale	w4TEST\x0D

Global Scripter Module Communication Sheet

Revision: 9/4/2018

Test Pattern None	w0TEST\x0D
Treble -24	wD6* - 240GRPM\x0D
Treble 12	wD6*+120GRPM\x0D
User Preset Recall 1	1*1.
User Preset Recall 16	1*16.
User Preset Save 1	1*1,
User Preset Save 16	1*16,
Variable Analog Output Mic Exclude Mic	\x1Bm20804*1au\x0D\x1Bm20805*1au\x0D\x1Bm20904*1au\x0D\x1Bm20905*1au\x0D
Variable Analog Output Mic Include Mic	\x1Bm20804*0au\x0D\x1Bm20805*0au\x0D\x1Bm20904*0au\x0D\x1Bm20905*0au\x0D
Variable Analog Output Program Dual Mono	\x1Bn50004*1au\x0D\x1Bn50005*1au\x0D\x1Bm50004*0au\x0D\x1Bm50005*0au\x0D
Variable Analog Output Program No Program	\x1Bm50004*1au\x0D\x1Bm50005*1au\x0D
Variable Analog Output Program Stereo	\x1Bn50004*0au\x0D\x1Bn50005*0au\x0D\x1Bm50004*0au\x0D\x1Bm50005*0au\x0D
Video Mute Off Output A	1*0B
Video Mute On Output A	1*1B
Video Mute On with Sync Output A	1*2B
Video Mute Off Output B	2*0B
Video Mute On Output B	2*1B
Video Mute On with Sync Output B	2*2B
Video Mute Off Output C	3*0B
Video Mute On Output C	3*1B
Video Mute On with Sync Output C	3*2B

Appendix B. Update Commands

Aspect Ratio Input 1	w1ASPR\x0D
Aspect Ratio Input 8	w8ASPR\x0D
Audio Format Input 1	wI1AFMT\x0D
Audio Format Input 8	wI8AFMT\x0D
Audio Mute Output Left Digital Output	wM60006AU\x0D
Audio Mute Output Left Variable Output	wM60004AU\x0D
Audio Mute Output Output 1	wM60000AU\x0D
Audio Mute Output Output 2	wM60002AU\x0D
Audio Mute Output Right Digital Output	wM60007AU\x0D
Audio Mute Output Right Variable Output	wM60005AU\x0D
Audio Mute Output Amplified Output	wM60008AU\x0D
Audio Mute Output Left Amplified Output	wM60008AU\x0D
Audio Mute Output Right Amplified Output	wM60009AU\x0D
Auto Switch Mode	wAUSW\x0D
Bass	wD5GRPM\x0D
Ducking Mic 1	we44800au\x0D
Ducking Mic 2	we44801au\x0D
Executive Mode	X
Freeze	F
Global Video Mute	B
Group Mic Mute	wD4GRPM\x0D
Group Mic Volume	wD3GRPM\x0D
Group Output Mute	wD7GRPM\x0D
Group Output Volume	wD8GRPM\x0D
Group Program Mute	wD2GRPM\x0D
Group Program Volume	wD1GRPM\x0D
HDCP Input Authorization Input 3	wE3HDCP\x0D
HDCP Input Authorization Input 8	wE8HDCP\x0D
HDCP Input Status Input 3	wI3HDCP\x0D
HDCP Input Status Input 8	wI8HDCP\x0D
HDCP Output Status Output A	wO1HDCP\x0D
HDCP Output Status Output B	wO2HDCP\x0D
HDCP Output Status Output C	wO3HDCP\x0D
Input Type Audio	\$
Input Type Video	&
Input Gain Type Analog Channel Left Input 1	wG30000AU\x0D
Input Gain Type Analog Channel Left Input 8	wG30014AU\x0D

Global Scriptor Module Communication Sheet

Input Gain Type Analog Channel Right Input 1	wG30001AU\x0D
Input Gain Type Analog Channel Right Input 8	wG30015AU\x0D
Input Gain Type Digital Channel Left Input 1	wD30100AU\x0D
Input Gain Type Digital Channel Left Input 8	wD30114AU\x0D
Input Gain Type Digital Channel Right Input 1	wD30101AU\x0D
Input Gain Type Digital Channel Right Input 8	wD30115AU\x0D
Input Signal Status Input 1	w0LS\x0D
Input Signal Status Input 8	w0LS\x0D
Input Signal Type Input 1	1\
Input Signal Type Input 2	2\
Mic Mix Level Mic 1	wG40100AU\x0D
Mic Mix Level Mic 2	wG40101AU\x0D
Mic Mix Mute Mic 1	wM40000AU\x0D
Mic Mix Mute Mic 2	wM40001AU\x0D
Output Format Output A	w1VTP0\x0D
Output Format Output B	w2VTP0\x0D
Output Format Output C	w3VTP0\x0D
Output Gain Output Left Digital Output	wG60006AU\x0D
Output Gain Output Left Variable Output	wG60004AU\x0D
Output Gain Output Output 1	wG60000AU\x0D
Output Gain Output Output 2	wG60002AU\x0D
Output Gain Output Right Digital Output	wG60007AU\x0D
Output Gain Output Right Variable Output	wG60005AU\x0D
Output Gain Output Amplified Output	wG60008AU\x0D
Output Gain Output Left Amplified Output	wG60008AU\x0D
Output Gain Output Right Amplified Output	wG60009AU\x0D
Output Resolution	wRATE\x0D
Phantom Power Mic 1	wZ400000\x0D
Phantom Power Mic 2	wZ400001\x0D
Power Save Mode	wPSAV\x0D
Screen Saver Status	wSSSAV\x0D
Switching Effect	wSWEF\x0D
Temperature	w20STAT\x0D
Test Pattern	wTEST\x0D
Treble	wD6GRPM\x0D
Video Mute Output A	1*B
Video Mute Output C	3*B