

16.3 Interrupt and exception vectors

The grey rows in [Table 104](#) describe the vectors without specific position.

Table 104. STM32L552xx and STM32L562xx vector table

Position	Priority	Type of priority	Acronym	Description	Address
-	-	-	-	Reserved	0x0000 0000
-	-4	Fixed	Reset	Reset	0x0000 0004
-	-2	Fixed	NMI	Non maskable interrupt. SRAM parity err + FLASH ECC err + HSE CSS	0x0000 0008
-	-3 or -1	Fixed	Secure HardFault	Secure hard fault	0x0000 000C
-	-1	Fixed	Non-secure HardFault	Non-secure hard fault. All classes of fault	0x0000 000C
-	0	Settable	MemManage	Memory management	0x0000 0010
-	1	Settable	BusFault	Pre-fetch fault, memory access fault	0x0000 0014
-	2	Settable	UsageFault	Undefined instruction or illegal state	0x0000 0018
-	3	Settable	SecureFault	Secure fault	0x0000 001C
-	-	-	-	Reserved	0x0000 0020 - 0x0000 0028
-	4	-	SVC	System service call via SWI instruction	0x0000 002C
-	5	-	Debug Monitor	Debug monitor	0x0000 0030
-	-	-	-	Reserved	0x0000 0034
-	6	Settable	PendSV	Pendable request for system service	0x0000 0038
-	7	Settable	SysTick	System tick timer	0x0000 003C
0	8	Settable	WWDG	Window watchdog interrupt	0x0000 0040
1	9	Settable	PDV_PVM	PVD/PVM1/PVM2/PVM3/PVM4 through EXTI lines 16/35/36/37/38 interrupts	0x0000 0044
2	10	Settable	RTC	RTC global interrupts (EXTI line 17)	0x0000 0048
3	11	Settable	RTC_S	RTC secure global interrupts (EXTI line 18)	0x0000 004C
4	12	Settable	TAMP	Tamper global interrupt (EXTI line 19)	0x0000 0050
5	13	Settable	TAMP_S	Tamper secure global interrupt (EXTI line 20)	0x0000 0054
6	14	Settable	FLASH	Flash memory global interrupt	0x0000 0058
7	15	Settable	FLASH_S	Flash memory secure global interrupt	0x0000 005C
8	16	Settable	GTZC	TZIC secure global interrupt	0x0000 0060
9	17	Settable	RCC	RCC global interrupt	0x0000 0064
10	18	Settable	RCC_S	RCC secure global interrupt	0x0000 0068