

Project Report on

Rewinding of Single-Phase Induction Motor

Submitted By,

Md. Rifat Rahman

ID: 2006137

Samia Hossain

ID: 2006138

Sami Hasib Khan

ID: 2006139

Alif Mahmud

ID: 2006140

Asikul Islam Asik

ID: 2006141

Rajin Abdullah

Zeeshan

ID: 2006142

**BANGLADESH UNIVERSITY OF ENGINEERING AND
TECHNOLOGY**



Department of Electrical and Electronic Engineering

EEE 206 (January 2023)

Energy Conversion Laboratory

Final Project Report

Section: C1 Group: 02

Rewinding of a Single-Phase Induction Motor

Course Instructors:

Ashikur Rahman Jowel, Lecturer

Shafin Bin Hamid, Lecturer

Signature of Instructor: _____

Academic Honesty Statement:

IMPORTANT! Please carefully read and sign the Academic Honesty Statement, below. Type the student ID and name, and put your signature. *You will not receive credit for this project experiment unless this statement is signed in the presence of your lab instructor.*

"In signing this statement, We hereby certify that the work on this project is our own and that we have not copied the work of any other students (past or present), and cited all relevant sources while completing this project. We understand that if we fail to honor this agreement, We will each receive a score of ZERO for this project and be subject to failure of this course."

Signature: _____

Full name: Md. Rifat Rahman

Student ID: 2006137

Signature: _____

Full name: Samia Hossain

Student ID: 2006138

Signature: _____

Full name: Sami Hasib Khan

Student ID: 2006139

Signature: _____

Full name: Alif Mahmud

Student ID: 2006140

Signature: _____

Full name: Asikul Islam Asik

Student ID: 2006141

Signature: _____

Full name: Rajin Abdullah Zeeshan

Student ID: 2006142

Forwarding letter

September 12, 2023

Ashikur Rahman Jowel, Shafin Bin Hamid

Department of Electrical and Electronic Engineering

Bangladesh University of Engineering & Technology

Subject: A letter regarding submission of a report on a project entitled “Rewinding of a single-phase Induction Motor” of course no. EEE 206 (Energy Conversion Laboratory).

Dear Teachers,

We are part of Group No. 2 (C1) in the Energy Conversion Laboratory (EEE 206). As part of our academic curriculum in the Energy Conversion Laboratory, we were assigned a project involving the rewinding of a single-phase induction motor. Our project allowed us to closely examine the physical construction of this widely-used induction motor. We are pleased to present the comprehensive project report outlining our work on this endeavor. In our project, we focused on the refurbishment of a single-phase induction motor through rewiring. Single-phase induction motors are widely used in various applications, and this project provided us with a valuable opportunity to delve into the intricacies of their operation and construction. Our primary objective was to transform an aging motor into a fully functional one by replacing its old wiring with new materials, ensuring it operates at its intended specifications. Throughout the project, we encountered various challenges and learned invaluable lessons, which we have documented in our report. We are grateful for the opportunity to work on this project, as it has enriched our understanding of single-phase induction motors and deepened our practical knowledge in the field of electrical engineering. Enclosed with this letter, please find the complete project report, which provides a detailed account of our work, methodologies, results, and any challenges we encountered along the way. We hope that our efforts and findings will be of interest and benefit to you.

Thank you for your time and consideration. We look forward to your feedback and insights on our project.

Sincerely,

Md. Rifat Rahman	2006137
Samia Hossain	2006138
Sami Hasib Khan	2006139
Alif Mahmud	2006140
Asikul Islam Asik	2006141
Rajin Abdullah Zeeshan	2006142

Table of Contents

Academic Honesty Statement	i
Forwarding Letter.....	ii
Table of Contents	iii
1 Abstract	1
2 Introduction	1
2.1 Historical Perspective	1
2.2 Principles of Operation.....	2
2.3 Objectives	2
3 Design Problem	3
3.1 Design Method (PO(a))	3
3.1.1 Construction Of Single-Phase Induction Motor	3
3.1.2 Working Principle of Single-Phase Induction Motor	6
3.2 Problem Formulation (PO(b))	9
4 Implementation	9
4.1 Description	9
4.2 Experiment and Data Collection	11
4.3 Data Analysis	19
5 Design Analysis & Evaluation	20
5.1 Design Consideration (PO(c))	20
5.2 Investigations (PO(d))	20
5.3 Limitations of Tools (PO(e))	22
5.4 Impact Assessment (PO(f))	23
5.5 Sustainability and Environment Impact Evaluation (PO(g))	24
5.6 Ethical Issued (PO(h))	24
6 Reflection on Individual and Team Work (PO(i))	25
7 Communication (PO(j))	25
8 Project Management & Cost (PO(k))	26
9 Future Work (PO(l))	27
10 References	28

1. Abstract

Single-phase induction motors stand as stalwarts in various industrial and domestic applications due to their simplicity, reliability, and cost-effectiveness. However, as these motors age or adapt to evolving operational needs, the requirement for rewinding becomes evident. This report offers an in-depth exploration of the rewinding process for single-phase induction motors—an indispensable component in numerous settings. The report begins by elucidating the fundamental principles governing the operation of these motors, demystifying the roles of key components. A firm grasp of these principles is indispensable for a successful rewinding endeavor. The heart of this report lies in the detailed, step-by-step rewiring process, commencing with motor disassembly and meticulous component identification. Each rewiring scenario is thoughtfully complemented by comprehensive diagrams and precise instructions, ensuring absolute clarity and accuracy in execution. In summary, this report is an indispensable resource for individuals and professionals embarking on the rewiring journey for single-phase induction motors. It provides an exhaustive insight into the rewiring procedure, places a premium on safety, and showcases the potential enhancements that motor rewiring can offer across a spectrum of applications. By following the guidelines presented in this report, readers can confidently undertake the rewiring of single-phase induction motors, tailoring them to meet precise operational requirements, ultimately contributing to elevated motor performance and a prolonged lifespan.

Keywords: Single-phase induction motors, rewiring, principles, components, step-by-step process, safety, enhancements, applications, motor performance, prolonged lifespan.

2. Introduction

The project titled "**Single-Phase Induction Motor Rewiring**" embarks on a journey that extends beyond mere technical exploration. It ventures into the realm of electrical engineering, where an essential component of industrial and domestic electrification, the single-phase induction motor, takes center stage. This motor, a fundamental and enduring invention in the annals of electrical engineering, has powered a myriad of machines and appliances since its inception.

A motor serves as a mechanism that transforms electrical energy into mechanical energy, enabling it to carry out specific functions. Motors can be categorized into two primary types: AC motors and DC motors. An example of an AC motor is the single-phase induction motor, which operates by harnessing a single-phase alternating current (a type of current characterized by its fluctuating direction, polarity, and magnitude). The functioning of a single-phase induction motor is rooted in the principle of electromagnetic induction.

2.1 Historical Perspective

Jacobi achieved a significant breakthrough when he created the inaugural electric motor in May 1834. Four years later, he ingeniously adapted his invention to propel a boat carrying 14 individuals. This pioneering work inspired researchers globally to craft motors closely resembling Jacobi's initial design.

However, it was Nikola Tesla who made a groundbreaking contribution to the field by inventing the first single-phase induction motor in 1887 during his experimental endeavors. Today, the utility of single-phase induction motors extends to a myriad of household appliances, including fans, dishwashers, and washing machines.

2.2 Principles of Operation:

Single-phase induction motors operate on the electromagnetic induction principle, where the interaction of a rotating magnetic field with a stationary conductor induces a current and imparts motion to the rotor. The simplicity of this mechanism, combined with the absence of brushes and commutators, renders these motors robust and reliable.

Within this context, our project embarks on a mission to revitalize aging single-phase induction motors through the meticulous process of rewiring. Beyond preserving their functionality, our goal is to acquire an in-depth understanding of the intricate components that enable their operation. Throughout this endeavor, we will explore the construction of these motors, the intricacies of their slot systems, and the significance of the nameplate specifications.

Our journey will delve into the establishment of equivalent circuit models, the art of measuring circuit parameters, and a comprehensive understanding of motor ratings. Furthermore, we will investigate the practicalities of reconnecting the motor's components post-rewiring.

By the culmination of this project, we aim not only to possess a deeper comprehension of single-phase induction motors but also to acquire the practical expertise necessary to refurbish and optimize these motors for a wide spectrum of applications. Join us as we embark on this enlightening expedition, bridging the chasm between theoretical knowledge and hands-on application, where the history and intricacies of single-phase induction motors converge with contemporary engineering excellence.

2.3 Objectives

- Exploring the inner workings of an older single-phase induction motor through systematic disassembly.
- Gaining insights into the structural design of a single-phase induction motor.
- Examining the slot configuration within a single-phase induction motor.
- Learning about the essential information provided on the nameplate of a single-phase induction motor.
- Conducting the rewinding process for a single-phase induction motor and closely observing its internal components.
- Establishing the equivalent circuit model specific to a single-phase induction motor.
- Mastering the techniques for measuring circuit model parameters in a single-phase induction motor.
- Grasping the key ratings and specifications associated with single-phase induction motors.
- Reconnecting the components post-rewinding and initiating the operation of the single-phase induction motor.

Acquiring data on the speed-torque characteristics unique to the rewound single-phase induction motor.

3. Design Problem

3.1 Design Method (PO(a))

3.1.1 Construction of Single-Phase Induction Motor

In our project, we have used ‘Squirrel Cage Single Phase Induction Motor’. The image of the motor used in our project is attached below:



Figure 1: Single-Phase Induction Motor.




Figure 2: Dismantled View of a single-phase induction motor.

This Squirrel Cage Induction Motor consists of the following parts:

- Stator
- Rotor
- Bearings
- Centrifugal Switch.
- Shaft
- Capacitor

The structure of a single-phase induction motor is described as follows:

A single-phase induction motor closely resembles a 3-phase squirrel cage induction motor in its physical appearance. However, the key distinction lies in the stator, which features a distributed single-phase winding. There is a consistent air gap maintained between the stator and rotor, with no electrical connection between them.

The single-phase induction motor comprises two primary components: the stator, which remains stationary, and the rotor, which rotates.

Stator




Figure 3: Stator.

The stator serves as the immobile part of the motor and comprises three primary segments:

Outer Frame: This component forms the outer structure of the motor, providing support for both the stator core and stator windings.

Stator Core: Constructed from thin laminations, typically 0.3 to 0.5 mm thick, the stator core plays a crucial role in carrying the alternating flux responsible for generating eddy current and hysteresis losses.

Stator Windings: These windings are connected to a single-phase AC power supply, resulting in the creation of a rotating magnetic field.

The stator of a single-phase induction motor is designed with laminated stampings, which serve to reduce eddy current losses along its outer edge. These stampings feature slots to accommodate the stator or main winding. These stampings are crafted from silicon steel to minimize hysteresis losses. When a single-phase AC power supply is applied to the stator winding, it generates a magnetic field that drives the motor to rotate at a speed slightly below the synchronous speed (N_s). The formula for synchronous speed N_s is given by:

$$N_s = \frac{120f}{p}$$

Where:

- f represents the supply voltage frequency.
- P stands for the number of poles in the motor.

The construction of the stator in a single-phase induction motor closely resembles that of a three-phase induction motor, with two notable differences in the winding arrangement.

Firstly, single-phase induction motors typically employ concentric coils for their windings. This allows for easy adjustment of the number of turns per coil, facilitated by the concentric coil design. This results in a nearly sinusoidal distribution of magnetomotive force (mmf).

Except for shaded pole motors, asynchronous motors possess two stator windings: the main winding and the auxiliary winding. These two windings are positioned at right angles (in space quadrature) to each other.

Squirrel Cage Rotor



Figure 4: Rotor.

A squirrel cage rotor is a critical component of an electric motor, responsible for converting electrical energy into mechanical output. This rotor comprises a cylindrical laminated core featuring parallel slots designed to hold conductor bars. These conductor bars, unlike ordinary wires, are thick and robust, typically made of copper. The laminated core construction serves to reduce losses due to eddy currents and hysteresis.

To assemble the rotor, conductor bars are inserted into these slots, one bar per slot, from one end. At both ends of the rotor, there are end rings. These end rings are secured by welding, electrical connections, or even bolts, ensuring electrical continuity within the rotor. Notably, these end rings are short-circuited, a design that, upon assembly, gives the rotor a distinctive appearance resembling a squirrel, hence the name "squirrel cage rotor."

Because the end rings and rotor conductor bars are permanently short-circuited, it is not feasible to introduce external resistance in series with the rotor circuit for starting purposes. This design choice aids in achieving a smooth transition of power between the stator and the rotor. Additionally, the rotor conductor bars are often intentionally skewed, not parallel to the shaft, for specific performance advantages.

Bearings

Bearings support the rotor and allow it to rotate smoothly within the stator. Common types of bearings used in induction motors include ball bearings and sleeve bearings.

Shaft

The shaft connects the rotor to the external load, such as a fan, pump, or conveyor belt. It transfers the mechanical energy produced by the motor to the load.

Capacitor

In some single-phase induction motors, especially those used for applications like fans or pumps, a capacitor is added to the circuit to create a phase difference between the main and auxiliary windings, which aids in starting and running the motor.

Housing or Frame

The motor housing or frame provides structural support and protection for the internal components. It is typically made of cast iron, aluminum, or other suitable materials.

Centrifugal switch

In the capacitor start single-phase induction motor, a centrifugal switch is used which is used to cut off the auxiliary windings from the main winding after reaching a specific speed. It helps to reduce the copper loss due to auxiliary winding during the operation of a single-phase induction motor and increases efficiency.

3.1.2 Working Principle of Single-Phase Induction Motor

Single-phase AC supply is given to the stator winding (main winding). The alternating current flowing through the stator winding produces magnetic flux. This flux is known as the main flux.

Now we assume that the rotor is rotating and it is placed in a magnetic field produced by the stator winding. According to Faraday's law, the current starts flowing in the rotor circuit it is a close path. This current is known as rotor current.

Due to the rotor current, the flux is produced around the rotor winding. This flux is known as rotor flux.

There are two fluxes; the **main flux which is produced by the stator** and the second is the **rotor flux which is produced by the rotor**.

Interaction between the main flux and rotor flux, the torque produced in the rotor and it starts rotating.

The stator field is alternating in nature. The speed of the stator field is the same as synchronous speed. The synchronous speed of the motor depends on the number of poles and supply frequency.

It can be represented by two revolving fields. These fields are equal in magnitude and rotating in the opposite direction.

Let say Φ_m is a maximum field induced in the main winding. So, this field is divided into two equal parts and that is $\Phi_m/2$ and $\Phi_m/2$.

Out of these two fields, one field Φ_f is rotating in an anticlockwise direction and the second field Φ_b is rotating in a clockwise direction. Therefore, the resultant field is zero.

$$\Phi_r = \Phi_f - \Phi_b$$


$$\Phi_r = \frac{\Phi_m}{2} - \frac{\Phi_m}{2}$$

$$\Phi_r = 0$$

Now consider the resultant field at different instants.

When a motor starts, two fields are induced as shown in the above figure. These two fields are the same magnitude and opposite direction. So, resultant flux is zero.

In this condition, the stator field cannot cut by rotor field and resultant torque is zero. So, the rotor cannot rotate but it produces humming.



Now consider after the rotation of 90° , both fields are rotated and pointing in the same direction. Therefore, the resultant flux is a summation of both fields.

$$\Phi_r = \Phi_f + \Phi_b$$

$$\Phi_r = \frac{\Phi_m}{2} + \frac{\Phi_m}{2}$$

$$\Phi_r = 0$$

In this condition, the resultant field is equal to the maximum field induced by the stator. Now, both fields rotate separately and it is alternative in nature.

So, both fields cut by the rotor circuit and EMF induced in the rotor conductor. Due to this EMF, the current starts flowing in the rotor circuit and it induces a rotor flux.

Due to the interaction between stator flux and rotor flux motor continues to rotate. **This theory is known as Double Revolving Theory or double field revolving theory.**

Now, from the above explanation, we can conclude that the single-phase induction motor is not self-starting.

To make this motor self-starting motor, we need stator flux rotating in nature instead of alternating nature. This can be done by various methods.

Single-phase induction motor can be classified according to starting methods.

Why Single-Phase Induction Motor is not a Self-starting motor?

According to the double-field revolving theory, any alternating quantity can be divided into two components, each having half the maximum magnitude of the alternating quantity. These two components rotate in opposite directions to each other. If one component rotates clockwise, the other rotates counterclockwise.

When a single-phase AC supply is applied to the stator winding of a single-phase induction motor, it generates a flux with a magnitude Φ_m . Following the double-field revolving theory, this alternating flux Φ_m is split into two equal-magnitude components, $\Phi_m/2$ each. Both of these components rotate in opposite directions at the synchronous speed N_s .

We can refer to these two components of the alternating flux as the forward component (Φ_f) and the backward component (Φ_b). The instantaneous stator flux at any given moment is the result of adding these two components:

$$\Phi_r = \Phi_m/2 + \Phi_m/2$$

Or, Rotating Flux $\Phi_r = \Phi_f + \Phi_b$


Initially, at startup, the forward and backward components of the alternating flux are exactly opposite in direction and have the same magnitude. Consequently, these components cancel each other out, resulting in a net effective torque of zero on the rotor. Therefore, we can conclude that single-phase induction motors, known as 1- Φ induction motors, are not self-starting motors.

In this project, we undertook the task of rewiring a capacitor-start single-phase induction motor. This motor type is commonly found in various appliances and machinery, making it crucial to understand its wiring and functioning for both maintenance and customization purposes. Before delving into the specifics of our project, it's important to grasp the fundamentals of this motor and the significance of its rewiring process.

Capacitor Start-Induction Motor

This type of motor is an advanced version of the Split phase induction motor. The disadvantage of split-phase induction is low torque production. Because in this motor, the phase difference created is much less.

This disadvantage is compensated in this motor with the help of a capacitor connected in series with auxiliary winding. The circuit diagram of this motor is shown in the below figure.



Capacitor Start Induction Motor

The capacitor used in this motor is a dry-type capacitor. This is designed to be used with alternating current. However, this capacitor is not used for continuous operation.

In this method also, a centrifugal switch is used which disconnects the capacitor and auxiliary winding when the motor runs at 75-80% of synchronous speed.

The current through the auxiliary will lead the supply voltage by some angle. This angle is more than the angle increased in a split-phase induction motor.

So, the starting torque of this motor is very high compared to the split-phase induction motor. The starting torque of this motor is 300% more than the full load torque.

Due to high starting torque, this motor is used in applications where high starting torque is required like a Lath machine, compressor, drilling machines, etc.

3.2 Problem Statement

The problem statement of the project on single-phase induction motor rewinding revolves around addressing various challenges and concerns associated with this maintenance procedure. These challenges encompass:

i. Efficiency and Sustainability: Many single-phase induction motors are in operation, and their rewinding process often neglects energy efficiency and environmental sustainability. This project seeks to improve the rewinding process to enhance motor efficiency, reduce energy consumption, and align with sustainability goals.

ii. Material Handling and Hazardous Substances: Insulation materials within motors may contain hazardous substances. The safe handling and disposal of these materials during rewinding are critical issues. The project aims to find safer alternatives and establish best practices for material management.

iii. Energy Consumption: The rewinding process consumes energy, and the environmental impact depends on the source of this energy. The project seeks to explore energy-efficient methods and sustainable energy sources to minimize the carbon footprint associated with rewinding.

iv. Waste Generation: The process generates waste, including discarded winding materials and components. Effective waste management practices must be developed to minimize environmental pollution.

v. Ethical and Labor Concerns: Labor-intensive rewinding processes raise ethical concerns about labor practices and workplace safety. The project aims to address these concerns by establishing ethical labor standards and safety protocols.

vi. Cost-Benefit Analysis: The economic aspects of motor rewinding are crucial. The project will conduct a comprehensive cost-benefit analysis to determine the financial viability of rewinding compared to motor replacement.

vii. Regulatory Compliance: Compliance with environmental regulations and safety standards is paramount. The project will ensure that all aspects of the rewinding process adhere to legal and ethical guidelines.

In summary, the problem statement of the project on single-phase induction motor rewinding centers on improving efficiency, safety, and environmental responsibility while ensuring economic viability and ethical labor practices throughout the rewinding process.

4. Implementations

4.1 Description

Our motor is a 4-pole single-phase induction motor. There are 24 slots in the stator. As each slot is for one arm of a coil and a coil has two arms,

Total number of coils = Slot / 2 = $24/2 = 12$

Number of Running Coils (Main Winding) = Total coil*(2/3) = $12*(2/3) = 8$

Number of Starting Coils (Auxiliary Winding) = Total coil – Running coil = $12 - 8 = 4$

Number of Running coils per phase per pole = Running coil / Pole = $8 / 4 = 2$

Number of Running coils per phase per pole = Starting coil / Pole = $4 / 4 = 1$

Coil Span = Slot / Pole = 24/ 4 = 6

Phase Difference (The span between the largest Running coil and The largest Starting Coil) = $(90/180) * \text{coil span} = (90/180) * 6 = 3$

Winding Arrangement :

Winding Type	Slot No. for each Coil	Direction of Current
Main (Small)	5-8	+
Main (Large)	4-9	+
Main (Small)	11-14	-
Main (Large)	10-15	-
Main (Small)	17-20	+
Main (Large)	16-21	+
Main (Small)	2-23	-
Main (Large)	3-22	-
Auxiliary	1-6	+
Auxiliary	7-12	-
Auxiliary	13-18	+
Auxiliary	19-24	-

Apparatus & Components

1. A 4-pole single-phase Squirrel Cage induction motor.
2. Copper wire for winding. Special fiber paper and tubes for insulation.
3. Basic tools for opening/disassembling the motor such as screwdrivers, hammers, wrenches, blades, and chisel.
4. Pen, pencil, clip, pins.
5. Spray Lubricants such as varnishing materials.

Nameplate

The image of the nameplate of our Squirrel Cage Single-phase Induction motor is given below:
From the motor's nameplate, we gather the following information:

Type: The type designation used by manufacturers can vary and may denote whether the motor is single-phase, polyphase, multi-speed, or based on construction. However, it's important to note that there are no industry standards for type classification. In our project, we utilized a JY7124-type motor.

Power: This value represents the motor's mechanical output rating, signifying its capacity to




Figure 5: Nameplate of the motor.

deliver the required torque at the rated speed. In our project, the motor has a power rating of 550W, indicating its ability to provide a maximum of 550W of power under rated conditions.

Full load speed: Full-load speed, often expressed in RPM (Revolutions Per Minute), is the operational speed at which the motor delivers its rated full-load torque while producing the rated power output. This speed is also referred to as slip speed or the actual rotor speed. In the case of our Induction Motor, the full-load speed is 1400 RPM.

Voltage: The information regarding "Voltage" on the nameplate specifies the voltage level at which the motor is designed to operate optimally. The nameplate also establishes critical motor parameters like power factor, efficiency, torque, and current, with these values being valid under the rated voltage and frequency conditions. Deviating from the voltage indicated on the nameplate can significantly impact the motor's performance. According to the nameplate data, the motor will provide a voltage of 220V.

Current: Regarding "Current," the value specified on the nameplate is directly tied to the rated power output, in conjunction with the voltage and frequency parameters. It's important to note that the current may diverge from the nameplate's amperage in cases of unbalanced phases or if the line voltage falls below the indicated level. As per the nameplate, the motor will supply a current of 3.1A

Frequency: Usually for motors, the input frequency is 50 or 60 Hz. The input frequency of our motor is also 50 Hz.

Phase: This parameter represents the number of AC power lines that supply the motor. Our motor is a Single-Phase Induction Motor that we see from the nameplate.

Poles: In an induction motor nameplate, the term "pole" refers to the number of magnetic poles in the motor's stator. These poles are essentially regions of alternating magnetic polarity within the stator that generate the rotating magnetic field necessary for the motor's operation. Our induction motor has 4 poles.

Class: The "Class" on an induction motor nameplate refers to a classification system used to indicate the motor's intended application and operating conditions. Design classes are typically represented by letters or alphanumeric codes and provide information about the motor's design features, characteristics, and suitability for specific applications. Each design class represents a set of motor specifications and attributes. Our induction motor belongs to Class E, which typically represents the insulation class of the motor's windings. Class E corresponds to an insulation system that is designed to withstand a maximum temperature rise of 120 degrees Celsius (248 degrees Fahrenheit) at the hottest spot within the motor under normal operating conditions.

4.2 Experiment and Data Collection

Disassembling

Preparation of the Work Surface: Before starting, we ensured that our work surface was spotless. Using a lint-free cloth, we meticulously wiped the work area clean, removing any dust or contaminants. This initial step was vital to create a clean and organized workspace conducive to the task at hand.

Outer Housing Removal: To gain access to the motor's internals, we carefully began by taking off the outer housing or casing. Depending on the motor's design, this process required us to systematically remove bolts, release clips, or use the appropriate tools. Throughout this step, we exercised caution to prevent any inadvertent damage to the motor's components.



Old Windings Disconnection: Once inside the motor, we pinpointed the old windings. With a combination of scissors and pliers, we methodically cut the old windings free. We were careful not to apply excessive force, prioritizing the preservation of the motor's core and other essential elements.

Turns Per Coil: As our primary objective was to rewind the motor, we needed to know the characteristics of the wire used in the motor. That's why after cutting the wires with scissors, we calculated the number of turns per coil, both auxiliary winding & main winding.

Coil Extraction: After successfully severing the old windings, we proceeded to extract the cut coils from the armature or stator. Employing a gentle and controlled approach, we manually pulled out the coils one by one. This required a secure grip to ensure safety and avoid any unintended mishaps.

Old Insulation Removal: With the coils removed, our attention shifted to the stator slots housing the old insulations. To remove these aging insulating materials, we utilized pliers. Carefully gripping the old insulation, we gently extracted them from the slots. Throughout this process, we were vigilant to prevent any harm to the stator slots themselves.

Wire Data

Parameter	Previous	New
Wire Type	Copper	Copper
SWG	24	24
Weight	405gm	420gm
Turns (Main Winding)	1 st coil: 91 2 nd coil: 100	1 st coil: 95 2 nd coil: 100
Turns (Auxiliary Winding)	81	85
Maximum Current	3.5A	3.5A
Diameter	.0201 inch	.0201 inch
Resistance (per 1000 feet)	25.67 ohms	25.67 ohms



Reassembling






Slot Insulation Replacement: We initiated the reassembly process by measuring the width of the slots within the stator. Next, we took sheets of insulation paper and meticulously cut them into strips of the exact same width as the slots. These strips were then gently folded and

manually inserted one by one into the stator slots. This step was crucial to ensure proper insulation within the motor.

Creating New Coils: Armed with the calculated wire gauge, we proceeded to craft new coils. Using precision and expertise, we wound the wire to create coils that matched the motor's specifications. Due to the unavailability of commercial forma, we tried to wound the wire using nails inserted into wood boards as per the measurement of previous windings. That was one of our major tool limitations in the project.



Coil Reinsertion: With the new coils in hand, we carefully reinserted them into the stator, positioning them correctly within the slots. This step required precision to ensure that the coils fit snugly and securely. This operation became quite difficult for us as there were large turns per coil as well as due to the unavailability of the commercial forma. Besides, we lack the coil insertion tools. However, we managed to reinsert the coils properly considering all our limitations. After inserting the coils, we inserted another insulation paper on top of each winding for proper insulation as well as the compactness of the coils.





Extension Separation: To complete the coil setup, we separated the extensions of the coils, ensuring that they were appropriately positioned and spaced for optimal performance. This step is critical for achieving the desired electrical connections. We also inserted insulation papers between the main & auxiliary windings. Furthermore, we bind each coil using threads for compactness.

Soldering Coil Terminals: Ensuring a reliable and proper electrical connection, we proceeded to solder the terminals of the coils. This step involved precision soldering techniques to create strong, durable connections that would withstand the motor's operation.



Power Supply Terminal Setup: We then carefully brought out the power supply terminals, positioning them in the designated locations. This step was crucial for facilitating the motor's electrical connections.

Varnish Application: As a final protective measure, we applied varnish to the motor's internal components. This varnish served to insulate and safeguard the motor's electrical elements against moisture and external factors.

Reassembling the Casing: After connections and varnish application, we finally reassembled the casing with rotors. We used a hammer to reinsert the rotor with the casing to the motor and a screwdriver to connect the casing.

Finishing: As a final touch, we repainted the motor casing with a spray color. We used spray colors to avoid any insertion of colors into the inner structure, coils, etc. For extra caution, we covered various parts of the motor with masking tape.






Figure 6: Induction motor after reassembling.

Testing



Figure 7: Testing of the motor.

i. No load test:

Performing a no-load test on a single-phase induction motor involves several steps to evaluate its core losses and magnetization current without any mechanical load applied. Here's a step-by-step description of how we carry out this test:

Setup:

- First, we securely mount the single-phase induction motor in a suitable test environment.
- Next, we make the necessary electrical connections to measure various parameters.

Voltage Application:

To begin the test, we supply the motor with its rated voltage, which is the voltage specified for normal operation.

Load-Free Operation:

Crucially, we ensure that the motor's shaft remains completely disconnected from any mechanical load or equipment throughout the test. This is essential to assess the motor's behavior under no-load conditions.

Motor Start-Up:

We start the motor and allow it to run until it reaches its stable operating conditions. This involves waiting for the motor to attain a consistent speed and temperature.

Parameter Measurement:

We measure several key parameters during the test:

Voltage (V): We use a voltmeter to measure the voltage across the motor's terminals. This tells us the voltage the motor is operating at during the test.

Current (I): An ammeter is employed to measure the current flowing through the motor's winding. This gives us information about the electrical current consumption of the motor.

Active Power (P): We use a wattmeter to measure the active power consumed by the motor. This helps us quantify the power losses associated with the motor's core.




Figure 8: No-load test.

ii. Locked Rotor Test

Performing a locked rotor test on an induction motor is a crucial procedure to evaluate its behavior under extreme conditions when its rotor is prevented from moving (locked) while being supplied with rated current. This test helps in determining the motor's starting current, and its ability to withstand mechanical blockages. Here's a step-by-step description of how we carry out the locked rotor test:

Preparation:

- We began by setting up the induction motor securely in our controlled testing area, ensuring it was properly mounted.

- All the necessary electrical connections were made in advance for measuring critical parameters during the test.

Rated Current Application:

To simulate real-world conditions, we supplied the motor with its rated current, the current specified for normal operation.

Mechanical Locking:

The next step was to physically lock the rotor of the motor, preventing it from turning. We achieved this by using a suitable locking mechanism, ensuring the rotor remained stationary.

Safety Precautions:

Prioritizing safety, we made certain that all safety measures were in place, knowing that the locked rotor test could generate exceptionally high starting currents and torque, which could potentially stress the motor.

Motor Start-Up:

With the rotor securely locked in place, we initiated the motor startup. As expected, the motor tried to start, but because of the locked rotor, it encountered extremely high starting current and torque conditions.



Figure 9: Locked-rotor test.

Parameter Measurement:

During the test, we carefully measured the following critical parameters:

Current (I_{start}): We used a precise ammeter to measure the starting current, capturing the moment when the motor attempted to start with the rotor locked. This value gave us crucial insights into the motor's ability to handle high starting currents.

iii. Measurement of Main Winding Resistance: For obtaining the equivalent circuit parameter, another crucial data that is required is the value of the main winding resistance. To measure this, we used a multimeter. Using the multimeter and selecting the main winding's output wires, we measured the resistance of the main winding, which is denoted as R_1 in the equivalent circuit model.

4.3 Data Analysis

From the measurement of the stator winding resistance using a multimeter, we got the value of **$R_1 = 21.0 \Omega$**

From the no-load test, we got the following data:

V_{nl}	220V
W_{nl}	160W
I_{nl}	2.6A

$$\text{Mod } (Z_{nl}) = \frac{V_{nl}}{I_{nl}} = \frac{220}{2.6} = 84.6154 \Omega = (R_1 + R_2/4) + j\{X_1 + 0.5(X_2 + X_M)\}$$

$$\cos \theta_{nl} = \frac{W_{nl}}{V_{nl} I_{nl}} = 160 / (220 \times 2.6) = 0.2797$$

$$(R_1 + R_2/4) = (Z_{nl}) \cos \theta_{nl} = 23.6686 \Omega$$

$$X_1 + 0.5(X_2 + X_M) = (Z_{nl}) \sqrt{1 - \cos^2 \theta_{nl}} = 81.2377 \Omega$$

From the locked-load test, we got the following data:

V_{LR}	60V
W_{LR}	125W
I_{LR}	3.1A

$$\text{Mod } (Z_{LR}) = \frac{V_{LR}}{I_{LR}} = \frac{60}{3.1} = 19.3548 \Omega$$

$$\cos \theta_{LR} = \frac{W_{LR}}{V_{LR} I_{LR}} = 0.672$$

$$R_1 + R_2 = \text{Mod } (Z_{LR}) \cos \theta_{LR} = 13.0073 \Omega$$

$$X_1 + X_2 = \text{Mod } (Z_{LR}) \sin \theta_{LR} = 14.3324 \Omega$$

Assuming $X_1 = X_2$, we got, **$X_1 = X_2 = 7.1662 \Omega$**

So, we got, **$X_M = 140.9768 \Omega$** [$X_1 + 0.5(X_2 + X_M) = 81.2377 \Omega$]

Now, we will use the value of $(R_1 + R_2/4)$ from the no-load test. We will not use the data $(R_1 + R_2)$ from the locked-rotor test as there was auxiliary winding being connected. That's why, there might be a little error in the data analysis as the test has to be done by opening the auxiliary winding connection.

We got, $(R_1 + R_2/4) = 23.6686 \Omega$ & $R_1 = 21.0 \Omega$;

By putting the value of R_1 and equating we got, **$R_2 = 10.6744 \Omega$**

From locked-rotor test, we found $V_{LR} = 60V$ and $I_{LR} = 3.1A$

So, Starting Current, $I_{\text{Start}} = (V_{\text{rated}} \times I_{LR}) / V_{LR}$; **$I_{\text{Start}} = 11.367A$**

5. Design Analysis & Evaluation

5.1 Design Consideration(PO(c))

Rewinding single-phase induction motors extends beyond just sustainability; it encompasses broader societal and environmental considerations. This practice is an indispensable facet of professional engineering endeavors in Bangladesh. The significance of this endeavor in ensuring the efficient utilization of electrical energy is underscored in this project report, especially within a nation like Bangladesh, where energy generation and resources are constrained. By rewinding these motors, we can actively contribute to the sustainable management of electricity, thereby reducing both energy wastage and the carbon footprint associated with power generation.

Furthermore, professional engineering work transcends mere technical solutions. It assumes a pivotal role in addressing complex socioeconomic challenges in the specific context of Bangladesh. Single-phase induction motors hold a vital position across numerous industries, spanning from small-scale manufacturing to agriculture, farming, small businesses, and household applications. Their pervasive presence in our daily lives and economic activities underscores their critical importance. The enhancements in motor performance resulting from this effort indirectly contribute to socioeconomic progress.

Additionally, we must take into account the broader environmental implications. The improper winding of single-phase motors results in substantial energy losses during operation, placing considerable strain on power generation facilities. Given the prevalence of single-phase motors in public life, this inefficiency gives rise to heightened carbon emissions, particularly as our power generation predominantly relies on fossil fuels. In a nation susceptible to the impacts of climate change, these initiatives have widespread consequences.

In summary, rewinding single-phase induction motors stands as a vital component of professional engineering work in Bangladesh, with profound implications for long-term sustainability, societal advancement, and environmental conservation. This project report underscores the indispensable role that engineers play in addressing intricate technical challenges within the unique context of Bangladesh.

5.2 Investigations (PO(d))

Winding Diagram:

During the removal of the old coil from the stator, we collected data regarding how the coils were inserted in the stator, the slot gap between each coil, and the number of turns per coil. Using these data, we were able to construct a winding diagram which helped us to reconstruct the motor by having a clear idea about the reinsertion procedure of the motor.

Winding diagram is important for a motor as it describes various information about the motor's internal wire architecture and connection. The winding diagram of our 4-pole single-phase induction motor is given below-




Figure 10: Winding diagram of the 4-pole single-phase induction motor.

Equivalent Circuit:

From the data analysis from various tests of our induction motor, we were able to find out the equivalent circuit parameters of our motor. We get,

$$R_1 = 21.0\Omega; R_2 = 10.6744\Omega; X_1 = X_2 = 7.1662\Omega; X_M = 140.9768\Omega$$

So, the equivalent circuit using :




Figure 11: The equivalent circuit of the single-phase induction motor.

Torque-Speed Characteristic:

Using the single-phase equivalent circuit parameters, we are able to create the torque-speed characteristics of our single-phase induction motor. However, it is to be noted that the following torque-speed characteristic is of main winding only; that means there will be no starting torque as we ignored the auxiliary winding. The torque-speed characteristics of main winding of our single-phase induction motor:




Figure 12: Torque-speed characteristic of main winding of the single-phase induction motor.

5.3 Limitations of Tools (PO(e))

i. Forma Unavailability: The lack of a motor winding form, typically used to ensure precise alignment and proper winding tension during the rewinding process, can pose a significant challenge. Without this forma, achieving consistent and accurate rewinding becomes difficult, potentially impacting the motor's operational efficiency.

ii. Coil Insertion Tool: The absence of a specialized coil insertion tool can slow down and make the rewinding process more laborious. This tool facilitates the neat placement of coils within the stator slots, ensuring adequate insulation and spacing. Its non-availability may result in uneven winding and insulation issues.

iii. Wire Cutter: A wire cutter is indispensable for trimming and preparing copper wires for rewinding. Without an appropriate wire cutter, achieving uniform and precise wire lengths becomes challenging, potentially causing variations in coil sizes and affecting electrical performance.

iv. Rotor Bar Removal (Hammer): Using a hammer to remove rotor bars can be imprecise and pose safety risks. It may inadvertently damage the rotor or stator core and may not be suitable for more delicate motor rewinding tasks.

v. Connecting Tools (Soldering Iron): Soldering irons are typically employed for establishing electrical connections within the motor. The unavailability of a soldering iron can limit the ability to create secure and dependable connections, potentially resulting in electrical issues in the rewound motor.

vi. Balancing Equipment: Properly balancing the rotor is vital for ensuring the motor operates smoothly. The absence of access to balancing equipment can lead to motor vibrations and reduced efficiency following rewinding.

vii. Testing Instruments: Testing instruments such as insulation testers and ohmmeters are essential for confirming the quality and safety of the rewound motor. The lack of these instruments can introduce uncertainty regarding the motor's performance and reliability.

To address these limitations, it may be necessary to explore alternative methods and improvisations that can be employed using the available tools and resources. Additionally,

collaboration with local workshops or institutions may facilitate access to some of the missing tools or equipment, ultimately enhancing the effectiveness of the motor rewinding process.

5.4 Impact Assessment (PO(f))

The rewinding of single-phase induction motors entails various consequences, encompassing both positive and negative aspects, necessitating a comprehensive evaluation for informed decision-making.

Positive Impacts:

One of the notable benefits is resource conservation. The process of rewinding prolongs the operational life of these motors, thereby diminishing the necessity for the production of new motors and the associated consumption of raw materials. Moreover, the rewinding procedure can result in energy savings. Well-executed rewinding endeavors enhance the operational efficiency of motors, culminating in reduced energy consumption over their lifespans. This energy conservation not only provides economic advantages but also has favorable environmental implications by diminishing the demand for energy generation. Financially, the act of rewinding is often more economical than procuring new motors, translating into tangible economic benefits for individuals and businesses alike. Additionally, it mitigates the issue of electronic waste. By refurbishing and repurposing motors, the practice of rewinding contributes to a reduction in the disposal of electronic waste. This reduction is particularly significant as electronic waste poses hazardous environmental consequences and resource depletion concerns.

Negative Impacts:

Conversely, the rewinding of single-phase induction motors is not devoid of environmental and ethical concerns. One critical issue pertains to the materials involved, specifically the insulation materials within motors. These materials often contain hazardous substances, which, if mishandled or improperly disposed of, can pose health and environmental risks. Furthermore, the rewinding process incurs energy consumption. It necessitates energy for tasks such as motor disassembly, rewiring, and rigorous testing. The source of this energy is pivotal; if it derives from non-renewable or environmentally detrimental sources, it may lead to increased carbon emissions, thereby counteracting the potential energy efficiency gains from motor rewinding. Another noteworthy consideration is waste generation. The rewinding process generates waste in the form of discarded winding materials and components. The improper disposal of these materials can exacerbate waste-related environmental problems, potentially leading to pollution. Moreover, the rewinding process can be labor-intensive, raising ethical concerns regarding workplace safety and labor practices. Ensuring safe and ethical labor practices throughout the rewinding process is imperative to mitigate these concerns.

Assessment Considerations:

In the evaluation of motor rewinding, several key factors warrant consideration, first and foremost is the assessment of potential efficiency gains. Determining whether the rewound motor will operate more energy-efficiently than its original state is essential. This assessment should account for energy consumption and potential reductions in emissions. The selection of materials used in rewinding is pivotal. The environmental impact of insulation materials should be scrutinized, with a preference for eco-friendly alternatives whenever feasible. The energy source powering the rewinding process should be carefully considered. Utilizing renewable or low-impact energy sources can mitigate carbon emissions associated with the rewinding procedure. Efficient waste management is fundamental. Establishing protocols for proper disposal and recycling of old winding materials and components is crucial to minimize waste generation and potential pollution. A cost-benefit analysis is advisable to weigh the financial savings accrued through rewinding against the potential environmental and safety concerns.

Compliance with environmental regulations and safety standards is a non-negotiable aspect, ensuring that the rewinding process adheres to legal and ethical guidelines. In conclusion, a thorough impact assessment of motor rewinding should strike a balance between the economic advantages and potential environmental and ethical implications, ultimately aiming for a sustainable and responsible approach.

5.5 Sustainability and Environment Impact Evaluation (PO(g))

The rewinding process of a single-phase induction motor can have both positive and negative environmental impacts, depending on various factors:

i. Positive Impact:

Rewinding can extend the motor's lifespan, reducing the need for manufacturing new motors and conserving resources. By refurbishing and reusing motors, it decreases the disposal of old motors as electronic waste, which can be hazardous to the environment.

ii. Negative Impact:

The insulation materials used in motors often contain hazardous chemicals. During rewinding, these materials may be exposed or damaged, potentially releasing harmful substances into the environment. The rewinding process requires energy for dismantling, rewiring, and testing the motor. If the energy used is not from sustainable sources, it can contribute to carbon emissions. Old winding materials and damaged components may be discarded, contributing to waste and potential environmental pollution.

The overall environmental impact of rewinding a single-phase induction motor depends on several factors, including the efficiency of the rewinding process, the disposal or recycling of old components, and the source of energy used during rewinding. To minimize negative impacts, environmentally conscious practices, such as using eco-friendly insulation materials, energy-efficient rewinding processes, and proper disposal of old components, should be employed. Additionally, considering the benefits of motor efficiency and resource conservation through rewinding can contribute to a more sustainable approach to motor maintenance.

5.6 Ethical Issued (PO(h))

When embarking on a project related to single-phase induction motors, engineers, researchers, and project managers must consider various ethical issues to ensure that their work aligns with societal values and standards. While the development and improvement of single-phase induction motors are essential for various applications, ethical concerns should not be overlooked. This section discusses some of the key ethical issues that may arise in the context of single-phase induction motor projects.

Single-phase induction motors, widely used across industries, raise ethical concerns in several areas. Prioritizing cost and performance over environmental sustainability can have adverse effects on energy efficiency and greenhouse gas emissions. Respecting intellectual property rights is crucial to avoid legal and ethical complications. Neglecting safety measures for cost savings or performance enhancements poses ethical issues. Engineers must also assess the societal impact of motor applications, ensuring they align with social responsibility and inclusivity principles. Ethical considerations extend to global supply chains to prevent support for exploitative labor practices. In the age of IoT, protecting data security and user privacy in smart systems is imperative.

Besides, as a team project, we have to highlight individual performance in the report. As an academic work, we have to learn something from the project. That's why if we needed any expert's help, we tried to learn the process and then tried to implement the learning by

completing the work that was initiated by the expert. Besides these, we had many tool limitations, that's why we tried to complete our project with our available tools. That's why we made our own form by using woods and nails. This incident reflects our dedication to complete the task on our own without taking any experts help if not necessary.

6. Reflection on Individual and Team Work (PO(i))

Teamwork is the main key to perform any project fluently and effectively. In our project, we tried to demonstrate the highest form of team effort. We tried to participate in all the respective tasks of the project. But, due to many reasons 100% participation was not possible for everyone. For that, we tried to compensate by dividing some work among ourselves. The table described below highlighted all our works performed by individuals-

Team Members	Task Performed
Md. Rifat Rahman ID: 2006137	Wire and Insulation Purchase, Insulation, Coil Making, Coil Insertion, Connection, Reassembling of Rotor and casing, Testing.
Samia Hossain ID: 2006138	Insulation, Coil Making, Coil Insertion, Connection, Application of varnish, Reassembling of Rotor and casing, Testing.
Sami Hasib Khan ID: 2006139	Disassembling the motor, Removal of coil and insulation, Insulation, Coil Making, Coil Insertion, Connection, Reassembling of Rotor and casing, Testing.
Alif Mahmud ID: 2006140	Wire and Insulation Purchase, Insulation, Coil Making, Coil Insertion, Connection, Reassembling of Rotor and casing, Testing.
Asikul Islam Asik ID: 2006141	Motor Purchase, Disassembling the motor, Removal of coil and insulation, Insulation, Coil Making, Coil Insertion, Connection, Reassembling of Rotor and casing, Painting, Testing.
Rajin Abdullah Zeeshan ID: 2006142	Removal of coil and insulation, Insulation, Coil Making, Coil Insertion, Connection, Reassembling of Rotor and casing, Testing.

7. Communication (PO(j))

The rewinding of single-phase induction motors is a critical maintenance practice with multifaceted impacts. On the positive side, it prolongs motor lifespan, contributing to resource conservation and a reduction in the need for new motor production. This translates into significant cost savings and a decrease in electronic waste, aligning with environmental sustainability objectives.

However, this process is not without its challenges. It involves handling insulation materials that can contain hazardous substances, necessitating careful disposal and handling to mitigate potential environmental and health risks. Energy consumption during the rewinding process is another consideration, with the source of this energy being crucial in determining its overall environmental impact.

Additionally, the rewinding process generates waste in the form of discarded winding materials and components, necessitating effective waste management practices. Ethical concerns arise concerning labor practices and workplace safety.

To navigate these complexities, comprehensive assessments are essential. These assessments should encompass evaluating efficiency gains, selecting environmentally friendly materials, using sustainable energy sources, implementing robust waste management, conducting cost-

benefit analyses, and ensuring compliance with environmental regulations and safety standards. Striking a balance between economic benefits and environmental and ethical considerations is key to fostering sustainable and responsible practices in the rewinding of single-phase induction motors.

8. Project Management & Cost (PO(k))

We've embraced the concept of distributing project responsibilities equally among team members in our project management approach. This ensures that each individual's unique skills and experiences are effectively leveraged, leading to smoother project execution. Our goal is to offer cost-effective solutions that cultivate a harmonious and productive work environment by fostering collaboration and placing strong emphasis on equal participation.

At the core of our single-phase induction motor rewinding project lies efficient project management and prudent cost control. As we navigate the complex motor rewinding process, we've grown increasingly aware of the critical importance of sound financial management. This strategy not only aligns with our budgetary constraints but also aligns with environmentally responsible practices by minimizing technological waste and conserving resources.

Firstly, one of our primary cost-saving approaches is the acquisition of used motors with sound structural integrity but in need of rewinding. To ensure value for money, we conducted multiple market price assessments independently. Additionally, we cross-referenced motor and wire prices from reputable manufacturers' websites and compared them with the prevailing local market rates.

Furthermore, we place significant emphasis on a comprehensive assessment of each motor's condition before acquisition. This proactive approach mitigates the risk of unexpected expenses and empowers us to select motors that best suit our project requirements. Through thorough testing, inspections, and collaborative efforts, we ensure that each motor used in rewinding aligns with the sustainability and economic objectives of our project.

Cost

Serial No.	Sector	Cost (Bdt)
1	Single-Phase Induction Motor	3500
2	Wire, Insulation, Varnish	1275
3	Professional Assistance	800
4	Paintings	100
5	Others	130
	Total	5805

Work Flow

	Task	Assigned To	Start	End	Dur	%	2023									
							7/9	7/16	7/23	7/30	8/6	8/13	8/20	8/27	9/3	
	Rewinding of Single-Phase Induction Motor☹	Group 2	7/12/23	8/27/23	33											
1	Motor Purchase	2006141	7/12/23	7/12/23	1											
2	Preparation for Disassembling	2006141, 2006139	7/14/23	7/15/23	1											
3	Separation of Casing & Rotor	2006141, 2006139	7/17/23	7/17/23	1											
4	Removal of Coils & Insulation	2006141, 2006139, 200142	7/19/23	7/20/23	2											
5	Wire & Insulation Purchase	2006140, 2006137	7/21/23	7/21/23	1											
6	Insulation	All members	7/23/23	7/26/23	3											
7	Coil Making	All members	7/28/23	8/4/23	6											
8	Coil Insertion	All members	8/5/23	8/14/23	6											
9	Connection	All members	8/15/23	8/15/23	1											
10	Application of Varnish	2006138	8/16/23	8/16/23	1											
11	Reassembling of Rotor & Casing	All members	8/17/23	8/17/23	1											
12	Painting	2006141	8/24/23	8/24/23	1											
13	Testing	All members	8/27/23	8/28/23												

9. Future Work (PO(I))

As we look ahead to the future tasks required for our single-phase induction motor rewinding project, we identify several promising opportunities for further development and innovation. To begin, there's the intriguing prospect of exploring pole number modification. Adjusting the number of poles in these motors offers a captivating avenue for potentially enhancing their performance and adaptability to specific applications, thereby maximizing energy efficiency.

Furthermore, we envision delving deeper into refining winding methods to achieve even greater efficiency gains. Advancing our understanding of advanced winding configurations and materials can help us push the boundaries of motor efficiency, resulting in reduced energy consumption and operational costs.

Another avenue we consider is the modification of rotor types. Different rotor designs can exert a significant influence on motor performance, and experimenting with various rotor types may lead to improved and more innovative solutions. This approach can yield new solutions that better suit specific applications or environmental conditions, given the substantial impact rotor designs can have on motor performance.

Additionally, enhancing speed regulation and starting conditions remains a top priority. The development of novel control systems and techniques to ensure smoother motor operation during startup and steady-state operation will enhance the overall reliability and performance of the motor.

The implementation of these future initiatives for the single-phase induction motor rewinding project necessitates a systematic approach:

i. Changing Pole Number:

Initiate with a comprehensive literature review to grasp the implications of pole number changes on motor performance and applications. Identify the desired pole number modification based on specific operational requirements. Collaborate with motor design experts to create a motor with the desired pole configuration. This may entail alterations to the stator winding and core design, ensuring compatibility with the motor's existing frame and dimensions. Construct a prototype of the modified motor and subject it to rigorous testing. Assess performance metrics, including speed, torque, efficiency, and power factor, to ensure alignment with specifications.

ii. Exploring More Efficient Winding Techniques:

Investigate advanced winding configurations and materials conducive to enhancing motor efficiency. Experiment with diverse winding techniques, such as concentric windings, to optimize coil placement and minimize losses. Procure high-quality winding materials suitable for the chosen winding technique. Confirm the availability of appropriate insulation materials and conductors. Develop precise winding procedures, encompassing tension control and insulation placement, to consistently achieve efficient windings.

iii. Altering Rotor Type:

Collaborate with rotor design specialists to create or source alternative rotor types, including squirrel-cage, wound rotors, or hysteresis-type rotors. Ensure compatibility with motor specifications. Carefully replace the existing rotor with the new rotor type, ensuring proper alignment and electrical connections. Depending on the rotor type, installation of brushes and slip rings for electrical connections may be necessary. Conduct comprehensive testing to assess motor performance with the new rotor. Adjust and optimize the rotor type as required to achieve the desired speed regulation and starting conditions.

iv. Improving Speed Regulation and Starting Conditions:

Explore and implement advanced motor control systems like variable frequency drives (VFDs) or soft starters to attain precise speed regulation and smoother starting conditions. Rigorously test and calibrate the control system to ensure alignment with motor requirements. Adjust parameters as needed to optimize performance.

Throughout these implementations, thorough documentation and performance testing are imperative. Collaboration with experts in motor design, electrical engineering, and control systems is strongly recommended to ensure safe and effective integration. Field testing in real-world applications, along with continuous monitoring and maintenance, is vital to uphold the long-term reliability and efficiency of the modified motors.

10. References

- Chapman, S. J. (2022). *Electric Machinery Fundamentals* (5th ed.). McGraw-Hill.
- S, A. K. (2022, September 7). History of Single phase induction Motor: Its construction, working principle and types. *Skill-Lync*. <https://skill-lync.com/blogs/history-of-single-phase-induction-motor-its-construction-working-principle-and-types>
- Workbook, E. (2022, April 19). *Single Phase Induction Motor – construction, diagram, working principle, types, applications, and disadvantages - ElectricalWorkbook*. ElectricalWorkbook. <https://electricalworkbook.com/single-phase-induction-motor/>
- Electrical4U. (2020, October 25). *Single phase induction motor*. Electrical4U. https://www.electrical4u.com/single-phase-induction-motor/#google_vignette
- Technology, E., & Technology, E. (2020). Single-Phase Induction Motor – Construction, Working, Types & applications. *ELECTRICAL TECHNOLOGY*. <https://www.electricaltechnology.org/2020/05/single-phase-induction-motor.html>

YouTube Links:

- <https://www.youtube.com/watch?v=o2PRLchy1is&list=PLWaPASYPc94OiFeoIms3lvIp3ghogwHLb>
- <https://www.youtube.com/watch?v=an3etSGT-qM>
- <https://www.youtube.com/watch?v=b6jYD0vQPk0>
- <https://www.youtube.com/watch?v=ibrDOISVCgo>