# Silan Semiconductors

SC6122

INFRARED REMOTE CONTROL TRANSMITTER

DESCRIPTION

The SC6122 is a remote control transmitter utilizing CMOS Technology specially designed for use on infrared remote control applications. It is capable of controlling 64 function keys and 3 double keys. SC6122 is housed in a 24-pins SO package.

FEATURES

* CMOS Technology
* Low Operating Voltage (VDD=2.0~5.5V)
* Using SEL pin, SC6122 can support 128+6 function codes
* Customer Code can be selected

SOP-24

APPLICATIONS

* TV and VCR
* Audio Equipment
* Air Conditioner
* VCD and DVD ROM/Player
* Moniputer/Multi-Media Personal Computer System

### ORDERING INFORMATION

SC6122-001	ROM Content=0
SC6122-002	Custom Version

PIN CONFIGURATION

Pin	Name		Pin	Name
1	KI2		24	KI1
2	KI3		23	KI0
3	KI4		22	CCS
4	KI5		21	KI/O0
5	KI6		20	KI/O1
6	KI7	SC6122	19	KI/O2
7	REM		18	KI/O3
8	VDD		17	KI/O4
9	SEL		16	KI/O5
10	OSCO		15	KI/O6
11	OSCI		14	KI/O7
12	Vss		13	LMP

—— HANGZHOU SILAN MICROELECTRONICS JOINT-STOCK CO.,LTD ——

BLOCK DIAGRAM

ABSOLUTE MAXIMUM RATING (Tamb=25°C, unless otherwise specified)

Characteristic	Symbol	Value	Unit
Supply Voltage	V_{DD}	6.0	V
Input Voltage	V_{IN}	-0.3~VDD	V
Power Dissipation	Pd	250	mW
Storage Temperature	T_{stg}	-40~+125	°C
Operating Temperature	T_{opr}	-20~+75	°C

RECOMMENDED OPERATING CONDITIONS (Tamb=25°C,unless otherwise specified)

Characteristic	Symbol	Min.	Typ.	Max.	Unit
Supply Voltage	V_{DD}	2.0	3.0	3.3	V
Oscillation Frequency	fosc	400	455	500	KHz
Input Voltage	V_{IN}	0	--	V_{DD}	V
Custom Code Select Pull-Up Resistance	Rup	--	100	--	KΩ

ELECTRICAL CHARACTERISTICS (Tamb=25°C,V_{DD}=3.0V,unless otherwise specified)

Parameter	Symbol	Test conditions	Min	Typ	Max	Unit
Supply Voltage	V_{DD}		2.0	3.0	5.5	V
Current Consumption 1	I_{DD1}	Fosc =455KHz		0.1	1.0	mA
Current Consumption 2	I_{DD2}	Fosc =STOP			1.0	µA
REM High Level Output Current	I_{OH1}	Vo=1.5V	-5.0	-8.0		mA
REM Low Level Output Current	I_{OL1}	Vo=0.3V	15	30		µA
LMP High Level Output Current	I_{OH2}	Vo=2.7V	-15	-30		µA
LMP Low Level Output Current	I_{OL2}	Vo=0.3V	1	1.5		mA
KI High Level Input Current	I_{IH1}	V_{IN}=3.0V	5		30	µA
KI Low Level Input Current	I_{IL1}	V_{IN} =0V			-0.2	µA
KI High Level Input Voltage	V_{IH1}		0.7 V_{DD}		V_{DD}	V
KI Low Level Input Voltage	V_{IL1}		0		0.3 V_{DD}	V
KI/O High Level Input Voltage	V_{IH2}		0.7 V_{DD}		V_{DD}	V
KI/O Low Level Input Voltage	V_{IL2}		0		0.4	V
KI/O High Level Input Current	I_{IH2}	V_{IN} =3.0V	2		7	µA
KI/O Low Level Input Current	I_{IL2}	V_{IN} =0V			-0.2	µA
KI/O High Level Output Current	I_{OH3}	Vo=2.5V	0.5		1.5	mA
KI/O Low Level Output Current	I_{OL3}	Vo=1.7V	1.5		2.5	mA
CCS Low Level Input Voltage	V_{IH3}		1.1			V
CCS High Level Input Current	I_{IH3}	Pull Up V_{IN} =3.0V			0.2	µA
CCS Low Level Input Current	I_{IL3}	Pull Up V_{IN} =0V	-3		-15	µA
CCS High Level Input Current	I_{IH4}	Pull Down V_{IN} =3.0V	5		30	µA
CCS Low Level Input Current	I_{IL4}	Pull Down V_{IN} =0V			-0.2	µA

PIN DESCRIPTION

Pin No.	Symbol	I/O	Description
23,24,1~6	KI0~KI7	I	Key Input Pin Nos. 0~7
7	REM	O	Data Output Pin
8	VDD	--	Power Supply
9	SEL	I	Select Pin
10	OSCO	O	Oscillator Pin
11	OSCI	I	Oscillator Pin
12	Vss	--	Power Supply
13	LMP	--	Output LED Indicator
21~14	KI/O0~KI/O7	I/O	Key Input/Output Pin Nos.0~7
22	CCS	I	Custom Code Scan Input Pin

FUNCTIONAL DESCRIPTION

1. TRANSMISSION CODE

The transmission code consists of a leader code, 16-bits custom codes, and 8-bits data codes. The inverse code of the data code is also sent simultaneously. The following diagram shows this one frame construction.

| Leader Code | Custom Code 8 bits | Custom Code' 8 bits | Key Data 8 bits | $\overline{\text{Key Data}}$ 8 bits |

The leader codes consist of a 9ms carrier waveform followed by a 4.5ms OFF waveform. It is used as the leader for the following code. Thus, when reception is configured by a microcomputer, the time relationship between the reception detection and other processes can be managed efficiently. The code uses the PPM (Pulse Position Modulation) Method, with "0" and "1" differentiated by the time between pulses. Each code consists of 8 bits, and simultaneous transmission of the inverse code allows configuration of a system with an extremely low error rate.

2. KEY INPUT MATRIX

The Key Input Matrix of SC6122 if given below:

3. KEY INPUT

A total of 64 keys can be connected by SC6122 Key Input Pins--KI0~KI7 and the Timing Signal Output Pins KI/O0~KI/O7.

Double Key Operation is possible for only Key No.21 in combination with other keys connected to the KI/O5 line namely: Key No.22,23 or 24.thus, only the following key combinations may be used for the double key operation:

1. Key Nos.21 and 22 ;   2. Key Nos.21 and 23 ;   3. Key Nos.21 and 24

—— HANGZHOU SILAN MICROELECTRONICS JOINT-STOCK CO.,LTD ——

Pull-down resistors are connected between the Key Input and Vss Pins. When more than one key (except the double key combinations:K21+22, K21+23, K21+24) are pressed simultaneously, the transmission output stops.

Two key inputs are regarded as being pressed simultaneously when the time interval between these two key entries is less than 36ms.

The order of priority given to two key inputs with a time interval of more than 36ms is on a First-Pressed-First-Served or Longer-Pressed-First-Served Basis.

When a key is pressed, the custom and data codes are read. 36ms later, the Remote (REM) Output is activated. When the key is kept depressed during this 36ms, one transmission is outputted. If the key is depressed for more than 108ms, then the only the leader code is transmitted continuously.

4. DOUBLE KEY OPERATION

Double Key Operation is useful for operations such as tape deck recording. The following table shows the Key Data corresponding to the double keys pressed. Also refer to the Key Input Section.

The Double Key operation forms are as follows:

Key	D0	D1	D2	D3	D4	D5	D6	D7
K21+K22	1	0	1	0	1	1	0	0/1
K21+K23	0	1	1	0	1	1	0	0/1
K21+K24	1	1	1	0	1	1	0	0/1

Note: D7=1 when SEL is connected to VSS, or D7=0 when SEL is connected to VDD.

5. REMOTE OUTPUT WAVEFORMS

The Remote Output Waveforms are given in the diagram below:

Ex. fosc=455KHz

Key ON

Min. 36ms

① 58.5 to 76.5ms ②

③

108ms   108ms

① 9ms   4.5ms   13.5ms Leader Code   Custom Code 8bits   Custom Code   Data Code 8bits   Data Code 8bits   18ms to 36ms   27ms   58.5ms to 76.5ms

② 9ms   4.5ms   13.5ms   0.56ms   0 1 1 0 0 1   2.25ms   1.125ms

③ 9ms   2.25ms   0.56ms   11.25ms

Carrier

8.77µs   26.3µs   9ms to 0.56ms

Carrier Frequency---Fc=fosc/12=38KHz

SC6122 KEYS DATA CODE

The Keys Data Code is given in the table below.

Key No.	Connection					Data Code							
	KI0	KI1	KI2	KI3	KI/O	D0	D1	D2	D3	D4	D5	D6	D7
K1	•				KI/O0	0	0	0	0	0	0	0	0/1
K2		•				1	0	0	0	0	0	0	0/1
K3			•			0	1	0	0	0	0	0	0/1
K4				•		1	1	0	0	0	0	0	0/1
K5	•				KI/O1	0	0	1	0	0	0	0	0/1
K6		•				1	0	1	0	0	0	0	0/1
K7			•			0	1	1	0	0	0	0	0/1
K8				•		1	1	1	0	0	0	0	0/1
K9	•				KI/O2	0	0	0	1	0	0	0	0/1
K10		•				1	0	0	1	0	0	0	0/1
K11			•			0	1	0	1	0	0	0	0/1
K12				•		1	1	0	1	0	0	0	0/1
K13	•				KI/O3	0	0	1	1	0	0	0	0/1
K14		•				1	0	1	1	0	0	0	0/1
K15			•			0	1	1	1	0	0	0	0/1
K16				•		1	1	1	1	0	0	0	0/1
K17	•				KI/O4	0	0	0	0	1	0	0	0/1
K18		•				1	0	0	0	1	0	0	0/1
K19			•			0	1	0	0	1	0	0	0/1
K20				•		1	1	0	0	1	0	0	0/1
K21	•				KI/O5	0	0	1	0	1	0	0	0/1
K22		•				1	0	1	0	1	0	0	0/1
K23			•			0	1	1	0	1	0	0	0/1
K24				•		1	1	1	0	1	0	0	0/1
K25	•				KI/O6	0	0	0	1	1	0	0	0/1
K26		•				1	0	0	1	1	0	0	0/1
K27			•			0	1	0	1	1	0	0	0/1
K28				•		1	1	0	1	1	0	0	0/1
K29	•				KI/O7	0	0	1	1	1	0	0	0/1
K30		•				1	0	1	1	1	0	0	0/1
K31			•			0	1	1	1	1	0	0	0/1
K32				•		1	1	1	1	1	0	0	0/1

(to be continued)

Silan
Semiconductors

(continued)

Key No.	Connection					Data Code							
	KI4	KI5	KI6	KI7	KI/O	D0	D1	D2	D3	D4	D5	D6	D7
K33	•					0	0	0	0	0	0	1	0/1
K34		•			KI/O0	1	0	0	0	0	0	1	0/1
K35			•			0	1	0	0	0	0	1	0/1
K36				•		1	1	0	0	0	0	1	0/1
K37	•					0	0	1	0	0	0	1	0/1
K38		•			KI/O1	1	0	1	0	0	0	1	0/1
K39			•			0	1	1	0	0	0	1	0/1
K40				•		1	1	1	0	0	0	1	0/1
K41	•					0	0	0	1	0	0	1	0/1
K42		•			KI/O2	1	0	0	1	0	0	1	0/1
K43			•			0	1	0	1	0	0	1	0/1
K44				•		1	1	0	1	0	0	1	0/1
K45	•					0	0	1	1	0	0	1	0/1
K46		•			KI/O3	1	0	1	1	0	0	1	0/1
K47			•			0	1	1	1	0	0	1	0/1
K48				•		1	1	1	1	0	0	1	0/1
K49	•					0	0	0	0	1	0	1	0/1
K50		•			KI/O4	1	0	0	0	1	0	1	0/1
K51			•			0	1	0	0	1	0	1	0/1
K52				•		1	1	0	0	1	0	1	0/1
K53	•					0	0	1	0	1	0	1	0/1
K54		•			KI/O5	1	0	1	0	1	0	1	0/1
K55			•			0	1	1	0	1	0	1	0/1
K56				•		1	1	1	0	1	0	1	0/1
K57	•					0	0	0	1	1	0	1	0/1
K58		•			KI/O6	1	0	0	1	1	0	1	0/1
K59			•			0	1	0	1	1	0	1	0/1
K60				•		1	1	0	1	1	0	1	0/1
K61	•					0	0	1	1	1	0	1	0/1
K62		•			KI/O7	1	0	1	1	1	0	1	0/1
K63			•			0	1	1	1	1	0	1	0/1
K64				•		1	1	1	1	1	0	1	0/1

Note: D7=1 when SEL is connected to V_{SS}, or D7=0 when SEL is connected to V_{DD}.

TYPICAL APPLICATION CIRCUIT

Note:1. Two capacitance connect with Vcc should as near as possible.
   2. The line between two capacitance and Vcc and ground should as short as possible.

CHIP TOPOGRAPHY

Size: 1.84 x 1.46 mm^2

PAD COORDINATES (Unit: μm)

No.	Symbol	X	Y	No.	Symbol	X	Y
1	P1	-602.80	-322.10	13	P13	605.70	217.90
2	P2	-602.80	-452.10	14	P14	542.00	452.00
3	P3	-350.70	-452.10	15	P15	403.50	452.00
4	P4	-220.90	-452.10	16	P16	160.40	452.00
5	P5	-89.50	-452.10	17	P17	12.50	452.00
6	P6	41.00	-452.10	18	P18	-230.30	452.00
7	P7	171.40	-452.10	19	P19	-361.30	451.90
8	P8	347.90	-452.10	20	P20	-602.50	451.90
9	P9	477.80	-452.10	21	P21	-607.50	252.40
10	P10	608.00	-452.10	22	P22	-602.80	68.50
11	P11	607.20	-176.00	23	P23	-602.80	-61.20
12	P12	607.20	-44.60	24	P24	-602.80	-191.50

Note: The original point of the coordinate is the die center.

—— HANGZHOU SILAN MICROELECTRONICS JOINT-STOCK CO.,LTD ——

PCB WIRE LAYOUT SCHEMATIC:

Transmitting tube output ground line

The transmitting tube ground line and IC ground line should layout separated or overstriking ground line.

The above IC only use to hint, not to specified.

Note:：

* In wire layout, the power filter capacitor should near to IC.

* In wire layout, should avoid power line and ground line too long.

* Recommended infrared transmit unit and IC ground line should layout separated, or overstriking lines.

* The emitter of triode connect $1\,\Omega$ resistor at least.

* Recommended triode use 9014.

PACKAGE OUTLINE

SOP-24-375-1.27	Unit: mm

Attach

Revision History

Data	REV	Description	Page
2000.12.31	2.0	Change name of company in page footer	
2001.12.12	2.1		
2002.03.01	2.2	Modify the "Typical application circuit"	9
		Add the "PCB wire layout schematic"	11
		Modify the "Package outline"	12